



ACOS 6.0.8

SNMP MIB Reference

December, 2025

© 2025 A10 Networks, Inc. CONFIDENTIAL AND PROPRIETARY- ALL RIGHTS RESERVED.

Information in this document is subject to change without notice.

PATENT PROTECTION

A10 Networks, Inc. products are protected by patents in the U.S. and elsewhere. The following website is provided to satisfy the virtual patent marking provisions of various jurisdictions including the virtual patent marking provisions of the America Invents Act. A10 Networks, Inc. products, including all Thunder Series products, are protected by one or more of U.S. patents and patents pending listed at:

[a10-virtual-patent-marking](#).

TRADEMARKS

A10 Networks, Inc. trademarks are listed at: [a10-trademarks](#)

CONFIDENTIALITY

This document contains confidential materials proprietary to A10 Networks, Inc.. This document and information and ideas herein may not be disclosed, copied, reproduced or distributed to anyone outside A10 Networks, Inc. without prior written consent of A10 Networks, Inc..

DISCLAIMER

This document does not create any express or implied warranty about A10 Networks, Inc. or about its products or services, including but not limited to fitness for a particular use and non-infringement. A10 Networks, Inc. has made reasonable efforts to verify that the information contained herein is accurate, but A10 Networks, Inc. assumes no responsibility for its use. All information is provided "as-is." The product specifications and features described in this publication are based on the latest information available; however, specifications are subject to change without notice, and certain features may not be available upon initial product release. Contact A10 Networks, Inc. for current information regarding its products or services. A10 Networks, Inc. products and services are subject to A10 Networks, Inc. standard terms and conditions.

ENVIRONMENTAL CONSIDERATIONS

Some electronic components may possibly contain dangerous substances. For information on specific component types, please contact the manufacturer of that component. Always consult local authorities for regulations regarding proper disposal of electronic components in your area.

FURTHER INFORMATION

For additional information about A10 products, terms and conditions of delivery, and pricing, contact your nearest A10 Networks, Inc. location, which can be found by visiting www.a10networks.com.

Table of Contents

Introduction	9
SNMP Versions	10
SNMP MIB Information	11
Downloading the MIBs	11
AX MIB Groups	11
MIB Access	12
SNMP RFCs Support	12
ifIndex Table Support	16
Partition-aware SNMP Configuration	17
Prerequisites	17
Limitations	17
Multi-PU Platform Support	19
CLI Configuration	19
Limitation	19
SNMP Views and Community Strings	20
SNMP Views	20
GUI Configuration	20
CLI Configuration	21
SNMP Community Strings	21
GUI Configuration	21
CLI Configuration	22
SNMP Groups	25
GUI Configuration	25
CLI Configuration	25
Authentication and Encryption for SNMPv3 Users	26
GUI Configuration	26
CLI Configuration	27

SNMP Traps	28
GUI Configuration for Enabling SNMP Traps	28
CLI Configuration for Enabling SNMP Traps	29
CLI Configuration for Disabling the SNMP Traps for L3V Partitions	31
SNMP Configuration	33
GUI Configuration	33
CLI Configuration	34
Source Interface for SNMP Notifications	36
GUI Configuration	36
CLI Configuration	37
List of MIB Objects	38
A10-AX-CHASSIS_axChassisMgmt_oid_list	39
A10-AX-MIB_axMgmt_oid_list	57
A10-AX-NOTIFICATIONS_axNotifications_oid_list	245
ACOS-AAM-STATS-MIB_acosAam_oid_list	261
ACOS-ACOS-EVENTS-STATS-MIB_acosAcosEvents_oid_list	293
ACOS-CGNV6-DDOS-PROTECTION-MIB_oid_list	304
ACOS-CGNV6-DNS64-MIB_oid_list	315
ACOS-CGNV6-HTTP-ALG-MIB_oid_list	317
ACOS-CGNV6-ICMP-MIB_oid_list	320
ACOS-CGNV6-L4-MIB_oid_list	325
ACOS-CGNV6-LOGGING-MIB_oid_list	332
ACOS-CGNV6-SERVER-MIB_oid_list	344
ACOS-CGNV6-SERVICE-GROUP-MIB_oid_list	364
ACOS-CGNV6-SHARED-SERVICE-GROUP-MIB_oid_list	376
ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list	377
ACOS-CLASS-LIST-MIB_oid_list	649
ACOS-CONFIG-SYNC-STATUS-MIB_oid_list	658
ACOS-DDOS-STATS-MIB_acosDdos_oid_list	659
ACOS-EVENT-NOTIFICATION-STATS-MIB_acosEventNotification_oid_list	752

ACOS-FW-APP-MIB_oid_list	762
ACOS-FW-DDOS-PROTECTION-MIB_oid_list	764
ACOS-FW-FULL-CONE-SESSION-MIB_oid_list	768
ACOS-FW-LOGGING-MIB_oid_list	770
ACOS-FW-OPER-MIB_acosFw_oid_list	778
ACOS-FW-RATE-LIMIT-MIB_oid_list	784
ACOS-FW-RESOURCE-USAGE-MIB_oid_list	793
ACOS-FW-SERVER-MIB_oid_list	797
ACOS-FW-STATS-MIB_acosFw_oid_list	804
ACOS-FW-STATUS-MIB_oid_list	892
ACOS-FW-SYSTEM-STATUS-MIB_oid_list	893
ACOS-FW-TCP-WINDOW-CHECK-MIB_oid_list	894
ACOS-GSLB-SERVICE-IP-MIB_oid_list	895
ACOS-GSLB-SERVICE-PORT-MIB_oid_list	902
ACOS-GSLB-SITE-MIB_oid_list	904
ACOS-GSLB-STATISTICS-MIB_oid_list	936
ACOS-GSLB-STATS-MIB_acosGslb_oid_list	937
ACOS-GSLB-ZONE-MIB_oid_list	943
ACOS-HEALTH-STATS-MIB_acosHealth_oid_list	970
ACOS-INTERFACE-AVAILABLE-ETH-LIST-MIB_oid_list	972
ACOS-INTERFACE-BRIEF-MIB_oid_list	974
ACOS-INTERFACE-COMMON-MIB_oid_list	977
ACOS-INTERFACE-ETHERNET-MIB_oid_list	981
ACOS-INTERFACE-MANAGEMENT-MIB_oid_list	992
ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list	997
ACOS-IP-ANOMALY-DROP-MIB_oid_list	1011
ACOS-IP-STATS-MIB_acosIp_oid_list	1017
ACOS-IPV6-IN-IPV4-STATS-MIB_acosIpv6InIpv4_oid_list	1031
ACOS-IPV6-STATS-MIB_acosIpv6_oid_list	1036
ACOS-JWT-CACHE-MIB_oid_list	1043
ACOS-NAT-POOL-MIB_oid_list	1045

ACOS-NETFLOW-MONITOR-MIB_oid_list	1053
ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list	1069
ACOS-NETWORK-STATS-MIB_acosNetwork_oid_list	1084
ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list	1088
ACOS-NGWAF-STATUS-MIB_oid_list	1101
ACOS-OVERLAY-TUNNEL-STATS-MIB_acosOverlayTunnel_oid_list	1103
ACOS-PARTITION-STATS-MIB_acosPartition_oid_list	1108
ACOS-PKI-CERT-STATS-MIB_oid_list	1109
ACOS-RULE-SET-MIB_oid_list	1110
ACOS-RULESET-RULE-MIB_oid_list	1115
ACOS-RULESET-RULES-BY-ZONE-MIB_oid_list	1122
ACOS-RULE-SET-STATS-MIB_acosRuleSet_oid_list	1128
ACOS-SCTP-GLOBAL-MIB_oid_list	1129
ACOS-SCTP-STATS-MIB_acosSctp_oid_list	1137
ACOS-SFLOW-STATS-MIB_acosSflow_oid_list	1144
ACOS-SLB-DNS-CACHE-MIB_oid_list	1145
ACOS-SLB-DNS-MIB_oid_list	1156
ACOS-SLB-HTTP-PROXY-MIB_oid_list	1161
ACOS-SLB-L4-MIB_oid_list	1235
ACOS-SLB-L7SESSION-MIB_oid_list	1265
ACOS-SLB-OPER-MIB_acosSlb_oid_list	1271
ACOS-SLB-SERVER-MIB_oid_list	1304
ACOS-SLB-SERVICE-GROUP-MIB_oid_list	1338
ACOS-SLB-SSL-ACME-CERT-STATUS-MIB_oid_list	1351
ACOS-SLB-SSL-FORWARD-PROXY-MIB_oid_list	1352
ACOS-SLB-SSL-JA3-MIB_oid_list	1357
ACOS-SLB-SSL-JA4-MIB_oid_list	1358
ACOS-SLB-SSL-STATS-MIB_oid_list	1359
ACOS-SLB-STATS-MIB_acosSlb_oid_list	1368
ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list	1717
ACOS-SO-COUNTERS-STATS-MIB_acosSoCounters_oid_list	1758

ACOS-SYSTEM-CONTROL-CPU-MIB_oid_list	1764
ACOS-SYSTEMCPU-CTRL-CPU-MIB_oid_list	1772
ACOS-SYSTEMCPU-DATA-CPU-MIB_oid_list	1774
ACOS-SYSTEM-CPU-OPER-MIB_acosSystemCpu_oid_list	1776
ACOS-SYSTEM-DATA-CPU-MIB_oid_list	1782
ACOS-SYSTEM-OPER-MIB_acosSystem_oid_list	1793
ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list	1794
ACOS-SYSTEM-VIEW-STATS-MIB_acosSystemView_oid_list	1911
ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list	1912
ACOS-THREAT-INTEL-STATS-MIB_acosThreatIntel_oid_list	1926
ACOS-TRAFFIC-CONTROL-STATS-MIB_acosTrafficControl_oid_list	1930
ACOS-VCSCHAISSIS-SLOT-SUMMARY-MIB_oid_list	1931
ACOS-VCS-IMAGES-MIB_oid_list	1936
ACOS-VCS-STAT-MIB_oid_list	1937
ACOS-VCSVBLADES-STAT-MIB_oid_list	1945
ACOS-VCS-VBLADES-STATS-MIB_acosVcsVblades_oid_list	1947
ACOS-VCS-VCS-SUMMARY-MIB_oid_list	1949
ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list	1954
ACOS-VRRPA-COMMON-MIB_oid_list	1969
ACOS-VRRPA-DETAIL-MIB_oid_list	1970
ACOS-VRRPA-HOSTID-MIB_oid_list	1976
ACOS-VRRPA-MAC-MIB_oid_list	1978
ACOS-VRRPA-PARTITION-VRID-ALL-STATUS-MIB_oid_list	1979
ACOS-VRRPA-PARTITION-VRID-STATUS-MIB_oid_list	1981
ACOS-VRRPA-SETID-MONITOR-MIB_oid_list	1983
ACOS-VRRPA-STATE-CPU-MIB_oid_list	1986
ACOS-VRRPA-STATE-MIB_oid_list	1987
ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list	2007
ACOS-WAF-RULE-SET-STATS-MIB_acosWafRuleSet_oid_list	2027
ACOS-WAF-STATS-MIB_acosWaf_oid_list	2031
ACOS-WEBCATEGORY-LICENSE-MIB_oid_list	2108

ACOS-WEB-CATEGORY-MIB_oid_list 2110

ACOS-WEBCATEGORY-STATISTICS-MIB_oid_list 2112

ACOS-WEB-CATEGORY-STATS-MIB_acosWebCategory_oid_list 2116

Introduction

Simple Network Management Protocol or SNMP is a commonly used protocol for managing and monitoring network devices. It provides a standard way to collect network information, set configurations, and receive alerts about network devices. Thus, SNMP helps to maintain network reliability and performance.

SNMP has multiple versions such as SNMPv1, SNMPv2c, and SNMPv3. SNMPv3 is a more preferred protocol as it offers improved security features compared to earlier versions.

SNMP supports single as well as multi-PU platforms.

The main components of SNMP are as follows:

- Managed devices
These are the network nodes such as routers, switches, servers, printers, and so on that are to be monitored.
- SNMP Agents
SNMP agent is a process that runs on a managed device to collect, store, and make the managed device's configuration available to the SNMP Manager.
 - SNMP Subagent extends the functionality of SNMP agent. It allows to define custom MIB variables and register them with the SNMP agent.
 - SNMP Schema agent provides the SNMP manager with data from individual PU or aggregated data from multiple PU. Multiple SNMP MIB tables are generated for stats data and oper data of a configuration management object. Each SNMP table contains a default index, `slotId`, for identifying blades in a multi-PU platform:
 - `slotId 0`: Aggregation of all blades
 - `slotId 1`: Data from PU1/Standalone platform
 - `slotId 2`: Data from PU2
- SNMP Manager
SNMP manager makes a request to the SNMP agent to receive data and configure the managed devices.

- Management Information Base (MIB)
MIB defines the structure and organization of data that can be accessed using SNMP. It acts as a database of available information for SNMP managers.

SNMP Versions

ACOS Devices support the following SNMP versions: v1, v2c, v3. SNMP is disabled by default.

You can configure an ACOS Device to send the SNMP traps to the Syslog and to the external trap receivers. You also can configure read (GET) access to SNMP Management Information Base (MIB) objects on the ACOS Device by external SNMP managers. .

NOTE: SNMP access to the ACOS Device is read-only. SET operations (write access) are not supported.

The following list of items clarifies the current implementation of SNMP:

- Limit the number of SNMP polling requests to two or three instances. Several concurrent “snmpwalk” requests, will result in delays, unfinished requests, time out, or error messages.
- Certain SNMP objects, such as the “CPU Per Partition” value, might not work in the current release.
- As the ACOS Device generates the SNMP community string for private partitions, you are not allowed to configure or change the community string.
- The SNMP process may consume 100% of the Control CPU cycles.

SNMP MIB Information

The following topics are covered:

Downloading the MIBs	11
AX MIB Groups	11
MIB Access	12
SNMP RFCs Support	12
ifIndex Table Support	16

Downloading the MIBs

The MIB files are available for download through the ACOS GUI:

1. Hover over **System** on the menu bar and select **Monitoring**.
2. Click on the **SNMP** tab and select **SNMP MIB Download** from the drop-down menu.
3. Select a target location for the MIB archive file and click **Save**.

AX MIB Groups

The AX MIB Groups classify the MIB structure and provide a way to organize or manage related information for network devices. The AX MIB consists of the following groups:

Table 1 : AX MIB Groups

Group	Description
axSystem	Provides system-level information about the ACOS Device, such as the installed software versions, the serial number, and current CPU utilization.
axLogging	Provides configuration information about system logging.
axApp	Provides configuration and operational information for ACOS

Table 1 : AX MIB Groups

Group	Description
	Device features.
axChassis	Provides configuration information about multiple processing units (PUs).
acosSchema	Provides stats and oper tables of configuration management objects.
acosRootStats	Deprecated.
acosRootOper	Deprecated.

MIB Access

SNMP access to the ACOS Device is read-only. SNMP managers can retrieve information using GET or GET NEXT requests. SET requests are not supported.

To enable the SNMP traps from the GUI, select **System > Monitoring > SNMP > SNMP** tab, then select **Enable** in the **General Fields** section. Expand the **Trap List** section to select the traps you want to enable or disable. For more information, refer to the online help.

To enable the SNMP traps from the CLI, use the `snmp-server enable traps` command.

The following example enables system start traps:

```
ACOS(config)# snmp-server enable traps system start
```

NOTE: For more information about the SNMP CLI commands, see the *Command Line Interface Reference*.

SNMP RFCs Support

ACOS Device supports the SNMP-related RFCs described as follows:

Table 2 : Supported SNMP-related RFCs

RFC	Description and Notes
RFC 1155	Structure and Identification of Management Information for TCP/IP-based Networks.
RFC 1157	A Simple Network Management Protocol (SNMP).
RFC 1212	Concise MIB Definitions: the MIB SET operation is not supported.
RFC 1213	Management Information Base for Network Management of TCP/IP-based Networks: MIB-II. The following system objects are supported: • sysDescr • sysObjectID • sysUpTime • sysContact • sysName • sysLocation • sysServices The sysService object returns a value that indicates the set of services the ACOS Device offers. For the ACOS Device, the sysService object always returns the value 76. This value indicates that the ACOS Device offers the following services (for information about how this value is calculated, refer to the RFC): • datalink/subnetwork – 0x2 • internet – 0x4 • end-to-end – 0x8 • applications – 0x40 The following interfaces on MIB-II are supported: • ifNumber

Table 2 : Supported SNMP-related RFCs

RFC	Description and Notes
	ifTable The ipAddrTable on MIB-II are also supported.
RFC 1215	A convention for defining traps for use with the SNMP.
RFC 1850	OSPF Version 2 Management Information Base.
RFC 1901	Introduction to Community-based SNMPv2.
RFC 2233	The Interfaces Group MIB using SMIv2. The ifXTable table is supported.
RFC 2465	Management Information Base for IP Version 6: Textual Conventions and General Group. The ipv6AddrTable on MIB-II is supported.
RFC 2576	Coexistence between Version 1, Version 2, and Version 3 of the Internet-standard Network Management Framework.
RFC 2578	Structure of Management Information Version 2 (SMIv2).
RFC 2790	Host Resources MIB. The following subtrees are supported: - hrSystem: .1.3.6.1.2.1.25.1 - hrStorage: .1.3.6.1.2.1.25.2 - hrDeviceTable: .1.3.6.1.2.1.25.3.2 - hrProcessorTable: .1.3.6.1.2.1.25.3.3
RFC 2863	The Interfaces Group MIB. The following table is supported: ifXTable: .1.3.6.1.2.1.31.1.1
RFC 3418	Physical Topology MIB. The following objects are supported: - IldpV2PortConfigTable - IldpV2DestAddrTable - IldpV2LocPortTable - IldpV2LocManAddrTable - IldpV2RemTable - IldpV2RemManAddrTable

Table 2 : Supported SNMP-related RFCs

RFC	Description and Notes
	• IldpV2LocChassisIdSubtype • IldpV2LocChassisId • IldpV2LocSysName • IldpV2LocSysDesc • IldpV2LocSysCapSupported • IldpV2LocSysCapEnabled
RFC 3410	Introduction and Applicability Statements for Internet Standard Management Framework.
RFC 3411	An Architecture for Describing Simple Network Management Protocol (SNMP) Management Frameworks.
RFC 3412	Message Processing and Dispatching for the Simple Network Management Protocol (SNMP).
RFC 3413	Simple Network Management Protocol (SNMP) Applications.
RFC 3414	User-based Security Model (USM) for version 3 of the Simple Network Management Protocol (SNMPv3).
RFC 3415	View-based Access Control Model (VACM) for the Simple Network Management Protocol (SNMP).
RFC 3416	Version 2 of Protocol Operations for the SNMP.
RFC 3418	MIB for the SNMP.
RFC 3635	Definitions of Managed Objects for the Ethernet-like Interface Types.
RFC 4001	Textual Conventions for Internet Network Addresses. The following values for IP address types are supported: • 0 - Unknown • 1 - IPv4 • 2 - IPv6
RFC 4273	Definitions of Managed Objects for BGP-4. The following traps are supported:

Table 2 : Supported SNMP-related RFCs

RFC	Description and Notes
	• bgpEstablishedNotification • bgpBackwardTransNotification
RFC 4293	Management Information Base for the Internet Protocol. The following tables are supported: • Ipv4InterfaceTable • Ipv6InterfaceTable • IpAddrTable • Ipv6AddrTable

ifIndex Table Support

The `ifInUnknownProtos` and `ifOutLen` objects in the `ifIndex` table are not implemented on AX interfaces and always return value 0. Likewise, the `ifSpecific` object is not present and always returns "0.0".

Partition-aware SNMP Configuration

SNMP can be configured on private partitions. The SNMP configurations only apply to the partition being configured and these configuration are partition-aware.

When SNMP is disabled in the shared partition, no configuration change is required in any L3V partition. From the shared partition, the ACOS Device will not get SNMP responses nor see any L3V traps.

You can get SNMP response and traps of a L3V partition through shared VLAN interfaces. Traps in the L3V partition uses different community strings.

To enable L3V partition traps, SNMP service and community string on L3V partition must be configured. The enabling/disabling of traps in L3V partition can only be done on the group level, and not on individual trap level.

Since the community string on the L3V partition is configured and encrypted, there is no auto-generated community string on the L3V partition.

The following topics are covered:

Prerequisites	17
Limitations	17

Prerequisites

- SNMP must be enabled in the L3V partition.
- SNMP service and community string on the L3V partition must be configured.

Limitations

- SNMP traps will be only snmp-v2 traps.
- SNMP configuration of GSLB group traps is not supported on L3V partitions.

- The SNMPv2 and SNMPv3 get requests with or without `communityString@partition_name` are supported on L3V partitions. However, if the partition name is not provided, the `snmpget` request returns:
 - Data from the shared partition only for OIDs under `axChassis`
 - Data from all partitions for all other OIDs.

Multi-PU Platform Support

SNMP supports MIB OIDs and tables for multi-PU platforms. A schema agent is used to provide the SNMP manager with data from individual PU or aggregated data from multiple PUs. For multi-PU platform support, enable the schema agent on ACOS.

The following topics are covered:

CLI Configuration	19
Limitation	19

CLI Configuration

To allow SNMP monitoring for multi-PU platform, enable the new CM subagent:

```
ACOS(config)#snmp-server enable schema-agent
```

Limitation

- The SNMP tables do not include an index for L3V partitions. To request data for an L3V partition, attach the partition name to the community string (e.g., public@p1) in the SNMP request. The response for the request will contain data specific to the requested L3V partition.

SNMP Views and Community Strings

You can allow external SNMP managers to access the values of MIB objects from the ACOS Device. To allow remote read-only access to the ACOS MIB objects, configure one or both of the following types of access:

- [SNMP Views](#)
- [SNMP Community Strings](#)

SNMP Views

An SNMP view is like a filter that permits or denies access to a specific OID or portions of an OID. You can configure SNMP user groups and individual SNMP users, and allow or disallow them to read specific portions of the ACOS MIBs using different views.

When you configure an SNMP user group or user, you specify the SNMP version. SNMP v1 and SNMP v2c do not support authentication or encryption of the SNMP packets, while SNMPv3 does. You can enable authentication, encryption, or both, on an individual SNMP user-group when you configure the groups. You can specify the authentication method and the password for individual SNMP users when you configure the users.

The following topics are covered:

GUI Configuration	20
CLI Configuration	21

GUI Configuration

To configure an SNMP view using the GUI:

1. Hover over **System** in the menu bar and select **Monitoring**.
2. Select **SNMP** and select **SNMP Views** from the drop-down menu.

3. Click **Create**.
4. Enter a name for the view in the Viewname field.
5. Enter the MIB view family name or OID in the Oid field and then specify whether this OID should be included or excluded in the view.
6. Click **Create**.

CLI Configuration

Use the `snmp-server view` command to configure an SNMP view from the CLI. The following example creates a view called “exampleview” that includes OID 1.2.3:

```
ACOS(config)# snmp-server view exampleview 1.2.3 included
```

SNMP Community Strings

An SNMP community string is a string that an SNMP manager can present to the ACOS Device when requesting MIB values.

Community strings are similar like passwords. You can minimize security risk by applying the same principles for selecting a community name as you would do for selecting a password. Use a hard-to-guess string and avoid use of commonly used community names such as “public” or “private”.

You also can restrict access to specific Object IDs (OIDs) within the MIB, on an individual community basis. OIDs indicate the position of a set of MIB objects in the global MIB tree. The OID for A10 Networks, Inc. Thunder Series objects is 1.3.6.1.4.1.22610.

The following topics are covered:

GUI Configuration	21
CLI Configuration	22

GUI Configuration

To configure an SNMP community string using the GUI:

1. Hover over **System** and select **Monitoring**.
2. Select the **SNMP** tab and then select **SNMP** from the drop-down menu.
3. Enter the community string in the Community Read field and click **Add**.
4. Click **Configure SNMP**.

CLI Configuration

This section contains the following examples:

- [CLI Example—Configuring a Community String for SNMPv1 or SNMPv2c Users](#)
- [CLI Example—Configuring a Community String for SNMPv3 Users](#)
- [CLI Example—Restricting Access to Specific Remote Hosts](#)
- [CLI Example—Restricting Access to Specific OIDs](#)

CLI Example—Configuring a Community String for SNMPv1 or SNMPv2c Users

The following example shows how to configure an SNMP community string using the CLI for SNMPv1 or SNMPv2c users:

```
ACOS(config)# snmp-server SNMPv1-v2c user u1
ACOS(config-user:u1)# community read examplestring
ACOS(config-user:u1)# show running-config | sec snmp
snmp-server enable service
snmp-server enable traps all
snmp-server SNMPv1-v2c user u1
    community read encrypted
mGXzd9xrcGiMBaDQuY/jnDwQjLjV2wDnPBCMuNXbAOc8EIy41dsA5zwQjLjV2wDn
snmp-server host 10.6.7.22 version v2c public
```

NOTE: The community string is encrypted in the `show running-config` output for security purposes. Each SNMP v1-v2c user has a community string. You can change the value of this string by using the `community read` command and enter a new community string.

The username `u1` is a system-specific name and cannot be used to retrieve any SNMP data. Instead, the encrypted community string configured under this user should be

used to retrieve data. This community string can also be used by any remote host to access the ACOS Device, assuming there are no access restrictions configured.

CLI Example—Configuring a Community String for SNMPv3 Users

The following example shows how to configure an SNMP community string for SNMPv3 users. An SNMP view and group must be configured prior to configuring the SNMPv3 user.

```
ACOS(config)# snmp-server view exampleview 1.2.3 included
ACOS(config)# snmp-server group examplegroup v3 auth read exampleview
ACOS(config)# snmp-server SNMPv3 user exampleuser group examplegroup v3
auth md5 examplepassword1 priv aes examplepassword2
ACOS(config)# show running-config | sec snmp
snmp-server enable service
snmp-server enable traps all
snmp-server view exampleview 1.2.3 included
snmp-server group examplegroup v3 auth read exampleview
snmp-server SNMPv3 user exampleuser group examplegroup v3 auth md5
encrypted IrrqRoL9DI2HGP3wipS0lDwQjLjV2wDnPBCMuNXbAOc8EIy4l dsA5zwQjLjV2wDn
priv aes encrypted
6D2AC0vBjbGHGP3wipS0lLD/mjXR6wFMPBCMuNXbAOc8EIy4l dsA5zwQjLjV2wDn
snmp-server host 10.6.7.22 version v2c public
```

CLI Example—Restricting Access to Specific Remote Hosts

The following example shows how to restrict access to allow only specific remote hosts to access SNMP data. From the SNMP v1-v2c user configuration level, specify which remote hosts are allowed to access the ACOS Device using the community string:

```
ACOS(config-user:u1)# remote 192.168.20.1 /24
ACOS(config-user:u1)# remote 192.168.30.1 /24
```

CLI Example—Restricting Access to Specific OIDs

The following example shows how to restrict access so that only a specific OID (1.2.3) can be accessed by the specified hosts (subnets 192.168.30.x and 192.168.40.x). From the SNMPv1-v2c user configuration level:

```
ACOS(config-user:u1)# oid 1.2.3
```

```
ACOS(config-user:u1-oid:1.2.3)# remote 192.168.40.1 255.255.255.0  
ACOS(config-user:u1-oid:1.2.3)# remote 192.168.50.1 255.255.255.0
```


SNMP Groups

SNMP users can be organized into groups, which can be configured to allow or disallow users access to read specific SNMP views.

The following topics are covered:

GUI Configuration	25
CLI Configuration	25

GUI Configuration

To configure an SNMP group using the GUI:

1. Hover over **System** in the menu bar and select **Monitoring**.
2. Select **SNMP** and select **SNMP Groups** from the drop-down menu.
3. Click **Create**.
4. Enter a name for the group in the Groupname field.
5. Select the desired SNMPv3 packet authentication level.
6. Select a read-only view for accessing MIB objects.
7. Click **Create**.

CLI Configuration

Use the `snmp-server group` command to configure an SNMP group from the CLI. The following example creates a group called “examplegroup”:

```
ACOS(config)# snmp-server group examplegroup v3 priv read exampleview
```

Authentication and Encryption for SNMPv3 Users

Advanced Encryption Standard (AES) or Data Encryption Standard (DES) encryption can be added at the SNMP “user” level. This feature extends overall security with support for SNMPv3 notifications (traps). SNMPv3 traps are authenticated and encrypted, using the same options already supported for SNMPv3 in previous releases.

- Authentication is performed by using authentication key of a user to sign the message being sent. This can be done using either MD5 or SHA authentication. The authentication key is generated using the specified authentication method and the specified password. The key size for SHA is typically 512, 384, 256, or 224 bits.
- Encryption is performed by using the privacy key of a user to encrypt the data portion of the message being sent. This can be done using either AES or DES encryption. The privacy key is generated using the specified encryption method and the specified password. The AES method uses a fixed block size of 128 bits and a key size of 128, 192, or 256 bits.

NOTE: After changing the encryption for an SNMP user, SNMP must be restarted to reload the configuration. This process takes some time before the SNMP service becomes available.

The following topics are covered:

GUI Configuration	26
CLI Configuration	27

GUI Configuration

To configure authentication and encryption for SNMPv3 users from the GUI:

1. Go to **System > Monitoring**, under **SNMP** tab, select **SNMP Users**.
2. Click **Create** to create a new user and enter the appropriate information.

3. Click **Create** to save the configuration.

CLI Configuration

To configure the SNMPv3 user authentication and encryption, use the following command:

```
ACOS(config)# snmp-server enable service
ACOS(config)# snmp-server view exampleview 1.2.3 included
ACOS(config)# snmp-server group examplegroup v3 auth read exampleview
ACOS(config)# snmp-server SNMPv3 user exampleuser group examplegroup v3
auth sha-512
ACOS(config)# snmp-server SNMPv3 user exampleuser group examplegroup v3
auth sha-512 examplepassword1 priv aes-192 examplepassword2
```

In this example, **exampleuser** is an SNMPv3 user, who is a member in **examplegroup**, which is part of **exampleview**. The **auth sha-512 examplepassword1** portion of the command generates a user key using SHA-512 authentications and an **examplepassword1** string. The **priv aes-192 examplepassword2** portion of the command encrypts the message using a key with AES-192 encryption and an **examplepassword2** string.

SNMP Traps

To start receiving SNMP traps, you must enable the SNMP traps on a configured SNMP server. You can enable any of the individual traps, or a category of new SNMP traps. Follow the steps below to enable the SNMP traps. All traps are disabled by default.

For more information about the SNMP CLI commands used for enabling SNMP traps, along with a list of available traps, see the *Command Line Interface Reference*.

For information about configuring the SNMP traps on L3V partitions, see the *Configuring Application Delivery Partitions* guide.

Take note of the following:

- To begin receiving the `ssl-cert-expire` SNMP traps, you must enable email notification of SSL certificate expiration. To do so, use the `logging email-address` command from the global configuration level in the CLI. For more information, refer to the *Command Line Interface Reference*.
- To begin receiving the `resource-usage-warning` SNMP traps, you must set resource utilization thresholds for partitions.
- If you have a DNS anycast configuration, all ports of a given virtual server must to be down before an SNMP trap is sent.

NOTE: Enabling/disabling of traps in the L3V partition can only be done on the group level, and not on an individual trap level.

The following topics are covered:

GUI Configuration for Enabling SNMP Traps	28
CLI Configuration for Enabling SNMP Traps	29
CLI Configuration for Disabling the SNMP Traps for L3V Partitions	31

GUI Configuration for Enabling SNMP Traps

To enable the SNMP traps:

1. Hover over **System** in the navigation bar and select **Monitoring**.
2. Click **SNMP** on the menu bar and select **SNMP** from the drop-down menu that appears.
3. Click **Trap List** to display the traps you can add, sorted by category.
4. Select the checkbox next to any SNMP traps you want to enable.
5. Click **Configure SNMP** to save your changes.

CLI Configuration for Enabling SNMP Traps

The `snmp-server enable traps` command allows you to enable the SNMP traps. The following traps are available on the shared partition:

- all
- gslb
- lldp
- lsn
- network
- routing
- scaleout
- slb
- slb-change
- snmp
- system
- vcs
- vrrp-a

NOTE: On the L3V partition, only the all, snmp, gslb, slb, slb-change, and vrrp-a traps are available. For details on these traps, see the *Command Line Interface Reference*.

The following CLI command enables the SNMP traps for all SLB events. Note that using the ? allows you to see all the SNMP traps within the category before activating that category.

```
ACOS(config)# snmp-server enable traps slb ?
all                               Enable all SLB traps
application-buffer-limit          Enable application buffer reach limit trap
bw-rate-limit-exceed              Enable SLB server/port bandwidth rate limit
exceed                             trap
bw-rate-limit-resume              Enable SLB server/port bandwidth rate limit
resume                             trap
server-conn-limit                 Enable SLB server connection limit trap
server-conn-resume                Enable SLB server connection resume trap
server-disabled                   Enable SLB server-disabled trap
server-down                       Enable SLB server-down trap
server-selection-failure           Enable SLB server selection failure trap
server-up                         Enable slb server up trap
service-conn-limit                Enable SLB service connection limit trap
service-conn-resume               Enable SLB service connection resume trap
service-down                      Enable SLB service-down trap
service-group-down                Enable SLB service-group-down trap
service-group-member-down         Enable SLB service-group-member-down trap
service-group-member-up           Enable SLB service-group-member-up trap
service-group-up                  Enable SLB service-group-up trap
service-up                        Enable SLB service-up trap
vip-connnlimit                    Enable the virtual server reach conn-limit
trap
vip-connnratelimit                Enable the virtual server reach conn-rate-
limit                             trap
vip-down                          Enable SLB virtual server down trap
vip-port-connnlimit               Enable the virtual port reach conn-limit trap
vip-port-connnratelimit           Enable the virtual port reach conn-rate-limit
trap
vip-port-down                     Enable SLB virtual port down trap
vip-port-up                       Enable SLB virtual port up trap
vip-up                            Enable SLB virtual server up trap
```

The following CLI command enables the SNMP traps for all SLB changes. An SNMP trap will be sent whenever a change has been made to the SLB configuration. This includes the creation or deletion of virtual or real servers or ports, and changes to or near expiration of SSL certificates.

```
ACOS(config)# snmp-server enable traps slb-change
```

The following CLI commands enable the SNMP traps for the creation or removal of virtual and real servers and ports.

```
ACOS(config)# snmp-server enable traps slb-change server
ACOS(config)# snmp-server enable traps slb-change server-port
ACOS(config)# snmp-server enable traps slb-change vip
ACOS(config)# snmp-server enable traps slb-change vip-port
```

CLI Configuration for Disabling the SNMP Traps for L3V Partitions

ACOS allows you to enable the SNMP traps on shared partitions. The ACOS Device can disable traps on L3V partitions while the SNMP traps are still enabled on shared partitions. The default behavior is for both shared and L3V partition traps to be sent out when the SNMP traps are enabled on shared partitions.

When SNMP is disabled in the shared partition, no configuration change is required in any L3V partition. From the shared partition, the ACOS Device will not send any SNMP responses nor traps once SNMP is disabled.

NOTE: GSLB group traps are not partition-aware, so they cannot be controlled using the `snmp-server disable traps gslb` command.

To disable the SNMP traps on L3V partitions, use the CLI and make sure that you are in the configuration level for an L3V partition.

The following command helps to switch to the private partition named “pl3v,” and then disables the network and LLDP traps on this partition:

```
ACOS(config)# active-partition pl3v
ACOS[pl3v](config)# snmp-server disable traps network
ACOS[pl3v](config)# snmp-server disable traps LLDP
```

The community string is encrypted in the output of the **show running-config** command and cannot be viewed as readable text.

SNMP Configuration

By default, SNMP service is disabled for all data interfaces. See “Default Management Access Settings” in the *Management Access and Security Guide* for more information.

To configure SNMP:

1. If desired, configure location and contact information.
2. If desired, configure external SNMP trap receivers.
3. If desired, configure SNMPv1/v2c.
4. If desired, configure views, groups, and users.
5. Enable the SNMP agent and the SNMP traps.
6. Save the configuration changes.

You are not required to perform these configuration tasks in this order precisely. The workflow in the GUI may be slightly different from the workflow shown here.

The following topics are covered:

GUI Configuration	33
CLI Configuration	34

GUI Configuration

To configure the basic SNMP parameters:

1. Hover over **System** in the navigation bar, and select **Monitoring**.
2. Click **SNMP** on the menu bar and, then select **SNMP** from the drop-down list.
3. Configure general SNMP settings, including the system information, Engine ID, and trap host, in the General Fields section. Refer to the GUI online help for detailed information about each field.

4. Configure the SNMP trap settings by clicking and expanding the Trap List section and then select the traps that you want to monitor.
5. Click **Create SNMP Server**.

CLI Configuration

All SNMP configuration commands are available at the global configuration level of the CLI.

1. To configure SNMPv1/v2c, use the following command:

```
ACOS(config)# snmp-server snmpv1-v2c
```

2. To configure an SNMPv3 user, specify the username, group name, and authentication method. For example:

```
ACOS(config)# snmp-server snmpv3 user example-user group example-group  
v3 auth md5 example-password
```

3. To configure contact information, use the `snmp-server contact` command:

```
ACOS(config)# snmp-server contact example-contact
```

4. To enable the SNMP agent and SNMP traps, use the `snmp-server enable traps` command. For example, to enable all SNMP traps:

```
ACOS(config)# snmp-server enable traps all
```

5. To enable the SNMP schema agent for IP Anomaly Drop Statistics, and multi-PU platform, use the following command:

```
ACOS(config)# snmp-server enable schema-agent
```

6. To configure an SNMP group, specify the group name and security level. For example:

```
ACOS(config)# snmp-server group example-grou-name v3 auth read example-  
read-view-name
```

7. To configure the external SNMP trap receivers, use the `snmp-server host` command:

```
ACOS(config)# snmp-server host 10.10.10.10 version v3 user WDCS
```

8. To configure the location information, use the `snmp-server location` command:

```
ACOS(config)# snmp-server location example-location
```

9. To configure an SNMP view, use the following command:

```
ACOS(config)# snmp-server view example-view-name example-oid included
```

NOTE: For more information about these commands and other SNMP-related commands, refer to the *Command Line Interface Reference*.

Make sure that you run the `write memory` command to save the changes.

Source Interface for SNMP Notifications

You can specify a data interface to use as the source interface for the SNMP traps. By default, the management interface is the source interface for the SNMP traps.

- This feature does not support IPv6.
- This feature supports SNMPv1 but not SNMPv2c or SNMPv3.

The interface can be any of the following types:

- Ethernet
- VLAN / VE
- Loopback

When the ACOS Device sends an SNMP trap from the data interface you specify, the “agent-address” in the SNMP trap is the IP address for data interface.

The following topics are covered:

GUI Configuration	36
CLI Configuration	37

GUI Configuration

To configure an Ethernet interface as the source for the SNMP traps:

1. Hover over **Network** in the navigation bar and select **Interface**.
2. On the menu bar, click **LAN**.
3. Click **Edit** in the Actions column for the Ethernet interface.
4. Select the checkbox next to Trap Source in the General Fields section.
5. Click **Update**.

CLI Configuration

The following command attempts to set a loopback interface as the SNMP trap source. However, the feature has already been enabled on Ethernet port 1, and only one interface can be enabled for the SNMP traps, so this example shows that the existing trap source will be overwritten with the new one:

```
ACOS(config)# interface loopback 1  
ACOS(config-if:loopback:1)# snmp-server trap-source  
The trap source already exists for interface eth1. Do you want to  
overwrite? [yes/no]:yes  
ACOS(config-if:loopback:1)#
```

List of MIB Objects

This section will list the Management Information Base (MIB) objects supported in this release.

It will include each OID, its description, and its functional category.

A10-AX-CHASSIS_axChassisMgmt_oid_list

Field Name : axCurrFiveSecCtrlCpuUsageTable
Field Type : TABLE
Field Status : current
Description : The table contains current 5 second control cpu usage
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.10

Field Name : axCurrFiveSecDataCpuUsageTable
Field Type : TABLE
Field Status : current
Description : The table contains current 5 second data cpu usage
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.9

Field Name : axCurrFiveSecDataCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axCurrFiveSecDataCpuUsageTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.9.1

Field Name : axCurrFiveSecDataCpuUsage
Field Type : Integer32
Field Status : current
Description : The five second data cpu usage in the slot.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.9.1.3

Field Name : axCurrFiveSecDataCpuId
Field Type : Integer32
Field Status : current
Description : The data cpu id.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.9.1.2

Field Name : axCurrFiveSecDataCpuUsageSlotId
Field Type : Integer32
Field Status : current
Description : The slot id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.9.1.1

Field Name : axDiskTable
Field Type : TABLE
Field Status : current
Description : The table contains disk information
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.8

Field Name : axDiskEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axDiskTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.8.1

Field Name : axDiskFree
Field Type : Integer32
Field Status : current
Description : Free disk.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.8.1.4

Field Name : axDiskUsed
Field Type : Integer32
Field Status : current

A10-AX-CHASSIS_axChassisMgmt_oid_list

Description : Used disk.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.8.1.3

Field Name : axDiskTotal

Field Type : Integer32

Field Status : current

Description : Total Disk Space.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.8.1.2

Field Name : axDiskSlotId

Field Type : Integer32

Field Status : current

Description : The slot id of chassis.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.8.1.1

Field Name : axPowerSupplyTable

Field Type : TABLE

Field Status : current

Description : The table contains power supply.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.7

Field Name : axPowerSupplyEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axPowerSupplyTable

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.7.1

Field Name : axPowerSupplyStatus

Field Type : EnumVal

Field Status : current

Description : System Voltage status:

: 0: off, 1: on, 2: absent, -1: unknown.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.7.1.4

Field Name : axPowerSupplyName

Field Type : String

Field Status : current

Description : Power supply name.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.7.1.3

Field Name : axPowerSupplyIndex

Field Type : Integer32

Field Status : current

Description : The power supply index.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.7.1.2

Field Name : axPowerSupplySlotId

Field Type : Integer32

Field Status : current

Description : The slot id of chassis.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.7.1.1

Field Name : axSystemVoltageTable

Field Type : TABLE

Field Status : current

Description : The table contains system voltage.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.6

A10-AX-CHASSIS_axChassisMgmt_oid_list

Field Name : axSystemVoltageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axSystemVoltageTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.6.1

Field Name : axSystemVoltageDesc
Field Type : String
Field Status : current
Description : System voltage description.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.6.1.4

Field Name : axSystemVoltageStatus
Field Type : EnumVal
Field Status : current
Description : System Voltage status:
: 0: invalid, 1: normal, 2: unknown.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.6.1.3

Field Name : axSystemVoltageIndex
Field Type : Integer32
Field Status : current
Description : The system voltage index.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.6.1.2

Field Name : axSystemVoltageSlotId
Field Type : Integer32
Field Status : current
Description : The slot id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.6.1.1

Field Name : axMemoryTable
Field Type : TABLE
Field Status : current
Description : The table contains memory information
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.5

Field Name : axMemoryEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axMemoryTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.5.1

Field Name : axMemoryUsage
Field Type : Integer32
Field Status : current
Description : Memory Usage.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.5.1.3

Field Name : axMemoryTotal
Field Type : Integer32
Field Status : current
Description : Total Memory(KB).
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.5.1.2

Field Name : axMemorySlotId

A10-AX-CHASSIS_axChassisMgmt_oid_list

Field Type : Integer32
Field Status : current
Description : The slot id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.5.1.1

Field Name : axAverageDataCpuUsageTable
Field Type : TABLE
Field Status : current
Description : The table contains average data cpu usage
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.4

Field Name : axAverageDataCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axAverageDataCpuUsageTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.4.1

Field Name : axAverageDataCpuUsage
Field Type : Integer32
Field Status : current
Description : The average Data cpu usage in the slot.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.4.1.2

Field Name : axAverageDataCpuUsageSlotId
Field Type : Integer32
Field Status : current
Description : The slot id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.4.1.1

Field Name : axAverageControlCpuUsageTable
Field Type : TABLE
Field Status : current
Description : The table contains average control cpu usage.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.3

Field Name : axAverageControlCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axAverageControlCpuUsageTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.3.1

Field Name : axAverageControlCpuUsage
Field Type : Integer32
Field Status : current
Description : The average control cpu usage in the slot.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.3.1.2

Field Name : axAverageControlCpuUsageSlotId
Field Type : Integer32
Field Status : current
Description : The slot id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.3.1.1

Field Name : axTemperatureTable
Field Type : TABLE
Field Status : current
Description : The table contains system temperature.

A10-AX-CHASSIS_axChassisMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.2

Field Name : axTemperatureEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axTemperatureTable

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.2.1

Field Name : axTemperature

Field Type : EnumVal

Field Status : current

Description : The physical temperature.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.2.1.3

Field Name : axTemperatureIndex

Field Type : Integer32

Field Status : current

Description : The index of axTemperature

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.2.1.2

Field Name : axTemperatureSlotId

Field Type : Integer32

Field Status : current

Description : The slot id in chassis, slot id start from 1 for master.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.2.1.1

Field Name : axFanTable

Field Type : TABLE

Field Status : current

Description : The table contains system fan status

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1

Field Name : axFanEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axFanTable

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.1

Field Name : axFanSpeed

Field Type : Integer32

Field Status : current

Description : The fan speed.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.1.5

Field Name : axFanStatus

Field Type : EnumVal

Field Status : current

Description : Fan status:

: 0: Failed, 4: OK-fixed/high, 5: OK-low/med, 6: OK-med/med, 7:

: OK-med/high,

: -2: not ready, -1: unknown.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.1.4

Field Name : axFanName

Field Type : String

Field Status : current

Description : The system fan name.

A10-AX-CHASSIS_axChassisMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.1.3

Field Name : axFanIndex

Field Type : Integer32

Field Status : current

Description : The system fan index, index start from 1 which is the first fan.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.1.2

Field Name : axFanSlotId

Field Type : Integer32

Field Status : current

Description : The slot id in chassis, slot id start from 1 for master.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.1.1

Field Name : axCurrFiveSecCtrlCpuUsageEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axCurrFiveSecCtrlCpuUsageTable

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.10.1

Field Name : axCurrFiveSecCtrlCpuUsage

Field Type : Integer32

Field Status : current

Description : The five second control cpu usage in the slot.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.10.1.3

Field Name : axCurrFiveSecCtrlCpuId

Field Type : Integer32

Field Status : current

Description : The data cpu id.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.10.1.2

Field Name : axCurrFiveSecCtrlCpuUsageSlotId

Field Type : Integer32

Field Status : current

Description : The slot id of chassis.

OID : 1.3.6.1.4.1.22610.2.4.4.1.1.1.1.10.1.1

Field Name : axSlbL4StatsTable

Field Type : TABLE

Field Status : current

Description : The table contains slb layer 4 statistics

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.5.1

Field Name : axSlbL4StatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axSlbL4Table

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.5.1.1

Field Name : axSlbL4StatsNatNoSessionDrops

Field Type : CounterBasedGauge64

Field Status : current

Description : SLB L4 NAT no session drops.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.5.1.1.2

Field Name : axSlbL4StatsSlotId

A10-AX-CHASSIS_axChassisMgmt_oid_list

Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.5.1.1.1

Field Name : axFwGlobalStatsTable
Field Type : TABLE
Field Status : current
Description : The table contains fw global statistics.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1

Field Name : axFwSystemStatusTable
Field Type : TABLE
Field Status : current
Description : The table contains fw system-status.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.4

Field Name : axFwSystemStatusEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFwSystemStatusTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.4.1

Field Name : axFwSystemStatusDataSessionFree
Field Type : CounterBasedGauge64
Field Status : current
Description : The fw data session free.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.4.1.3

Field Name : axFwSystemStatusDataSessionUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : The fw data session used.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.4.1.2

Field Name : axFwSystemStatusSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.4.1.1

Field Name : axFwGlobalStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFwGlobalStatsTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1

Field Name : axFwDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall data session freed.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.8

Field Name : axFwFullconeCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall full cone creation failure.

A10-AX-CHASSIS_axChassisMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.7

Field Name : axFwActiveFullconeSession
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall active full cone session.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.6

Field Name : axFwUdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall udp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.5

Field Name : axFwUdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall udp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.4

Field Name : axFwTcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall tcp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.3

Field Name : axFwTcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : The firewall tcp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.2

Field Name : axFwGlobalStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.4.1.1.1

Field Name : axLsnGlobalStatsTable
Field Type : TABLE
Field Status : current
Description : The table contains cgnv6 lsn global statistics.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.4

Field Name : axLsnGlobalStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axLsnGlobalStatsTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.4.1

Field Name : axLsnGlobalStatsIcmpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : The lsn global icmp user quota exceeded
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.4.1.4

Field Name : axLsnGlobalStatsUdpUserQuotaExceeded

A10-AX-CHASSIS_axChassisMgmt_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : The lsn global udp user quota exceeded
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.4.1.3

Field Name : axLsnGlobalStatsTcpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : The lsn global tcp user quota exceeded
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.4.1.2

Field Name : axLsnGlobalStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.4.1.1

Field Name : axLsnSystemStatusNatPortUsageTable
Field Type : TABLE
Field Status : current
Description : The table contains nat port usage of cgnv6 lsn system-status.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3

Field Name : axLsnSystemStatusNatPortUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axLsnSystemStatusNatPortUsageTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3.1

Field Name : axLsnSystemStatusUdpNatPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : The udp nat port free on cgnv6 lsn system status
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3.1.5

Field Name : axLsnSystemStatusUdpNatPortUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : The udp nat port used on cgnv6 lsn system status
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3.1.4

Field Name : axLsnSystemStatusTcpNatPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : The tcp nat port free on cgnv6 lsn system status
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3.1.3

Field Name : axLsnSystemStatusTcpNatPortUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : The tcp nat port used on cgnv6 lsn system status
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3.1.2

Field Name : axLsnSystemStatusNatPortUsageSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .

A10-AX-CHASSIS_axChassisMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.3.1.1

Field Name : axLsnSystemStatusSessionTable

Field Type : TABLE

Field Status : current

Description : The table contains session of cgnv6 lsn system-status.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2

Field Name : axLsnSystemStatusSessionEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axLsnSystemStatusSessionTable

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2.1

Field Name : axLsnSystemStatusSMPSessionFree

Field Type : CounterBasedGauge64

Field Status : current

Description : The SMP session free on cgnv6 lsn system status

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2.1.5

Field Name : axLsnSystemStatusSMPSessionUsed

Field Type : CounterBasedGauge64

Field Status : current

Description : The SMP session used on cgnv6 lsn system status

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2.1.4

Field Name : axLsnSystemStatusDataSessionFree

Field Type : CounterBasedGauge64

Field Status : current

Description : The data session free on cgnv6 lsn system status

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2.1.3

Field Name : axLsnSystemStatusDataSessionUsed

Field Type : CounterBasedGauge64

Field Status : current

Description : The data session used on cgnv6 lsn system status

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2.1.2

Field Name : axLsnSystemStatusSessionSlotId

Field Type : Integer32

Field Status : current

Description : The slot-id of chassis .

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.2.1.1

Field Name : axLsnUserQuotaSessionTable

Field Type : TABLE

Field Status : current

Description : The table contains cgnv6 lsn user quota session count

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.1.1

Field Name : axLsnUserQuotaSessionEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axLsnUserQuotaSessionTable

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.1.1.1

Field Name : axLsnUserQuotaSessionCount

A10-AX-CHASSIS_axChassisMgmt_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : The total session of lsn user quota session.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.1.1.2

Field Name : axLsnUserQuotaSessionSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.1.1.1

Field Name : axLsnFullConeSessionStatsTable
Field Type : TABLE
Field Status : current
Description : The table contains cgnv6 lsn full-cone-session statistics.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.5.1

Field Name : axLsnFullConeSessionStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axLsnFullConeSessionStatsTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.5.1.1

Field Name : axLsnFullConeSessionStatsTotalSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : The lsn total full cone sessions.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.5.1.2

Field Name : axLsnFullConeSessionStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.1.5.1.1.1

Field Name : axNatPoolStatTable
Field Type : TABLE
Field Status : current
Description : The table contains pool statistics of cgnv6 nat pool.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.2.1

Field Name : axNatPoolStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axNatPoolStatTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.2.1.1

Field Name : axNatPoolStatUsers
Field Type : CounterBasedGauge64
Field Status : current
Description : The number of users of cgnv6 lsn nat pool.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.2.1.1.3

Field Name : axNatPoolStatPoolName
Field Type : String
Field Status : current
Description : The pool name of cgnv6 lsn nat pool.

A10-AX-CHASSIS_axChassisMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.2.1.1.2

Field Name : axNatPoolStatSlotId

Field Type : Integer32

Field Status : current

Description : The slot-id of chassis .

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.3.2.1.1.1

Field Name : axEthIntfStatsTable

Field Type : TABLE

Field Status : current

Description : The table contains ethernet interface statistics.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3

Field Name : axLifIntfStatsTable

Field Type : TABLE

Field Status : current

Description : The table contains lif interface statistics.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.2

Field Name : axLifIntfStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axLifIntfStatsTable.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.2.1

Field Name : axLifIntfStatsRateBitsSend

Field Type : CounterBasedGauge64

Field Status : current

Description : The rate bites send out on the lif interface.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.2.1.4

Field Name : axLifIntfStatsRateBitsRcv

Field Type : CounterBasedGauge64

Field Status : current

Description : The rate bites received on the lif interface.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.2.1.3

Field Name : axLifIntfStatsIntfName

Field Type : String

Field Status : current

Description : The lif interface name.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.2.1.2

Field Name : axLifIntfStatsSlotId

Field Type : Integer32

Field Status : current

Description : The slot-id of chassis .

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.2.1.1

Field Name : axVEIntfStatsTable

Field Type : TABLE

Field Status : current

Description : The table contains ve interface statistics.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.1

Field Name : axVEIntfStatsEntry

A10-AX-CHASSIS_axChassisMgmt_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVEIntfStatsTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.1.1

Field Name : axVEIntfStatsRateBitsSend
Field Type : CounterBasedGauge64
Field Status : current
Description : The rate bites send out on the ve interface.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.1.1.4

Field Name : axVEIntfStatsRateBitsRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : The rate bites received on the ve interface.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.1.1.3

Field Name : axVEIntfStatsIntfNum
Field Type : Integer32
Field Status : current
Description : The ve interface number.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.1.1.2

Field Name : axVEIntfStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.1.1.1

Field Name : axEthIntfStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axEthIntfStatsTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1

Field Name : axEthIntfStatUtilPercentOut
Field Type : Integer32
Field Status : current
Description : The output utilization in percentage.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.11

Field Name : axEthIntfStatUtilPercentIn
Field Type : Integer32
Field Status : current
Description : The input utilization in percentage
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.10

Field Name : axEthIntfStatCollisions
Field Type : CounterBasedGauge64
Field Status : current
Description : The number of collisions on this interface, incremented by the
: number of collisions experienced during transmissions of a frame
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.9

Field Name : axEthIntfStatDropsOut
Field Type : CounterBasedGauge64
Field Status : current

A10-AX-CHASSIS_axChassisMgmt_oid_list

Description : The number of packets aged out or with excessive transmission
: delays due to multiple deferrals.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.8

Field Name : axEthIntfStatDropsIn

Field Type : CounterBasedGauge64

Field Status : current

Description : The number of packets dropped on ingress for various reasons.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.7

Field Name : axEthIntfStatErrorsOut

Field Type : CounterBasedGauge64

Field Status : current

Description : The number of excessive collisions, incremented for each
: frame that experienced 16 collisions during transmission and
: was aborted.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.6

Field Name : axEthIntfStatErrorsIn

Field Type : CounterBasedGauge64

Field Status : current

Description : The number of received packets that are either undersized,
: oversized, or have FCS errors.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.5

Field Name : axEthIntfStatsRateBitsSend

Field Type : CounterBasedGauge64

Field Status : current

Description : The rate bites send out on the ethernet interface.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.4

Field Name : axEthIntfStatsRateBitsRcv

Field Type : CounterBasedGauge64

Field Status : current

Description : The rate bites received on the ethernet interface.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.3

Field Name : axEthIntfStatsIfNum

Field Type : Integer32

Field Status : current

Description : The ethernet interface number.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.2

Field Name : axEthIntfStatsSlotId

Field Type : Integer32

Field Status : current

Description : The slot-id of chassis .

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.2.3.1.1

Field Name : axSystemAppBufferTable

Field Type : TABLE

Field Status : current

Description : The table contains system application buffer data.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.5

Field Name : axSystemRadiusServerStatTable

Field Type : TABLE

A10-AX-CHASSIS_axChassisMgmt_oid_list

Field Status : current

Description : The table contains radius server statistics of system

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1

Field Name : axSystemRadiusServerStatEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axSystemRadiusServerStatTable

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1.1

Field Name : axSystemRadiusServerRequestTableFullDropped

Field Type : TABLE

Field Status : current

Description : The radius request table full dropped on system radius server statistics

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1.1.5

Field Name : axSystemRadiusServerRequestMalformedDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : The radius request malformed dropped on system radius server statistics

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1.1.4

Field Name : axSystemRadiusServerRequestBadSecretDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : The radius request bad secret dropped on system radius server statistics

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1.1.3

Field Name : axSystemRadiusServerRequestReceived

Field Type : CounterBasedGauge64

Field Status : current

Description : The radius request received on system radius server statistics

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1.1.2

Field Name : axSystemRadiusServerStatSlotId

Field Type : Integer32

Field Status : current

Description : The slot-id of chassis .

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.4.1.1.1

Field Name : axSessionStatsTable

Field Type : TABLE

Field Status : current

Description : The table contains session stats.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3

Field Name : axSessionStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axSessionStatsTable.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1

Field Name : axSessionStatsTcpEstabRate

Field Type : INTEGER

Field Status : current

Description : The TCP Estab Rate.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.97

A10-AX-CHASSIS_axChassisMgmt_oid_list

Field Name : axSessionStatsTcpHalfOpenCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : The TCP half open.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.14

Field Name : axSessionStatsTcpEstCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : The TCP established.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.13

Field Name : axSessionStatsConnCount
Field Type : CounterBasedGauge64
Field Status : current
Description : The global total connection count.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.5

Field Name : axSessionStatsTotalFwConn
Field Type : CounterBasedGauge64
Field Status : current
Description : The global total firewall connections.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.4

Field Name : axSessionStatsCurrFreeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : The global current free connections.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.3

Field Name : axSessionStatsUDP
Field Type : CounterBasedGauge64
Field Status : current
Description : The global UDP connections.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.2

Field Name : axSessionStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.3.1.1

Field Name : axSystemAppPerformanceTable
Field Type : TABLE
Field Status : current
Description : The table contains system app-performance cpi.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2

Field Name : axSystemAppPerformanceEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axSystemAppPerformanceTable.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2.1

Field Name : axSystemAppPerformanceFwCpi
Field Type : CounterBasedGauge64

A10-AX-CHASSIS_axChassisMgmt_oid_list

Field Status : current

Description : The FW cpi of global system app-performance.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2.1.5

Field Name : axSystemAppPerformanceNatCpi

Field Type : CounterBasedGauge64

Field Status : current

Description : The NAT cpi of global system app-performance.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2.1.4

Field Name : axSystemAppPerformanceNewConnections

Field Type : CounterBasedGauge64

Field Status : current

Description : The total new connections of global system app-performance.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2.1.3

Field Name : axSystemAppPerformanceCurrentConnections

Field Type : CounterBasedGauge64

Field Status : current

Description : The total current connections of global system app-performance.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2.1.2

Field Name : axSystemAppPerformanceSlotId

Field Type : Integer32

Field Status : current

Description : The slot-id of chassis .

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.2.1.1

Field Name : axGlobalThroughputTable

Field Type : TABLE

Field Status : current

Description : The table contains throughput.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.1

Field Name : axGlobalThroughputEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axGlobalThroughputTable.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.1.1

Field Name : axGlobalThroughput

Field Type : CounterBasedGauge64

Field Status : current

Description : The total throughput.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.1.1.2

Field Name : axGlobalThroughputSlotId

Field Type : Integer32

Field Status : current

Description : The slot-id of chassis .

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.1.1.1

Field Name : axSystemAppBufferEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axSystemAppBufferTable.

OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.5.1

A10-AX-CHASSIS_axChassisMgmt_oid_list

Field Name : axSystemAppBufferTotalDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of accumulative buffer drop.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.5.1.3

Field Name : axSystemAppBufferDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of buffer drop in last 10 seconds.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.5.1.2

Field Name : axSystemAppBufferSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.1.5.1.1

Field Name : axNetflowMonitorStatsTable
Field Type : TABLE
Field Status : current
Description : The table contains netflow monitor statistics
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.6.1

Field Name : axNetflowMonitorStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axNetflowMonitorTable
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.6.1.1

Field Name : axNetflowMonitorStatsCustSesEveNat44DelRecSentFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom sessoin event nat44 deletion records sent failure.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.6.1.1.4

Field Name : axNetflowMonitorStatsCustSesEveNat44CreatRecSentFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom sessoin event nat44 creation records sent failure.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.6.1.1.3

Field Name : axNetflowMonitorStatsName
Field Type : String
Field Status : current
Description : The netflow monitor name.
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.6.1.1.2

Field Name : axNetflowMonitorStatsSlotId
Field Type : Integer32
Field Status : current
Description : The slot-id of chassis .
OID : 1.3.6.1.4.1.22610.2.4.4.1.2.6.1.1.1

A10-AX-MIB_axMgmt_oid_list

Field Name : axFPGADropCounterTable
Field Type : TABLE
Field Status : current
Description : A table has information of FPGA drop-counter
: it will contain the result as the CLI command,
: 'show system platform drop-counter'
OID : 1.3.6.1.4.1.22610.2.4.3.25.2

Field Name : axFPGACount
Field Type : INTEGER
Field Status : current
Description : The number of FPGA in the platform.
OID : 1.3.6.1.4.1.22610.2.4.3.25.1

Field Name : axFPGADropCounterEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axAppGlobalSystemResourceUsage Table
OID : 1.3.6.1.4.1.22610.2.4.3.25.2.1

Field Name : axFPGADropCounterValue
Field Type : String
Field Status : current
Description : The value of the counter.
OID : 1.3.6.1.4.1.22610.2.4.3.25.2.1.4

Field Name : axFPGADropCounterName
Field Type : String
Field Status : current
Description : The counter name.
OID : 1.3.6.1.4.1.22610.2.4.3.25.2.1.3

Field Name : axFPGADropCounterFPGANum
Field Type : INTEGER
Field Status : current
Description : The FPGA number.
OID : 1.3.6.1.4.1.22610.2.4.3.25.2.1.2

Field Name : axFPGADropCounterIndex
Field Type : INTEGER
Field Status : current
Description : The index of the table.
OID : 1.3.6.1.4.1.22610.2.4.3.25.2.1.1

Field Name : axDDosStatsHWL4EntryMatchDrop
Field Type : Counter64
Field Status : current
Description : The number of HW L4 entry match drops.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.16

Field Name : axDDosStatsL4EntryMatchDrop
Field Type : Counter64
Field Status : current
Description : The number of L4 entry match drops.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.15

Field Name : axDDosStatsHWOutOfL4Entries

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The number of times HW is out of L4 entries.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.14

Field Name : axDDosStatsL4EntryRemovedFromHW
Field Type : Counter64
Field Status : current
Description : The number of L4 entries removed from HW.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.13

Field Name : axDDosStatsL4EntryAddedToHW
Field Type : Counter64
Field Status : current
Description : The number of L4 entries added to HW.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.12

Field Name : axDDosStatsL4EntryDeleted
Field Type : Counter64
Field Status : current
Description : The number of L4 entries deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.11

Field Name : axDDosStatsL4EntryAdded
Field Type : Counter64
Field Status : current
Description : The number of L4 entries added.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.10

Field Name : axDDosStatsHWL3EntryMatchDrop
Field Type : Counter64
Field Status : current
Description : The number of HW L3 entry match drops.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.9

Field Name : axDDosStatsL3EntryMatchDrop
Field Type : Counter64
Field Status : current
Description : The number of L3 entry match drops.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.8

Field Name : axDDosStatsTooManyL3Entries
Field Type : Counter64
Field Status : current
Description : The number of times L3 entries are exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.7

Field Name : axDDosStatsL3EntryRemovedFromHW
Field Type : Counter64
Field Status : current
Description : The number of L3 entries removed from HW.
OID : 1.3.6.1.4.1.22610.2.4.3.24.1.6

Field Name : axDDosStatsL3EntryAddedToHW
Field Type : Counter64
Field Status : current
Description : The number of L3 entries added to HW.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.24.1.5

Field Name : axDDosStatsL3EntryRemovedFromBGP

Field Type : Counter64

Field Status : current

Description : The number of L3 entries removed from BGP.

OID : 1.3.6.1.4.1.22610.2.4.3.24.1.4

Field Name : axDDosStatsL3EntryAddedToBGP

Field Type : Counter64

Field Status : current

Description : The number of L3 entries added to BGP.

OID : 1.3.6.1.4.1.22610.2.4.3.24.1.3

Field Name : axDDosStatsL3EntryDeleted

Field Type : Counter64

Field Status : current

Description : The number of L3 entries deleted.

OID : 1.3.6.1.4.1.22610.2.4.3.24.1.2

Field Name : axDDosStatsL3EntryAdded

Field Type : Counter64

Field Status : current

Description : The number of L3 entries added.

OID : 1.3.6.1.4.1.22610.2.4.3.24.1.1

Field Name : axVrrpGroupStatusTable

Field Type : TABLE

Field Status : current

Description : A table contains the Vrrp group status information.

OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1

Field Name : axVrrpGroupStatusEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axVrrpGroupStatus Table

OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1

Field Name : axVrrpGroupForcedStandBy

Field Type : EnumVal

Field Status : current

Description : It is forcedStandBy or not.

OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1.6

Field Name : axVrrpGroupPriority

Field Type : Integer32

Field Status : current

Description : The priority of this vrrp group.

OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1.5

Field Name : axVrrpGroupWeight

Field Type : Integer32

Field Status : current

Description : The Weight of this vrrp group.

OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1.4

Field Name : axVrrpGroupStatus

A10-AX-MIB_axMgmt_oid_list

Field Type : EnumVal
Field Status : current
Description : The status of this vrrp group.
OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1.3

Field Name : axVrrpUnit
Field Type : INTEGER
Field Status : current
Description : The devive id.
OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1.2

Field Name : axVrid
Field Type : INTEGER
Field Status : current
Description : The vrid. Zero(0) is default.
OID : 1.3.6.1.4.1.22610.2.4.3.23.1.1.1.1

Field Name : axIpv4InIpv6SessionMaxPacketsExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment Session max packets exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.39

Field Name : axIpv4InIpv6TooManyPacketsPerReassemblyDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment too many packets per reassembly drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.38

Field Name : axIpv4InIpv6FragmentProcessingDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment processing drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.37

Field Name : axIpv4InIpv6MtuExceedPolicyDrop
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 MTU exceed policy drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.36

Field Name : axIpv4InIpv6FragmentReassemblyFailure
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment reassembly failure.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.35

Field Name : axIpv4InIpv6FragmentMaxDataLengthExceed
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment max data length exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.34

Field Name : axIpv4InIpv6FragmentReassemblySuccess
Field Type : Counter64
Field Status : current
Description : The count of l3 ipv4 in ipv6 fragment reassembly success.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.33

Field Name : axIpv4InIpv6FragmentQueueFailure

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 fragment queue failure.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.32

Field Name : axIpv4InIpv6TotalQueuedFragmentsExceed

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 total queued fragments exceed.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.31

Field Name : axIpv4InIpv6DuplicateLastFragment

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 duplicate last fragment.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.30

Field Name : axIpv4InIpv6DuplicateFirstFragment

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 duplicate first fragment.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.29

Field Name : axIpv4InIpv6PayloadLengthOutOfBounds

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 payload length out of bounds.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.28

Field Name : axIpv4InIpv6PayloadLengthUnaligned

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 payload length unaligned.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.27

Field Name : axIpv4InIpv6FragmentQueueSuccess

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 fragment queue success.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.26

Field Name : axIpv4InIpv6FragmentationFastAgingUnset

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 fragmentation fast aging unset.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.25

Field Name : axIpv4InIpv6FragmentationFastAgingSet

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 fragmentation fast aging set.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.24

Field Name : axIpv4InIpv6OutOfSessionMemory

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 out of session memory.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.23

Field Name : axIpv4InIpv6TotalSessionsExceedDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 total sessions exceed drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.22

Field Name : axIpv4InIpv6FirstL4FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 first L4 fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.21

Field Name : axIpv4InIpv6FirstTcpFragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 first TCP fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.20

Field Name : axIpv4InIpv6FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.19

Field Name : axIpv4InIpv6BadIpLength
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 bad ip length.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.18

Field Name : axIpv4InIpv6OverlappingFragmentDropped
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 overlapping fragment dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.17

Field Name : axIpv4InIpv6OtherDropped
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 Other dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.16

Field Name : axIpv4InIpv6Ipv6InIpDropped
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 Ipv6-In-Ip dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.15

Field Name : axIpv4InIpv6IpInIpDropped
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 Ip-In-Ip dropped.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.14

Field Name : axIpv4InIpv6TcpDropped

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 TCP dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.13

Field Name : axIpv4InIpv6UdpDropped

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 UDP dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.12

Field Name : axIpv4InIpv6Icmpv6Dropped

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 ICMPv6 dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.11

Field Name : axIpv4InIpv6IcmpDropped

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 ICMP dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.10

Field Name : axIpv4InIpv6OtherReceived

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 other Received.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.9

Field Name : axIpv4InIpv6Ipv6InIpReceived

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 Ipv6-In-Ip Received.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.8

Field Name : axIpv4InIpv6IpInIpReceived

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 Ip-In-Ip Received.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.7

Field Name : axIpv4InIpv6TcpReceived

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 Tcp Received.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.6

Field Name : axIpv4InIpv6UdpReceived

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv4 in ipv6 UDP Received.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.5

Field Name : axIpv4InIpv6Icmpv6Received

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 ICMPv6 Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.4

Field Name : axIpv4InIpv6IcmpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 ICMP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.3

Field Name : axIpv4InIpv6SessionExpired
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 session expired.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.2

Field Name : axIpv4InIpv6SessionInsert
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 in ipv6 session inserts.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.3.1

Field Name : axIpv6SessionMaxPacketsExceed
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 fragment Session max packets exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.39

Field Name : axIpv6TooManyPacketsPerReassemblyDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 fragment too many packets per reassembly drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.38

Field Name : axIpv6FragmentProcessingDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 fragment processing drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.37

Field Name : axIpv6MtuExceedPolicyDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 MTU exceed policy drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.36

Field Name : axIpv6FragmentReassemblyFailure
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 fragment reassembly failure.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.35

Field Name : axIpv6FragmentMaxDataLengthExceed
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 fragment max data length exceed.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.34

Field Name : axIpv6FragmentReassemblySuccess

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv6 fragment reassembly success.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.33

Field Name : axIpv6FragmentQueueFailure

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv6 fragment queue failure.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.32

Field Name : axIpv6TotalQueuedFragmentsExceed

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv6 total queued fragments exceed.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.31

Field Name : axIpv6DuplicateLastFragment

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv6 duplicate last fragment.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.30

Field Name : axIpv6DuplicateFirstFragment

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv6 duplicate first fragment.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.29

Field Name : axIpv6PayloadLengthOutOfBounds

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv6 payload length out of bounds.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.28

Field Name : axIpv6PayloadLengthUnaligned

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv6 payload length unaligned.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.27

Field Name : axIpv6FragmentQueueSuccess

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv6 fragment queue success.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.26

Field Name : axIpv6FragmentationFastAgingUnset

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv6 fragmentation fast aging unset.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.25

Field Name : axIpv6FragmentationFastAgingSet

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 fragmentation fast aging set.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.24

Field Name : axIpv6OutOfSessionMemory
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 out of session memory.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.23

Field Name : axIpv6TotalSessionsExceedDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 total sessions exceed drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.22

Field Name : axIpv6FirstL4FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 first L4 fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.21

Field Name : axIpv6FirstTcpFragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 first TCP fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.20

Field Name : axIpv6FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.19

Field Name : axIpv6BadIpLength
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 bad ip length.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.18

Field Name : axIpv6OverlappingFragmentDropped
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 overlapping fragment dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.17

Field Name : axIpv6OtherDropped
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 Other dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.16

Field Name : axIpv6Ipv6InIpDropped
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 Ipv6-In-Ip dropped.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.15

Field Name : axIpv6IpInIpDropped
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 Ip-In-Ip dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.14

Field Name : axIpv6TcpDropped
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 TCP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.13

Field Name : axIpv6UdpDropped
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 UDP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.12

Field Name : axIpv6Icmpv6Dropped
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 ICMPv6 dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.11

Field Name : axIpv6IcmpDropped
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 ICMP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.10

Field Name : axIpv6OtherReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 other Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.9

Field Name : axIpv6Ipv6InIpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 Ipv6-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.8

Field Name : axIpv6IpInIpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 Ip-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.7

Field Name : axIpv6TcpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 Tcp Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.6

Field Name : axIpv6UdpReceived

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 UDP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.5

Field Name : axIpv6Icmpv6Received
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 ICMPv6 Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.4

Field Name : axIpv6IcmpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 ICMP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.3

Field Name : axIpv6SessionExpired
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 session expired.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.2

Field Name : axIpv6SessionInsert
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 session inserts.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.2.1

Field Name : axIpv4DDoSProtectionDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 fragment DDoS protection drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.43

Field Name : axIpv4HighCpuDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 fragment high cpu drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.42

Field Name : axIpv4LowCpuThresholdReached
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 fragment low cpu threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.41

Field Name : axIpv4HighCpuThresholdReached
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 fragment high cpu threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.40

Field Name : axIpv4SessionMaxPacketsExceed
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 fragment Session max packets exceed.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.39

Field Name : axIpv4TooManyPacketsPerReassemblyDrop

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 fragment too many packets per reassembly drop.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.38

Field Name : axIpv4FragmentProcessingDrop

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 fragment processing drop.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.37

Field Name : axIpv4MtuExceedPolicyDrop

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 MTU exceed policy drop.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.36

Field Name : axIpv4FragmentReassemblyFailure

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 fragment reassembly failure.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.35

Field Name : axIpv4FragmentMaxDataLengthExceed

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 fragment max data length exceed.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.34

Field Name : axIpv4FragmentReassemblySuccess

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 fragment reassembly success.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.33

Field Name : axIpv4FragmentQueueFailure

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 fragment queue failure.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.32

Field Name : axIpv4TotalQueuedFragmentsExceed

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 total queued fragments exceed.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.31

Field Name : axIpv4DuplicateLastFragment

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 duplicate last fragment.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.30

Field Name : axIpv4DuplicateFirstFragment

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 duplicate first fragment.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.29

Field Name : axIpv4PayloadLengthOutOfBounds
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 payload length out of bounds.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.28

Field Name : axIpv4PayloadLengthUnaligned
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 payload length unaligned.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.27

Field Name : axIpv4FragmentQueueSuccess
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 fragment queue success.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.26

Field Name : axIpv4FragmentationFastAgingUnset
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 fragmentation fast aging unset.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.25

Field Name : axIpv4FragmentationFastAgingSet
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 fragmentation fast aging set.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.24

Field Name : axIpv4OutOfSessionMemory
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 out of session memory.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.23

Field Name : axIpv4TotalSessionsExceedDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 total sessions exceed drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.22

Field Name : axIpv4FirstL4FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 first L4 fragment too small drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.21

Field Name : axIpv4FirstTcpFragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 first TCP fragment too small drop.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.20

Field Name : axIpv4FragmentTooSmallDrop

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 fragment too small drop.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.19

Field Name : axIpv4BadIpLength

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 bad ip length.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.18

Field Name : axIpv4OverlappingFragmentDropped

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 overlapping fragment dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.17

Field Name : axIpv4OtherDropped

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 Other dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.16

Field Name : axIpv4Ipv6InIpDropped

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 Ipv6-In-Ip dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.15

Field Name : axIpv4IpInIpDropped

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 Ip-In-Ip dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.14

Field Name : axIpv4TcpDropped

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 TCP dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.13

Field Name : axIpv4UdpDropped

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 UDP dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.12

Field Name : axIpv4Icmpv6Dropped

Field Type : Counter64

Field Status : current

Description : The count of 13 ipv4 ICMPv6 dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.11

Field Name : axIpv4IcmpDropped

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 ICMP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.10

Field Name : axIpv4OtherReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 other Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.9

Field Name : axIpv4Ipv6InIpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 Ipv6-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.8

Field Name : axIpv4IpInIpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 Ip-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.7

Field Name : axIpv4TcpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 Tcp Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.6

Field Name : axIpv4UdpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 UDP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.5

Field Name : axIpv4Icmpv6Received
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 ICMPv6 Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.4

Field Name : axIpv4IcmpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 ICMP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.3

Field Name : axIpv4SessionExpired
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 session expired.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.2

Field Name : axIpv4SessionInsert
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv4 session inserts.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.1.1

Field Name : axIpv6InIpv4SessionMaxPacketsExceed

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 fragment Session max packets exceed.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.39

Field Name : axIpv6InIpv4TooManyPacketsPerReassemblyDrop

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 fragment too many packets per reassembly drop.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.38

Field Name : axIpv6InIpv4FragmentProcessingDrop

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 fragment processing drop.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.37

Field Name : axIpv6InIpv4MtuExceedPolicyDrop

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 MTU exceed policy drop.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.36

Field Name : axIpv6InIpv4FragmentReassemblyFailure

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 fragment reassembly failure.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.35

Field Name : axIpv6InIpv4FragmentMaxDataLengthExceed

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 fragment max data length exceed.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.34

Field Name : axIpv6InIpv4FragmentReassemblySuccess

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 fragment reassembly success.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.33

Field Name : axIpv6InIpv4FragmentQueueFailure

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 fragment queue failure.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.32

Field Name : axIpv6InIpv4TotalQueuedFragmentsExceed

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 total queued fragments exceed.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.31

Field Name : axIpv6InIpv4DuplicateLastFragment

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 duplicate last fragment.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.30

Field Name : axIpv6InIpv4DuplicateFirstFragment
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 duplicate first fragment.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.29

Field Name : axIpv6InIpv4PayloadLengthOutOfBounds
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 payload length out of bounds.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.28

Field Name : axIpv6InIpv4PayloadLengthUnaligned
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 payload length unaligned.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.27

Field Name : axIpv6InIpv4FragmentQueueSuccess
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 fragment queue success.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.26

Field Name : axIpv6InIpv4FragmentationFastAgingUnset
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 fragmentation fast aging unset.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.25

Field Name : axIpv6InIpv4FragmentationFastAgingSet
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 fragmentation fast aging set.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.24

Field Name : axIpv6InIpv4OutOfSessionMemory
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 out of session memory.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.23

Field Name : axIpv6InIpv4TotalSessionsExceedDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 total sessions exceed drop.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.22

Field Name : axIpv6InIpv4FirstL4FragmentTooSmallDrop
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 first L4 fragment too small drop.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.21

Field Name : axIpv6InIpv4FirstTcpFragmentTooSmallDrop

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 first TCP fragment too small drop.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.20

Field Name : axIpv6InIpv4FragmentTooSmallDrop

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 fragment too small drop.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.19

Field Name : axIpv6InIpv4BadIpLength

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 bad ip length.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.18

Field Name : axIpv6InIpv4OverlappingFragmentDropped

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 overlapping fragment dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.17

Field Name : axIpv6InIpv4OtherDropped

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 Other dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.16

Field Name : axIpv6InIpv4Ipv6InIpDropped

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 Ipv6-In-Ip dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.15

Field Name : axIpv6InIpv4IpInIpDropped

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 Ip-In-Ip dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.14

Field Name : axIpv6InIpv4TcpDropped

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 TCP dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.13

Field Name : axIpv6InIpv4UdpDropped

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 UDP dropped.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.12

Field Name : axIpv6InIpv4Icmpv6Dropped

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 ICMPv6 dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.11

Field Name : axIpv6InIpv4IcmpDropped
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 ICMP dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.10

Field Name : axIpv6InIpv4OtherReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 other Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.9

Field Name : axIpv6InIpv4Ipv6InIpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 Ipv6-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.8

Field Name : axIpv6InIpv4IpInIpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 Ip-In-Ip Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.7

Field Name : axIpv6InIpv4TcpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 Tcp Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.6

Field Name : axIpv6InIpv4UdpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 UDP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.5

Field Name : axIpv6InIpv4Icmpv6Received
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 ICMPv6 Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.4

Field Name : axIpv6InIpv4IcmpReceived
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 ICMP Received.
OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.3

Field Name : axIpv6InIpv4SessionExpired
Field Type : Counter64
Field Status : current
Description : The count of 13 ipv6 in ipv4 session expired.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.2

Field Name : axIpv6InIpv4SessionInsert

Field Type : Counter64

Field Status : current

Description : The count of l3 ipv6 in ipv4 session inserts.

OID : 1.3.6.1.4.1.22610.2.4.3.21.1.4.1

Field Name : axGslbSiteSlbDeviceTable

Field Type : TABLE

Field Status : current

Description : A table has information of GSLB service ports

OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1

Field Name : axGslbSiteSlbDeviceEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axGslbSiteSlbDevices Table

OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1

Field Name : axGslbSiteSlbDeviceServiceIpCount

Field Type : Counter

Field Status : current

Description : The number of the service-ip entries.

OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.8

Field Name : axGslbSiteSlbDeviceAvailSessionCount

Field Type : Counter

Field Status : current

Description : The number of the available sessions in the SLB device entry.

OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.7

Field Name : axGslbSiteSlbDeviceSessionUtilization

Field Type : INTEGER

Field Status : current

Description : The session utilization of the SLB device entry in percentage.

OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.6

Field Name : axGslbSiteSlbDeviceAdminPreference

Field Type : INTEGER

Field Status : current

Description : The administrative preference of the SLB device entry.

OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.5

Field Name : axGslbSiteSlbDeviceProtocolFlag

Field Type : EnumVal

Field Status : current

Description : The SLB device with the GSLB protocol or local protocol.

OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.4

Field Name : axGslbSiteForSlbDeviceName

Field Type : String

Field Status : current

Description : The name of the slb-device entry.

OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.3

Field Name : axGslbSiteSlbForDeviceIpAddr

A10-AX-MIB_axMgmt_oid_list

Field Type : String
Field Status : current
Description : The IP address of the slb-device entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.2

Field Name : axGslbSiteSlbDeviceSiteName
Field Type : String
Field Status : current
Description : The site name of the slb-device entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.5.1.1.1

Field Name : axGslbServiceIpPortTable
Field Type : TABLE
Field Status : current
Description : A table has information of GSLB service ports
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1

Field Name : axGslbServiceIpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axGslbServicePorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1

Field Name : axGslbServiceIpPortCurrConns
Field Type : Counter64
Field Status : current
Description : The number of the current connections.
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1.6

Field Name : axGslbServiceIpPortActiveServerCount
Field Type : Counter
Field Status : current
Description : The number of the active real servers.
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1.5

Field Name : axGslbServiceIpPortProtocolFlag
Field Type : EnumVal
Field Status : current
Description : The service-ip port with the GSLB protocol or local protocol.
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1.4

Field Name : axGslbServiceIpPortOperState
Field Type : EnumVal
Field Status : current
Description : The service-ip port operational state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1.3

Field Name : axGslbServiceIpPortNum
Field Type : INTEGER
Field Status : current
Description : The port number of the service-ip port entry
OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1.2

Field Name : axGslbServiceIpPortAddr
Field Type : String
Field Status : current
Description : The IP address of the service-ip entry.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.20.4.1.1.1

Field Name : axGslbServiceIPTable

Field Type : TABLE

Field Status : current

Description : A table has information of GSLB service IPs

OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2

Field Name : axGslbServiceIPCount

Field Type : INTEGER

Field Status : current

Description : The number of axGslbServiceIPTable entries in the table.

OID : 1.3.6.1.4.1.22610.2.4.3.20.3.1

Field Name : axGslbServiceIPEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axGslbServiceIPs Table

OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1

Field Name : axGslbServiceIpHitCount

Field Type : Counter64

Field Status : current

Description : The hit count of the service-ip entry.

OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.9

Field Name : axGslbServiceIpServicePortCount

Field Type : Counter

Field Status : current

Description : The number of ports for the service-ip entry.

OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.8

Field Name : axGslbServiceIpProtocolFlag

Field Type : EnumVal

Field Status : current

Description : The service-ip with the GSLB protocol or local protocol.

OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.7

Field Name : axGslbServiceIpIsVirtualServerFlag

Field Type : EnumVal

Field Status : current

Description : The flag of virtual server.

OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.6

Field Name : axGslbServiceIpOperState

Field Type : EnumVal

Field Status : current

Description : The service-ip operational state.

OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.5

Field Name : axGslbServiceIpAdminState

Field Type : EnumVal

Field Status : current

Description : The service-ip administrative state.

OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.4

Field Name : axGslbServiceIpSiteName

A10-AX-MIB_axMgmt_oid_list

Field Type : String
Field Status : current
Description : The site name has the service-ip entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.3

Field Name : axGslbServiceIpName
Field Type : String
Field Status : current
Description : The name of the service-ip entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.2

Field Name : axGslbServiceIpAddr
Field Type : String
Field Status : current
Description : The IP address of the service-ip entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.3.2.1.1

Field Name : axGslbSiteDeviceStatsTable
Field Type : TABLE
Field Status : current
Description : A table has information of GSLB site devices
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3

Field Name : axGslbSiteStatsTable
Field Type : TABLE
Field Status : current
Description : A table has information of GSLB sites
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.2

Field Name : axGslbSiteStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axGslbSiteStats Table
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.2.1

Field Name : axGslbSiteHitCount
Field Type : Counter64
Field Status : current
Description : The hit count of the site.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.2.1.4

Field Name : axGslbSiteOperState
Field Type : EnumVal
Field Status : current
Description : The site operational state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.2.1.3

Field Name : axGslbSiteAdminState
Field Type : EnumVal
Field Status : current
Description : The site administrative state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.2.1.2

Field Name : axGslbSiteName
Field Type : String
Field Status : current
Description : The name of the site entry.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.20.2.2.1.1

Field Name : axGslbSiteCount

Field Type : INTEGER

Field Status : current

Description : The total number of sites.

OID : 1.3.6.1.4.1.22610.2.4.3.20.2.1

Field Name : axGslbSiteDeviceStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axGslbSiteDevicesStats Table

OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1

Field Name : axGslbSiteServiceIpHitCount

Field Type : Counter64

Field Status : current

Description : The hit count of the service-ip name in the site device entry.

OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.9

Field Name : axGslbSiteServiceIpOperState

Field Type : EnumVal

Field Status : current

Description : The service-ip operational state.

OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.8

Field Name : axGslbSiteServiceIpAdminState

Field Type : EnumVal

Field Status : current

Description : The service-ip administrative state.

OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.7

Field Name : axGslbSiteServiceIpName

Field Type : String

Field Status : current

Description : The service-ip name in the site device entry.

OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.6

Field Name : axGslbSiteSlbDeviceName

Field Type : String

Field Status : current

Description : The SLB device name in the site device entry.

OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.5

Field Name : axGslbSiteServiceIpPortNum

Field Type : INTEGER

Field Status : current

Description : The port number of the service-ip in the site device entry.

OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.4

Field Name : axGslbSiteServiceIpAddr

Field Type : String

Field Status : current

Description : The IP address of the service-ip in the site device entry.

OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.3

Field Name : axGslbSiteSlbDeviceIpAddr

A10-AX-MIB_axMgmt_oid_list

Field Type : String
Field Status : current
Description : The IP address of the SLB device in the site entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.2

Field Name : axGslbSiteNameInDeviceEntry
Field Type : String
Field Status : current
Description : The name of the site.
OID : 1.3.6.1.4.1.22610.2.4.3.20.2.3.1.1

Field Name : axGslbZoneServiceStatsTable
Field Type : TABLE
Field Status : current
Description : A table has information of GSLB zone services
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3

Field Name : axGslbZoneStatsTable
Field Type : TABLE
Field Status : current
Description : A table has information of GSLB zones
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2

Field Name : axGslbZoneStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axGslbStatsZones Table
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1

Field Name : axGslbZoneBackupModeCount
Field Type : Counter64
Field Status : current
Description : The count in backup mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.10

Field Name : axGslbZoneStickyModeCount
Field Type : Counter64
Field Status : current
Description : The count in sticky mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.9

Field Name : axGslbZoneServerModeCount
Field Type : Counter64
Field Status : current
Description : The count in server mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.8

Field Name : axGslbZoneCacheModeCount
Field Type : Counter64
Field Status : current
Description : The count in cache mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.7

Field Name : axGslbZoneProxyModeCount
Field Type : Counter64
Field Status : current
Description : The count in proxy mode.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.6

Field Name : axGslbZoneSentResponses

Field Type : Counter64

Field Status : current

Description : The number of sent response on the zone entry.

OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.5

Field Name : axGslbZoneReceivedQueries

Field Type : Counter64

Field Status : current

Description : The number of received queries on the zone entry.

OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.4

Field Name : axGslbZoneOperState

Field Type : EnumVal

Field Status : current

Description : The Zone operational state.

OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.3

Field Name : axGslbZoneAdminState

Field Type : EnumVal

Field Status : current

Description : The Zone administrative state.

OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.2

Field Name : axGslbZoneName

Field Type : String

Field Status : current

Description : The name of the zone entry.

OID : 1.3.6.1.4.1.22610.2.4.3.20.1.2.1.1

Field Name : axGslbZoneCount

Field Type : INTEGER

Field Status : current

Description : The number of axGslbZoneStatsTable entries in the table.

OID : 1.3.6.1.4.1.22610.2.4.3.20.1.1

Field Name : axGslbZoneServiceStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axGslbZoneServiceStats Table

OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1

Field Name : axGslbZoneServiceBackupModeCount

Field Type : Counter64

Field Status : current

Description : The count in backup mode.

OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.13

Field Name : axGslbZoneServiceStickyModeCount

Field Type : Counter64

Field Status : current

Description : The count in sticky mode.

OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.12

Field Name : axGslbZoneServiceServerModeCount

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The count in server mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.11

Field Name : axGslbZoneServiceCacheModeCount
Field Type : Counter64
Field Status : current
Description : The count in cache mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.10

Field Name : axGslbZoneServiceProxyModeCount
Field Type : Counter64
Field Status : current
Description : The count in proxy mode.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.9

Field Name : axGslbZoneServiceSentResponses
Field Type : Counter64
Field Status : current
Description : The number of sent response on the zone service entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.8

Field Name : axGslbZoneServiceReceivedQueries
Field Type : Counter64
Field Status : current
Description : The number of received queries on the zone service entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.7

Field Name : axGslbZoneServiceOperState
Field Type : EnumVal
Field Status : current
Description : The Zone Service operational state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.6

Field Name : axGslbZoneServiceAdminState
Field Type : EnumVal
Field Status : current
Description : The Zone Service administrative state.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.5

Field Name : axGslbZoneServicePortNum
Field Type : INTEGER
Field Status : current
Description : The port number of the zone service entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.4

Field Name : axGslbZoneServiceName
Field Type : String
Field Status : current
Description : The service name of the zone service entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.3

Field Name : axGslbZoneNameInServiceEntry
Field Type : String
Field Status : current
Description : The name of the zone in service entry.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.2

Field Name : axGslbZoneServiceFqdn
Field Type : String
Field Status : current
Description : The Fqdn of Zone Service Entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.1.3.1.1

Field Name : axGslbGroupTable
Field Type : TABLE
Field Status : current
Description : A table has information on GSLB groups.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1

Field Name : axGslbGroupEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axGslbGroup Table
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1

Field Name : axGslbGroupAddress
Field Type : String
Field Status : current
Description : The ip address of the member in the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.7

Field Name : axGslbGroupStatus
Field Type : EnumVal
Field Status : current
Description : The status of the member in the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.6

Field Name : axGslbGroupAttribute
Field Type : BitString
Field Status : current
Description : The attribute of the member in the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.5

Field Name : axGslbGroupPriority
Field Type : INTEGER
Field Status : current
Description : The priority of the member in the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.4

Field Name : axGslbGroupSysID
Field Type : String
Field Status : current
Description : The sys id of the member in the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.3

Field Name : axGslbGroupMember
Field Type : String
Field Status : current
Description : The member of the group in the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.2

Field Name : axGslbGroupName

A10-AX-MIB_axMgmt_oid_list

Field Type : String
Field Status : current
Description : The name of the axGslbGroupTable entry.
OID : 1.3.6.1.4.1.22610.2.4.3.20.6.1.1.1

Field Name : axSessionGlobalStatConnSMPFree
Field Type : Gauge
Field Status : current
Description : The count of free SMP connections.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.14

Field Name : axSessionGlobalStatConnSMPAllocated
Field Type : Gauge
Field Status : current
Description : The count of allocated SMP connections.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.13

Field Name : axSessionGlobalStatTCPSynHalfOpen
Field Type : Gauge
Field Status : current
Description : The count of TCP SYN half open.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.12

Field Name : axSessionGlobalStatConnFree
Field Type : Gauge
Field Status : current
Description : The count of freed connections.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.11

Field Name : axSessionGlobalStatConnCount
Field Type : Gauge
Field Status : current
Description : The count of current connections.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.10

Field Name : axSessionGlobalStatFreeCurrentConns
Field Type : Gauge
Field Status : current
Description : The count of free current connections.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.9

Field Name : axSessionGlobalStatReverseNATUDP
Field Type : Gauge
Field Status : current
Description : The count of reverse NAT UDP.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.7

Field Name : axSessionGlobalStatReverseNATTCP
Field Type : Gauge
Field Status : current
Description : The count of reverse NAT TCP.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.6

Field Name : axSessionGlobalStatOther
Field Type : Gauge
Field Status : current
Description : The count of others.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.19.1.5

Field Name : axSessionGlobalStatNonTcpUdpIPSession
Field Type : Gauge
Field Status : current
Description : The count of non TCP/UDP IP sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.4

Field Name : axSessionGlobalStatUDP
Field Type : Gauge
Field Status : current
Description : The count of UDP connections.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.3

Field Name : axSessionGlobalStatTCPHalfOpen
Field Type : Gauge
Field Status : current
Description : The count of TCP half open.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.2

Field Name : axSessionGlobalStatTCPEstablished
Field Type : Gauge
Field Status : current
Description : The count of TCP established.
OID : 1.3.6.1.4.1.22610.2.4.3.19.1.1

Field Name : axIpNatStatsDynamicMappingAclNameTable
Field Type : TABLE
Field Status : current
Description : A table has information of IP NAT interface inside/outside
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1

Field Name : axIpNatStatsDynamicMappingAclNameEndAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axIpNatStatsDynamicMappingEndAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.10

Field Name : axIpNatStatsDynamicMappingAclNameStartAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axIpNatStatsDynamicMappingStartAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.9

Field Name : axIpNatStatsDynamicMappingAclNameMissAddresses
Field Type : INTEGER
Field Status : current
Description : The total misses in the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.8

Field Name : axIpNatStatsDynamicMappingAclNameAllocAddresses
Field Type : INTEGER
Field Status : current
Description : The total allocated addresses in the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.7

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatStatsDynamicMappingAclNameTotalAddresses
Field Type : INTEGER
Field Status : current
Description : The total addresses in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.6

Field Name : axIpNatStatsDynamicMappingAclNameEndAddress
Field Type : String
Field Status : current
Description : The end address of the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.5

Field Name : axIpNatStatsDynamicMappingAclNameStartAddress
Field Type : String
Field Status : current
Description : The start address of the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.4

Field Name : axIpNatStatsDynamicMappingAclNamePoolName
Field Type : String
Field Status : current
Description : The IP source NAT pool name
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.3

Field Name : axIpNatStatsDynamicMappingAclNameAccessListID
Field Type : INTEGER
Field Status : current
Description : The access list id.
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.2

Field Name : axIpNatStatsDynamicMappingAclNameAccessListName
Field Type : String
Field Status : current
Description : The access list acl name.
OID : 1.3.6.1.4.1.22610.2.4.3.18.19.1.1.1

Field Name : axIpNatDsliteStatNoRadiusProfileMatch
Field Type : Counter64
Field Status : current
Description : The number of no radius profile match for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.48

Field Name : axIpNatDsliteStatNatHANatPoolUnusable
Field Type : Counter64
Field Status : current
Description : The number of HA nat pool unusable for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.47

Field Name : axIpNatDsliteStatNatPoolUnusable
Field Type : Counter64
Field Status : current
Description : The number of nat pool unusable for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.46

Field Name : axIpNatDsliteStatUdpPortOverloadingSessionFreed
Field Type : Counter64

A10-AX-MIB_axMgmt_oid_list

Field Status : current

Description : The number of UDP port overloading session freed for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.45

Field Name : axIpNatDsliteStatTcpPortOverloadingSessionFreed

Field Type : Counter64

Field Status : current

Description : The number of TCP port overloading session Freed for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.44

Field Name : axIpNatDsliteStatUdpPortOverloadingSessionCreated

Field Type : Counter64

Field Status : current

Description : The number of UDP port overloading session created for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.43

Field Name : axIpNatDsliteStatTcpPortOverloadingSessionCreated

Field Type : Counter64

Field Status : current

Description : The number of TCP port overloading session created for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.42

Field Name : axIpNatDsliteStatUdpPortOverloaded

Field Type : Counter64

Field Status : current

Description : The number of UDP port overloaded for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.41

Field Name : axIpNatDsliteStatTcpPortOverloaded

Field Type : Counter64

Field Status : current

Description : The number of TCP port overloaded for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.40

Field Name : axIpNatDsliteStatNatPoolMismatchDrop

Field Type : Counter64

Field Status : current

Description : The number of nat pool mismatch drop for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.39

Field Name : axIpNatDsliteStatEndpointIndependentFilterInboundLimitExceeded

Field Type : Counter64

Field Status : current

Description : The number of endpoint independent filter inbound limit exceeded for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.38

Field Name : axIpNatDsliteStatConnRateUserQuotaExceeded

Field Type : Counter64

Field Status : current

Description : The number of connect rate user quota exceeded for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.37

Field Name : axIpNatDsliteStatDataSessionUserQuotaExceeded

Field Type : Counter64

Field Status : current

Description : The number of data session user quota exceeded for the DsLite.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.36

Field Name : axIpNatDsliteStatPermitClassListDrop

Field Type : Counter64

Field Status : current

Description : The number of drop of permit class list for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.35

Field Name : axIpNatDsliteStatNoClassListMatch

Field Type : Counter64

Field Status : current

Description : The number of no class list match for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.34

Field Name : axIpNatDsliteStatLsnLidPassThrough

Field Type : Counter64

Field Status : current

Description : The number of pass through of lsn lid for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.33

Field Name : axIpNatDsliteStatLsnLidDrop

Field Type : Counter64

Field Status : current

Description : The number of drop of lsn lid for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.32

Field Name : axIpNatDsliteStatTruncatedPacket

Field Type : Counter64

Field Status : current

Description : The number of truncated packets for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.31

Field Name : axIpNatDsliteStatEndpointDependentFilterDrop

Field Type : Counter64

Field Status : current

Description : The number of endpoint independent filtering drop for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.30

Field Name : axIpNatDsliteStatEndpointIndependentFilterMatched

Field Type : Counter64

Field Status : current

Description : The number of endpoint independent filtering matched for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.29

Field Name : axIpNatDsliteStatEndpointIndependentMapMatched

Field Type : Counter64

Field Status : current

Description : The number of endpoint independent mapping for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.28

Field Name : axIpNatDsliteStatSelfHairpinDrop

Field Type : Counter64

Field Status : current

Description : The number of self hairpin drop for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.27

Field Name : axIpNatDsliteStatHairpinSessionCreated

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The number of created hairpin session for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.26

Field Name : axIpNatDsLiteStatFullConeSessionFailed
Field Type : Counter64
Field Status : current
Description : The number of failed full cone session for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.25

Field Name : axIpNatDsLiteStatUdpFullConeSessionFreed
Field Type : Counter64
Field Status : current
Description : The total ICMP ports allocated for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.24

Field Name : axIpNatDsliteStatUdpFullConeSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of created UDP full cone session for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.23

Field Name : axIpNatDsliteStatTcpFullConeSessionFreed
Field Type : Counter64
Field Status : current
Description : The number of freed TCP full cone session for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.22

Field Name : axIpNatDsliteStatTcpFullConeSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of created TCP full cone session for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.21

Field Name : axIpNatDsliteStatExtendedUserQuotaExceeded
Field Type : Counter64
Field Status : current
Description : The number of exceeded extend user quota for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.20

Field Name : axIpNatDsliteStatExtendedUserQuotaMatched
Field Type : Counter64
Field Status : current
Description : The number of Extended user quota matched for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.19

Field Name : axIpNatDsliteStatIcmpUserQuotaExceed
Field Type : Counter64
Field Status : current
Description : The total ICMP ports allocated for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.18

Field Name : axIpNatDsliteStatUdpUserQuotaExceed
Field Type : Counter64
Field Status : current
Description : The number of exceeding UDP user quota for the DsLite.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.17

Field Name : axIpNatDsliteStatTcpUserQuotaExceed

Field Type : Counter64

Field Status : current

Description : The number of exceeding TCP user quota for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.16

Field Name : axIpNatDsliteStatNewUserResourceUnAvail

Field Type : Counter64

Field Status : current

Description : The number of unavailable new user resource for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.15

Field Name : axIpNatDsliteStatIcmpNatPortUnavail

Field Type : Counter64

Field Status : current

Description : The number of unavailable ICM NAT ports for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.14

Field Name : axIpNatDsliteStatUdpNatPortUnAvail

Field Type : Counter64

Field Status : current

Description : The number of unavailable UDP NAT ports for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.13

Field Name : axIpNatDsliteStatTcpNatPortUnAvail

Field Type : Counter64

Field Status : current

Description : The number of unavailable TCP NAT ports DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.12

Field Name : axIpNatDsliteUserQuotaCreateFailed

Field Type : Counter64

Field Status : current

Description : The number of user quota creation failed for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.11

Field Name : axIpNatDsliteUserQuotaFreed

Field Type : Counter64

Field Status : current

Description : The number of user quota freed for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.10

Field Name : axIpNatDsliteUserQuotaCreated

Field Type : Counter64

Field Status : current

Description : The number of user quota created for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.9

Field Name : axIpNatDsliteStatDataSessionFreed

Field Type : Counter64

Field Status : current

Description : The number of session freed for the DsLite.

OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.8

Field Name : axIpNatDsliteStatDataSessionCreated

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The number of session created for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.7

Field Name : axIpNatDsliteStatTotalIcmpPortFreed
Field Type : Counter64
Field Status : current
Description : The total ICMP ports freed for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.6

Field Name : axIpNatDsliteStatTotalIcmpPortAlloc
Field Type : Counter64
Field Status : current
Description : The total ICMP ports allocated for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.5

Field Name : axIpNatDsliteStatTotalUdpPortFreed
Field Type : Counter64
Field Status : current
Description : The total UDP ports allocated for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.4

Field Name : axIpNatDsliteStatTotalUdpPortAlloc
Field Type : Counter64
Field Status : current
Description : The total UDP ports allocated for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.3

Field Name : axIpNatDsliteStatTotalTcpPortFreed
Field Type : Counter64
Field Status : current
Description : The total TCP ports freed for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.2

Field Name : axIpNatDsliteStatTotalTcpPortAlloc
Field Type : Counter64
Field Status : current
Description : The total TCP ports allocated for the DsLite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.6.1.1

Field Name : axIpNatNat64StatNoRadiusProfileMatch
Field Type : Counter64
Field Status : current
Description : The number of no radius profile match.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.48

Field Name : axIpNatNat64StatHANatPoolUnusable
Field Type : Counter64
Field Status : current
Description : The number of HA nat pool unusable.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.47

Field Name : axIpNatNat64StatNatPoolUnusable
Field Type : Counter64
Field Status : current
Description : The number of nat pool unusable.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.46

Field Name : axIpNatNat64StatUdpPortOverloadingSessionFreed

Field Type : Counter64

Field Status : current

Description : The number of UDP port overloading session Freed.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.45

Field Name : axIpNatNat64StatTcpPortOverloadingSessionFreed

Field Type : Counter64

Field Status : current

Description : The number of TCP port overloading session Freed.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.44

Field Name : axIpNatNat64StatUdpPortOverloadingSessionCreated

Field Type : Counter64

Field Status : current

Description : The number of UDP port overloading session created.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.43

Field Name : axIpNatNat64StatTcpPortOverloadingSessionCreated

Field Type : Counter64

Field Status : current

Description : The number of TCP port overloading session created.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.42

Field Name : axIpNatNat64StatUdpPortOverloaded

Field Type : Counter64

Field Status : current

Description : The number of UDP port overloaded.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.41

Field Name : axIpNatNat64StatTcpPortOverloaded

Field Type : Counter64

Field Status : current

Description : The number of TCP port overloaded.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.40

Field Name : axIpNatNat64StatEndPointIndependentFilteringInboundLimitExceeded

Field Type : Counter64

Field Status : current

Description : The number of endpoint independent filtering inbound limit exceeded.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.39

Field Name : axIpNatNat64StatConnRateUserQuotaExceeded

Field Type : Counter64

Field Status : current

Description : The number of connection rate user-quota exceeded.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.38

Field Name : axIpNatNat64StatDataSessionUserQuotaExceeded

Field Type : Counter64

Field Status : current

Description : The number of data session user-quota exceeded.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.37

Field Name : axIpNatNat64StatNatPoolMismatchDrop

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The number of nat pool mismatch drop for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.36

Field Name : axIpNatNat64StatNoClassListMatch
Field Type : Counter64
Field Status : current
Description : The number of no class list match for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.35

Field Name : axIpNatNat64StatLsnLidPassThrough
Field Type : Counter64
Field Status : current
Description : The number of pass through of lsn lid for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.34

Field Name : axIpNatNat64StatLsnLidDrop
Field Type : Counter64
Field Status : current
Description : The number of drop of lsn lid for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.33

Field Name : axIpNatNat64StatSourceAddrPrefixMatchDrop
Field Type : Counter64
Field Status : current
Description : The number of drop of source address prefix match for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.32

Field Name : axIpNatNat64StatLayer3ForwardPackets
Field Type : Counter64
Field Status : current
Description : The number of packets NAT64 layer 3 forwarded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.31

Field Name : axIpNatNat64StatEndpointDependentFilterDrop
Field Type : Counter64
Field Status : current
Description : The number of endpoint independent filtering drop for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.30

Field Name : axIpNatNat64StatEndpointIndependentFilterMatched
Field Type : Counter64
Field Status : current
Description : The number of endpoint independent filtering matched for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.29

Field Name : axIpNatNat64StatEndpointIndependentMapMatched
Field Type : Counter64
Field Status : current
Description : The number of endpoint independent mapping for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.28

Field Name : axIpNatNat64StatSelfHairpinDrop
Field Type : Counter64
Field Status : current
Description : The number of self hairpin drop for the NAT64.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.27

Field Name : axIpNatNat64StatHairpinSessionCreated

Field Type : Counter64

Field Status : current

Description : The number of created hairpin session for the NAT64.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.26

Field Name : axIpNatNat64StatFullConeSessionFailed

Field Type : Counter64

Field Status : current

Description : The number of failed full cone session for the NAT64.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.25

Field Name : axIpNatNat64StatUdpFullConeSessionFreed

Field Type : Counter64

Field Status : current

Description : The total ICMP ports allocated for the NAT64.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.24

Field Name : axIpNatNat64StatUdpFullConeSessionCreated

Field Type : Counter64

Field Status : current

Description : The number of created UDP full cone session for the NAT64.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.23

Field Name : axIpNatNat64StatTcpFullConeSessionFreed

Field Type : Counter64

Field Status : current

Description : The number of freed TCP full cone session for the NAT64.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.22

Field Name : axIpNatNat64StatTcpFullConeSessionCreated

Field Type : Counter64

Field Status : current

Description : The number of created TCP full cone session for the NAT64.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.21

Field Name : axIpNatNat64StatExtendedUserQuotaExceeded

Field Type : Counter64

Field Status : current

Description : The number of exceeded extend user quota for the NAT64.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.20

Field Name : axIpNatNat64StatExtendedUserQuotaMatched

Field Type : Counter64

Field Status : current

Description : The number of Extended user quota matched for the NAT64.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.19

Field Name : axIpNatNat64StatIcmpUserQuotaExceed

Field Type : Counter64

Field Status : current

Description : The total ICMP ports allocated for the NAT64.

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.18

Field Name : axIpNatNat64StatUdpUserQuotaExceed

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter64
Field Status : current
Description : The number of exceeding UDP user quota for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.17

Field Name : axIpNatNat64StatTcpUserQuotaExceed
Field Type : Counter64
Field Status : current
Description : The number of exceeding TCP user quota for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.16

Field Name : axIpNatNat64StatNewUserResourceUnAvail
Field Type : Counter64
Field Status : current
Description : The number of unavailable new user resource for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.15

Field Name : axIpNatNat64StatIcmpNatPortUnavail
Field Type : Counter64
Field Status : current
Description : The number of unavailable ICM NAT ports for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.14

Field Name : axIpNatNat64StatUdpNatPortUnAvail
Field Type : Counter64
Field Status : current
Description : The number of unavailable UDP NAT ports for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.13

Field Name : axIpNatNat64StatTcpNatPortUnAvail
Field Type : Counter64
Field Status : current
Description : The number of unavailable TCP NAT ports NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.12

Field Name : axIpNatNat64UserQuotaCreateFailed
Field Type : Counter64
Field Status : current
Description : The number of user quota creation failed for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.11

Field Name : axIpNatNat64UserQuotaFreed
Field Type : Counter64
Field Status : current
Description : The number of user quota freed for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.10

Field Name : axIpNatNat64UserQuotaCreated
Field Type : Counter64
Field Status : current
Description : The number of user quota created for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.9

Field Name : axIpNatNat64StatDataSessionFreed
Field Type : Counter64
Field Status : current
Description : The number of session freed for the NAT64.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.8

Field Name : axIpNatNat64StatDataSessionCreated
Field Type : Counter64
Field Status : current
Description : The number of session created for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.7

Field Name : axIpNatNat64StatTotalIcmpPortFreed
Field Type : Counter64
Field Status : current
Description : The total ICMP ports allocated for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.6

Field Name : axIpNatNat64StatTotalIcmpPortAlloc
Field Type : Counter64
Field Status : current
Description : The total ICMP ports allocated for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.5

Field Name : axIpNatNat64StatTotalUdpPortFreed
Field Type : Counter64
Field Status : current
Description : The total UDP ports allocated for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.4

Field Name : axIpNatNat64StatTotalUdpPortAlloc
Field Type : Counter64
Field Status : current
Description : The total UDP ports allocated for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.3

Field Name : axIpNatNat64StatTotalTcpPortFreed
Field Type : Counter64
Field Status : current
Description : The total TCP ports freed for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.2

Field Name : axIpNatNat64StatTotalTcpPortAlloc
Field Type : Counter64
Field Status : current
Description : The total TCP ports allocated for the NAT64.
OID : 1.3.6.1.4.1.22610.2.4.3.18.5.1.1

Field Name : axIpNatLsnPoolNameStatTable
Field Type : TABLE
Field Status : current
Description : A table has information of IP NAT Lsn Pool Statistics group by the pool name.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12

Field Name : axIpNatLsnPoolNameStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnPoolNameStats Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatLsnPoolNameStatTotalUsedIps
Field Type : Counter64
Field Status : current
Description : The number of ips used in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.25

Field Name : axIpNatLsnPoolNameStatTotalFreeIps
Field Type : Counter64
Field Status : current
Description : The number of free ips in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.24

Field Name : axIpNatLsnPoolNameStatTotalIps
Field Type : Counter64
Field Status : current
Description : The total number of ips in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.23

Field Name : axIpNatLsnPoolNameStatUdpHitFull
Field Type : Counter64
Field Status : current
Description : The number of times port limit reached for UDP port allocation in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.22

Field Name : axIpNatLsnPoolNameStatUdpPeak
Field Type : Counter64
Field Status : current
Description : The number of udp ports in the peak for the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.21

Field Name : axIpNatLsnPoolNameStatUdpReserved
Field Type : Counter64
Field Status : current
Description : The number reserved icmp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.20

Field Name : axIpNatLsnPoolNameStatUdpTotal
Field Type : Counter64
Field Status : current
Description : The total number of icmp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.19

Field Name : axIpNatLsnPoolNameStatUdpFreed
Field Type : Counter64
Field Status : current
Description : The number of port Udpicmp freed in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.18

Field Name : axIpNatLsnPoolNameStatUdpUsed
Field Type : Counter64
Field Status : current
Description : The number of port udp used in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.17

Field Name : axIpNatLsnPoolNameStatTcpHitFull
Field Type : Counter64
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The number of times port limit reached for TCP port allocation in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.16

Field Name : axIpNatLsnPoolNameStatTcpPeak
Field Type : Counter64
Field Status : current
Description : The number of tcp ports in the peak for the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.15

Field Name : axIpNatLsnPoolNameStatTcpReserved
Field Type : Counter64
Field Status : current
Description : The number reserved tcp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.14

Field Name : axIpNatLsnPoolNameStatTcpTotal
Field Type : Counter64
Field Status : current
Description : The total number of tcp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.13

Field Name : axIpNatLsnPoolNameStatTcpFreed
Field Type : Counter64
Field Status : current
Description : The number of port tcp freed in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.12

Field Name : axIpNatLsnPoolNameStatTcpUsed
Field Type : Counter64
Field Status : current
Description : The number of port tcp used in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.11

Field Name : axIpNatLsnPoolNameStatIcmpHitFull
Field Type : Counter64
Field Status : current
Description : The number of times port limit reached for ICMP port allocation in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.10

Field Name : axIpNatLsnPoolNameStatIcmpPeak
Field Type : Counter64
Field Status : current
Description : The number of icmp ports in the peak for the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.9

Field Name : axIpNatLsnPoolNameStatIcmpTotal
Field Type : Counter64
Field Status : current
Description : The total number of icmp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.7

Field Name : axIpNatLsnPoolNameStatIcmpFreed
Field Type : Counter64
Field Status : current
Description : The number of port icmp freed in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.6

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatLsnPoolNameStatIcmpUsed
Field Type : Counter64
Field Status : current
Description : The number of port icmp used in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.5

Field Name : axIpNatLsnPoolNameStatUsers
Field Type : Counter64
Field Status : current
Description : The number of users in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.4

Field Name : axIpNatLsnPoolNameEndAddress
Field Type : String
Field Status : current
Description : The pool end IP address.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.3

Field Name : axIpNatLsnPoolNameStatAddress
Field Type : String
Field Status : current
Description : The pool start IP address.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.2

Field Name : axIpNatLsnPoolNameStatPoolName
Field Type : String
Field Status : current
Description : The name of the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.12.1.1

Field Name : axIpNatLsnPoolStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnPoolStats Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1

Field Name : axIpNatLsnPoolStatUdpHitFull
Field Type : Counter64
Field Status : current
Description : The number of times port limit reached for UDP port allocation in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.21

Field Name : axIpNatLsnPoolStatUdpPeak
Field Type : Counter64
Field Status : current
Description : The number of udp ports in the peak for the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.20

Field Name : axIpNatLsnPoolStatUdpReserved
Field Type : Counter64
Field Status : current
Description : The number reserved icmp ports in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.19

Field Name : axIpNatLsnPoolStatUdpTotal
Field Type : Counter64

A10-AX-MIB_axMgmt_oid_list

Field Status : current

Description : The total number of icmp ports in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.18

Field Name : axIpNatLsnPoolStatUdpFreed

Field Type : Counter64

Field Status : current

Description : The number of port Udpicmp freed in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.17

Field Name : axIpNatLsnPoolStatUdpUsed

Field Type : Counter64

Field Status : current

Description : The number of port udp used in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.16

Field Name : axIpNatLsnPoolStatTcpHitFull

Field Type : Counter64

Field Status : current

Description : The number of times port limit reached for TCP port allocation in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.15

Field Name : axIpNatLsnPoolStatTcpPeak

Field Type : Counter64

Field Status : current

Description : The number of tcp ports in the peak for the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.14

Field Name : axIpNatLsnPoolStatTcpReserved

Field Type : Counter64

Field Status : current

Description : The number reserved tcp ports in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.13

Field Name : axIpNatLsnPoolStatTcpTotal

Field Type : Counter64

Field Status : current

Description : The total number of tcp ports in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.12

Field Name : axIpNatLsnPoolStatTcpFreed

Field Type : Counter64

Field Status : current

Description : The number of port tcp freed in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.11

Field Name : axIpNatLsnPoolStatTcpUsed

Field Type : Counter64

Field Status : current

Description : The number of port tcp used in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.10

Field Name : axIpNatLsnPoolStatIcmpHitFull

Field Type : Counter64

Field Status : current

Description : The number of times port limit reached for ICMP port allocation in the pool.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.9

Field Name : axIpNatLsnPoolStatIcmpPeak

Field Type : Counter64

Field Status : current

Description : The number of icmp ports in the peak for the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.8

Field Name : axIpNatLsnPoolStatIcmpReserved

Field Type : Counter64

Field Status : current

Description : The number reserved icmp ports in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.7

Field Name : axIpNatLsnPoolStatIcmpTotal

Field Type : Counter64

Field Status : current

Description : The total number of icmp ports in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.6

Field Name : axIpNatLsnPoolStatIcmpFreed

Field Type : Counter64

Field Status : current

Description : The number of port icmp freed in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.5

Field Name : axIpNatLsnPoolStatIcmpUsed

Field Type : Counter64

Field Status : current

Description : The number of port icmp used in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.4

Field Name : axIpNatLsnPoolStatUsers

Field Type : Counter64

Field Status : current

Description : The number of users in the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.3

Field Name : axIpNatLsnPoolStatAddress

Field Type : String

Field Status : current

Description : The IP address of the server.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.2

Field Name : axIpNatLsnPoolStatPoolName

Field Type : String

Field Status : current

Description : The name of the pool.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.11.1.1

Field Name : axIpNatLsnPoolGroupTable

Field Type : TABLE

Field Status : current

Description : Table has information of IP NAT Lsn Pool group statistics indexed by the pool group name.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatLsnPoolGroupCount

Field Type : INTEGER

Field Status : current

Description : The number of pool group in the system.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.1

Field Name : axIpNatLsnPoolGroupEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axIpNatLsnPoolGroup Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1

Field Name : axIpNatLsnPoolGroupFreedIp

Field Type : Counter64

Field Status : current

Description : The number of ip freed in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.23

Field Name : axIpNatLsnPoolGroupUsedIp

Field Type : Counter64

Field Status : current

Description : The number of IP addressed used in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.22

Field Name : axIpNatLsnPoolGroupTotalIp

Field Type : Counter64

Field Status : current

Description : Total number of IP addressed in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.21

Field Name : axIpNatLsnPoolGroupUdpHitFull

Field Type : Counter64

Field Status : current

Description : The number of times port limit reached for UDP port allocation in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.20

Field Name : axIpNatLsnPoolGroupUdpPeak

Field Type : Counter64

Field Status : current

Description : The peak number of UDP ports for the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.19

Field Name : axIpNatLsnPoolGroupUdpReserved

Field Type : Counter64

Field Status : current

Description : The number of reserved UDP ports in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.18

Field Name : axIpNatLsnPoolGroupUdpTotal

Field Type : Counter64

Field Status : current

Description : The total number of UDP ports in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.17

Field Name : axIpNatLsnPoolGroupUdpFreed

Field Type : Counter64

A10-AX-MIB_axMgmt_oid_list

Field Status : current

Description : The number of UDP ports freed in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.16

Field Name : axIpNatLsnPoolGroupUdpUsed

Field Type : Counter64

Field Status : current

Description : The number of UDP ports used in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.15

Field Name : axIpNatLsnPoolGroupTcpHitFull

Field Type : Counter64

Field Status : current

Description : The number of times port limit reached for TCP port allocation in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.14

Field Name : axIpNatLsnPoolGroupTcpPeak

Field Type : Counter64

Field Status : current

Description : The peak number of TCP ports for the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.13

Field Name : axIpNatLsnPoolGroupTcpReserved

Field Type : Counter64

Field Status : current

Description : The number of reserved TCP ports in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.12

Field Name : axIpNatLsnPoolGroupTcpTotal

Field Type : Counter64

Field Status : current

Description : The total number of tcp ports in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.11

Field Name : axIpNatLsnPoolGroupTcpFreed

Field Type : Counter64

Field Status : current

Description : The number of TCP ports freed in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.10

Field Name : axIpNatLsnPoolGroupTcpUsed

Field Type : Counter64

Field Status : current

Description : The number of TCP ports used in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.9

Field Name : axIpNatLsnPoolGroupIcmpHitFull

Field Type : Counter64

Field Status : current

Description : The number of times port limit reached for ICMP port allocation in the pool group.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.8

Field Name : axIpNatLsnPoolGroupIcmpPeak

Field Type : Counter64

Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The peak number of ICMP ports for the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.7

Field Name : axIpNatLsnPoolGroupIcmpReserved
Field Type : Counter64
Field Status : current
Description : The number reserved ICMP ports in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.6

Field Name : axIpNatLsnPoolGroupIcmpTotal
Field Type : Counter64
Field Status : current
Description : The total number of ICMP ports in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.5

Field Name : axIpNatLsnPoolGroupIcmpFreed
Field Type : Counter64
Field Status : current
Description : The number of ICMP ports freed in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.4

Field Name : axIpNatLsnPoolGroupIcmpUsed
Field Type : Counter64
Field Status : current
Description : The number of port icmp used in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.3

Field Name : axIpNatLsnPoolGroupUsers
Field Type : Counter64
Field Status : current
Description : The number of users in the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.2

Field Name : axIpNatLsnPoolGroupName
Field Type : String
Field Status : current
Description : The name of the pool group.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.14.13.2.1.1

Field Name : axIpNatLsnAlgSipStatMethodUnknown
Field Type : Counter64
Field Status : current
Description : The number of Sip method unknown on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.15

Field Name : axIpNatLsnAlgSipStatMethodUpdate
Field Type : Counter64
Field Status : current
Description : The number of Sip method update on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.14

Field Name : axIpNatLsnAlgSipStatMethodMessage
Field Type : Counter64
Field Status : current
Description : The number of Sip method message on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.13

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatLsnAlgSipStatMethodRefer
Field Type : Counter64
Field Status : current
Description : The number of Sip method refer on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.12

Field Name : axIpNatLsnAlgSipStatMethodInfo
Field Type : Counter64
Field Status : current
Description : The number of Sip method info on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.11

Field Name : axIpNatLsnAlgSipStatMethodPublish
Field Type : Counter64
Field Status : current
Description : The number of Sip method publish on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.10

Field Name : axIpNatLsnAlgSipStatMethodNotify
Field Type : Counter64
Field Status : current
Description : The number of Sip method notify on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.9

Field Name : axIpNatLsnAlgSipStatMethodSubscribe
Field Type : Counter64
Field Status : current
Description : The number of Sip method subscribte on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.8

Field Name : axIpNatLsnAlgSipStatMethodPrack
Field Type : Counter64
Field Status : current
Description : The number of Sip method Prack on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.7

Field Name : axIpNatLsnAlgSipStatMethodOptions
Field Type : Counter64
Field Status : current
Description : The number of Sip method options on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.6

Field Name : axIpNatLsnAlgSipStatMethodBye
Field Type : Counter64
Field Status : current
Description : The number of Sip method bye on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.5

Field Name : axIpNatLsnAlgSipStatMethodCancel
Field Type : Counter64
Field Status : current
Description : The number of Sip method cancel on Ip Nat Lsn.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.4

Field Name : axIpNatLsnAlgSipStatMethodAck
Field Type : Counter64
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The number of Sip method Ack on Ip Nat Lsn.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.3

Field Name : axIpNatLsnAlgSipStatMethodInvite

Field Type : Counter64

Field Status : current

Description : The number of Sip method invite on Ip Nat Lsn.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.2

Field Name : axIpNatLsnAlgSipStatMethodRegister

Field Type : Counter64

Field Status : current

Description : The number of Sip method register on Ip Nat Lsn.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.13.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotUdpPortTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 global pool IPs and total number of UDP ports.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.12.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotUdpPortEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axIpNatLsnTop5GlobalPoolIpAddrTotUdpPorts Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.12.1.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotNumUdpPorts

Field Type : Integer32

Field Status : current

Description : The total number of UDP ports in the Top 5 global pool IPs entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.12.1.1.2

Field Name : axIpNatLsnTop5GlobalPoolIpAddrInUdp

Field Type : String

Field Status : current

Description : The global pool IP address in the Top 5 global pool IPs entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.12.1.1.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotTcpPortTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 global pool IPs and total number of TCP ports.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.11.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotTcpPortEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axIpNatLsnTop5GlobalPoolIpAddrTotTcpPorts Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.11.1.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotNumTcpPorts

Field Type : Integer32

Field Status : current

Description : The total number of TCP ports in the Top 5 global pool IPs entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.11.1.1.2

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatLsnTop5GlobalPoolIpAddrInTcp

Field Type : String

Field Status : current

Description : The global pool IP address in the Top 5 global pool IPs entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.11.1.1.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotUserTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 global pool IPs and total number of users.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.10.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotUserEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axIpNatLsnTop5GlobalPoolIpAddrTotUsers Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.10.1.1

Field Name : axIpNatLsnTop5GlobalPoolIpAddrTotNumUsers

Field Type : Integer32

Field Status : current

Description : The total number of users in the Top 5 global pool IPs entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.10.1.1.2

Field Name : axIpNatLsnTop5GlobalPoolIpAddr

Field Type : String

Field Status : current

Description : The global pool IP address in the Top 5 global pool IPs entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.10.1.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotIcmpSessionTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 users private IPs and total number of sessions.

: To monitor users who use most of resources: pick up global pool IP which

: ports are most used total of TCP/UDP/ICMP sessions;

: then, find out the top 5 users who use the global pool most used total of ICMP sessions.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.9.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotIcmpSessionEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axIpNatLsnTop5UserPrivateIpAddrTotIcmpSessions Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.9.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrGlobalIpAddrInIcmp

Field Type : String

Field Status : current

Description : The global IP address in the Top 5 user entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.9.1.1.3

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotNumIcmpSessions

Field Type : Integer32

Field Status : current

Description : The total number of ICMP sessions in the Top 5 user entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.9.1.1.2

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatLsnTop5UserPrivateIpAddrInIcmp

Field Type : String

Field Status : current

Description : The private IP address in the Top 5 user entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.9.1.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotUdpSessionTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 users private IPs and total number of sessions.

: To monitor users who use most of resources: pick up global pool IP which

: ports are most used total of TCP/UDP/ICMP sessions;

: then, find out the top 5 users who use the global pool most used total of UDP sessions.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.8.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotUdpSessionEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axIpNatLsnTop5UserPrivateIpAddrTotUdpSessions Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.8.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrGlobalIpAddrInUdp

Field Type : String

Field Status : current

Description : The global IP address in the Top 5 user entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.8.1.1.3

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotNumUdpSessions

Field Type : Integer32

Field Status : current

Description : The total number of UDP sessions in the Top 5 user entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.8.1.1.2

Field Name : axIpNatLsnTop5UserPrivateIpAddrInUdp

Field Type : String

Field Status : current

Description : The private IP address in the Top 5 user entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.8.1.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotTcpSessionTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 users private IPs and total number of sessions.

: To monitor users who use most of resources: pick up global pool IP which

: ports are most used total of TCP/UDP/ICMP sessions;

: then, find out the top 5 users who use the global pool most used total of TCP sessions.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.7.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotTcpSessionEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axIpNatLsnTop5UserPrivateIpAddrTotTcpSessions Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.7.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrGlobalIpAddrInTcp

Field Type : String

Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The global IP address in the Top 5 user entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.7.1.1.3

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotNumTcpSessions

Field Type : Integer32

Field Status : current

Description : The total number of TCP sessions in the Top 5 user entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.7.1.1.2

Field Name : axIpNatLsnTop5UserPrivateIpAddrInTcp

Field Type : String

Field Status : current

Description : The private IP address in the Top 5 user entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.7.1.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotSessionTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 users private IPs and total number of sessions.

: To monitor users who use most of resources: pick up global pool IP which

: ports are most used total of TCP/UDP/ICMP sessions;

: then, find out the top 5 users who use the global pool most used total of TCP/UDP/ICMP sessions.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.6.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotSessionEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axIpNatLsnTop5UserPrivateIpAddrTotSessions Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.6.1.1

Field Name : axIpNatLsnTop5UserPrivateIpAddrGlobalIpAddr

Field Type : String

Field Status : current

Description : The global IP address in the Top 5 user entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.6.1.1.3

Field Name : axIpNatLsnTop5UserPrivateIpAddrTotNumSessions

Field Type : Integer32

Field Status : current

Description : The total number of TCP/UDP/ICMP sessions in the Top 5 user entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.6.1.1.2

Field Name : axIpNatLsnTop5UserPrivateIpAddr

Field Type : String

Field Status : current

Description : The private IP address in the Top 5 user entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.6.1.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotIcmpPortTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 private IPs and total number of ICMP ports.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.5.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotIcmpPortEntry

Field Type : CounterBasedGauge64

Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : Columns in the axIpNatLsnTop5PrivateIpAddrTotIcmpPorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.5.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrGlobalIpAddrInIcmpPort
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.5.1.1.3

Field Name : axIpNatLsnTop5PrivateIpAddrTotNumIcmpPorts
Field Type : Integer32
Field Status : current
Description : The total number of ICMP sessions in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.5.1.1.2

Field Name : axIpNatLsnTop5PrivateIpAddrInIcmpPort
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.5.1.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotUdpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 private IPs and total number of UDP ports.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.4.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotUdpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnTop5PrivateIpAddrTotUdpPorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.4.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrGlobalIpAddrInUdpPort
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.4.1.1.3

Field Name : axIpNatLsnTop5PrivateIpAddrTotNumUdpPorts
Field Type : Integer32
Field Status : current
Description : The total number of UDP sessions in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.4.1.1.2

Field Name : axIpNatLsnTop5PrivateIpAddrInUdpPort
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.4.1.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotTcpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 private IPs and total number of TCP ports.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.3.1

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatLsnTop5PrivateIpAddrTotTcpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnTop5PrivateIpAddrTotTcpPorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.3.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrGlobalIpAddrInTcpPort
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.3.1.1.3

Field Name : axIpNatLsnTop5PrivateIpAddrTotNumTcpPorts
Field Type : Integer32
Field Status : current
Description : The total number of TCP sessions in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.3.1.1.2

Field Name : axIpNatLsnTop5PrivateIpAddrInTcpPort
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.3.1.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotSessionTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 private IPs and total number of sessions(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.2.1

Field Name : axIpNatLsnTop5PrivateIpAddrTotSessionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatLsnTop5PrivateIpAddrTotSessions Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.2.1.1

Field Name : axIpNatLsnTop5PrivateIpAddrGlobalIpAddr
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.2.1.1.3

Field Name : axIpNatLsnTop5PrivateIpAddrTotNumSessions
Field Type : Integer32
Field Status : current
Description : The total number of sessions in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.2.1.1.2

Field Name : axIpNatLsnTop5PrivateIpAddr
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.2.1.1.1

Field Name : axIpNatLsnSessionLsnCps
Field Type : Counter64
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The LSN CPS.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.5.5

Field Name : axIpNatLsnSessionSmpSessionsFree

Field Type : Counter64

Field Status : current

Description : The number of SMP sessions free.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.5.4

Field Name : axIpNatLsnSessionSmpSessionsUsed

Field Type : Counter64

Field Status : current

Description : The number of SMP sessions used.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.5.3

Field Name : axIpNatLsnSessionDataSessionsFree

Field Type : Counter64

Field Status : current

Description : The number of data sessions free.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.5.2

Field Name : axIpNatLsnSessionDataSessionsUsed

Field Type : Counter64

Field Status : current

Description : The number of data sessions used.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.5.1

Field Name : axIpNatLsnTrafficNewUserResourceUnavailable64Gauge

Field Type : Counter64

Field Status : current

Description : The total number of NAT resource unavailable for new users.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.32

Field Name : axIpNatLsnTrafficNatPortUnavailable64Gauge

Field Type : Counter64

Field Status : current

Description : The total number of NAT port unavailable.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.31

Field Name : axIpNatLsnTrafficExtendedUserQuotasExceeded64Gauge

Field Type : Counter64

Field Status : current

Description : The total number of extended user-quotas exceeded.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.30

Field Name : axIpNatLsnTrafficExtendedUserQuotasMatch64Gauge

Field Type : Counter64

Field Status : current

Description : The total number of extended user-quotas matches.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.29

Field Name : axIpNatLsnTrafficTcpUserQuotasExceeded64Gauge

Field Type : Counter64

Field Status : current

Description : The total number of TCP user-quotas exceeded.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.28

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatLsnTrafficUdpUserQuotasExceeded64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of UDP user-quotas exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.27

Field Name : axIpNatLsnTrafficIcmpUserQuotasExceeded64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of ICMP user-quotas exceeded.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.26

Field Name : axIpNatLsnTrafficFailsInUserQuotasCreation64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of user-quotas creation failure.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.25

Field Name : axIpNatLsnTrafficUserQuotasFreed64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of user-quotas freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.24

Field Name : axIpNatLsnTrafficUserQuotasCreated64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of user-quotas created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.23

Field Name : axIpNatLsnTrafficEndpointIndepFilterMatch64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of endpoint independent filtering match.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.22

Field Name : axIpNatLsnTrafficEndpointIndepMapMatch64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of endpoint independent mapping match.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.21

Field Name : axIpNatLsnTrafficHairpinSessionCreated64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of hairpin session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.20

Field Name : axIpNatLsnTrafficFailsInFullConeSessionCreation64Gauge
Field Type : Counter64
Field Status : current
Description : The total number of full-cone session creation failure.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.19

Field Name : axIpNatLsnTrafficFullConeSessionFreed64Gauge
Field Type : Counter64
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The total number of full-cone session freed.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.18

Field Name : axIpNatLsnTrafficFullConeSessionCreated64Gauge

Field Type : Counter64

Field Status : current

Description : The total number of full-cone session created.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.17

Field Name : axIpNatLsnTrafficNewUserResourceUnavailable

Field Type : Integer32

Field Status : current

Description : The total number of NAT resource unavailable for new users.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.16

Field Name : axIpNatLsnTrafficNatPortUnavailable

Field Type : Integer32

Field Status : current

Description : The total number of NAT port unavailable.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.15

Field Name : axIpNatLsnTrafficExtendedUserQuotasExceeded

Field Type : Integer32

Field Status : current

Description : The total number of extended user-quotas exceeded.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.14

Field Name : axIpNatLsnTrafficExtendedUserQuotasMatch

Field Type : Integer32

Field Status : current

Description : The total number of extended user-quotas matches.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.13

Field Name : axIpNatLsnTrafficTcpUserQuotasExceeded

Field Type : Integer32

Field Status : current

Description : The total number of TCP user-quotas exceeded.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.12

Field Name : axIpNatLsnTrafficUdpUserQuotasExceeded

Field Type : Integer32

Field Status : current

Description : The total number of UDP user-quotas exceeded.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.11

Field Name : axIpNatLsnTrafficIcmpUserQuotasExceeded

Field Type : Integer32

Field Status : current

Description : The total number of ICMP user-quotas exceeded.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.10

Field Name : axIpNatLsnTrafficFailsInUserQuotasCreation

Field Type : Integer32

Field Status : current

Description : The total number of user-quotas creation failure.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.9

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatLsnTrafficUserQuotasFreed
Field Type : Integer32
Field Status : current
Description : The total number of user-quotas freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.8

Field Name : axIpNatLsnTrafficUserQuotasCreated
Field Type : Integer32
Field Status : current
Description : The total number of user-quotas created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.7

Field Name : axIpNatLsnTrafficEndpointIndepFilterMatch
Field Type : Integer32
Field Status : current
Description : The total number of endpoint independent filtering match.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.6

Field Name : axIpNatLsnTrafficEndpointIndepMapMatch
Field Type : Integer32
Field Status : current
Description : The total number of endpoint independent mapping match.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.5

Field Name : axIpNatLsnTrafficHairpinSessionCreated
Field Type : Integer32
Field Status : current
Description : The total number of hairpin session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.4

Field Name : axIpNatLsnTrafficFailsInFullConeSessionCreation
Field Type : Integer32
Field Status : current
Description : The total number of full-cone session creation failure.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.3

Field Name : axIpNatLsnTrafficFullConeSessionFreed
Field Type : Integer32
Field Status : current
Description : The total number of full-cone session freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.2

Field Name : axIpNatLsnTrafficFullConeSessionCreated
Field Type : Integer32
Field Status : current
Description : The total number of full-cone session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.4.1

Field Name : axIpNatLsnTotalFullConeSessions
Field Type : Integer32
Field Status : current
Description : The total number of full cone sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.3

Field Name : axIpNatLsnTotalIpAddrTranslated
Field Type : Integer32
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The total number of global (translated) Ip addresses which has at least 1 users.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.2

Field Name : axIpNatLsnTotalUserQuotaSessions

Field Type : Integer32

Field Status : current

Description : The total number of user-quota sessions.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.1

Field Name : axIpNatLsnNatPortUdpNatPortFree

Field Type : Counter64

Field Status : current

Description : The number of UDP NAT ports free.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.6.4

Field Name : axIpNatLsnNatPortUdpNatPortUsed

Field Type : Counter64

Field Status : current

Description : The number of UDP NAT ports used.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.6.3

Field Name : axIpNatLsnNatPortTcpNatPortFree

Field Type : Counter64

Field Status : current

Description : The number of TCP NAT ports free.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.6.2

Field Name : axIpNatLsnNatPortTcpNatPortUsed

Field Type : Counter64

Field Status : current

Description : The number of TCP NAT ports used.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.1.6.1

Field Name : axIpNatLsnRadiusSecretNotConfigDropped

Field Type : Counter64

Field Status : current

Description : The non-configured secret dropped on lsn radius server.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.12

Field Name : axIpNatLsnHABstandbyDropped

Field Type : Counter64

Field Status : current

Description : The HA standby dropped on lsn radius server.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.11

Field Name : axIpNatLsnRadiusRequestTableFullDropped

Field Type : TABLE

Field Status : current

Description : The radius request table full dropped on lsn radius server.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.10

Field Name : axIpNatLsnRadiusRequestIgnored

Field Type : Counter64

Field Status : current

Description : The radius request ignored on lsn radius server.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.9

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatLsnRadiusRequestMalFormedDropped

Field Type : Counter64

Field Status : current

Description : The malformed radius request dropped on lsn radius server.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.8

Field Name : axIpNatLsnRadiusRequestNoKeyAttrDropped

Field Type : Counter64

Field Status : current

Description : The radius request no key attribute dropped on lsn radius server.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.7

Field Name : axIpNatLsnRadiusRequestBadSecretDropped

Field Type : Counter64

Field Status : current

Description : The radius request bad secret dropped on lsn radius server.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.6

Field Name : axIpNatLsnRadiusRequestReceived

Field Type : Counter64

Field Status : current

Description : The radius request received on lsn radius server.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.5

Field Name : axIpNatLsnCustAttrReceived

Field Type : Counter64

Field Status : current

Description : The custom attribute received on lsn radius server.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.4

Field Name : axIpNatLsnRadiusIMSIReceived

Field Type : Counter64

Field Status : current

Description : The IMSI received on lsn radius server.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.3

Field Name : axIpNatLsnRadiusIMEIReceived

Field Type : Counter64

Field Status : current

Description : The IMEI received on lsn radius server.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.2

Field Name : axIpNatLsnMSISDNReceived

Field Type : Counter64

Field Status : current

Description : The MSISDN received on lsn radius server.

OID : 1.3.6.1.4.1.22610.2.4.3.18.4.15.1

Field Name : axIpNatHttpRequestLogged

Field Type : Counter64

Field Status : current

Description : Total number of HTTP request logged.

OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.42

Field Name : axIpNatUdpPortOverloadingFreed

Field Type : Counter64

A10-AX-MIB_axMgmt_oid_list

Field Status : current

Description : Total number of TCP port overloading freed.

OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.41

Field Name : axIpNatUdpPortOverloadingAllocated

Field Type : Counter64

Field Status : current

Description : Total number of UDP port overloading allocated.

OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.40

Field Name : axIpNatTcpPortOverloadingFreed

Field Type : Counter64

Field Status : current

Description : Total number of TCP port overloading freed.

OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.39

Field Name : axIpNatTcpPortOverloadingAllocated

Field Type : Counter64

Field Status : current

Description : Total number of TCP port overloading allocated.

OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.38

Field Name : axIpNatTcpConnectionLost

Field Type : Counter64

Field Status : current

Description : Total number of TCP connection lost.

OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.37

Field Name : axIpNatTcpConnectionEstablished

Field Type : Counter64

Field Status : current

Description : Total number of TCP connection established.

OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.36

Field Name : axIpNatLoggingLogPacketsDrop

Field Type : Counter64

Field Status : current

Description : Total number of log packets drop.

OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.35

Field Name : axIpNatLoggingFixedNatPeriodicConfigLogged

Field Type : Counter64

Field Status : current

Description : Total number of Fixed NAT periodic config logged.

OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.34

Field Name : axIpNatLoggingFixedNatPeriodicConfigLogsSent

Field Type : Counter64

Field Status : current

Description : Total number of Fixed NAT periodic config logs sent.

OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.33

Field Name : axIpNatLoggingFixedNatDisabledConfigLogsSent

Field Type : Counter64

Field Status : current

Description : Total number of Fixed NAT disabled config logs sent out.

OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.32

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatLoggingFixedNatDisabledConfigLogged
Field Type : Counter64
Field Status : current
Description : Total number of Fixed NAT disabled configs logged.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.31

Field Name : axIpNatLoggingFixedNatInsideUserPortMapping
Field Type : Counter64
Field Status : current
Description : Total number of Fixed NAT inside user port mappings.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.30

Field Name : axIpNatLoggingEspResourceFreed
Field Type : Counter64
Field Status : current
Description : Total number of ESP resource freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.29

Field Name : axIpNatLoggingEspResourceAllocated
Field Type : Counter64
Field Status : current
Description : Total number of ESP resource allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.28

Field Name : axIpNatLoggingEspSessDeleted
Field Type : Counter64
Field Status : current
Description : Total number of ESP sessions deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.27

Field Name : axIpNatLoggingEspSessCreated
Field Type : Counter64
Field Status : current
Description : Total number of ESP sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.26

Field Name : axIpNatLoggingGreResourceFreed
Field Type : Counter64
Field Status : current
Description : Total number of GRE resource freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.25

Field Name : axIpNatLoggingGreResourceAllocated
Field Type : Counter64
Field Status : current
Description : Total number of GRE resource allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.24

Field Name : axIpNatLoggingGreSessDeleted
Field Type : Counter64
Field Status : current
Description : Total number of GRE sessions deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.23

Field Name : axIpNatLoggingGreSessCreated
Field Type : Counter64

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : Total number of GRE sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.22

Field Name : axIpNatLoggingIcmpV6ResourcetFreed
Field Type : Counter64
Field Status : current
Description : Total number of ICMPv6 resource freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.21

Field Name : axIpNatLoggingIcmpV6ResourceAllocated
Field Type : Counter64
Field Status : current
Description : Total number of ICMPv6 resource allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.20

Field Name : axIpNatLoggingIcmpV6SessDeleted
Field Type : Counter64
Field Status : current
Description : Total number of ICMPv6 sessions deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.19

Field Name : axIpNatLoggingIcmpV6SessCreated
Field Type : Counter64
Field Status : current
Description : Total number of ICMPv6 sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.18

Field Name : axIpNatLoggingIcmpResourcetFreed
Field Type : Counter64
Field Status : current
Description : Total number of ICMP resource freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.17

Field Name : axIpNatLoggingIcmpResourceAllocated
Field Type : Counter64
Field Status : current
Description : Total number of ICMP resource allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.16

Field Name : axIpNatLoggingIcmpSessDeleted
Field Type : Counter64
Field Status : current
Description : Total number of ICMP sessions deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.15

Field Name : axIpNatLoggingIcmpSessCreated
Field Type : Counter64
Field Status : current
Description : Total number of ICMP sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.14

Field Name : axIpNatLoggingUdpPortBatchFreed
Field Type : Counter64
Field Status : current
Description : Total number of UDP ports batch-freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.13

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatLoggingUdpPortBatchAllocated
Field Type : Counter64
Field Status : current
Description : Total number of UDP ports batch-allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.12

Field Name : axIpNatLoggingUdpPortFreed
Field Type : Counter64
Field Status : current
Description : Total number of UDP ports freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.11

Field Name : axIpNatLoggingUdpPortAllocated
Field Type : Counter64
Field Status : current
Description : Total number of UDP ports allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.10

Field Name : axIpNatLoggingUdpSessDeleted
Field Type : Counter64
Field Status : current
Description : Total number of UDP sessions deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.9

Field Name : axIpNatLoggingUdpSessCreated
Field Type : Counter64
Field Status : current
Description : Total number of UDP sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.8

Field Name : axIpNatLoggingTcpPortBatchFreed
Field Type : Counter64
Field Status : current
Description : Total number of TCP ports batch-freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.7

Field Name : axIpNatLoggingTcpPortBatchAllocated
Field Type : Counter64
Field Status : current
Description : Total number of TCP ports batch-allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.6

Field Name : axIpNatLoggingTcpPortFreed
Field Type : Counter64
Field Status : current
Description : Total number of TCP ports freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.5

Field Name : axIpNatLoggingTcpPortAllocated
Field Type : Counter64
Field Status : current
Description : Total number of TCP ports allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.4

Field Name : axIpNatLoggingTcpSessDeleted
Field Type : Counter64

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : Total number of TCP sessions deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.3

Field Name : axIpNatLoggingTcpSessCreated
Field Type : Counter64
Field Status : current
Description : Total number of TCP sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.2

Field Name : axIpNatLoggingLogPktSent
Field Type : Counter64
Field Status : current
Description : Total number of logging packets sent out.
OID : 1.3.6.1.4.1.22610.2.4.3.18.101.1.1

Field Name : axIpNatPoolStatsTable
Field Type : TABLE
Field Status : current
Description : A table has information of IP NAT pool statistics.
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1

Field Name : axIpNatPoolStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatPoolStats Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1

Field Name : axIpNatPoolFailed
Field Type : INTEGER
Field Status : current
Description : The total misses in the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.7

Field Name : axIpNatPoolTotalFree
Field Type : INTEGER
Field Status : current
Description : The total of free addresses in the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.6

Field Name : axIpNatPoolTotalUsed
Field Type : INTEGER
Field Status : current
Description : The total of used addresses in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.5

Field Name : axIpNatPoolPortUsage
Field Type : INTEGER
Field Status : current
Description : The total port usage in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.4

Field Name : axIpNatPoolEndAddress
Field Type : String
Field Status : current
Description : The IP NAT pool end address (IPv4 or IPv6)
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.3

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatPoolStartAddress
Field Type : String
Field Status : current
Description : The IP NAT pool start address (IPv4 or IPv6)
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.2

Field Name : axIpNatPoolName
Field Type : String
Field Status : current
Description : The IP NAT pool name
OID : 1.3.6.1.4.1.22610.2.4.3.18.100.1.1.1

Field Name : axIpNatStatsDynamicMappingEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatStatsDynamicMapping Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1

Field Name : axIpNatStatsDynamicMappingEndAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axIpNatStatsDynamicMappingEndAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.9

Field Name : axIpNatStatsDynamicMappingStartAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axIpNatStatsDynamicMappingStartAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.8

Field Name : axIpNatStatsDynamicMappingMissAddresses
Field Type : INTEGER
Field Status : current
Description : The total misses in the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.7

Field Name : axIpNatStatsDynamicMappingAllocAddresses
Field Type : INTEGER
Field Status : current
Description : The total allocated addresses in the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.6

Field Name : axIpNatStatsDynamicMappingTotalAddresses
Field Type : INTEGER
Field Status : current
Description : The total addresses in the pool.
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.5

Field Name : axIpNatStatsDynamicMappingEndAddress
Field Type : String
Field Status : current
Description : The end address of the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.4

A10-AX-MIB_axMgmt_oid_list

Field Name : axIpNatStatsDynamicMappingStartAddress
Field Type : String
Field Status : current
Description : The start address of the pool
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.3

Field Name : axIpNatStatsDynamicMappingPoolName
Field Type : String
Field Status : current
Description : The IP source NAT pool name
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.2

Field Name : axIpNatStatsDynamicMappingAccessListID
Field Type : INTEGER
Field Status : current
Description : The access list id.
OID : 1.3.6.1.4.1.22610.2.4.3.18.3.1.1.1

Field Name : axIpNatStatsIntfInsideOutsideTable
Field Type : TABLE
Field Status : current
Description : A table has information of IP NAT interface inside/outside
OID : 1.3.6.1.4.1.22610.2.4.3.18.2.1

Field Name : axIpNatStatsIntfInsideOutsideEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axIpNatStatsIntfInsideOutside Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.2.1.1

Field Name : axIpNatStatsInsideOutsideIntfDirection
Field Type : EnumVal
Field Status : current
Description : The interface bind direction, inside or outside.
OID : 1.3.6.1.4.1.22610.2.4.3.18.2.1.1.3

Field Name : axIpNatStatsInsideOutsideIntfName
Field Type : String
Field Status : current
Description : The interface name, such as ethernet1, ethernet2, ve3, ...
OID : 1.3.6.1.4.1.22610.2.4.3.18.2.1.1.2

Field Name : axIpNatStatsInsideOutsideIntfIndex
Field Type : INTEGER
Field Status : current
Description : The index of the AxIpNatStatsIntfInsideOutside table.
OID : 1.3.6.1.4.1.22610.2.4.3.18.2.1.1.1

Field Name : axIpNatStatsGlobalMisses
Field Type : Counter64
Field Status : current
Description : Total misses in the IP source NAT
OID : 1.3.6.1.4.1.22610.2.4.3.18.1.2

Field Name : axIpNatStatsGlobalHits
Field Type : Counter64
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : Total hits in the IP source NAT.

OID : 1.3.6.1.4.1.22610.2.4.3.18.1.1

Field Name : axFixedNatTop5GlobalIpAddrTotUdpPortTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 fixed nat private IPs and total number of udp(ports).

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.15.1

Field Name : axFixedNatTop5GlobalIpAddrTotUdpPortEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axFixedNatTop5GlobalIpAddrTotUdpPort Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.15.1.1

Field Name : axFixedNatTop5GlobalIpAddrTotNumInUdp

Field Type : Integer32

Field Status : current

Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.15.1.1.2

Field Name : axFixedNatTop5GlobalIpAddrInUdp

Field Type : String

Field Status : current

Description : The private IP address in the Top 5 fixed nat global IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.15.1.1.1

Field Name : axFixedNatTop5GlobalIpAddrTotTcpPortTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 fixed nat private IPs and total number of tcp(ports).

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.14.1

Field Name : axFixedNatTop5GlobalIpAddrTotTcpPortEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axFixedNatTop5GlobalIpAddrTotTcpPort Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.14.1.1

Field Name : axFixedNatTop5GlobalIpAddrTotNumInTcp

Field Type : Integer32

Field Status : current

Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.14.1.1.2

Field Name : axFixedNatTop5GlobalIpAddrInTcp

Field Type : String

Field Status : current

Description : The private IP address in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.14.1.1.1

Field Name : axFixedNatTop5GlobalIpAddrTotUserTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 fixed nat private IPs and total number of udp(ports).

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.13.1

Field Name : axFixedNatTop5GlobalIpAddrTotUserEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axFixedNatTop5GlobalIpAddrTotUser Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.13.1.1

Field Name : axFixedNatTop5GlobalIpAddrTotNum

Field Type : Integer32

Field Status : current

Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.13.1.1.2

Field Name : axFixedNatTop5GlobalIpAddrUser

Field Type : String

Field Status : current

Description : The private IP address in the Top 5 fixed nat global IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.13.1.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotIcmpPortTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 fixed nat user private IPs and total number of icmp(ports).

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.12.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotIcmpPortEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axFixedNatTop5UserPrivateIpAddrTotIcmpPort Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.12.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrGlobalIpAddrInIcmp

Field Type : String

Field Status : current

Description : The global IP address in the Top 5 fixed nat user private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.12.1.1.3

Field Name : axFixedNatTop5UserPrivateIpAddrTotNumInIcmp

Field Type : Integer32

Field Status : current

Description : The total number of icmp ports in the Top 5 fixed nat user private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.12.1.1.2

Field Name : axFixedNatTop5UserPrivateIpAddrInIcmp

Field Type : String

Field Status : current

Description : The private IP address in the Top 5 fixed nat user private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.12.1.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotUdpPortTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 fixed nat private IPs and total number of udp(ports).

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.11.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotUdpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5UserPrivateIpAddrTotUdpPort Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.11.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrGlobalIpAddrInUdp
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.11.1.1.3

Field Name : axFixedNatTop5UserPrivateIpAddrTotNumInUdp
Field Type : Integer32
Field Status : current
Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.11.1.1.2

Field Name : axFixedNatTop5UserPrivateIpAddrInUdp
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.11.1.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotTcpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 fixed nat private IPs and total number of tcp(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.10.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotTcpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5UserPrivateIpAddrTotTcpPort Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.10.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrGlobalIpAddrInTcp
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.10.1.1.3

Field Name : axFixedNatTop5UserPrivateIpAddrTotNumInTcp
Field Type : Integer32
Field Status : current
Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.10.1.1.2

Field Name : axFixedNatTop5UserPrivateIpAddrInTcp
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.10.1.1.1

A10-AX-MIB_axMgmt_oid_list

Field Name : axFixedNatTop5UserPrivateIpAddrTotSessionTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 fixed nat private IPs and total number of tcp(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.9.1

Field Name : axFixedNatTop5UserPrivateIpAddrTotSessionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5UserPrivateIpAddrSession Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.9.1.1

Field Name : axFixedNatTop5UserPrivateIpAddrGlobalIpAddr
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.9.1.1.3

Field Name : axFixedNatTop5UserPrivateIpAddrTotNumSession
Field Type : Integer32
Field Status : current
Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.9.1.1.2

Field Name : axFixedNatTop5UserPrivateIpAddr
Field Type : String
Field Status : current
Description : The private IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.9.1.1.1

Field Name : axFixedNatTop5PrivateIpAddrTotIcmpPortTable
Field Type : TABLE
Field Status : current
Description : A table containing Top 5 fixed nat private IPs and total number of icmp(ports).
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.8.1

Field Name : axFixedNatTop5PrivateIpAddrTotIcmpPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatTop5PrivateIpAddrTotIcmpPorts Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.8.1.1

Field Name : axFixedNatTop5PrivateIpAddrGlobalIpAddrInIcmpPort
Field Type : String
Field Status : current
Description : The global IP address in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.8.1.1.3

Field Name : axFixedNatTop5PrivateIpAddrTotNumInIcmpPort
Field Type : Integer32
Field Status : current
Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.8.1.1.2

A10-AX-MIB_axMgmt_oid_list

Field Name : axFixedNatTop5PrivateIpAddrInIcmpPort

Field Type : String

Field Status : current

Description : The private IP address in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.8.1.1.1

Field Name : axFixedNatTop5PrivateIpAddrTotUdpPortTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 fixed nat private IPs and total number of udp(ports).

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.7.1

Field Name : axFixedNatTop5PrivateIpAddrTotUdpPortEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axFixedNatTop5PrivateIpAddrTotUdpPorts Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.7.1.1

Field Name : axFixedNatTop5PrivateIpAddrGlobalIpAddrInUdpPort

Field Type : String

Field Status : current

Description : The global IP address in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.7.1.1.3

Field Name : axFixedNatTop5PrivateIpAddrTotNumInUdpPort

Field Type : Integer32

Field Status : current

Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.7.1.1.2

Field Name : axFixedNatTop5PrivateIpAddrInUdpPort

Field Type : String

Field Status : current

Description : The private IP address in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.7.1.1.1

Field Name : axFixedNatTop5PrivateIpAddrTotTcpPortTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 fixed nat private IPs and total number of tcp(ports).

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.6.1

Field Name : axFixedNatTop5PrivateIpAddrTotTcpPortEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axFixedNatTop5PrivateIpAddrTotTcpPorts Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.6.1.1

Field Name : axFixedNatTop5PrivateIpAddrGlobalIpAddrInTcpPort

Field Type : String

Field Status : current

Description : The global IP address in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.6.1.1.3

Field Name : axFixedNatTop5PrivateIpAddrTotNumInTcpPort

Field Type : Integer32

A10-AX-MIB_axMgmt_oid_list

Field Status : current

Description : The total number of tcp ports in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.6.1.1.2

Field Name : axFixedNatTop5PrivateIpAddrInTcpPort

Field Type : String

Field Status : current

Description : The private IP address in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.6.1.1.1

Field Name : axFixedNatTop5PrivateIpAddrTotSessionTable

Field Type : TABLE

Field Status : current

Description : A table containing Top 5 fixed nat private IPs and total number of sessions(ports).

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.5.1

Field Name : axFixedNatTop5PrivateIpAddrTotSessionEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axFixedNatTop5PrivateIpAddrTotSessions Table

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.5.1.1

Field Name : axFixedNatTop5PrivateIpAddrGlobalIpAddr

Field Type : String

Field Status : current

Description : The global IP address in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.5.1.1.3

Field Name : axFixedNatTop5PrivateIpAddrTotNumSessions

Field Type : Integer32

Field Status : current

Description : The total number of sessions in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.5.1.1.2

Field Name : axFixedNatTop5PrivateIpAddr

Field Type : String

Field Status : current

Description : The private IP address in the Top 5 fixed nat private IP address entry.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.5.1.1.1

Field Name : axFixedNatFullConeSessNat64Table

Field Type : TABLE

Field Status : current

Description : A table has information of fixed nat full-cone-session NAT64.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3

Field Name : axFixedNatFullConeSessNat44Table

Field Type : TABLE

Field Status : current

Description : A table has information of fixed nat full-cone-session NAT44.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2

Field Name : axFixedNatFullConeSessNat44Entry

Field Type : CounterBasedGauge64

Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : Columns in the axFixedNatFullConeSessNat44Table Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1

Field Name : axFixedNatFullConeSessNat44PcpFlags
Field Type : EnumVal
Field Status : current
Description : The flag of pcp.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.8

Field Name : axFixedNatFullConeSessNat44Age
Field Type : INTEGER
Field Status : current
Description : The ages of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.7

Field Name : axFixedNatFullConeSessNat44CPU
Field Type : INTEGER
Field Status : current
Description : The CPU of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.6

Field Name : axFixedNatFullConeSessNat44EIF
Field Type : INTEGER
Field Status : current
Description : The EIF value of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.5

Field Name : axFixedNatFullConeSessNat44EIM
Field Type : INTEGER
Field Status : current
Description : The EIM value of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.4

Field Name : axFixedNatFullConeSessNat44ProtType
Field Type : EnumVal
Field Status : current
Description : The protocol type of fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.3

Field Name : axFixedNatFullConeSessNat44InsideUser
Field Type : String
Field Status : current
Description : The inside user address and port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.2

Field Name : axFixedNatFullConeSessNat44NatIpAddress
Field Type : String
Field Status : current
Description : The nat ip address and port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.2.1.1

Field Name : axFixedNatFullConeSessDsLiteTable
Field Type : TABLE
Field Status : current
Description : A table has information of fixed nat full-cone-session ds-lite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1

A10-AX-MIB_axMgmt_oid_list

Field Name : axFixedNatFullConeSessDsliteEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatFullConeSessDsliteTable Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1

Field Name : axFixedNatFullConeSessDslitePcpFlags
Field Type : EnumVal
Field Status : current
Description : The flag of pcp.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.8

Field Name : axFixedNatFullConeSessDsliteAge
Field Type : INTEGER
Field Status : current
Description : The ages of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.7

Field Name : axFixedNatFullConeSessDsliteCPU
Field Type : INTEGER
Field Status : current
Description : The CPU of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.6

Field Name : axFixedNatFullConeSessDsliteEIF
Field Type : INTEGER
Field Status : current
Description : The EIF value of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.5

Field Name : axFixedNatFullConeSessDsliteEIM
Field Type : INTEGER
Field Status : current
Description : The EIM value of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.4

Field Name : axFixedNatFullConeSessDsliteProtType
Field Type : EnumVal
Field Status : current
Description : The protocol type of fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.3

Field Name : axFixedNatFullConeSessDsliteInsideUser
Field Type : String
Field Status : current
Description : The inside user address and port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.2

Field Name : axFixedNatFullConeSessDsliteNatIpAddress
Field Type : String
Field Status : current
Description : The nat ip address and port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.1.1.1

Field Name : axFixedNatFullConeSessNat64Entry
Field Type : CounterBasedGauge64
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : Columns in the axFixedNatFullConeSessNat64Table Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1

Field Name : axFixedNatFullConeSessNat64PcpFlags
Field Type : EnumVal
Field Status : current
Description : The flag of pcp.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.8

Field Name : axFixedNatFullConeSessNat64Age
Field Type : INTEGER
Field Status : current
Description : The ages of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.7

Field Name : axFixedNatFullConeSessNat64CPU
Field Type : INTEGER
Field Status : current
Description : The CPU of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.6

Field Name : axFixedNatFullConeSessNat64EIF
Field Type : INTEGER
Field Status : current
Description : The EIF value of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.5

Field Name : axFixedNatFullConeSessNat64EIM
Field Type : INTEGER
Field Status : current
Description : The EIM value of the full cone session fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.4

Field Name : axFixedNatFullConeSessNat64ProtType
Field Type : EnumVal
Field Status : current
Description : The protocol type of fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.3

Field Name : axFixedNatFullConeSessNat64InsideUser
Field Type : String
Field Status : current
Description : The inside user address and port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.2

Field Name : axFixedNatFullConeSessNat64NatIpAddress
Field Type : String
Field Status : current
Description : The nat ip address and port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.4.3.1.1

Field Name : axFixedNatPortMappingPortTable
Field Type : TABLE
Field Status : current
Description : A table has information of the servers.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1

A10-AX-MIB_axMgmt_oid_list

Field Name : axFixedNatPortMappingPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatPortMappingPortTable Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1

Field Name : axFixedNatPortMappingPortIcmpEndPort
Field Type : INTEGER
Field Status : current
Description : The ICMP end port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.9

Field Name : axFixedNatPortMappingPortIcmpBeginPort
Field Type : INTEGER
Field Status : current
Description : The ICMP end port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.8

Field Name : axFixedNatPortMappingPortUdpEndPort
Field Type : INTEGER
Field Status : current
Description : The UDP end port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.7

Field Name : axFixedNatPortMappingPortUdpBeginPort
Field Type : INTEGER
Field Status : current
Description : The UDP end port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.6

Field Name : axFixedNatPortMappingPortTcpEndPort
Field Type : INTEGER
Field Status : current
Description : The TCP end port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.5

Field Name : axFixedNatPortMappingPortTcpBeginPort
Field Type : INTEGER
Field Status : current
Description : The TCP begin port of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.4

Field Name : axFixedNatPortMappingPortInsideUserIpType
Field Type : EnumVal
Field Status : current
Description : The inside user address type of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.3

Field Name : axFixedNatPortMappingPortInsideUser
Field Type : String
Field Status : current
Description : The inside user address of the fixed nat.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.2

Field Name : axFixedNatPortMappingPortNatIpAddress
Field Type : String
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The nat ip address of the fixed nat.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.3.1.1.1

Field Name : axFixedNatAlgSipMethodUnknown

Field Type : Counter64

Field Status : current

Description : The fixed nat alg sip method unknown.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.15

Field Name : axFixedNatAlgSipMethodUpdate

Field Type : Counter64

Field Status : current

Description : The fixed nat alg sip method update.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.14

Field Name : axFixedNatAlgSipMethodMessage

Field Type : Counter64

Field Status : current

Description : The fixed nat alg sip method message.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.13

Field Name : axFixedNatAlgSipMethodRefer

Field Type : Counter64

Field Status : current

Description : The fixed nat alg sip method Refer.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.12

Field Name : axFixedNatAlgSipMethodInfo

Field Type : Counter64

Field Status : current

Description : The fixed nat alg sip method information.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.11

Field Name : axFixedNatAlgSipMethodPublish

Field Type : Counter64

Field Status : current

Description : The fixed nat alg sip method publish.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.10

Field Name : axFixedNatAlgSipMethodNotify

Field Type : Counter64

Field Status : current

Description : The fixed nat alg sip method notify.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.9

Field Name : axFixedNatAlgSipMethodSubscribe

Field Type : Counter64

Field Status : current

Description : The fixed nat alg sip method subscribe.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.8

Field Name : axFixedNatAlgSipMethodPrack

Field Type : Counter64

Field Status : current

Description : The fixed nat alg sip method prack.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.7

A10-AX-MIB_axMgmt_oid_list

Field Name : axFixedNatAlgSipMethodOptions
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method options.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.6

Field Name : axFixedNatAlgSipMethodBye
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method bye.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.5

Field Name : axFixedNatAlgSipMethodCancel
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method cancel.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.4

Field Name : axFixedNatAlgSipMethodAck
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method ack.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.3

Field Name : axFixedNatAlgSipMethodInvite
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method invite.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.2

Field Name : axFixedNatAlgSipMethodReg
Field Type : Counter64
Field Status : current
Description : The fixed nat alg sip method register.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.6.1

Field Name : axFixedNatAlgRtspDataSessionCreationFailed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp data session creation failures.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.10

Field Name : axFixedNatAlgRtspDataSessionFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp data session freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.9

Field Name : axFixedNatAlgRtspDataSessionCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp data session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.8

Field Name : axFixedNatAlgRtspSrvRepWithUnknownClientPorts
Field Type : Counter64
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The fixed nat alg rtsp server replies with unknown client ports.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.7

Field Name : axFixedNatAlgRtspStreamClientPortAllocationFailed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp stream client port allocation failures.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.6

Field Name : axFixedNatAlgRtspStreamClientPortFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp stream client ports freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.5

Field Name : axFixedNatAlgRtspStreamClientPortAllocated
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp stream client ports allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.4

Field Name : axFixedNatAlgRtspStreamCreationFailed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp stream creation failures.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.3

Field Name : axFixedNatAlgRtspStreamFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp stream freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.2

Field Name : axFixedNatAlgRtspStreamCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat alg rtsp stream created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.5.1

Field Name : axFixedNatAlgPptpGreNoMatchGreSession
Field Type : Counter64
Field Status : current
Description : The fixed nat alg pptp no matching gre sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.4.5

Field Name : axFixedNatAlgPptpGreSessionFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat alg pptp gre sessions freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.4.4

Field Name : axFixedNatAlgPptpGreSessionCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat alg pptp gre sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.4.3

A10-AX-MIB_axMgmt_oid_list

Field Name : axFixedNatAlgPptpMismatchedPnsCallId
Field Type : Counter64
Field Status : current
Description : The fixed nat alg pptp mismatched pns call id.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.4.2

Field Name : axFixedNatAlgPptpCallEsp
Field Type : Counter64
Field Status : current
Description : The fixed nat alg pptp calls established.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.4.1

Field Name : axFixedNatAlgH323FastStart
Field Type : Counter64
Field Status : current
Description : The fixed nat alg H323 fast start.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.3.5

Field Name : axFixedNatAlgH323H245TunnelMsg
Field Type : Counter64
Field Status : current
Description : The fixed nat alg H323 H245 Tunnelled message.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.3.4

Field Name : axFixedNatAlgH323H245MedCtrMsg
Field Type : Counter64
Field Status : current
Description : The fixed nat alg H323 H245 media control message.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.3.3

Field Name : axFixedNatAlgH323H225CallSigMsg
Field Type : Counter64
Field Status : current
Description : The fixed nat alg H323 H225 Call Signaling Message.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.3.2

Field Name : axFixedNatAlgH323H225RasMsg
Field Type : Counter64
Field Status : current
Description : The fixed nat alg H323 H225 Ras message.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.3.1

Field Name : axFixedNatAlgFtpLpsvRepFromServer
Field Type : Counter64
Field Status : current
Description : The fixed nat alg ftp lpsv replies from server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.2.6

Field Name : axFixedNatAlgFtpEpsvRepFromServer
Field Type : Counter64
Field Status : current
Description : The fixed nat alg ftp epsv replies from server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.2.5

Field Name : axFixedNatAlgFtpPasvRepFromServer
Field Type : Counter64
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The fixed nat alg ftp pasv replies from server.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.2.4

Field Name : axFixedNatAlgFtpLprtReqFromClient
Field Type : Counter64
Field Status : current
Description : The fixed nat alg ftp lprt requests from client.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.2.3

Field Name : axFixedNatAlgFtpEprtReqFromClient
Field Type : Counter64
Field Status : current
Description : The fixed nat alg ftp eprt requests from client.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.2.2

Field Name : axFixedNatAlgFtpPortReqFromClient
Field Type : Counter64
Field Status : current
Description : The fixed nat alg ftp port requests from client.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.2.1

Field Name : axFixedNatAlgEspSessionCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat alg esp session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.1.1

Field Name : axFixedNatAlgTftpClientSessionCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat alg tftp client sessions created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.2.7.1

Field Name : axFixedNatNat64HairpinSessionCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 hairpin session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.13

Field Name : axFixedNatNat64EndpointIndependentFilteringLimitExceed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.12

Field Name : axFixedNatNat64EndpointIndependentFilteringDrop
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.11

Field Name : axFixedNatNat64EndpointIndependentFilteringMatched
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.10

A10-AX-MIB_axMgmt_oid_list

Field Name : axFixedNatNat64EndpointIndependentMappingMatched
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 endpoint independent mapping matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.9

Field Name : axFixedNatNat64UdpAlgFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 udp alg full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.8

Field Name : axFixedNatNat64UdpAlgFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 udp alg full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.7

Field Name : axFixedNatNat64UdpFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 udp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.6

Field Name : axFixedNatNat64UdpFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 udp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.5

Field Name : axFixedNatNat64TcpFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 tcp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.4

Field Name : axFixedNatNat64TcpFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 tcp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.3

Field Name : axFixedNatNat64DataSessionsFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 data session freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.2

Field Name : axFixedNatNat64DataSessionsCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat64 data session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.19.1

Field Name : axFixedNatNat44HairpinSessionCreated
Field Type : Counter64
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The fixed nat nat44 hairpin session created.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.13

Field Name : axFixedNatNat44EndpointIndependentFilteringLimitExceed

Field Type : Counter64

Field Status : current

Description : The fixed nat nat44 endpoint independent filtering matched.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.12

Field Name : axFixedNatNat44EndpointIndependentFilteringDrop

Field Type : Counter64

Field Status : current

Description : The fixed nat nat44 endpoint independent filtering matched.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.11

Field Name : axFixedNatNat44EndpointIndependentFilteringMatched

Field Type : Counter64

Field Status : current

Description : The fixed nat nat44 endpoint independent filtering matched.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.10

Field Name : axFixedNatNat44EndpointIndependentMappingMatched

Field Type : Counter64

Field Status : current

Description : The fixed nat nat44 endpoint independent mapping matched.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.9

Field Name : axFixedNatNat44UdpAlgFullConeFreed

Field Type : Counter64

Field Status : current

Description : The fixed nat nat44 udp alg full cone freed.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.8

Field Name : axFixedNatNat44UdpAlgFullConeCreated

Field Type : Counter64

Field Status : current

Description : The fixed nat nat44 udp alg full cone created.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.7

Field Name : axFixedNatNat44UdpFullConeFreed

Field Type : Counter64

Field Status : current

Description : The fixed nat nat44 udp full cone freed.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.6

Field Name : axFixedNatNat44UdpFullConeCreated

Field Type : Counter64

Field Status : current

Description : The fixed nat nat44 udp full cone created.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.5

Field Name : axFixedNatNat44TcpFullConeFreed

Field Type : Counter64

Field Status : current

Description : The fixed nat nat44 tcp full cone freed.

OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.4

A10-AX-MIB_axMgmt_oid_list

Field Name : axFixedNatNat44TcpFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 tcp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.3

Field Name : axFixedNatNat44DataSessionsFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 data session freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.2

Field Name : axFixedNatNat44DataSessionsCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat nat44 data session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.18.1

Field Name : axFixedNatDestRuleListPassThrough
Field Type : Counter64
Field Status : current
Description : The fixed nat destination rule list pass through.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.17

Field Name : axFixedNatDestRuleListDrop
Field Type : Counter64
Field Status : current
Description : The fixed nat destination rule list drop.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.16

Field Name : axFixedNatIpv6InIpv4PacketDrop
Field Type : Counter64
Field Status : current
Description : The fixed nat ipv6 in ipv4 packet drop.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.15

Field Name : axFixedNatSelfHairpinningDrop
Field Type : Counter64
Field Status : current
Description : The fixed nat self hairpinning drop.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.14

Field Name : axFixedNatLidStandbyDrop
Field Type : Counter64
Field Status : current
Description : The fixed nat lid standby drop.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.13

Field Name : axFixedNatFullConeSessionCreationFailed
Field Type : Counter64
Field Status : current
Description : The fixed nat full cone session creation failed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.12

Field Name : axFixedNatSessionUserQuotaExceed
Field Type : Counter64
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The fixed nat session user quota exceed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.11

Field Name : axFixedNatIcmpNatPortUnavailable
Field Type : Counter64
Field Status : current
Description : The fixed nat icmp nat port unavailable.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.10

Field Name : axFixedNatUdpNatPortUnavailable
Field Type : Counter64
Field Status : current
Description : The fixed nat udp nat port unavailable.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.9

Field Name : axFixedNatTcpNatPortUnavailable
Field Type : Counter64
Field Status : current
Description : The fixed nat tcp nat port unavailable.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.8

Field Name : axFixedNatTotalIcmpPortsFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat total icmp ports freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.7

Field Name : axFixedNatTotalIcmpPortsAllocated
Field Type : Counter64
Field Status : current
Description : The fixed nat total icmp ports allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.6

Field Name : axFixedNatTotalUdpPortsFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat total udp ports freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.5

Field Name : axFixedNatTotalUdpPortsAllocated
Field Type : Counter64
Field Status : current
Description : The fixed nat total udp ports allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.4

Field Name : axFixedNatTotalTcpPortsFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat total tcp ports freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.3

Field Name : axFixedNatTotalTcpPortsAllocated
Field Type : Counter64
Field Status : current
Description : The fixed nat total tcp ports allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.2

A10-AX-MIB_axMgmt_oid_list

Field Name : axFixedNatTotalNatAddressInUse
Field Type : Counter64
Field Status : current
Description : The fixed nat total nat address in use.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.1

Field Name : axFixedNatDsliteHairpinSessionCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite hairpin session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.13

Field Name : axFixedNatDsliteEndpointIndependentFilteringLimitExceed
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.12

Field Name : axFixedNatDsliteEndpointIndependentFilteringDrop
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.11

Field Name : axFixedNatDsliteEndpointIndependentFilteringMatched
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite endpoint independent filtering matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.10

Field Name : axFixedNatDsliteEndpointIndependentMappingMatched
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite endpoint independent mapping matched.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.9

Field Name : axFixedNatDsliteUdpAlgFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite udp alg full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.8

Field Name : axFixedNatDsliteUdpAlgFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite udp alg full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.7

Field Name : axFixedNatDsliteUdpFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite udp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.6

Field Name : axFixedNatDsliteUdpFullConeCreated
Field Type : Counter64
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The fixed nat dslite udp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.5

Field Name : axFixedNatDsliteTcpFullConeFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite tcp full cone freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.4

Field Name : axFixedNatDsliteTcpFullConeCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite tcp full cone created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.3

Field Name : axFixedNatDsliteDataSessionsFreed
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite data session freed.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.2

Field Name : axFixedNatDsliteDataSessionsCreated
Field Type : Counter64
Field Status : current
Description : The fixed nat dslite data session created.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.1.20.1

Field Name : axFixedNatFileTable
Field Type : TABLE
Field Status : current
Description : A table containing fixed nat files.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.16.1

Field Name : axFixedNatFileEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axFixedNatFile Table
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.16.1.1

Field Name : axFixedNatFileTimeStamp
Field Type : String
Field Status : current
Description : The time stamp of fixed nat files.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.16.1.1.2

Field Name : axFixedNatFileName
Field Type : String
Field Status : current
Description : The file name in fixed nat file table entry.
OID : 1.3.6.1.4.1.22610.2.4.3.18.120.16.1.1.1

Field Name : axHAGroupStatusTable
Field Type : TABLE
Field Status : current
Description : A table contains the HA group status information.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2

A10-AX-MIB_axMgmt_oid_list

Field Name : axHAGroupCount
Field Type : INTEGER
Field Status : current
Description : The number of valid HA groups.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.1

Field Name : axHAGroupStatusEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axHAGroupStatus Table
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2.1

Field Name : axHAGroupPeerPriority
Field Type : Integer32
Field Status : current
Description : The peer priority of this HA group.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2.1.5

Field Name : axHAGroupPeerStatus
Field Type : EnumVal
Field Status : current
Description : The peer status of this HA group.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2.1.4

Field Name : axHAGroupLocalPriority
Field Type : Integer32
Field Status : current
Description : The local priority of this HA group.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2.1.3

Field Name : axHAGroupLocalStatus
Field Type : EnumVal
Field Status : current
Description : The local status of this HA group.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2.1.2

Field Name : axHAGroupID
Field Type : Integer32
Field Status : current
Description : The HA group ID.
OID : 1.3.6.1.4.1.22610.2.4.3.17.2.2.1.1

Field Name : axHAARPRetry
Field Type : INTEGER
Field Status : current
Description : The ARP retries.
OID : 1.3.6.1.4.1.22610.2.4.3.17.1.7

Field Name : axHATimeoutRetry
Field Type : INTEGER
Field Status : current
Description : The HA retries when time out.
OID : 1.3.6.1.4.1.22610.2.4.3.17.1.6

Field Name : axHATimeoutInterval
Field Type : INTEGER
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The HA time interval.

OID : 1.3.6.1.4.1.22610.2.4.3.17.1.5

Field Name : axHAPreemptStatusEnabled

Field Type : EnumVal

Field Status : current

Description : The HA preempt enabled flag

OID : 1.3.6.1.4.1.22610.2.4.3.17.1.4

Field Name : axHASetID

Field Type : INTEGER

Field Status : current

Description : Local configured HA group set-id

OID : 1.3.6.1.4.1.22610.2.4.3.17.1.3

Field Name : axHAID

Field Type : INTEGER

Field Status : current

Description : Local configured HA group ID.

OID : 1.3.6.1.4.1.22610.2.4.3.17.1.2

Field Name : axHAConfigEnabled

Field Type : EnumVal

Field Status : current

Description : The HA configuration enabled flag.

OID : 1.3.6.1.4.1.22610.2.4.3.17.1.1

Field Name : axHAFloatingIPTable

Field Type : TABLE

Field Status : current

Description : A table contains the HA floating-IP information.

OID : 1.3.6.1.4.1.22610.2.4.3.17.3.2

Field Name : axHAFloatingIPCount

Field Type : INTEGER

Field Status : current

Description : The number of HA floating-IP entries.

OID : 1.3.6.1.4.1.22610.2.4.3.17.3.1

Field Name : axHAFloatingIPEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The index column in the axHAFloatingIP Table

OID : 1.3.6.1.4.1.22610.2.4.3.17.3.2.1

Field Name : axHAFloatingIPHaGroupID

Field Type : INTEGER

Field Status : current

Description : The HA group ID for the HA floating-IP entry.

OID : 1.3.6.1.4.1.22610.2.4.3.17.3.2.1.3

Field Name : axHAFloatingIPAddress

Field Type : String

Field Status : current

Description : HA floating-IP address (either IPv4 or IPv6).

OID : 1.3.6.1.4.1.22610.2.4.3.17.3.2.1.2

A10-AX-MIB_axMgmt_oid_list

Field Name : axHAFloatingIPIndex

Field Type : INTEGER

Field Status : current

Description : The index column.

OID : 1.3.6.1.4.1.22610.2.4.3.17.3.2.1.1

Field Name : axSwitchStatTable

Field Type : TABLE

Field Status : current

Description : The switch status table.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31

Field Name : axSwitchStatsAnomAnyDrop

Field Type : INTEGER

Field Status : current

Description : Number of packets dropped by any type of hardware-based DDoS protection filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.30

Field Name : axSwitchStatsAnomTCPSynFinDrop

Field Type : INTEGER

Field Status : current

Description : Number of packets dropped by a tcp-syn-fin filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.29

Field Name : axSwitchStatsAnomSYNFragDrop

Field Type : INTEGER

Field Status : current

Description : Number of packets dropped by a tcp-syn-frag filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.28

Field Name : axSwitchStatsAnomTCPNoFragDrop

Field Type : INTEGER

Field Status : current

Description : Number of packets dropped by a tcp-no-flag filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.27

Field Name : axSwitchStatsAnomAllFragDrop

Field Type : INTEGER

Field Status : current

Description : Number of packets dropped by a frag filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.26

Field Name : axSwitchStatsAnomPingDeathDrop

Field Type : INTEGER

Field Status : current

Description : Number of packets dropped by a ping-of-death filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.25

Field Name : axSwitchStatsAnomIPOptionDrop

Field Type : INTEGER

Field Status : current

Description : Number of packets dropped by an IP option filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.24

Field Name : axSwitchStatsAnomLanAttackDrop

Field Type : INTEGER

A10-AX-MIB_axMgmt_oid_list

Field Status : current

Description : Number of packets dropped by an IP land attack filter. This statistic and the other Anomaly statistics show how many packets were dropped by DDoS protection filters. For the AX device to drop these packets, the corresponding DDoS protection options must be enabled.

OID : 1.3.6.1.4.1.22610.2.4.3.16.23

Field Name : axSwitchStatsIPFragReasmFail

Field Type : INTEGER

Field Status : current

Description : Number of fragment reassembly failures.

OID : 1.3.6.1.4.1.22610.2.4.3.16.22

Field Name : axSwitchStatsIPFragReasmOk

Field Type : INTEGER

Field Status : current

Description : Number of successfully reassembled IP fragments.

OID : 1.3.6.1.4.1.22610.2.4.3.16.21

Field Name : axSwitchStatsIPFragOverlapDrop

Field Type : INTEGER

Field Status : current

Description : Number of fragments dropped due to overload.

OID : 1.3.6.1.4.1.22610.2.4.3.16.20

Field Name : axSwitchStatsIPFragOverlap

Field Type : INTEGER

Field Status : current

Description : Number of overlapping fragments received.

OID : 1.3.6.1.4.1.22610.2.4.3.16.19

Field Name : axSwitchStatsIPTCPFragRcv

Field Type : INTEGER

Field Status : current

Description : Number of IP TCP fragments received.

OID : 1.3.6.1.4.1.22610.2.4.3.16.18

Field Name : axSwitchStatsFwdKernel

Field Type : INTEGER

Field Status : current

Description : Number of packets received by the kernel from data interfaces.

OID : 1.3.6.1.4.1.22610.2.4.3.16.17

Field Name : axSwitchStatsARPRespRcv

Field Type : INTEGER

Field Status : current

Description : Number of ARP responses that have been received.

OID : 1.3.6.1.4.1.22610.2.4.3.16.16

Field Name : axSwitchStatsARPReqRcv

Field Type : INTEGER

Field Status : current

Description : Number of ARP requests that have been received.

OID : 1.3.6.1.4.1.22610.2.4.3.16.15

Field Name : axSwitchStatsIPFragRcv

Field Type : INTEGER

A10-AX-MIB_axMgmt_oid_list

Field Status : current

Description : Number of IPv4 fragments that have been received.

OID : 1.3.6.1.4.1.22610.2.4.3.16.14

Field Name : axSwitchStatsVLANFlood

Field Type : INTEGER

Field Status : current

Description : Number of packets that have been broadcast to a VLAN.

OID : 1.3.6.1.4.1.22610.2.4.3.16.13

Field Name : axSwitchStatsSRCPortSuppress

Field Type : INTEGER

Field Status : current

Description : Packet drops because of source port suppression.

OID : 1.3.6.1.4.1.22610.2.4.3.16.12

Field Name : axSwitchStatsLinkdownDrop

Field Type : INTEGER

Field Status : current

Description : Number of packets dropped because the outgoing link was down.

OID : 1.3.6.1.4.1.22610.2.4.3.16.11

Field Name : axSwitchStatsTTLExceedDrop

Field Type : INTEGER

Field Status : current

Description : Number of packets dropped due to TTL expiration.

OID : 1.3.6.1.4.1.22610.2.4.3.16.10

Field Name : axSwitchStatsUnknownProtoDrop

Field Type : INTEGER

Field Status : current

Description : Number of packets dropped because the protocol was unknown.

OID : 1.3.6.1.4.1.22610.2.4.3.16.9

Field Name : axSwitchStatsProtoDownDrop

Field Type : INTEGER

Field Status : current

Description : Number of packets dropped because the corresponding protocol was disabled.

OID : 1.3.6.1.4.1.22610.2.4.3.16.8

Field Name : axSwitchStatsIncorrectLenDrop

Field Type : INTEGER

Field Status : current

Description : Number of packets dropped due to incorrect protocol length. A high value for this counter can indicate a packet length attack.

OID : 1.3.6.1.4.1.22610.2.4.3.16.7

Field Name : axSwitchStatsL4Process

Field Type : INTEGER

Field Status : current

Description : Number of packets that went to a VIP or NAT for processing.

OID : 1.3.6.1.4.1.22610.2.4.3.16.6

Field Name : axSwitchStatsIPv6NoRouteDrop

Field Type : INTEGER

Field Status : current

Description : Number of IPv6 packets that were dropped due to routing failures.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.16.5

Field Name : axSwitchStatsL3IPv6Forward

Field Type : INTEGER

Field Status : current

Description : Number of IPv6 packets that have been Layer 3 routed.

OID : 1.3.6.1.4.1.22610.2.4.3.16.4

Field Name : axSwitchStatsIPv4NoRouteDrop

Field Type : INTEGER

Field Status : current

Description : Number of IPv4 packets that were dropped due to routing failures.

OID : 1.3.6.1.4.1.22610.2.4.3.16.3

Field Name : axSwitchStatsL3IPForward

Field Type : INTEGER

Field Status : current

Description : Number of packets that have been Layer 3 routed.

OID : 1.3.6.1.4.1.22610.2.4.3.16.2

Field Name : axSwitchStatsL2Forward

Field Type : INTEGER

Field Status : current

Description : Number of packets that have been Layer 2 switched.

OID : 1.3.6.1.4.1.22610.2.4.3.16.1

Field Name : axSwitchStatEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The Switch status entry.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1

Field Name : axSwitchStatAnomAnyDrop

Field Type : Counter

Field Status : current

Description : Number of packets dropped by any type of hardware-based DDoS protection filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.31

Field Name : axSwitchStatAnomTCPSynFinDrop

Field Type : Counter

Field Status : current

Description : Number of packets dropped by a tcp-syn-fin filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.30

Field Name : axSwitchStatAnomSYNFragDrop

Field Type : Counter

Field Status : current

Description : Number of packets dropped by a tcp-syn-frag filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.29

Field Name : axSwitchStatAnomTCPNoFragDrop

Field Type : Counter

Field Status : current

Description : Number of packets dropped by a tcp-no-flag filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.28

A10-AX-MIB_axMgmt_oid_list

Field Name : axSwitchStatAnomAllFragDrop

Field Type : Counter

Field Status : current

Description : Number of packets dropped by a frag filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.27

Field Name : axSwitchStatAnomPingDeathDrop

Field Type : Counter

Field Status : current

Description : Number of packets dropped by a ping-of-death filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.26

Field Name : axSwitchStatAnomIPOptionDrop

Field Type : Counter

Field Status : current

Description : Number of packets dropped by an IP option filter.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.25

Field Name : axSwitchStatAnomLanAttackDrop

Field Type : Counter

Field Status : current

Description : Number of packets dropped by an IP land attack filter. This statistic and the other Anomaly statistics show how many packets were dropped by DDoS protection filters. For the AX device to drop these packets, the corresponding DDoS protection options must be enabled.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.24

Field Name : axSwitchStatIPFragReasmFail

Field Type : Counter

Field Status : current

Description : Number of fragment reassembly failures.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.23

Field Name : axSwitchStatIPFragReasmOk

Field Type : Counter

Field Status : current

Description : Number of successfully reassembled IP fragments.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.22

Field Name : axSwitchStatIPFragOverlapDrop

Field Type : Counter

Field Status : current

Description : Number of fragments dropped due to overload.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.21

Field Name : axSwitchStatIPFragOverlap

Field Type : Counter

Field Status : current

Description : Number of overlapping fragments received.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.20

Field Name : axSwitchStatIPTCPFragRcv

Field Type : Counter

Field Status : current

Description : Number of IP TCP fragments received.

OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.19

A10-AX-MIB_axMgmt_oid_list

Field Name : axSwitchStatFwdKernel
Field Type : Counter
Field Status : current
Description : Number of packets received by the kernel from data interfaces.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.18

Field Name : axSwitchStatARPRespRcv
Field Type : Counter
Field Status : current
Description : Number of ARP responses that have been received.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.17

Field Name : axSwitchStatARPReqRcv
Field Type : Counter
Field Status : current
Description : Number of ARP requests that have been received.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.16

Field Name : axSwitchStatIPFragRcv
Field Type : Counter
Field Status : current
Description : Number of IPv4 fragments that have been received.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.15

Field Name : axSwitchStatVLANFlood
Field Type : Counter
Field Status : current
Description : Number of packets that have been broadcast to a VLAN.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.14

Field Name : axSwitchStatSRCPortSuppress
Field Type : Counter
Field Status : current
Description : Packet drops because of source port suppression.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.13

Field Name : axSwitchStatLinkdownDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped because the outgoing link was down.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.12

Field Name : axSwitchStatTTLExceedDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped due to TTL expiration.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.11

Field Name : axSwitchStatUnknownProtoDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped because the protocol was unknown.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.10

Field Name : axSwitchStatProtoDownDrop
Field Type : Counter
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : Number of packets dropped because the corresponding protocol was disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.9

Field Name : axSwitchStatIncorrectLenDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped due to incorrect protocol length.A high value for this counter can indicate a packet length attack.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.8

Field Name : axSwitchStatL4Process
Field Type : Counter
Field Status : current
Description : Number of packets that went to a VIP or NAT for processing.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.7

Field Name : axSwitchStatIPv6NoRouteDrop
Field Type : Counter
Field Status : current
Description : Number of IPv6 packets that were dropped due to routing failures.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.6

Field Name : axSwitchStatL3IPv6Forward
Field Type : Counter
Field Status : current
Description : Number of IPv6 packets that have been Layer 3 routed.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.5

Field Name : axSwitchStatIPv4NoRouteDrop
Field Type : Counter
Field Status : current
Description : Number of IPv4 packets that were dropped due to routing failures.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.4

Field Name : axSwitchStatL3IPForward
Field Type : Counter
Field Status : current
Description : Number of packets that have been Layer 3 routed.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.3

Field Name : axSwitchStatL2Forward
Field Type : Counter
Field Status : current
Description : Number of packets that have been Layer 2 switched.
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.2

Field Name : axSwitchStatCpuIndex
Field Type : Integer32
Field Status : current
Description : The cpu index of Switch STAT table
OID : 1.3.6.1.4.1.22610.2.4.3.16.31.1.1

Field Name : axPersistentStatTable
Field Type : TABLE
Field Status : current
Description : The Persistent STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.15.11

A10-AX-MIB_axMgmt_oid_list

Field Name : axPersistentStatsPersistCookieNotFound

Field Type : INTEGER

Field Status : current

Description : Total number of cookie persistent failure in not-found cases.

OID : 1.3.6.1.4.1.22610.2.4.3.15.10

Field Name : axPersistentStatsCookiePersistFail

Field Type : INTEGER

Field Status : current

Description : Total number of cookie persistent failure.

OID : 1.3.6.1.4.1.22610.2.4.3.15.9

Field Name : axPersistentStatsCookiePersistOK

Field Type : INTEGER

Field Status : current

Description : Total number of cookie persistent success.

OID : 1.3.6.1.4.1.22610.2.4.3.15.8

Field Name : axPersistentStatsSSLSIDPersistFail

Field Type : INTEGER

Field Status : current

Description : Total number of SSL session ID persistent failure.

OID : 1.3.6.1.4.1.22610.2.4.3.15.7

Field Name : axPersistentStatsSSLSIDPersistOK

Field Type : INTEGER

Field Status : current

Description : Total number of SSL session ID persistent success.

OID : 1.3.6.1.4.1.22610.2.4.3.15.6

Field Name : axPersistentStatsSIPPersistFail

Field Type : INTEGER

Field Status : current

Description : Number of requests that could not be fulfilled by the same server as previous requests from the same client, based on source-IP persistence.

OID : 1.3.6.1.4.1.22610.2.4.3.15.5

Field Name : axPersistentStatsSIPPersistOK

Field Type : INTEGER

Field Status : current

Description : Number of requests successfully sent to the same server as previous requests from the same client, based on source-IP persistence.

OID : 1.3.6.1.4.1.22610.2.4.3.15.4

Field Name : axPersistentStatsUrlHashPersistFail

Field Type : INTEGER

Field Status : current

Description : Number of requests that could not be fulfilled using URL hashing.

OID : 1.3.6.1.4.1.22610.2.4.3.15.3

Field Name : axPersistentStatsUrlHashPersistOKSec

Field Type : INTEGER

Field Status : current

Description : Number of requests that were sent to another server (a secondary server) because the primary server selected by URL hashing was unavailable.

OID : 1.3.6.1.4.1.22610.2.4.3.15.2

A10-AX-MIB_axMgmt_oid_list

Field Name : axPersistentStatsUrlHashPersistOKPri

Field Type : INTEGER

Field Status : current

Description : Number of requests successfully sent to the primary server selected by URL hashing. The primary server is the one that was initially selected and then re-used based on the hash value.

OID : 1.3.6.1.4.1.22610.2.4.3.15.1

Field Name : axPersistentStatEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The Persistent STAT entry.

OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1

Field Name : axPersistentStatPersistCookieNotFound

Field Type : Counter

Field Status : current

Description : Number of cookie persistent failure in not-found cases.

OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.11

Field Name : axPersistentStatCookiePersistFail

Field Type : Counter

Field Status : current

Description : Number of cookie persistent failure.

OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.10

Field Name : axPersistentStatCookiePersistOK

Field Type : Counter

Field Status : current

Description : Number of cookie persistent success.

OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.9

Field Name : axPersistentStatSSLSIDPersistFail

Field Type : Counter

Field Status : current

Description : Number of SSL session ID persistent failure.

OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.8

Field Name : axPersistentStatSSLSIDPersistOK

Field Type : Counter

Field Status : current

Description : Number of SSL session ID persistent success.

OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.7

Field Name : axPersistentStatSIPPersistFail

Field Type : Counter

Field Status : current

Description : Number of requests that could not be fulfilled by the same server as previous requests from the same client, based on source-IP persistence.

OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.6

Field Name : axPersistentStatSIPPersistOK

Field Type : Counter

Field Status : current

Description : Number of requests successfully sent to the same server as previous requests from the same client, based on source-IP persistence.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.5

Field Name : axPersistentStatUrlHashPersistFail

Field Type : Counter

Field Status : current

Description : Number of requests that could not be fulfilled using URL hashing.

OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.4

Field Name : axPersistentStatUrlHashPersistOKSec

Field Type : Counter

Field Status : current

Description : Number of requests that were sent to another server (a secondary server) because the primary server selected by URL hashing was unavailable.

OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.3

Field Name : axPersistentStatUrlHashPersistOKPri

Field Type : Counter

Field Status : current

Description : Number of requests successfully sent to the primary server selected by URL hashing. The primary server is the one that was initially selected and then re-used based on the hash value.

OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.2

Field Name : axPersistentStatCpuIndex

Field Type : Integer32

Field Status : current

Description : The cpu index of Persistent STAT table

OID : 1.3.6.1.4.1.22610.2.4.3.15.11.1.1

Field Name : axSslProxyStatsSNATFail

Field Type : INTEGER

Field Status : current

Description : Number of occurrences of source NAT failure.

OID : 1.3.6.1.4.1.22610.2.4.3.14.8

Field Name : axSslProxyStatsSvrSelFail

Field Type : INTEGER

Field Status : current

Description : Number of times selection or a real server failed.

OID : 1.3.6.1.4.1.22610.2.4.3.14.7

Field Name : axSslProxyStatsNoRoute

Field Type : INTEGER

Field Status : current

Description : Number of times no route was available.

OID : 1.3.6.1.4.1.22610.2.4.3.14.6

Field Name : axSslProxyStatsSessNotFound

Field Type : INTEGER

Field Status : current

Description : Number of times a session was not found.

OID : 1.3.6.1.4.1.22610.2.4.3.14.5

Field Name : axSslProxyStatsServerErr

Field Type : INTEGER

Field Status : current

Description : Number of server errors.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.14.4

Field Name : axSslProxyStatsClientErr

Field Type : INTEGER

Field Status : current

Description : Number of client errors.

OID : 1.3.6.1.4.1.22610.2.4.3.14.3

Field Name : axSslProxyStatsTotalProxyConns

Field Type : INTEGER

Field Status : current

Description : Total number of connections using the AX device as an SSL proxy.

OID : 1.3.6.1.4.1.22610.2.4.3.14.2

Field Name : axSslProxyStatsCurrProxyConns

Field Type : INTEGER

Field Status : current

Description : Number of currently active connections using the AX device as an SSL proxy.

OID : 1.3.6.1.4.1.22610.2.4.3.14.1

Field Name : axSmtProxyStatTable

Field Type : TABLE

Field Status : current

Description : The Smt proxy STAT table.

OID : 1.3.6.1.4.1.22610.2.4.3.13.19

Field Name : axSmtProxyStatsSNATFail

Field Type : INTEGER

Field Status : current

Description : Number of source NAT failures.

OID : 1.3.6.1.4.1.22610.2.4.3.13.18

Field Name : axSmtProxyStatsSvrConnMade

Field Type : INTEGER

Field Status : current

Description : Number of connections made with servers.

OID : 1.3.6.1.4.1.22610.2.4.3.13.17

Field Name : axSmtProxyStatsSvrPrematureClose

Field Type : INTEGER

Field Status : current

Description : Number of times the connection with a server closed prematurely.

OID : 1.3.6.1.4.1.22610.2.4.3.13.16

Field Name : axSmtProxyStatsServerResel

Field Type : INTEGER

Field Status : current

Description : Number of times a request was forwarded to another server because the current server was failing.

OID : 1.3.6.1.4.1.22610.2.4.3.13.15

Field Name : axSmtProxyStatsReqPktOutOrder

Field Type : INTEGER

Field Status : current

Description : Number of request packets received from clients out of sequence.

OID : 1.3.6.1.4.1.22610.2.4.3.13.14

A10-AX-MIB_axMgmt_oid_list

Field Name : axSmtProxyStatsReqRetrans
Field Type : INTEGER
Field Status : current
Description : Number of retransmitted requests.
OID : 1.3.6.1.4.1.22610.2.4.3.13.13

Field Name : axSmtProxyStatsFwdReqDataFail
Field Type : INTEGER
Field Status : current
Description : Number of forward request data failures.
OID : 1.3.6.1.4.1.22610.2.4.3.13.12

Field Name : axSmtProxyStatsFwdReqFail
Field Type : INTEGER
Field Status : current
Description : Number of forward request failures.
OID : 1.3.6.1.4.1.22610.2.4.3.13.11

Field Name : axSmtProxyStatsServerSelFail
Field Type : INTEGER
Field Status : current
Description : Number of times selection of a real server failed.
OID : 1.3.6.1.4.1.22610.2.4.3.13.10

Field Name : axSmtProxyStatsParseReqFail
Field Type : INTEGER
Field Status : current
Description : Number of times parsing of an SMTP request failed.
OID : 1.3.6.1.4.1.22610.2.4.3.13.9

Field Name : axSmtProxyStatsNoTupleError
Field Type : INTEGER
Field Status : current
Description : Number of tuple errors.
OID : 1.3.6.1.4.1.22610.2.4.3.13.8

Field Name : axSmtProxyStatsServerRST
Field Type : INTEGER
Field Status : current
Description : Number of times TCP connections with servers were reset.
OID : 1.3.6.1.4.1.22610.2.4.3.13.7

Field Name : axSmtProxyStatsClientRST
Field Type : INTEGER
Field Status : current
Description : Number of times TCP connections with clients were reset.
OID : 1.3.6.1.4.1.22610.2.4.3.13.6

Field Name : axSmtProxyStatsNoProxyError
Field Type : INTEGER
Field Status : current
Description : Number of proxy errors.
OID : 1.3.6.1.4.1.22610.2.4.3.13.5

Field Name : axSmtProxyStatsSmtReqSuccs
Field Type : INTEGER
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : Number of SMTP requests received by the AX Series device that were successfully fulfilled (by connection to a real server).

OID : 1.3.6.1.4.1.22610.2.4.3.13.4

Field Name : axSmtProxyStatsSmtRequests

Field Type : INTEGER

Field Status : current

Description : Total number of SMTP requests received by the SMTP proxy.

OID : 1.3.6.1.4.1.22610.2.4.3.13.3

Field Name : axSmtProxyStatsTotalProxyConns

Field Type : INTEGER

Field Status : current

Description : Total number of SMTP connections that have used the AX Series device as an SMTP proxy.

OID : 1.3.6.1.4.1.22610.2.4.3.13.2

Field Name : axSmtProxyStatsCurrProxyConns

Field Type : INTEGER

Field Status : current

Description : Number of currently active SMTP connections using the AX Series device as an SMTP proxy.

OID : 1.3.6.1.4.1.22610.2.4.3.13.1

Field Name : axSmtProxyStatEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The Smt proxy STAT entry.

OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1

Field Name : axSmtProxyStatSNATFail

Field Type : Counter

Field Status : current

Description : Number of source NAT failures.

OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.19

Field Name : axSmtProxyStatSvrConnMade

Field Type : Counter

Field Status : current

Description : Number of connections made with servers.

OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.18

Field Name : axSmtProxyStatSvrPrematureClose

Field Type : Counter

Field Status : current

Description : TNumber of times the connection with a server closed prematurely.

OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.17

Field Name : axSmtProxyStatServerResel

Field Type : Counter

Field Status : current

Description : Number of times a request was forwarded to another server because the current server was failing.

OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.16

Field Name : axSmtProxyStatReqPktOutOrder

Field Type : Counter

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : Number of request packets received from clients out of sequence.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.15

Field Name : axSmtProxyStatReqRetrans
Field Type : Counter
Field Status : current
Description : Number of retransmitted requests.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.14

Field Name : axSmtProxyStatFwdReqDataFail
Field Type : Counter
Field Status : current
Description : Number of forward request data failures.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.13

Field Name : axSmtProxyStatFwdReqFail
Field Type : Counter
Field Status : current
Description : Number of forward request failures.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.12

Field Name : axSmtProxyStatServerSelFail
Field Type : Counter
Field Status : current
Description : Number of times selection of a real server failed.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.11

Field Name : axSmtProxyStatParseReqFail
Field Type : Counter
Field Status : current
Description : Number of times parsing of an SMTP request failed.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.10

Field Name : axSmtProxyStatNoTupleError
Field Type : Counter
Field Status : current
Description : Number of tuple errors.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.9

Field Name : axSmtProxyStatServerRST
Field Type : Counter
Field Status : current
Description : Number of times TCP connections with servers were reset.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.8

Field Name : axSmtProxyStatClientRST
Field Type : Counter
Field Status : current
Description : Number of times TCP connections with clients were reset.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.7

Field Name : axSmtProxyStatNoProxyError
Field Type : Counter
Field Status : current
Description : Number of proxy errors.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.6

A10-AX-MIB_axMgmt_oid_list

Field Name : axSmtProxyStatSmtReqSucc
Field Type : Counter
Field Status : current
Description : Number of SMTP requests received by the AX Series device that were successfully fulfilled (by connection to a real server).
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.5

Field Name : axSmtProxyStatSmtReq
Field Type : Counter
Field Status : current
Description : Total number of SMTP requests received by the SMTP proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.4

Field Name : axSmtProxyStatTotalProxyConn
Field Type : Counter
Field Status : current
Description : Total number of SMTP connections that have used the AX Series device as an SMTP proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.3

Field Name : axSmtProxyStatCurrProxyConn
Field Type : Counter
Field Status : current
Description : Number of currently active SMTP connections using the AX Series device as an SMTP proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.2

Field Name : axSmtProxyStatCpuIndex
Field Type : Integer32
Field Status : current
Description : The Module Index of Smt Proxy STAT table
OID : 1.3.6.1.4.1.22610.2.4.3.13.19.1.1

Field Name : axNetStatTable
Field Type : TABLE
Field Status : current
Description : The Net STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100

Field Name : axNetStatExtPSBLBEntryLimitExceed
Field Type : Counter
Field Status : current
Description : Number of L4 skip insert client ip
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.70

Field Name : axNetStatExtL4ServerDownDel
Field Type : Counter
Field Status : current
Description : Number of L4 skip insert client ip
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.69

Field Name : axNetStatExtL4SkipInsertClientIp
Field Type : Counter
Field Status : current
Description : Number of L4 skip insert client ip
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.68

A10-AX-MIB_axMgmt_oid_list

Field Name : axNetStatExtL4TcpEst
Field Type : Counter
Field Status : current
Description : Number of L4 TCP Established
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.67

Field Name : axNetStatExtL4UdpRsps
Field Type : Counter
Field Status : current
Description : Number of L4 UDP rsps
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.66

Field Name : axNetStatExtL4UdpReqs
Field Type : Counter
Field Status : current
Description : Number of L4 UDP reqs
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.65

Field Name : axNetStatExtL4UdpRspsGreaterReqs
Field Type : Counter
Field Status : current
Description : Number of L4 UDP rsps > reqs
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.64

Field Name : axNetStatExtL4UdpReqGreaterRsps
Field Type : Counter
Field Status : current
Description : Number of L4 UDP req > rsps
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.63

Field Name : axNetStatExtL4UdpReqRspNotMatch
Field Type : Counter
Field Status : current
Description : Number of L4 UDP req/rsp not match
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.62

Field Name : axNetStatExtL4UdpReqRsps
Field Type : Counter
Field Status : current
Description : Number of L4 UDP req rsps
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.61

Field Name : axNetStatExtL4UdpReqsNoRsp
Field Type : Counter
Field Status : current
Description : Number of L4 UDP reqs no rsp
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.60

Field Name : axNetStatExtL4RcfRevRst
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rev RST
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.59

Field Name : axNetStatExtL4RcvFwdRst
Field Type : Counter

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : Number of L4 rcv fwd RST
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.58

Field Name : axNetStatExtL4RcvFevFinAck
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rev FIN|ACK
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.57

Field Name : axNetStatExtL4RcvRevFinDup
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rev FIN dup
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.56

Field Name : axNetStatExtL4RcvRevFin
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rev FIN
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.55

Field Name : axNetStatExtL4RcvFwdFinAck
Field Type : Counter
Field Status : current
Description : Number of L4 rcv fwd FIN|ACK
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.54

Field Name : axNetStatExtL4RcvFwdFinDrop
Field Type : Counter
Field Status : current
Description : Number of L4 rcv fwd FIN dup
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.53

Field Name : axNetStatExtL4RcvFwdFin
Field Type : Counter
Field Status : current
Description : Number of L4 rcv fwd FIN
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.52

Field Name : axNetStatExtL4RcvRevLastAck
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rev last ACK
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.51

Field Name : axNetStatExtL4RcvFwdLastAck
Field Type : Counter
Field Status : current
Description : Number of L4 rcv fwd last ACK
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.50

Field Name : axNetStatExtL4RcvReXmitSynAckDq
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rexmit SYN|ACK DQ
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.49

A10-AX-MIB_axMgmt_oid_list

Field Name : axNetStatExtL4RcvReXmitSynAck
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rexmit SYN|ACK
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.48

Field Name : axNetStatExtL4RcvReXmitSynDelq
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rexmit SYN (delq)
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.47

Field Name : axNetStatExtL4RcvReXmitSyn
Field Type : Counter
Field Status : current
Description : Number of L4 rcv rexmit SYN
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.46

Field Name : axNetStatExtNoEstSsynSntAgedOut
Field Type : Counter
Field Status : current
Description : Number of no-Est SSYN snt aged out
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.45

Field Name : axNetStatExtNoEstCsynRcvAgedOut
Field Type : Counter
Field Status : current
Description : Number of no-Est CSYN rcv aged out
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.44

Field Name : axNetStatExtTcpNoEstSessionAgedOut
Field Type : Counter
Field Status : current
Description : Number of TCP no-Est Sess aged out
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.43

Field Name : axNetStatExtL4RcvRstOnSyn
Field Type : Counter
Field Status : current
Description : Number of L4 rcv RST on SYN
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.42

Field Name : axNetStatExtL4RcvAckOnSyn
Field Type : Counter
Field Status : current
Description : Number of L4 rcv ACK on SYN
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.41

Field Name : axNetStatExtL4AxReXmitSyn
Field Type : Counter
Field Status : current
Description : Number of L4 AX re-xmit SYN
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.40

Field Name : axNetStatExtL4ServerHandshakeFail
Field Type : Counter

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : Number of L4 server handshake fail
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.39

Field Name : axNetStatExtL3vConnLimitDrop
Field Type : Counter
Field Status : current
Description : Number of L3V Conn Limit Drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.38

Field Name : axNetStatExtSslTptWaterMarkDrop
Field Type : Counter
Field Status : current
Description : Number of SSL TPT-Watermark drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.37

Field Name : axNetStatExtSslTptExceedDrop
Field Type : Counter
Field Status : current
Description : Number of SSL TPT exceed drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.36

Field Name : axNetStatExtSslCpsExceedDrop
Field Type : Counter
Field Status : current
Description : Number of SSL CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.35

Field Name : axNetStatExtL7CpsExceedDrop
Field Type : Counter
Field Status : current
Description : Number of L7 CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.34

Field Name : axNetStatExtNatCpsExceedDrop
Field Type : Counter
Field Status : current
Description : Number of NAT CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.33

Field Name : axNetStatExtL4CpsExceedDrop
Field Type : Counter
Field Status : current
Description : Number of L4 CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.32

Field Name : axNetStatExtBwWaterMarkDrop
Field Type : Counter
Field Status : current
Description : Number of BW-Watermark drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.31

Field Name : axNetStatExtBwLimitExceedDrop
Field Type : Counter
Field Status : current
Description : Number of BW-Limit Exceed drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.30

A10-AX-MIB_axMgmt_oid_list

Field Name : axNetStatExtNatPortPreserveSucc
Field Type : Counter
Field Status : current
Description : Number of NAT Port Preserve Succ
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.29

Field Name : axNetStatExtNatPortPreserveTry
Field Type : Counter
Field Status : current
Description : Number of NAT Port Preserve Try
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.28

Field Name : axNetStatExtIgnoreMsl
Field Type : Counter
Field Status : current
Description : Number of ignore msl
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.27

Field Name : axNetStatExtTcpSynWithDataDrop
Field Type : Counter
Field Status : current
Description : Number of TCP SYN With Data Drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.26

Field Name : axNetStatExtTcpSynOtherFlagsDrop
Field Type : Counter
Field Status : current
Description : Number of TCP SYN Other Flags Drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.25

Field Name : axNetStatExtRstL7OnFailover
Field Type : Counter
Field Status : current
Description : Number of RST L7 on failover
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.24

Field Name : axNetStatExtResetUnknownConns
Field Type : Counter
Field Status : current
Description : Number of Reset unknown conn
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.23

Field Name : axNetStatExtNoResourceDrop
Field Type : Counter
Field Status : current
Description : Number of No resource drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.22

Field Name : axNetStatExtAnomalyPbslbDrop
Field Type : Counter
Field Status : current
Description : Number of Anomaly pbslb drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.21

Field Name : axNetStatExtAnomalyBadContent
Field Type : Counter

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : Number of Anomaly bad content
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.20

Field Name : axNetStatExtAnomalyZeroWindow
Field Type : Counter
Field Status : current
Description : Number of Anomaly zero window
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.19

Field Name : axNetStatExtAnomalyOutOfSeq
Field Type : Counter
Field Status : current
Description : Number of Anomaly out of sequence
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.18

Field Name : axNetStatExtTcpSynStaleSessionDrop
Field Type : Counter
Field Status : current
Description : Number of SYN stale sess drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.17

Field Name : axNetStatExtOutOfSeqAckDrop
Field Type : Counter
Field Status : current
Description : Number of Out of sequence ACK drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.16

Field Name : axNetStatExtTcpInvalidDrop
Field Type : Counter
Field Status : current
Description : Number of TCP invalid drop
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.15

Field Name : axNetStatExtFastAgingReset
Field Type : Counter
Field Status : current
Description : Number of Fast aging reset
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.14

Field Name : axNetStatExtFastAgingSet
Field Type : Counter
Field Status : current
Description : Number of Fast aging set
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.13

Field Name : axNetStatExtAutoReselectServer
Field Type : Counter
Field Status : current
Description : Number of Auto-reselect server
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.12

Field Name : axNetStatExtOtherSessionAgedOut
Field Type : Counter
Field Status : current
Description : Number of Other Session aged out
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.11

A10-AX-MIB_axMgmt_oid_list

Field Name : axNetStatExtUdpSessionAgedOut
Field Type : Counter
Field Status : current
Description : Number of UDP Session aged out
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.10

Field Name : axNetStatExtTcpSessionAgedOut
Field Type : Counter
Field Status : current
Description : Number of TCP Session aged out
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.9

Field Name : axNetStatExtNoVportDrop
Field Type : Counter
Field Status : current
Description : Number of vport not matching drops
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.8

Field Name : axNetStatExtAutoNatIdMismatch
Field Type : Counter
Field Status : current
Description : Number of Auto NAT id mismatch
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.7

Field Name : axNetStatExtNatIcmpNoMatch
Field Type : Counter
Field Status : current
Description : Number of Source NAT ICMP no match
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.6

Field Name : axNetStatExtNatIcmpProcess
Field Type : Counter
Field Status : current
Description : Number of Source NAT ICMP process
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.5

Field Name : axNetStatExtNatNoRevRoute
Field Type : Counter
Field Status : current
Description : Number of Source NAT no rev route
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.4

Field Name : axNetStatExtNatNoFwdRoute
Field Type : Counter
Field Status : current
Description : Number of Source NAT no fwd route
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.3

Field Name : axNetStatExtL3Dsr
Field Type : Counter
Field Status : current
Description : Number of L3 DSR
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.2

Field Name : axNetStatExtL2Dsr
Field Type : Counter

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : Number of L2 DSR
OID : 1.3.6.1.4.1.22610.2.4.3.11.90.1

Field Name : axNetStatL4SynAttack
Field Type : Counter
Field Status : current
Description : Number of L4 SYN attacks
OID : 1.3.6.1.4.1.22610.2.4.3.11.47

Field Name : axNetStat2UDPReceive
Field Type : Counter64
Field Status : current
Description : Number of UDP packets received in the 64-bit counter.
OID : 1.3.6.1.4.1.22610.2.4.3.11.46

Field Name : axNetStat2TCPReceive
Field Type : Counter64
Field Status : current
Description : Number of TCP packets received in the 64-bit counter.
OID : 1.3.6.1.4.1.22610.2.4.3.11.45

Field Name : axNetStatInbandHMReassign
Field Type : Counter
Field Status : current
Description : Total number of Inband HM reassign.
OID : 1.3.6.1.4.1.22610.2.4.3.11.44

Field Name : axNetStatInbandHMRetry
Field Type : Counter
Field Status : current
Description : Total number of Inband HM retry.
OID : 1.3.6.1.4.1.22610.2.4.3.11.43

Field Name : axNetStatConnRateLimitResets
Field Type : Counter
Field Status : current
Description : Total number of Conn rate limit resets.
OID : 1.3.6.1.4.1.22610.2.4.3.11.42

Field Name : axNetStatConnRateLimitDrops
Field Type : Counter
Field Status : current
Description : Total number of Conn rate limit drops.
OID : 1.3.6.1.4.1.22610.2.4.3.11.41

Field Name : axNetStatCreateSSLSIDFail
Field Type : Counter
Field Status : current
Description : Total number of Create SSL SID failed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.40

Field Name : axNetStatCreateSSLSIDSucc
Field Type : Counter
Field Status : current
Description : Total number of Create SSL SID successfully.
OID : 1.3.6.1.4.1.22610.2.4.3.11.39

A10-AX-MIB_axMgmt_oid_list

Field Name : axNetStatServerSSLSIDNotMatch
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID not match.
OID : 1.3.6.1.4.1.22610.2.4.3.11.38

Field Name : axNetStatServerSSLSIDMatch
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID match.
OID : 1.3.6.1.4.1.22610.2.4.3.11.37

Field Name : axNetStatServerSSLSIDReset
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID reset.
OID : 1.3.6.1.4.1.22610.2.4.3.11.36

Field Name : axNetStatServerSSLSIDNotFound
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID not found.
OID : 1.3.6.1.4.1.22610.2.4.3.11.35

Field Name : axNetStatClientSSLSIDNotMatch
Field Type : Counter
Field Status : current
Description : Total number of Client SSL SID not match.
OID : 1.3.6.1.4.1.22610.2.4.3.11.34

Field Name : axNetStatClientSSLSIDMatch
Field Type : Counter
Field Status : current
Description : Total number of Client SSL SID match
OID : 1.3.6.1.4.1.22610.2.4.3.11.33

Field Name : axNetStatClientSSLSIDNotFound
Field Type : Counter
Field Status : current
Description : Total number of Client SSL SID not found.
OID : 1.3.6.1.4.1.22610.2.4.3.11.32

Field Name : axNetStatSSLSIDPersistFail
Field Type : Counter
Field Status : current
Description : Total number of SSL SID persist failed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.31

Field Name : axNetStatSSLSIDPersistSucc
Field Type : Counter
Field Status : current
Description : Total number of SSL SID persist successful.
OID : 1.3.6.1.4.1.22610.2.4.3.11.30

Field Name : axNetStatSYNThrotte
Field Type : Counter

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : Total number of SYN Throttle.
OID : 1.3.6.1.4.1.22610.2.4.3.11.29

Field Name : axNetStatNoSYNPktDropACK
Field Type : Counter
Field Status : current
Description : Total number of No SYN pkt drops - ACK.
OID : 1.3.6.1.4.1.22610.2.4.3.11.28

Field Name : axNetStatNoSYNPktDropRST
Field Type : Counter
Field Status : current
Description : Total number of No SYN pkt drops - RST.
OID : 1.3.6.1.4.1.22610.2.4.3.11.27

Field Name : axNetStatNoSYNPktDropFIN
Field Type : Counter
Field Status : current
Description : Total number of No SYN pkt drops - FIN.
OID : 1.3.6.1.4.1.22610.2.4.3.11.26

Field Name : axNetStatTCPOutRSTProxy
Field Type : Counter
Field Status : current
Description : Total number of TCP out RST TCP proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.11.25

Field Name : axNetStatTCPOutRSTStaleSess
Field Type : Counter
Field Status : current
Description : Total number of TCP out RST stale session.
OID : 1.3.6.1.4.1.22610.2.4.3.11.24

Field Name : axNetStatTCPOutRSTAFlex
Field Type : Counter
Field Status : current
Description : Total number of TCP out RST aFlex.
OID : 1.3.6.1.4.1.22610.2.4.3.11.23

Field Name : axNetStatTCPOutRSTACKattack
Field Type : Counter
Field Status : current
Description : Total number of TCP out RST ACK attack.
OID : 1.3.6.1.4.1.22610.2.4.3.11.22

Field Name : axNetStatTCPOutRSTL4Proxy
Field Type : Counter
Field Status : current
Description : Total number of TCP out RST L4 proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.11.21

Field Name : axNetStatTCPOutRSTNoSYN
Field Type : Counter
Field Status : current
Description : Total number of TCP out RST no SYN.
OID : 1.3.6.1.4.1.22610.2.4.3.11.20

A10-AX-MIB_axMgmt_oid_list

Field Name : axNetStatUDPNoSLB
Field Type : Counter
Field Status : current
Description : Total number of UDP packets in non SLB processing.
OID : 1.3.6.1.4.1.22610.2.4.3.11.19

Field Name : axNetStatTCPNoSLB
Field Type : Counter
Field Status : current
Description : Total number of TCP packets in non SLB processing.
OID : 1.3.6.1.4.1.22610.2.4.3.11.18

Field Name : axNetStatSessionAgingOut
Field Type : Counter
Field Status : current
Description : Number of sessions that have aged out.
OID : 1.3.6.1.4.1.22610.2.4.3.11.17

Field Name : axNetStataFlexDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped due to an aFlex.
OID : 1.3.6.1.4.1.22610.2.4.3.11.16

Field Name : axNetStatProxyNoSockDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped because the proxy did not have an available socket.
OID : 1.3.6.1.4.1.22610.2.4.3.11.15

Field Name : axNetStatConnLimitReset
Field Type : Counter
Field Status : current
Description : Number of connections reset because the server connection limit had been reached.
OID : 1.3.6.1.4.1.22610.2.4.3.11.14

Field Name : axNetStatConnLimitDrop
Field Type : Counter
Field Status : current
Description : Number of packets dropped because the server connection limit had been reached.
OID : 1.3.6.1.4.1.22610.2.4.3.11.13

Field Name : axNetStatNoSynPktDrop
Field Type : Counter
Field Status : current
Description : Number of SYN packets dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.11.12

Field Name : axNetStatNoVportDrop
Field Type : Counter
Field Status : current
Description : Number of times traffic was dropped because the requested virtual port was not available.
OID : 1.3.6.1.4.1.22610.2.4.3.11.11

A10-AX-MIB_axMgmt_oid_list

Field Name : axNetStatTCPSynCookieFail
Field Type : Counter
Field Status : current
Description : Number of times a TCP SYN cookie failure occurred.
OID : 1.3.6.1.4.1.22610.2.4.3.11.10

Field Name : axNetStatSourceNATFail
Field Type : Counter
Field Status : current
Description : Number of times a source NAT failure occurred.
OID : 1.3.6.1.4.1.22610.2.4.3.11.9

Field Name : axNetStatServerSelFail
Field Type : Counter
Field Status : current
Description : Number of times selection of a real server failed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.8

Field Name : axNetStatUDPReceive
Field Type : Counter
Field Status : current
Description : Number of UDP packets received.
OID : 1.3.6.1.4.1.22610.2.4.3.11.7

Field Name : axNetStatTCPReceive
Field Type : Counter
Field Status : current
Description : Number of TCP packets received.
OID : 1.3.6.1.4.1.22610.2.4.3.11.6

Field Name : axNetStatTCPSYNCookieSentFail
Field Type : Counter
Field Status : current
Description : The count of TCP SYN cookie sent fail.
OID : 1.3.6.1.4.1.22610.2.4.3.11.5

Field Name : axNetStatTCPSYNCookieSent
Field Type : Counter
Field Status : current
Description : The count of TCP SYN cookie sent.
OID : 1.3.6.1.4.1.22610.2.4.3.11.4

Field Name : axNetStatTCPSynRcv
Field Type : Counter
Field Status : current
Description : The count of TCP SYN packets received.
OID : 1.3.6.1.4.1.22610.2.4.3.11.3

Field Name : axNetStatTCPOutRst
Field Type : Counter
Field Status : current
Description : The count of TCP out Reset.
OID : 1.3.6.1.4.1.22610.2.4.3.11.2

Field Name : axNetStatIPOutNoRoute
Field Type : Counter

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : The count of IP out no route.
OID : 1.3.6.1.4.1.22610.2.4.3.11.1

Field Name : axNetStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The Net STAT entry.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1

Field Name : axNetStatEntryInbandHMReassign
Field Type : Counter
Field Status : current
Description : Number of Inband HM reassign.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.45

Field Name : axNetStatEntryInbandHMRetry
Field Type : Counter
Field Status : current
Description : Number of Inband HM retry.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.44

Field Name : axNetStatEntryConnRateLimitResets
Field Type : Counter
Field Status : current
Description : Number of Conn rate limit resets.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.43

Field Name : axNetStatEntryConnRateLimitDrops
Field Type : Counter
Field Status : current
Description : Number of Conn rate limit drops.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.42

Field Name : axNetStatEntryCreateSSLSIDFail
Field Type : Counter
Field Status : current
Description : Total number of Create SSL SID failed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.41

Field Name : axNetStatEntryCreateSSLSIDSucc
Field Type : Counter
Field Status : current
Description : Total number of Create SSL SID successfully.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.40

Field Name : axNetStatEntryServerSSLSIDNotMatch
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID not match.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.39

Field Name : axNetStatEntryServerSSLSIDMatch
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID match.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.38

A10-AX-MIB_axMgmt_oid_list

Field Name : axNetStatEntryServerSSLSIDReset
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID reset.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.37

Field Name : axNetStatEntryServerSSLSIDNotFound
Field Type : Counter
Field Status : current
Description : Total number of Server SSL SID not found.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.36

Field Name : axNetStatEntryClientSSLSIDNotMatch
Field Type : Counter
Field Status : current
Description : Total number of Client SSL SID not match.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.35

Field Name : axNetStatEntryClientSSLSIDMatch
Field Type : Counter
Field Status : current
Description : Total number of Client SSL SID match
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.34

Field Name : axNetStatEntryClientSSLSIDNotFound
Field Type : Counter
Field Status : current
Description : Total number of Client SSL SID not found.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.33

Field Name : axNetStatEntrySSLSIDPersistFail
Field Type : Counter
Field Status : current
Description : Total number of SSL SID persist failed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.32

Field Name : axNetStatEntrySSLSIDPersistSucc
Field Type : Counter
Field Status : current
Description : Total number of SSL SID persist successful.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.31

Field Name : axNetStatEntrySYNThrotte
Field Type : Counter
Field Status : current
Description : Number of SYN Throttle.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.30

Field Name : axNetStatEntryNoSYNPktDropACK
Field Type : Counter
Field Status : current
Description : Number of No SYN pkt drops - ACK.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.29

Field Name : axNetStatEntryNoSYNPktDropRST
Field Type : Counter

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : Number of No SYN pkt drops - RST.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.28

Field Name : axNetStatEntryNoSYNPktDropFIN
Field Type : Counter
Field Status : current
Description : Number of No SYN pkt drops - FIN.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.27

Field Name : axNetStatEntryTCPOutRSTProxy
Field Type : Counter
Field Status : current
Description : Number of TCP out RST TCP proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.26

Field Name : axNetStatEntryTCPOutRSTStaleSess
Field Type : Counter
Field Status : current
Description : Number of TCP out RST stale session.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.25

Field Name : axNetStatEntryTCPOutRSTAFlex
Field Type : Counter
Field Status : current
Description : Number of TCP out RST aFlex.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.24

Field Name : axNetStatEntryTCPOutRSTACKattack
Field Type : Counter
Field Status : current
Description : Number of TCP out RST ACK attack.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.23

Field Name : axNetStatEntryTCPOutRSTL4Proxy
Field Type : Counter
Field Status : current
Description : Number of TCP out RST L4 proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.22

Field Name : axNetStatEntryTCPOutRSTNoSYN
Field Type : Counter
Field Status : current
Description : Number of TCP out RST no SYN.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.21

Field Name : axNetStatUDPsNoSLB
Field Type : Counter
Field Status : current
Description : Number of UDP packets in non SLB processing.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.20

Field Name : axNetStatTCPsNoSLB
Field Type : Counter
Field Status : current
Description : Number of TCP packets in non SLB processing.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.19

A10-AX-MIB_axMgmt_oid_list

Field Name : axNetStatSessionsAgingOut
Field Type : Counter
Field Status : current
Description : Number of sessions that have aged out.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.18

Field Name : axNetStatFlexDrops
Field Type : Counter
Field Status : current
Description : Number of packets dropped due to an aFlex.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.17

Field Name : axNetStatProxyNoSockDrops
Field Type : Counter
Field Status : current
Description : Number of packets dropped because the proxy did not have an available socket.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.16

Field Name : axNetStatConnLimitResets
Field Type : Counter
Field Status : current
Description : Number of connections reset because the server connection limit had been reached.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.15

Field Name : axNetStatConnLimitDrops
Field Type : Counter
Field Status : current
Description : Number of packets dropped because the server connection limit had been reached.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.14

Field Name : axNetStatNoSynPktDrops
Field Type : Counter
Field Status : current
Description : Number of SYN packets dropped.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.13

Field Name : axNetStatNoVportDrops
Field Type : Counter
Field Status : current
Description : Number of times traffic was dropped because the requested virtual port was not available.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.12

Field Name : axNetStatTCPSynCookieFails
Field Type : Counter
Field Status : current
Description : Number of times a TCP SYN cookie failure occurred.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.11

Field Name : axNetStatSourceNATFails
Field Type : Counter
Field Status : current
Description : Number of times a source NAT failure occurred.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.10

A10-AX-MIB_axMgmt_oid_list

Field Name : axNetStatServerSelfFails
Field Type : Counter
Field Status : current
Description : Number of times selection of a real server failed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.9

Field Name : axNetStatUDPRcv
Field Type : Counter
Field Status : current
Description : Number of UDP packets received.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.8

Field Name : axNetStatTCPRcv
Field Type : Counter
Field Status : current
Description : Number of TCP packets received.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.7

Field Name : axNetStatTCPSYNCookieSntFail
Field Type : Counter
Field Status : current
Description : Number of TCP SYN cookie send attempts that failed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.6

Field Name : axNetStatTCPSYNCookieSnt
Field Type : Counter
Field Status : current
Description : Number of TCP SYN cookies sent.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.5

Field Name : axNetStatTCPSynRecv
Field Type : Counter
Field Status : current
Description : Number of TCP SYN packets received.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.4

Field Name : axNetStatTCPOutReset
Field Type : Counter
Field Status : current
Description : Number of TCP Resets sent.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.3

Field Name : axNetStatIPOutNoRt
Field Type : Counter
Field Status : current
Description : Number of IP packets that could not be routed.
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.2

Field Name : axNetStatCpuIndex
Field Type : Gauge
Field Status : current
Description : The Module Index of Net STAT table
OID : 1.3.6.1.4.1.22610.2.4.3.11.100.1.1

Field Name : axFtpStatOutConnData
Field Type : Integer32

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : The total count of out of data connections.
OID : 1.3.6.1.4.1.22610.2.4.3.10.6

Field Name : axFtpStatTotalDataSession
Field Type : INTEGER
Field Status : current
Description : The total count of data sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.10.5

Field Name : axFtpStatOutConnCtrl
Field Type : INTEGER
Field Status : current
Description : The count of out of control connections.
OID : 1.3.6.1.4.1.22610.2.4.3.10.4

Field Name : axFtpStatALGPktReXmit
Field Type : INTEGER
Field Status : current
Description : The count of ALG packets rexmitted.
OID : 1.3.6.1.4.1.22610.2.4.3.10.3

Field Name : axFtpStatTotalALGPkt
Field Type : INTEGER
Field Status : current
Description : The total count of ALG packets.
OID : 1.3.6.1.4.1.22610.2.4.3.10.2

Field Name : axFtpStatTotalCtrlSession
Field Type : INTEGER
Field Status : current
Description : The total count of control sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.10.1

Field Name : axSslStatSSLFailedCryptoOperation
Field Type : INTEGER
Field Status : current
Description : Number of times when the crypto operation fails.
OID : 1.3.6.1.4.1.22610.2.4.3.9.10

Field Name : axSslStatSSLHWRingFull
Field Type : INTEGER
Field Status : current
Description : Number of times the AX software was unable to enqueue an SSL record to the SSL processor for encryption/decryption.(Number of times the processor reached its performance limit.)
OID : 1.3.6.1.4.1.22610.2.4.3.9.9

Field Name : axSslStatSSLNoHWContextMem
Field Type : INTEGER
Field Status : current
Description : Number of times the encryption processor was unable to allocate memory.
OID : 1.3.6.1.4.1.22610.2.4.3.9.8

Field Name : axSslStatSSLFailedCAVfy
Field Type : INTEGER
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : Number of times an SSL session was terminated due to a certificate verification failure.

OID : 1.3.6.1.4.1.22610.2.4.3.9.7

Field Name : axSslStatTable

Field Type : TABLE

Field Status : current

Description : The SSL STAT table.

OID : 1.3.6.1.4.1.22610.2.4.3.9.6

Field Name : axSslStatEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The SSL STAT entry.

OID : 1.3.6.1.4.1.22610.2.4.3.9.6.1

Field Name : axSslStatAvailCryptoEngine

Field Type : Counter

Field Status : current

Description : The number of available crypto engines.

OID : 1.3.6.1.4.1.22610.2.4.3.9.6.1.3

Field Name : axSslStatEnableCryptoEngine

Field Type : Counter

Field Status : current

Description : The number of enabled crypto engines.

OID : 1.3.6.1.4.1.22610.2.4.3.9.6.1.2

Field Name : axSslStatModuleIndex

Field Type : Integer32

Field Status : current

Description : The Module Index of SSL STAT table

OID : 1.3.6.1.4.1.22610.2.4.3.9.6.1.1

Field Name : axSslStatSSLMemUsage

Field Type : INTEGER

Field Status : current

Description : The SSL Memory usage(Byte).

OID : 1.3.6.1.4.1.22610.2.4.3.9.5

Field Name : axSslStatFailSSLHandshake

Field Type : Counter64

Field Status : current

Description : Failed SSL handshake.

OID : 1.3.6.1.4.1.22610.2.4.3.9.4

Field Name : axSslStatTotalSSLConn

Field Type : Counter64

Field Status : current

Description : Total SSL connections.

OID : 1.3.6.1.4.1.22610.2.4.3.9.3

Field Name : axSslStatCurrSSLConn

Field Type : Counter64

Field Status : current

Description : Current SSL Connections.

OID : 1.3.6.1.4.1.22610.2.4.3.9.2

A10-AX-MIB_axMgmt_oid_list

Field Name : axSslStatSSLModNum
Field Type : INTEGER
Field Status : current
Description : The number of SSL modules.
OID : 1.3.6.1.4.1.22610.2.4.3.9.1

Field Name : axTCPProxyStatTable
Field Type : TABLE
Field Status : current
Description : The TCP proxy STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10

Field Name : axTcpProxyStatTotalRstSent
Field Type : INTEGER
Field Status : current
Description : The total count of reset sent.
OID : 1.3.6.1.4.1.22610.2.4.3.8.9

Field Name : axTcpProxyStatTotalRstRcvOnEstConn
Field Type : INTEGER
Field Status : current
Description : The total count of reset received on established connection.
OID : 1.3.6.1.4.1.22610.2.4.3.8.8

Field Name : axTcpProxyStatTotalReXmitPkt
Field Type : INTEGER
Field Status : current
Description : The total count of re-transmitted packets.
OID : 1.3.6.1.4.1.22610.2.4.3.8.7

Field Name : axTcpProxyStatTotalOutTCPPkt
Field Type : INTEGER
Field Status : current
Description : The total count of sent tcp packets.
OID : 1.3.6.1.4.1.22610.2.4.3.8.6

Field Name : axTcpProxyStatTotalInTCPPacket
Field Type : INTEGER
Field Status : current
Description : The total count of received tcp packets.
OID : 1.3.6.1.4.1.22610.2.4.3.8.5

Field Name : axTcpProxyStatTotalConnAttemptFail
Field Type : INTEGER
Field Status : current
Description : The total count of connecting attempt fails.
OID : 1.3.6.1.4.1.22610.2.4.3.8.4

Field Name : axTcpProxyStatTotalPassiveOpenConn
Field Type : INTEGER
Field Status : current
Description : The total count of passively opened tcp connections.
OID : 1.3.6.1.4.1.22610.2.4.3.8.3

Field Name : axTcpProxyStatTotalActiveOpenConn
Field Type : INTEGER

A10-AX-MIB_axMgmt_oid_list

Field Status : current

Description : The total count of actively opened tcp Connections.

OID : 1.3.6.1.4.1.22610.2.4.3.8.2

Field Name : axTcpProxyStatTotalCurrEstConn

Field Type : INTEGER

Field Status : current

Description : The total count of currently established tcp Connections.

OID : 1.3.6.1.4.1.22610.2.4.3.8.1

Field Name : axTCPProxyStatEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The TCP proxy STAT entry.

OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1

Field Name : axTcpProxyStatTCPClosingState

Field Type : Counter

Field Status : current

Description : The count of TCP connections in closing state.

OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.26

Field Name : axTcpProxyStatTCPListenState

Field Type : Counter

Field Status : current

Description : The count of TCP connections in listen state.

OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.25

Field Name : axTcpProxyStatTCPLastACKState

Field Type : Counter

Field Status : current

Description : The count of TCP connections in lastACK state.

OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.24

Field Name : axTcpProxyStatTCPCloseWState

Field Type : Counter

Field Status : current

Description : The count of TCP connections in closeW state.

OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.23

Field Name : axTcpProxyStatTCPCloseState

Field Type : Counter

Field Status : current

Description : The count of TCP connections in close state.

OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.22

Field Name : axTcpProxyStatTimeWstate

Field Type : Counter

Field Status : current

Description : The count of TCP connections in TCP TimeW state.

OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.21

Field Name : axTcpProxyStatTCPFINW2State

Field Type : Counter

Field Status : current

Description : The count of TCP connections in FIN-W2 state.

OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.20

A10-AX-MIB_axMgmt_oid_list

Field Name : axTcpProxyStatTCPFINW1State
Field Type : Counter
Field Status : current
Description : The count of TCP connections in FIN-W1 state.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.19

Field Name : axTcpProxyStatTCPSYNRCVState
Field Type : Counter
Field Status : current
Description : The count of TCP connections in SYN-RCV state.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.18

Field Name : axTcpProxyStatTCPSYNSNTState
Field Type : Counter
Field Status : current
Description : The count of TCP connections in SYN-SNT state.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.17

Field Name : axTcpProxyStatTotalTxBuf
Field Type : Counter
Field Status : current
Description : The size of TX buffer.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.16

Field Name : axTcpProxyStatTotalRxBuf
Field Type : Counter
Field Status : current
Description : The size of Rx buffer.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.15

Field Name : axTcpProxyStatMemAlloc
Field Type : Counter
Field Status : current
Description : The size of allocated memory used by tcp proxy.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.14

Field Name : axTcpProxyStatOrphanSocket
Field Type : Counter
Field Status : current
Description : The count of orphan sockets.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.13

Field Name : axTcpProxyStatSocketAlloc
Field Type : Counter
Field Status : current
Description : The count of socket allocated.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.12

Field Name : axTcpProxyStatInputErr
Field Type : Counter
Field Status : current
Description : The count of Input Error.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.11

Field Name : axTcpProxyStatRstSent
Field Type : Counter

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : The count of Reset Sent.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.10

Field Name : axTcpProxyStatRstRvdEstConn
Field Type : Counter
Field Status : current
Description : The count of reset received on established connections.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.9

Field Name : axTcpProxyStatReTranPkt
Field Type : Counter
Field Status : current
Description : The count of re-transmit packets.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.8

Field Name : axTcpProxyStatTotalOutPkt
Field Type : Counter
Field Status : current
Description : The total count of packets sent.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.7

Field Name : axTcpProxyStatTotalInTCPPkt
Field Type : Counter
Field Status : current
Description : The total count of packet received.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.6

Field Name : axTcpProxyStatConnAttempFail
Field Type : Counter
Field Status : current
Description : The count of connecting attempt fail.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.5

Field Name : axTcpProxyStatPassiveOpenConns
Field Type : Counter
Field Status : current
Description : The count of passive open connections.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.4

Field Name : axTcpProxyStatActiveOpenConns
Field Type : Counter
Field Status : current
Description : The count of active open connections.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.3

Field Name : axTcpProxyStatCurrEstConns
Field Type : Counter
Field Status : current
Description : The count of currently established connections.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.2

Field Name : axTcpProxyStatCpuIndex
Field Type : Integer32
Field Status : current
Description : The cpu index of TCP proxy STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.8.10.1.1

A10-AX-MIB_axMgmt_oid_list

Field Name : axHttpProxyStatTable
Field Type : TABLE
Field Status : current
Description : The http proxy STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18

Field Name : axHttpProxyStatTotalSNATErr
Field Type : INTEGER
Field Status : current
Description : The total count of Source NAT failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.17

Field Name : axHttpProxyStatTotalSvrConn
Field Type : INTEGER
Field Status : current
Description : The total count of server connections made.
OID : 1.3.6.1.4.1.22610.2.4.3.7.16

Field Name : axHttpProxyStatTotalPreMatureClose
Field Type : INTEGER
Field Status : current
Description : The total count of server premature closed connections.
OID : 1.3.6.1.4.1.22610.2.4.3.7.15

Field Name : axHttpProxyStatTotalSvrReSel
Field Type : INTEGER
Field Status : current
Description : The total count of server reselect.
OID : 1.3.6.1.4.1.22610.2.4.3.7.14

Field Name : axHttpProxyStatTotalReqPktOutOrder
Field Type : INTEGER
Field Status : current
Description : The total count of request packet out of order.
OID : 1.3.6.1.4.1.22610.2.4.3.7.13

Field Name : axHttpProxyStatTotalReqReXmit
Field Type : INTEGER
Field Status : current
Description : The total count of retransmitted http request.
OID : 1.3.6.1.4.1.22610.2.4.3.7.12

Field Name : axHttpProxyStatTotalFwdDataReqErr
Field Type : INTEGER
Field Status : current
Description : The total count of firewall data request failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.11

Field Name : axHttpProxyStatTotalFwdReqErr
Field Type : INTEGER
Field Status : current
Description : The total count of firewall request fail.
OID : 1.3.6.1.4.1.22610.2.4.3.7.10

Field Name : axHttpProxyStatTotalSvrSelErr
Field Type : INTEGER

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : The total count of server select failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.9

Field Name : axHttpProxyStatTotalReqErr
Field Type : INTEGER
Field Status : current
Description : The total count of request parse failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.8

Field Name : axHttpProxyStatTotalNoTuple
Field Type : INTEGER
Field Status : current
Description : The total count of no tuple fail.
OID : 1.3.6.1.4.1.22610.2.4.3.7.7

Field Name : axHttpProxyStatTotalSRst
Field Type : INTEGER
Field Status : current
Description : The total count of http connections reset by server.
OID : 1.3.6.1.4.1.22610.2.4.3.7.6

Field Name : axHttpProxyStatTotalCRst
Field Type : INTEGER
Field Status : current
Description : The total count of http connections reset by client.
OID : 1.3.6.1.4.1.22610.2.4.3.7.5

Field Name : axHttpProxyStatTotalNoProxy
Field Type : INTEGER
Field Status : current
Description : The total count of no proxy fail.
OID : 1.3.6.1.4.1.22610.2.4.3.7.4

Field Name : axHttpProxyStatTotalSuccReq
Field Type : INTEGER
Field Status : current
Description : The total count of http requests which connected
: successful.
OID : 1.3.6.1.4.1.22610.2.4.3.7.3

Field Name : axHttpProxyStatTotalReq
Field Type : INTEGER
Field Status : current
Description : The total count of http requests.
OID : 1.3.6.1.4.1.22610.2.4.3.7.2

Field Name : axHttpProxyStatTotalConn
Field Type : INTEGER
Field Status : current
Description : The total count of proxy connections.
OID : 1.3.6.1.4.1.22610.2.4.3.7.1

Field Name : axHttpProxyStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The http proxy STAT entry.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1

Field Name : axHttpProxyStatServerConnMade
Field Type : Counter
Field Status : current
Description : The count of server connections made.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.18

Field Name : axHttpProxyStatServerPreMatureClose
Field Type : Counter
Field Status : current
Description : The count of server premature closed connections.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.17

Field Name : axHttpProxyStatServerReSel
Field Type : Counter
Field Status : current
Description : The count of server reselect.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.16

Field Name : axHttpProxyStatReqPktOutOrder
Field Type : Counter
Field Status : current
Description : The count of request packet out of order.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.15

Field Name : axHttpProxyStatReqReTran
Field Type : Counter
Field Status : current
Description : The count of retransmitted http request.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.14

Field Name : axHttpProxyStatFwdReqDataFail
Field Type : Counter
Field Status : current
Description : The count of firewall data request failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.13

Field Name : axHttpProxyStatFwdReqFail
Field Type : Counter
Field Status : current
Description : The count of firewall request fail.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.12

Field Name : axHttpProxyStatServerSelFail
Field Type : Counter
Field Status : current
Description : he count of server select failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.11

Field Name : axHttpProxyStatParseReqFail
Field Type : Counter
Field Status : current
Description : The count of request parse failed.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.10

Field Name : axHttpProxyStatNoTupleErr

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter
Field Status : current
Description : The count of no tuple fail.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.9

Field Name : axHttpProxyStatServerRst
Field Type : Counter
Field Status : current
Description : The count of http connections reset by server.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.8

Field Name : axHttpProxyStatClientRst
Field Type : Counter
Field Status : current
Description : The count of http connections reset by client.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.7

Field Name : axHttpProxyStatNoProxyErr
Field Type : Counter
Field Status : current
Description : The count of no proxy error.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.6

Field Name : axHttpProxyStatHttpReqSucc
Field Type : Counter
Field Status : current
Description : The count of http requests which connected successfully.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.5

Field Name : axHttpProxyStatHttpReq
Field Type : Counter
Field Status : current
Description : The count of http requests.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.4

Field Name : axHttpProxyStatTotalProxyConns
Field Type : Counter
Field Status : current
Description : The total count of http proxy connections of current cpu.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.3

Field Name : axHttpProxyStatCurrProxyConns
Field Type : Counter
Field Status : current
Description : The count of current http proxy connections
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.2

Field Name : axHttpProxyStatCpuIndex
Field Type : Integer32
Field Status : current
Description : The cpu Index of http proxy STAT table.
OID : 1.3.6.1.4.1.22610.2.4.3.7.18.1.1

Field Name : axFastHttpProxyStatTable
Field Type : TABLE
Field Status : current
Description : The fast http proxy status table.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.6.18

Field Name : axFastHttpProxyStatTotalSNATerr
Field Type : INTEGER
Field Status : current
Description : The total count of Source NAT failed.
OID : 1.3.6.1.4.1.22610.2.4.3.6.17

Field Name : axFastHttpProxyStatTotalSvrConn
Field Type : INTEGER
Field Status : current
Description : The total count of server connections made.
OID : 1.3.6.1.4.1.22610.2.4.3.6.16

Field Name : axFastHttpProxyStatTotalPreMatureClose
Field Type : INTEGER
Field Status : current
Description : The total count of server premature closed connections.
OID : 1.3.6.1.4.1.22610.2.4.3.6.15

Field Name : axFastHttpProxyStatTotalSvrReSel
Field Type : INTEGER
Field Status : current
Description : The total count of server reselect.
OID : 1.3.6.1.4.1.22610.2.4.3.6.14

Field Name : axFastHttpProxyStatTotalReqPktOutOrder
Field Type : INTEGER
Field Status : current
Description : The total count of request packet out of order.
OID : 1.3.6.1.4.1.22610.2.4.3.6.13

Field Name : axFastHttpProxyStatTotalReqReXmit
Field Type : INTEGER
Field Status : current
Description : The total count of retransmitted http request.
OID : 1.3.6.1.4.1.22610.2.4.3.6.12

Field Name : axFastHttpProxyStatTotalFwdDataReqErr
Field Type : INTEGER
Field Status : current
Description : The total count of firewall data request failed.
OID : 1.3.6.1.4.1.22610.2.4.3.6.11

Field Name : axFastHttpProxyStatTotalFwdReqErr
Field Type : INTEGER
Field Status : current
Description : The total count of firewall request fail.
OID : 1.3.6.1.4.1.22610.2.4.3.6.10

Field Name : axFastHttpProxyStatTotalSvrSelErr
Field Type : INTEGER
Field Status : current
Description : The total count of server select failed.
OID : 1.3.6.1.4.1.22610.2.4.3.6.9

Field Name : axFastHttpProxyStatTotalReqErr

A10-AX-MIB_axMgmt_oid_list

Field Type : INTEGER
Field Status : current
Description : The total count of request parse failed.
OID : 1.3.6.1.4.1.22610.2.4.3.6.8

Field Name : axFastHttpProxyStatTotalNoTuple
Field Type : INTEGER
Field Status : current
Description : The total count of no tuple fail.
OID : 1.3.6.1.4.1.22610.2.4.3.6.7

Field Name : axFastHttpProxyStatTotalSRst
Field Type : INTEGER
Field Status : current
Description : The total count of http connections reset by server.
OID : 1.3.6.1.4.1.22610.2.4.3.6.6

Field Name : axFastHttpProxyStatTotalCRst
Field Type : INTEGER
Field Status : current
Description : The total count of http connections reset by client.
OID : 1.3.6.1.4.1.22610.2.4.3.6.5

Field Name : axFastHttpProxyStatTotalNoProxy
Field Type : INTEGER
Field Status : current
Description : The total count of no proxy fail.
OID : 1.3.6.1.4.1.22610.2.4.3.6.4

Field Name : axFastHttpProxyStatTotalSuccReq
Field Type : INTEGER
Field Status : current
Description : The total count of http requests which connected successful.
OID : 1.3.6.1.4.1.22610.2.4.3.6.3

Field Name : axFastHttpProxyStatTotalReq
Field Type : INTEGER
Field Status : current
Description : The total count of http requests.
OID : 1.3.6.1.4.1.22610.2.4.3.6.2

Field Name : axFastHttpProxyStatTotalConn
Field Type : INTEGER
Field Status : current
Description : The total count of proxy connections.
OID : 1.3.6.1.4.1.22610.2.4.3.6.1

Field Name : axFastHttpProxyStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The fast http proxy status entry.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1

Field Name : axFastHttpProxyStatServerConnMade
Field Type : Counter
Field Status : current
Description : The count of server connections made.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.18

Field Name : axFastHttpProxyStatServerPreMatureClose

Field Type : Counter

Field Status : current

Description : The count of server premature closed connections.

OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.17

Field Name : axFastHttpProxyStatServerReSel

Field Type : Counter

Field Status : current

Description : The count of server reselect.

OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.16

Field Name : axFastHttpProxyStatReqPktOutOrder

Field Type : Counter

Field Status : current

Description : The count of request packet out of order.

OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.15

Field Name : axFastHttpProxyStatReqReTran

Field Type : Counter

Field Status : current

Description : The count of retransmitted http request.

OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.14

Field Name : axFastHttpProxyStatFwdReqDataFail

Field Type : Counter

Field Status : current

Description : The count of firewall data request failed.

OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.13

Field Name : axFastHttpProxyStatFwdReqFail

Field Type : Counter

Field Status : current

Description : The count of firewall request fail.

OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.12

Field Name : axFastHttpProxyStatServerSelFail

Field Type : Counter

Field Status : current

Description : The count of server select failed.

OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.11

Field Name : axFastHttpProxyStatParseReqFail

Field Type : Counter

Field Status : current

Description : The count of request parse failed.

OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.10

Field Name : axFastHttpProxyStatNoTupleErr

Field Type : Counter

Field Status : current

Description : The count of no tuple fail.

OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.9

Field Name : axFastHttpProxyStatServerRst

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter
Field Status : current
Description : The count of http connections reset by server.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.8

Field Name : axFastHttpProxyStatClientRst
Field Type : Counter
Field Status : current
Description : The count of http connections reset by client.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.7

Field Name : axFastHttpProxyStatNoProxyErr
Field Type : Counter
Field Status : current
Description : The count of no proxy error.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.6

Field Name : axFastHttpProxyStatHttpReqSucc
Field Type : Counter
Field Status : current
Description : The count of http requests which connected successfully.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.5

Field Name : axFastHttpProxyStatHttpReq
Field Type : Counter
Field Status : current
Description : The count of http requests.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.4

Field Name : axFastHttpProxyStatTotalProxyConns
Field Type : Counter
Field Status : current
Description : The total count of fast http proxy connections of current cpu.
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.3

Field Name : axFastHttpProxyStatCurrProxyConns
Field Type : Counter
Field Status : current
Description : The count of current fast http proxy connections
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.2

Field Name : axFastHttpProxyStatCpuIndex
Field Type : Integer32
Field Status : current
Description : The cpu index of fast http proxy STAT table
OID : 1.3.6.1.4.1.22610.2.4.3.6.18.1.1

Field Name : axConnReuseStatTotalMissedResponse
Field Type : INTEGER
Field Status : current
Description : Number of missed responses to HTTP requests.
OID : 1.3.6.1.4.1.22610.2.4.3.5.10

Field Name : axConnReuseStatTotalLongResponse
Field Type : INTEGER
Field Status : current
Description : Number of responses that took too long.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.5.9

Field Name : axConnReuseStatTotalDelayedUNBound
Field Type : INTEGER
Field Status : current
Description : Number of connections whose unbinding was delayed.
OID : 1.3.6.1.4.1.22610.2.4.3.5.8

Field Name : axConnReuseStatTable
Field Type : TABLE
Field Status : current
Description : The connection-reuse status table.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7

Field Name : axConnReuseStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The connection-reuse entry.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1

Field Name : axConnReuseStatTotalMissedRes
Field Type : Counter
Field Status : current
Description : Number of missed responses to HTTP requests.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.10

Field Name : axConnReuseStatTotalLongRes
Field Type : Counter
Field Status : current
Description : Number of responses that took too long.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.9

Field Name : axConnReuseStatTotalDelayedUNBind
Field Type : Counter
Field Status : current
Description : Number of connections whose unbinding was delayed.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.8

Field Name : axConnReuseStatTotalUNBind
Field Type : Counter
Field Status : current
Description : The count of unbound connection-reuse sessions
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.7

Field Name : axConnReuseStatTotalBind
Field Type : Counter
Field Status : current
Description : The count of bound connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.6

Field Name : axConnReuseStatTotalTerm
Field Type : Counter
Field Status : current
Description : The count of terminated connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.5

Field Name : axConnReuseStatTotalEst

A10-AX-MIB_axMgmt_oid_list

Field Type : Counter
Field Status : current
Description : The count of established connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.4

Field Name : axConnReuseStatActivePersist
Field Type : Counter
Field Status : current
Description : The count of active persistent connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.3

Field Name : axConnReuseStatOpenPersist
Field Type : Counter
Field Status : current
Description : The count of open persistent connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.2

Field Name : axConnReuseStatCpuIndex
Field Type : Integer32
Field Status : current
Description : Cpu Index to the connection-reuse STAT.
OID : 1.3.6.1.4.1.22610.2.4.3.5.7.1.1

Field Name : axConnReuseStatTotalUNBound
Field Type : INTEGER
Field Status : current
Description : The total count of unbound connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.6

Field Name : axConnReuseStatTotalBound
Field Type : INTEGER
Field Status : current
Description : The total count of bound connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.5

Field Name : axConnReuseStatTotalTerminated
Field Type : INTEGER
Field Status : current
Description : The total count of terminated connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.4

Field Name : axConnReuseStatTotalEstablished
Field Type : INTEGER
Field Status : current
Description : The total count of established connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.3

Field Name : axConnReuseStatTotalActivePersist
Field Type : INTEGER
Field Status : current
Description : The total count of active persistent connection-reuse sessions.
OID : 1.3.6.1.4.1.22610.2.4.3.5.2

Field Name : axConnReuseStatTotalOpenPersist
Field Type : INTEGER
Field Status : current
Description : The total count of open persistent connection-reuse sessions.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.5.1

Field Name : axVirtualServerNameStatTable

Field Type : TABLE

Field Status : current

Description : A table containing statistic information of virtual servers.

OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1

Field Name : axVirtualServerNameStatEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axVirtualServerNameStat Table

OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1

Field Name : axVirtualServerNameStatPeakConns

Field Type : Counter

Field Status : current

Description : The number of peak connections

OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.14

Field Name : axVirtualServerNameStatTotalSuccL7Reqs

Field Type : Counter64

Field Status : current

Description : The number of successful L7 requests if applicable

OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.13

Field Name : axVirtualServerNameStatTotalCurrL7Reqs

Field Type : Counter64

Field Status : current

Description : The number of current L7 requests if applicable

OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.12

Field Name : axVirtualServerNameStatTotalL7Reqs

Field Type : Counter64

Field Status : current

Description : The total number of L7 requests if applicable

OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.11

Field Name : axVirtualServerNameStatDisplayStatus

Field Type : EnumVal

Field Status : current

Description : The display status of this virtual server:

: Disabled(0), AllUp(1), FunctionalUp(2), PartialUp(3), Stopped(4).

OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.10

Field Name : axVirtualServerNameStatStatus

Field Type : EnumVal

Field Status : current

Description : The current virtual server status.

OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.9

Field Name : axVirtualServerNameStatCurConns

Field Type : Integer32

Field Status : current

Description : The current connections from client side.

OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.8

A10-AX-MIB_axMgmt_oid_list

Field Name : axVirtualServerNameStatTotConns
Field Type : Counter64
Field Status : current
Description : The total connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.7

Field Name : axVirtualServerNameStatBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.5

Field Name : axVirtualServerNameStatPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.4

Field Name : axVirtualServerNameStatBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.3

Field Name : axVirtualServerNameStatPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.2

Field Name : axVirtualServerStatDisplayName
Field Type : String
Field Status : current
Description : The name of this virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.5.1.1.1

Field Name : axVirtualServerPortStatTable
Field Type : TABLE
Field Status : current
Description : A table containing statistic information of virtual server service ports.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1

Field Name : axVirtualServerPortStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVirtualServerPortStat Table
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1

Field Name : axVirtualServerPortStatAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axVirtualServerPortStatAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.18

Field Name : axVirtualServerPortStatPeakConns
Field Type : Counter

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : The number of peak connections
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.17

Field Name : axVirtualServerPortStatTotalSuccL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of successful L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.16

Field Name : axVirtualServerPortStatTotalCurrL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of current L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.15

Field Name : axVirtualServerPortStatTotalL7Reqs
Field Type : Counter64
Field Status : current
Description : The total number of L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.14

Field Name : axVirtualServerStatPortDisplayStatus
Field Type : EnumVal
Field Status : current
Description : The display status of this virtual server port:
: Disabled(0), AllUp(1), FunctionalUp(2), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.13

Field Name : axVirtualServerPortStatCurConns
Field Type : Integer32
Field Status : current
Description : Current connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.12

Field Name : axVirtualServerPortStatTotConns
Field Type : Counter64
Field Status : current
Description : Total connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.11

Field Name : axVirtualServerPortStatBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.9

Field Name : axVirtualServerPortStatPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.8

Field Name : axVirtualServerPortStatBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.7

Field Name : axVirtualServerPortStatPktsIn

Field Type : Counter64

Field Status : current

Description : The number of packets received from client to server.

OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.6

Field Name : axVirtualServerStatPortStatus

Field Type : EnumVal

Field Status : current

Description : The status of this virtual server port.

OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.5

Field Name : axVirtualServerPortStatName

Field Type : String

Field Status : current

Description : The name of the virtual server

OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.4

Field Name : axVirtualServerStatPortNum

Field Type : Integer32

Field Status : current

Description : The service port number.

OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.3

Field Name : axVirtualServerStatPortType

Field Type : EnumVal

Field Status : current

Description : The port type of a virtual server port

OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.2

Field Name : axVirtualServerPortStatAddress

Field Type : String

Field Status : current

Description : The ip address of this virtual address.

OID : 1.3.6.1.4.1.22610.2.4.3.4.4.1.1.1

Field Name : axVirtualServerPortTable

Field Type : TABLE

Field Status : current

Description : A table containing information of virtual server port configuration.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1

Field Name : axVirtualServerPortEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axVirtualServerPort Table

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1

Field Name : axVirtualServerPortDiameterTemplate

Field Type : String

Field Status : current

Description : The Diameter template for diameter type only.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.25

Field Name : axVirtualServerPortAddressType

A10-AX-MIB_axMgmt_oid_list

Field Type : EnumVal
Field Status : current
Description : The type of axVirtualServerPortAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.24

Field Name : axVirtualServerPortDisplayStatus
Field Type : EnumVal
Field Status : current
Description : The display status of this virtual server port:
: Disabled(0), AllUp(1), FunctionalUp(2), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.23

Field Name : axVirtualServerPortUDPTemplate
Field Type : String
Field Status : current
Description : The UDP template for UDP port type only.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.22

Field Name : axVirtualServerPortSIPTemplate
Field Type : String
Field Status : current
Description : The SIP template for SIP port type only.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.21

Field Name : axVirtualServerPortSMTPTemplate
Field Type : String
Field Status : current
Description : The SMTP template for SMTP port type only.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.20

Field Name : axVirtualServerPortRTSPTemplate
Field Type : String
Field Status : current
Description : The RTSP template for RTSP port type only.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.19

Field Name : axVirtualServerPortServerSSLTemplate
Field Type : String
Field Status : current
Description : The Server-SSL template for HTTPS port type only.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.18

Field Name : axVirtualServerPortClientSSLTemplate
Field Type : String
Field Status : current
Description : The Client-SSL template for HTTPS/SSLProxy/SMTP port types.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.17

Field Name : axVirtualServerPortTCPProxyTemplate
Field Type : String
Field Status : current
Description : The TCP proxy template for HTTP/HTTPS/SSLProxy/SMTP port types.
OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.16

Field Name : axVirtualServerPortConnReuseTemplate
Field Type : String

A10-AX-MIB_axMgmt_oid_list

Field Status : current

Description : The connection reuse template for HTTP/HTTPS/FastHTTP port types.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.15

Field Name : axVirtualServerPortRamCacheTemplate

Field Type : String

Field Status : current

Description : The RAM cache template for HTTP/HTTPS port types.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.14

Field Name : axVirtualServerPortHTTPTemplate

Field Type : String

Field Status : current

Description : The HTTP template for HTTP/HTTPS/FastHTTP port types.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.13

Field Name : axVirtualServerPortTCPTemplate

Field Type : String

Field Status : current

Description : The TCP template for TPC/FastHTTP/RTSP/FTP/MMS/Others port types.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.12

Field Name : axVirtualServerPortPolicyTemplate

Field Type : String

Field Status : current

Description : The policy template for all port types except for Firewall.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.11

Field Name : axVirtualServerPortTemplate

Field Type : String

Field Status : current

Description : The virtual server port template for all port types except for Firewall.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.10

Field Name : axVirtualServerPortPersistTemplate

Field Type : String

Field Status : current

Description : The persistent template dependent on the axVirtualServerPortPersistTemplateType value.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.9

Field Name : axVirtualServerPortPersistTemplateType

Field Type : EnumVal

Field Status : current

Description : The persistent template type if applicable.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.8

Field Name : axVirtualServerPortHaGroupID

Field Type : INTEGER

Field Status : current

Description : The HA group ID assigned to the virtual service port.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.7

Field Name : axVirtualServerPortServiceGroup

Field Type : String

Field Status : current

Description : The service group is assigned to the virtual server port.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.6

Field Name : axVirtualServerPortEnabled

Field Type : EnumVal

Field Status : current

Description : The status of this virtual server port is enabled.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.5

Field Name : axVirtualServerPortAddress

Field Type : String

Field Status : current

Description : The ip address of this virtual server.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.4

Field Name : axVirtualServerPortNum

Field Type : Integer32

Field Status : current

Description : The virtual server port number.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.3

Field Name : axVirtualServerPortType

Field Type : EnumVal

Field Status : current

Description : The port type of a virtual server port.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.2

Field Name : axVirtualServerPortName

Field Type : String

Field Status : current

Description : The name of the virtual server.

OID : 1.3.6.1.4.1.22610.2.4.3.4.3.1.1.1

Field Name : axVirtualServerStatTable

Field Type : TABLE

Field Status : current

Description : A table containing statistic information of virtual servers.

OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1

Field Name : axVirtualServerStatEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axVirtualServerStat Table

OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1

Field Name : axVirtualServerStatAddressType

Field Type : EnumVal

Field Status : current

Description : The type of axVirtualServerStatAddress:

: unknown(0), ipv4(1), ipv6(2)...

OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.16

Field Name : axVirtualServerStatPeakConns

Field Type : Counter

Field Status : current

Description : The number of peak connections

OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.15

A10-AX-MIB_axMgmt_oid_list

Field Name : axVirtualServerStatTotalSuccL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of successful L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.14

Field Name : axVirtualServerStatTotalCurrL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of current L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.13

Field Name : axVirtualServerStatTotalL7Reqs
Field Type : Counter64
Field Status : current
Description : The total number of L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.12

Field Name : axVirtualServerStatDisplayStatus
Field Type : EnumVal
Field Status : current
Description : The display status of this virtual server:
: Disabled(0), AllUp(1), FunctionalUp(2), PartialUp(3), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.11

Field Name : axVirtualServerStatStatus
Field Type : EnumVal
Field Status : current
Description : The current virtual server status.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.10

Field Name : axVirtualServerStatCurConns
Field Type : Integer32
Field Status : current
Description : The current connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.9

Field Name : axVirtualServerStatTotConns
Field Type : Counter64
Field Status : current
Description : The total connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.8

Field Name : axVirtualServerStatBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.6

Field Name : axVirtualServerStatPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.5

Field Name : axVirtualServerStatBytesIn
Field Type : Counter64

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.4

Field Name : axVirtualServerStatPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.3

Field Name : axVirtualServerStatName
Field Type : String
Field Status : current
Description : The name of this virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.2

Field Name : axVirtualServerStatAddress
Field Type : String
Field Status : current
Description : The address of this virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.2.1.1.1

Field Name : axVirtualServerTable
Field Type : TABLE
Field Status : current
Description : A table containing information of virtual servers.
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2

Field Name : axVirtualServerCount
Field Type : INTEGER
Field Status : current
Description : The number of axVirtualServer entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.1

Field Name : axVirtualServerEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVirtualServer Table
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1

Field Name : axVirtualServerVrid
Field Type : INTEGER
Field Status : current
Description : The assigned vrid for the virtual server
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.7

Field Name : axVirtualServerAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axVirtualServerAddress:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.6

Field Name : axVirtualServerDisplayStatus
Field Type : EnumVal
Field Status : current
Description : The display status of this virtual server port:

A10-AX-MIB_axMgmt_oid_list

: Disabled(0), AllUp(1), FunctionalUp(2), PartialUp(3), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.5

Field Name : axVirtualServerHAGroup
Field Type : String
Field Status : current
Description : HA group name configured for the virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.4

Field Name : axVirtualServerEnabled
Field Type : EnumVal
Field Status : current
Description : Whether this virtual server is enabled.
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.3

Field Name : axVirtualServerAddress
Field Type : String
Field Status : current
Description : The ip address of this virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.2

Field Name : axVirtualServerName
Field Type : String
Field Status : current
Description : The name of this virtual server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.1.2.1.1

Field Name : axVirtualServerNamePortStatTable
Field Type : TABLE
Field Status : current
Description : A table containing statistic information of virtual server service ports.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1

Field Name : axVirtualServerNamePortStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVirtualServerNamePortStat Table
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1

Field Name : axVirtualServerNamePortStatPeakConns
Field Type : Counter
Field Status : current
Description : The number of peak connections
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.16

Field Name : axVirtualServerNamePortStatTotalSuccL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of successful L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.15

Field Name : axVirtualServerNamePortStatTotalCurrL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of current L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.14

A10-AX-MIB_axMgmt_oid_list

Field Name : axVirtualServerNamePortStatTotalL7Reqs
Field Type : Counter64
Field Status : current
Description : The total number of L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.13

Field Name : axVirtualServerNameStatPortDisplayStatus
Field Type : EnumVal
Field Status : current
Description : The display status of this virtual server port:
: Disabled(0), AllUp(1), FunctionalUp(2), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.12

Field Name : axVirtualServerNamePortStatCurConns
Field Type : Integer32
Field Status : current
Description : Current connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.11

Field Name : axVirtualServerNamePortStatTotConns
Field Type : Counter64
Field Status : current
Description : Total connections from client side.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.10

Field Name : axVirtualServerNamePortStatBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.8

Field Name : axVirtualServerNamePortStatPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.7

Field Name : axVirtualServerNamePortStatBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.6

Field Name : axVirtualServerNamePortStatPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.5

Field Name : axVirtualServerNameStatPortStatus
Field Type : EnumVal
Field Status : current
Description : The status of this virtual server port.
OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.4

Field Name : axVirtualServerNameStatPortNum
Field Type : Integer32

A10-AX-MIB_axMgmt_oid_list

Field Status : current

Description : The service port number.

OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.3

Field Name : axVirtualServerNameStatPortType

Field Type : EnumVal

Field Status : current

Description : The port type of a virtual server port

OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.2

Field Name : axVirtualServerNamePortStatName

Field Type : String

Field Status : current

Description : The name of the virtual server

OID : 1.3.6.1.4.1.22610.2.4.3.4.6.1.1.1

Field Name : axServiceGroupMemberTable

Field Type : TABLE

Field Status : current

Description : A table containing information of service group members.

OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1

Field Name : axServiceGroupMemberEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axServiceGroupMember Table

OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1

Field Name : axServerPortStatusInServiceGroupMember

Field Type : EnumVal

Field Status : current

Description : The server port status of the service group member:
: Disabled(0), Up(1), Down(2).

OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1.6

Field Name : axServerPortPriorityInServiceGroupMember

Field Type : Integer32

Field Status : current

Description : The priority value of a service group member.

OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1.5

Field Name : axServerPortNumInServiceGroupMember

Field Type : Integer32

Field Status : current

Description : The port number of this member.

OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1.4

Field Name : axServerNameInServiceGroupMember

Field Type : String

Field Status : current

Description : The server name in the service group member.

OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1.3

Field Name : axServiceGroupMemberAddrType

Field Type : EnumVal

Field Status : current

Description : The type of service group

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1.2

Field Name : axServiceGroupNameInMember
Field Type : String
Field Status : current
Description : The name of axServiceGroup.
OID : 1.3.6.1.4.1.22610.2.4.3.3.3.1.1.1

Field Name : axServiceGroupStatTable
Field Type : TABLE
Field Status : current
Description : A table containing statistic information of service groups.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1

Field Name : axServiceGroupStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServiceGroupStat Table
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1

Field Name : axServiceGroupStatPeakConns
Field Type : Counter
Field Status : current
Description : The number of peak connections
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.13

Field Name : axServiceGroupStatTotalSuccL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of successful L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.12

Field Name : axServiceGroupStatTotalCurrL7Reqs
Field Type : Counter64
Field Status : current
Description : The number of current L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.11

Field Name : axServiceGroupStatTotalL7Reqs
Field Type : Counter64
Field Status : current
Description : The total number of L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.10

Field Name : axServiceGroupStatDisplayStatus
Field Type : EnumVal
Field Status : current
Description : The display status of the service group:
: AllUp(1), FunctionalUp(2), PartialUp(3), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.9

Field Name : axServiceGroupStatCurConns
Field Type : Integer32
Field Status : current
Description : The current connections from server side.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.7

A10-AX-MIB_axMgmt_oid_list

Field Name : axServiceGroupStatTotConns
Field Type : Counter64
Field Status : current
Description : The total connections from server side.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.6

Field Name : axServiceGroupStatBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.5

Field Name : axServiceGroupStatPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.4

Field Name : axServiceGroupStatBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.3

Field Name : axServiceGroupStatPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.2

Field Name : axServiceGroupStatName
Field Type : String
Field Status : current
Description : The service group name.
OID : 1.3.6.1.4.1.22610.2.4.3.3.2.1.1.1

Field Name : axServiceGroupTable
Field Type : TABLE
Field Status : current
Description : A table containing information of service groups.
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.2

Field Name : axServiceGroupCount
Field Type : Integer32
Field Status : current
Description : The number of axServiceGroup entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.1

Field Name : axServiceGroupEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServiceGroup Table
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.2.1

Field Name : axServiceGroupDisplayStatus
Field Type : EnumVal
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The display status of the service group:
: AllUp(1), FunctionalUp(2), PartialUp(3), Stopped(4).
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.2.1.4

Field Name : axServiceGroupLbAlgorithm
Field Type : EnumVal
Field Status : current
Description : The load balance method for the service group
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.2.1.3

Field Name : axServiceGroupType
Field Type : EnumVal
Field Status : current
Description : The type of the service group.
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.2.1.2

Field Name : axServiceGroupName
Field Type : String
Field Status : current
Description : The service group name.
OID : 1.3.6.1.4.1.22610.2.4.3.3.1.2.1.1

Field Name : axServiceGroupMemberStatTable
Field Type : TABLE
Field Status : current
Description : A table containing statistic information of service group members.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1

Field Name : axServiceGroupMemberStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServiceGroupMemberStat Table
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1

Field Name : axServiceGroupMemberStatPeakConns
Field Type : Counter
Field Status : current
Description : The service group member peak connections.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.17

Field Name : axServiceGroupMemberStatResponseTime
Field Type : Integer32
Field Status : current
Description : The service group member response time in millisecond.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.16

Field Name : axServiceGroupMemberStatTotalSuccl7Reqs
Field Type : Counter64
Field Status : current
Description : The number of successful L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.15

Field Name : axServiceGroupMemberStatTotalCurrl7Reqs
Field Type : Counter64
Field Status : current
Description : The number of current L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.14

A10-AX-MIB_axMgmt_oid_list

Field Name : axServiceGroupMemberStatTotalL7Reqs
Field Type : Counter64
Field Status : current
Description : The total number of L7 requests if applicable
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.13

Field Name : axServerPortStatusInServiceGroupMemberStat
Field Type : EnumVal
Field Status : current
Description : The server port status of the service group member:
: Disabled(0), Up(1), Down(2)
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.12

Field Name : axServiceGroupMemberStatCurConns
Field Type : Integer32
Field Status : current
Description : The current connections from server side.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.11

Field Name : axServiceGroupMemberStatTotConns
Field Type : Counter64
Field Status : current
Description : The total connections from server side.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.10

Field Name : axServiceGroupMemberStatBytesOut
Field Type : Counter64
Field Status : current
Description : The number of bytes sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.8

Field Name : axServiceGroupMemberStatPktsOut
Field Type : Counter64
Field Status : current
Description : The number of packets sent from server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.7

Field Name : axServiceGroupMemberStatBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.6

Field Name : axServiceGroupMemberStatPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.5

Field Name : axServerPortNumInServiceGroupMemberStat
Field Type : Integer32
Field Status : current
Description : The port number of this member.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.4

Field Name : axServerNameInServiceGroupMemberStat

A10-AX-MIB_axMgmt_oid_list

Field Type : String
Field Status : current
Description : The ip address of this member in the service group.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.3

Field Name : axServiceGroupMemberStatAddrType
Field Type : EnumVal
Field Status : current
Description : The type of service group
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.2

Field Name : axServiceGroupMemberStatName
Field Type : String
Field Status : current
Description : The service group name.
OID : 1.3.6.1.4.1.22610.2.4.3.3.4.1.1.1

Field Name : axServerPortTable
Field Type : TABLE
Field Status : current
Description : A table has information of real servers.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1

Field Name : axServerPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServer Port Table
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1

Field Name : axServerPortAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axServerAddressInPort:
: unknown(0), ipv4(1), ipv6(2)...
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.10

Field Name : axServerPortMonitorState
Field Type : EnumVal
Field Status : current
Description : The server port status is in
: 0: Disabled (administrative disabled)
: 1: Up (administrative enabled)
: 2: Down (administrative enabled)
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.9

Field Name : axServerPortWeight
Field Type : Integer32
Field Status : current
Description : The weight of the server port.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.8

Field Name : axServerPortConnLimit
Field Type : Integer32
Field Status : current
Description : The connection limit of the server port.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.7

A10-AX-MIB_axMgmt_oid_list

Field Name : axServerPortHealthMonitor
Field Type : String
Field Status : current
Description : The health monitor name assigned to the server
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.6

Field Name : axServerPortEnabledState
Field Type : EnumVal
Field Status : current
Description : The monitor state for this node address.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.5

Field Name : axServerAddressInPort
Field Type : String
Field Status : current
Description : The IP address or host name of the server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.4

Field Name : axServerPortNum
Field Type : Integer32
Field Status : current
Description : The port number of the server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.3

Field Name : axServerPortType
Field Type : EnumVal
Field Status : current
Description : The port type of the server port.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.2

Field Name : axServerNameInPort
Field Type : String
Field Status : current
Description : The server name.
OID : 1.3.6.1.4.1.22610.2.4.3.2.3.1.1.1

Field Name : axServerStatTable
Field Type : TABLE
Field Status : current
Description : A table containing statistic information of node addresses.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2

Field Name : axServerStatCount
Field Type : INTEGER
Field Status : current
Description : The total count of axServerStat entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.1

Field Name : axServerStatEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServerStat Table
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1

Field Name : axServerStatAddressType
Field Type : EnumVal
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The type of axServerStatAddress:

: unknown(0), ipv4(1), ipv6(2)...

OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.15

Field Name : axServerStatServerPeakConns

Field Type : Counter

Field Status : current

Description : The number of the peak connections

OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.14

Field Name : axServerStatServerTotalSuccL7Reqs

Field Type : Counter64

Field Status : current

Description : The number of successful L7 requests if applicable

OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.13

Field Name : axServerStatServerTotalCurrL7Reqs

Field Type : Counter64

Field Status : current

Description : The number of current L7 requests if applicable

OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.12

Field Name : axServerStatServerTotalL7Reqs

Field Type : Counter64

Field Status : current

Description : The total number of L7 requests if applicable

OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.11

Field Name : axServerStatServerStatus

Field Type : EnumVal

Field Status : current

Description : The server status is in

: 0: Disabled (administrative disabled)

: 1: Up (administrative enabled)

: 2: Down (administrative enabled)

OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.10

Field Name : axServerStatServerCurConns

Field Type : Integer32

Field Status : current

Description : The current connections from server side.

OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.8

Field Name : axServerStatServerTotalConns

Field Type : Counter64

Field Status : current

Description : The total connections from server side.

OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.7

Field Name : axServerStatServerBytesOut

Field Type : Counter64

Field Status : current

Description : The number of bytes sent from server to client.

OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.6

Field Name : axServerStatServerPktsOut

Field Type : Counter64

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : The number of packets sent for server to client.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.5

Field Name : axServerStatServerBytesIn
Field Type : Counter64
Field Status : current
Description : The number of bytes received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.4

Field Name : axServerStatServerPktsIn
Field Type : Counter64
Field Status : current
Description : The number of packets received from client to server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.3

Field Name : axServerStatName
Field Type : String
Field Status : current
Description : The server name.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.2

Field Name : axServerStatAddress
Field Type : String
Field Status : current
Description : The ip address of this server.
OID : 1.3.6.1.4.1.22610.2.4.3.2.2.2.1.1

Field Name : axServerTable
Field Type : TABLE
Field Status : current
Description : A table has information of the servers.
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2

Field Name : axServerCount
Field Type : INTEGER
Field Status : current
Description : The total count of axServer entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.1

Field Name : axServerEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axServer Table
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1

Field Name : axServerWeight
Field Type : INTEGER
Field Status : current
Description : The server weight
OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.7

Field Name : axServerAddressType
Field Type : EnumVal
Field Status : current
Description : The type of axServerAddress:
: unknown(0), ipv4(1), ipv6(2)...

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.6

Field Name : axServerMonitorState

Field Type : EnumVal

Field Status : current

Description : The server monitor status is in

: 0: Disabled (administrative disabled)

: 1: Up (administrative enabled)

: 2: Down (administrative enabled)

OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.5

Field Name : axServerHealthMonitor

Field Type : String

Field Status : current

Description : The health monitor name assigned to the server

OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.4

Field Name : axServerEnabledState

Field Type : EnumVal

Field Status : current

Description : The monitor state for this node address.

OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.3

Field Name : axServerAddress

Field Type : String

Field Status : current

Description : The IP address or host name of the server.

OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.2

Field Name : axServerName

Field Type : String

Field Status : current

Description : The name of the server.

OID : 1.3.6.1.4.1.22610.2.4.3.2.1.2.1.1

Field Name : axServerPortStatTable

Field Type : TABLE

Field Status : current

Description : A table containing statistic information of node addresses.

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1

Field Name : axServerPortStatEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axServerStat Table

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1

Field Name : axServerPortStatAddressType

Field Type : EnumVal

Field Status : current

Description : The type of axServerStatAddrInPort:

: unknown(0), ipv4(1), ipv6(2)...

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.17

Field Name : axServerPortStatPeakConns

Field Type : Counter

Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The number of peak connections

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.16

Field Name : axServerPortStatTotalSuccL7Reqs

Field Type : Counter64

Field Status : current

Description : The number of successful L7 requests if applicable

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.15

Field Name : axServerPortStatTotalCurrL7Reqs

Field Type : Counter64

Field Status : current

Description : The number of current L7 requests if applicable

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.14

Field Name : axServerPortStatTotalL7Reqs

Field Type : Counter64

Field Status : current

Description : The total number of L7 requests if applicable

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.13

Field Name : axServerPortStatStatus

Field Type : EnumVal

Field Status : current

Description : The server port status is in

: 0: Disabled (administrative disabled)

: 1: Up (administrative enabled)

: 2: Down (administrative enabled)

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.12

Field Name : axServerPortStatCurConns

Field Type : Integer32

Field Status : current

Description : The current connections from server side.

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.10

Field Name : axServerPortStatTotalConns

Field Type : Counter64

Field Status : current

Description : The maximum connections from server side.

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.9

Field Name : axServerPortStatBytesOut

Field Type : Counter64

Field Status : current

Description : The number of bytes sent from server to client.

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.8

Field Name : axServerPortStatPktsOut

Field Type : Counter64

Field Status : current

Description : The number of packets sent from server to client.

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.7

Field Name : axServerPortStatBytesIn

Field Type : Counter64

Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The number of bytes received from client to server.

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.6

Field Name : axServerPortStatPktsIn

Field Type : Counter64

Field Status : current

Description : The number of packets received from client to server.

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.5

Field Name : axServerStatNameInPort

Field Type : String

Field Status : current

Description : The ip address of this server.

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.4

Field Name : axServerStatPortNum

Field Type : Integer32

Field Status : current

Description : The server port number.

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.3

Field Name : axServerStatPortType

Field Type : EnumVal

Field Status : current

Description : The server port type.

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.2

Field Name : axServerStatAddrInPort

Field Type : String

Field Status : current

Description : The ip address of this server.

OID : 1.3.6.1.4.1.22610.2.4.3.2.4.1.1.1

Field Name : axAppGlobalBufferCurrentUsage

Field Type : INTEGER

Field Status : current

Description : Application buffer current usage.

OID : 1.3.6.1.4.1.22610.2.4.3.1.3.2

Field Name : axAppGlobalBufferConfigLimit

Field Type : INTEGER

Field Status : current

Description : Application buffer configured limit.

OID : 1.3.6.1.4.1.22610.2.4.3.1.3.1

Field Name : axGlobalAggregateCps

Field Type : Counter64

Field Status : current

Description : Global aggregate connection per second.

OID : 1.3.6.1.4.1.22610.2.4.3.1.2.24

Field Name : axGlobalFWCps

Field Type : Counter64

Field Status : current

Description : Firewall connection per second.

OID : 1.3.6.1.4.1.22610.2.4.3.1.2.23

A10-AX-MIB_axMgmt_oid_list

Field Name : axGlobalL7ConnectionCps
Field Type : Counter64
Field Status : current
Description : Layer 7 connections per second.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.22

Field Name : axGlobalL4ConnectionCps
Field Type : Counter64
Field Status : current
Description : Layer 4 connections per second.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.21

Field Name : axGlobalConcurrentConnection
Field Type : Counter64
Field Status : current
Description : Total layer 4 and layer 7 established connections.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.20

Field Name : axGlobalThroughputPerSecond
Field Type : Counter64
Field Status : current
Description : The per second throughput across all Ethernet ports.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.19

Field Name : axGlobalTotalSslCps
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL CPS across all the partitions.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.18

Field Name : axGlobalTotalL7Cps
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L7 CPS across all the partitions.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.17

Field Name : axGlobalTotalL4Cps
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L4 CPS across all the partitions.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.16

Field Name : axGlobalTotalSslThroughput
Field Type : Counter64
Field Status : current
Description : Total SSL throughput across all the partitions.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.15

Field Name : axGlobalTotalBandWidth
Field Type : CounterBasedGauge64
Field Status : current
Description : Total bandwidth across all the partitions.
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.14

Field Name : axGlobalTotalThroughput
Field Type : Counter64
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : Total throughput of all the interfaces.

OID : 1.3.6.1.4.1.22610.2.4.3.1.2.13

Field Name : axGlobalTotalL4SessionInteger

Field Type : INTEGER

Field Status : current

Description : Total number of L4 sessions.

OID : 1.3.6.1.4.1.22610.2.4.3.1.2.12

Field Name : axAppGlobalTotalCurrentConnectionsInteger

Field Type : INTEGER

Field Status : current

Description : Total current connections

OID : 1.3.6.1.4.1.22610.2.4.3.1.2.11

Field Name : axGlobalTotalL4Session

Field Type : CounterBasedGauge64

Field Status : current

Description : Total number of L4 sessions.

OID : 1.3.6.1.4.1.22610.2.4.3.1.2.10

Field Name : axGlobalTotalAppPacketDrop

Field Type : Counter64

Field Status : current

Description : Total number of accumulative buffer drops.

OID : 1.3.6.1.4.1.22610.2.4.3.1.2.9

Field Name : axGlobalAppPacketDrop

Field Type : INTEGER

Field Status : current

Description : Total number of buffer drops in the last 10 seconds.

OID : 1.3.6.1.4.1.22610.2.4.3.1.2.8

Field Name : axAppGlobalTotalL7Requests

Field Type : Counter64

Field Status : current

Description : Total L7 requests

OID : 1.3.6.1.4.1.22610.2.4.3.1.2.7

Field Name : axAppGlobalTotalSSLConnections

Field Type : CounterBasedGauge64

Field Status : current

Description : Total SSL connections

OID : 1.3.6.1.4.1.22610.2.4.3.1.2.6

Field Name : axAppGlobalTotalNewIPNatConnections

Field Type : CounterBasedGauge64

Field Status : current

Description : Total new IP-NAT connections

OID : 1.3.6.1.4.1.22610.2.4.3.1.2.5

Field Name : axAppGlobalTotalNewL7Connections

Field Type : Counter64

Field Status : current

Description : Total new L7 connections

OID : 1.3.6.1.4.1.22610.2.4.3.1.2.4

A10-AX-MIB_axMgmt_oid_list

Field Name : axAppGlobalTotalNewL4Connections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total new L4 connections
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.3

Field Name : axAppGlobalTotalNewConnections
Field Type : Counter64
Field Status : current
Description : Total new connections
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.2

Field Name : axAppGlobalTotalCurrentConnections
Field Type : Counter64
Field Status : current
Description : Total current connections
OID : 1.3.6.1.4.1.22610.2.4.3.1.2.1

Field Name : axAppGlobalResourceUsageTable
Field Type : TABLE
Field Status : current
Description : A table has information of the resource usages,
: it should contains the results as the CLI command,
: 'show resouce-usage'
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2

Field Name : axAppGlobalSystemResourceUsageTable
Field Type : TABLE
Field Status : current
Description : A table has information of the system resource usages,
: it should contains the results as the CLI command,
: 'show slb resource-usage'
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1

Field Name : axAppGlobalSystemResourceUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axAppGlobalSystemResourceUsage Table
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1

Field Name : axAppGlobalAllowedMaxValue
Field Type : INTEGER
Field Status : current
Description : The maximum value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1.6

Field Name : axAppGlobalAllowedMinValue
Field Type : INTEGER
Field Status : current
Description : The minimum value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1.5

Field Name : axAppGlobalAllowedDefaultValue
Field Type : INTEGER
Field Status : current
Description : The default value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1.4

A10-AX-MIB_axMgmt_oid_list

Field Name : axAppGlobalAllowedCurrentValue
Field Type : INTEGER
Field Status : current
Description : The current value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1.3

Field Name : axAppGlobalSystemResourceName
Field Type : String
Field Status : current
Description : The system resource name.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1.2

Field Name : axAppGlobalSystemResourceIndex
Field Type : INTEGER
Field Status : current
Description : The system resource usage table index.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.1.1.1

Field Name : axAppGlobalResourceUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axAppGlobalResourceUsage Table
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1

Field Name : axAppGlobalResourcePeak
Field Type : INTEGER
Field Status : current
Description : The peak utilization of the resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.11

Field Name : axAppGlobalResourceAverage
Field Type : INTEGER
Field Status : current
Description : The average of the resource usage.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.10

Field Name : axAppGlobalResourceThresholdExceeded
Field Type : INTEGER
Field Status : current
Description : The number of threshold exceeded for the resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.9

Field Name : axAppGlobalResourceMaxExceeded
Field Type : INTEGER
Field Status : current
Description : The number of maximum exceeded for the resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.8

Field Name : axAppGlobalResourceUtilization
Field Type : INTEGER
Field Status : current
Description : The utilization percentage of the resource usage.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.7

Field Name : axAppGlobalResourceAllowedMaxValue
Field Type : INTEGER

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : The maximum value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.6

Field Name : axAppGlobalResourceAllowedMinValue
Field Type : INTEGER
Field Status : current
Description : The minimum value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.5

Field Name : axAppGlobalResourceAllowedCurrentValue
Field Type : INTEGER
Field Status : current
Description : The current value for the allowed system resource.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.3

Field Name : axAppGlobalResourceName
Field Type : String
Field Status : current
Description : The resource name.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.2

Field Name : axAppGlobalResourceIndex
Field Type : INTEGER
Field Status : current
Description : The resource usage table index.
OID : 1.3.6.1.4.1.22610.2.4.3.1.1.2.1.1

Field Name : axL3vGlobalStatsTable
Field Type : TABLE
Field Status : current
Description : The global statistics on a l3v partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1

Field Name : axL3vGlobalStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axL3vGlobalStatsTable
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1

Field Name : axL3vGlobalStatsL7ConnectionCps
Field Type : Counter64
Field Status : current
Description : Layer 7 connection per second in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.12

Field Name : axL3vGlobalStatsL4ConnectionCps
Field Type : Counter64
Field Status : current
Description : Layer 4 connection per second in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.11

Field Name : axL3vGlobalStatsConcurrentConnections
Field Type : Counter64
Field Status : current
Description : Total layer 4 and layer 7 established connections in a L3V Partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.10

A10-AX-MIB_axMgmt_oid_list

Field Name : axL3vGlobalStatsTotalL4Sessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Total layer 4 sessions in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.9

Field Name : axL3vGlobalStatsTotalL7Requests
Field Type : Counter64
Field Status : current
Description : Total layer 7 requests in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.8

Field Name : axL3vGlobalStatsTotalSslConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : The SSL connections per second in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.7

Field Name : axL3vGlobalStatsTotalNewL7Connections
Field Type : Counter64
Field Status : current
Description : Total new layer 7 connections in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.6

Field Name : axL3vGlobalStatsTotalNewL4Connections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total new layer 4 connections in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.5

Field Name : axL3vGlobalStatsTotalNewConnections
Field Type : Counter64
Field Status : current
Description : Total new connections in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.4

Field Name : axL3vGlobalStatsTotalCurrentConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total current connections in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.3

Field Name : axL3vGlobalStatsTotalThroughput
Field Type : CounterBasedGauge64
Field Status : current
Description : Total throughput of all the interfaces in a L3V partition.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.2

Field Name : axL3vGlobalStatsPartitionName
Field Type : String
Field Status : current
Description : The L3V partition name.
OID : 1.3.6.1.4.1.22610.2.4.3.1.4.1.1.1

Field Name : axFwDataSessionFree
Field Type : Counter64

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : The foward data session free.
OID : 1.3.6.1.4.1.22610.2.4.3.26.2

Field Name : axFwDataSessionUsed
Field Type : Counter64
Field Status : current
Description : The foward data session used.
OID : 1.3.6.1.4.1.22610.2.4.3.26.1

Field Name : axLogMonitorPri
Field Type : EnumVal
Field Status : current
Description : The logging monitor priority, logging messages which levels above
: that value must be output to snmp trap host.
OID : 1.3.6.1.4.1.22610.2.4.2.11

Field Name : axLogSyslogPort
Field Type : Integer32
Field Status : current
Description : The logging syslog host port.
OID : 1.3.6.1.4.1.22610.2.4.2.10

Field Name : axLogSyslogHostTable
Field Type : TABLE
Field Status : current
Description : The syslog host table.
OID : 1.3.6.1.4.1.22610.2.4.2.9

Field Name : axLogSyslogHostEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The syslog host entry
OID : 1.3.6.1.4.1.22610.2.4.2.9.1

Field Name : axLogSyslogHost
Field Type : String
Field Status : current
Description : The syslog host IP address or DNS name.
OID : 1.3.6.1.4.1.22610.2.4.2.9.1.2

Field Name : axLogSyslogHostIndex
Field Type : Integer32
Field Status : current
Description : The index of the syslog host list.
OID : 1.3.6.1.4.1.22610.2.4.2.9.1.1

Field Name : axLogSyslogPri
Field Type : EnumVal
Field Status : current
Description : The logging syslog priority, logging messages which levels above
: that value must be output to syslog host.
OID : 1.3.6.1.4.1.22610.2.4.2.8

Field Name : axLogEmailAddr
Field Type : String
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The email address that receive the logging messages.

OID : 1.3.6.1.4.1.22610.2.4.2.5

Field Name : axLogEmailPri

Field Type : EnumVal

Field Status : current

Description : The logging email priority, logging messages which levels above
: that value must be output to email address.

OID : 1.3.6.1.4.1.22610.2.4.2.4

Field Name : axLogConsolePri

Field Type : EnumVal

Field Status : current

Description : The logging console priority, logging messages which levels above
: that value must be output to console.

OID : 1.3.6.1.4.1.22610.2.4.2.3

Field Name : axLogBufferPri

Field Type : EnumVal

Field Status : current

Description : The logging buffer priority, logging messages which levels above
: that value must be output to internal database.

OID : 1.3.6.1.4.1.22610.2.4.2.2

Field Name : axLogBufferSize

Field Type : Integer32

Field Status : current

Description : The logging database size.

OID : 1.3.6.1.4.1.22610.2.4.2.1

Field Name : axSysVendorModelVersion

Field Type : String

Field Status : current

Description : The system vendor, model and version.

OID : 1.3.6.1.4.1.22610.2.4.1.6.5

Field Name : axSysAFlexEngineVersion

Field Type : String

Field Status : current

Description : The system aFlex engine version.

OID : 1.3.6.1.4.1.22610.2.4.1.6.4

Field Name : axSysFirmwareVersion

Field Type : String

Field Status : current

Description : The system firmware version.

OID : 1.3.6.1.4.1.22610.2.4.1.6.3

Field Name : axSysSerialNumber

Field Type : String

Field Status : current

Description : The system serial number.

OID : 1.3.6.1.4.1.22610.2.4.1.6.2

Field Name : axSysStartupMode

Field Type : EnumVal

Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The startup mode.

OID : 1.3.6.1.4.1.22610.2.4.1.6.1

Field Name : axSysPowerSupplyStatusTable

Field Type : TABLE

Field Status : current

Description : The table contains power supply status.

OID : 1.3.6.1.4.1.22610.2.4.1.5.12

Field Name : axPowerSupplyVoltageTable

Field Type : TABLE

Field Status : current

Description : A table contains the system power supply voltage status.

OID : 1.3.6.1.4.1.22610.2.4.1.5.11

Field Name : axPowerSupplyVoltageEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axPowerSupplyVoltageTable

OID : 1.3.6.1.4.1.22610.2.4.1.5.11.1

Field Name : axPowerSupplyVoltageValue

Field Type : INTEGER

Field Status : current

Description : The value of the power supply's voltage.

: This is only supported for the platform where the sensor data is available.

OID : 1.3.6.1.4.1.22610.2.4.1.5.11.1.4

Field Name : axPowerSupplyVoltageDescription

Field Type : String

Field Status : current

Description : The description of the system power supply voltage.

OID : 1.3.6.1.4.1.22610.2.4.1.5.11.1.3

Field Name : axPowerSupplyVoltageStatus

Field Type : EnumVal

Field Status : current

Description : The status of the indexed system power supply voltage.

: This is only supported for the platform where the sensor data is available.

OID : 1.3.6.1.4.1.22610.2.4.1.5.11.1.2

Field Name : axPowerSupplyVoltageIndex

Field Type : INTEGER

Field Status : current

Description : The table index.

OID : 1.3.6.1.4.1.22610.2.4.1.5.11.1.1

Field Name : axPowerSupplyVoltageTotal

Field Type : INTEGER

Field Status : current

Description : The total number of axPowerSupplyVoltage entries.

OID : 1.3.6.1.4.1.22610.2.4.1.5.10

Field Name : axSysFanStatusTable

Field Type : TABLE

Field Status : current

Description : The table contains system fan status

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.1.5.9

Field Name : axSysFanStatusEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axSysFanStatusTable
OID : 1.3.6.1.4.1.22610.2.4.1.5.9.1

Field Name : axFanSpeed
Field Type : Integer32
Field Status : current
Description : The fan speed.
OID : 1.3.6.1.4.1.22610.2.4.1.5.9.1.4

Field Name : axFanStatus
Field Type : EnumVal
Field Status : current
Description : Fan status:
: 0: Failed, 4: OK-fixed/high, 5: OK-low/med, 6: OK-med/med, 7: OK-med/high,
: -2: not ready, -1: unknown.
OID : 1.3.6.1.4.1.22610.2.4.1.5.9.1.3

Field Name : axFanName
Field Type : String
Field Status : current
Description : The system fan name.
OID : 1.3.6.1.4.1.22610.2.4.1.5.9.1.2

Field Name : axFanIndex
Field Type : Integer32
Field Status : current
Description : The system fan index.
OID : 1.3.6.1.4.1.22610.2.4.1.5.9.1.1

Field Name : axSysHwPhySystemTempStatus
Field Type : EnumVal
Field Status : current
Description : The system temperature status range
OID : 1.3.6.1.4.1.22610.2.4.1.5.5

Field Name : axSysHwPhySystemTemp
Field Type : Integer32
Field Status : current
Description : The physical system temperature in Celsius.
OID : 1.3.6.1.4.1.22610.2.4.1.5.1

Field Name : axSysPowerSupplyStatusEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axSysPowerSupplyStatusTable
OID : 1.3.6.1.4.1.22610.2.4.1.5.12.1

Field Name : axPowerSupplyCurrentValue
Field Type : INTEGER
Field Status : current
Description : The value of the power supply's current.
OID : 1.3.6.1.4.1.22610.2.4.1.5.12.1.5

A10-AX-MIB_axMgmt_oid_list

Field Name : axPowerSupplyVoltValue
Field Type : INTEGER
Field Status : current
Description : The value of the power supply's voltage.
OID : 1.3.6.1.4.1.22610.2.4.1.5.12.1.4

Field Name : axPowerSupplyStatus
Field Type : EnumVal
Field Status : current
Description : The power supply status.
OID : 1.3.6.1.4.1.22610.2.4.1.5.12.1.3

Field Name : axPowerSupplyName
Field Type : String
Field Status : current
Description : The pwer supply name.
OID : 1.3.6.1.4.1.22610.2.4.1.5.12.1.2

Field Name : axPowerSupplyIndex
Field Type : Integer32
Field Status : current
Description : The system power supply index.
OID : 1.3.6.1.4.1.22610.2.4.1.5.12.1.1

Field Name : axSysDiskFreeSpace
Field Type : Integer32
Field Status : current
Description : The free space of the disk in MB.
OID : 1.3.6.1.4.1.22610.2.4.1.4.2

Field Name : axSysDiskTotalSpace
Field Type : Integer32
Field Status : current
Description : The total space of the disk in MB.
OID : 1.3.6.1.4.1.22610.2.4.1.4.1

Field Name : axSysCpuUsagePerPartitionTable
Field Type : TABLE
Field Status : current
Description : The cpu usage per partition information table.
OID : 1.3.6.1.4.1.22610.2.4.1.3.7

Field Name : axSysCpuUsageTable
Field Type : TABLE
Field Status : current
Description : The cpu usage information table.
OID : 1.3.6.1.4.1.22610.2.4.1.3.6

Field Name : axSysCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The CPU Usage entry
OID : 1.3.6.1.4.1.22610.2.4.1.3.6.1

Field Name : axSysCpuUsageCtrlCpuFlag
Field Type : Integer32

A10-AX-MIB_axMgmt_oid_list

Field Status : current

Description : The control CPU flag: 1 - control CPU, 0 - data CPU.

OID : 1.3.6.1.4.1.22610.2.4.1.3.6.1.4

Field Name : axSysCpuUsageValueAtPeriod

Field Type : Integer32

Field Status : current

Description : The CPU usage value at given period, 1-sec, 5-sec, 10-sec, 30-sec, and 60-sec.

OID : 1.3.6.1.4.1.22610.2.4.1.3.6.1.3

Field Name : axSysCpuUsagePeriodIndex

Field Type : Integer32

Field Status : current

Description : The CPU usage sampling period:

: 1: 1-second sampling,

: 2: 5-second sampling,

: 3: 10-second sampling,

: 4: 30-second sampling,

: 5: 60-second sampling.

OID : 1.3.6.1.4.1.22610.2.4.1.3.6.1.2

Field Name : axSysCpuIndexInUsage

Field Type : Integer32

Field Status : current

Description : The index of the CPU.

OID : 1.3.6.1.4.1.22610.2.4.1.3.6.1.1

Field Name : axSysAverageDataCpuUsage

Field Type : Integer32

Field Status : current

Description : The average data CPU usage in last 5 seconds.

OID : 1.3.6.1.4.1.22610.2.4.1.3.5

Field Name : axSysAverageControlCpuUsage

Field Type : Integer32

Field Status : current

Description : The average control CPU usage in last 5 seconds.

OID : 1.3.6.1.4.1.22610.2.4.1.3.4

Field Name : axSysAverageCpuUsage

Field Type : Integer32

Field Status : current

Description : The average CPU usage in last 5 seconds.

OID : 1.3.6.1.4.1.22610.2.4.1.3.3

Field Name : axSysCpuTable

Field Type : TABLE

Field Status : current

Description : The cpu information table.

OID : 1.3.6.1.4.1.22610.2.4.1.3.2

Field Name : axSysCpuEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The cpu entry

OID : 1.3.6.1.4.1.22610.2.4.1.3.2.1

A10-AX-MIB_axMgmt_oid_list

Field Name : axSysCpuCtrlCpuFlag
Field Type : Integer32
Field Status : current
Description : The control CPU flag: 1 - control CPU, 0 - data CPU.
OID : 1.3.6.1.4.1.22610.2.4.1.3.2.1.4

Field Name : axSysCpuUsageValue
Field Type : Integer32
Field Status : current
Description : The CPU usage value.
OID : 1.3.6.1.4.1.22610.2.4.1.3.2.1.3

Field Name : axSysCpuUsage
Field Type : String
Field Status : current
Description : The CPU Usage.
OID : 1.3.6.1.4.1.22610.2.4.1.3.2.1.2

Field Name : axSysCpuIndex
Field Type : Integer32
Field Status : current
Description : The index of the CPU.
OID : 1.3.6.1.4.1.22610.2.4.1.3.2.1.1

Field Name : axSysCpuNumber
Field Type : Integer32
Field Status : current
Description : The cpu number in a10System
OID : 1.3.6.1.4.1.22610.2.4.1.3.1

Field Name : axSysCpuUsagePerPartitionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The CPU Usage per partition entry
OID : 1.3.6.1.4.1.22610.2.4.1.3.7.1

Field Name : axSysCpuUsagePerPartitionCtrlCpuFlag
Field Type : Integer32
Field Status : current
Description : The control CPU flag: 1 - control CPU, 0 - data CPU.
OID : 1.3.6.1.4.1.22610.2.4.1.3.7.1.5

Field Name : axSysCpuUsagePerPartitionValueAtPeriod
Field Type : Integer32
Field Status : current
Description : The CPU usage per partition value at given period, 1-sec, 5-sec, 10-sec, 30-sec, and 60-sec.
OID : 1.3.6.1.4.1.22610.2.4.1.3.7.1.4

Field Name : axSysCpuUsagePartitionName
Field Type : String
Field Status : current
Description : The partition name in the CPU usage per partition table.
OID : 1.3.6.1.4.1.22610.2.4.1.3.7.1.3

Field Name : axSysCpuUsagePerPartitionPeriodIndex

A10-AX-MIB_axMgmt_oid_list

Field Type : Integer32
Field Status : current
Description : The CPU usage per partition sampling period:
: 1: 1-second sampling,
: 2: 5-second sampling,
: 3: 10-second sampling,
: 4: 30-second sampling,
: 5: 60-second sampling.

OID : 1.3.6.1.4.1.22610.2.4.1.3.7.1.2

Field Name : axSysCpuIndexInUsagePerPartition
Field Type : Integer32
Field Status : current
Description : The index of the CPU. The value, 0, is for the control CPU.
OID : 1.3.6.1.4.1.22610.2.4.1.3.7.1.1

Field Name : axSysMemoryUsage
Field Type : Integer32
Field Status : current
Description : The usage memory(KB).
OID : 1.3.6.1.4.1.22610.2.4.1.2.2

Field Name : axSysMemoryTotal
Field Type : Integer32
Field Status : current
Description : The total memory(KB).
OID : 1.3.6.1.4.1.22610.2.4.1.2.1

Field Name : axSysSecondaryVersionOnCF
Field Type : String
Field Status : current
Description : The secondary system image version on Compact Flash.
OID : 1.3.6.1.4.1.22610.2.4.1.1.4

Field Name : axSysPrimaryVersionOnCF
Field Type : String
Field Status : current
Description : The primary system image version on Compact Flash.
OID : 1.3.6.1.4.1.22610.2.4.1.1.3

Field Name : axSysSecondaryVersionOnDisk
Field Type : String
Field Status : current
Description : The secondary system image version on hard disk.
OID : 1.3.6.1.4.1.22610.2.4.1.1.2

Field Name : axSysPrimaryVersionOnDisk
Field Type : String
Field Status : current
Description : The primary system image version on hard disk.
OID : 1.3.6.1.4.1.22610.2.4.1.1.1

Field Name : axTrunkStatTable
Field Type : TABLE
Field Status : current
Description : A table contains trunk statistic information.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2

A10-AX-MIB_axMgmt_oid_list

Field Name : axTrunkStatTotal

Field Type : INTEGER

Field Status : current

Description : The total number of axTrunkStat entries in the table.

OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.1

Field Name : axTrunkStatEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axTrunkStatTable

OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1

Field Name : axTrunkStatDropsOut

Field Type : Counter64

Field Status : current

Description : The total number of packets aged out or with excessive transmission
: delays due to multiple deferrals on the given trunk.

OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.11

Field Name : axTrunkStatDropsIn

Field Type : Counter64

Field Status : current

Description : The total number of dropped packets on the given trunk.

OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.10

Field Name : axTrunkStatErrorsOut

Field Type : Counter64

Field Status : current

Description : The total number of excessive collisions, incremented for each
: frame that experienced 16 collisions during transmission and
: was aborted on the given trunk.

OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.9

Field Name : axTrunkStatErrorsIn

Field Type : Counter64

Field Status : current

Description : The total number of received packets with errors by the given trunk.

OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.8

Field Name : axTrunkStatMcastOut

Field Type : Counter64

Field Status : current

Description : The total number of transmitted multicast packets out of the given trunk.

OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.7

Field Name : axTrunkStatMcastIn

Field Type : Counter64

Field Status : current

Description : The total number of received multicast packets on the given trunk.

OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.6

Field Name : axTrunkStatBytesOut

Field Type : Counter64

Field Status : current

Description : The total number of transmitted bytes on the given trunk.

OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.5

A10-AX-MIB_axMgmt_oid_list

Field Name : axTrunkStatPktsOut
Field Type : Counter64
Field Status : current
Description : The total number of transmitted packets on the given trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.4

Field Name : axTrunkStatBytesIn
Field Type : Counter64
Field Status : current
Description : The total number of received bytes on the given trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.3

Field Name : axTrunkStatPktsIn
Field Type : Counter64
Field Status : current
Description : The total number of received packets on the given trunk.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.2

Field Name : axTrunkStatName
Field Type : String
Field Status : current
Description : The trunk name.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.2.2.1.1

Field Name : axTrunkTable
Field Type : TABLE
Field Status : current
Description : A table contains trunk information.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2

Field Name : axTrunkTotal
Field Type : INTEGER
Field Status : current
Description : The total number of axTrunk entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.1

Field Name : axTrunkEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axTrunkTable
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1

Field Name : axTrunkAlias
Field Type : String
Field Status : current
Description : The trunk alias name.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.8

Field Name : axTrunkPortThresholdTimer
Field Type : INTEGER
Field Status : current
Description : Timer for port-threshold in second.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.7

Field Name : axTrunkPortThreshold
Field Type : INTEGER

A10-AX-MIB_axMgmt_oid_list

Field Status : current
Description : Threshold for minimum number of ports that need to be up.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.6

Field Name : axTrunkCfgMemberCount
Field Type : INTEGER
Field Status : current
Description : The total number of configured trunk members.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.5

Field Name : axTrunkTypeLacpEnabled
Field Type : EnumVal
Field Status : current
Description : The trunk type is dynamic, LACP.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.4

Field Name : axTrunkDescription
Field Type : String
Field Status : current
Description : The trunk description.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.3

Field Name : axTrunkStatus
Field Type : EnumVal
Field Status : current
Description : The trunk status.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.2

Field Name : axTrunkName
Field Type : String
Field Status : current
Description : The trunk name.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.1.2.1.1

Field Name : axTrunkCfgMemberTable
Field Type : TABLE
Field Status : current
Description : A table contains configured trunk member information.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.2

Field Name : axTrunkCfgMemberTotal
Field Type : INTEGER
Field Status : current
Description : The total number of axTrunkCfgMember entries.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.1

Field Name : axTrunkCfgMemberEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the sysTrunkCfgMember Table
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.2.1

Field Name : axTrunkCfgMemberOperStatus
Field Type : EnumVal
Field Status : current
Description : The trunk port member operational status.
OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.2.1.4

A10-AX-MIB_axMgmt_oid_list

Field Name : axTrunkCfgMemberAdminStatus

Field Type : EnumVal

Field Status : current

Description : The trunk port member administrative status.

OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.2.1.3

Field Name : axTrunkCfgMemberName

Field Type : String

Field Status : current

Description : The trunk member name: the physical port belongs to the trunk.

OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.2.1.2

Field Name : axTrunkCfgMemberTrunkName

Field Type : String

Field Status : current

Description : The trunk name.

OID : 1.3.6.1.4.1.22610.2.4.1.7.3.3.2.1.1

Field Name : axVlanCfgMemberTable

Field Type : TABLE

Field Status : current

Description : The table contains VLAN member configuration.

OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.2

Field Name : axVlanCfgTable

Field Type : TABLE

Field Status : current

Description : The table contains VLAN configuration.

OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.1

Field Name : axVlanCfgEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axVlanCfgTable

OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.1.1

Field Name : axVlanRouterInterface

Field Type : Integer32

Field Status : current

Description : VLAN router interface (ve) if configured. If a SNMP-Get value is zero, that means this object is not configured.

OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.1.1.3

Field Name : axVlanName

Field Type : String

Field Status : current

Description : The VLAN name.

OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.1.1.2

Field Name : axVlanId

Field Type : Integer32

Field Status : current

Description : The VLAN id.

OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.1.1.1

Field Name : axVlanCfgMemberEntry

A10-AX-MIB_axMgmt_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axVlanCfgMemberTable
OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.2.1

Field Name : axVlanMemberTagged
Field Type : EnumVal
Field Status : current
Description : The tagged/untagged state of the specific VLAN member.
OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.2.1.3

Field Name : axVlanMemberIntfId
Field Type : Integer32
Field Status : current
Description : The interface id configures as the VLAN member.
OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.2.1.2

Field Name : axVlanMemberVlanId
Field Type : Integer32
Field Status : current
Description : The VLAN id.
OID : 1.3.6.1.4.1.22610.2.4.1.7.2.1.2.1.1

Field Name : axInterfaceTable
Field Type : TABLE
Field Status : current
Description : A table containing information of the physical interfaces.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2

Field Name : axInterfaceCount
Field Type : Integer32
Field Status : current
Description : The number of axInterface entries in the table.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.1

Field Name : axInterfaceEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Columns in the axInterface Table
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1

Field Name : axInterfaceFlowCtrlOperStatus
Field Type : EnumVal
Field Status : current
Description : The control flow state of this interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.13

Field Name : axInterfaceFlowCtrlAdminStatus
Field Type : EnumVal
Field Status : current
Description : The control flow of this interface is enabled or disabled.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.12

Field Name : axInterfaceAlias
Field Type : String
Field Status : current
Description : The alias name of the interface if defined.

A10-AX-MIB_axMgmt_oid_list

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.11

Field Name : axInterfaceStatus

Field Type : EnumVal

Field Status : current

Description : The current state of the interface.

: up - has link and is initialized;
: down - has no link and is initialized;
: disabled - has been forced down

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.10

Field Name : axInterfaceAdminStatus

Field Type : EnumVal

Field Status : current

Description : The state of this interface, whether it is enabled.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.9

Field Name : axInterfaceMtu

Field Type : Integer32

Field Status : current

Description : The maximum transmission unit size of datagram which can be
: sent/received on the specified interface.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.8

Field Name : axInterfaceMacAddr

Field Type : String

Field Status : current

Description : The MAC address of the specified interface.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.7

Field Name : axInterfaceMediaActiveDuplex

Field Type : EnumVal

Field Status : current

Description : The active media duplex mode for the specified interface.

: half - Half duplex;
: full - Full duplex;
: auto - Auto duplex;
: none - All media is disabled.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.6

Field Name : axInterfaceMediaActiveSpeed

Field Type : Integer32

Field Status : current

Description : The current active media speed for the interface.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.5

Field Name : axInterfaceMediaMaxDuplex

Field Type : EnumVal

Field Status : current

Description : The best possible media duplex mode for the interface.

: half - Force half duplex;
: full - Force full duplex;
: none - All media is deselected.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.4

Field Name : axInterfaceMediaMaxSpeed

Field Type : Integer32

A10-AX-MIB_axMgmt_oid_list

Field Status : current

Description : The best possible media speed in MBPS for the interface.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.3

Field Name : axInterfaceName

Field Type : String

Field Status : current

Description : The name of the interface.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.2

Field Name : axInterfaceIndex

Field Type : Integer32

Field Status : current

Description : The index value of the interface.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.1.2.1.1

Field Name : axInterfaceStatTable

Field Type : TABLE

Field Status : current

Description : A table containing statistic information of the physical interfaces.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1

Field Name : axInterfaceStatEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axInterfaceStat Table

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1

Field Name : axInterfaceStatUtilPercentOut

Field Type : Integer32

Field Status : current

Description : The output utilization in percentage. For the ve interface, it's 0.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.18

Field Name : axInterfaceStatPktsPerSecOut

Field Type : Counter64

Field Status : current

Description : The output rate in packets per second.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.17

Field Name : axInterfaceStatBitsPerSecOut

Field Type : Counter64

Field Status : current

Description : The output rate in bits per second.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.16

Field Name : axInterfaceStatUtilPercentIn

Field Type : Integer32

Field Status : current

Description : The input utilization in percentage. For the ve interface, it's 0.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.15

Field Name : axInterfaceStatPktsPerSecIn

Field Type : Counter64

Field Status : current

Description : The input rate in packets per second.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.14

A10-AX-MIB_axMgmt_oid_list

Field Name : axInterfaceStatBitsPerSecIn
Field Type : Counter64
Field Status : current
Description : The input rate in bits per second.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.13

Field Name : axInterfaceStatCollisions
Field Type : Counter64
Field Status : current
Description : The number of collisions on this interface, incremented by the
: number of collisions experienced during transmissions of a frame
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.12

Field Name : axInterfaceStatDropsOut
Field Type : Counter64
Field Status : current
Description : The number of packets aged out or with excessive transmission
: delays due to multiple deferrals.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.11

Field Name : axInterfaceStatDropsIn
Field Type : Counter64
Field Status : current
Description : The number of packets dropped on ingress for various reasons.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.10

Field Name : axInterfaceStatErrorsOut
Field Type : Counter64
Field Status : current
Description : The number of excessive collisions, incremented for each
: frame that experienced 16 collisions during transmission and
: was aborted.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.9

Field Name : axInterfaceStatErrorsIn
Field Type : Counter64
Field Status : current
Description : The number of received packets that are either undersized,
: oversized, or have FCS errors.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.8

Field Name : axInterfaceStatMcastOut
Field Type : Counter64
Field Status : current
Description : The number of multicast packets transmitted out of this interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.7

Field Name : axInterfaceStatMcastIn
Field Type : Counter64
Field Status : current
Description : The number of multicast packets received on this interface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.6

Field Name : axInterfaceStatBytesOut
Field Type : Counter64
Field Status : current

A10-AX-MIB_axMgmt_oid_list

Description : The number of bytes transmitted out of this interface.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.5

Field Name : axInterfaceStatPktsOut

Field Type : Counter64

Field Status : current

Description : The number of packets transmitted out of this interface.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.4

Field Name : axInterfaceStatBytesIn

Field Type : Counter64

Field Status : current

Description : The number of bytes received on this interface.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.3

Field Name : axInterfaceStatPktsIn

Field Type : Counter64

Field Status : current

Description : The number of packets received on this interface.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.2

Field Name : axInterfaceStatIndex

Field Type : Integer32

Field Status : current

Description : The index value of the interface.

OID : 1.3.6.1.4.1.22610.2.4.1.7.1.2.1.1.1

Field Name : axArpInfoTable

Field Type : TABLE

Field Status : current

Description : A table contains optional ARP information.

OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2

Field Name : axArpEntryTotal

Field Type : INTEGER

Field Status : current

Description : The total number of ARP entries in the table.

OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.1

Field Name : axArpInfoEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : Columns in the axArpInfoTable

OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1

Field Name : axArpEntryAging

Field Type : INTEGER

Field Status : current

Description : The aging time of the ARP entry in seconds.

OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.7

Field Name : axArpEntryType

Field Type : EnumVal

Field Status : current

Description : The type of the ARP entry.

OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.6

A10-AX-MIB_axMgmt_oid_list

Field Name : axArpEntrySourceIntName
Field Type : String
Field Status : current
Description : The interface description name for axArpEntrySourceInterface.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.5

Field Name : axArpEntrySourceInterface
Field Type : INTEGER
Field Status : current
Description : The port number in ifIndex for the ARP entry taking effective.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.4

Field Name : axArpEntryVlan
Field Type : INTEGER
Field Status : current
Description : The VLAN identifier for the ARP entry.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.3

Field Name : axArpMacAddr
Field Type : String
Field Status : current
Description : The MAC address for the ARP entry.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.2

Field Name : axArpIpAddr
Field Type : String
Field Status : current
Description : The destination IP address of the ARP entry.
OID : 1.3.6.1.4.1.22610.2.4.1.7.100.1.2.1.1

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Field Name : axGslbGroupMemberLeaveGroup
Field Type : Trap
Field Status : none
Description : The GSLB group member is leaving a group.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.26

Field Name : axGslbGroupMemberJoinGroup
Field Type : Trap
Field Status : none
Description : The GSLB group member is joining a group.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.25

Field Name : axGslbGroupRemovedMaster
Field Type : Trap
Field Status : none
Description : The GSLB group is removed from the Master.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.24

Field Name : axGslbGroupBecomeMaster
Field Type : Trap
Field Status : none
Description : The GSLB group becomes the Master.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.23

Field Name : axGslbZoneServiceOperationalStateDown
Field Type : Trap
Field Status : none
Description : The GSLB zone service is operational down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.22

Field Name : axGslbZoneServiceOperationalStateUp
Field Type : Trap
Field Status : none
Description : The GSLB zone service is operational up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.21

Field Name : axGslbZoneServiceAdminDisabled
Field Type : Trap
Field Status : none
Description : The GSLB zone service is administratively disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.20

Field Name : axGslbZoneServiceAdminEnabled
Field Type : Trap
Field Status : none
Description : The GSLB zone service is administratively enabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.19

Field Name : axGslbZoneOperationalStateDown
Field Type : Trap
Field Status : none
Description : The GSLB zone is operational down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.18

Field Name : axGslbZoneOperationalStateUp
Field Type : Trap
Field Status : none

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Description : The GSLB zone is operational up.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.17

Field Name : axGslbZoneAdminDisabled

Field Type : Trap

Field Status : none

Description : The GSLB zone status is administratively disabled.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.16

Field Name : axGslbZoneAdminEnabled

Field Type : Trap

Field Status : none

Description : The GSLB zone status is administratively enabled.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.15

Field Name : axGslbServiceIpPortStateDown

Field Type : Trap

Field Status : none

Description : The GSLB service IP port status is changed to down.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.14

Field Name : axGslbServiceIpPortStateUp

Field Type : Trap

Field Status : none

Description : The GSLB service IP port status is changed to up.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.13

Field Name : axGslbServiceIpOperationalStateDown

Field Type : Trap

Field Status : none

Description : The GSLB service IP is operational down.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.12

Field Name : axGslbServiceIpOperationalStateUp

Field Type : Trap

Field Status : none

Description : The GSLB service IP is operational up.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.11

Field Name : axGslbServiceIpAdminDisabled

Field Type : Trap

Field Status : none

Description : The GSLB service IP is administratively disabled.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.10

Field Name : axGslbServiceIpAdminEnabled

Field Type : Trap

Field Status : none

Description : The GSLB service IP is administratively enabled.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.9

Field Name : axGslbSiteSlbDeviceStateDown

Field Type : Trap

Field Status : none

Description : The GSLB site SLB device status is changed to down.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.6

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Field Name : axGslbSiteSlbDeviceStateUp
Field Type : Trap
Field Status : none
Description : The GSLB site SLB device status is changed to up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.5

Field Name : axGslbSiteOperationalStateDown
Field Type : Trap
Field Status : none
Description : The GSLB site is operational down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.4

Field Name : axGslbSiteOperationalStateUp
Field Type : Trap
Field Status : none
Description : The GSLB site is operational up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.3

Field Name : axGslbSiteAdminDisabled
Field Type : Trap
Field Status : none
Description : The GSLB site is administratively disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.2

Field Name : axGslbSiteAdminEnabled
Field Type : Trap
Field Status : none
Description : The GSLB site is administratively enabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.5.1

Field Name : axNetworkTrunkPortsThreshold
Field Type : Trap
Field Status : none
Description : The trunk ports threshold trap.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.3.1

Field Name : axServiceBwRateResume
Field Type : Trap
Field Status : none
Description : A SLB service has reached the configured bandwidth rate resuming value.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.40

Field Name : axServiceBwRateLimit
Field Type : Trap
Field Status : none
Description : A SLB service has reached the configured bandwidth rate limit.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.39

Field Name : axServerBwRateResume
Field Type : Trap
Field Status : none
Description : A SLB server has reached the configured bandwidth rate resuming value.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.38

Field Name : axServerBwRateLimit
Field Type : Trap
Field Status : none

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Description : A SLB server has reached the configured bandwidth rate limit.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.37

Field Name : axGatewayDown

Field Type : Trap

Field Status : none

Description : A gateway server is down.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.36

Field Name : axGatewayUp

Field Type : Trap

Field Status : none

Description : A gateway server is up.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.35

Field Name : axVcsStateChange

Field Type : Trap

Field Status : none

Description : A VCS state change notification.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.34

Field Name : axServiceGroupMemberDown

Field Type : Trap

Field Status : none

Description : A SLB service group member is down.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.33

Field Name : axServiceGroupMemberUp

Field Type : Trap

Field Status : none

Description : A SLB service group member is up.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.32

Field Name : axServiceGroupDown

Field Type : Trap

Field Status : none

Description : A SLB service group is down.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.31

Field Name : axServiceGroupUp

Field Type : Trap

Field Status : none

Description : A SLB service group is Up.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.30

Field Name : axServerDisabled

Field Type : Trap

Field Status : none

Description : A SLB server is disabled.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.29

Field Name : axVirtualServerDown

Field Type : Trap

Field Status : none

Description : Slb virtual server is down.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.28

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Field Name : axVirtualServerUp

Field Type : Trap

Field Status : none

Description : Slb virtual server is up.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.27

Field Name : axServerSelectionFailure

Field Type : Trap

Field Status : none

Description : A SLB server has got a server selection failure.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.26

Field Name : axSslServerCertificateErr

Field Type : Trap

Field Status : none

Description : The SSL server certificate error is detected.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.25

Field Name : axVrrpStandby

Field Type : Trap

Field Status : none

Description : The vrid, axNotificationVrid, in the specific partition becomes the Standby state.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.24

Field Name : axVrrpActive

Field Type : Trap

Field Status : none

Description : The vrid, axNotificationVrid, in the specific partition becomes the Active state.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.23

Field Name : axServiceGroupMemberDisabledForNewConn

Field Type : Trap

Field Status : none

Description : A SLB service group member is disabled, when the current connections of group members are reduced to the conn-resume.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.22

Field Name : axServiceGroupMemberEnabledForNewConn

Field Type : Trap

Field Status : none

Description : A SLB service group member is enabled to accept the new connection, when the current connections of group members exceed the conn-limit.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.21

Field Name : axServiceConnRateLimit

Field Type : Trap

Field Status : none

Description : A SLB service group member has reached the configured conn-rate-limits.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.20

Field Name : axServerConnRateLimit

Field Type : Trap

Field Status : none

Description : A SLB server has reached the configured conn-rate-limits.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.19

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Field Name : axVirtualServerReachConnRateLimit

Field Type : Trap

Field Status : none

Description : A virtual server has reached the configured connection rate-limits.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.18

Field Name : axVirtualServerReachConnLimit

Field Type : Trap

Field Status : none

Description : A virtual server has reached the configured connection limits.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.17

Field Name : axVirtualServerPortReachConnRateLimit

Field Type : Trap

Field Status : none

Description : A virtual service port has reached the configured connection rate-limits.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.16

Field Name : axVirtualServerPortReachConnLimit

Field Type : Trap

Field Status : none

Description : A virtual service port has reached the configured connection limits.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.15

Field Name : axApplicationBufferReachLimit

Field Type : Trap

Field Status : none

Description : The AX SLB application buffer usage exceeded the configured threshold.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.14

Field Name : axVirtualServerPortUp

Field Type : Trap

Field Status : none

Description : A SLB virtual server port is up.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.13

Field Name : axVirtualServerPortDown

Field Type : Trap

Field Status : none

Description : A SLB virtual server port is down.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.12

Field Name : axServiceConnResume

Field Type : Trap

Field Status : none

Description : A SLB service has reached the configured connection-resume value.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.11

Field Name : axServiceConnLimit

Field Type : Trap

Field Status : none

Description : A SLB service has reached the configured connection limits.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.10

Field Name : axServerConnResume

Field Type : Trap

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Field Status : none
Description : A SLB server has reached the configured connection-resume value.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.9

Field Name : axServerConnLimit
Field Type : Trap
Field Status : none
Description : A SLB server has reached the configured connection limits.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.8

Field Name : axServerUp
Field Type : Trap
Field Status : none
Description : A SLB server is up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.7

Field Name : axServerDown
Field Type : Trap
Field Status : none
Description : A SLB server is down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.6

Field Name : axServiceUp
Field Type : Trap
Field Status : none
Description : A SLB service is up.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.5

Field Name : axServiceDown
Field Type : Trap
Field Status : none
Description : A service is detected DOWN.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.4

Field Name : axHAActiveActive
Field Type : Trap
Field Status : none
Description : The system is going into active-active mode.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.3

Field Name : axHAActive
Field Type : Trap
Field Status : none
Description : The system is going into active mode.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.2

Field Name : axHAStandby
Field Type : Trap
Field Status : none
Description : The system is going into standby mode.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.2.1

Field Name : axSystemBandwidthThresholdAlert
Field Type : Trap
Field Status : none
Description : The system bandwidth has crossed the threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.45

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Field Name : axAppsGlobalCpsThreshold
Field Type : Trap
Field Status : none
Description : The Connections Per Second (CPS) has crossed the threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.44

Field Name : axAppsGlobalSessionsThreshold
Field Type : Trap
Field Status : none
Description : The number of Sessions has crossed the threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.43

Field Name : axSystemLicenseModuleDisabled
Field Type : Trap
Field Status : none
Description : The license module is disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.42

Field Name : axHighPrioritySyslog
Field Type : Trap
Field Status : none
Description : The high severity issue such as hardware failure.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.41

Field Name : axTacacsMonitorServerUpDown
Field Type : Trap
Field Status : none
Description : The AX Tacacs Monitor Server is up/down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.39

Field Name : axSystemSmpResourceBecomeNormal
Field Type : Trap
Field Status : none
Description : The SMP is back to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.38

Field Name : axSystemSmpResourceHigh
Field Type : Trap
Field Status : none
Description : The system SMP is high.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.37

Field Name : axSystemConnectionResourceBecomeNormal
Field Type : Trap
Field Status : none
Description : The system connection is back to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.36

Field Name : axSystemConnectionResourceHigh
Field Type : Trap
Field Status : none
Description : The system connection is high.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.35

Field Name : axSystemPowerSupplyRecover
Field Type : Trap

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Field Status : none

Description : The system power supply is recover.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.34

Field Name : axSystemFanRecover

Field Type : Trap

Field Status : none

Description : The system fan is recover.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.33

Field Name : axMemoryUsageBecomeNormal

Field Type : Trap

Field Status : none

Description : The memory usage is back to normal.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.32

Field Name : axHardDiskUsageBecomeNormal

Field Type : Trap

Field Status : none

Description : The hard disk usage is back to normal.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.31

Field Name : axSystemTempBecomeNormal

Field Type : Trap

Field Status : none

Description : The system tempature is back to normal, axNotificationMsg will contain the system temperature index if it not default system temperature.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.30

Field Name : axSystemDataCpuBecomeNormal

Field Type : Trap

Field Status : none

Description : The AX data CPU usage is back to normal.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.29

Field Name : axSystemControlCpuBecomeNormal

Field Type : Trap

Field Status : none

Description : The AX control CPU usage is back to normal.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.28

Field Name : axSystemLicensedModuleDisabledForDuration

Field Type : Trap

Field Status : none

Description : The system disables the specific licensed module for the past duration seconds.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.27

Field Name : axFileSystemBecomeReadOnly

Field Type : Trap

Field Status : none

Description : The file system is becoming the read-only.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.26

Field Name : axSystemShutdownForReason

Field Type : Trap

Field Status : none

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Description : The AX system is mandatorily shut down.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.25

Field Name : axSystemLicenseExpiring

Field Type : Trap

Field Status : none

Description : The license is expiring or will expire at the given time.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.24

Field Name : axSystemLicenseLoadSuccessful

Field Type : Trap

Field Status : none

Description : The system loads the license for specific module successfully.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.23

Field Name : axSystemLicenseRequired

Field Type : Trap

Field Status : none

Description : The system requires the valid license for specific module.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.22

Field Name : axSystemPowerSupplyFailure

Field Type : Trap

Field Status : none

Description : The system power supply is failed.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.21

Field Name : axSystemFanFailure

Field Type : Trap

Field Status : none

Description : The system fan is failed.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.20

Field Name : axSystemDataCpuHigh

Field Type : Trap

Field Status : none

Description : The AX data CPU usage is high.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.19

Field Name : axSystemControlCpuHigh

Field Type : Trap

Field Status : none

Description : The AX control CPU usage is high.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.18

Field Name : axSystemRelieveDropPacketEvent

Field Type : Trap

Field Status : none

Description : The AX recovers from the packet dropped before.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.17

Field Name : axSystemDropPacketEvent

Field Type : Trap

Field Status : none

Description : The AX experiences the packet dropped of axNotificationDroppedPackets.

OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.16

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Field Name : axSystemRestart
Field Type : Trap
Field Status : none
Description : Notify that the agent has been restarted.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.15

Field Name : axMemoryUsageHigh
Field Type : Trap
Field Status : none
Description : The memory usage is high.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.14

Field Name : axHardDiskUsageHigh
Field Type : Trap
Field Status : none
Description : The hard disk usage is high.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.13

Field Name : axSecondaryHardDiskFailure
Field Type : Trap
Field Status : none
Description : The secondary hard disk is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.12

Field Name : axPrimaryHardDiskFailure
Field Type : Trap
Field Status : none
Description : The primary hard disk is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.11

Field Name : axLowerPowerSupplyFailure
Field Type : Trap
Field Status : none
Description : The system lower power supply is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.10

Field Name : axUpperPowerSupplyFailure
Field Type : Trap
Field Status : none
Description : The system upper power supply is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.9

Field Name : axSystemTempLow
Field Type : Trap
Field Status : none
Description : The system temperature is low, axNotificationMsg will contain system temperature index if it is not default system temperature.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.7

Field Name : axFan3Failure
Field Type : Trap
Field Status : none
Description : The system fan3 is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.6

Field Name : axFan2Failure
Field Type : Trap

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Field Status : none
Description : The system fan2 is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.5

Field Name : axFan1Failure
Field Type : Trap
Field Status : none
Description : The system fan1 is failed.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.4

Field Name : axSystemTempHigh
Field Type : Trap
Field Status : none
Description : The system temperature is high, axNotificationMsg will contain system temperature index if it is not default system temperature.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.3

Field Name : axSystemShutdown
Field Type : Trap
Field Status : none
Description : Notify that the system is in the process of being shut down.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.2

Field Name : axSystemStart
Field Type : Trap
Field Status : none
Description : Notify that the system has started running.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.1.1

Field Name : axSlbQpsLowToNormal
Field Type : Trap
Field Status : none
Description : The QPS is changed from low to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.16

Field Name : axSlbQpsLow
Field Type : Trap
Field Status : none
Description : The QPS is changed from normal to low.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.15

Field Name : axSlbQpsHighToNormal
Field Type : Trap
Field Status : none
Description : The QPS is changed from high to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.14

Field Name : axSlbQpsHigh
Field Type : Trap
Field Status : none
Description : The QPS is changed from normal to high.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.13

Field Name : axSlbSystemThresholdLowBecomeNormal
Field Type : Trap
Field Status : none
Description : The slb system level resource indicated by

A10-AX-NOTIFICATIONS_axNotifications_oid_list

: axNotificationSlbThresholdResourceId is changed from low to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.12

Field Name : axSlbSystemThresholdLow
Field Type : Trap
Field Status : none
Description : The slb system level resource indicated by
: axNotificationSlbThresholdResourceId is lower than the configured
: threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.11

Field Name : axSlbSystemThresholdHighBecomeNormal
Field Type : Trap
Field Status : none
Description : The slb system level resource indicated by
: axNotificationSlbThresholdResourceId is changed from high to normal.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.10

Field Name : axSlbSystemThresholdHigh
Field Type : Trap
Field Status : none
Description : The slb system level resource indicated by
: axNotificationSlbThresholdResourceId is higher than the configured
: threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.9

Field Name : axPartitionResourceUsageWarning
Field Type : Trap
Field Status : none
Description : The partition resource usage becomes above/below the configured limitation.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.7

Field Name : axSslCertificateExpiring
Field Type : Trap
Field Status : none
Description : The certification is going to be expired.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.6

Field Name : axSslCertificateCreateDelete
Field Type : Trap
Field Status : none
Description : Ssl certification is create or delete.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.5

Field Name : axServerPortCreateDelete
Field Type : Trap
Field Status : none
Description : Slb server port is added or delete.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.4

Field Name : axServerCreateDelete
Field Type : Trap
Field Status : none
Description : Slb server is added or deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.3

Field Name : axVirtualServerPortCreateDelete

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Field Type : Trap
Field Status : none
Description : Slb virtual server port is added or deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.2

Field Name : axVirtualServerCreateDelete
Field Type : Trap
Field Status : none
Description : Slb virtual server is added or deleted.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.6.1

Field Name : axLsnFixedNatPortMappingFileChange
Field Type : Trap
Field Status : none
Description : LSN: Fixed nat porting mapping file change.Fixed nat porting mapping file change.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.14

Field Name : axLsnSessionUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: Session user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.13

Field Name : axLsnFullconeCreationFailed
Field Type : Trap
Field Status : none
Description : LSN: Full-cone session creation failed (out-of-memory) for a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.12

Field Name : axLsnTrafficNewUserQuotasCreationFailed
Field Type : Trap
Field Status : none
Description : LSN: User-quota creation failed (out of memory) for a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.11

Field Name : axLsnTrafficTcpExtendedUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: TCP extended user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.10

Field Name : axLsnTrafficUdpExtendedUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: UDP extended user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.9

Field Name : axLsnTrafficNewUserResourceUnavailable
Field Type : Trap
Field Status : none
Description : LSN: New user could not get a NAT IP on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.8

Field Name : axLsnTrafficNatPortUnavailable
Field Type : Trap
Field Status : none

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Description : LSN: NAT port usage exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.7

Field Name : axLsnTrafficEspUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: ESP user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.6

Field Name : axLsnTrafficTcpUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: TCP user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.5

Field Name : axLsnTrafficUdpUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: UDP user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.4

Field Name : axLsnTrafficIcmpUserQuotasExceed
Field Type : Trap
Field Status : none
Description : LSN: ICMP user-quota exceeded on a specific pool.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.3

Field Name : axLsnIpAllPortExhausted
Field Type : Trap
Field Status : none
Description : LSN any IP port usage reaches the maximum threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.2

Field Name : axLsnNatAllPortUsageReachThreshold
Field Type : Trap
Field Status : none
Description : LSN NAT total port usage reaches the maximum threshold.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.4.1

Field Name : axScaleoutTrafficMapDistribution
Field Type : Trap
Field Status : none
Description : Scale out traffic map distribution
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.9

Field Name : axScaleoutTrafficMapUpdate
Field Type : Trap
Field Status : none
Description : Scale out traffic map change.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.8

Field Name : axScaleoutNodeStatus
Field Type : Trap
Field Status : none
Description : Scale out node status change.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.7

A10-AX-NOTIFICATIONS_axNotifications_oid_list

Field Name : axScaleoutMasterNodeCallingReelection
Field Type : Trap
Field Status : none
Description : Scale out master node calling reelection.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.6

Field Name : axScaleoutElection
Field Type : Trap
Field Status : none
Description : Number of devices on Scale out election.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.5

Field Name : axScaleoutSingleNodeStatus
Field Type : Trap
Field Status : none
Description : Scale out single node status change.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.4

Field Name : axScaleoutServiceMaster
Field Type : Trap
Field Status : none
Description : Scale out service master change.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.3

Field Name : axScaleoutLocalNodeDisabled
Field Type : Trap
Field Status : none
Description : Scale out local node disabled.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.2

Field Name : axScaleoutVserverTrafficMap
Field Type : Trap
Field Status : none
Description : Scale out Vserver Traffic Map change.
OID : 1.3.6.1.4.1.22610.2.4.3.12.2.7.1

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : aamAaaPolicySTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1

Field Name : aamAaaPolicySEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1

Field Name : failureBypass

Field Type : CounterBasedGauge64

Field Status : current

Description : Auth Failure Bypass

OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.8

Field Name : error

Field Type : CounterBasedGauge64

Field Status : current

Description : Error

OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.7

Field Name : reqSkip

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Skipped

OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.6

Field Name : reqBypass

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Bypassed

OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.5

Field Name : reqAuth

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Matching Authentication Template

OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.4

Field Name : reqReject

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Rejected

OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.3

Field Name : req

Field Type : CounterBasedGauge64

Field Status : current

Description : Request

OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.2

Field Name : aamAaaPolicyName

Field Type : String

Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Specify AAA policy name

OID : 1.3.6.1.4.1.22610.2.4.10.103.3.1.1.1.1

Field Name : aamJwtAuthorizationSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1

Field Name : aamJwtAuthorizationSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1

Field Name : jwtOtherError

Field Type : CounterBasedGauge64

Field Status : current

Description : JWT Other Error

OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.9

Field Name : jwtSignatureFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : JWT Signature Failure

OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.8

Field Name : jwtTokenExpired

Field Type : CounterBasedGauge64

Field Status : current

Description : JWT Token Expired

OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.7

Field Name : jwtMissingClaim

Field Type : CounterBasedGauge64

Field Status : current

Description : JWT Missing Claim

OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.6

Field Name : jwtMissingToken

Field Type : CounterBasedGauge64

Field Status : current

Description : JWT Missing Token

OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.5

Field Name : jwtAuthorizeFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : JWT Authorize Failure

OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.4

Field Name : jwtAuthorizeSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : JWT Authorize Success

OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.3

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : jwtRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : JWT Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify JWT authorization template name
OID : 1.3.6.1.4.1.22610.2.4.10.103.8.1.1.1.1

Field Name : aamAuthenticationRelaySamlSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1

Field Name : aamAuthenticationRelaySamlSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1.1

Field Name : aamAuthRelaySamlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1.1.5

Field Name : aamAuthRelaySamlFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1.1.4

Field Name : aamAuthRelaySamlSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1.1.3

Field Name : aamAuthRelaySamlRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1.1.2

Field Name : aamAuthRelaySAMLName
Field Type : String
Field Status : current
Description : Specify SAML authentication relay name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.6.1.1.1.1

Field Name : pollingControlError
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Total Polling Control Error

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.13

Field Name : jobStartError

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Job Start Error

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.12

Field Name : responseOther

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Other Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.11

Field Name : responseTimeout

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Timeout Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.10

Field Name : responseError

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Error Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.9

Field Name : responseFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Failure Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.8

Field Name : responseSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Success Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.7

Field Name : requestDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Dropped Request

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.6

Field Name : requestNormal

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Normal Request

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.5

Field Name : otherError

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Other Error

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.4

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : timeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.3

Field Name : responseGet
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Response Get
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.2

Field Name : requestSend
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request Send
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.1.1

Field Name : aamAuthRelayKerberosSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1

Field Name : aamAuthRelayKerberosSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1.1

Field Name : tickets
Field Type : CounterBasedGauge64
Field Status : current
Description : Tickets
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1.1.5

Field Name : currentRequestsOfUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Pending Requests of User
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1.1.4

Field Name : responseReceive
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Receive
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1.1.3

Field Name : requestSend
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Send
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Specify Kerberos authentication relay name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.2.2.1.1.1.1

Field Name : aamAuthenticationRelayOauthSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.7.1.1.1

Field Name : aamAuthenticationRelayOauthSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.7.1.1.1.1

Field Name : relayFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.7.1.1.1.1.4

Field Name : relaySucc
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.7.1.1.1.1.3

Field Name : relayReq
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.7.1.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify oauth authentication relay name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.10.7.1.1.1.1.1

Field Name : aamAuthenticationServiceGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1

Field Name : aamAuthenticationServiceGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1

Field Name : serviceCurrConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connection counter overflow count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.13

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : serviceResp5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 5xx count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.12

Field Name : serviceResp4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 4xx count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.11

Field Name : serviceResp3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 3xx count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.10

Field Name : serviceResp2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 2xx count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.9

Field Name : serviceRespCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.8

Field Name : serviceReqCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group request count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.7

Field Name : serviceUnhealthyHost
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group unhealthy host count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.6

Field Name : serviceHealthyHost
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group healthy host count
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.5

Field Name : servicePeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connection count for the Service Group
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.4

Field Name : serverSelectionFailReset
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Resets sent out for Service selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.3

Field Name : serverSelectionFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Drops due to Service selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify AAM service group name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.9.1.1.1.1

Field Name : otherError
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.8

Field Name : relayFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.7

Field Name : relaySucc
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.6

Field Name : relayReq
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.5

Field Name : authError
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.4

Field Name : authFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.3

Field Name : authSucc
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.2

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : authReq
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.17.1.1.1

Field Name : aamAuthSamlOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.22

Field Name : aamAuthSamlGlobalRelayError
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.21

Field Name : aamAuthSamlGlobalRelayFailure
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.20

Field Name : aamAuthSamlGlobalRelaySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.19

Field Name : aamAuthSamlGlobalRelayRequest
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.18

Field Name : aamAuthSamlGlobalParSloSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Partial Logout Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.17

Field Name : aamAuthSamlGlobalLocSloSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Local Logout Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.16

Field Name : aamAuthSamlGlobalGloSloSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Global Logout Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.15

Field Name : aamAuthSamlGlobalSpSloReq
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Total SP-initiated Single Logout Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.14

Field Name : aamAuthSamlGlobalSloError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Single Logout Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.13

Field Name : aamAuthSamlGlobalSloSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Single Logout Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.12

Field Name : aamAuthSamlGlobalSloReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Single Logout Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.11

Field Name : aamAuthSamlGlobalAcsError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SAML Single-Sign-On Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.10

Field Name : aamAuthSamlGlobalAcsAuthzFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SAML Single-Sign-On Authorization Fail
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.9

Field Name : aamAuthSamlGlobalAcsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SAML Single-Sign-On Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.8

Field Name : aamAuthSamlGlobalAcsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SAML Single-Sign-On Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.7

Field Name : aamAuthSamlGlobalLoginAuthResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Login Authentication Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.6

Field Name : aamAuthSamlGlobalLoginAuthReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Login Authentication Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.5

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : aamAuthSamlGlobalSpMetadataExportSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Toal Metadata Export Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.4

Field Name : aamAuthSamlGlobalSpMetadataExportReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Metadata Export Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.3

Field Name : responsesFromA10saml
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Response from A10 SAML Service
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.2

Field Name : requestsToA10saml
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request to A10 SAML Service
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.8.1.1.1

Field Name : aamAuthAccountResponseOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.7

Field Name : aamAuthAccountResponseTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.6

Field Name : aamAuthAccountResponseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.5

Field Name : aamAuthAccountResponseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.4

Field Name : aamAuthAccountResponseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.3

Field Name : aamAuthAccountRequestDropped
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Total Dropped Request

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.2

Field Name : aamAuthAccountRequestNormal

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Normal Request

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.7.1.1

Field Name : accountingFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Accounting Failure

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.20

Field Name : accountingSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Accounting Success

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.19

Field Name : accountingRequestSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Accounting-Request Sent

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.18

Field Name : aamAuthServerRadiusPollingControlError

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Polling Control Error

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.17

Field Name : aamAuthServerRadiusJobStartError

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Job Start Error

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.16

Field Name : aamAuthServerRadiusResponseOther

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Other Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.15

Field Name : aamAuthServerRadiusResponseTimeout

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Timeout Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.14

Field Name : aamAuthServerRadiusResponseError

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Error Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.13

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : aamAuthServerRadiusResponseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.12

Field Name : aamAuthServerRadiusResponseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.11

Field Name : aamAuthServerRadiusRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.10

Field Name : aamAuthServerRadiusRequestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.9

Field Name : aamAuthServerRadiusRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.8

Field Name : aamAuthServerRadiusOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.7

Field Name : aamAuthServerRadiusTimeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.6

Field Name : accessChallenge
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Access-Challenge Message Receive
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.5

Field Name : aamAuthServerRadiusAuthorizeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.4

Field Name : aamAuthServerRadiusAuthorizeSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Total Authorization Success

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.3

Field Name : authenFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Authentication Failure

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.2

Field Name : authenSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Authentication Success

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.1.1

Field Name : aamAuthServerRadiusSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1

Field Name : aamAuthServerRadiusSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1

Field Name : accountingFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Accounting Failure

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.12

Field Name : accountingSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Accounting Success

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.11

Field Name : accountingRequestSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Accounting-Request Sent

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.10

Field Name : request

Field Type : CounterBasedGauge64

Field Status : current

Description : Request

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.9

Field Name : otherError

Field Type : CounterBasedGauge64

Field Status : current

Description : Other Error

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.8

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : timeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.7

Field Name : accessChallenge
Field Type : CounterBasedGauge64
Field Status : current
Description : Access-Challenge Message Receive
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.6

Field Name : authorizeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Authorization Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.5

Field Name : authorizeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Authorization Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.4

Field Name : authenFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.3

Field Name : authenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify RADIUS authentication server name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.4.2.1.1.1.1

Field Name : aamAuthServerOcsppollingControlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSPPolling Control Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.19

Field Name : aamAuthServerOcsppJobStartError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSPP Job Start Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.18

Field Name : aamAuthServerOcsppResponseOther
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Total OCSP Other Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.17

Field Name : aamAuthServerOcsResponseTimeout

Field Type : CounterBasedGauge64

Field Status : current

Description : Total OCSP Timeout Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.16

Field Name : aamAuthServerOcsResponseError

Field Type : CounterBasedGauge64

Field Status : current

Description : Total OCSP Error Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.15

Field Name : aamAuthServerOcsResponseFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Total OCSP Failure Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.14

Field Name : aamAuthServerOcsResponseSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Total OCSP Success Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.13

Field Name : aamAuthServerOcsRequestDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : Total OCSP Dropped Request

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.12

Field Name : aamAuthServerOcsRequestNormal

Field Type : CounterBasedGauge64

Field Status : current

Description : Total OCSP Normal Request

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.11

Field Name : staplingResponseOther

Field Type : CounterBasedGauge64

Field Status : current

Description : Total OCSP Stapling Other Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.10

Field Name : staplingResponseTimeout

Field Type : CounterBasedGauge64

Field Status : current

Description : Total OCSP Stapling Timeout Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.9

Field Name : staplingResponseError

Field Type : CounterBasedGauge64

Field Status : current

Description : Total OCSP Stapling Error Response

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.8

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : staplingResponseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.7

Field Name : staplingResponseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.6

Field Name : staplingRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.5

Field Name : staplingRequestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.4

Field Name : staplingCertificateUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Unknown Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.3

Field Name : staplingCertificateRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Revoked Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.2

Field Name : staplingCertificateGood
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OCSP Stapling Good Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.1.1

Field Name : authServerOcspSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1

Field Name : authServerOcspSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1

Field Name : staplingFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Handle OCSF response failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.13

Field Name : staplingTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSF Stapling Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.12

Field Name : staplingCertificateUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSF Stapling Unknown Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.11

Field Name : staplingCertificateRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSF Stapling Revoked Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.10

Field Name : staplingCertificateGood
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSF Stapling Good Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.9

Field Name : staplingRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSF Stapling Request Send
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.8

Field Name : fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Handle OCSF response failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.7

Field Name : timeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.6

Field Name : certificateUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.5

Field Name : certificateRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : Revoked Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.4

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : certificateGood
Field Type : CounterBasedGauge64
Field Status : current
Description : Good Certificate Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.3

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.2

Field Name : aamAuthServerOcspName
Field Type : String
Field Status : current
Description : Specify OCSP authentication server name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.3.2.1.1.1.1

Field Name : pwChangeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total password change failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.27

Field Name : pwChangeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total password change success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.26

Field Name : pwExpiry
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Password expiry
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.25

Field Name : ldapsInuseConnNum
Field Type : CounterBasedGauge64
Field Status : current
Description : LDAPS In-use Connection Number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.24

Field Name : ldapsIdleConnNum
Field Type : CounterBasedGauge64
Field Status : current
Description : LDAPS Idle Connection Number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.23

Field Name : sslSessionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS/SSL Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.22

Field Name : sslSessionCreated
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : TLS/SSL Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.21

Field Name : aamAuthServerLdapPollingControlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Polling Control Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.20

Field Name : aamAuthServerLdapJobStartError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Job Start Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.19

Field Name : aamAuthServerLdapResponseOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.18

Field Name : aamAuthServerLdapResponseTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.17

Field Name : aamAuthServerLdapResponseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.16

Field Name : aamAuthServerLdapResponseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.15

Field Name : aamAuthServerLdapResponseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.14

Field Name : aamAuthServerLdapRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.13

Field Name : aamAuthServerLdapRequestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.12

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : aamAuthServerLdapRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.11

Field Name : aamAuthServerLdapOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.10

Field Name : aamAuthServerLdapTimeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.9

Field Name : aamAuthServerLdapAuthorizeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.8

Field Name : aamAuthServerLdapAuthorizeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.7

Field Name : aamAuthServerLdapSearchFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Search Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.6

Field Name : aamAuthServerLdapSearchSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Search Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.5

Field Name : aamAuthServerLdapBindFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Bind Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.4

Field Name : aamAuthServerLdapBindSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Bind Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.3

Field Name : aamAuthServerLdapAdminBindFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Total Admin Bind Failure

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.2

Field Name : aamAuthServerLdapAdminBindSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Admin Bind Success

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.1.1

Field Name : aamAuthServerLdapSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1

Field Name : aamAuthServerLdapSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1

Field Name : pwChangeFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Password change failure

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.17

Field Name : pwChangeSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Password change success

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.16

Field Name : pwExpiry

Field Type : CounterBasedGauge64

Field Status : current

Description : Password expiry

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.15

Field Name : sslSessionFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : TLS/SSL Session Failure

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.14

Field Name : sslSessionCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : TLS/SSL Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.13

Field Name : request

Field Type : CounterBasedGauge64

Field Status : current

Description : Request

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.12

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : aamAuthServerOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.11

Field Name : aamAuthServerTimeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.10

Field Name : authorizeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Authorization Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.9

Field Name : authorizeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Authorization Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.8

Field Name : searchFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Search Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.7

Field Name : searchSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Search Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.6

Field Name : bindFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : User Bind Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.5

Field Name : bindSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : User Bind Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.4

Field Name : adminBindFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Admin Bind Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.3

Field Name : adminBindSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Admin Bind Success

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.2

Field Name : name

Field Type : String

Field Status : current

Description : Specify LDAP authentication server name

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.2.2.1.1.1.1

Field Name : kerberosKdcKeytabCount

Field Type : CounterBasedGauge64

Field Status : current

Description : Current Kerberos KDC Keytab Count

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.42

Field Name : kerberosDeleteKdcKeytabFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Kerberos KDC Keytab Deletion Failure

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.41

Field Name : kerberosDeleteKdcKeytabSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Kerberos KDC Keytab Deletion Success

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.40

Field Name : kerberosGenerateKdcKeytabFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Kerberos KDC Keytab Generation Failure

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.39

Field Name : kerberosGenerateKdcKeytabSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Kerberos KDC Keytab Generation Success

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.38

Field Name : kerberosValidateKdcFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Kerberos KDC Validation Failure

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.37

Field Name : kerberosValidateKdcSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Kerberos KDC Validation Success

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.36

Field Name : kerberosPwChangeFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Kerberos password change failure

OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.35

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : kerberosPwChangeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos password change success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.34

Field Name : kerberosPwExpiry
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos password expiry
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.33

Field Name : kerberosPollingControlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Polling Control Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.19

Field Name : kerberosJobStartError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Job Start Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.18

Field Name : kerberosResponseOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.17

Field Name : kerberosResponseTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.16

Field Name : kerberosResponseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.15

Field Name : kerberosResponseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.14

Field Name : kerberosResponseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.13

Field Name : kerberosRequestDropped
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Total Kerberos Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.12

Field Name : kerberosRequestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.11

Field Name : kerberosOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.4

Field Name : kerberosTimeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.3

Field Name : kerberosResponseGet
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.2

Field Name : kerberosRequestSend
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Kerberos Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.1.1

Field Name : aamAuthServerWindowsSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1

Field Name : aamAuthServerWindowsSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1

Field Name : krbValidateKdcFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos KDC Validation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.20

Field Name : krbValidateKdcSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos KDC Validation Success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.19

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : krbPwChangeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos password change failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.8

Field Name : krbPwChangeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos password change success
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.7

Field Name : krbPwExpiry
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos password expiry
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.6

Field Name : krbOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.5

Field Name : krbTimeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.4

Field Name : krbGetRespSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.3

Field Name : krbSendReqSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Kerberos Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify Windows authentication server name
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.5.5.2.1.1.1.1

Field Name : authCtxNum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Auth Contexts
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.25

Field Name : domainWlistUnmatch
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Total DOMAIN WHITELIST unmatched number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.24

Field Name : domainWlistMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Total DOMAIN WHITELIST match number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.23

Field Name : dnsResolveFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM DNS resolve failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.22

Field Name : activeUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Active Users
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.21

Field Name : activeSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Active Auth-Sessions
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.20

Field Name : authzFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization failure number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.19

Field Name : authzSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization success number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.18

Field Name : authnFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authentication failure number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.17

Field Name : authnSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authentication success number
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.16

Field Name : aFlexAuthzFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization failure number in aFlex
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.15

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : aflexAuthzSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authorization success number in aFlex
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.14

Field Name : getSocketOptionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Get Socket Option Failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.13

Field Name : totalRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request Received by A10 Auth Service
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.12

Field Name : createTimerFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Timer Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.11

Field Name : createdTimer
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Timer Created
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.10

Field Name : aamAuthGlobalConnectFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Connect Failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.9

Field Name : connect
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Connection
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.8

Field Name : aamAuthGlobalOpenSocketFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Open Socket Failed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.7

Field Name : openedSocket
Field Type : CounterBasedGauge64
Field Status : current
Description : Total AAM Socket Opened
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.6

Field Name : ocsStaplingResponsesFromA10authd
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Total OSCP Stapling Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.5

Field Name : obspStaplingRequestsToA10authd
Field Type : CounterBasedGauge64
Field Status : current
Description : Total OSCP Stapling Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.4

Field Name : misses
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authentication Request Missed
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.3

Field Name : responses
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authentication Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.2

Field Name : requests
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Authentication Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.1.1.1

Field Name : pollingControlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Polling Control Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.16

Field Name : jobStartError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Job Start Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.15

Field Name : otherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.14

Field Name : timeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.13

Field Name : attrFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Attribute Check Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.12

ACOS-AAM-STATS-MIB_acosAam_oid_list

Field Name : jsonFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure JSON Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.11

Field Name : parseFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total JSON Response Parse Failure
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.10

Field Name : verifySucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Verification Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.9

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.8

Field Name : responseOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.7

Field Name : responseTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.6

Field Name : responseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.5

Field Name : responseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.4

Field Name : responseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.3

Field Name : requestDropped
Field Type : CounterBasedGauge64
Field Status : current

ACOS-AAM-STATS-MIB_acosAam_oid_list

Description : Total Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.2

Field Name : requestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.1.18.1.1

Field Name : responseOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.7

Field Name : responseTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.6

Field Name : responseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Error Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.5

Field Name : responseFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.4

Field Name : responseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.3

Field Name : requestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Dropped Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.2

Field Name : requestNormal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Normal Request
OID : 1.3.6.1.4.1.22610.2.4.10.103.7.1.1

ACOS-ACOS-EVENTS-STATS-MIB_acosAcosEvents_oid_list

Field Name : acosEventsCollectorGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.104.4.1.1

Field Name : acosEventsCollectorGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.104.4.1.1.1

Field Name : msgsDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of messages dropped for other reasons
OID : 1.3.6.1.4.1.22610.2.4.10.104.4.1.1.1.4

Field Name : msgsRateLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of rate limited log messages
OID : 1.3.6.1.4.1.22610.2.4.10.104.4.1.1.1.3

Field Name : msgsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of log messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.104.4.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify log server group name
OID : 1.3.6.1.4.1.22610.2.4.10.104.4.1.1.1.1

Field Name : acosEventsLogServerSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.104.3.1.1

Field Name : acosEventsLogServerSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.104.3.1.1.1

Field Name : msgsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of log messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.104.3.1.1.1.2

Field Name : name
Field Type : String
Field Status : current

ACOS-ACOS-EVENTS-STATS-MIB_acosAcosEvents_oid_list

Description : Server Name

OID : 1.3.6.1.4.1.22610.2.4.10.104.3.1.1.1.1

Field Name : outBytesCurrAgg

Field Type : CounterBasedGauge64

Field Status : current

Description : Current Aggregate, Number of bytes sent to log-servers

OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.49

Field Name : outLogsCurrAgg

Field Type : CounterBasedGauge64

Field Status : current

Description : Current Aggregate, Number of logs sent to log servers

OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.48

Field Name : inDiscardBytesCurrAgg

Field Type : CounterBasedGauge64

Field Status : current

Description : Current Aggregate, Number of old bytes discarded to fit in new logs

OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.47

Field Name : inDiscardLogsCurrAgg

Field Type : CounterBasedGauge64

Field Status : current

Description : Current Aggregate, Number of old logs discarded to fit in new logs

OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.46

Field Name : inBytesBacklogCurrAgg

Field Type : CounterBasedGauge64

Field Status : current

Description : Current Aggregate, Number of backlog bytes loaded from disk

OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.45

Field Name : inLogsBacklogCurrAgg

Field Type : CounterBasedGauge64

Field Status : current

Description : Current Aggregate, Number of backlogs loaded from disk

OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.44

Field Name : inBytesCurrAgg

Field Type : CounterBasedGauge64

Field Status : current

Description : Current Aggregate, Number of bytes successfully stored

OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.43

Field Name : inLogsCurrAgg

Field Type : CounterBasedGauge64

Field Status : current

Description : Current Aggregate, Number of logs successfully stored

OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.42

Field Name : outRetryFailAgg

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Aggregate, Number of retries failed with error

OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.41

ACOS-ACOS-EVENTS-STATS-MIB_acosAcosEvents_oid_list

Field Name : outRetryAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of attempted retries to send logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.40

Field Name : outErrorAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of errors during send
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.39

Field Name : outBytesAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of bytes sent to log-servers
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.38

Field Name : outLogsAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of logs sent to log servers
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.37

Field Name : inDiscardBytesAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of old bytes discarded to fit in new logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.36

Field Name : inDiscardLogsAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of old logs discarded to fit in new logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.35

Field Name : inStoreFailNoSpaceAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of logs Dropped, failed without disk space
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.34

Field Name : inBytesBacklogAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of backlog bytes loaded from disk
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.33

Field Name : inLogsBacklogAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of backlogs loaded from disk
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.32

Field Name : inBytesAgg
Field Type : CounterBasedGauge64
Field Status : current

ACOS-ACOS-EVENTS-STATS-MIB_acosAcosEvents_oid_list

Description : Total Aggregate, Number of bytes successfully stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.31

Field Name : inLogsAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Aggregate, Number of logs successfully stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.30

Field Name : currFsChunksDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Current blocks in file system not loaded in memory
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.29

Field Name : currFsChunksUp
Field Type : CounterBasedGauge64
Field Status : current
Description : Current blocks in file system loaded in memory
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.28

Field Name : currFsChunks
Field Type : CounterBasedGauge64
Field Status : current
Description : Current blocks in file system
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.27

Field Name : currMemChunks
Field Type : CounterBasedGauge64
Field Status : current
Description : Current blocks in memory
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.26

Field Name : currTotalChunks
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Number of blocks
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.25

Field Name : outRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of retries failed with error
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.24

Field Name : outRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of attempted retries to send logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.23

Field Name : movedToDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : Local Logging moved to delq to be deleted
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.22

ACOS-ACOS-EVENTS-STATS-MIB_acosAcosEvents_oid_list

Field Name : remainingBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of remaining bytes yet to be sent
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.21

Field Name : remainingLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of remaining logs yet to be sent
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.20

Field Name : outError
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of errors during send
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.19

Field Name : outBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of bytes sent to log-servers
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.18

Field Name : outLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs sent to log servers
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.17

Field Name : inDiscardBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of old bytes discarded to fit in new logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.16

Field Name : inDiscardLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of old logs discarded to fit in new logs
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.15

Field Name : inStoreFailNoSpace
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs Dropped, failed without disk space
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.14

Field Name : inBytesBacklog
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of backlog bytes loaded from disk
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.13

Field Name : inLogsBacklog
Field Type : CounterBasedGauge64
Field Status : current

ACOS-ACOS-EVENTS-STATS-MIB_acosAcosEvents_oid_list

Description : Number of backlogs loaded from disk
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.12

Field Name : inBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of bytes successfully stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.11

Field Name : inLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs successfully stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.10

Field Name : storeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs failed to be stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.9

Field Name : sentToStoreFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Logs sent to be stored Failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.8

Field Name : sentToStore
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs sent to be stored
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.7

Field Name : notInitied
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs Dropped, Local logging not initied
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.6

Field Name : rateLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs Dropped, Rate limited
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.5

Field Name : diskOverThres
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of logs Dropped, Disk reached threshold
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.4

Field Name : freed
Field Type : CounterBasedGauge64
Field Status : current
Description : Local logging Stopped
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.3

ACOS-ACOS-EVENTS-STATS-MIB_acosAcosEvents_oid_list

Field Name : initFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Local logging Init Fail
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.2

Field Name : initPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Local logging Init Successful
OID : 1.3.6.1.4.1.22610.2.4.10.104.14.1.1

Field Name : logdStatsAuditLogsDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Logd audit logs dropped
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.42

Field Name : logdStatsAuditLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Logd audit logs sent to hc
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.41

Field Name : logdStatsSystemLogsDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Logd system logs dropped
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.40

Field Name : logdStatsSystemLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Logd system logs sent to hc
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.39

Field Name : paramMsgEncodeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parameterized log AVRO encoding failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.38

Field Name : paramMsgSentFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parameterized log send to HC failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.37

Field Name : paramMsgSentToHc
Field Type : CounterBasedGauge64
Field Status : current
Description : Parameterized log sent to HC
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.36

Field Name : acosEvtTestLogsTicks
Field Type : CounterBasedGauge64
Field Status : current

ACOS-ACOS-EVENTS-STATS-MIB_acosAcosEvents_oid_list

Description : Number of ticks when running ACOS Event Test Logs

OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.35

Field Name : msgDroppedInvalidPart

Field Type : CounterBasedGauge64

Field Status : current

Description : Messages Dropped, Invalid partition Id

OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.34

Field Name : msgDroppedOtherLogd

Field Type : CounterBasedGauge64

Field Status : current

Description : Messages Dropped, unexpected error in Logd

OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.33

Field Name : msgDroppedNoActiveMemberLogd

Field Type : CounterBasedGauge64

Field Status : current

Description : Messages Dropped, no active member in collector grp in Logd

OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.32

Field Name : msgDroppedSendFailedLogd

Field Type : CounterBasedGauge64

Field Status : current

Description : Messages Dropped, send failed in Logd

OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.31

Field Name : msgDroppedCraftFailLogd

Field Type : CounterBasedGauge64

Field Status : current

Description : Messages Dropped, msg crafting failed in Logd

OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.30

Field Name : msgDroppedLostDuringConfigChangeLogd

Field Type : CounterBasedGauge64

Field Status : current

Description : Messages Dropped, lost during config change in Logd

OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.29

Field Name : msgDroppedNoTemplateLogd

Field Type : CounterBasedGauge64

Field Status : current

Description : Messages Dropped, no active template in Logd

OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.28

Field Name : msgSentRemoteCplane

Field Type : CounterBasedGauge64

Field Status : current

Description : Messages Sent, to remote in logd

OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.27

Field Name : msgDroppedGrpNotUsed

Field Type : CounterBasedGauge64

Field Status : current

Description : Messages Dropped, Collector group not used

OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.26

ACOS-ACOS-EVENTS-STATS-MIB_acosAcosEvents_oid_list

Field Name : msgDroppedLocalEnqueueFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, Enqueue to Logd failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.25

Field Name : msgDroppedRemoteDplaneLogRatelimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, Remote dplane log ratelimited
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.24

Field Name : msgDroppedRemoteCplaneLogRatelimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, Remote cplane log ratelimited
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.23

Field Name : msgDroppedTrylockFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, Trylock failed in axlog
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.22

Field Name : msgDroppedSendToLogdFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, send to Logd via IPC failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.21

Field Name : msgSentDirectSyslog
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages sent to syslog directly from axlog
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.20

Field Name : msgRetryAfterSocketFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages retried to be sent to Logd via IPC
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.19

Field Name : msgSentToLogd
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages sent to Logd via IPC
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.18

Field Name : localEnqueuePass
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages enqueue to Logd passed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.17

Field Name : msgDroppedLostDuringConfigChange
Field Type : CounterBasedGauge64
Field Status : current

ACOS-ACOS-EVENTS-STATS-MIB_acosAcosEvents_oid_list

Description : Messages Dropped, lost during config change
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.16

Field Name : noTemplate
Field Type : CounterBasedGauge64
Field Status : current
Description : Message API called, with no active template
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.15

Field Name : msgDroppedOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, unexpected error
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.14

Field Name : msgDroppedRouteFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, Route lookup failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.13

Field Name : msgDroppedNoActiveMember
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, no active member in collector grp
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.12

Field Name : msgDroppedSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, send failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.11

Field Name : msgDroppedRemoteLogRatelimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, remote log ratelimited
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.10

Field Name : msgDroppedLocalLogRatelimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, local log ratelimited
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.9

Field Name : msgDroppedCraftFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, msg crafting failed
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.8

Field Name : msgDroppedTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, invalid length
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.7

ACOS-ACOS-EVENTS-STATS-MIB_acosAcosEvents_oid_list

Field Name : msgDroppedSelector
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, selector does not enable msg
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.6

Field Name : msgDroppedNoTemplate
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, no active template
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.5

Field Name : msgDroppedMallocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, malloc failure
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.4

Field Name : msgDroppedFormatNotDefined
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages Dropped, format not defined
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.3

Field Name : msgSentLogdb
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages sent, to LogDB
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.2

Field Name : msgSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages sent, to Remote
OID : 1.3.6.1.4.1.22610.2.4.10.104.8.1.1

ACOS-CGNV6-DDOS-PROTECTION-MIB_oid_list

Field Name : ipEntriesOperDdosIpEntriesListTable
Field Type : TABLE
Field Status : current
Description : from object 'cgnv6.ddos-protection.ip-entries'
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3

Field Name : ipEntriesOperTable
Field Type : TABLE
Field Status : current
Description : from object 'cgnv6.ddos-protection.ip-entries'
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2

Field Name : ipEntriesOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ipEntriesOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2.1

Field Name : ipEntriesOperV4Netmask
Field Type : String
Field Status : current
Description : v4-netmask
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2.1.5

Field Name : ipEntriesOperNatPool
Field Type : String
Field Status : current
Description : nat-pool
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2.1.4

Field Name : ipEntriesOperAll
Field Type : Integer32
Field Status : current
Description : all
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2.1.3

Field Name : ipEntriesOperTotalEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : total-entries
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2.1.2

Field Name : ipEntriesOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.2.1.1

Field Name : ipEntriesOperDdosIpEntriesListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ipEntriesOperDdosIpEntriesList entry:ddos-ip-entries-list
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1

Field Name : ipEntriesOperDdosIpEntriesListHardwareIndex
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-DDOS-PROTECTION-MIB_oid_list

Description : hardware-index

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.15

Field Name : ipEntriesOperDdosIpEntriesListInHardware

Field Type : CounterBasedGauge64

Field Status : current

Description : in-hardware

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.14

Field Name : ipEntriesOperDdosIpEntriesListInBlacklist

Field Type : CounterBasedGauge64

Field Status : current

Description : in-blacklist

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.13

Field Name : ipEntriesOperDdosIpEntriesListTotalPps

Field Type : CounterBasedGauge64

Field Status : current

Description : total-pps

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.12

Field Name : ipEntriesOperDdosIpEntriesListHwL3DropPps

Field Type : CounterBasedGauge64

Field Status : current

Description : hw-l3-drop-pps

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.11

Field Name : ipEntriesOperDdosIpEntriesListSwL3DropPps

Field Type : CounterBasedGauge64

Field Status : current

Description : sw-l3-drop-pps

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.10

Field Name : ipEntriesOperDdosIpEntriesListHwL4DropPps

Field Type : CounterBasedGauge64

Field Status : current

Description : hw-l4-drop-pps

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.9

Field Name : ipEntriesOperDdosIpEntriesListSwL4DropPps

Field Type : CounterBasedGauge64

Field Status : current

Description : sw-l4-drop-pps

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.8

Field Name : ipEntriesOperDdosIpEntriesListSwReceivePps

Field Type : CounterBasedGauge64

Field Status : current

Description : sw-receive-pps

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.7

Field Name : ipEntriesOperDdosIpEntriesListL4EntriesCount

Field Type : CounterBasedGauge64

Field Status : current

Description : l4-entries-count

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.6

ACOS-CGNV6-DDOS-PROTECTION-MIB_oid_list

Field Name : ipEntriesOperDdosIpEntriesListHints
Field Type : String
Field Status : current
Description : hints
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.5

Field Name : ipEntriesOperDdosIpEntriesListExpiration
Field Type : CounterBasedGauge64
Field Status : current
Description : expiration
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.4

Field Name : ipEntriesOperDdosIpEntriesListV4Address
Field Type : String
Field Status : current
Description : v4-address
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.3

Field Name : ipEntriesOperDdosIpEntriesListDdosIpEntriesListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.2

Field Name : ipEntriesOperDdosIpEntriesListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.3.3.1.1

Field Name : l4EntriesOperDdosL4EntriesListTable
Field Type : TABLE
Field Status : current
Description : from object 'cgnv6.ddos-protection.l4-entries'
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3

Field Name : l4EntriesOperTable
Field Type : TABLE
Field Status : current
Description : from object 'cgnv6.ddos-protection.l4-entries'
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2

Field Name : l4EntriesOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The l4EntriesOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1

Field Name : l4EntriesOperNotInHardware
Field Type : Integer32
Field Status : current
Description : not-in-hardware
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1.6

Field Name : l4EntriesOperV4Netmask
Field Type : String
Field Status : current

ACOS-CGNV6-DDOS-PROTECTION-MIB_oid_list

Description : v4-netmask

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1.5

Field Name : l4EntriesOperNatPool

Field Type : String

Field Status : current

Description : nat-pool

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1.4

Field Name : l4EntriesOperAll

Field Type : Integer32

Field Status : current

Description : all

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1.3

Field Name : l4EntriesOperTotalEntries

Field Type : CounterBasedGauge64

Field Status : current

Description : total-entries

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1.2

Field Name : l4EntriesOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.2.1.1

Field Name : l4EntriesOperDdosL4EntriesListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The l4EntriesOperDdosL4EntriesList entry:ddos-l4-entries-list

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1

Field Name : l4EntriesOperDdosL4EntriesListIsDeleted

Field Type : CounterBasedGauge64

Field Status : current

Description : is-deleted

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.10

Field Name : l4EntriesOperDdosL4EntriesListExpiration

Field Type : CounterBasedGauge64

Field Status : current

Description : expiration

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.9

Field Name : l4EntriesOperDdosL4EntriesListPps

Field Type : CounterBasedGauge64

Field Status : current

Description : pps

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.8

Field Name : l4EntriesOperDdosL4EntriesListHardwareIndex

Field Type : CounterBasedGauge64

Field Status : current

Description : hardware-index

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.7

ACOS-CGNV6-DDOS-PROTECTION-MIB_oid_list

Field Name : l4EntriesOperDdosL4EntriesListInHardware
Field Type : CounterBasedGauge64
Field Status : current
Description : in-hardware
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.6

Field Name : l4EntriesOperDdosL4EntriesListPort
Field Type : CounterBasedGauge64
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.5

Field Name : l4EntriesOperDdosL4EntriesListL4Protocol
Field Type : String
Field Status : current
Description : l4-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.4

Field Name : l4EntriesOperDdosL4EntriesListV4Address
Field Type : String
Field Status : current
Description : v4-address
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.3

Field Name : l4EntriesOperDdosL4EntriesListDdosL4EntriesListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.2

Field Name : l4EntriesOperDdosL4EntriesListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.2.3.1.1

Field Name : ddosProtectionStatsTable
Field Type : TABLE
Field Status : current
Description : ConfigureCGNV6DDoSProtection from object 'cgnv6.ddos-protection'
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1

Field Name : ddosProtectionStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ddosProtectionStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1

Field Name : ddosProtectionStatsSynCookieConnSetupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : syn_cookie_conn_setup_failed
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.40

Field Name : ddosProtectionStatsSynCookieVerificationFailed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-DDOS-PROTECTION-MIB_oid_list

Description : syn_cookie_verification_failed
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.39

Field Name : ddosProtectionStatsSynCookieVerificationPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : syn_cookie_verification_passed
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.38

Field Name : ddosProtectionStatsSynCookieSynAckSent
Field Type : CounterBasedGauge64
Field Status : current
Description : syn_cookie_syn_ack_sent
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.37

Field Name : ddosProtectionStatsL3EntryAddToHwFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_add_to_hw_failure
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.36

Field Name : ddosProtectionStatsL3EntryRemoveFromBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_remove_from_bgp_failure
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.35

Field Name : ddosProtectionStatsL3EntryAddToBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_add_to_bgp_failure
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.34

Field Name : ddosProtectionStatsEntryInvalidated
Field Type : CounterBasedGauge64
Field Status : current
Description : entry_invalidated
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.33

Field Name : ddosProtectionStatsEntryAddedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : entry_added_shadow
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.32

Field Name : ddosProtectionStatsIpOtherBlockAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_other_block_alloc_failure
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.31

Field Name : ddosProtectionStatsIpOtherBlockFree
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_other_block_free
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.30

ACOS-CGNV6-DDOS-PROTECTION-MIB_oid_list

Field Name : ddosProtectionStatsIpOtherBlockAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_other_block_alloc
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.29

Field Name : ddosProtectionStatsIpPortBlockAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_port_block_alloc_failure
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.28

Field Name : ddosProtectionStatsIpPortBlockFree
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_port_block_free
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.27

Field Name : ddosProtectionStatsIpPortBlockAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_port_block_alloc
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.26

Field Name : ddosProtectionStatsIpNodeAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_node_alloc_failure
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.25

Field Name : ddosProtectionStatsIpNodeFree
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_node_free
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.24

Field Name : ddosProtectionStatsIpNodeAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_node_alloc
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.23

Field Name : ddosProtectionStatsL4EntryListAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_entry_list_alloc_failure
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.22

Field Name : ddosProtectionStatsL4EntryListFree
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_entry_list_free
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.21

Field Name : ddosProtectionStatsL4EntryListAlloc
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-DDOS-PROTECTION-MIB_oid_list

Description : l4_entry_list_alloc

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.20

Field Name : ddosProtectionStatsL4EntryDropMaxHwExceeded

Field Type : CounterBasedGauge64

Field Status : current

Description : l4_entry_drop_max_hw_exceeded

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.19

Field Name : ddosProtectionStatsL4EntryMatchDropHw

Field Type : CounterBasedGauge64

Field Status : current

Description : l4_entry_match_drop_hw

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.18

Field Name : ddosProtectionStatsL4EntryMatchDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : l4_entry_match_drop

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.17

Field Name : ddosProtectionStatsL4HwOutOfEntries

Field Type : CounterBasedGauge64

Field Status : current

Description : l4_hw_out_of_entries

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.16

Field Name : ddosProtectionStatsL4EntryRemovedFromHw

Field Type : CounterBasedGauge64

Field Status : current

Description : l4_entry_removed_from_hw

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.15

Field Name : ddosProtectionStatsL4EntryAddedToHw

Field Type : CounterBasedGauge64

Field Status : current

Description : l4_entry_added_to_hw

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.14

Field Name : ddosProtectionStatsL4EntryDeleted

Field Type : CounterBasedGauge64

Field Status : current

Description : l4_entry_deleted

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.13

Field Name : ddosProtectionStatsL4EntryAdded

Field Type : CounterBasedGauge64

Field Status : current

Description : l4_entry_added

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.12

Field Name : ddosProtectionStatsL3EntryDropMaxHwExceeded

Field Type : CounterBasedGauge64

Field Status : current

Description : l3_entry_drop_max_hw_exceeded

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.11

ACOS-CGNV6-DDOS-PROTECTION-MIB_oid_list

Field Name : ddosProtectionStatsL3EntryMatchDropHw
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_match_drop_hw
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.10

Field Name : ddosProtectionStatsL3EntryMatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_match_drop
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.9

Field Name : ddosProtectionStatsL3EntryTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_too_many
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.8

Field Name : ddosProtectionStatsL3EntryRemovedFromHw
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_removed_from_hw
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.7

Field Name : ddosProtectionStatsL3EntryAddedToHw
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_added_to_hw
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.6

Field Name : ddosProtectionStatsL3EntryRemovedFromBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_removed_from_bgp
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.5

Field Name : ddosProtectionStatsL3EntryAddedToBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_added_to_bgp
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.4

Field Name : ddosProtectionStatsL3EntryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_deleted
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.3

Field Name : ddosProtectionStatsL3EntryAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_entry_added
OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.2

Field Name : ddosProtectionStatsSlotId
Field Type : Integer32
Field Status : current

ACOS-CGNV6-DDOS-PROTECTION-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.1.1.1

Field Name : disableNatIpByBgpOperDdosDisabledByBgpEntriesListTable

Field Type : TABLE

Field Status : current

Description : from object 'cgnv6.ddos-protection.disable-nat-ip-by-bgp'

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.3

Field Name : disableNatIpByBgpOperTable

Field Type : TABLE

Field Status : current

Description : from object 'cgnv6.ddos-protection.disable-nat-ip-by-bgp'

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.2

Field Name : disableNatIpByBgpOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The disableNatIpByBgpOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.2.1

Field Name : disableNatIpByBgpOperV4Address

Field Type : String

Field Status : current

Description : v4-address

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.2.1.4

Field Name : disableNatIpByBgpOperAll

Field Type : Integer32

Field Status : current

Description : all

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.2.1.3

Field Name : disableNatIpByBgpOperTotalEntries

Field Type : CounterBasedGauge64

Field Status : current

Description : total-entries

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.2.1.2

Field Name : disableNatIpByBgpOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.2.1.1

Field Name : disableNatIpByBgpOperDdosDisabledByBgpEntriesListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The disableNatIpByBgpOperDdosDisabledByBgpEntriesList entry:ddos-disabled-by-bgp-entries-

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.3.1

Field Name : disableNatIpByBgpOperDdosDisabledByBgpEntriesListNatPoolName

Field Type : String

Field Status : current

Description : nat-pool-name

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.3.1.4

ACOS-CGNV6-DDOS-PROTECTION-MIB_oid_list

Field Name : disableNatIpByBgpOperDdosDisabledByBgpEntriesListV4Address

Field Type : String

Field Status : current

Description : v4-address

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.3.1.3

Field Name : disableNatIpByBgpOperDdosDisabledByBgpEntriesListDdosDisabledByBgpEntriesListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.3.1.2

Field Name : disableNatIpByBgpOperDdosDisabledByBgpEntriesListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.411.1.4.3.1.1

ACOS-CGNV6-DNS64-MIB_oid_list

Field Name : dns64StatsTable
Field Type : TABLE
Field Status : current
Description : DNS64Statistics from object 'cgnv6.dns64'
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1

Field Name : dns64StatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dns64Stats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1

Field Name : dns64StatsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : drop
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.16

Field Name : dns64StatsCache
Field Type : CounterBasedGauge64
Field Status : current
Description : cache
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.15

Field Name : dns64StatsAdjust
Field Type : CounterBasedGauge64
Field Status : current
Description : adjust
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.14

Field Name : dns64StatsRespLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-local
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.13

Field Name : dns64StatsRespEmpty
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-empty
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.12

Field Name : dns64StatsRespErr
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-err
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.11

Field Name : dns64StatsRespChg
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-chg
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.10

Field Name : dns64StatsRespBadQr
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-DNS64-MIB_oid_list

Description : resp-bad-qr
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.9

Field Name : dns64StatsRespBadPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-bad-pkt
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.8

Field Name : dns64StatsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : resp
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.7

Field Name : dns64StatsQueryPassive
Field Type : CounterBasedGauge64
Field Status : current
Description : query-passive
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.6

Field Name : dns64StatsQueryParallel
Field Type : CounterBasedGauge64
Field Status : current
Description : query-parallel
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.5

Field Name : dns64StatsQueryChg
Field Type : CounterBasedGauge64
Field Status : current
Description : query-chg
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.4

Field Name : dns64StatsQueryBadPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : query-bad-pkt
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.3

Field Name : dns64StatsQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : query
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.2

Field Name : dns64StatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.420.1.1.1.1

ACOS-CGNV6-HTTP-ALG-MIB_oid_list

Field Name : httpAlgStatsTable
Field Type : TABLE
Field Status : current
Description : HTTPALGStatistics from object 'cgnv6.http-alg'
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1

Field Name : httpAlgStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The httpAlgStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1

Field Name : httpAlgStatsNoQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : no-queue
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.20

Field Name : httpAlgStatsHeaderRemovalFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : header-removal-failed
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.19

Field Name : httpAlgStatsHeaderInsertionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : header-insertion-failed
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.18

Field Name : httpAlgStatsBuffSpiltFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : buff-spilt-failed
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.17

Field Name : httpAlgStatsBuffResent
Field Type : CounterBasedGauge64
Field Status : current
Description : buff-resent
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.16

Field Name : httpAlgStatsOutOfOrderDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : out-of-order-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.15

Field Name : httpAlgStatsQueueLenExceedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : queue-len-exceed-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.14

Field Name : httpAlgStatsOutOfMemoryDropped
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-HTTP-ALG-MIB_oid_list

Description : out-of-memory-dropped

OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.13

Field Name : httpAlgStatsRadiusResponseDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : radius-response-dropped

OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.12

Field Name : httpAlgStatsRadiusResponseReceived

Field Type : CounterBasedGauge64

Field Status : current

Description : radius-response-received

OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.11

Field Name : httpAlgStatsRadiusRequestDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : radius-request-dropped

OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.10

Field Name : httpAlgStatsRadiusRequestSent

Field Type : CounterBasedGauge64

Field Status : current

Description : radius-request-sent

OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.9

Field Name : httpAlgStatsRadiusQueryFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : radius-query-failed

OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.8

Field Name : httpAlgStatsRadiusQuerySucceed

Field Type : CounterBasedGauge64

Field Status : current

Description : radius-query-succeed

OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.7

Field Name : httpAlgStatsQueuedSessionTooMany

Field Type : CounterBasedGauge64

Field Status : current

Description : queued-session-too-many

OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.6

Field Name : httpAlgStatsRequestInsertMsisdnUnavailable

Field Type : CounterBasedGauge64

Field Status : current

Description : request-insert-msisdn-unavailable

OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.5

Field Name : httpAlgStatsRequestInsertClientIpPerformed

Field Type : CounterBasedGauge64

Field Status : current

Description : request-insert-client-ip-performed

OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.4

ACOS-CGNV6-HTTP-ALG-MIB_oid_list

Field Name : httpAlgStatsRequestInsertMsisdnPerformed
Field Type : CounterBasedGauge64
Field Status : current
Description : request-insert-msisdn-performed
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.3

Field Name : httpAlgStatsRequestProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : request-processed
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.2

Field Name : httpAlgStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.419.1.1.1.1

ACOS-CGNV6-ICMP-MIB_oid_list

Field Name : icmpStatsTable
Field Type : TABLE
Field Status : current
Description : CGNV6ICMPStatistics from object 'cgnv6.icmp'
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1

Field Name : icmpStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The icmpStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1

Field Name : icmpStatsErrorIpMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : error-ip-mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.38

Field Name : icmpStatsErrorToPoolDropV6
Field Type : CounterBasedGauge64
Field Status : current
Description : error-to-pool-drop-v6
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.37

Field Name : icmpStatsEchoToPoolDropV6
Field Type : CounterBasedGauge64
Field Status : current
Description : echo-to-pool-drop-v6
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.36

Field Name : icmpStatsEchoToPoolReplyV6
Field Type : CounterBasedGauge64
Field Status : current
Description : echo-to-pool-reply-v6
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.35

Field Name : icmpStatsErrorToPoolDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : error-to-pool-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.34

Field Name : icmpStatsEchoToPoolDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : echo-to-pool-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.33

Field Name : icmpStatsEchoToPoolReply
Field Type : CounterBasedGauge64
Field Status : current
Description : echo-to-pool-reply
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.32

Field Name : icmpStatsStaticNat
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-ICMP-MIB_oid_list

Description : static-nat

OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.31

Field Name : icmpStatsIcmpv6ToIcmpv6UnknownL4

Field Type : CounterBasedGauge64

Field Status : current

Description : icmpv6-to-icmpv6-unknown-l4

OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.30

Field Name : icmpStatsIcmpv6ToIcmpUnknownL4

Field Type : CounterBasedGauge64

Field Status : current

Description : icmpv6-to-icmp-unknown-l4

OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.29

Field Name : icmpStatsIcmpToIcmpv6UnknownL4

Field Type : CounterBasedGauge64

Field Status : current

Description : icmp-to-icmpv6-unknown-l4

OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.28

Field Name : icmpStatsIcmpToIcmpUnknownL4

Field Type : CounterBasedGauge64

Field Status : current

Description : icmp-to-icmp-unknown-l4

OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.27

Field Name : icmpStatsEncapCrossCpuPreprocessErr

Field Type : CounterBasedGauge64

Field Status : current

Description : encap-cross-cpu-preprocess-err

OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.26

Field Name : icmpStatsEncapCrossCpuNoMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : encap-cross-cpu-no-match

OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.25

Field Name : icmpStatsIcmpv6ToIcmpv6Err

Field Type : CounterBasedGauge64

Field Status : current

Description : icmpv6-to-icmpv6-err

OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.24

Field Name : icmpStatsIcmpv6ToIcmpErr

Field Type : CounterBasedGauge64

Field Status : current

Description : icmpv6-to-icmp-err

OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.23

Field Name : icmpStatsIcmpToIcmpv6Err

Field Type : CounterBasedGauge64

Field Status : current

Description : icmp-to-icmpv6-err

OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.22

ACOS-CGNV6-ICMP-MIB_oid_list

Field Name : icmpStatsIcmpToIcmpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-to-icmp-err
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.21

Field Name : icmpStats46BadEncapIpHeaderLen
Field Type : CounterBasedGauge64
Field Status : current
Description : 46-bad-encap-ip-header-len
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.20

Field Name : icmpStats46NoPrefixForIpv4
Field Type : CounterBasedGauge64
Field Status : current
Description : 46-no-prefix-for-ipv4
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.19

Field Name : icmpStats46UnknownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : 46-unknown-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.18

Field Name : icmpStats46KnownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : 46-known-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.17

Field Name : icmpStats64MidpointHop
Field Type : CounterBasedGauge64
Field Status : current
Description : 64-midpoint-hop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.16

Field Name : icmpStats64UnknownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : 64-unknown-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.15

Field Name : icmpStats64KnownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : 64-known-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.14

Field Name : icmpStatsIcmpv6BadType
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-bad-type
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.13

Field Name : icmpStatsIcmpBadType
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-ICMP-MIB_oid_list

Description : icmp-bad-type
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.12

Field Name : icmpStatsIcmpv6ToIcmpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-to-icmpv6
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.11

Field Name : icmpStatsIcmpv6ToIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-to-icmp
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.10

Field Name : icmpStatsIcmpToIcmpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-to-icmpv6
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.9

Field Name : icmpStatsIcmpToIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-to-icmp
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.8

Field Name : icmpStatsIcmpv6NoSessionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-no-session-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.7

Field Name : icmpStatsIcmpv6NoPortInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-no-port-info
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.6

Field Name : icmpStatsIcmpv6UnknownType
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-unknown-type
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.5

Field Name : icmpStatsIcmpNoSessionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-no-session-drop
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.4

Field Name : icmpStatsIcmpNoPortInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-no-port-info
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.3

ACOS-CGNV6-ICMP-MIB_oid_list

Field Name : icmpStatsIcmpUnknownType
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-unknown-type
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.2

Field Name : icmpStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.418.1.1.1.1

ACOS-CGNV6-L4-MIB_oid_list

Field Name : l4StatsTable
Field Type : TABLE
Field Status : current
Description : CGNV6L4Statistics from object 'cgnv6.l4'
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1

Field Name : l4StatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The l4Stats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1

Field Name : l4StatsFwNextActionIncorrectDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-next-action-incorrect-drop
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.64

Field Name : l4StatsNatRangeListAclPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : nat-range-list-acl-permit
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.63

Field Name : l4StatsNatRangeListAclDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : nat-range-list-acl-deny
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.62

Field Name : l4StatsFwZoneMismatchReroutingDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-zone-mismatch-rerouting-drop
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.61

Field Name : l4StatsL3Ipv6DstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : l3-ipv6-dst-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.60

Field Name : l4StatsL3Ipv6SrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : l3-ipv6-src-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.59

Field Name : l4StatsL3IpDstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : l3-ip-dst-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.58

Field Name : l4StatsL3IpSrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-L4-MIB_oid_list

Description : l3-ip-src-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.57

Field Name : l4StatsDstNatPoolNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : dst-nat-pool-not-found
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.56

Field Name : l4StatsSrcNatPoolNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : src-nat-pool-not-found
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.55

Field Name : l4StatsIpUnknownProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : ip-unknown-process
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.54

Field Name : l4StatsFwMatchNoRuleDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-match-no-rule-drop
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.53

Field Name : l4StatsProcessError
Field Type : CounterBasedGauge64
Field Status : current
Description : process-error
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.52

Field Name : l4StatsProcessContinue
Field Type : CounterBasedGauge64
Field Status : current
Description : process-continue
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.51

Field Name : l4StatsProcessSpecial
Field Type : CounterBasedGauge64
Field Status : current
Description : process-special
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.50

Field Name : l4StatsPreprocessError
Field Type : CounterBasedGauge64
Field Status : current
Description : preprocess-error
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.49

Field Name : l4StatsProcessL4
Field Type : CounterBasedGauge64
Field Status : current
Description : process-l4
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.48

ACOS-CGNV6-L4-MIB_oid_list

Field Name : l4StatsStaticNatFree
Field Type : CounterBasedGauge64
Field Status : current
Description : static-nat-free
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.47

Field Name : l4StatsStaticNatAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : static-nat-alloc
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.46

Field Name : l4StatsTcpRstLoopDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-rst-loop-drop
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.45

Field Name : l4StatsInvalidNat64TranslatedAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid-nat64-translated-addr
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.44

Field Name : l4StatsDstNatNeededDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dst-nat-needed-drop
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.43

Field Name : l4StatsStaticNatFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : static-nat-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.42

Field Name : l4StatsStaticNatFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : static-nat-fast-setup
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.41

Field Name : l4StatsFixedNatFastSetupMtuTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-fast-setup-mtu-too-small
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.40

Field Name : l4StatsFixedNatFastSetupDelayedErr
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-fast-setup-delayed-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.39

Field Name : l4StatsFixedNatDsliteFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-L4-MIB_oid_list

Description : fixed-nat-dslite-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.38

Field Name : l4StatsFixedNatDsliteFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-dslite-fast-setup
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.37

Field Name : l4StatsFixedNat64FastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat64-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.36

Field Name : l4StatsFixedNat64FastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat64-fast-setup
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.35

Field Name : l4StatsFixedNat44FastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat44-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.34

Field Name : l4StatsFixedNat44FastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat44-fast-setup
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.33

Field Name : l4StatsFastSetupMtuTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : fast-setup-mtu-too-small
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.32

Field Name : l4StatsFastSetupDelayedErr
Field Type : CounterBasedGauge64
Field Status : current
Description : fast-setup-delayed-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.31

Field Name : l4StatsDsliteFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : dslite-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.30

Field Name : l4StatsDsliteFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : dslite-fast-setup
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.29

ACOS-CGNV6-L4-MIB_oid_list

Field Name : l4StatsNat64FastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : nat64-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.28

Field Name : l4StatsNat64FastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : nat64-fast-setup
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.27

Field Name : l4StatsLsnFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : lsn-fast-setup-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.26

Field Name : l4StatsLsnFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : lsn-fast-setup
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.25

Field Name : l4StatsCrossCpuAlgGrePreprocessErr
Field Type : CounterBasedGauge64
Field Status : current
Description : cross-cpu-alg-gre-preprocess-err
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.24

Field Name : l4StatsCrossCpuAlgGreNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : cross-cpu-alg-gre-no-match
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.23

Field Name : l4StatsTtlExceededSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ttl-exceeded-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.22

Field Name : l4StatsOutOfStateDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : out-of-state-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.21

Field Name : l4StatsIcmpv6ReplySent
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-reply-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.20

Field Name : l4StatsIcmpReplySent
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-L4-MIB_oid_list

Description : icmp-reply-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.19

Field Name : l4StatsSpecialIpv6NoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : special-ipv6-no-route
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.18

Field Name : l4StatsSpecialIpv4NoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : special-ipv4-no-route
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.17

Field Name : l4StatsBadL3Protocol
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-l3-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.16

Field Name : l4StatsRateDropResetUnkn
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_drop_reset_unkn
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.15

Field Name : l4StatsIpv6DstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-dst-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.14

Field Name : l4StatsIpv6SrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-src-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.13

Field Name : l4StatsIpDstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : ip-dst-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.12

Field Name : l4StatsIpSrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : ip-src-invalid-unicast
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.11

Field Name : l4StatsIpipTruncated
Field Type : CounterBasedGauge64
Field Status : current
Description : ipip-truncated
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.10

ACOS-CGNV6-L4-MIB_oid_list

Field Name : l4StatsIcmpReplyNoSessionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-reply-no-session-drop
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.9

Field Name : l4StatsIcmpHostUnreachableSent
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-host-unreachable-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.8

Field Name : l4StatsIcmpFilteredSent
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-filtered-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.7

Field Name : l4StatsIpipIcmpReplySent
Field Type : CounterBasedGauge64
Field Status : current
Description : ipip-icmp-reply-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.6

Field Name : l4StatsTcpRstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-rst-sent
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.5

Field Name : l4StatsOutOfSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : out-of-session-memory
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.4

Field Name : l4StatsNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : no-rev-route
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.3

Field Name : l4StatsNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : no-fwd-route
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.2

Field Name : l4StatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.417.1.1.1.1

ACOS-CGNV6-LOGGING-MIB_oid_list

Field Name : tcpSvrStatusOperTcpSvrListTable
Field Type : TABLE
Field Status : current
Description : from object 'cgnv6.logging.tcp-svr-status'
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2

Field Name : tcpSvrStatusOperTcpSvrListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The tcpSvrStatusOperTcpSvrList entry:tcp-svr-list
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1

Field Name : tcpSvrStatusOperTcpSvrListStatus
Field Type : String
Field Status : current
Description : status
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.8

Field Name : tcpSvrStatusOperTcpSvrListNumCpus
Field Type : CounterBasedGauge64
Field Status : current
Description : num-cpus
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.7

Field Name : tcpSvrStatusOperTcpSvrListOverallStatus
Field Type : CounterBasedGauge64
Field Status : current
Description : overall-status
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.6

Field Name : tcpSvrStatusOperTcpSvrListServerPort
Field Type : CounterBasedGauge64
Field Status : current
Description : server-port
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.5

Field Name : tcpSvrStatusOperTcpSvrListServerName
Field Type : String
Field Status : current
Description : server-name
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.4

Field Name : tcpSvrStatusOperTcpSvrListTemplate
Field Type : String
Field Status : current
Description : template
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.3

Field Name : tcpSvrStatusOperTcpSvrListTcpSvrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.2

Field Name : tcpSvrStatusOperTcpSvrListSlotId
Field Type : Integer32
Field Status : current

ACOS-CGNV6-LOGGING-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.3.2.1.1

Field Name : sourceAddressOperSourceAddressListTable

Field Type : TABLE

Field Status : current

Description : from object 'cgnv6.logging.source-address'

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2

Field Name : sourceAddressOperSourceAddressListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The sourceAddressOperSourceAddressList entry:source-address-list

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1

Field Name : sourceAddressOperSourceAddressListUdpFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : udp-failed

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.12

Field Name : sourceAddressOperSourceAddressListUdpFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : udp-freed

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.11

Field Name : sourceAddressOperSourceAddressListUdpAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : udp-allocated

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.10

Field Name : sourceAddressOperSourceAddressListUdpTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : udp-total

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.9

Field Name : sourceAddressOperSourceAddressListTcpFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp-failed

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.8

Field Name : sourceAddressOperSourceAddressListTcpFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp-freed

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.7

Field Name : sourceAddressOperSourceAddressListTcpAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp-allocated

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.6

ACOS-CGNV6-LOGGING-MIB_oid_list

Field Name : sourceAddressOperSourceAddressListTcpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-total
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.5

Field Name : sourceAddressOperSourceAddressListRefCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ref-count
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.4

Field Name : sourceAddressOperSourceAddressListSourceAddress
Field Type : String
Field Status : current
Description : source-address
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.3

Field Name : sourceAddressOperSourceAddressListSourceAddressListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.2

Field Name : sourceAddressOperSourceAddressListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.2.2.1.1

Field Name : loggingStatsTable
Field Type : TABLE
Field Status : current
Description : CGNV6LoggingStatistics from object 'cgnv6.logging'
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1

Field Name : loggingStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The loggingStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1

Field Name : loggingStatsIddosL4EntryDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : iddos-l4-entry-delete
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.84

Field Name : loggingStatsIddosL4EntryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : iddos-l4-entry-create
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.83

Field Name : loggingStatsIddosL3EntryDelete
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-LOGGING-MIB_oid_list

Description : iddos-l3-entry-delete
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.82

Field Name : loggingStatsIddosL3EntryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : iddos-l3-entry-create
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.81

Field Name : loggingStatsHttpSpmFreeType4
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-free-type4
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.80

Field Name : loggingStatsHttpSpmFreeType3
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-free-type3
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.79

Field Name : loggingStatsHttpSpmFreeType2
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-free-type2
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.78

Field Name : loggingStatsHttpSpmFreeType1
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-free-type1
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.77

Field Name : loggingStatsHttpSpmFreeType0
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-free-type0
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.76

Field Name : loggingStatsHttpSpmAllocType4
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-alloc-type4
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.75

Field Name : loggingStatsHttpSpmAllocType3
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-alloc-type3
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.74

Field Name : loggingStatsHttpSpmAllocType2
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-alloc-type2
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.73

ACOS-CGNV6-LOGGING-MIB_oid_list

Field Name : loggingStatsHttpSpmAllocType1
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-alloc-type1
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.72

Field Name : loggingStatsHttpSpmAllocType0
Field Type : CounterBasedGauge64
Field Status : current
Description : http-spm-alloc-type0
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.71

Field Name : loggingStatsHttpMfree
Field Type : CounterBasedGauge64
Field Status : current
Description : http-mfree
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.70

Field Name : loggingStatsHttpMalloc
Field Type : CounterBasedGauge64
Field Status : current
Description : http-malloc
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.69

Field Name : loggingStatsHttpFragMergeFailedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : http-frag-merge-failed-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.68

Field Name : loggingStatsHttpAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : http-alloc-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.67

Field Name : loggingStatsHttpOutOfOrderDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : http-out-of-order-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.66

Field Name : loggingStatsLogMessageTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : log-message-too-long
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.65

Field Name : loggingStatsPortBlockAccountingAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : port-block-accounting-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.64

Field Name : loggingStatsPortBlockAccountingFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-LOGGING-MIB_oid_list

Description : port-block-accounting-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.63

Field Name : loggingStatsUdpPortBatchInterimUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-batch-interim-updated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.62

Field Name : loggingStatsTcpPortBatchInterimUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-batch-interim-updated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.61

Field Name : loggingStatsInterimUpdateNoBuffRetried
Field Type : CounterBasedGauge64
Field Status : current
Description : interim-update-no-buff-retried
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.60

Field Name : loggingStatsInterimUpdateMemoryFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : interim-update-memory-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.59

Field Name : loggingStatsInterimUpdateTerminated
Field Type : CounterBasedGauge64
Field Status : current
Description : interim-update-terminated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.58

Field Name : loggingStatsInterimUpdateScheduleFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : interim-update-schedule-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.57

Field Name : loggingStatsInterimUpdateScheduled
Field Type : CounterBasedGauge64
Field Status : current
Description : interim-update-scheduled
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.56

Field Name : loggingStatsIpv6FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-frag-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.55

Field Name : loggingStatsIpv6FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-frag-applied
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.54

ACOS-CGNV6-LOGGING-MIB_oid_list

Field Name : loggingStatsIpv4FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-frag-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.53

Field Name : loggingStatsIpv4FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-frag-applied
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.52

Field Name : loggingStatsConnTcpCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : conn-tcp-create-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.51

Field Name : loggingStatsRtspPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : rtsp-port-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.50

Field Name : loggingStatsRtspPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : rtsp-port-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.49

Field Name : loggingStatsAddMsgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : add-msg-failed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.48

Field Name : loggingStatsOutOfBuffers
Field Type : CounterBasedGauge64
Field Status : current
Description : out-of-buffers
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.47

Field Name : loggingStatsReducedLogsByDestination
Field Type : CounterBasedGauge64
Field Status : current
Description : reduced-logs-by-destination
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.46

Field Name : loggingStatsHttpRequestLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : http-request-logged
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.45

Field Name : loggingStatsUdpPortOverloadingFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-LOGGING-MIB_oid_list

Description : udp-port-overloading-freed

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.44

Field Name : loggingStatsUdpPortOverloadingAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : udp-port-overloading-allocated

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.43

Field Name : loggingStatsTcpPortOverloadingFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp-port-overloading-freed

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.42

Field Name : loggingStatsTcpPortOverloadingAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp-port-overloading-allocated

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.41

Field Name : loggingStatsConnTcpDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : conn-tcp-dropped

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.40

Field Name : loggingStatsConnTcpEstablished

Field Type : CounterBasedGauge64

Field Status : current

Description : conn-tcp-established

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.39

Field Name : loggingStatsLogDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : log-dropped

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.38

Field Name : loggingStatsLogSent

Field Type : CounterBasedGauge64

Field Status : current

Description : log-sent

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.37

Field Name : loggingStatsEnhancedUserLog

Field Type : CounterBasedGauge64

Field Status : current

Description : enhanced-user-log

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.36

Field Name : loggingStatsFixedNatInterimUpdated

Field Type : CounterBasedGauge64

Field Status : current

Description : fixed-nat-interim-updated

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.35

ACOS-CGNV6-LOGGING-MIB_oid_list

Field Name : loggingStatsFixedNatPeriodicConfigLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-periodic-config-logged
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.34

Field Name : loggingStatsFixedNatPeriodicConfigLogsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-periodic-config-logs-sent
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.33

Field Name : loggingStatsFixedNatDisableConfigLogsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-disable-config-logs-sent
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.32

Field Name : loggingStatsFixedNatDisableConfigLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-disable-config-logged
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.31

Field Name : loggingStatsFixedNatUserPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : fixed-nat-user-ports
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.30

Field Name : loggingStatsEspResourceFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : esp-resource-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.29

Field Name : loggingStatsEspResourceAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : esp-resource-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.28

Field Name : loggingStatsEspSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : esp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.27

Field Name : loggingStatsEspSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : esp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.26

Field Name : loggingStatsGreResourceFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-LOGGING-MIB_oid_list

Description : gre-resource-freed

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.25

Field Name : loggingStatsGreResourceAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : gre-resource-allocated

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.24

Field Name : loggingStatsGreSessionDeleted

Field Type : CounterBasedGauge64

Field Status : current

Description : gre-session-deleted

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.23

Field Name : loggingStatsGreSessionCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : gre-session-created

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.22

Field Name : loggingStatsIcmpv6ResourceFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : icmpv6-resource-freed

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.21

Field Name : loggingStatsIcmpv6ResourceAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : icmpv6-resource-allocated

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.20

Field Name : loggingStatsIcmpv6SessionDeleted

Field Type : CounterBasedGauge64

Field Status : current

Description : icmpv6-session-deleted

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.19

Field Name : loggingStatsIcmpv6SessionCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : icmpv6-session-created

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.18

Field Name : loggingStatsIcmpResourceFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : icmp-resource-freed

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.17

Field Name : loggingStatsIcmpResourceAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : icmp-resource-allocated

OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.16

ACOS-CGNV6-LOGGING-MIB_oid_list

Field Name : loggingStatsIcmpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.15

Field Name : loggingStatsIcmpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.14

Field Name : loggingStatsUdpPortBatchFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-batch-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.13

Field Name : loggingStatsUdpPortBatchAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-batch-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.12

Field Name : loggingStatsUdpPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.11

Field Name : loggingStatsUdpPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.10

Field Name : loggingStatsUdpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.9

Field Name : loggingStatsUdpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.8

Field Name : loggingStatsTcpPortBatchFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-batch-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.7

Field Name : loggingStatsTcpPortBatchAllocated
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-LOGGING-MIB_oid_list

Description : tcp-port-batch-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.6

Field Name : loggingStatsTcpPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-freed
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.5

Field Name : loggingStatsTcpPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.4

Field Name : loggingStatsTcpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.3

Field Name : loggingStatsTcpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.2

Field Name : loggingStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.416.1.1.1.1

ACOS-CGNV6-SERVER-MIB_oid_list

Field Name : serverOperDrsListTable
Field Type : TABLE
Field Status : current
Description : CGNV6LoggingServer from object 'cgnv6.server'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3

Field Name : serverOperDrsListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serverOperDrsList entry:drs-list
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1

Field Name : serverOperDrsListDrsWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-weight
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.28

Field Name : serverOperDrsListDrsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.27

Field Name : serverOperDrsListDrsTotRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-rev-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.26

Field Name : serverOperDrsListDrsTotRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-rev-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.25

Field Name : serverOperDrsListDrsTotFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-fwd-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.24

Field Name : serverOperDrsListDrsTotFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-fwd-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.23

Field Name : serverOperDrsListDrsTotReqSuc
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-req-suc
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.22

Field Name : serverOperDrsListDrsTotReq
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-SERVER-MIB_oid_list

Description : drs-tot-req
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.21

Field Name : serverOperDrsListDrsTotConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.20

Field Name : serverOperDrsListDrsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-req
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.19

Field Name : serverOperDrsListDrsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.18

Field Name : serverOperDrsListDrsDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-disable
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.17

Field Name : serverOperDrsListDrsCurrObserveRate
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr_observe_rate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.16

Field Name : serverOperDrsListDrsConnRateUnit
Field Type : String
Field Status : current
Description : drs-conn_rate_unit
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.15

Field Name : serverOperDrsListDrsCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr_conn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.14

Field Name : serverOperDrsListDrsSlowStartConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-slow_start_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.13

Field Name : serverOperDrsListDrsIsAutocreate
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-is_autocreate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.12

ACOS-CGNV6-SERVER-MIB_oid_list

Field Name : serverOperDrsListDrsSrvGatewayArp
Field Type : String
Field Status : current
Description : drs-srv_gateway_arp
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.11

Field Name : serverOperDrsListDrsServerTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-server_ttl
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.10

Field Name : serverOperDrsListDrsDnsUpdateTime
Field Type : String
Field Status : current
Description : drs-dns_update_time
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.9

Field Name : serverOperDrsListDrsCreationType
Field Type : String
Field Status : current
Description : drs-creation_type
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.8

Field Name : serverOperDrsListDrsState
Field Type : String
Field Status : current
Description : drs-state
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.7

Field Name : serverOperDrsListDrsServerIpv6Addr
Field Type : String
Field Status : current
Description : drs-server-ipv6-addr
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.6

Field Name : serverOperDrsListDrsHost
Field Type : String
Field Status : current
Description : drs-host
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.5

Field Name : serverOperDrsListDrsName
Field Type : String
Field Status : current
Description : drs-name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.4

Field Name : serverOperDrsListDrsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.3

Field Name : serverOperDrsListName
Field Type : String
Field Status : current

ACOS-CGNV6-SERVER-MIB_oid_list

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.2

Field Name : serverOperDrsListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.3.1.1

Field Name : serverOperTable

Field Type : TABLE

Field Status : current

Description : CGNV6LoggingServer from object 'cgnv6.server'

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2

Field Name : serverOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The serverOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1

Field Name : serverOperWeight

Field Type : CounterBasedGauge64

Field Status : current

Description : weight

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.14

Field Name : serverOperDisable

Field Type : CounterBasedGauge64

Field Status : current

Description : disable

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.13

Field Name : serverOperCurrObserveRate

Field Type : CounterBasedGauge64

Field Status : current

Description : curr_observe_rate

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.12

Field Name : serverOperConnRateUnit

Field Type : String

Field Status : current

Description : conn_rate_unit

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.11

Field Name : serverOperCurrConnRate

Field Type : CounterBasedGauge64

Field Status : current

Description : curr_conn_rate

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.10

Field Name : serverOperSlowStartConnLimit

Field Type : CounterBasedGauge64

Field Status : current

Description : slow_start_conn_limit

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.9

ACOS-CGNV6-SERVER-MIB_oid_list

Field Name : serverOperIsAutocreate
Field Type : CounterBasedGauge64
Field Status : current
Description : is_autocreate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.8

Field Name : serverOperSrvGatewayArp
Field Type : String
Field Status : current
Description : srv_gateway_arp
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.7

Field Name : serverOperServerTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : server_ttl
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.6

Field Name : serverOperDnsUpdateTime
Field Type : String
Field Status : current
Description : dns_update_time
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.5

Field Name : serverOperCreationType
Field Type : String
Field Status : current
Description : creation_type
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.4

Field Name : serverOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.3

Field Name : serverOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.2

Field Name : serverOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.2.1.1

Field Name : serverStatsTable
Field Type : TABLE
Field Status : current
Description : CGNV6LoggingServer from object 'cgnv6.server'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1

Field Name : serverStatsEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-SERVER-MIB_oid_list

Description : The serverStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1

Field Name : serverStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.7

Field Name : serverStatsRevPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : rev-pkt
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.6

Field Name : serverStatsFwdPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : fwd-pkt
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.5

Field Name : serverStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total-conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.4

Field Name : serverStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.3

Field Name : serverStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.2

Field Name : serverStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.1.1.1

Field Name : portOperDrsIpNatListNatPoolAddrListTable
Field Type : TABLE
Field Status : current
Description : RealServerPort from object 'cgnv6.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8

Field Name : portOperDrsIpNatListTable
Field Type : TABLE
Field Status : current
Description : RealServerPort from object 'cgnv6.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7

ACOS-CGNV6-SERVER-MIB_oid_list

Field Name : portOperDrsIpNatListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsIpNatList entry:drs-ip-nat-list
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1

Field Name : portOperDrsIpNatListPoolName
Field Type : String
Field Status : current
Description : pool_name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.8

Field Name : portOperDrsIpNatListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs_port
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.7

Field Name : portOperDrsIpNatListDrsName
Field Type : String
Field Status : current
Description : drs_name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.6

Field Name : portOperDrsIpNatListDrsIpNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.5

Field Name : portOperDrsIpNatListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.4

Field Name : portOperDrsIpNatListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.3

Field Name : portOperDrsIpNatListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.2

Field Name : portOperDrsIpNatListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.7.1.1

Field Name : portOperNatPoolAddrListTable
Field Type : TABLE
Field Status : current

ACOS-CGNV6-SERVER-MIB_oid_list

Description : RealServerPort from object 'cgnv6.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6

Field Name : portOperNatPoolAddrListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperNatPoolAddrList entry:nat-pool-addr-list
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1

Field Name : portOperNatPoolAddrListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.10

Field Name : portOperNatPoolAddrListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.9

Field Name : portOperNatPoolAddrListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.8

Field Name : portOperNatPoolAddrListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.7

Field Name : portOperNatPoolAddrListNatIp
Field Type : String
Field Status : current
Description : nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.6

Field Name : portOperNatPoolAddrListNatPoolAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.5

Field Name : portOperNatPoolAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.4

Field Name : portOperNatPoolAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.3

ACOS-CGNV6-SERVER-MIB_oid_list

Field Name : portOperNatPoolAddrListName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.2

Field Name : portOperNatPoolAddrListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.6.1.1

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListTable

Field Type : TABLE

Field Status : current

Description : RealServerPort from object 'cgnv6.server.port'

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The portOperDrsAutoNatListDrsAutoNatAddressList entry:drs-auto-nat-address-list

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListAllocFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : alloc_failed

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.14

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPortsFreedTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_freed_total

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.13

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPortsConsumedTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_consumed_total

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.12

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPortsConsumed

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_consumed

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.11

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListIpRr

Field Type : CounterBasedGauge64

Field Status : current

Description : ip_rr

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.10

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListHaGroupId

Field Type : CounterBasedGauge64

Field Status : current

ACOS-CGNV6-SERVER-MIB_oid_list

Description : ha_group_id

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.9

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListVrid

Field Type : CounterBasedGauge64

Field Status : current

Description : vrid

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.8

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListAutoNatIp

Field Type : String

Field Status : current

Description : auto_nat_ip

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.7

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListDrsAutoNatAddressListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.6

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListDrsAutoNatListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.5

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListProtocol

Field Type : String

Field Status : current

Description : protocol

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.4

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPort

Field Type : Integer32

Field Status : current

Description : port-number

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.3

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.2

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.5.1.1

Field Name : portOperDrsAutoNatListTable

Field Type : TABLE

Field Status : current

Description : RealServerPort from object 'cgnv6.server.port'

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4

ACOS-CGNV6-SERVER-MIB_oid_list

Field Name : portOperDrsAutoNatListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsAutoNatList entry:drs-auto-nat-list
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1

Field Name : portOperDrsAutoNatListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs_port
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.7

Field Name : portOperDrsAutoNatListDrsName
Field Type : String
Field Status : current
Description : drs_name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.6

Field Name : portOperDrsAutoNatListDrsAutoNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.5

Field Name : portOperDrsAutoNatListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.4

Field Name : portOperDrsAutoNatListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.3

Field Name : portOperDrsAutoNatListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.2

Field Name : portOperDrsAutoNatListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.4.1.1

Field Name : portOperAutoNatAddrListTable
Field Type : TABLE
Field Status : current
Description : RealServerPort from object 'cgnv6.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3

Field Name : portOperAutoNatAddrListEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-SERVER-MIB_oid_list

Description : The portOperAutoNatAddrList entry:auto-nat-addr-list
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1

Field Name : portOperAutoNatAddrListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.13

Field Name : portOperAutoNatAddrListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.12

Field Name : portOperAutoNatAddrListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.11

Field Name : portOperAutoNatAddrListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.10

Field Name : portOperAutoNatAddrListIpRr
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_rr
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.9

Field Name : portOperAutoNatAddrListHaGroupId
Field Type : CounterBasedGauge64
Field Status : current
Description : ha_group_id
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.8

Field Name : portOperAutoNatAddrListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.7

Field Name : portOperAutoNatAddrListAutoNatIp
Field Type : String
Field Status : current
Description : auto_nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.6

Field Name : portOperAutoNatAddrListAutoNatAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.5

ACOS-CGNV6-SERVER-MIB_oid_list

Field Name : portOperAutoNatAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.4

Field Name : portOperAutoNatAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.3

Field Name : portOperAutoNatAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.2

Field Name : portOperAutoNatAddrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.3.1.1

Field Name : portOperTable
Field Type : TABLE
Field Status : current
Description : RealServerPort from object 'cgnv6.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2

Field Name : portOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1

Field Name : portOperPoolName
Field Type : String
Field Status : current
Description : pool_name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.23

Field Name : portOperResvConn
Field Type : CounterBasedGauge64
Field Status : current
Description : resv_conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.22

Field Name : portOperAflowQueueSize
Field Type : CounterBasedGauge64
Field Status : current
Description : aflow_queue_size
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.21

Field Name : portOperAflowConnLimit
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-SERVER-MIB_oid_list

Description : aflow_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.20

Field Name : portOperSoftDownTime
Field Type : CounterBasedGauge64
Field Status : current
Description : soft_down_time
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.19

Field Name : portOperHmIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-index
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.18

Field Name : portOperHmKey
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-key
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.17

Field Name : portOperDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : disable
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.16

Field Name : portOperInbandHmReassignNum
Field Type : CounterBasedGauge64
Field Status : current
Description : inband_hm_reassign_num
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.15

Field Name : portOperEsRespTime
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_time
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.14

Field Name : portOperDiameterEnabled
Field Type : CounterBasedGauge64
Field Status : current
Description : diameter_enabled
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.13

Field Name : portOperDownTimeGracePeriod
Field Type : CounterBasedGauge64
Field Status : current
Description : down_time_grace_period
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.12

Field Name : portOperCurrentTime
Field Type : CounterBasedGauge64
Field Status : current
Description : current_time
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.11

ACOS-CGNV6-SERVER-MIB_oid_list

Field Name : portOperDownGracePeriodAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : down_grace_period_allowed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.10

Field Name : portOperCurrObserveRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_observe_rate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.9

Field Name : portOperSlowStartConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : slow_start_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.8

Field Name : portOperConnRateUnit
Field Type : String
Field Status : current
Description : conn_rate_unit
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.7

Field Name : portOperCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.6

Field Name : portOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.5

Field Name : portOperProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.4

Field Name : portOperPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.3

Field Name : portOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.2

Field Name : portOperSlotId
Field Type : Integer32
Field Status : current

ACOS-CGNV6-SERVER-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.2.1.1

Field Name : portStatsTable

Field Type : TABLE

Field Status : current

Description : RealServerPort from object 'cgnv6.server.port'

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1

Field Name : portStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The portStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1

Field Name : portStatsSlowestRspTime

Field Type : CounterBasedGauge64

Field Status : current

Description : slowest_rsp_time

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.28

Field Name : portStatsFastestRspTime

Field Type : CounterBasedGauge64

Field Status : current

Description : fastest_rsp_time

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.27

Field Name : portStatsResponseTime

Field Type : CounterBasedGauge64

Field Status : current

Description : response_time

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.26

Field Name : portStatsTotalRevPktsInspectedGoodStatusCode

Field Type : CounterBasedGauge64

Field Status : current

Description : total_rev_pkts_inspected_good_status_code

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.25

Field Name : portStatsTotalRevPktsInspected

Field Type : CounterBasedGauge64

Field Status : current

Description : total_rev_pkts_inspected

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.24

Field Name : portStatsEsRespInvalidHttp

Field Type : CounterBasedGauge64

Field Status : current

Description : es_resp_invalid_http

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.23

Field Name : portStatsEsRespCount

Field Type : CounterBasedGauge64

Field Status : current

Description : es_resp_count

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.22

ACOS-CGNV6-SERVER-MIB_oid_list

Field Name : portStatsEsReqCount
Field Type : CounterBasedGauge64
Field Status : current
Description : es_req_count
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.21

Field Name : portStatsEsRespOther
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_other
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.20

Field Name : portStatsEsResp500
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_500
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.19

Field Name : portStatsEsResp400
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_400
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.18

Field Name : portStatsEsResp300
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_300
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.17

Field Name : portStatsEsResp200
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_200
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.16

Field Name : portStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.15

Field Name : portStatsLastTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : last_total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.14

Field Name : portStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.13

Field Name : portStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-SERVER-MIB_oid_list

Description : total_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.12

Field Name : portStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.11

Field Name : portStatsTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.10

Field Name : portStatsTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.9

Field Name : portStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.8

Field Name : portStatsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.7

Field Name : portStatsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_req
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.6

Field Name : portStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.5

Field Name : portStatsProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.4

Field Name : portStatsPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.3

ACOS-CGNV6-SERVER-MIB_oid_list

Field Name : portStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.2

Field Name : portStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.1.1.1

Field Name : portOperDrsIpNatListNatPoolAddrListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsIpNatListNatPoolAddrList entry:nat-pool-addr-list
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1

Field Name : portOperDrsIpNatListNatPoolAddrListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.11

Field Name : portOperDrsIpNatListNatPoolAddrListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.10

Field Name : portOperDrsIpNatListNatPoolAddrListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.9

Field Name : portOperDrsIpNatListNatPoolAddrListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.8

Field Name : portOperDrsIpNatListNatPoolAddrListNatIp
Field Type : String
Field Status : current
Description : nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.7

Field Name : portOperDrsIpNatListNatPoolAddrListNatPoolAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.6

Field Name : portOperDrsIpNatListNatPoolAddrListDrsIpNatListListId
Field Type : Integer32
Field Status : current

ACOS-CGNV6-SERVER-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.5

Field Name : portOperDrsIpNatListNatPoolAddrListProtocol

Field Type : String

Field Status : current

Description : protocol

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.4

Field Name : portOperDrsIpNatListNatPoolAddrListPort

Field Type : Integer32

Field Status : current

Description : port-number

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.3

Field Name : portOperDrsIpNatListNatPoolAddrListName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.2

Field Name : portOperDrsIpNatListNatPoolAddrListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.409.1.4.8.1.1

ACOS-CGNV6-SERVICE-GROUP-MIB_oid_list

Field Name : serviceGroupOperSgmListTable
Field Type : TABLE
Field Status : current
Description : ServiceGroup from object 'cgnv6.service-group'
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3

Field Name : serviceGroupOperSgmListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceGroupOperSgmList entry:sgm-list
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3.1

Field Name : serviceGroupOperSgmListSgmPort
Field Type : CounterBasedGauge64
Field Status : current
Description : sgm-port
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3.1.5

Field Name : serviceGroupOperSgmListSgmName
Field Type : String
Field Status : current
Description : sgm-name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3.1.4

Field Name : serviceGroupOperSgmListSgmListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3.1.3

Field Name : serviceGroupOperSgmListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3.1.2

Field Name : serviceGroupOperSgmListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.3.1.1

Field Name : serviceGroupOperTable
Field Type : TABLE
Field Status : current
Description : ServiceGroup from object 'cgnv6.service-group'
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2

Field Name : serviceGroupOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceGroupOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1

Field Name : serviceGroupOperFilter
Field Type : String
Field Status : current

ACOS-CGNV6-SERVICE-GROUP-MIB_oid_list

Description : filter

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.14

Field Name : serviceGroupOperPriAffinityPriority

Field Type : CounterBasedGauge64

Field Status : current

Description : pri_affinity_priority

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.13

Field Name : serviceGroupOperHmDsrEnableAllVip

Field Type : CounterBasedGauge64

Field Status : current

Description : hm_dsr_enable_all_vip

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.12

Field Name : serviceGroupOperStatelessType

Field Type : CounterBasedGauge64

Field Status : current

Description : stateless_type

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.11

Field Name : serviceGroupOperStatelessState

Field Type : CounterBasedGauge64

Field Status : current

Description : stateless_state

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.10

Field Name : serviceGroupOperStatelessCurrentUsage

Field Type : CounterBasedGauge64

Field Status : current

Description : stateless_current_usage

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.9

Field Name : serviceGroupOperStatelessCurrentRate

Field Type : CounterBasedGauge64

Field Status : current

Description : stateless_current_rate

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.8

Field Name : serviceGroupOperServersTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : servers_total

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.7

Field Name : serviceGroupOperServersDisable

Field Type : CounterBasedGauge64

Field Status : current

Description : servers_disable

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.6

Field Name : serviceGroupOperServersDown

Field Type : CounterBasedGauge64

Field Status : current

Description : servers_down

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.5

ACOS-CGNV6-SERVICE-GROUP-MIB_oid_list

Field Name : serviceGroupOperServersUp
Field Type : CounterBasedGauge64
Field Status : current
Description : servers_up
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.4

Field Name : serviceGroupOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.3

Field Name : serviceGroupOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.2

Field Name : serviceGroupOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.2.1.1

Field Name : serviceGroupStatsTable
Field Type : TABLE
Field Status : current
Description : ServiceGroup from object 'cgnv6.service-group'
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1

Field Name : serviceGroupStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceGroupStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1.1

Field Name : serviceGroupStatsServicePeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : service_peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1.1.5

Field Name : serviceGroupStatsServerSelectionFailReset
Field Type : CounterBasedGauge64
Field Status : current
Description : server_selection_fail_reset
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1.1.4

Field Name : serviceGroupStatsServerSelectionFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : server_selection_fail_drop
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1.1.3

Field Name : serviceGroupStatsName
Field Type : String
Field Status : current

ACOS-CGNV6-SERVICE-GROUP-MIB_oid_list

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1.1.2

Field Name : serviceGroupStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.1.1.1

Field Name : memberOperAltListTable

Field Type : TABLE

Field Status : current

Description : ServiceGroupMember from object 'cgnv6.service-group.member'

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4

Field Name : memberOperDrsListTable

Field Type : TABLE

Field Status : current

Description : ServiceGroupMember from object 'cgnv6.service-group.member'

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3

Field Name : memberOperDrsListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The memberOperDrsList entry:drs-list

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1

Field Name : memberOperDrsListDrsSrspTime

Field Type : CounterBasedGauge64

Field Status : current

Description : drs-srsp-time

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.25

Field Name : memberOperDrsListDrsFrspTime

Field Type : CounterBasedGauge64

Field Status : current

Description : drs-frsp-time

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.24

Field Name : memberOperDrsListDrsRspTime

Field Type : CounterBasedGauge64

Field Status : current

Description : drs-rsp-time

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.23

Field Name : memberOperDrsListDrsPeakConn

Field Type : CounterBasedGauge64

Field Status : current

Description : drs-peak-conn

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.22

Field Name : memberOperDrsListDrsFwdBts

Field Type : CounterBasedGauge64

Field Status : current

Description : drs-fwd-bts

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.21

ACOS-CGNV6-SERVICE-GROUP-MIB_oid_list

Field Name : memberOperDrsListDrsRevBts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-rev-bts
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.20

Field Name : memberOperDrsListDrsFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-fwd-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.19

Field Name : memberOperDrsListDrsRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-rev-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.18

Field Name : memberOperDrsListDrsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-total-req-succ
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.17

Field Name : memberOperDrsListDrsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-total-req
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.16

Field Name : memberOperDrsListDrsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-req
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.15

Field Name : memberOperDrsListDrsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-total-conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.14

Field Name : memberOperDrsListDrsPersConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-pers-conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.13

Field Name : memberOperDrsListDrsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.12

Field Name : memberOperDrsListDrsPriority
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-SERVICE-GROUP-MIB_oid_list

Description : drs-priority
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.11

Field Name : memberOperDrsListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-port
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.10

Field Name : memberOperDrsListDrsHmIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-hm-index
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.9

Field Name : memberOperDrsListDrsHmKey
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-hm-key
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.8

Field Name : memberOperDrsListDrsState
Field Type : String
Field Status : current
Description : drs-state
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.7

Field Name : memberOperDrsListDrsName
Field Type : String
Field Status : current
Description : drs-name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.6

Field Name : memberOperDrsListDrsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.5

Field Name : memberOperDrsListPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.4

Field Name : memberOperDrsListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.3

Field Name : memberOperDrsListServiceGroupName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.2

ACOS-CGNV6-SERVICE-GROUP-MIB_oid_list

Field Name : memberOperDrsListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.3.1.1

Field Name : memberOperTable
Field Type : TABLE
Field Status : current
Description : ServiceGroupMember from object 'cgnv6.service-group.member'
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2

Field Name : memberOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The memberOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1

Field Name : memberOperHmIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-index
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.7

Field Name : memberOperHmKey
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-key
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.6

Field Name : memberOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.5

Field Name : memberOperPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.4

Field Name : memberOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.3

Field Name : memberOperServiceGroupName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.2

Field Name : memberOperSlotId
Field Type : Integer32
Field Status : current

ACOS-CGNV6-SERVICE-GROUP-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.2.1.1

Field Name : memberStatsTable

Field Type : TABLE

Field Status : current

Description : ServiceGroupMember from object 'cgnv6.service-group.member'

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1

Field Name : memberStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The memberStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1

Field Name : memberStatsStateFlaps

Field Type : CounterBasedGauge64

Field Status : current

Description : state_flaps

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.24

Field Name : memberStatsCurrConnOverflow

Field Type : CounterBasedGauge64

Field Status : current

Description : curr_conn_overflow

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.23

Field Name : memberStatsTotalSslConn

Field Type : CounterBasedGauge64

Field Status : current

Description : total_ssl_conn

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.22

Field Name : memberStatsCurrSslConn

Field Type : CounterBasedGauge64

Field Status : current

Description : curr_ssl_conn

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.21

Field Name : memberStatsSlowestRspTime

Field Type : CounterBasedGauge64

Field Status : current

Description : slowest_rsp_time

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.20

Field Name : memberStatsFastestRspTime

Field Type : CounterBasedGauge64

Field Status : current

Description : fastest_rsp_time

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.19

Field Name : memberStatsResponseTime

Field Type : CounterBasedGauge64

Field Status : current

Description : response_time

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.18

ACOS-CGNV6-SERVICE-GROUP-MIB_oid_list

Field Name : memberStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.17

Field Name : memberStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.16

Field Name : memberStatsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.15

Field Name : memberStatsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_req
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.14

Field Name : memberStatsTotalRevPktsInspectedStatusCodeNon5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected_status_code_non_5xx
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.13

Field Name : memberStatsTotalRevPktsInspectedStatusCode2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected_status_code_2xx
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.12

Field Name : memberStatsTotalRevPktsInspected
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.11

Field Name : memberStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.10

Field Name : memberStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.9

Field Name : memberStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-SERVICE-GROUP-MIB_oid_list

Description : total_rev_bytes

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.8

Field Name : memberStatsTotalFwdPkts

Field Type : CounterBasedGauge64

Field Status : current

Description : total_fwd_pkts

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.7

Field Name : memberStatsTotalFwdBytes

Field Type : CounterBasedGauge64

Field Status : current

Description : total_fwd_bytes

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.6

Field Name : memberStatsCurrConn

Field Type : CounterBasedGauge64

Field Status : current

Description : curr_conn

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.5

Field Name : memberStatsPort

Field Type : Integer32

Field Status : current

Description : port

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.4

Field Name : memberStatsName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.3

Field Name : memberStatsServiceGroupName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.2

Field Name : memberStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.1.1.1

Field Name : memberOperAltListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The memberOperAltList entry:alt-list

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1

Field Name : memberOperAltListAltPeakConn

Field Type : CounterBasedGauge64

Field Status : current

Description : alt-peak-conn

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.13

ACOS-CGNV6-SERVICE-GROUP-MIB_oid_list

Field Name : memberOperAltListAltFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-fwd-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.12

Field Name : memberOperAltListAltRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-rev-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.11

Field Name : memberOperAltListAltTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-total-conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.10

Field Name : memberOperAltListAltCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.9

Field Name : memberOperAltListAltState
Field Type : String
Field Status : current
Description : alt-state
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.8

Field Name : memberOperAltListAltPort
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-port
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.7

Field Name : memberOperAltListAltName
Field Type : String
Field Status : current
Description : alt-name
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.6

Field Name : memberOperAltListAltListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.5

Field Name : memberOperAltListPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.4

Field Name : memberOperAltListName
Field Type : String
Field Status : current

ACOS-CGNV6-SERVICE-GROUP-MIB_oid_list

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.3

Field Name : memberOperAltListServiceGroupName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.2

Field Name : memberOperAltListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.410.1.4.4.1.1

ACOS-CGNV6-SHARED-SERVICE-GROUP-MIB_oid_list

Field Name : sharedServiceGroupOperSharedServiceGroupListTable

Field Type : TABLE

Field Status : current

Description : CGNV6SharedServiceGroup from object 'cgnv6.shared-service-group'

OID : 1.3.6.1.4.1.22610.2.4.8.412.1.2

Field Name : sharedServiceGroupOperSharedServiceGroupListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The sharedServiceGroupOperSharedServiceGroupList entry:shared-service-group-list

OID : 1.3.6.1.4.1.22610.2.4.8.412.1.2.1

Field Name : sharedServiceGroupOperSharedServiceGroupListServiceGroupName

Field Type : String

Field Status : current

Description : service-group-name

OID : 1.3.6.1.4.1.22610.2.4.8.412.1.2.1.3

Field Name : sharedServiceGroupOperSharedServiceGroupListSharedServiceGroupListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.412.1.2.1.2

Field Name : sharedServiceGroupOperSharedServiceGroupListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.412.1.2.1.1

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6MapTranslationDomainSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1

Field Name : cgnv6MapTranslationDomainSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1

Field Name : activeDhcpv6Leases
Field Type : CounterBasedGauge64
Field Status : current
Description : Active DHCPv6 leases
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.16

Field Name : helperCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Helper Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.15

Field Name : bmrPrefixrulesConfigured
Field Type : CounterBasedGauge64
Field Status : current
Description : BMR prefix rules configured
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.18

Field Name : interfaceNotConfigured
Field Type : CounterBasedGauge64
Field Status : current
Description : Interfaces not Configured Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.14

Field Name : fragIcmpSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Packet Too Big Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.13

Field Name : packetMtuExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Exceeded MTU
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.12

Field Name : outboundDestUnreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv4 Destination Address Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.11

Field Name : outboundRevLookupFailed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Outbound IPv6 Reverse Route Lookup Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.10

Field Name : outboundAddrValidationFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Outbound IPv6 Source Address Validation Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.9

Field Name : outboundFragPacketReceived

Field Type : CounterBasedGauge64

Field Status : current

Description : Outbound IPv6 Fragment Packets Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.8

Field Name : outboundPacketReceived

Field Type : CounterBasedGauge64

Field Status : current

Description : Outbound IPv6 Packets Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.7

Field Name : inboundDestUnreachable

Field Type : CounterBasedGauge64

Field Status : current

Description : Inbound IPv6 Destination Address Unreachable

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.6

Field Name : inboundRevLookupFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Inbound IPv4 Reverse Route Lookup Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.5

Field Name : inboundAddrPortValidationFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Inbound IPv4 Destination Address Port Validation Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.4

Field Name : inboundFragPacketReceived

Field Type : CounterBasedGauge64

Field Status : current

Description : Inbound IPv4 Fragment Packets Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.3

Field Name : inboundPacketReceived

Field Type : CounterBasedGauge64

Field Status : current

Description : Inbound IPv4 Packets Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.2

Field Name : name

Field Type : String

Field Status : current

Description : MAP-T domain name

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.1.2.1.1.1.1

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6MapEncapsulationDomainSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1

Field Name : cgnv6MapEncapsulationDomainSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1

Field Name : activeDhcpv6Leases
Field Type : CounterBasedGauge64
Field Status : current
Description : Active DHCPv6 leases
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.16

Field Name : helperCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Helper Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.15

Field Name : bmrPrefixrulesConfigured
Field Type : CounterBasedGauge64
Field Status : current
Description : BMR prefix rules configured
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.18

Field Name : interfaceNotConfigured
Field Type : CounterBasedGauge64
Field Status : current
Description : Interfaces not Configured Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.14

Field Name : fragIcmpSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Packet Too Big Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.13

Field Name : packetMtuExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Exceeded MTU
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.12

Field Name : outboundDestUnreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv4 Destination Address Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1.11

Field Name : outboundRevLookupFailed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Outbound IPv6 Reverse Route Lookup Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.10

Field Name : outboundAddrValidationFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Outbound IPv6 Source Address Validation Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.9

Field Name : outboundFragPacketReceived

Field Type : CounterBasedGauge64

Field Status : current

Description : Outbound IPv6 Fragment Packets Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.8

Field Name : outboundPacketReceived

Field Type : CounterBasedGauge64

Field Status : current

Description : Outbound IPv6 Packets Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.7

Field Name : inboundDestUnreachable

Field Type : CounterBasedGauge64

Field Status : current

Description : Inbound IPv6 Destination Address Unreachable

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.6

Field Name : inboundRevLookupFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Inbound IPv4 Reverse Route Lookup Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.5

Field Name : inboundAddrPortValidationFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Inbound IPv4 Destination Address Port Validation Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.4

Field Name : inboundFragPacketReceived

Field Type : CounterBasedGauge64

Field Status : current

Description : Inbound IPv4 Fragment Packets Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.3

Field Name : inboundPacketReceived

Field Type : CounterBasedGauge64

Field Status : current

Description : Inbound IPv4 Packets Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.2

Field Name : name

Field Type : String

Field Status : current

Description : MAP-E domain name

OID : 1.3.6.1.4.1.22610.2.4.10.115.32.2.2.1.1.1

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : drop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.15

Field Name : cache
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.14

Field Name : adjust
Field Type : CounterBasedGauge64
Field Status : current
Description : Translated
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.13

Field Name : respLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Local
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.12

Field Name : respEmpty
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Empty
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.11

Field Name : respErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.10

Field Name : respChg
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Changed
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.9

Field Name : respBadQr
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Bad Query
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.8

Field Name : respBadPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Bad Packet
OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.7

Field Name : resp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Response

OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.6

Field Name : queryPassive

Field Type : CounterBasedGauge64

Field Status : current

Description : Query Passive

OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.5

Field Name : queryParallel

Field Type : CounterBasedGauge64

Field Status : current

Description : Query Parallel

OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.4

Field Name : queryChg

Field Type : CounterBasedGauge64

Field Status : current

Description : Query Changed

OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.3

Field Name : queryBadPkt

Field Type : CounterBasedGauge64

Field Status : current

Description : Query Bad Packet

OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.2

Field Name : query

Field Type : CounterBasedGauge64

Field Status : current

Description : Query

OID : 1.3.6.1.4.1.22610.2.4.10.115.31.1.1

Field Name : noQueue

Field Type : CounterBasedGauge64

Field Status : current

Description : No Queue

OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.19

Field Name : headerRemovalFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Buff Removal Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.18

Field Name : headerInsertionFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Buff Insertion Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.17

Field Name : buffSpiltFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Buff Split Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.16

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : buffResent
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Resent from Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.15

Field Name : outOfOrderDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Out-of-Order Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.14

Field Name : queueLenExceedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Queue Length Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.13

Field Name : outOfMemoryDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-of-Memory Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.12

Field Name : radiusResponseDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Response Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.11

Field Name : radiusResponseReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Response Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.10

Field Name : radiusRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Request Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.9

Field Name : radiusRequestSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Request Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.8

Field Name : radiusQueryFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : MSISDN Query Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.7

Field Name : radiusQuerySucceed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : MSISDN Query Succeed

OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.6

Field Name : queuedSessionTooMany

Field Type : CounterBasedGauge64

Field Status : current

Description : Queued Session Exceed Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.5

Field Name : requestInsertMsisdnUnavailable

Field Type : CounterBasedGauge64

Field Status : current

Description : Inserted MSISDN is 0000 (MSISDN Unavailable)

OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.4

Field Name : requestInsertClientIpPerformed

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP Client IP Insertion Performed

OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.3

Field Name : requestInsertMsisdnPerformed

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP MSISDN Insertion Performed

OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.2

Field Name : requestProcessed

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP Request Processed

OID : 1.3.6.1.4.1.22610.2.4.10.115.30.1.1

Field Name : errorIpMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : ICMP IP address mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.37

Field Name : errorToPoolDropV6

Field Type : CounterBasedGauge64

Field Status : current

Description : Error to IPv6 Pool Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.36

Field Name : echoToPoolDropV6

Field Type : CounterBasedGauge64

Field Status : current

Description : Ping6 to Pool Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.35

Field Name : echoToPoolReplyV6

Field Type : CounterBasedGauge64

Field Status : current

Description : Ping6 to Pool Reply

OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.34

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : errorToPoolDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Error to Pool Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.33

Field Name : echoToPoolDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Ping to Pool Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.32

Field Name : echoToPoolReply
Field Type : CounterBasedGauge64
Field Status : current
Description : Ping to Pool Reply
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.31

Field Name : staticNat
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Static NAT
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.30

Field Name : icmpv6ToIcmpv6UnknownL4
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMPv6 Embedded Unknown L4 Protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.29

Field Name : icmpv6ToIcmpUnknownL4
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMP Embedded Unknown L4 Protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.28

Field Name : icmpToIcmpv6UnknownL4
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMPv6 Embedded Unknown L4 Protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.27

Field Name : icmpToIcmpUnknownL4
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Embedded Unknown L4 Protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.26

Field Name : encapCrossCpuPreprocessErr
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Embedded Cross CPU Preprocess Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.25

Field Name : encapCrossCpuNoMatch
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : ICMP Embedded Cross CPU No Matching Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.24

Field Name : icmpv6ToIcmpv6Err
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMPv6 Conversion Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.23

Field Name : icmpv6ToIcmpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMP Conversion Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.22

Field Name : icmpToIcmpv6Err
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMPv6 Conversion Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.21

Field Name : icmpToIcmpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMP Conversion Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.20

Field Name : cgnv6Icmp46BadEncapIpHeaderLen
Field Type : CounterBasedGauge64
Field Status : current
Description : 4to6 Bad Encapsulated IP Header Length
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.19

Field Name : cgnv6Icmp46NoPrefixForIpv4
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Reverse No Prefix Match for IPv4
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.18

Field Name : cgnv6Icmp46UnknownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Reverse Known ICMPv6 Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.17

Field Name : cgnv6Icmp46KnownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Reverse Known ICMP Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.16

Field Name : cgnv6Icmp64MidpointHop
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Forward Unknown Source Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.15

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6Icmp64UnknownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Forward Unknown ICMPv6 Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.14

Field Name : cgnv6Icmp64KnownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Forward Known ICMPv6 Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.13

Field Name : icmpv6BadType
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Embedded ICMPv6 Type
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.12

Field Name : icmpBadType
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Embedded ICMP Type
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.11

Field Name : icmpv6ToIcmpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMPv6 Conversion
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.10

Field Name : cgnv6IcmpIcmpv6ToIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMP Conversion
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.9

Field Name : cgnv6IcmpIcmpToIcmpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMPv6 Conversion
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.8

Field Name : icmpToIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMP Conversion
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.7

Field Name : icmpv6NoSessionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 No Matching Session Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.6

Field Name : icmpv6NoPortInfo
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : ICMPv6 Port Info Not Included
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.5

Field Name : icmpv6UnknownType
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Unknown Type
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.4

Field Name : icmpNoSessionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP No Matching Session Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.3

Field Name : icmpNoPortInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Port Info Not Included
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.2

Field Name : icmpUnknownType
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Unknown Type
OID : 1.3.6.1.4.1.22610.2.4.10.115.29.1.1

Field Name : fwNextActionIncorrectDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : FW Next Action Incorrect Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.63

Field Name : natRangeListAclPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : Nat range-list ACL permit
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.62

Field Name : natRangeListAclDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : Nat range-list ACL deny
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.61

Field Name : fwZoneMismatchReroutingDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Rerouting Zone Mismatch Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.60

Field Name : l3Ipv6DstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 L3 Destination Invalid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.59

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : l3Ipv6SrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 L3 Source Invalid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.58

Field Name : l3IpDstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 L3 Destination Invalid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.57

Field Name : l3IpSrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 L3 Source Invalid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.56

Field Name : dstNatPoolNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst NAT Pool Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.55

Field Name : srcNatPoolNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Src NAT Pool Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.54

Field Name : ipUnknownProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : Process IP Unknown
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.53

Field Name : fwMatchNoRuleDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Firewall Matched No CGNV6 Rule Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.52

Field Name : processError
Field Type : CounterBasedGauge64
Field Status : current
Description : Process Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.51

Field Name : processContinue
Field Type : CounterBasedGauge64
Field Status : current
Description : Process Continue
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.50

Field Name : processSpecial
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Process Special

OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.49

Field Name : preprocessError

Field Type : CounterBasedGauge64

Field Status : current

Description : Preprocess Error

OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.48

Field Name : processL4

Field Type : CounterBasedGauge64

Field Status : current

Description : Process L4

OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.47

Field Name : staticNatFree

Field Type : CounterBasedGauge64

Field Status : current

Description : Static NAT Free

OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.46

Field Name : staticNatAlloc

Field Type : CounterBasedGauge64

Field Status : current

Description : Static NAT Alloc

OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.45

Field Name : tcpRstLoopDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : RST Loop Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.44

Field Name : invalidNat64TranslatedAddr

Field Type : CounterBasedGauge64

Field Status : current

Description : Invalid NAT64 Translated IPv4 Address

OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.43

Field Name : dstNatNeededDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Destination NAT Needed Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.42

Field Name : staticNatFastSetupErr

Field Type : CounterBasedGauge64

Field Status : current

Description : Static NAT Fast Setup Error

OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.41

Field Name : staticNatFastSetup

Field Type : CounterBasedGauge64

Field Status : current

Description : Static NAT Fast Setup Attempt

OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.40

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fixedNatFastSetupMtuTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup MTU Too Small
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.39

Field Name : fixedNatFastSetupDelayedErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup Delayed Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.38

Field Name : fixedNatDsliteFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.37

Field Name : fixedNatDsliteFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.36

Field Name : fixedNat64FastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.35

Field Name : fixedNat64FastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.34

Field Name : fixedNat44FastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.33

Field Name : fixedNat44FastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Fast Setup Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.32

Field Name : fastSetupMtuTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Fast Setup MTU Too Small
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.31

Field Name : fastSetupDelayedErr
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Fast Setup Delayed Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.30

Field Name : dsliteFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Fast Setup Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.29

Field Name : dsliteFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Fast Setup Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.28

Field Name : nat64FastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Fast Setup Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.27

Field Name : nat64FastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Fast Setup Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.26

Field Name : lsnFastSetupErr
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fast Setup Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.25

Field Name : lsnFastSetup
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fast Setup Attempt
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.24

Field Name : crossCpuAlgGrePreprocessErr
Field Type : CounterBasedGauge64
Field Status : current
Description : ALG GRE Cross CPU Preprocess Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.23

Field Name : crossCpuAlgGreNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : ALG GRE Cross CPU No Matching Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.22

Field Name : ttlExceededSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP TTL Exceeded Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.21

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : outOfStateDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Out of State packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.20

Field Name : icmpv6ReplySent
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Echo Reply Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.19

Field Name : icmpReplySent
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Echo Reply Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.18

Field Name : specialIpv6NoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Stateless IPv6 No Forward Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.17

Field Name : specialIpv4NoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Stateless IPv4 No Forward Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.16

Field Name : badL3Protocol
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Layer 3 Protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.15

Field Name : rateDropResetUnkn
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate Drop reset
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.14

Field Name : ipv6DstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Destination Not Valid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.13

Field Name : ipv6SrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Source Not Valid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.12

Field Name : ipDstInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : IPv4 Destination Not Valid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.11

Field Name : ipSrcInvalidUnicast
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Source Not Valid Unicast
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.10

Field Name : ipipTruncated
Field Type : CounterBasedGauge64
Field Status : current
Description : IPIP Truncated Packet
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.9

Field Name : icmpReplyNoSessionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Reply No Session Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.8

Field Name : icmpHostUnreachableSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Host Unreachable Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.7

Field Name : icmpFilteredSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Administratively Filtered Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.6

Field Name : ipipIcmpReplySent
Field Type : CounterBasedGauge64
Field Status : current
Description : IPIP ICMP Echo Reply Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.5

Field Name : tcpRstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP RST Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.4

Field Name : outOfSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Session Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.3

Field Name : noRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Reverse Route for Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.2

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : noFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Forward Route for Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.28.1.1

Field Name : iddosL4EntryDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : iDDoS L4 Entry Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.83

Field Name : iddosL4EntryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : iDDoS L4 Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.82

Field Name : iddosL3EntryDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : iDDoS L3 Entry Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.81

Field Name : iddosL3EntryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : iDDoS L3 Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.80

Field Name : httpSpmFreeType4
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 4 free
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.79

Field Name : httpSpmFreeType3
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 3 free
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.78

Field Name : httpSpmFreeType2
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 2 free
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.77

Field Name : httpSpmFreeType1
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 1 free
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.76

Field Name : httpSpmFreeType0
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : HTTP Conn SPM Type 0 free
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.75

Field Name : httpSpmAllocType4
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 4 allocate
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.74

Field Name : httpSpmAllocType3
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 3 allocate
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.73

Field Name : httpSpmAllocType2
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 2 allocate
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.72

Field Name : httpSpmAllocType1
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 1 allocate
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.71

Field Name : httpSpmAllocType0
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Conn SPM Type 0 allocate
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.70

Field Name : httpMfree
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP mem free
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.69

Field Name : httpMalloc
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP mem allocate
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.68

Field Name : httpFragMergeFailedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP frag merge failed dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.67

Field Name : httpAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Request Info Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.66

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : httpOutOfOrderDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP out-of-order dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.65

Field Name : logMessageTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Log message too long
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.64

Field Name : portBlockAccountingAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocation Accounting Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.63

Field Name : portBlockAccountingFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocation Accounting Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.62

Field Name : udpPortBatchInterimUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Batch Interim Updated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.61

Field Name : tcpPortBatchInterimUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Batch Interim Updated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.60

Field Name : interimUpdateNoBuffRetried
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocation Interim Update Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.59

Field Name : interimUpdateMemoryFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocation Interim Update Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.58

Field Name : interimUpdateTerminated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocation Interim Update Terminated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.57

Field Name : interimUpdateScheduleFailed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Port Allocation Interim Update Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.56

Field Name : interimUpdateScheduled
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocation Interim Update Scheduled
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.55

Field Name : ipv6FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Fragmentation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.54

Field Name : ipv6FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Fragmentation Applied
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.53

Field Name : ipv4FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragmentation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.52

Field Name : ipv4FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragmentation Applied
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.51

Field Name : connTcpCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Connection Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.50

Field Name : rtspPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : RTSP UDP Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.49

Field Name : rtspPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : RTSP UDP Port Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.48

Field Name : addMsgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Add Message to Buffer Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.47

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : outOfBuffers
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Buffers
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.46

Field Name : reducedLogsByDestination
Field Type : CounterBasedGauge64
Field Status : current
Description : Reduced Logs by Destination Protocol and Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.45

Field Name : httpRequestLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Request Logged
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.44

Field Name : udpPortOverloadingFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.43

Field Name : udpPortOverloadingAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.42

Field Name : tcpPortOverloadingFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.41

Field Name : tcpPortOverloadingAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.40

Field Name : connTcpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Connection Lost
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.39

Field Name : connTcpEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Connection Established
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.38

Field Name : logDropped
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Log Packets Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.37

Field Name : logSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Log Packets Sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.36

Field Name : enhancedUserLog

Field Type : CounterBasedGauge64

Field Status : current

Description : Enhanced User Log

OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.35

Field Name : fixedNatInterimUpdated

Field Type : CounterBasedGauge64

Field Status : current

Description : Fixed NAT Interim Updated

OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.34

Field Name : fixedNatPeriodicConfigLogged

Field Type : CounterBasedGauge64

Field Status : current

Description : Fixed NAT Disabled Config Logs Sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.33

Field Name : fixedNatPeriodicConfigLogsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Fixed NAT Disabled Configs Logged

OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.32

Field Name : fixedNatDisableConfigLogsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Fixed NAT Periodic Config Logs Sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.31

Field Name : fixedNatDisableConfigLogged

Field Type : CounterBasedGauge64

Field Status : current

Description : Fixed NAT Periodic Configs Logged

OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.30

Field Name : fixedNatUserPorts

Field Type : CounterBasedGauge64

Field Status : current

Description : Fixed NAT Inside User Port Mapping

OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.29

Field Name : espResourceFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : ESP Resource Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.28

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : espResourceAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Resource Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.27

Field Name : espSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.26

Field Name : espSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.25

Field Name : greResourceFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Resource Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.24

Field Name : greResourceAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Resource Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.23

Field Name : greSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.22

Field Name : cgnv6LoggingGreSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.21

Field Name : icmpv6ResourceFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPV6 Resource Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.20

Field Name : icmpv6ResourceAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPV6 Resource Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.19

Field Name : icmpv6SessionDeleted
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : ICMPV6 Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.18

Field Name : icmpv6SessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPV6 Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.17

Field Name : icmpResourceFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Resource Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.16

Field Name : icmpResourceAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Resource Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.15

Field Name : icmpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.14

Field Name : icmpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.13

Field Name : udpPortBatchFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Batch Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.12

Field Name : udpPortBatchAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Batch Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.11

Field Name : udpPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.10

Field Name : udpPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.9

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : udpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.8

Field Name : udpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.7

Field Name : tcpPortBatchFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Batch Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.6

Field Name : tcpPortBatchAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Batch Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.5

Field Name : tcpPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.4

Field Name : tcpPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.3

Field Name : tcpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.2

Field Name : tcpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.27.1.1

Field Name : cgnv6Nptv6DomainSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1

Field Name : cgnv6Nptv6DomainSEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1

Field Name : packetsDestUnreachable

Field Type : CounterBasedGauge64

Field Status : current

Description : Packets Destination Unreachable

OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.7

Field Name : inboundPacketsNoMap

Field Type : CounterBasedGauge64

Field Status : current

Description : Inbound Packets No Map

OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.6

Field Name : addressNotValidForTranslation

Field Type : CounterBasedGauge64

Field Status : current

Description : Address Not Valid For Translation

OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.5

Field Name : hairpinPackets

Field Type : CounterBasedGauge64

Field Status : current

Description : Hairpin Packets

OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.4

Field Name : inboundPackets

Field Type : CounterBasedGauge64

Field Status : current

Description : Inbound Packets

OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.3

Field Name : outboundPackets

Field Type : CounterBasedGauge64

Field Status : current

Description : Outbound Packets

OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.2

Field Name : name

Field Type : String

Field Status : current

Description : Name of NPTv6 domain

OID : 1.3.6.1.4.1.22610.2.4.10.115.26.2.1.1.1.1

Field Name : interBoardPkts

Field Type : CounterBasedGauge64

Field Status : current

Description : PCP Inter board packets

OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.41

Field Name : mapFilterDeny

Field Type : CounterBasedGauge64

Field Status : current

Description : PCP MAP Filter Deny Inbound

OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.40

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : mapFilterSet
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP MAP Filter Set
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.39

Field Name : clientNonceMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Client Nonce Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.38

Field Name : fullconeExtReuse
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Fullcone Extension Reuse
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.37

Field Name : fullconeExtNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Fullcone Extension Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.36

Field Name : fullconeExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Fullcone Extension Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.35

Field Name : fullconeExtFree
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Fullcone Extension Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.34

Field Name : fullconeExtAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Fullcone Extension Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.33

Field Name : haSyncEpochRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Sync PCP Epoch Recv
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.32

Field Name : haSyncEpochSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Sync PCP Epoch Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.31

Field Name : unsolAnceSentFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Unsolicited Announce Send Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.30

Field Name : unsolAnceSentSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsolicited Announce Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.29

Field Name : internalErrorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Internal Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.28

Field Name : l4ProcessError
Field Type : CounterBasedGauge64
Field Status : current
Description : L3/L4 Process Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.27

Field Name : pktNotFromNatInside
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Dropped For Not Coming From NAT Inside
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.26

Field Name : excessiveRemotePeers
Field Type : CounterBasedGauge64
Field Status : current
Description : Excessive Remote Peers
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.25

Field Name : addressMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Client Address Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.24

Field Name : cannotProvideSuggest
Field Type : CounterBasedGauge64
Field Status : current
Description : Cannot Provide Suggested Port When PREFER_FAILURE
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.23

Field Name : userQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.22

Field Name : unsuppProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported Mapping Protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.21

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : noResources
Field Type : CounterBasedGauge64
Field Status : current
Description : No System or NAT Resources
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.20

Field Name : malformOption
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Option Malformed
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.19

Field Name : unsuppOption
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PCP Option
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.18

Field Name : unsuppOpcode
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PCP Opcode
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.17

Field Name : malformRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Request Malformed
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.16

Field Name : notAuthorized
Field Type : CounterBasedGauge64
Field Status : current
Description : PCP Request Not Authorized
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.15

Field Name : unsupportedVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PCP version
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.14

Field Name : norouteDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Response No Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.13

Field Name : pktTooShortDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Too Short
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.12

Field Name : pktNotRequestDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Packet Not a PCP Request

OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.11

Field Name : nat64AnnounceProcessSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : PCP ANNOUNCE Request Processing Success (NAT64)

OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.10

Field Name : dsliteAnnounceProcessSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : PCP ANNOUNCE Request Processing Success (DS-Lite)

OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.9

Field Name : lsnAnnounceProcessSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : PCP ANNOUNCE Request Processing Success (NAT44)

OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.8

Field Name : nat64PeerProcessSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : PCP PEER Request Processing Success (NAT64)

OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.7

Field Name : dslitePeerProcessSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : PCP PEER Request Processing Success (DS-Lite)

OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.6

Field Name : lsnPeerProcessSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : PCP PEER Request Processing Success (NAT44)

OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.5

Field Name : nat64MapProcessSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : PCP MAP Request Processing Success (NAT64)

OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.4

Field Name : dsliteMapProcessSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : PCP MAP Request Processing Success (DS-Lite)

OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.3

Field Name : lsnMapProcessSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : PCP MAP Request Processing Success (NAT44)

OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.2

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : packetsRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.25.1.1

Field Name : helperInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session in Remove List
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.7

Field Name : helperAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session already used
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.6

Field Name : helperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.5

Field Name : helperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed used
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.4

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.3

Field Name : helperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.2

Field Name : sessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Client Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.7.1.1

Field Name : tcpOutOfOrderDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-of-Order Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.19

Field Name : rewriteFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : MGCP Message Rewrite Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.18

Field Name : modifyFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP Message Modify Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.17

Field Name : sdpAllocPortMapFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP Alloc SDP Port Map Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.16

Field Name : sdpAllocPortMapSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP Alloc SDP Port Map Success

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.15

Field Name : sdpOpFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP Operate SDP Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.14

Field Name : sdpProcessCandidateFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP Operate SDP Media Candidate Attribute Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.13

Field Name : thirdPartySdp

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP Third-Party SDP

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.12

Field Name : connExtCreationFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP Create Connection Extension Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.11

Field Name : parseError

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP Message Parse Error

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.10

Field Name : rsip

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP RSIP

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.9

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : rqnt
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP RQNT
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.8

Field Name : ntfy
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP NTFY
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.7

Field Name : mdcx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP MDCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.6

Field Name : epcf
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP EPCF
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.5

Field Name : dlcx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP DLCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.4

Field Name : crcx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP CRCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.3

Field Name : aucx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP AUCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.2

Field Name : auep
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP AUEP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.6.1.1

Field Name : helperFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.43

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : SMP Helper Conn Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.42

Field Name : helperDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Already Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.41

Field Name : helperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.40

Field Name : helperFound
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.39

Field Name : smpConnAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.38

Field Name : tcpOutOfOrderDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-of-Order Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.37

Field Name : rewriteFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Message Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.36

Field Name : modifyFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Message Modify Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.35

Field Name : sdpAllocPortMapFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Alloc SDP Port Map Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.34

Field Name : sdpAllocPortMapSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Alloc SDP Port Map Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.33

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : sdpOpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate SDP Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.32

Field Name : sdpProcessCandidateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate SDP Media Candidate Attribute Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.31

Field Name : thirdPartySdp
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Third-Party SDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.30

Field Name : insideContactPortMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Inside Contact Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.29

Field Name : outsideContactPortMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Outside Contact Port Mismatch NAT Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.28

Field Name : allocContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Alloc Contact Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.27

Field Name : connExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Create Connection Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.26

Field Name : thirdPartyRegistration
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Third-Party Registration
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.25

Field Name : contentLengthHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Content-Length Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.24

Field Name : recordRouteHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : SIP Operate Record-Route Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.23

Field Name : routeHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Route Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.22

Field Name : toHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate To Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.21

Field Name : fromHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate From Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.20

Field Name : contactHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Contact Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.19

Field Name : viaHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Via Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.18

Field Name : reqUriOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Request Uri Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.17

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.16

Field Name : cgnv6FixedNatAlgSipMethodUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method UNKNOWN
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.15

Field Name : cgnv6FixedNatAlgSipMethodUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method UPDATE
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.14

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6FixedNatAlgSipMethodMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method MESSAGE
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.13

Field Name : cgnv6FixedNatAlgSipMethodRefer
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method REFER
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.12

Field Name : cgnv6FixedNatAlgSipMethodInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method INFO
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.11

Field Name : cgnv6FixedNatAlgSipMethodPublish
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method PUBLISH
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.10

Field Name : cgnv6FixedNatAlgSipMethodNotify
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method NOTIFY
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.9

Field Name : cgnv6FixedNatAlgSipMethodSubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method SUBSCRIBE
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.8

Field Name : cgnv6FixedNatAlgSipMethodPrack
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method PRACK
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.7

Field Name : methodOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method OPTIONS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.6

Field Name : cgnv6FixedNatAlgSipMethodBye
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method BYE
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.5

Field Name : cgnv6FixedNatAlgSipMethodCancel
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : SIP Method CANCEL
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.4

Field Name : cgnv6FixedNatAlgSipMethodAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method ACK
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.3

Field Name : cgnv6FixedNatAlgSipMethodInvite
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method INVITE
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.2

Field Name : cgnv6FixedNatAlgSipMethodRegister
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method REGISTER
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.5.1.1

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP ALG App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.41

Field Name : haStreamSmpAcquireFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Session Acquire Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.40

Field Name : haStreamSmpReused
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Session Reused
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.39

Field Name : haExtensionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Conn Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.38

Field Name : haDataExists
Field Type : CounterBasedGauge64
Field Status : current
Description : HA New Data Session Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.37

Field Name : haControlClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : HA New Data Control Session Closed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.36

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : haDataNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Data Session SMP Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.35

Field Name : haDataSessionRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Data Session Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.34

Field Name : haDataSessionSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Data Session Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.33

Field Name : haPortAllocationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Stream Port Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.32

Field Name : haStreamExists
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Stream Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.31

Field Name : haStreamIncompatible
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Incompatible Streams Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.30

Field Name : haStreamsRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Streams Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.29

Field Name : haStreamsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Streams Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.28

Field Name : dataFreeSmpNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Free SMP Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.27

Field Name : dataFreeSmpRetryLookup
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Data Session Free SMP Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.26

Field Name : crossCpuRcvFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Receive Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.25

Field Name : crossCpuCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Creation
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.24

Field Name : crossCpuNoSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU No Session Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.23

Field Name : crossCpuRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.22

Field Name : crossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.21

Field Name : rtcpReversed
Field Type : CounterBasedGauge64
Field Status : current
Description : RTCP Reverse Creation
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.20

Field Name : rtpReversed
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Reverse Creation
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.19

Field Name : dataSessionCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : New Data Session Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.18

Field Name : dataSessionExists
Field Type : CounterBasedGauge64
Field Status : current
Description : New Session Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.17

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : controlClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : New Session Closed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.16

Field Name : smpDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : New Session SMP Already Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.15

Field Name : fixedNatLidStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : New Session Fixed NAT LID Standby
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.14

Field Name : smpReused
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Reused
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.13

Field Name : smpRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Removed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.12

Field Name : smpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.11

Field Name : noSessionMem
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Creation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.10

Field Name : cgnv6FixedNatAlgRtspDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.9

Field Name : cgnv6FixedNatAlgRtspDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.8

Field Name : unknownClientPortFromServer
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Server Replies With Unknown Client Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.7

Field Name : portAllocationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Client Port Allocation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.6

Field Name : portsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Client Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.5

Field Name : portsAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Client Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.4

Field Name : streamCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Creation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.3

Field Name : streamsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Streams Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.2

Field Name : streamsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Streams Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.4.1.1

Field Name : controlFreeSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.44

Field Name : controlFreeNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free No SMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.43

Field Name : controlFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.42

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : controlFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.41

Field Name : greFreeSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.40

Field Name : greFreeNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free No SMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.39

Field Name : greFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.38

Field Name : greConnAlreadyExists
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.37

Field Name : greNoControlConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Control Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.36

Field Name : greNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Rev Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.35

Field Name : greNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Fwd Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.34

Field Name : greConnExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.33

Field Name : greConnCreationFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : GRE Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.32

Field Name : smpAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.31

Field Name : smpClientCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Client Call ID Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.30

Field Name : callReplyExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.29

Field Name : callReplyRetransmitAcquired
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit Acquired
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.28

Field Name : callReplyRetransmitWrongControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit Wrong Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.27

Field Name : callReplyRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.26

Field Name : callReplyCallIdUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Unknown Client Call ID
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.25

Field Name : callReqExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.24

Field Name : callReqNew
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request New
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.23

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : callReqRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.22

Field Name : callReplyPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Reply
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.21

Field Name : callReqPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Request
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.20

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP ALG App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.19

Field Name : haSmpInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.18

Field Name : haSmpConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Conflicts
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.17

Field Name : haCallRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.16

Field Name : haCallSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.15

Field Name : haOverwrite
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call ID Overwrites
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.14

Field Name : haConflict
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : HA Call ID Conflicts

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.13

Field Name : haNoMem

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Memory Allocation Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.12

Field Name : haRcv

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Info Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.11

Field Name : haSent

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Info Sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.10

Field Name : extensionCreationFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Extension Creation Failures

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.9

Field Name : smpSessionCreationFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : SMP Session Creation Failures

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.8

Field Name : smpSessionsFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : SMP Sessions Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.7

Field Name : smpSessionsCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : SMP Sessions Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.6

Field Name : noGreSessionMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : No Matching GRE Session

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.5

Field Name : greSessionsFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE Sessions Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.4

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : greSessionsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.3

Field Name : cgnv6FixedNatAlgPptpMismatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Mismatched PNS Call ID
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.2

Field Name : cgnv6FixedNatAlgPptpCallsEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : Calls Established
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.3.1.1

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP ALG App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.18

Field Name : getConnExtFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Get Conn Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.17

Field Name : pasvHelperCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Helper Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.16

Field Name : portHelperCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Helper Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.15

Field Name : pasvHelperUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Mode Helper Unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.14

Field Name : portHelperUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mode Helper Unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.13

Field Name : pasvHelperFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Passive Mode Helper Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.12

Field Name : portHelperFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Mode Helper Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.11

Field Name : pasvHelperCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : Passive Mode Helper Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.10

Field Name : portHelperCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Mode Helper Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.9

Field Name : pasvRetransmits

Field Type : CounterBasedGauge64

Field Status : current

Description : Passive Mode Reply Retransmits

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.8

Field Name : portRetransmits

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Mode Request Retransmits

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.7

Field Name : cgnv6FixedNatAlgFtpLpsvReplies

Field Type : CounterBasedGauge64

Field Status : current

Description : LPSV Replies From Server

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.6

Field Name : cgnv6FixedNatAlgFtpEpsvReplies

Field Type : CounterBasedGauge64

Field Status : current

Description : EPSV Replies From Server

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.5

Field Name : cgnv6FixedNatAlgFtpPasvReplies

Field Type : CounterBasedGauge64

Field Status : current

Description : PASV Replies From Server

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.4

Field Name : cgnv6FixedNatAlgFtpLprtRequests

Field Type : CounterBasedGauge64

Field Status : current

Description : LPRT Requests From Client

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.3

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6FixedNatAlgFtpEpprtRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : EPRT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.2

Field Name : cgnv6FixedNatAlgFtpPortRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.2.1.1

Field Name : placeholderDebug
Field Type : CounterBasedGauge64
Field Status : current
Description : Placeholder Debug
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.1.1.2

Field Name : cgnv6FixedNatAlgEspSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.1.1.1

Field Name : h245DynamicAddrExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H245 Dynamic Address Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.11

Field Name : tcpOutOfOrderDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-of-Order Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.10

Field Name : rewriteFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 Message Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.9

Field Name : connExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 Packet Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.8

Field Name : messageCrossMultiPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 Message Cross Multiple Packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.7

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Message Parse Error

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.6

Field Name : fastStart

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 FastStart

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.5

Field Name : h245Tunneled

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 H245 Tunnelled Message

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.4

Field Name : h245ctlMessage

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 H245 Media Control Message

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.3

Field Name : h225csMessage

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 H225 Call Signaling Message

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.2

Field Name : h225rasMessage

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 H225 RAS Message

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.4.8.1.1

Field Name : crossCpuRrNoConnDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Packets Dropped no conn

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.346

Field Name : crossCpuRrSelfSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Packets Self Sent in CPU RR

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.345

Field Name : unusedIpDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Fixed NAT UNUSED IP Hit and Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.344

Field Name : configNotFoundInCtx

Field Type : CounterBasedGauge64

Field Status : current

Description : Fixed NAT Config Pointer Not Found in MY_CTX

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.343

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6FixednatGlobalActiveSubscriberRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : Active Subscriber Removed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.342

Field Name : cgnv6FixednatGlobalActiveSubscriberAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : Active Subscriber Added
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.341

Field Name : fnatdsliteRevEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.340

Field Name : fnatdsliteRevEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.339

Field Name : fnatdsliteRevEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.338

Field Name : fnatdsliteRevEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.337

Field Name : fnatdsliteRevIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.336

Field Name : fnatdsliteRevIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.335

Field Name : fnatdsliteRevIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.334

Field Name : fnatdsliteRevIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Fixed DS-Lite Reverse Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.333

Field Name : fnatdsliteFwdEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.332

Field Name : fnatdsliteFwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.331

Field Name : fnatdsliteFwdEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.330

Field Name : fnatdsliteFwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.329

Field Name : fnatdsliteFwdIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.328

Field Name : fnatdsliteFwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.327

Field Name : fnatdsliteFwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.326

Field Name : fnatdsliteFwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.325

Field Name : fnatdsliteRevEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.324

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fnatdsliteRevIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.323

Field Name : fnatdsliteFwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.322

Field Name : fnatdsliteFwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.321

Field Name : fnatdsliteRevEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.320

Field Name : fnatdsliteRevIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.319

Field Name : fnatdsliteFwdEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.318

Field Name : fnatdsliteFwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.317

Field Name : fnatdsliteRevEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.316

Field Name : fnatdsliteRevIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.315

Field Name : fnatdsliteFwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Fixed DS-Lite Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.314

Field Name : fnatdsliteFwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.313

Field Name : fnatdsliteRevEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.312

Field Name : fnatdsliteRevIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.311

Field Name : fnatdsliteFwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.310

Field Name : fnatdsliteFwdIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.309

Field Name : fnatdsliteRevEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.308

Field Name : fnatdsliteRevIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.307

Field Name : fnatdsliteFwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.306

Field Name : fnatdsliteFwdIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.305

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fnatdsliteRevEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.304

Field Name : fnatdsliteRevIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.303

Field Name : fnatdsliteFwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.302

Field Name : fnatdsliteFwdIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.301

Field Name : fnatdsliteRevEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.300

Field Name : fnatdsliteRevIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.299

Field Name : fnatdsliteFwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.298

Field Name : fnatdsliteFwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.297

Field Name : fnatdsliteRevEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Reverse Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.296

Field Name : fnatdsliteRevIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Fixed DS-Lite Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.295

Field Name : fnatdsliteFwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.294

Field Name : fnatdsliteFwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed DS-Lite Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.293

Field Name : fnat64RevEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.292

Field Name : fnat64RevEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.291

Field Name : fnat64RevEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.290

Field Name : fnat64RevEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.289

Field Name : fnat64RevIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.288

Field Name : fnat64RevIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.287

Field Name : fnat64RevIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.286

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fnat64RevIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.285

Field Name : fnat64FwdEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.284

Field Name : fnat64FwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.283

Field Name : fnat64FwdEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.282

Field Name : fnat64FwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.281

Field Name : fnat64FwdIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.280

Field Name : fnat64FwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.279

Field Name : fnat64FwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.278

Field Name : fnat64FwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.277

Field Name : fnat64RevEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Fixed NAT64 Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.276

Field Name : fnat64RevIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.275

Field Name : fnat64FwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.274

Field Name : fnat64FwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.273

Field Name : fnat64RevEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.272

Field Name : fnat64RevIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.271

Field Name : fnat64FwdEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.270

Field Name : fnat64FwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.269

Field Name : fnat64RevEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.268

Field Name : fnat64RevIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.267

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fnat64FwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.266

Field Name : fnat64FwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.265

Field Name : fnat64RevEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.264

Field Name : fnat64RevIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.263

Field Name : fnat64FwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.262

Field Name : fnat64FwdIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.261

Field Name : fnat64RevEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.260

Field Name : fnat64RevIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.259

Field Name : fnat64FwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.258

Field Name : fnat64FwdIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Fixed NAT64 Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.257

Field Name : fnat64RevEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.256

Field Name : fnat64RevIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.255

Field Name : fnat64FwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.254

Field Name : fnat64FwdIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.253

Field Name : fnat64RevEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.252

Field Name : fnat64RevIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.251

Field Name : fnat64FwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.250

Field Name : fnat64FwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.249

Field Name : fnat64RevEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.248

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fnat64RevIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.247

Field Name : fnat64FwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.246

Field Name : fnat64FwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT64 Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.245

Field Name : fnat44RevEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.244

Field Name : fnat44RevEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.243

Field Name : fnat44RevEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.242

Field Name : fnat44RevEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.241

Field Name : fnat44RevIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.240

Field Name : fnat44RevIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.239

Field Name : fnat44RevIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Fixed NAT44 Reverse Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.238

Field Name : fnat44RevIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.237

Field Name : fnat44FwdEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.236

Field Name : fnat44FwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.235

Field Name : fnat44FwdEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.234

Field Name : fnat44FwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.233

Field Name : fnat44FwdIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.232

Field Name : fnat44FwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.231

Field Name : fnat44FwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.230

Field Name : fnat44FwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.229

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fnat44RevEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.228

Field Name : fnat44RevIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.227

Field Name : fnat44FwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.226

Field Name : fnat44FwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.225

Field Name : fnat44RevEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.224

Field Name : fnat44RevIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.223

Field Name : fnat44FwdEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.222

Field Name : fnat44FwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.221

Field Name : fnat44RevEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.220

Field Name : fnat44RevIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Fixed NAT44 Reverse Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.219

Field Name : fnat44FwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.218

Field Name : fnat44FwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.217

Field Name : fnat44RevEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.216

Field Name : fnat44RevIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.215

Field Name : fnat44FwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.214

Field Name : fnat44FwdIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.213

Field Name : fnat44RevEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.212

Field Name : fnat44RevIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.211

Field Name : fnat44FwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.210

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fnat44FwdIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.209

Field Name : fnat44RevEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.208

Field Name : fnat44RevIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.207

Field Name : fnat44FwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.206

Field Name : fnat44FwdIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.205

Field Name : fnat44RevEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.204

Field Name : fnat44RevIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.203

Field Name : fnat44FwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.202

Field Name : fnat44FwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.201

Field Name : fnat44RevEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Fixed NAT44 Reverse Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.200

Field Name : fnat44RevIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.199

Field Name : fnat44FwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.198

Field Name : fnat44FwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT44 Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.197

Field Name : cgnv6FixednatGlobalNatPortUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : HA ICMP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.196

Field Name : cgnv6FixednatGlobalNatPortUnavailableUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : HA UDP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.195

Field Name : cgnv6FixednatGlobalNatPortUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : HA TCP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.194

Field Name : haIcmpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : HA ICMP User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.193

Field Name : haUdpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : HA UDP User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.192

Field Name : haTcpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : HA TCP User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.191

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : icmpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.190

Field Name : udpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.189

Field Name : tcpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.188

Field Name : haSessionUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Sessions User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.187

Field Name : totalUdpFreeOverloadShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP freed via overload shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.186

Field Name : totalTcpFreeOverloadShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP freed via overload shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.185

Field Name : totalUdpAllocOverloadShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP allocated via overload shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.184

Field Name : totalTcpAllocOverloadShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP allocated via overload shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.183

Field Name : totalUdpOverloadReleasedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ports released from port overloading shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.182

Field Name : totalTcpOverloadReleasedShadow
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Total TCP ports released from port overloading shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.181

Field Name : totalUdpOverloadAcquiredShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ports acquired for port overloading shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.180

Field Name : totalTcpOverloadAcquiredShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP ports acquired for port overloading shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.179

Field Name : portOverloadFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port overload failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.178

Field Name : portOverloadFreeSmpNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port overload free SMP conn not found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.177

Field Name : portOverloadSmpFreeNoLid
Field Type : CounterBasedGauge64
Field Status : current
Description : Port overload SMP conn free no lid
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.176

Field Name : portOverloadSmpFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port overload SMP conn free
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.175

Field Name : portOverloadOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Port overload out of memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.174

Field Name : portOverloadSmpMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port overload SMP mem allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.173

Field Name : portOverloadSmpDeleteScheduled
Field Type : CounterBasedGauge64
Field Status : current
Description : Port overload SMP conn delete scheduled
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.172

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : totalUdpFreeOverload
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ports freed via overload
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.171

Field Name : totalTcpFreeOverload
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP ports freed via overload
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.170

Field Name : totalUdpAllocOverload
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ports allocated via overload
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.169

Field Name : totalTcpAllocOverload
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP ports allocated via overload
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.168

Field Name : totalUdpOverloadReleased
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ports released from port overloading
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.167

Field Name : totalTcpOverloadReleased
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP ports released from port overloading
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.166

Field Name : totalUdpOverloadAcquired
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ports acquired for port overloading
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.165

Field Name : totalTcpOverloadAcquired
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP ports acquired for port overloading
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.164

Field Name : dsliteTunnelFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragment DS-Lite Packet
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.163

Field Name : ipdDisabled
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Fixed NAT IPD disabled
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.162

Field Name : ipv6UserUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT IPv6 User Marked Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.161

Field Name : ipv4UserUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT IPv4 User Marked Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.160

Field Name : userUnusableDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT User Unusable Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.159

Field Name : mgcpAlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.158

Field Name : mgcpAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.157

Field Name : mgcpAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.156

Field Name : mgcpAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.155

Field Name : mgcpAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.154

Field Name : mgcpAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.153

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : mgcpAlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.152

Field Name : mgcpAlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.151

Field Name : mgcpAlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.150

Field Name : h323AlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.149

Field Name : h323AlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.148

Field Name : h323AlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.147

Field Name : h323AlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.146

Field Name : h323AlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.145

Field Name : h323AlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.144

Field Name : h323AlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : H323 ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.143

Field Name : h323AlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.142

Field Name : h323AlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.141

Field Name : dsliteUdpAlgFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP ALG Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.140

Field Name : dsliteUdpAlgFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP ALG Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.139

Field Name : dsliteUdpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.138

Field Name : dsliteUdpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.137

Field Name : dsliteTcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite TCP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.136

Field Name : dsliteTcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite TCP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.135

Field Name : nat64UdpAlgFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP ALG Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.134

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : nat64UdpAlgFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP ALG Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.133

Field Name : nat64UdpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.132

Field Name : nat64UdpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.131

Field Name : nat64TcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 TCP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.130

Field Name : nat64TcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 TCP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.129

Field Name : nat44UdpAlgFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP ALG Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.128

Field Name : nat44UdpAlgFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP ALG Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.127

Field Name : nat44UdpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.126

Field Name : nat44UdpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.125

Field Name : nat44TcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : NAT44 TCP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.124

Field Name : nat44TcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 TCP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.123

Field Name : dsliteDataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.122

Field Name : dsliteDataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.121

Field Name : nat64DataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.120

Field Name : nat64DataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.119

Field Name : nat44DataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.118

Field Name : nat44DataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.117

Field Name : totalIcmpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.116

Field Name : totalIcmpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.115

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : totalUdpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.114

Field Name : totalUdpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.113

Field Name : totalTcpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.112

Field Name : totalTcpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.111

Field Name : natEspIpConflicts
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT ESP IP Conflicts
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.110

Field Name : icmpOutOfStateUqeDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Queue Exceeded ICMP notification dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.109

Field Name : icmpOutOfStateUqeHostUnreachableSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Quota Exceeded ICMP host unreachable sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.108

Field Name : icmpOutOfStateUqeAdminFilteredSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Quota Exceeded ICMP admin filtered sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.107

Field Name : sipAlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.106

Field Name : sipAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : SIP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.105

Field Name : sipAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.104

Field Name : sipAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.103

Field Name : sipAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.102

Field Name : sipAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.101

Field Name : sipAlgCreateContactFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Contact Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.100

Field Name : sipAlgContactFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Contact Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.99

Field Name : sipAlgReuseContactFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse Contact Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.98

Field Name : disableLogMsgFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Disable Log Msg Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.97

Field Name : disableLogMsgAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Disable Log Msg Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.96

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : periodicLogMsgFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Periodic Log Msg Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.95

Field Name : periodicLogMsgAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Periodic Log Msg Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.94

Field Name : fragIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Packet Too Big Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.93

Field Name : frag
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmented Packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.92

Field Name : mtuExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Exceeded MTU
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.91

Field Name : udpAlgAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Port Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.90

Field Name : udpAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.89

Field Name : udpAlgEimMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Endpoint-Independent Mapping Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.88

Field Name : haEndpointIndepMapMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Endpoint-Independent-Mapping Match
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.87

Field Name : haFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : HA Full-Cone Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.86

Field Name : haNatPortUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : HA NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.85

Field Name : haDnatMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Destination NAT Config Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.84

Field Name : haFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Full-Cone Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.83

Field Name : haUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : HA User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.82

Field Name : haConfigMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Fixed NAT Config Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.81

Field Name : fullconeOverflowEif
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone EIF Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.80

Field Name : fullconeOverflowEim
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone EIM Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.79

Field Name : fullconeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session not found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.78

Field Name : fullconeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session retry look-up
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.77

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fullconeInboundIdxMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-Cone Session Fixed NAT LID mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.76

Field Name : fullconeOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-Cone Session Conn-Count Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.75

Field Name : fullconeInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-Cone Session in Delete Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.74

Field Name : configNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT Config not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.73

Field Name : crossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Packets Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.72

Field Name : crossCpuHelperCpuMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper CPU Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.71

Field Name : crossCpuHelperFixedNatLidStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Fixed NAT LID Standby
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.70

Field Name : crossCpuHelperDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.69

Field Name : crossCpuNoSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU no Session Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.68

Field Name : crossCpuBadL4
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Cross CPU Unsupported L4

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.67

Field Name : crossCpuBadL3

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Unsupported L3

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.66

Field Name : crossCpuRcv

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Packets Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.65

Field Name : crossCpuHelperFree

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Session Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.64

Field Name : crossCpuHelperFreeNotFound

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Session Free not Found

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.63

Field Name : crossCpuHelperFreeRetryLookup

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Session Free Retry Lookup

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.62

Field Name : crossCpuHelperCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.61

Field Name : destRlistSnatDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Fixed NAT Dest Rules List Source NAT Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.60

Field Name : destRlistPassThrough

Field Type : CounterBasedGauge64

Field Status : current

Description : Fixed NAT Dest Rule List Pass-Through

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.59

Field Name : destRlistDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Fixed NAT Dest Rule List Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.58

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6FixednatGlobal6rdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT IPv6 in IPv4 Packet Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.57

Field Name : fixedNatFullconeSelfHairpinningDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Self-Hairpinning Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.56

Field Name : standbyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fixed NAT LID Standby Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.55

Field Name : dsliteHairpin
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Hairpin Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.54

Field Name : nat64Hairpin
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Hairpin Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.53

Field Name : nat44Hairpin
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Hairpin Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.52

Field Name : dsliteEifLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Endpoint-Independent-Filtering Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.51

Field Name : nat64EifLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Endpoint-Independent-Filtering Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.50

Field Name : nat44EifLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Endpoint-Independent-Filtering Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.49

Field Name : dsliteInboundFiltered
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : DS-Lite Endpoint-Dependent Filtering Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.48

Field Name : nat64InboundFiltered
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Endpoint-Dependent Filtering Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.47

Field Name : nat44InboundFiltered
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Endpoint-Dependent Filtering Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.46

Field Name : dsliteEifMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Endpoint-Independent-Filtering Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.45

Field Name : nat64EifMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Endpoint-Independent-Filtering Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.44

Field Name : nat44EifMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Endpoint-Independent-Filtering Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.43

Field Name : dsliteEimMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Endpoint-Independent-Mapping Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.42

Field Name : nat64EimMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Endpoint-Independent-Mapping Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.41

Field Name : nat44EimMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Endpoint-Independent-Mapping Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.40

Field Name : cgnv6FixednatGlobalFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-Cone Session Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.39

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : dsliteUdpAlgFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP ALG Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.38

Field Name : dsliteUdpAlgFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP ALG Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.37

Field Name : dsliteUdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.36

Field Name : dsliteUdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite UDP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.35

Field Name : dsliteTcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite TCP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.34

Field Name : dsliteTcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite TCP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.33

Field Name : nat64UdpAlgFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP ALG Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.32

Field Name : nat64UdpAlgFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP ALG Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.31

Field Name : nat64UdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 UDP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.30

Field Name : nat64UdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : NAT64 UDP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.29

Field Name : nat64TcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 TCP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.28

Field Name : nat64TcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 TCP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.27

Field Name : nat44UdpAlgFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP ALG Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.26

Field Name : nat44UdpAlgFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP ALG Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.25

Field Name : nat44UdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.24

Field Name : nat44UdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 UDP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.23

Field Name : nat44TcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 TCP Full-Cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.22

Field Name : nat44TcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 TCP Full-Cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.21

Field Name : sessionUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Sessions User Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.20

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6FixednatGlobalNatPortUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.16

Field Name : cgnv6FixednatGlobalNatPortUnavailableUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.15

Field Name : cgnv6FixednatGlobalNatPortUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.14

Field Name : dsliteDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.13

Field Name : dsliteDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.12

Field Name : nat64DataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.11

Field Name : nat64DataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT64 Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.10

Field Name : nat44DataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.9

Field Name : nat44DataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT44 Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.8

Field Name : cgnv6FixednatGlobalTotalTotalIcmpFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Total ICMP Ports Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.7

Field Name : cgnv6FixednatGlobalTotalIcmpAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : Total ICMP Ports Allocated

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.6

Field Name : cgnv6FixednatGlobalTotalUdpFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : Total UDP Ports Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.5

Field Name : cgnv6FixednatGlobalTotalUdpAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : Total UDP Ports Allocated

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.4

Field Name : cgnv6FixednatGlobalTotalTcpFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : Total TCP Ports Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.3

Field Name : cgnv6FixednatGlobalTotalTcpAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : Total TCP Ports Allocated

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.2

Field Name : totalNatInUse

Field Type : CounterBasedGauge64

Field Status : current

Description : Total NAT Addresses in-use

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.2.1.1

Field Name : tcamCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : TCAM Flow Count

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.20

Field Name : tcamFree

Field Type : CounterBasedGauge64

Field Status : current

Description : TCAM Flows Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.19

Field Name : tcamCreate

Field Type : CounterBasedGauge64

Field Status : current

Description : TCAM Flows Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.18

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : entryInvalidateServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Invalidate due to server down
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.17

Field Name : entryForceHwInvalidate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Force HW Invalidate
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.16

Field Name : entryAgeOutInvalidDst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - invalid dst
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.15

Field Name : entryAgeOutTcpRst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP RST
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.14

Field Name : entryAgeOutTcpFin
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP FIN
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.13

Field Name : entryAgeOutIdle
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.12

Field Name : entryAgeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.11

Field Name : entryCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.10

Field Name : entryFreeNoSwEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no software entry
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.9

Field Name : entryFreeNoConn
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : HW Entry Freed - no matched conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.8

Field Name : entryFreeNoHwProg
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no HW prog
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.7

Field Name : entryFreeOppEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Freed - opposite tuple entry aged-out
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.6

Field Name : entryFree
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.5

Field Name : entryCreateFailMaxEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed - max entries exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.4

Field Name : entryCreateFailServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed - server down
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.3

Field Name : entryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.2

Field Name : entryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.24.14.1.1

Field Name : connCount
Field Type : CounterBasedGauge64
Field Status : current
Description : conn count
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.19

Field Name : nat46StatelessOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Other errors
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.18

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : haStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : HA is standby
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.17

Field Name : icmpToIcmpv6Error
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMPv6 errors
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.16

Field Name : icmpToIcmpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP to ICMPv6
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.15

Field Name : icmpv6ToIcmpError
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMP errors
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.14

Field Name : icmpv6ToIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 to ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.13

Field Name : fragmentError
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment processing errors
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.12

Field Name : packetTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet too big
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.11

Field Name : inboundIpv4Fragmented
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 packets fragmented
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.10

Field Name : inboundIpv4Unreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 destination unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.9

Field Name : inboundIpv6FragmentReceived
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Inbound IPv6 fragment packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.8

Field Name : inboundIpv6Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv6 packets dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.7

Field Name : inboundIpv6Received
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv6 packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.6

Field Name : outboundIpv6Fragmented
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 packets fragmented
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.5

Field Name : outboundIpv6Unreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 destination unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.4

Field Name : outboundIpv4FragmentReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv4 fragment packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.3

Field Name : outboundIpv4Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv4 packets dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.2

Field Name : outboundIpv4Received
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv4 packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.23.1.1.1

Field Name : haStandbySessionEif
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Session EIF
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.58

Field Name : haStandbySessionEim
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Session EIM
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.57

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : haStandbySessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.56

Field Name : eifFiltered
Field Type : CounterBasedGauge64
Field Status : current
Description : EIF Filtered
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.55

Field Name : eifProcessFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : EIF Process Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.54

Field Name : eifDisableDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : EIF Disable Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.53

Field Name : eifLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : EIF Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.52

Field Name : fullconeFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.51

Field Name : fullconeFreeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Retry Look-up
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.50

Field Name : fullconeFreeFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Free Found From Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.49

Field Name : fullconeOverflowEif
Field Type : CounterBasedGauge64
Field Status : current
Description : EIF Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.48

Field Name : fullconeOverflowEim
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : EIM Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.47

Field Name : fullconeInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Found in Delete Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.46

Field Name : udpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.45

Field Name : udpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.44

Field Name : tcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.43

Field Name : tcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.42

Field Name : ctlMemFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Memory Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.41

Field Name : ctlMemAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Memory Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.40

Field Name : badSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Session Proto on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.39

Field Name : sessionCreationFailureShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Creation Failure Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.38

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : otherSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Session Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.37

Field Name : otherSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.36

Field Name : udpSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.35

Field Name : udpSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.34

Field Name : tcpSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.33

Field Name : tcpSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.32

Field Name : inboundSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Session Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.31

Field Name : inboundSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.30

Field Name : outboundSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound Session Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.29

Field Name : outboundSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Outbound Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.28

Field Name : cgnv6StatefullFirewallGlobalNoClassListMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No Class-List Match Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.27

Field Name : oneArmDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : One-Arm Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.26

Field Name : eifProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpnt-Independent Filter Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.25

Field Name : fullconeCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-Cone Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.24

Field Name : cgnv6StateFullFirewallGlobalUdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.23

Field Name : cgnv6StateFullFirewallGlobalUdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.22

Field Name : cgnv6StateFullFirewallGlobalTcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.21

Field Name : cgnv6StateFullFirewallGlobalTcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.20

Field Name : packetStandbyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.19

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6StateFullFirewallGlobalNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Reverse Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.18

Field Name : cgnv6StateFullFirewallGlobalNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Forward Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.17

Field Name : sessionCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.16

Field Name : otherSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.15

Field Name : otherSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.14

Field Name : udpSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.13

Field Name : cgnv6StateFullFirewallGlobalUdpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.12

Field Name : tcpSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.11

Field Name : cgnv6StateFullFirewallGlobalTcpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.10

Field Name : inboundSessionFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Inbound Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.9

Field Name : inboundSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.8

Field Name : outboundSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.7

Field Name : outboundSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.6

Field Name : packetProcessFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.5

Field Name : packetInboundDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Packet Denied
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.4

Field Name : otherPacketProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Packet Process
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.3

Field Name : udpPacketProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Packet Process
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.2

Field Name : tcpPacketProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Packet Process
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.1.1.1

Field Name : rtpEim
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP EIM
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.35

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : rtpAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.34

Field Name : rtpNew
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.33

Field Name : contactEimSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact EIM Set
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.32

Field Name : contactEim
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact EIM
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.31

Field Name : contactAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.30

Field Name : contactNew
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.29

Field Name : contactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.28

Field Name : contactPortSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Port Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.27

Field Name : contactPortNoOp
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Port No Op
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.26

Field Name : rtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : RTCP Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.25

Field Name : rtpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.24

Field Name : rtpRtcpPortSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP RTCP Port Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.23

Field Name : rtpPortNoOp
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Port No Op
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.22

Field Name : sdpError
Field Type : CounterBasedGauge64
Field Status : current
Description : SDP Process Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.21

Field Name : contactError
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Process Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.20

Field Name : keepAlive
Field Type : CounterBasedGauge64
Field Status : current
Description : Keep Alive
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.19

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.18

Field Name : methodUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Method Unknown
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.17

Field Name : methodUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : Method UPDATE
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.16

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : methodMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : Method MESSAGE
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.15

Field Name : methodRefer
Field Type : CounterBasedGauge64
Field Status : current
Description : Method REFER
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.14

Field Name : methodInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Method INFO
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.13

Field Name : methodPublish
Field Type : CounterBasedGauge64
Field Status : current
Description : Method PUBLISH
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.12

Field Name : methodNotify
Field Type : CounterBasedGauge64
Field Status : current
Description : Method NOTIFY
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.11

Field Name : methodSubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description : Method SUBSCRIBE
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.10

Field Name : methodPrack
Field Type : CounterBasedGauge64
Field Status : current
Description : Method PRACK
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.9

Field Name : methodPortConfig
Field Type : CounterBasedGauge64
Field Status : current
Description : Method OPTIONS
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.8

Field Name : methodBye
Field Type : CounterBasedGauge64
Field Status : current
Description : Method BYE
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.7

Field Name : methodCancel
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Method CANCEL

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.6

Field Name : methodAck

Field Type : CounterBasedGauge64

Field Status : current

Description : Method ACK

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.5

Field Name : methodInvite

Field Type : CounterBasedGauge64

Field Status : current

Description : Method INVITE

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.4

Field Name : methodRegister

Field Type : CounterBasedGauge64

Field Status : current

Description : Method REGISTER

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.3

Field Name : statResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : Response Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.2

Field Name : statRequest

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.5.1.1

Field Name : haDataSessionCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Data Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.35

Field Name : haControlSessionCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Control Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.34

Field Name : haControlExtCreationFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Control Extension Creation Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.33

Field Name : dataSessionFreedShadow

Field Type : CounterBasedGauge64

Field Status : current

Description : Data Session Freed Shadow

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.32

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : dataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.31

Field Name : transportNotFoundOnDataFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Not Found Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.30

Field Name : transportRetryLookupOnDataFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Retry Lookup Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.29

Field Name : transportDoubleReleaseFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Double Release Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.28

Field Name : transportReleasedFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Released Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.27

Field Name : transportAcquireFailureFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquire Failure Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.26

Field Name : transportAcquiredFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquired Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.25

Field Name : transportDoubleReleaseFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Double Release Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.24

Field Name : transportReleasedFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Released Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.23

Field Name : transportAcquireFailureFromControl
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Transport Acquire Failure Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.22

Field Name : transportFoundFromPrevControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Found From Prev Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.21

Field Name : transportAcquiredFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquired Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.20

Field Name : transportFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.19

Field Name : transportPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Put in Delete Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.18

Field Name : transportAllocFailureShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Alloc Failure Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.17

Field Name : transportCreationRace
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Create Race
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.16

Field Name : transportInsertedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Inserted Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.15

Field Name : transportLinkExtFailureData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Link to Extension Failure Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.14

Field Name : transportLinkExtData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Link to Extension Data
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.13

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : transportLinkExtFailureControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Link to Extension Failure Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.12

Field Name : transportExists
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.11

Field Name : transportAlreadyInExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Already in Extension
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.10

Field Name : transportTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : Too Many Transports for Control Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.9

Field Name : transportRemovedFromExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Removed from Extension
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.8

Field Name : transportAddToExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Added to Extension
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.7

Field Name : extCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Extension Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.6

Field Name : cgnv6StatefullFireWallAlgRtspDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.5

Field Name : cgnv6StatefullFireWallAlgRtspDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.4

Field Name : transportAllocFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Transport Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.3

Field Name : transportFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.2

Field Name : transportInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.4.1.1

Field Name : controlFreeSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.29

Field Name : controlFreeNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free No SMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.28

Field Name : controlFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.27

Field Name : controlFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.26

Field Name : greFreeSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.25

Field Name : greFreeNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free No SMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.24

Field Name : greFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.23

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : greConnAlreadyExists
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.22

Field Name : greNoControlConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Control Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.21

Field Name : greNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Rev Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.20

Field Name : greNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Fwd Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.19

Field Name : greConnExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.18

Field Name : greConnCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.17

Field Name : smpAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.16

Field Name : smpSessionsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.15

Field Name : smpSessionsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.14

Field Name : smpClientCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : SMP Client Call ID Mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.13

Field Name : smpAppTypeMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : SMP App Type Mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.12

Field Name : callReplyExtExtAllocFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Call Request Ext Alloc Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.11

Field Name : callReplyRetransmit

Field Type : CounterBasedGauge64

Field Status : current

Description : Call Reply Retransmit

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.10

Field Name : callReplyCallIdUnknown

Field Type : CounterBasedGauge64

Field Status : current

Description : Call Reply Unknown Client Call ID

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.9

Field Name : callReqExtAllocFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Call Request Ext Alloc Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.8

Field Name : callReqNew

Field Type : CounterBasedGauge64

Field Status : current

Description : Call Request New

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.7

Field Name : callReqRetransmit

Field Type : CounterBasedGauge64

Field Status : current

Description : Call Request Retransmit

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.6

Field Name : greSessionFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE Session Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.5

Field Name : greSessionCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.4

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : callReplyPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Reply
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.3

Field Name : callReqPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Request
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.2

Field Name : callsEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : Calls Established
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.2.1.1

Field Name : pasvHelperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Freed Unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.19

Field Name : pasvHelperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Freed Used
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.18

Field Name : portHelperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Freed Unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.17

Field Name : portHelperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Freed Used
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.16

Field Name : pasvHelperAcquireAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Acquire Already Used
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.15

Field Name : pasvHelperAcquireInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Acquire In Del Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.14

Field Name : portHelperAcquireAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : PORT Helper Acquire Already Used
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.13

Field Name : portHelperAcquireInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Acquire In Del Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.12

Field Name : pasvHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.11

Field Name : portHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.10

Field Name : smpConnAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.9

Field Name : retransmitSanityCheckFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Retransmit Sanity Check Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.8

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.7

Field Name : pasvRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.6

Field Name : portRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.5

Field Name : serverEpsvReply
Field Type : CounterBasedGauge64
Field Status : current
Description : EPSV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.4

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : serverPasvReply
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.3

Field Name : clientEprtRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : EPRT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.2

Field Name : clientPortRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.1.1.1

Field Name : helperInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session in Remove List
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.7

Field Name : helperAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session already used
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.6

Field Name : helperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.5

Field Name : helperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed used
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.4

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.3

Field Name : helperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.2

Field Name : cgnv6StateFullFirewallAlgTftpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : TFTP Client Sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.22.2.6.1.1

Field Name : systemAddressDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : LW-4over6 System Address Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.13

Field Name : sessionCount
Field Type : CounterBasedGauge64
Field Status : current
Description : LW-4over6 Session Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.12

Field Name : noBindingTableMatchesRev
Field Type : TABLE
Field Status : current
Description : No Reverse Binding Table Entry Match Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.11

Field Name : noBindingTableMatchesFwd
Field Type : TABLE
Field Status : current
Description : No Forward Binding Table Entry Match Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.10

Field Name : interfaceNotConfigured
Field Type : CounterBasedGauge64
Field Status : current
Description : LW-4over6 Interfaces not Configured Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.9

Field Name : revLookupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Route Lookup Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.8

Field Name : fwdLookupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Route Lookup Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.7

Field Name : icmpInboundDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound ICMP Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.6

Field Name : noMatchIcmpSent
Field Type : CounterBasedGauge64
Field Status : current
Description : No-Reverse-Match ICMP Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.5

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : noMatchIcmpv6Sent
Field Type : CounterBasedGauge64
Field Status : current
Description : No-Forward-Match ICMPv6 Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.4

Field Name : allHairpinningDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : All Hairpinning Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.3

Field Name : selfHairpinningDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Self-Hairpinning Drops
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.2

Field Name : entryCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entries Configured
OID : 1.3.6.1.4.1.22610.2.4.10.115.21.1.1.1

Field Name : cgnv6SixrdDomainSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1

Field Name : cgnv6SixrdDomainSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1

Field Name : cgnv6SixrdDomainOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Other errors
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.22

Field Name : cgnv6SixrdDomainFragmentError
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment processing errors
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.21

Field Name : notLocalIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Not local IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.20

Field Name : cgnv6SixrdDomainPacketTooBig
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Packet too big
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.19

Field Name : unknownDelegatedPrefix
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown 6rd delegated prefix
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.18

Field Name : vportMatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Traffic match SLB virtual port
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.17

Field Name : inboundTunnelFragmentIpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Fragmented IPv6 in tunnel
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.16

Field Name : inboundFragmentIpv4
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Fragmented IPv4
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.15

Field Name : inboundIpv4DestUnreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound IPv4 destination unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.14

Field Name : inboundPacketsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound packets dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.13

Field Name : inboundOtherPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound other packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.12

Field Name : inboundIcmpPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound ICMP packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.11

Field Name : inboundUdpPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound UDP packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.10

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : inboundTcpPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound TCP packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.9

Field Name : outboundFragmentIpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound Fragmented IPv6
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.8

Field Name : outboundIpv6DestUnreachable
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound IPv6 destination unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.7

Field Name : outboundPacketsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound packets dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.6

Field Name : outboundOtherPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound other packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.5

Field Name : outboundIcmpPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound ICMP packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.4

Field Name : outboundUdpPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound UDP packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.3

Field Name : outboundTcpPacketsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound TCP packets received
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.2

Field Name : cgnv6SixrdDomainName
Field Type : String
Field Status : current
Description : 6rd Domain name
OID : 1.3.6.1.4.1.22610.2.4.10.115.20.1.1.1.1.1

Field Name : portOverloadingPortFreeUdp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : UDP Port Overloading NAT Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.316

Field Name : portOverloadingPortFreeTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading NAT Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.315

Field Name : portOverloadingPortUdpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading NAT Port UDP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.314

Field Name : portOverloadingPortTcpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading NAT Port TCP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.313

Field Name : prefixQuotaMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Prefix Quota NAT IP Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.312

Field Name : revEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.311

Field Name : revEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.310

Field Name : revEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.309

Field Name : revEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.308

Field Name : revIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.307

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : revIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.306

Field Name : revIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.305

Field Name : revIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.304

Field Name : fwdEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.303

Field Name : fwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.302

Field Name : fwdEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.301

Field Name : fwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.300

Field Name : fwdIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.299

Field Name : fwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.298

Field Name : fwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.297

Field Name : fwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.296

Field Name : revEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.295

Field Name : revIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.294

Field Name : fwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.293

Field Name : fwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.292

Field Name : revEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.291

Field Name : revIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.290

Field Name : fwdEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.289

Field Name : fwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.288

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : revEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.287

Field Name : revIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.286

Field Name : fwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.285

Field Name : fwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.284

Field Name : revEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.283

Field Name : revIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.282

Field Name : fwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.281

Field Name : fwdIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.280

Field Name : revEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.279

Field Name : revIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.278

Field Name : fwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.277

Field Name : fwdIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.276

Field Name : revEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.275

Field Name : revIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.274

Field Name : fwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.273

Field Name : fwdIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.272

Field Name : revEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.271

Field Name : revIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.270

Field Name : fwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.269

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.268

Field Name : revEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.267

Field Name : revIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.266

Field Name : fwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.265

Field Name : fwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.264

Field Name : natPoolSamePortBatchUdpFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Simultaneous Batch Allocation UDP Port Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.263

Field Name : userQuotaUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Marked Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.262

Field Name : userQuotaUnusableDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Unusable Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.261

Field Name : mgcpAlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.260

Field Name : mgcpAlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : MGCP ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.259

Field Name : mgcpAlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.258

Field Name : mgcpAlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.257

Field Name : mgcpAlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.256

Field Name : mgcpAlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.255

Field Name : mgcpAlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.254

Field Name : mgcpAlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.253

Field Name : mgcpAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.252

Field Name : mgcpAlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.251

Field Name : mgcpAlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.250

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : mgcpAlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.249

Field Name : mgcpAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.248

Field Name : mgcpAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.247

Field Name : mgcpAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.246

Field Name : mgcpAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.245

Field Name : mgcpAlgReleasePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Release NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.244

Field Name : mgcpAlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.243

Field Name : mgcpAlgAllocPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.242

Field Name : mgcpAlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.241

Field Name : mgcpAlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : MGCP ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.240

Field Name : mgcpAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.239

Field Name : mgcpAlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.238

Field Name : mgcpAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.237

Field Name : natPoolAddFreeBatchFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Add Batch to Quota Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.236

Field Name : natPoolAttemptAddingMultipleFreeBatches
Field Type : CounterBasedGauge64
Field Status : current
Description : Attempt Adding Multiple Free Batches to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.235

Field Name : fragListBadL4Len
Field Type : CounterBasedGauge64
Field Status : current
Description : Frag List Bad L4 Len
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.234

Field Name : jumboListBadL4Len
Field Type : CounterBasedGauge64
Field Status : current
Description : Jumbo List Bad L4 Len
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.233

Field Name : l4ChecksumBadDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Checksum Bad Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.232

Field Name : l4ChecksumFixed
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Checksum Fixed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.231

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : l4ChecksumVerified
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Checksum Verified
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.230

Field Name : ipFragChecksumFixed
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Frag Checksum Fixed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.229

Field Name : ipChecksumBadDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Checksum Bad Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.228

Field Name : ipChecksumFixed
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Checksum Fixed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.227

Field Name : ipChecksumVerified
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Checksum Verified
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.226

Field Name : badIpTotLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IPv4 Total Length
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.225

Field Name : fullconeInboundNatPoolMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session NAT Pool Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.224

Field Name : standbyClassListDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Class-List Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.223

Field Name : natPoolNotFoundOnFree
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.222

Field Name : quotaExtTooMany
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Quota Ext Too Many

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.221

Field Name : natPoolForceDelete

Field Type : CounterBasedGauge64

Field Status : current

Description : NAT Pool Force Delete

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.220

Field Name : haPortOverloadingForNewUserSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Port Overloading for New User Success

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.219

Field Name : haPortOverloadingForNewUser

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Port Overloading for New User

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.218

Field Name : haPortOverloadingForQuotaExceededRaceSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Port Overloading for Quota Exceeded Race Success

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.217

Field Name : haPortOverloadingForQuotaExceededRace

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Port Overloading for Quota Exceeded Race

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.216

Field Name : haPortOverloadingForQuotaExceededSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Port Overloading for Quota Exceeded Success

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.215

Field Name : haPortOverloadingForQuotaExceeded

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Port Overloading for Quota Exceeded

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.214

Field Name : haPortOverloadingForNoPortsSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Port Overloading for No Ports Success

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.213

Field Name : haPortOverloadingForNoPorts

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Port Overloading for No Ports

OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.212

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : haPortOverloadingAttemptFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading Attempt Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.211

Field Name : portOverloadingForNewUserSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for New User Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.210

Field Name : portOverloadingForNewUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for New User
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.209

Field Name : portOverloadingForQuotaExceededRaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Race Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.208

Field Name : portOverloadingForQuotaExceededRace
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Race
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.207

Field Name : portOverloadingForQuotaExceededSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.206

Field Name : portOverloadingForQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.205

Field Name : portOverloadingForNoPortsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for No Ports Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.204

Field Name : portOverloadingForNoPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for No Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.203

Field Name : portOverloadingSmpFreePortFromQuota
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Port Overloading SMP Free Port From Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.202

Field Name : portOverloadingSmpFreePort
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.201

Field Name : portOverloadingSmpFreeNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free No Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.200

Field Name : portOverloadingSmpFreeDecFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Dec Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.199

Field Name : portOverloadingSmpPutInDelQFromConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free From Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.198

Field Name : portOverloadingSmpFreeUdpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP UDP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.197

Field Name : portOverloadingSmpFreeTcpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP TCP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.196

Field Name : portOverloadingSmpInsertedUdpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP UDP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.195

Field Name : portOverloadingSmpInsertedTcpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP TCP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.194

Field Name : portOverloadingSmpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.193

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : portOverloadingSmpMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.192

Field Name : portOverloadingSmpMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Session Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.191

Field Name : portOverloadingConnFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Conn Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.190

Field Name : portOverloadingConnFreeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Conn Free Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.189

Field Name : portOverloadingAttemptFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Attempt Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.188

Field Name : portOverloadingAttemptDiffPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Different Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.187

Field Name : portOverloadingAttemptSamePartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Same Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.186

Field Name : portOverloadingAttemptConsecutivePorts
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Consecutive Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.185

Field Name : portOverloadingIncOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Inc Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.184

Field Name : portOverloadingFreePortBatchOnConflict
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Port Overloading Free Port Batch on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.183

Field Name : portOverloadingFreePortOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Free Port on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.182

Field Name : portOverloadingDecOnFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Decrement on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.181

Field Name : portOverloadingDecOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Decrement on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.180

Field Name : portOverloadingInc
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Increment
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.179

Field Name : portOverloadingAssignUserPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Assign User Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.178

Field Name : portOverloadingAssignUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Assign User
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.177

Field Name : portOverloadingOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.176

Field Name : portOverloadingDestinationConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Destination Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.175

Field Name : portBatchContainerAllocRaceFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Container Race Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.174

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : portBatchContainerAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Container Alloc Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.173

Field Name : specificPortAllocatedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.172

Field Name : specificPortAllocatedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.171

Field Name : specificPortAllocatedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.170

Field Name : portBatchFreedFromQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Freed From Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.169

Field Name : portBatchAllocatedToQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Allocated to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.168

Field Name : portFreedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.167

Field Name : portFreedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.166

Field Name : portFreedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.165

Field Name : portAllocatedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Port Allocated from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.164

Field Name : portAllocatedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.163

Field Name : portAllocatedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.162

Field Name : poolPortBatchPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.161

Field Name : partitionPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.160

Field Name : consecutivePortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Consecutive Pool
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.159

Field Name : badPortToFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Freeing Bad Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.158

Field Name : haRcvPortNotInPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Not in Port Batch on Sync Rcv
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.157

Field Name : haSendPortBatchNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Not Found on Sync Send
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.156

Field Name : haSyncPortBatchRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Extension Sync Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.155

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : haSyncPortBatchSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Extension Sync Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.154

Field Name : quotaExtensionRemoveNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Not Found on Remove
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.153

Field Name : quotaExtensionRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Removed from Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.152

Field Name : quotaExtensionAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Added to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.151

Field Name : radiusQueryQuotaExtAllocRaceFree
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Query Container Alloc Race Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.150

Field Name : radiusQueryQuotaExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Query Container Alloc (No Memory)
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.149

Field Name : portBatchFreeWrongPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Free Wrong Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.148

Field Name : portBatchFreePortNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Port Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.147

Field Name : portBatchFreeQuotaNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Quota Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.146

Field Name : portBatchQuotaExtensionAllocFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Port Batch Extension Alloc Failure (No memory)
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.145

Field Name : h323AlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.144

Field Name : h323AlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.143

Field Name : h323AlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.142

Field Name : h323AlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.141

Field Name : h323AlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.140

Field Name : h323AlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.139

Field Name : h323AlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.138

Field Name : h323AlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.137

Field Name : h323AlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.136

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : h323AlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.135

Field Name : h323AlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.134

Field Name : h323AlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.133

Field Name : h323AlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.132

Field Name : h323AlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.131

Field Name : h323AlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.130

Field Name : h323AlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.129

Field Name : h323AlgReleasePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Release NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.128

Field Name : h323AlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.127

Field Name : h323AlgAllocPortFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : H323 ALG Alloc NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.126

Field Name : h323AlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.125

Field Name : h323AlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.124

Field Name : h323AlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.123

Field Name : h323AlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.122

Field Name : h323AlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.121

Field Name : sipAlgPortPairAllocFromQuotaPoolPortBatchWithFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Port Batch Version 2 with Frag Free Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.120

Field Name : sipAlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.119

Field Name : sipAlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.118

Field Name : sipAlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.117

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : sipAlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.116

Field Name : sipAlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.115

Field Name : sipAlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.114

Field Name : sipAlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.113

Field Name : sipAlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.112

Field Name : sipAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.111

Field Name : sipAlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.110

Field Name : sipAlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.109

Field Name : sipAlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.108

Field Name : sipAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : SIP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.107

Field Name : sipAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.106

Field Name : sipAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.105

Field Name : sipAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.104

Field Name : sipAlgReleaseContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Release Contact NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.103

Field Name : sipAlgCreateContactFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Contact Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.102

Field Name : sipAlgAllocContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc Contact NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.101

Field Name : sipAlgContactFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Contact Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.100

Field Name : sipAlgReuseContactFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse Contact Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.99

Field Name : sipAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.98

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : sipAlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.97

Field Name : sipAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.96

Field Name : udpAlgAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Port Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.95

Field Name : udpAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.94

Field Name : udpAlgEimMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Endpoint-Independent Mapping Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.93

Field Name : udpAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.92

Field Name : totalIcmpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.91

Field Name : totalIcmpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.90

Field Name : totalUdpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.89

Field Name : totalUdpAllocatedShadow
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.88

Field Name : totalTcpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.87

Field Name : totalTcpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.86

Field Name : newUserResourceUnavailableOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Other New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.85

Field Name : newUserResourceUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.84

Field Name : newUserResourceUnavailableUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.83

Field Name : newUserResourceUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.82

Field Name : natPortUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : Total NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.81

Field Name : natPortUnavailableOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Other NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.80

Field Name : extendedQuotaMismatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Mismatched
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.79

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : dataSessionUserQuotaMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Counter Per User Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.78

Field Name : dataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.77

Field Name : dataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.76

Field Name : fullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.75

Field Name : fullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.74

Field Name : udpAlgFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ALG Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.73

Field Name : udpAlgFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ALG Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.72

Field Name : udpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.71

Field Name : udpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.70

Field Name : tcpFullconeFreedShadow
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : Total TCP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.69

Field Name : tcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.68

Field Name : userQuotaNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.67

Field Name : icmpOutOfStateUqeDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Queue Exceeded ICMP notification dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.66

Field Name : icmpOutOfStateUqeHostUnreachableSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Quota Exceeded ICMP host unreachable sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.65

Field Name : icmpOutOfStateUqeAdminFilteredSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Quota Exceeded ICMP admin filtered sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.64

Field Name : tcpOutOfStateRstDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Out of State TCP RST dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.63

Field Name : tcpOutOfStateRstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Out of State TCP RST sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.62

Field Name : totalUserQuotaFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Quota Structure Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.61

Field Name : totalUserQuotaPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Quota Structure Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.60

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : totalUserQuotaCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Quota Structure Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.59

Field Name : prefixQuotaFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Prefix Quota Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.58

Field Name : prefixQuotaPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Prefix Quota Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.57

Field Name : prefixQuotaCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Prefix Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.56

Field Name : userQuotaPutInDelQShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User-Quota Put In Del Q
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.55

Field Name : quotaDeleteNotInBucket
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Delete Not In Bucket
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.54

Field Name : quotaMarkedDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.53

Field Name : userQuotaCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User-Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.52

Field Name : userQuotaMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.51

Field Name : userQuotaMemAllocated
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : User-Quota Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.50

Field Name : classListPermitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Permit Class-List Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.49

Field Name : noClassListMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No Class-List Match
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.48

Field Name : lidPassThrough
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN LID Pass-through
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.47

Field Name : lidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN LID Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.46

Field Name : truncatedPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Truncated Packet
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.45

Field Name : noRadiusProfileMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No RADIUS Profile Match
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.44

Field Name : haNatPoolBatchTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA NAT Pool Batch Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.43

Field Name : cgnv6DsliteGlobalHaNatPoolUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : HA NAT Pool Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.42

Field Name : cgnv6DsliteGlobalNatPoolUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.41

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6DsliteGlobalPortOverloadingSmpFreeUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.40

Field Name : cgnv6DsliteGlobalPortOverloadingSmpFreeTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.39

Field Name : cgnv6DsliteGlobalPortOverloadingSmpInsertedUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.38

Field Name : cgnv6DsliteGlobalPortOverloadingSmpInsertedTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.37

Field Name : cgnv6DsliteGlobalTotalUdpOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.36

Field Name : cgnv6DsliteGlobalTotalTcpOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.35

Field Name : cgnv6DsliteGlobalEifLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Filtering Inbound Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.33

Field Name : cgnv6DsliteGlobalInboundFiltered
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Dependent Filtering Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.32

Field Name : cgnv6DsliteGlobalEndpointIndepFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Filtering Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.31

Field Name : cgnv6DsliteGlobalEndpointIndepMapMatch
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : Endpoint-Independent Mapping Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.30

Field Name : cgnv6DsliteGlobalFullconeSelfHairpinningDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Self-Hairpinning Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.29

Field Name : cgnv6DsliteGlobalHairpin
Field Type : CounterBasedGauge64
Field Status : current
Description : Hairpin Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.28

Field Name : cgnv6DsliteGlobalFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.27

Field Name : cgnv6DsliteGlobalUdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.26

Field Name : cgnv6DsliteGlobalUdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.25

Field Name : cgnv6DsliteGlobalTcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.24

Field Name : cgnv6DsliteGlobalTcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.23

Field Name : cgnv6DsliteGlobalDataSesnRateUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Rate User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.22

Field Name : cgnv6DsliteGlobalDataSesnUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.21

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6DsliteGlobalExtendedQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.20

Field Name : cgnv6DsliteGlobalExtendedQuotaMatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.19

Field Name : cgnv6DsliteGlobalIcmpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.18

Field Name : cgnv6DsliteGlobalUdpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.17

Field Name : cgnv6DsliteGlobalTcpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.16

Field Name : cgnv6DsliteGlobalNewUserResourceUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.15

Field Name : cgnv6DsliteGlobalNatPortUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.14

Field Name : cgnv6DsliteGlobalNatPortUnavailableUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.13

Field Name : cgnv6DsliteGlobalNatPortUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.12

Field Name : cgnv6DsliteGlobalUserQuotaFailure
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : User-Quota Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.11

Field Name : cgnv6DsliteGlobalTotalUserQuotaPuInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.10

Field Name : cgnv6DsliteGlobalUserQuotaCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.9

Field Name : cgnv6DsliteGlobalDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.8

Field Name : cgnv6DsliteGlobalDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.7

Field Name : cgnv6DsliteGlobalTotalIcmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.6

Field Name : cgnv6DsliteGlobalTotalIcmpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.5

Field Name : cgnv6DsliteGlobalTotalUdpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.4

Field Name : cgnv6DsliteGlobalTotalUdpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.3

Field Name : cgnv6DsliteGlobalTotalTcpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.2

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6DsliteGlobalTotalTcpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.19.1.1.1

Field Name : natIpConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT IP Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.2.1.1.2

Field Name : sessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.2.1.1.1

Field Name : portOverloadingPortFreeUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading NAT Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.311

Field Name : portOverloadingPortFreeTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading NAT Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.310

Field Name : portOverloadingPortUdpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading NAT Port UDP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.309

Field Name : portOverloadingPortTcpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading NAT Port TCP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.308

Field Name : prefixQuotaMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Prefix Quota NAT IP Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.307

Field Name : revEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.306

Field Name : revEgressPktSizeRange3
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : Reverse Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.305

Field Name : revEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.304

Field Name : revEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.303

Field Name : revIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.302

Field Name : revIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.301

Field Name : revIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.300

Field Name : revIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.299

Field Name : fwdEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.298

Field Name : fwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.297

Field Name : fwdEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.296

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.295

Field Name : fwdIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.294

Field Name : fwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.293

Field Name : fwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.292

Field Name : fwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.291

Field Name : revEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.290

Field Name : revIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.289

Field Name : fwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.288

Field Name : fwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.287

Field Name : revEgressPacketsOthers
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.286

Field Name : revIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.285

Field Name : fwdEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.284

Field Name : fwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.283

Field Name : revEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.282

Field Name : revIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.281

Field Name : fwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.280

Field Name : fwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.279

Field Name : revEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.278

Field Name : revIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.277

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.276

Field Name : fwdIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.275

Field Name : revEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.274

Field Name : revIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.273

Field Name : fwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.272

Field Name : fwdIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.271

Field Name : revEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.270

Field Name : revIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.269

Field Name : fwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.268

Field Name : fwdIngressPacketsUdp
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.267

Field Name : revEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.266

Field Name : revIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.265

Field Name : fwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.264

Field Name : fwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.263

Field Name : revEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.262

Field Name : revIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.261

Field Name : fwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.260

Field Name : fwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.259

Field Name : adcPortAllocationIneligible
Field Type : CounterBasedGauge64
Field Status : current
Description : ADC Port Allocation Not Allowed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.258

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : adcPortAllocationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ADC Port Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.257

Field Name : natPoolSamePortBatchUdpFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Simultaneous Batch Allocation UDP Port Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.256

Field Name : userQuotaUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Marked Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.255

Field Name : userQuotaUnusableDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Unusable Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.254

Field Name : mgcpAlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.253

Field Name : mgcpAlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.252

Field Name : mgcpAlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.251

Field Name : mgcpAlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.250

Field Name : mgcpAlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.249

Field Name : mgcpAlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current

Description : MGCP ALG Port Pair Allocated From Partition

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.248

Field Name : mgcpAlgPortPairAllocFromConsecutive

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Port Pair Allocated From Consecutive

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.247

Field Name : mgcpAlgCreateRtcpFullconeFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Create RTCP Full-cone Session Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.246

Field Name : mgcpAlgCreateRtpFullconeFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Create RTP Full-cone Session Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.245

Field Name : mgcpAlgCreateSingleFullconeFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Create Single RTP or RTCP Full-cone Session Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.244

Field Name : mgcpAlgAllocSinglePortFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Alloc Single RTP or RTCP NAT Port Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.243

Field Name : mgcpAlgAllocRtpRtcpPortFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Alloc RTP/RTCP NAT Ports Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.242

Field Name : mgcpAlgReuseRtpRtcpFullcone

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Reuse RTP/RTCP Full-cone Session

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.241

Field Name : mgcpAlgRtcpFullconeMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG RTCP Full-cone NAT Port Mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.240

Field Name : mgcpAlgSingleRtcpFullcone

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Single RTCP Full-cone Found

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.239

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : mgcpAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.238

Field Name : mgcpAlgReleasePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Release NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.237

Field Name : mgcpAlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.236

Field Name : mgcpAlgAllocPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.235

Field Name : mgcpAlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.234

Field Name : mgcpAlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.233

Field Name : mgcpAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.232

Field Name : mgcpAlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.231

Field Name : mgcpAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.230

Field Name : natPoolAddFreeBatchFailed
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : Add Batch to Quota Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.229

Field Name : natPoolAttemptAddingMultipleFreeBatches
Field Type : CounterBasedGauge64
Field Status : current
Description : Attempt Adding Multiple Free Batches to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.228

Field Name : haPrefixNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : HA No Matching Prefix Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.227

Field Name : sixRdNoMatchDomainDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Sixrd Packets Domain Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.226

Field Name : fullconeInboundNatPoolMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session NAT Pool Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.225

Field Name : dstPrefixMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Destination Prefix Mismatch Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.224

Field Name : standbyClassListDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Class-List Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.223

Field Name : natPoolNotFoundOnFree
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.222

Field Name : quotaExtTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Ext Too Many
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.221

Field Name : natPoolForceDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Force Delete
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.220

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : haPortOverloadingForNewUserSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for New User Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.219

Field Name : haPortOverloadingForNewUser
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for New User
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.218

Field Name : haPortOverloadingForQuotaExceededRaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Race Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.217

Field Name : haPortOverloadingForQuotaExceededRace
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Race
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.216

Field Name : haPortOverloadingForQuotaExceededSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.215

Field Name : haPortOverloadingForQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.214

Field Name : haPortOverloadingForNoPortsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for No Ports Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.213

Field Name : haPortOverloadingForNoPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for No Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.212

Field Name : haPortOverloadingAttemptFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading Attempt Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.211

Field Name : portOverloadingForNewUserSuccess
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : Port Overloading for New User Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.210

Field Name : portOverloadingForNewUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for New User
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.209

Field Name : portOverloadingForQuotaExceededRaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Race Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.208

Field Name : portOverloadingForQuotaExceededRace
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Race
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.207

Field Name : portOverloadingForQuotaExceededSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.206

Field Name : portOverloadingForQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.205

Field Name : portOverloadingForNoPortsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for No Ports Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.204

Field Name : portOverloadingForNoPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for No Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.203

Field Name : portOverloadingSmpFreePortFromQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Port From Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.202

Field Name : portOverloadingSmpFreePort
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.201

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : portOverloadingSmpFreeNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free No Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.200

Field Name : portOverloadingSmpFreeDecFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Dec Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.199

Field Name : portOverloadingSmpPutInDelQFromConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free From Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.198

Field Name : portOverloadingSmpFreeUdpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP UDP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.197

Field Name : portOverloadingSmpFreeTcpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP TCP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.196

Field Name : portOverloadingSmpInsertedUdpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP UDP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.195

Field Name : portOverloadingSmpInsertedTcpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP TCP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.194

Field Name : portOverloadingSmpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.193

Field Name : portOverloadingSmpMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.192

Field Name : portOverloadingSmpMemAllocated
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : Port Overloading SMP Session Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.191

Field Name : portOverloadingConnFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Conn Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.190

Field Name : portOverloadingConnFreeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Conn Free Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.189

Field Name : portOverloadingAttemptFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Attempt Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.188

Field Name : portOverloadingAttemptDiffPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Different Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.187

Field Name : portOverloadingAttemptSamePartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Same Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.186

Field Name : portOverloadingAttemptConsecutivePorts
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading on Consecutive Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.185

Field Name : portOverloadingIncOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Inc Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.184

Field Name : portOverloadingFreePortBatchOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Free Port Batch on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.183

Field Name : portOverloadingFreePortOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Free Port on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.182

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : portOverloadingDecOnFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Decrement on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.181

Field Name : portOverloadingDecOnConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Decrement on Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.180

Field Name : portOverloadingInc
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Increment
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.179

Field Name : portOverloadingAssignUserPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Assign User Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.178

Field Name : portOverloadingAssignUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Assign User
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.177

Field Name : portOverloadingOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.176

Field Name : portOverloadingDestinationConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Destination Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.175

Field Name : portBatchContainerAllocRaceFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Container Race Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.174

Field Name : portBatchContainerAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Container Alloc Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.173

Field Name : specificPortAllocatedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : Specific Port Allocated from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.172

Field Name : specificPortAllocatedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.171

Field Name : specificPortAllocatedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.170

Field Name : portBatchFreedFromQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Freed From Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.169

Field Name : portBatchAllocatedToQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Allocated to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.168

Field Name : portFreedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.167

Field Name : portFreedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.166

Field Name : portFreedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.165

Field Name : portAllocatedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.164

Field Name : portAllocatedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.163

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : portAllocatedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.162

Field Name : poolPortBatchPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.161

Field Name : partitionPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.160

Field Name : consecutivePortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Consecutive Pool
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.159

Field Name : badPortToFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Freeing Bad Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.158

Field Name : haRcvPortNotInPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Not in Port Batch on Sync Rcv
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.157

Field Name : haSendPortBatchNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Not Found on Sync Send
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.156

Field Name : haSyncPortBatchRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Extension Sync Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.155

Field Name : haSyncPortBatchSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Extension Sync Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.154

Field Name : quotaExtensionRemoveNotFound
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : Quota Extension Not Found on Remove
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.153

Field Name : quotaExtensionRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Removed from Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.152

Field Name : quotaExtensionAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Added to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.151

Field Name : radiusQueryQuotaExtAllocRaceFree
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Query Container Alloc Race Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.150

Field Name : radiusQueryQuotaExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Query Container Alloc (No Memory)
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.149

Field Name : portBatchFreeWrongPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Free Wrong Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.148

Field Name : portBatchFreePortNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Port Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.147

Field Name : portBatchFreeQuotaNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Quota Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.146

Field Name : portBatchQuotaExtensionAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Extension Alloc Failure (No memory)
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.145

Field Name : h323AlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.144

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : h323AlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.143

Field Name : h323AlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.142

Field Name : h323AlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.141

Field Name : h323AlgPortPairAllocFromPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.140

Field Name : h323AlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.139

Field Name : h323AlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.138

Field Name : h323AlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.137

Field Name : h323AlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.136

Field Name : h323AlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.135

Field Name : h323AlgAllocSinglePortFailure
Field Type : CounterBasedGauge64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Status : current
Description : H323 ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.134

Field Name : h323AlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.133

Field Name : h323AlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.132

Field Name : h323AlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.131

Field Name : h323AlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.130

Field Name : h323AlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.129

Field Name : h323AlgReleasePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Release NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.128

Field Name : h323AlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.127

Field Name : h323AlgAllocPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.126

Field Name : h323AlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.125

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : h323AlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.124

Field Name : h323AlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.123

Field Name : h323AlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.122

Field Name : h323AlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.121

Field Name : sipAlgPortPairAllocFromQuotaPoolPortBatchWithFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Port Batch Version 2 with Frag Free Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.120

Field Name : sipAlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.119

Field Name : sipAlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.118

Field Name : sipAlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.117

Field Name : sipAlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.116

Field Name : sipAlgPortPairAllocFromPoolPortBatch

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.115

Field Name : sipAlgPortPairAllocFromPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.114

Field Name : sipAlgPortPairAllocFromConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Port Pair Allocated From Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.113

Field Name : sipAlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.112

Field Name : sipAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.111

Field Name : sipAlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.110

Field Name : sipAlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.109

Field Name : sipAlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.108

Field Name : sipAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.107

Field Name : sipAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG RTCP Full-cone NAT Port Mismatch

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.106

Field Name : sipAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.105

Field Name : sipAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.104

Field Name : sipAlgReleaseContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Release Contact NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.103

Field Name : sipAlgCreateContactFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Contact Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.102

Field Name : sipAlgAllocContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc Contact NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.101

Field Name : sipAlgContactFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Contact Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.100

Field Name : sipAlgReuseContactFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse Contact Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.99

Field Name : sipAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.98

Field Name : sipAlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.97

Field Name : sipAlgNoQuota

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.96

Field Name : udpAlgAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Port Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.95

Field Name : udpAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.94

Field Name : udpAlgEimMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Endpoint-Independent Mapping Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.93

Field Name : udpAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.92

Field Name : totalIcmpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.91

Field Name : totalIcmpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.90

Field Name : totalUdpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.89

Field Name : totalUdpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.88

Field Name : totalTcpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.87

Field Name : totalTcpAllocatedShadow

Field Type : CounterBasedGauge64

Field Status : current

Description : Total TCP Ports Allocated

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.86

Field Name : newUserResourceUnavailableOther

Field Type : CounterBasedGauge64

Field Status : current

Description : Other New User NAT Resource Unavailable

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.85

Field Name : newUserResourceUnavailableIcmp

Field Type : CounterBasedGauge64

Field Status : current

Description : ICMP New User NAT Resource Unavailable

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.84

Field Name : newUserResourceUnavailableUdp

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP New User NAT Resource Unavailable

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.83

Field Name : newUserResourceUnavailableTcp

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP New User NAT Resource Unavailable

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.82

Field Name : natPortUnavailable

Field Type : CounterBasedGauge64

Field Status : current

Description : Total NAT Port Unavailable

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.81

Field Name : natPortUnavailableOther

Field Type : CounterBasedGauge64

Field Status : current

Description : Other NAT Port Unavailable

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.80

Field Name : extendedQuotaMismatched

Field Type : CounterBasedGauge64

Field Status : current

Description : Extended User-Quota Mismatched

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.79

Field Name : dataSessionUserQuotaMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : Data Session Counter Per User Mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.78

Field Name : dataSessionFreedShadow

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.77

Field Name : dataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.76

Field Name : fullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.75

Field Name : fullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.74

Field Name : udpAlgFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ALG Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.73

Field Name : udpAlgFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ALG Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.72

Field Name : udpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.71

Field Name : udpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.70

Field Name : tcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.69

Field Name : tcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions created

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.68

Field Name : userQuotaNotFound

Field Type : CounterBasedGauge64

Field Status : current

Description : User-Quota Not Found

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.67

Field Name : icmpOutOfStateUqeDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : Total User Queue Exceeded ICMP notification dropped

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.66

Field Name : icmpOutOfStateUqeHostUnreachableSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Total User Quota Exceeded ICMP host unreachable sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.65

Field Name : icmpOutOfStateUqeAdminFilteredSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Total User Quota Exceeded ICMP admin filtered sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.64

Field Name : tcpOutOfStateRstDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Out of State TCP RST dropped

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.63

Field Name : tcpOutOfStateRstSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Out of State TCP RST sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.62

Field Name : totalUserQuotaFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Quota Structure Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.61

Field Name : totalUserQuotaPutInDelQ

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Quota Structure Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.60

Field Name : totalUserQuotaCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Quota Structure Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.59

Field Name : prefixQuotaFailure

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Total Prefix Quota Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.58

Field Name : prefixQuotaPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Prefix Quota Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.57

Field Name : prefixQuotaCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Prefix Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.56

Field Name : userQuotaPutInDelQShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User-Quota Put In Del Q
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.55

Field Name : quotaDeleteNotInBucket
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Delete Not In Bucket
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.54

Field Name : quotaMarkedDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.53

Field Name : userQuotaCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User-Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.52

Field Name : userQuotaMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.51

Field Name : userQuotaMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.50

Field Name : noClassListMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No Class-List Match

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.49

Field Name : lidPassThrough

Field Type : CounterBasedGauge64

Field Status : current

Description : LSN LID Pass-through

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.48

Field Name : lidDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : LSN LID Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.47

Field Name : sourceMatchesPrefix

Field Type : CounterBasedGauge64

Field Status : current

Description : Source Address Prefix Match Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.46

Field Name : l3

Field Type : CounterBasedGauge64

Field Status : current

Description : Layer 3 Forwarded Packets

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.45

Field Name : noRadiusProfileMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : No RADIUS Profile Match

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.44

Field Name : haNatPoolBatchTypeMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : HA NAT Pool Batch Type Mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.43

Field Name : haNatPoolUnusable

Field Type : CounterBasedGauge64

Field Status : current

Description : HA NAT Pool Unusable

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.42

Field Name : natPoolUnusable

Field Type : CounterBasedGauge64

Field Status : current

Description : NAT Pool Unusable

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.41

Field Name : portOverloadingSmpFreeUdp

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Port Overloading Session Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.40

Field Name : portOverloadingSmpFreeTcp

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.39

Field Name : portOverloadingSmpInsertedUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.38

Field Name : portOverloadingSmpInsertedTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.37

Field Name : totalUdpOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.36

Field Name : totalTcpOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.35

Field Name : eifLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Filtering Inbound Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.33

Field Name : inboundFiltered
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Dependent Filtering Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.32

Field Name : endpointIndepFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Filtering Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.31

Field Name : endpointIndepMapMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Endpoint-Independent Mapping Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.30

Field Name : fullconeSelfHairpinningDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Self-Hairpinning Drop

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.29

Field Name : hairpin

Field Type : CounterBasedGauge64

Field Status : current

Description : Hairpin Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.28

Field Name : fullconeFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Full-cone Session Creation Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.27

Field Name : udpFullconeFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Full-cone Session Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.26

Field Name : udpFullconeCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Full-cone Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.25

Field Name : tcpFullconeFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Full-cone Session Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.24

Field Name : tcpFullconeCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Full-cone Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.23

Field Name : dataSesnRateUserQuotaExceeded

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn Rate User-Quota Exceeded

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.22

Field Name : dataSesnUserQuotaExceeded

Field Type : CounterBasedGauge64

Field Status : current

Description : Data Session User-Quota Exceeded

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.21

Field Name : extendedQuotaExceeded

Field Type : CounterBasedGauge64

Field Status : current

Description : Extended User-Quota Exceeded

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.20

Field Name : extendedQuotaMatched

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.19

Field Name : icmpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.18

Field Name : udpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.17

Field Name : tcpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.16

Field Name : newUserResourceUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.15

Field Name : natPortUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.14

Field Name : natPortUnavailableUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.13

Field Name : natPortUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.12

Field Name : userQuotaFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.11

Field Name : userQuotaPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Freed

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.10

Field Name : userQuotaCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : User-Quota Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.9

Field Name : dataSessionFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : Data Session Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.8

Field Name : dataSessionCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : Data Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.7

Field Name : totalIcmpFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : Total ICMP Ports Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.6

Field Name : totalIcmpAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : Total ICMP Ports Allocated

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.5

Field Name : totalUdpFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : Total UDP Ports Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.4

Field Name : totalUdpAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : Total UDP Ports Allocated

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.3

Field Name : totalTcpFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : Total TCP Ports Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.2

Field Name : totalTcpAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : Total TCP Ports Allocated

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.1.1.1

Field Name : tcamCounter

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flow Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.20

Field Name : tcamFree
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flows Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.19

Field Name : tcamCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flows Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.18

Field Name : entryInvalidateServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Invalidate due to server down
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.17

Field Name : entryForceHwInvalidate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Force HW Invalidate
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.16

Field Name : entryAgeOutInvalidDst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - invalid dst
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.15

Field Name : entryAgeOutTcpRst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP RST
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.14

Field Name : entryAgeOutTcpFin
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP FIN
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.13

Field Name : entryAgeOutIdle
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.12

Field Name : entryAgeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.11

Field Name : entryCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entries Count

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.10

Field Name : entryFreeNoSwEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entry Freed - no software entry

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.9

Field Name : entryFreeNoConn

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entry Freed - no matched conn

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.8

Field Name : entryFreeNoHwProg

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entry Freed - no HW prog

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.7

Field Name : entryFreeOppEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entries Freed - opposite tuple entry aged-out

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.6

Field Name : entryFree

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entries Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.5

Field Name : entryCreateFailMaxEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entry Creation Failed - max entries exceeded

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.4

Field Name : entryCreateFailServerDown

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entry Creation Failed - server down

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.3

Field Name : entryCreateFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entry Creation Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.2

Field Name : entryCreate

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.18.9.1.1

Field Name : haAllocMapConflicts
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Allocate Mapping Conflicts
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.9

Field Name : haSelectAddrFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Allocate Address Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.8

Field Name : haMapMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Mapping Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.7

Field Name : mapNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Mapping to be Released Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.6

Field Name : allocMapRace
Field Type : CounterBasedGauge64
Field Status : current
Description : Mapping Exists When Allocating Address Mapping
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.5

Field Name : mapDbfFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Address Mapping Double Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.4

Field Name : mapAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : One-to-One Address Mapping Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.3

Field Name : totalMapFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total One-to-One Address Mapping Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.2

Field Name : totalMapAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total One-to-One Address Mapping Allocated

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.14.1.1.1

Field Name : cgnv6OneToOnePoolSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.115.14.2.1.1

Field Name : cgnv6OneToOnePoolSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.115.14.2.1.1.1

Field Name : freeAddress

Field Type : CounterBasedGauge64

Field Status : current

Description : Free Address

OID : 1.3.6.1.4.1.22610.2.4.10.115.14.2.1.1.1.4

Field Name : usedAddress

Field Type : CounterBasedGauge64

Field Status : current

Description : Used Address

OID : 1.3.6.1.4.1.22610.2.4.10.115.14.2.1.1.1.3

Field Name : totalAddress

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Address

OID : 1.3.6.1.4.1.22610.2.4.10.115.14.2.1.1.1.2

Field Name : cgnv6OneToOnePoolName

Field Type : String

Field Status : current

Description : Specify pool name or pool group

OID : 1.3.6.1.4.1.22610.2.4.10.115.14.2.1.1.1.1

Field Name : cgnv6Dns64VServerPortSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1

Field Name : cgnv6Dns64VServerPortSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1

Field Name : cgnv6Dns64VirtualServerPortSlowestRspTime

Field Type : CounterBasedGauge64

Field Status : current

Description : Slowest response time

OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.29

Field Name : cgnv6Dns64VirtualServerPortFastestRspTime

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Fastest response time
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.28

Field Name : lastRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Last response time
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.27

Field Name : currConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connection rate
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.26

Field Name : cgnv6Dns64VirtualServerPortPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.25

Field Name : totalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total successful requests
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.24

Field Name : cgnv6Dns64VirtualServerPortTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total requests
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.23

Field Name : cgnv6Dns64VirtualServerPortCurrentReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Current requests
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.22

Field Name : compressionMissTemplateExclusion
Field Type : CounterBasedGauge64
Field Status : current
Description : Compression miss template exclusion
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.21

Field Name : compressionMissNoClient
Field Type : CounterBasedGauge64
Field Status : current
Description : Compression miss no client
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.20

Field Name : compressionMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of requests NOT compressed

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.19

Field Name : compressionHit
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of requests compressed
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.18

Field Name : compressionBytesAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : Data out of compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.17

Field Name : compressionBytesBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : Data into compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.16

Field Name : esTotalFailureActions
Field Type : CounterBasedGauge64
Field Status : current
Description : Total failure actions
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.15

Field Name : totalMfDnsPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total MF DNS packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.14

Field Name : totalDnsPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total DNS packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.13

Field Name : cgnv6Dns64VServerPortTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total reverse packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.12

Field Name : cgnv6Dns64VServerPortTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Total reverse bytes
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.11

Field Name : cgnv6Dns64VServerPortTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total forward packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.10

Field Name : cgnv6VServerPortTotalFwdBytes

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Total forward bytes
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.9

Field Name : cgnv6Dns64VServerPortTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.8

Field Name : toatalTcpConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.7

Field Name : cgnv6Dns64VServerPortTotalL7Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L7 connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.6

Field Name : cgnv6Dns64VServerPortTotalL4Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L4 connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.5

Field Name : cgnv6Dns64VServerPortCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connection
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.4

Field Name : cgnv6Dns64VServerProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.3

Field Name : cgnv6Dns64VServerPortNumber
Field Type : INTEGER
Field Status : current
Description : Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.2

Field Name : cgnv6Dns64VirtualserverName
Field Type : String
Field Status : current
Description : CGNV6 Virtual Server Name
OID : 1.3.6.1.4.1.22610.2.4.10.115.11.2.1.1.1.1

Field Name : cgnv6NatPoolSTable
Field Type : TABLE
Field Status : current
Description :

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1

Field Name : cgnv6NatPoolSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1

Field Name : ipTotalCluster
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Total in Scaleout Cluster
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.36

Field Name : userOccupationPercentage
Field Type : CounterBasedGauge64
Field Status : current
Description : User Occupation Percentage
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.35

Field Name : maxUsersAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Users Allowed
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.34

Field Name : tcpPortUsagePercentage
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Usage Percentage
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.33

Field Name : tcpTotalPort
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Total Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.32

Field Name : udpPortUsagePercentage
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Usage Percentage
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.31

Field Name : udpTotalPort
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Total Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.30

Field Name : ipTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Total
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.29

Field Name : ipFree

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : IP Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.28

Field Name : ipUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Used
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.27

Field Name : tcpPortOverloadFree
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.26

Field Name : tcpPortOverloadCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.25

Field Name : tcpPortOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.24

Field Name : tcpHitFull
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Hit Full
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.23

Field Name : tcpPeak
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Peak
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.22

Field Name : tcpRsvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Reserved
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.21

Field Name : tcpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP total
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1.20

Field Name : tcpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Freed

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.19

Field Name : tcp

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP

OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.18

Field Name : udpPortOverloadFree

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Port Overloading Session Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.17

Field Name : udpPortOverloadCreate

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Port Overloading Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.16

Field Name : udpPortOverloaded

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Port Overloaded

OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.15

Field Name : udpHitFull

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Hit Full

OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.14

Field Name : udpPeak

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Peak

OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.13

Field Name : udpRsvd

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Reserved

OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.12

Field Name : udpTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Total

OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.11

Field Name : udpFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.10

Field Name : udp

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.9

Field Name : icmpHitFull
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Hit Full
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.8

Field Name : icmpPeak
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Peak
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.7

Field Name : icmpRsvd
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Reserved
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.6

Field Name : icmpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Total
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.5

Field Name : icmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.4

Field Name : icmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.3

Field Name : users
Field Type : CounterBasedGauge64
Field Status : current
Description : Users
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.2

Field Name : cgnv6NatPoolPoolName
Field Type : String
Field Status : current
Description : Specify pool name
OID : 1.3.6.1.4.1.22610.2.4.10.115.8.1.1.1.1

Field Name : radiusInterCardDupRedir
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packet dropped as redirected by other blade (S0)

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.44

Field Name : radiusPacketsDroppedNotLo

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS packets dropped dest not loopback (S0)

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.43

Field Name : radiusPacketsProcessLocal

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS packets processed locally without redirection (S0)

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.42

Field Name : radiusPacketsRedirectFailDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS packets dropped due to redirect failure (S0)

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.41

Field Name : radiusPacketsRedirected

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS packets redirected (S0)

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.40

Field Name : interCardMsgFailDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Inter-Card Message Fail Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.39

Field Name : haSyncNoKeyVapDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Record Sync No key dropped

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.38

Field Name : ipAddRaceDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Radius Entry IP Add Race Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.37

Field Name : ipMismatchDelete

Field Type : CounterBasedGauge64

Field Status : current

Description : Radius Entry IP Mismatch Delete

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.36

Field Name : acctOnDupRequest

Field Type : CounterBasedGauge64

Field Status : current

Description : Duplicate RADIUS Acct On Request

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.35

Field Name : acctOnFiltersFull

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Acct On Request Ignored(Filters Full)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.34

Field Name : haSyncDeleteRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Delete Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.33

Field Name : haSyncCreateRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Create Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.32

Field Name : haSyncDeleteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Delete Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.31

Field Name : haSyncCreateSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Create Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.30

Field Name : memFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.29

Field Name : memAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.28

Field Name : memAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.27

Field Name : smpInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP in RML
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.26

Field Name : smpMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Freed

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.25

Field Name : smpMemAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.24

Field Name : smpMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.23

Field Name : smpDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.17

Field Name : smpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.16

Field Name : invalidKey
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Request has Invalid Key Field
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.15

Field Name : ipv6PrefixLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Framed IPV6 Prefix Length Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.14

Field Name : haStandbyDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.13

Field Name : secretNotConfiguredDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Secret Not Configured Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.12

Field Name : radiusTableFull
Field Type : TABLE
Field Status : current
Description : RADIUS Request Dropped (Table Full)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.11

Field Name : requestIgnored

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Ignored
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.10

Field Name : requestMalformedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Malformed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.9

Field Name : requestNoKeyVapDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request No Key Attribute Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.8

Field Name : requestBadSecretDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Bad Secret Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.7

Field Name : radiusRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Dropped (Malformed Packet)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.6

Field Name : radiusRequestReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.5

Field Name : customReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom attribute Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.4

Field Name : imsiReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : IMSI Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.3

Field Name : imeiReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : IMEI Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.2

Field Name : msisdnReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : MSISDN Received

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.11.1.1.1

Field Name : h245DynamicAddrExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H245 Dynamic Address Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.11

Field Name : tcpOutOfOrderDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-of-Order Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.10

Field Name : rewriteFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 Message Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.9

Field Name : connExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 Packet Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.8

Field Name : messageCrossMultiPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 Message Cross Multiple Packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.7

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.6

Field Name : fastStart
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 FastStart
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.5

Field Name : h245Tunneled
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H245 Tunnelled Message
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.4

Field Name : h245ctlMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H245 Media Control Message
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.3

Field Name : h225csMessage

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H225 Call Signaling Message
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.2

Field Name : h225rasMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 H225 RAS Message
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.8.1.1

Field Name : tcpOutOfOrderDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-of-Order Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.19

Field Name : rewriteFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Message Rewrite Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.18

Field Name : modifyFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Message Modify Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.17

Field Name : sdpAllocPortMapFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Alloc SDP Port Map Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.16

Field Name : sdpAllocPortMapSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Alloc SDP Port Map Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.15

Field Name : sdpOpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Operate SDP Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.14

Field Name : sdpProcessCandidateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Operate SDP Media Candidate Attribute Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.13

Field Name : thirdPartySdp
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Third-Party SDP

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.12

Field Name : connExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Create Connection Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.11

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.10

Field Name : rsip
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP RSIP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.9

Field Name : rqnt
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP RQNT
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.8

Field Name : ntfy
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP NTFY
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.7

Field Name : mdcx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP MDCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.6

Field Name : epcf
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP EPCF
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.5

Field Name : dlcx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP DLCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.4

Field Name : crcx
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP CRCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.3

Field Name : aucx

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP AUCX
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.2

Field Name : auep
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP AUEP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.7.1.1

Field Name : helperFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.43

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.42

Field Name : helperDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Already Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.41

Field Name : helperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.40

Field Name : helperFound
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.39

Field Name : smpConnAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.38

Field Name : tcpOutOfOrderDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-of-Order Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.37

Field Name : rewriteFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Message Rewrite Failure

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.36

Field Name : modifyFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Message Modify Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.35

Field Name : sdpAllocPortMapFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Alloc SDP Port Map Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.34

Field Name : sdpAllocPortMapSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Alloc SDP Port Map Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.33

Field Name : sdpOpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate SDP Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.32

Field Name : sdpProcessCandidateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate SDP Media Candidate Attribute Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.31

Field Name : thirdPartySdp
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Third-Party SDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.30

Field Name : insideContactPortMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Inside Contact Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.29

Field Name : outsideContactPortMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Outside Contact Port Mismatch NAT Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.28

Field Name : allocContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Alloc Contact Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.27

Field Name : connExtCreationFailure

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Create Connection Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.26

Field Name : thirdPartyRegistration
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Third-Party Registration
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.25

Field Name : contentLengthHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Content-Length Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.24

Field Name : recordRouteHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Record-Route Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.23

Field Name : routeHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Route Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.22

Field Name : toHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate To Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.21

Field Name : fromHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate From Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.20

Field Name : contactHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Contact Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.19

Field Name : viaHdrOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Via Header Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.18

Field Name : reqUriOpFailrue
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Operate Request Uri Failure

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.17

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.16

Field Name : lsnAlgSipMethodUnkown
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method UNKNOWN
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.15

Field Name : lsnAlgSipMethodUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method UPDATE
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.14

Field Name : lsnAlgSipMethodMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method MESSAGE
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.13

Field Name : lsnAlgSipMethodRefer
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method REFER
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.12

Field Name : lsnAlgSipMethodInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method INFO
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.11

Field Name : lsnAlgSipMethodPublish
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method PUBLISH
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.10

Field Name : lsnAlgSipMethodNotify
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method NOTIFY
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.9

Field Name : lsnAlgSipMethodSubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method SUBSCRIBE
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.8

Field Name : lsnAlgSipMethodPrack

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method PRACK
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.7

Field Name : lsnAlgSipMethodOption
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method OPTIONS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.6

Field Name : lsnAlgSipMethodBye
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method BYE
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.5

Field Name : lsnAlgSipMethodCancel
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method CANCEL
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.4

Field Name : lsnAlgSipMethodAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method ACK
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.3

Field Name : lsnAlgSipMethodInvite
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method INVITE
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.2

Field Name : lsnAlgSipMethodRegister
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Method REGISTER
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.6.1.1

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP ALG App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.43

Field Name : haStreamSmpAcquireFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Session Acquire Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.42

Field Name : haStreamSmpReused
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Session Reused

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.41

Field Name : haExtensionFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Conn Extension Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.40

Field Name : haDataExists

Field Type : CounterBasedGauge64

Field Status : current

Description : HA New Data Session Already Exists

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.39

Field Name : haControlClosed

Field Type : CounterBasedGauge64

Field Status : current

Description : HA New Data Control Session Closed

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.38

Field Name : haDataNoSmp

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Data Session SMP Not Found

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.37

Field Name : haDataSessionRcv

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Data Session Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.36

Field Name : haDataSessionSent

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Data Session Sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.35

Field Name : haPortAllocationFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Stream Port Allocation Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.34

Field Name : haStreamExists

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Stream Already Exists

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.33

Field Name : haStreamIncompatible

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Incompatible Streams Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.32

Field Name : haStreamsRcv

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : HA Streams Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.31

Field Name : haStreamsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Streams Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.30

Field Name : dataFreeSmpNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Free SMP Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.29

Field Name : dataFreeSmpRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Free SMP Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.28

Field Name : crossCpuRcvFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Receive Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.27

Field Name : crossCpuCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Creation
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.26

Field Name : crossCpuNoSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU No Session Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.25

Field Name : crossCpuRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.24

Field Name : crossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.23

Field Name : rtcpReversed
Field Type : CounterBasedGauge64
Field Status : current
Description : RTCP Reverse Creation

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.22

Field Name : rtpReversed

Field Type : CounterBasedGauge64

Field Status : current

Description : RTP Reverse Creation

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.21

Field Name : dataSessionCreationFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : New Data Session Creation Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.20

Field Name : dataSessionExists

Field Type : CounterBasedGauge64

Field Status : current

Description : New Session Already Exists

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.19

Field Name : controlClosed

Field Type : CounterBasedGauge64

Field Status : current

Description : New Session Closed

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.18

Field Name : smpDeleted

Field Type : CounterBasedGauge64

Field Status : current

Description : New Session SMP Already Deleted

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.17

Field Name : natPoolStandby

Field Type : CounterBasedGauge64

Field Status : current

Description : New Session NAT Pool Standby

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.16

Field Name : smpReused

Field Type : CounterBasedGauge64

Field Status : current

Description : SMP Session Reused

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.15

Field Name : smpRemoved

Field Type : CounterBasedGauge64

Field Status : current

Description : SMP Session Removed

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.14

Field Name : smpInserted

Field Type : CounterBasedGauge64

Field Status : current

Description : SMP Session Inserted

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.13

Field Name : haRcv

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : HA RCV
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.12

Field Name : haSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.11

Field Name : cgnv6LsnAlgRtspNoSessionMem
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Creation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.10

Field Name : cgnv6LsnAlgRtspDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.9

Field Name : cgnv6LsnAlgRtspDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.8

Field Name : cgnv6LsnAlgRtspUnknownClientPortFromServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Server Replies With Unknown Client Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.7

Field Name : cgnv6LsnAlgRtspPortAllocationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Client Port Allocation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.6

Field Name : cgnv6LsnAlgRtspPortsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Client Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.5

Field Name : cgnv6LsnAlgRtspPortsAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Client Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.4

Field Name : cgnv6LsnAlgRtspStreamsCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Creation Failures

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.3

Field Name : cgnv6LsnAlgRtspStreamsFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : Streams Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.2

Field Name : cgnv6LsnAlgRtspStreamsCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : Streams Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.4.1.1

Field Name : controlFreeSmpAppTypeMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : Control Free SMP App Type Mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.48

Field Name : controlFreeNoSmp

Field Type : CounterBasedGauge64

Field Status : current

Description : Control Free No SMP

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.47

Field Name : controlFreeNoExt

Field Type : CounterBasedGauge64

Field Status : current

Description : Control Free No Ext

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.46

Field Name : controlFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : Control Session Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.45

Field Name : greFreeSmpAppTypeMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE Free SMP App Type Mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.44

Field Name : greFreeNoSmp

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE Free No SMP

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.43

Field Name : greFreeNoExt

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE Free No Ext

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.42

Field Name : greConnAlreadyExists

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.41

Field Name : greNoControlConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Control Conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.40

Field Name : greNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Rev Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.39

Field Name : greNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Fwd Route
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.38

Field Name : greConnExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.37

Field Name : greConnCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.36

Field Name : smpAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.35

Field Name : smpClientCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Client Call ID Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.34

Field Name : callReplyExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.33

Field Name : callReplyRetransmitAcquired
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit Acquired

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.32

Field Name : callReplyRetransmitWrongControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit Wrong Control
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.31

Field Name : callReplyRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.30

Field Name : callReplyCallIdUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Unknown Client Call ID
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.29

Field Name : callReqExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.28

Field Name : callReqNew
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request New
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.27

Field Name : callReqRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.26

Field Name : callReplyPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Reply
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.25

Field Name : callReqPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Request
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.24

Field Name : quotaDecNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Not Found on Decrement
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.23

Field Name : quotaIncNotFound

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Not Found on Increment
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.22

Field Name : quotaDec
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Decremented
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.21

Field Name : quotaInc
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Incremented
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.20

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP ALG App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.19

Field Name : haSmpInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.18

Field Name : haSmpConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : HA SMP Conflicts
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.17

Field Name : haCallRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.16

Field Name : haCallSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.15

Field Name : haOverwrite
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call ID Overwrites
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.14

Field Name : haConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Call ID Conflicts

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.13

Field Name : haNoMem

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Memory Allocation Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.12

Field Name : haRcv

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Info Received

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.11

Field Name : haSent

Field Type : CounterBasedGauge64

Field Status : current

Description : HA Info Sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.10

Field Name : extensionCreationFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Extension Creation Failures

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.9

Field Name : smpSessionCreationFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : SMP Session Creation Failures

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.8

Field Name : smpSessionsFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : SMP Sessions Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.7

Field Name : smpSessionsCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : SMP Sessions Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.6

Field Name : cgnv6LsnAlgPtptNoGreSessionMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : No Matching GRE Session

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.5

Field Name : cgnv6LsnAlgPtptGreSessionsFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE Sessions Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.4

Field Name : cgnv6LsnAlgPtptGreSessionsCreated

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.3

Field Name : cgnv6LsnAlgPptpMismatchedPnsCallId
Field Type : CounterBasedGauge64
Field Status : current
Description : Mismatched PNS Call ID
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.2

Field Name : cgnv6LsnAlgPptpCallsEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : Calls Established
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.3.1.1

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP ALG App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.18

Field Name : getConnExtFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Get Conn Extension Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.17

Field Name : pasvHelperCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Helper Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.16

Field Name : portHelperCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Helper Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.15

Field Name : pasvHelperUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Mode Helper Unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.14

Field Name : portHelperUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mode Helper Unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.13

Field Name : pasvHelperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Mode Helper Freed

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.12

Field Name : portHelperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mode Helper Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.11

Field Name : pasvHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Mode Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.10

Field Name : portHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mode Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.9

Field Name : pasvRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive Mode Reply Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.8

Field Name : portRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Mode Request Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.7

Field Name : lpsvReplies
Field Type : CounterBasedGauge64
Field Status : current
Description : LPSV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.6

Field Name : epsvReplies
Field Type : CounterBasedGauge64
Field Status : current
Description : EPSV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.5

Field Name : pasvReplies
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.4

Field Name : lpvtRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : LPRT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.3

Field Name : eprtRequests

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : EPRT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.2

Field Name : portRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.2.1.1

Field Name : natIpConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT IP Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.1.1.3

Field Name : placeholderDebug
Field Type : CounterBasedGauge64
Field Status : current
Description : Placeholder Debug
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.1.1.2

Field Name : cgnv6LsnAlgEspSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.1.1.1

Field Name : helperInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session in Remove List
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.7

Field Name : helperAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session already used
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.6

Field Name : helperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.5

Field Name : helperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed used
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.4

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.3

Field Name : helperCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : TFTP Helper Sessions created

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.2

Field Name : cgnv6LsnAlgTftpSessionCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : TFTP Client Sessions Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.5.9.1.1

Field Name : staticNatCrossCpuRrNoConnDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Static NAT Cross CPU Helper CPU RR packet dropped no conn

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.393

Field Name : crossCpuRrNoConnDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Packets CPU RR No Conn Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.392

Field Name : crossCpuRrLoopDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Packets Drop Due to CPU RR loop

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.391

Field Name : staticNatCrossCpuRrSelfSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Static NAT Cross CPU Helper CPU RR Self Sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.390

Field Name : crossCpuRrSelfSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Packets CPU RR Self Sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.389

Field Name : chassisIncorrectPu

Field Type : CounterBasedGauge64

Field Status : current

Description : chassis incorrect pu

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.388

Field Name : cgnv6lsnGlobalPortOverloadingPortFreeUdp

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Port Overloading NAT Port Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.387

Field Name : cgnv6lsnGlobalPortOverloadingPortFreeTcp

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading NAT Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.386

Field Name : cgnv6lsnGlobalPortOverloadingPortInsertedUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading NAT Port UDP Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.385

Field Name : cgnv6lsnGlobalPortOverloadingPortInsertedTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading NAT Port TCP Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.384

Field Name : revEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.383

Field Name : revEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.382

Field Name : revEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.381

Field Name : revEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.380

Field Name : revIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.379

Field Name : revIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.378

Field Name : revIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 201 and 800

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.377

Field Name : revIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.376

Field Name : fwdEgressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.375

Field Name : fwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.374

Field Name : fwdEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.373

Field Name : fwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.372

Field Name : fwdIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.371

Field Name : fwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.370

Field Name : fwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.369

Field Name : fwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.368

Field Name : revEgressBytesOthers

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.367

Field Name : revIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.366

Field Name : fwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.365

Field Name : fwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.364

Field Name : revEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.363

Field Name : revIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.362

Field Name : fwdEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.361

Field Name : fwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.360

Field Name : revEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.359

Field Name : revIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes ICMP

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.358

Field Name : fwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.357

Field Name : fwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.356

Field Name : revEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.355

Field Name : revIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.354

Field Name : fwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.353

Field Name : fwdIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.352

Field Name : revEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.351

Field Name : revIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.350

Field Name : fwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.349

Field Name : fwdIngressBytesUdp

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.348

Field Name : revEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.347

Field Name : revIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.346

Field Name : fwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.345

Field Name : fwdIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.344

Field Name : revEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.343

Field Name : revIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.342

Field Name : fwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.341

Field Name : fwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.340

Field Name : revEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets TCP

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.339

Field Name : revIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.338

Field Name : fwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.337

Field Name : fwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.336

Field Name : aclHttpDomainNodeExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ACL HTTP Domain Node Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.335

Field Name : adcPortAllocationIneligible
Field Type : CounterBasedGauge64
Field Status : current
Description : ADC Port Allocation Not Allowed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.334

Field Name : adcPortAllocationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ADC Port Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.333

Field Name : crossCpuHelperFreeNotFoundUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Cross CPU Helper Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.332

Field Name : crossCpuHelperFreeNotFoundTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Cross CPU Helper Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.331

Field Name : crossCpuHelperFreeNotFoundIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Cross CPU Helper Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.330

Field Name : crossCpuHelperFreeNotFoundIp

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : IP Cross CPU Helper Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.329

Field Name : crossCpuHelperCreatedIp
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.328

Field Name : crossCpuHelperCreatedIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.327

Field Name : crossCpuHelperCreatedTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.326

Field Name : crossCpuHelperCreatedUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.325

Field Name : crossCpuHelperCreatedEif
Field Type : CounterBasedGauge64
Field Status : current
Description : EIF Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.324

Field Name : crossCpuHelperCreatedEim
Field Type : CounterBasedGauge64
Field Status : current
Description : EIM Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.323

Field Name : natPoolSamePortBatchUdpFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Simultaneous Batch Allocation UDP Port Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.322

Field Name : userQuotaUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Marked Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.321

Field Name : userQuotaUnusableDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Unusable Drop

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.320

Field Name : mgcpAlgPortPairAllocFromQuotaPoolPortBatch

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Port Pair Allocated From Quota Pool Port Batch

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.319

Field Name : mgcpAlgPortPairAllocFromQuotaPartitionError

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Port Pair Allocated From Quota Partition Error

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.318

Field Name : mgcpAlgPortPairAllocFromQuotaPartition

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Port Pair Allocated From Quota Partition

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.317

Field Name : mgcpAlgPortPairAllocFromQuotaConsecutive

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Port Pair Allocated From Quota Consecutive

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.316

Field Name : mgcpAlgPortPairAllocFromPoolPortBatch

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Port Pair Allocated From Pool Port Batch

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.315

Field Name : mgcpAlgPortPairAllocFromPartition

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Port Pair Allocated From Partition

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.314

Field Name : mgcpAlgPortPairAllocFromConsecutive

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Port Pair Allocated From Consecutive

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.313

Field Name : mgcpAlgCreateRtcpFullconeFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Create RTCP Full-cone Session Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.312

Field Name : mgcpAlgCreateRtpFullconeFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : MGCP ALG Create RTP Full-cone Session Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.311

Field Name : mgcpAlgCreateSingleFullconeFailure

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.310

Field Name : mgcpAlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.309

Field Name : mgcpAlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.308

Field Name : mgcpAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.307

Field Name : mgcpAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.306

Field Name : mgcpAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.305

Field Name : mgcpAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.304

Field Name : mgcpAlgReleasePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Release NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.303

Field Name : mgcpAlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.302

Field Name : mgcpAlgAllocPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Alloc NAT Port Failure

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.301

Field Name : mgcpAlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.300

Field Name : mgcpAlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.299

Field Name : mgcpAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.298

Field Name : mgcpAlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.297

Field Name : mgcpAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : MGCP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.296

Field Name : natPoolAddFreeBatchFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Add Batch to Quota Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.295

Field Name : natPoolAttemptAddingMultipleFreeBatches
Field Type : CounterBasedGauge64
Field Status : current
Description : Attempt Adding Multiple Free Batches to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.294

Field Name : fullconeExtTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fullcone Extension Too Many
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.293

Field Name : fullconeExtAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fullcone Extension Added
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.292

Field Name : fullconeExtMemAllocInitFailure

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fullcone Extension Initialization Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.291

Field Name : fullconeExtMemAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fullcone Extension Memory Allocate Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.290

Field Name : fullconeExtMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fullcone Extension Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.289

Field Name : fullconeExtMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN Fullcone Extension Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.288

Field Name : natPoolNotFoundOnFree
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.287

Field Name : quotaExtTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Ext Too Many
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.286

Field Name : natPoolForceDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Force Delete
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.285

Field Name : haPortOverloadingForNewUserSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for New User Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.284

Field Name : haPortOverloadingForNewUser
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for New User
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.283

Field Name : haPortOverloadingForQuotaExceededRaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Race Success

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.282

Field Name : haPortOverloadingForQuotaExceededRace
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Race
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.281

Field Name : haPortOverloadingForQuotaExceededSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.280

Field Name : haPortOverloadingForQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.279

Field Name : haPortOverloadingForNoPortsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for No Ports Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.278

Field Name : haPortOverloadingForNoPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading for No Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.277

Field Name : haPortOverloadingAttemptFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Overloading Attempt Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.276

Field Name : portOverloadingForNewUserSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for New User Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.275

Field Name : portOverloadingForNewUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for New User
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.274

Field Name : portOverloadingForQuotaExceededRaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Race Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.273

Field Name : portOverloadingForQuotaExceededRace

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Race
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.272

Field Name : portOverloadingForQuotaExceededSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.271

Field Name : portOverloadingForQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.270

Field Name : portOverloadingForNoPortsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for No Ports Success
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.269

Field Name : portOverloadingForNoPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading for No Ports
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.268

Field Name : portOverloadingSmpFreePortFromQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Port From Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.267

Field Name : portOverloadingSmpFreePort
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.266

Field Name : portOverloadingSmpFreeNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free No Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.265

Field Name : portOverloadingSmpFreeDecFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free Dec Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.264

Field Name : portOverloadingSmpPutInDelQFromConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Free From Conn

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.263

Field Name : portOverloadingSmpFreeUdpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP UDP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.262

Field Name : portOverloadingSmpFreeTcpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP TCP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.261

Field Name : portOverloadingSmpInsertedUdpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP UDP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.260

Field Name : portOverloadingSmpInsertedTcpShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Port Overloading SMP TCP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.259

Field Name : portOverloadingSmpInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.258

Field Name : portOverloadingSmpMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.257

Field Name : portOverloadingSmpMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading SMP Session Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.256

Field Name : portOverloadingConnFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Conn Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.255

Field Name : portOverloadingConnFreeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Conn Free Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.254

Field Name : cgnv6lsnGlobalPortOverloadingAttemptFailed

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Overloading Attempt Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.253

Field Name : portOverloadingAttemptDiffPartition

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Overloading on Different Partition

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.252

Field Name : portOverloadingAttemptSamePartition

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Overloading on Same Partition

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.251

Field Name : portOverloadingAttemptConsecutivePorts

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Overloading on Consecutive Ports

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.250

Field Name : portOverloadingIncOverflow

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Overloading Inc Overflow

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.249

Field Name : portOverloadingFreePortBatchOnConflict

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Overloading Free Port Batch on Conflict

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.248

Field Name : portOverloadingFreePortOnConflict

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Overloading Free Port on Conflict

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.247

Field Name : portOverloadingDecOnFree

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Overloading Port Decrement on Free

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.246

Field Name : portOverloadingDecOnConflict

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Overloading Port Decrement on Conflict

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.245

Field Name : portOverloadingInc

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Overloading Port Increment

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.244

Field Name : portOverloadingAssignUserPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Assign User Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.243

Field Name : portOverloadingAssignUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Port Assign User
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.242

Field Name : portOverloadingOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.241

Field Name : portOverloadingDestinationConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Overloading Destination Conflict
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.240

Field Name : portBatchContainerAllocRaceFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Container Race Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.239

Field Name : portBatchContainerAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Container Alloc Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.238

Field Name : specificPortAllocatedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.237

Field Name : specificPortAllocatedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.236

Field Name : specificPortAllocatedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Allocated from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.235

Field Name : portBatchFreedFromQuota

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Freed From Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.234

Field Name : portBatchAllocatedToQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Allocated to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.233

Field Name : portFreedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.232

Field Name : portFreedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.231

Field Name : portFreedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.230

Field Name : portAllocatedFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.229

Field Name : portAllocatedFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.228

Field Name : portAllocatedFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Allocated from Quota Consecutive
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.227

Field Name : poolPortBatchPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.226

Field Name : partitionPortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Partition

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.225

Field Name : consecutivePortFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Freed from Consecutive Pool
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.224

Field Name : badPortToFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Freeing Bad Port
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.223

Field Name : haRcvPortNotInPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Not in Port Batch on Sync Rcv
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.222

Field Name : haSendPortBatchNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Not Found on Sync Send
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.221

Field Name : haSyncPortBatchRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Extension Sync Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.220

Field Name : haSyncPortBatchSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Batch Extension Sync Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.219

Field Name : quotaExtensionRemoveNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Not Found on Remove
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.218

Field Name : quotaExtensionRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Removed from Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.217

Field Name : quotaExtensionAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Added to Quota
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.216

Field Name : radiusQueryQuotaExtAllocRaceFree

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Query Container Alloc Race Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.215

Field Name : radiusQueryQuotaExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Query Container Alloc (No Memory)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.214

Field Name : portBatchFreeWrongPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Free Wrong Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.213

Field Name : portBatchFreePortNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Port Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.212

Field Name : portBatchFreeQuotaNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Quota Not Found on Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.211

Field Name : portBatchQuotaExtensionAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batch Extension Alloc Failure (No memory)
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.210

Field Name : h323AlgPortPairAllocFromQuotaPoolPortBatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Pool Port Batch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.209

Field Name : h323AlgPortPairAllocFromQuotaPartitionError
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Partition Error
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.208

Field Name : h323AlgPortPairAllocFromQuotaPartition
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Partition
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.207

Field Name : h323AlgPortPairAllocFromQuotaConsecutive
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Port Pair Allocated From Quota Consecutive

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.206

Field Name : h323AlgPortPairAllocFromPoolPortBatch

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 ALG Port Pair Allocated From Pool Port Batch

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.205

Field Name : h323AlgPortPairAllocFromPartition

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 ALG Port Pair Allocated From Partition

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.204

Field Name : h323AlgPortPairAllocFromConsecutive

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 ALG Port Pair Allocated From Consecutive

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.203

Field Name : h323AlgCreateRtcpFullconeFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 ALG Create RTCP Full-cone Session Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.202

Field Name : h323AlgCreateRtpFullconeFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 ALG Create RTP Full-cone Session Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.201

Field Name : h323AlgCreateSingleFullconeFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 ALG Create Single RTP or RTCP Full-cone Session Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.200

Field Name : h323AlgAllocSinglePortFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 ALG Alloc Single RTP or RTCP NAT Port Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.199

Field Name : h323AlgAllocRtpRtcpPortFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 ALG Alloc RTP/RTCP NAT Ports Failure

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.198

Field Name : h323AlgReuseRtpRtcpFullcone

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 ALG Reuse RTP/RTCP Full-cone Session

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.197

Field Name : h323AlgRtcpFullconeMismatch

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.196

Field Name : h323AlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.195

Field Name : h323AlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.194

Field Name : h323AlgReleasePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Release NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.193

Field Name : h323AlgCreateFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Create Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.192

Field Name : h323AlgAllocPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Alloc NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.191

Field Name : h323AlgFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.190

Field Name : h323AlgReuseFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Reuse Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.189

Field Name : h323AlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.188

Field Name : h323AlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : H323 ALG User-Quota Exceeded

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.187

Field Name : h323AlgNoQuota

Field Type : CounterBasedGauge64

Field Status : current

Description : H323 ALG User-Quota Not Found

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.186

Field Name : sipAlgPortPairAllocFromQuotaPoolPortBatchWithFrag

Field Type : CounterBasedGauge64

Field Status : current

Description : SIP ALG Port Pair Allocated From Quota Port Batch Version 2 with Frag Free Ports

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.185

Field Name : sipAlgPortPairAllocFromQuotaPoolPortBatch

Field Type : CounterBasedGauge64

Field Status : current

Description : SIP ALG Port Pair Allocated From Quota Pool Port Batch

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.184

Field Name : sipAlgPortPairAllocFromQuotaPartitionError

Field Type : CounterBasedGauge64

Field Status : current

Description : SIP ALG Port Pair Allocated From Quota Partition Error

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.183

Field Name : sipAlgPortPairAllocFromQuotaPartition

Field Type : CounterBasedGauge64

Field Status : current

Description : SIP ALG Port Pair Allocated From Quota Partition

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.182

Field Name : sipAlgPortPairAllocFromQuotaConsecutive

Field Type : CounterBasedGauge64

Field Status : current

Description : SIP ALG Port Pair Allocated From Quota Consecutive

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.181

Field Name : sipAlgPortPairAllocFromPoolPortBatch

Field Type : CounterBasedGauge64

Field Status : current

Description : SIP ALG Port Pair Allocated From Pool Port Batch

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.180

Field Name : sipAlgPortPairAllocFromPartition

Field Type : CounterBasedGauge64

Field Status : current

Description : SIP ALG Port Pair Allocated From Partition

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.179

Field Name : sipAlgPortPairAllocFromConsecutive

Field Type : CounterBasedGauge64

Field Status : current

Description : SIP ALG Port Pair Allocated From Consecutive

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.178

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : sipAlgCreateRtcpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.177

Field Name : sipAlgCreateRtpFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create RTP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.176

Field Name : sipAlgCreateSingleFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Single RTP or RTCP Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.175

Field Name : sipAlgAllocSinglePortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc Single RTP or RTCP NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.174

Field Name : sipAlgAllocRtpRtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc RTP/RTCP NAT Ports Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.173

Field Name : sipAlgReuseRtpRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse RTP/RTCP Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.172

Field Name : sipAlgRtcpFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG RTCP Full-cone NAT Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.171

Field Name : sipAlgSingleRtcpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTCP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.170

Field Name : sipAlgSingleRtpFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Single RTP Full-cone Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.169

Field Name : sipAlgReleaseContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : SIP ALG Release Contact NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.168

Field Name : sipAlgCreateContactFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Create Contact Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.167

Field Name : sipAlgAllocContactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Alloc Contact NAT Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.166

Field Name : sipAlgContactFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Contact Full-cone Session Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.165

Field Name : sipAlgReuseContactFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Reuse Contact Full-cone Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.164

Field Name : sipAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.163

Field Name : sipAlgQuotaIncFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.162

Field Name : sipAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.161

Field Name : udpAlgAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Port Allocation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.160

Field Name : udpAlgNoNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.159

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : udpAlgEimMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG Endpoint-Independent Mapping Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.158

Field Name : udpAlgNoQuota
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.157

Field Name : totalIcmpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.156

Field Name : totalIcmpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.155

Field Name : totalUdpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.154

Field Name : totalUdpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.153

Field Name : totalTcpFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.152

Field Name : totalTcpAllocatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.151

Field Name : newUserResourceUnavailableOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Other New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.150

Field Name : newUserResourceUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : ICMP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.149

Field Name : newUserResourceUnavailableUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.148

Field Name : newUserResourceUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.147

Field Name : natPortUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : Total NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.146

Field Name : natPortUnavailableOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Other NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.145

Field Name : extendedQuotaMismatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Mismatched
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.144

Field Name : dataSessionUserQuotaMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Counter Per User Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.143

Field Name : dataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.142

Field Name : dataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.141

Field Name : fullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.140

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.139

Field Name : udpAlgFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ALG Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.138

Field Name : udpAlgFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP ALG Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.137

Field Name : udpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.136

Field Name : udpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.135

Field Name : tcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.134

Field Name : tcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.133

Field Name : userQuotaNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.132

Field Name : icmpOutOfStateUqeDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Queue Exceeded ICMP notification dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.131

Field Name : icmpOutOfStateUqeHostUnreachableSent
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Total User Quota Exceeded ICMP host unreachable sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.130

Field Name : icmpOutOfStateUqeAdminFilteredSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User Quota Exceeded ICMP admin filtered sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.129

Field Name : tcpOutOfStateRstDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Out of State TCP RST dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.128

Field Name : tcpOutOfStateRstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Out of State TCP RST sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.127

Field Name : userQuotaPutInDelQShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User-Quota Put In Del Q
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.126

Field Name : quotaDeleteNotInBucket
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Delete Not In Bucket
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.125

Field Name : quotaMarkedDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.124

Field Name : userQuotaCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total User-Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.123

Field Name : userQuotaMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.122

Field Name : userQuotaMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.121

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fullconeForceDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session Force Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.120

Field Name : ipSlbCrossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : IP SLB Cross CPU Packets Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.119

Field Name : staticNatHaMapMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Mapping Mismatch on HA Standby
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.118

Field Name : staticNatCrossCpuHelperFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Helper Free Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.117

Field Name : staticNatCrossCpuHelperFreeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Helper Free Retry Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.116

Field Name : staticNatCrossCpuHelperFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Helper Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.115

Field Name : staticNatCrossCpuNoSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU No Session Found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.114

Field Name : staticNatCrossCpuBadL4
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Unsupported L4
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.113

Field Name : staticNatCrossCpuBadL3
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Unsupported L3
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.112

Field Name : staticNatCrossCpuRcv
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Static NAT Cross CPU Helper Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.111

Field Name : staticNatCrossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Helper Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.110

Field Name : staticNatCrossCpuHelperCpuMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Cross CPU Helper CPU Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.109

Field Name : staticNatCrossCpuHelperStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Static NAT Standby
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.108

Field Name : staticNatCrossCpuHelperDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Deleted for Static NAT
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.107

Field Name : staticNatCrossCpuHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Created for Static NAT
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.106

Field Name : freePortFromQuotaNoPortInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Free Port From Quota No Port Info
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.105

Field Name : freePortFromQuotaNoContainer
Field Type : CounterBasedGauge64
Field Status : current
Description : Free Port from Quota No Container
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.104

Field Name : portPairAllocBadMath
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Pair Alloc Bad Math
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.103

Field Name : portBatchIntervalMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Batch Port Interval Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.102

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : portBatchNumMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Specific Port Batch Num Ports Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.101

Field Name : quotaExtPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Put in Delete Queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.100

Field Name : quotaExtMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.99

Field Name : quotaExtMemAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.98

Field Name : quotaExtMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Quota Extension Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.97

Field Name : fragTunnelIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : DS-Lite ICMP Packet Too Big Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.96

Field Name : fragIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Packet Too Big Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.95

Field Name : sixrdTunnelFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Fragment IPv6-in-IPv4 Packet
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.94

Field Name : dsliteTunnelFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragment DS-Lite Packet
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.93

Field Name : frag
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Fragmented Packets

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.92

Field Name : mtuExceeded

Field Type : CounterBasedGauge64

Field Status : current

Description : Packet Exceeded MTU

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.91

Field Name : crossCpuHelperDoubleAdd

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Double Add Attempt

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.90

Field Name : crossCpuHelperNatPoolStandby

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper NAT Pool Standby

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.89

Field Name : crossCpuHelperCpuMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper CPU Mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.88

Field Name : crossCpuHelperDeleted

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Deleted

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.87

Field Name : crossCpuHelperFreeNotFound

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Free Not Found

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.86

Field Name : crossCpuHelperFreeRetryLookup

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Free Retry Lookup

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.85

Field Name : crossCpuHelperFree

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Free

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.84

Field Name : crossCpuNoSession

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU No Session Found

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.83

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : crossCpuBadL4
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Unsupported L4
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.82

Field Name : crossCpuBadL3
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Unsupported L3
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.81

Field Name : crossCpuRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.80

Field Name : crossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Packets Sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.79

Field Name : crossCpuHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Session Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.78

Field Name : fullconeOverflowEif
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session EIF Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.77

Field Name : fullconeOverflowEim
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session EIM Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.76

Field Name : fullconeInboundNatPoolMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session NAT Pool Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.75

Field Name : badSmpTupleNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad NAT IP from SMP tuple
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.74

Field Name : badTupleNatIp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Bad NAT IP from tuple
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.73

Field Name : standbyClassListDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Class-List drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.72

Field Name : haEndpointIndepMapMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Endpoint-independent Matching
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.71

Field Name : haFullconeCreateRaceFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Full-cone Create Race Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.70

Field Name : haFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.69

Field Name : haUnknownNatIp
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Unknown NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.68

Field Name : haNatPortUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : HA NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.67

Field Name : haDnatMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Destination NAT Config Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.66

Field Name : haPortMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Port Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.65

Field Name : haFullconeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Full-cone Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.64

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : haUserQuotaMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA User-Quota Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.63

Field Name : haClasslistMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Class-list Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.62

Field Name : greUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE User-Quota exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.61

Field Name : udpAlgUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP ALG User-Quota exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.60

Field Name : espUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP User-Quota exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.59

Field Name : natEspNoControlSesn
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN NAT ESP No Control Session
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.58

Field Name : natEspIpConflicts
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN NAT ESP IP Conflicts
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.57

Field Name : natPoolDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.56

Field Name : natPortFreedFromDiffCpu
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Port Freed On Different CPU
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.55

Field Name : natPortChunkFreedFromCpu
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : NAT Port Chunks Freed From CPU
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.54

Field Name : natPortDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Port Double Free
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.53

Field Name : fullconeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session not found
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.52

Field Name : fullconeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session retry look-up
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.51

Field Name : fullconeInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session found in delete queue
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.50

Field Name : lidPassThrough
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN LID Pass-through
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.49

Field Name : lidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : LSN LID Drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.48

Field Name : noClassListMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No Class-List Match
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.47

Field Name : natIpMaxUdpPortsAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT IP UDP Max Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.46

Field Name : natIpMaxTcpPortsAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT IP TCP Max Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.45

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : noRadiusProfileMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No RADIUS Profile Match
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.44

Field Name : haNatPoolBatchTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : HA NAT Pool Batch Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.43

Field Name : cgnv6lsnGlobalHaNatPoolUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : HA NAT Pool Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.42

Field Name : cgnv6lsnGlobalNatPoolUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Pool Unusable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.41

Field Name : cgnv6lsnGlobalPortOverloadingSmpFreeUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.40

Field Name : cgnv6lsnGlobalPortOverloadingSmpFreeTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.39

Field Name : cgnv6lsnGlobalPortOverloadingSmpInsertedUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.38

Field Name : cgnv6lsnGlobalPortOverloadingSmpInsertedTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port Overloading Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.37

Field Name : cgnv6lsnGlobalTotalUdpOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Overloaded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.36

Field Name : cgnv6lsnGlobalTotalTcpOverloaded
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : TCP Port Overloaded

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.35

Field Name : cgnv6lsnGlobalEifLimitExceeded

Field Type : CounterBasedGauge64

Field Status : current

Description : Endpoint-Independent Filtering Inbound Limit Exceeded

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.33

Field Name : cgnv6lsnGlobalInboundFiltered

Field Type : CounterBasedGauge64

Field Status : current

Description : Endpoint-Dependent Filtering Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.32

Field Name : cgnv6lsnGlobalEndpointIndepFilterMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : Endpoint-Independent Filtering Matched

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.31

Field Name : cgnv6lsnGlobalEndpointIndepMapMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : Endpoint-Independent Mapping Matched

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.30

Field Name : cgnv6lsnGlobalFullconeSelfHairpinningDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Self-Hairpinning Drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.29

Field Name : cgnv6lsnGlobalHairpin

Field Type : CounterBasedGauge64

Field Status : current

Description : Hairpin Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.28

Field Name : cgnv6lsnGlobalFullconeFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Full-cone Session Creation Failed

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.27

Field Name : cgnv6lsnGlobalUdpFullconeFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Full-cone Session Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.26

Field Name : cgnv6lsnGlobalUdpFullconeCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Full-cone Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.25

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6lsnGlobalTcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.24

Field Name : cgnv6lsnGlobalTcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.23

Field Name : cgnv6lsnGlobalDataSesnRateUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Rate User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.22

Field Name : cgnv6lsnGlobalDataSesnUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.21

Field Name : cgnv6lsnGlobalExtendedQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.20

Field Name : cgnv6lsnGlobalExtendedQuotaMatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Extended User-Quota Matched
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.19

Field Name : cgnv6lsnGlobalIcmpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.18

Field Name : cgnv6lsnGlobalUdpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.17

Field Name : cgnv6lsnGlobalTcpUserQuotaExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP User-Quota Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.16

Field Name : cgnv6lsnGlobalNewUserResourceUnavailable
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : New User NAT Resource Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.15

Field Name : cgnv6lsnGlobalNatPortUnavailableIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.14

Field Name : cgnv6lsnGlobalNatPortUnavailableUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.13

Field Name : cgnv6lsnGlobalNatPortUnavailableTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP NAT Port Unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.12

Field Name : cgnv6lsnGlobalUserQuotaFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.11

Field Name : cgnv6lsnGlobalUserQuotaPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.10

Field Name : cgnv6lsnGlobalTotalUserQuotaCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : User-Quota Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.9

Field Name : cgnv6lsnGlobalDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.8

Field Name : cgnv6lsnGlobalDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.7

Field Name : cgnv6lsnGlobalTotalIcmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.6

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6lsnGlobalTotalIcmpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.5

Field Name : cgnv6lsnGlobalTotalUdpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.4

Field Name : cgnv6lsnGlobalTotalUdpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.3

Field Name : cgnv6lsnGlobalTotalTcpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.2

Field Name : cgnv6lsnGlobalTotalTcpAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Ports Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.4.1.1

Field Name : userQuoteCreatedPreviousEpochLast
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.9

Field Name : fullconeCreatedPreviousEpochLast
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.8

Field Name : dataSessionsPreviousEpochLast
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.7

Field Name : userQuoteCreatedPreviousEpochFirst
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.6

Field Name : fullconeCreatedPreviousEpochFirst
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.5

Field Name : dataSessionsPreviousEpochFirst

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.4

Field Name : userQuoteCreatedCurrentEpoch

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.3

Field Name : fullconeCreatedCurrentEpoch

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.2

Field Name : dataSessionsCurrentEpoch

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.2.1.1

Field Name : tcamCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : TCAM Flow Count

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.20

Field Name : tcamFree

Field Type : CounterBasedGauge64

Field Status : current

Description : TCAM Flows Freed

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.19

Field Name : tcamCreate

Field Type : CounterBasedGauge64

Field Status : current

Description : TCAM Flows Created

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.18

Field Name : entryInvalidateServerDown

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entries Invalidate due to server down

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.17

Field Name : entryForceHwInvalidate

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entries Force HW Invalidate

OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.16

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : entryAgeOutInvalidDst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - invalid dst
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.15

Field Name : entryAgeOutTcpRst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP RST
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.14

Field Name : entryAgeOutTcpFin
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP FIN
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.13

Field Name : entryAgeOutIdle
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.12

Field Name : entryAgeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.11

Field Name : entryCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Count
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.10

Field Name : entryFreeNoSwEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no software entry
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.9

Field Name : entryFreeNoConn
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no matched conn
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.8

Field Name : entryFreeNoHwProg
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Freed - no HW prog
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.7

Field Name : entryFreeOppEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : HW Entries Freed - opposite tuple entry aged-out
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.6

Field Name : entryFree
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Freed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.5

Field Name : entryCreateFailMaxEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed - max entries exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.4

Field Name : entryCreateFailServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed - server down
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.3

Field Name : entryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entry Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.2

Field Name : entryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.115.7.23.1.1

Field Name : synCookieConnSetupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie connection setup failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.39

Field Name : synCookieVerificationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie verification failed
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.38

Field Name : synCookieVerificationPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie verification passed
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.37

Field Name : synCookieSynAckSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie SYN ACK sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.36

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : l3EntryAddToHwFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 entry HW add failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.35

Field Name : l3EntryRemoveFromBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 entry BGP remove failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.34

Field Name : l3EntryAddToBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Entry BGP add failures
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.33

Field Name : entryInvalidated
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry invalidated
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.32

Field Name : entryAddedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry added shadow
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.31

Field Name : ipOtherBlockAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Other block alloc failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.30

Field Name : ipOtherBlockFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Other block free
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.29

Field Name : ipOtherBlockAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Other block alloc
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.28

Field Name : ipPortBlockAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port block alloc failure
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.27

Field Name : ipPortBlockFree
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Port block free

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.26

Field Name : ipPortBlockAlloc

Field Type : CounterBasedGauge64

Field Status : current

Description : Port block alloc

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.25

Field Name : ipNodeAllocFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Node alloc failures

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.24

Field Name : ipNodeFree

Field Type : CounterBasedGauge64

Field Status : current

Description : Node free

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.23

Field Name : ipNodeAlloc

Field Type : CounterBasedGauge64

Field Status : current

Description : Node alloc

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.22

Field Name : l4EntryListAllocFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : L4 Entry list alloc failures

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.21

Field Name : l4EntryListFree

Field Type : CounterBasedGauge64

Field Status : current

Description : L4 Entry list free

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.20

Field Name : l4EntryListAlloc

Field Type : CounterBasedGauge64

Field Status : current

Description : L4 Entry list alloc

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.19

Field Name : l4EntryDropMaxHwExceeded

Field Type : CounterBasedGauge64

Field Status : current

Description : L4 Entry Drop due to HW Limit Exceeded

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.18

Field Name : l4EntryMatchDropHw

Field Type : CounterBasedGauge64

Field Status : current

Description : L4 HW Entry match drop

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.17

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : l4EntryMatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry match drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.16

Field Name : l4HwOutOfEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : HW out of L4 entries
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.15

Field Name : l4EntryRemovedFromHw
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry removed from HW
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.14

Field Name : l4EntryAddedToHw
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry added to HW
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.13

Field Name : l4EntryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry deleted
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.12

Field Name : l4EntryAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Entry added
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.11

Field Name : l3EntryDropMaxHwExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Entry Drop due to HW Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.10

Field Name : l3EntryMatchDropHw
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 HW entry match drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.9

Field Name : l3EntryMatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Entry match drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.8

Field Name : l3EntryTooMany
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : L3 Too many entries

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.7

Field Name : l3EntryRemovedFromHw

Field Type : CounterBasedGauge64

Field Status : current

Description : L3 Entry removed from HW

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.6

Field Name : l3EntryAddedToHw

Field Type : CounterBasedGauge64

Field Status : current

Description : L3 Entry added to HW

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.5

Field Name : l3EntryRemovedFromBgp

Field Type : CounterBasedGauge64

Field Status : current

Description : Entry removed from BGP

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.4

Field Name : l3EntryAddedToBgp

Field Type : CounterBasedGauge64

Field Status : current

Description : L3 Entry added to BGP

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.3

Field Name : l3EntryDeleted

Field Type : CounterBasedGauge64

Field Status : current

Description : L3 Entry Deleted

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.2

Field Name : l3EntryAdded

Field Type : CounterBasedGauge64

Field Status : current

Description : L3 Entry Added

OID : 1.3.6.1.4.1.22610.2.4.10.115.5.1.1

Field Name : cgnv6ServiceGroupSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.115.3.1.1

Field Name : cgnv6ServiceGroupSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.115.3.1.1.1

Field Name : cgnv6ServicePeakConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Service peak connection

OID : 1.3.6.1.4.1.22610.2.4.10.115.3.1.1.4

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : cgnv6ServerSelectionFailReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Service selection fail reset
OID : 1.3.6.1.4.1.22610.2.4.10.115.3.1.1.1.3

Field Name : cgnv6ServerSelectionFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Service selection fail drop
OID : 1.3.6.1.4.1.22610.2.4.10.115.3.1.1.1.2

Field Name : cgnv6ServiceGroupName
Field Type : String
Field Status : current
Description : CGNV6 Service Name
OID : 1.3.6.1.4.1.22610.2.4.10.115.3.1.1.1.1

Field Name : cgnv6ServerSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1

Field Name : cgnv6ServerSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1

Field Name : peakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1.6

Field Name : revPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1.5

Field Name : fwdPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward packets
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1.4

Field Name : totalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total connections
OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1.3

Field Name : cgnv6ServerCurrConn
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Current connections

OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1.2

Field Name : cgnv6Name

Field Type : String

Field Status : current

Description : Server Name

OID : 1.3.6.1.4.1.22610.2.4.10.115.2.1.1.1.1

Field Name : icmpTotalPortsAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : Total ICMP ports allocated

OID : 1.3.6.1.4.1.22610.2.4.10.115.1.1.3

Field Name : udpTotalPortsAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : Total UDP ports allocated

OID : 1.3.6.1.4.1.22610.2.4.10.115.1.1.2

Field Name : tcpTotalPortsAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : Total TCP ports allocated

OID : 1.3.6.1.4.1.22610.2.4.10.115.1.1.1

Field Name : rcvNotSupportedOption

Field Type : CounterBasedGauge64

Field Status : current

Description : PNot supported options received

OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.16

Field Name : rcvNotSupportedMsg

Field Type : CounterBasedGauge64

Field Status : current

Description : Packets with not supported messages sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.15

Field Name : noBindingMsgsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : NO_BINDING messages sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.14

Field Name : noPrefixAvailSent

Field Type : CounterBasedGauge64

Field Status : current

Description : NO_PREFIX_AVAILABLE messages sent

OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.13

Field Name : pktsDroppedDuringClear

Field Type : CounterBasedGauge64

Field Status : current

Description : Packets dropped during clear bindings process

OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.12

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : packetsDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.11

Field Name : informationReqRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Information request messages received
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.10

Field Name : relayReplySent
Field Type : CounterBasedGauge64
Field Status : current
Description : Relay reply messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.9

Field Name : replySent
Field Type : CounterBasedGauge64
Field Status : current
Description : Reply messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.8

Field Name : advertiseSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Advertise messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.7

Field Name : relayForwRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Relay forward message received
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.6

Field Name : releaseRev
Field Type : CounterBasedGauge64
Field Status : current
Description : Release messages received
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.5

Field Name : rebindRev
Field Type : CounterBasedGauge64
Field Status : current
Description : Rebind messages received
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.4

Field Name : renewRev
Field Type : CounterBasedGauge64
Field Status : current
Description : Renew messages received
OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.3

Field Name : requestRev
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Request messages received

OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.2

Field Name : solicitRev

Field Type : CounterBasedGauge64

Field Status : current

Description : Solicit messages received

OID : 1.3.6.1.4.1.22610.2.4.10.115.33.2.1.1

Field Name : fwTopThrSrcDb

Field Type : CounterBasedGauge64

Field Status : current

Description : Total local-log Firewall top threat and source summary database

OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.37

Field Name : fwTopThrDb

Field Type : CounterBasedGauge64

Field Status : current

Description : Total local-log Firewall top threat summary database

OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.36

Field Name : queryError

Field Type : CounterBasedGauge64

Field Status : current

Description : Total local-log axapi query error

OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.35

Field Name : response

Field Type : CounterBasedGauge64

Field Status : current

Description : Total local-log axapi response

OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.34

Field Name : query

Field Type : CounterBasedGauge64

Field Status : current

Description : Total local-log axapi query

OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.33

Field Name : dbErro

Field Type : CounterBasedGauge64

Field Status : current

Description : Total local-log database create error

OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.32

Field Name : fwTopCategoryDb

Field Type : CounterBasedGauge64

Field Status : current

Description : Total local-log Firewall top category summary database

OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.31

Field Name : fwTopAppSrcDb

Field Type : CounterBasedGauge64

Field Status : current

Description : Total local-log Firewall top application and source summary database

OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.30

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : fwTopSrcDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log Firewall top source summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.29

Field Name : fwTopAppDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log Firewall top application summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.28

Field Name : epTopHostDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP top host summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.22

Field Name : epTopWebCategoryDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP top web-category summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.21

Field Name : epTopDomainDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP top domain summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.20

Field Name : epTopDstDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP top destination summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.19

Field Name : epTopSrcDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP top client summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.18

Field Name : epTopUserDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP top user summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.17

Field Name : aamTopUserDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log AAM top user summary database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.16

Field Name : fwDb
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Description : Total local-log Firewall raw database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.15

Field Name : epDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log EP raw database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.13

Field Name : aamDb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log AAM raw database
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.12

Field Name : logSummarizedError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log summarization error
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.11

Field Name : l2LogSummarized
Field Type : CounterBasedGauge64
Field Status : current
Description : Total layer 2 log summarized
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.10

Field Name : l1LogSummarized
Field Type : CounterBasedGauge64
Field Status : current
Description : Total layer 1 log summarized
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.9

Field Name : logSummarized
Field Type : CounterBasedGauge64
Field Status : current
Description : Total raw log summarized
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.8

Field Name : rawLogError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total raw log logging error
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.7

Field Name : rawLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log raw logs
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.6

Field Name : dequeueError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log dequeue processing error
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.5

ACOS-CGNV6-STATS-MIB_acosCgnv6_oid_list

Field Name : dequeue
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log dequeue
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.4

Field Name : enqueueError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log enqueue error
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.3

Field Name : enqueueFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log queue full
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.2

Field Name : enqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Total local-log enqueue
OID : 1.3.6.1.4.1.22610.2.4.10.117.15.5.1.1

ACOS-CLASS-LIST-MIB_oid_list

Field Name : classListOperGeoLocationEntriesTable
Field Type : TABLE
Field Status : current
Description : ConfigureClassificationList from object 'class-list'
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8

Field Name : classListOperAcEntriesTable
Field Type : TABLE
Field Status : current
Description : ConfigureClassificationList from object 'class-list'
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7

Field Name : classListOperAcEntriesEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The classListOperAcEntries entry:ac-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1

Field Name : classListOperAcEntriesAcGtpPolicy
Field Type : String
Field Status : current
Description : ac-gtp-policy
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.8

Field Name : classListOperAcEntriesAcHitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ac-hit-count
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.7

Field Name : classListOperAcEntriesAcMatchValue
Field Type : String
Field Status : current
Description : ac-match-value
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.6

Field Name : classListOperAcEntriesAcMatchString
Field Type : String
Field Status : current
Description : ac-match-string
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.5

Field Name : classListOperAcEntriesAcMatchType
Field Type : String
Field Status : current
Description : ac-match-type
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.4

Field Name : classListOperAcEntriesAcEntriesListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.3

Field Name : classListOperAcEntriesName
Field Type : String
Field Status : current

ACOS-CLASS-LIST-MIB_oid_list

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.2

Field Name : classListOperAcEntriesSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.7.1.1

Field Name : classListOperStringEntriesTable

Field Type : TABLE

Field Status : current

Description : ConfigureClassificationList from object 'class-list'

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6

Field Name : classListOperStringEntriesEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The classListOperStringEntries entry:string-entries

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1

Field Name : classListOperStringEntriesStringHitCount

Field Type : CounterBasedGauge64

Field Status : current

Description : string-hit-count

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.8

Field Name : classListOperStringEntriesStringGlid

Field Type : CounterBasedGauge64

Field Status : current

Description : string-glid

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.7

Field Name : classListOperStringEntriesStringLid

Field Type : CounterBasedGauge64

Field Status : current

Description : string-lid

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.6

Field Name : classListOperStringEntriesStringValue

Field Type : String

Field Status : current

Description : string-value

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.5

Field Name : classListOperStringEntriesStringKey

Field Type : String

Field Status : current

Description : string-key

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.4

Field Name : classListOperStringEntriesStringEntriesListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.3

ACOS-CLASS-LIST-MIB_oid_list

Field Name : classListOperStringEntriesName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.2

Field Name : classListOperStringEntriesSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.6.1.1

Field Name : classListOperDnsEntriesTable
Field Type : TABLE
Field Status : current
Description : ConfigureClassificationList from object 'class-list'
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5

Field Name : classListOperDnsEntriesEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The classListOperDnsEntries entry:dns-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1

Field Name : classListOperDnsEntriesDnsRpzType
Field Type : CounterBasedGauge64
Field Status : current
Description : dns-rpz-type
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.9

Field Name : classListOperDnsEntriesDnsHitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : dns-hit-count
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.8

Field Name : classListOperDnsEntriesDnsGlid
Field Type : CounterBasedGauge64
Field Status : current
Description : dns-glid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.7

Field Name : classListOperDnsEntriesDnsLid
Field Type : CounterBasedGauge64
Field Status : current
Description : dns-lid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.6

Field Name : classListOperDnsEntriesDnsMatchString
Field Type : String
Field Status : current
Description : dns-match-string
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.5

Field Name : classListOperDnsEntriesDnsMatchType
Field Type : String
Field Status : current

ACOS-CLASS-LIST-MIB_oid_list

Description : dns-match-type

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.4

Field Name : classListOperDnsEntriesDnsEntriesListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.3

Field Name : classListOperDnsEntriesName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.2

Field Name : classListOperDnsEntriesSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.5.1.1

Field Name : classListOperIpv6EntriesTable

Field Type : TABLE

Field Status : current

Description : ConfigureClassificationList from object 'class-list'

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4

Field Name : classListOperIpv6EntriesEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The classListOperIpv6Entries entry:ipv6-entries

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1

Field Name : classListOperIpv6EntriesIpv6RpzType

Field Type : CounterBasedGauge64

Field Status : current

Description : ipv6-rpz-type

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.12

Field Name : classListOperIpv6EntriesIpv6Age

Field Type : CounterBasedGauge64

Field Status : current

Description : ipv6-age

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.11

Field Name : classListOperIpv6EntriesIpv6HitCount

Field Type : CounterBasedGauge64

Field Status : current

Description : ipv6-hit-count

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.10

Field Name : classListOperIpv6EntriesIpv6Category

Field Type : CounterBasedGauge64

Field Status : current

Description : ipv6-category

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.13

ACOS-CLASS-LIST-MIB_oid_list

Field Name : classListOperIpv6EntriesIpv6GtpPolicy
Field Type : String
Field Status : current
Description : ipv6-gtp-policy
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.9

Field Name : classListOperIpv6EntriesIpv6LsnRadiusProfile
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-lsn-radius-profile
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.8

Field Name : classListOperIpv6EntriesIpv6LsnLid
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-lsn-lid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.7

Field Name : classListOperIpv6EntriesIpv6Glid
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-glid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.6

Field Name : classListOperIpv6EntriesIpv6Lid
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-lid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.5

Field Name : classListOperIpv6EntriesIpv6addr
Field Type : String
Field Status : current
Description : ipv6addr
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.4

Field Name : classListOperIpv6EntriesIpv6EntriesListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.3

Field Name : classListOperIpv6EntriesName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.2

Field Name : classListOperIpv6EntriesSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.4.1.1

Field Name : classListOperIpv4EntriesTable
Field Type : TABLE
Field Status : current

ACOS-CLASS-LIST-MIB_oid_list

Description : ConfigureClassificationList from object 'class-list'
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3

Field Name : classListOperIpv4EntriesEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The classListOperIpv4Entries entry:ipv4-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1

Field Name : classListOperIpv4EntriesIpv4RpzType
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-rpz-type
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.12

Field Name : classListOperIpv4EntriesIpv4Age
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-age
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.11

Field Name : classListOperIpv4EntriesIpv4HitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-hit-count
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.10

Field Name : classListOperIpv4EntriesIpv4Category
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-category
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.13

Field Name : classListOperIpv4EntriesIpv4GtpPolicy
Field Type : String
Field Status : current
Description : ipv4-gtp-policy
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.9

Field Name : classListOperIpv4EntriesIpv4LsnRadiusProfile
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-lsn-radius-profile
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.8

Field Name : classListOperIpv4EntriesIpv4LsnLid
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-lsn-lid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.7

Field Name : classListOperIpv4EntriesIpv4Glid
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-glid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.6

ACOS-CLASS-LIST-MIB_oid_list

Field Name : classListOperIpv4EntriesIpv4Lid
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-lid
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.5

Field Name : classListOperIpv4EntriesIpv4Addr
Field Type : String
Field Status : current
Description : ipv4-addr
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.4

Field Name : classListOperIpv4EntriesIpv4EntriesListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.3

Field Name : classListOperIpv4EntriesName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.2

Field Name : classListOperIpv4EntriesSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.3.1.1

Field Name : classListOperTable
Field Type : TABLE
Field Status : current
Description : ConfigureClassificationList from object 'class-list'
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2

Field Name : classListOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The classListOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1

Field Name : classListOperGeoLocationTotalEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : geo-location-total-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.13

Field Name : classListOperAcTotalEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : ac-total-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.12

Field Name : classListOperStringTotalEntries
Field Type : CounterBasedGauge64
Field Status : current

ACOS-CLASS-LIST-MIB_oid_list

Description : string-total-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.11

Field Name : classListOperDnsTotalEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : dns-total-entries
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.10

Field Name : classListOperIpv6TotalSubnet
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-total-subnet
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.9

Field Name : classListOperIpv6TotalSingleIp
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-total-single-ip
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.8

Field Name : classListOperIpv4TotalSubnet
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-total-subnet
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.7

Field Name : classListOperIpv4TotalSingleIp
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-total-single-ip
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.6

Field Name : classListOperUserTag
Field Type : String
Field Status : current
Description : user-tag
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.5

Field Name : classListOperFileOrString
Field Type : String
Field Status : current
Description : file-or-string
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.4

Field Name : classListOperType
Field Type : String
Field Status : current
Description : type
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.3

Field Name : classListOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.2

ACOS-CLASS-LIST-MIB_oid_list

Field Name : classListOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.2.1.1

Field Name : classListOperGeoLocationEntriesEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The classListOperGeoLocationEntries entry:geo-location-entries

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8.1

Field Name : classListOperGeoLocationEntriesGeoLocationStatus

Field Type : String

Field Status : current

Description : geo-location-status

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8.1.5

Field Name : classListOperGeoLocationEntriesGeoLocation

Field Type : String

Field Status : current

Description : geo-location

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8.1.4

Field Name : classListOperGeoLocationEntriesGeoLocationEntriesListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8.1.3

Field Name : classListOperGeoLocationEntriesName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8.1.2

Field Name : classListOperGeoLocationEntriesSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.137.1.8.1.1

ACOS-CONFIG-SYNC-STATUS-MIB_oid_list

Field Name : configSyncStatusOperConfigSyncListTable
Field Type : TABLE
Field Status : current
Description : DisplayConfigSyncStatusForAllPartitions from object 'config-sync-status'
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2

Field Name : configSyncStatusOperConfigSyncListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The configSyncStatusOperConfigSyncList entry:config-sync-list
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2.1

Field Name : configSyncStatusOperConfigSyncListStartupSyncStatus
Field Type : String
Field Status : current
Description : startup-sync-status
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2.1.5

Field Name : configSyncStatusOperConfigSyncListRunSyncStatus
Field Type : String
Field Status : current
Description : run-sync-status
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2.1.4

Field Name : configSyncStatusOperConfigSyncListPartitionName
Field Type : String
Field Status : current
Description : partition-name
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2.1.3

Field Name : configSyncStatusOperConfigSyncListConfigSyncListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2.1.2

Field Name : configSyncStatusOperConfigSyncListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.170.1.2.1.1

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : tokenAuthenticationInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Token Authentication Invalid Packets
OID : 1.3.6.1.4.1.22610.2.4.10.102.83.1.3

Field Name : tokenAuthenticationMismatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Token Authentication Mismatched Packets
OID : 1.3.6.1.4.1.22610.2.4.10.102.83.1.2

Field Name : tokenAuthenticationMatched
Field Type : CounterBasedGauge64
Field Status : current
Description : Token Authentication Matched Packets
OID : 1.3.6.1.4.1.22610.2.4.10.102.83.1.1

Field Name : logMsgSendErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Send Error
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.9

Field Name : logMsgSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.8

Field Name : logMsgDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Dequeue Error
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.7

Field Name : logMsgDequeue
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Dequeue
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.6

Field Name : logMsgEnqueueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Enqueue Error
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.5

Field Name : logMsgEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Enqueue
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.4

Field Name : logQueueFull
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Log Message Queue Full
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.3

Field Name : logMsgOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Out of Memory Error
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.2

Field Name : logMsgQuotaExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Message Per CPU Quota Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.102.67.1.1

Field Name : syncSzpBlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.64

Field Name : syncSzpDnsTcpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService DNS Force-TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.63

Field Name : syncSzpDnsUdpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService DNS UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.62

Field Name : syncSzpOtherAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService OTHER Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.61

Field Name : syncSzpIcmpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService ICMP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.60

Field Name : syncSzpUdpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.59

Field Name : syncSzpTcpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcZoneService TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.58

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : syncSrcDstBlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.57

Field Name : syncSrcDstDnsTcpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst DNS Force-TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.56

Field Name : syncSrcDstDnsUdpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst DNS UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.55

Field Name : syncSrcDstOtherWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst OTHER Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.54

Field Name : syncSrcDstIcmpWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst ICMP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.53

Field Name : syncSrcDstTcpWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.52

Field Name : syncSrcDstUdpWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received SrcDst UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.51

Field Name : syncSrcBlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Src Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.50

Field Name : syncSrcDnsTcpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Src DNS Force-TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.49

Field Name : syncSrcDnsUdpAuthRcvd
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Sync Received Src DNS UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.48

Field Name : syncSrcOtherWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Src OTHER Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.47

Field Name : syncSrcIcmpWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Src ICMP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.46

Field Name : syncSrcTcpWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Src TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.45

Field Name : syncSrcUdpWlRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Src UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.44

Field Name : syncSzpBlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcZoneService Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.43

Field Name : syncSzpDnsTcpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcZoneService DNS Force-TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.42

Field Name : syncSzpDnsUdpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcZoneService DNS UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.41

Field Name : syncSzpOtherAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcZoneService OTHER Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.40

Field Name : syncSzpIcmpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcZoneService ICMP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.39

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : syncSzpUdpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcZoneService UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.38

Field Name : syncSzpTcpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcZoneService TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.37

Field Name : syncSrcDstBlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.36

Field Name : syncSrcDstDnsTcpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst DNS Force-TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.35

Field Name : syncSrcDstDnsUdpAuthSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst DNS UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.34

Field Name : syncSrcDstOtherWlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst OTHER Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.33

Field Name : syncSrcDstIcmpWlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst ICMP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.32

Field Name : syncSrcDstTcpWlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst TCP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.31

Field Name : syncSrcDstUdpWlSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent SrcDst UDP Authenticated
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.30

Field Name : syncSrcBlSent
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Sync Sent Src Blacklisted

OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.29

Field Name : syncSrcDnsTcpAuthSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Sync Sent Src DNS Force-TCP Authenticated

OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.28

Field Name : syncSrcDnsUdpAuthSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Sync Sent Src DNS UDP Authenticated

OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.27

Field Name : syncSrcOtherWlSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Sync Sent Src OTHER Authenticated

OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.26

Field Name : syncSrcIcmpWlSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Sync Sent Src ICMP Authenticated

OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.25

Field Name : syncSrcTcpWlSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Sync Sent Src TCP Authenticated

OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.24

Field Name : syncSrcUdpWlSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Sync Sent Src UDP Authenticated

OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.23

Field Name : syncRcvEntryUnk

Field Type : CounterBasedGauge64

Field Status : current

Description : Sync Received Unknown Entry

OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.22

Field Name : syncRcvEntryUnkSubtype

Field Type : CounterBasedGauge64

Field Status : current

Description : Sync Received Entry Unknown Subtype

OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.21

Field Name : syncRcvHelloUnkSubtype

Field Type : CounterBasedGauge64

Field Status : current

Description : Sync Received Hello Unknown Subtype

OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.20

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : syncRcvFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.19

Field Name : syncRcvUnkMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Unknown Msg
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.18

Field Name : syncRcvEntryConflictStatic
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Entry Conflict Static
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.17

Field Name : syncRcvEntryCreateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Entry Create Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.16

Field Name : syncSzpNoDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync SrcZoneService No-Dst
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.15

Field Name : syncSrcDstNoDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync SrcDst No-Dst
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.14

Field Name : syncRcvHelloUnkPeer
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Received Hello Unknown Peer
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.13

Field Name : syncSentFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.12

Field Name : syncSentNoPeer
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Sent No Peer
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.11

Field Name : syncSzpRcv
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Sync SrcZoneService Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.10

Field Name : syncSzpSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync SrcZoneService Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.9

Field Name : syncSrcDstRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync SrcDst Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.8

Field Name : syncSrcDstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync SrcDst Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.7

Field Name : syncSrcRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Src Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.6

Field Name : syncSrcSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Src Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.5

Field Name : syncDstRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Dst Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.4

Field Name : syncDstSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Dst Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.3

Field Name : syncHelloSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Hello Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.2

Field Name : syncHelloRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Hello Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.64.1.1

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : undersizeIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Undersize
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.36

Field Name : undersizeIpPl
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Payload Too Small
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.35

Field Name : tcpOptOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Option Error
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.34

Field Name : tunMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Tunnel Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.33

Field Name : runtTcpudpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : TCPUDP Runt Header
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.32

Field Name : runtIpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Runt Header
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.31

Field Name : udpBadCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Invalid Checksum
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.30

Field Name : udpPortLb
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port LB
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.29

Field Name : udpKbFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP KB Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.28

Field Name : udpShortLeng
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : UDP Invalid Length
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.27

Field Name : udpShortHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Short Header
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.26

Field Name : tcpBadCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Invalid Checksum
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.25

Field Name : tcpFragHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Fragment Header
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.24

Field Name : tcpSynFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.23

Field Name : tcpXmasScan
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP XMAS Scan
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.22

Field Name : tcpXmasFlags
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP XMAS Flags
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.21

Field Name : tcpSynFin
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN&FIN
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.20

Field Name : tcpNullScan
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Null Scan
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.19

Field Name : tcpNullFlags
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Null Flags
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.18

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : tcpBadIpLen
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Invalid IPv4 Length
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.17

Field Name : tcpShortHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Short Header
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.16

Field Name : tcpBadUrgOff
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Invalid Urgent Offset
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.15

Field Name : icmpPod
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Ping Of Death
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.14

Field Name : badIpCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Invalid Checksum
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.13

Field Name : badIpFragOff
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Invalid Fragment Offset
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.12

Field Name : badIpPlLen
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Invalid Payload Length
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.11

Field Name : oversizeIpPl
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Payload Too Large
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.10

Field Name : noIpPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Payload None
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.9

Field Name : badIpTtl
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : IP Invalid TTL
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.8

Field Name : badIpFlags
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Invalid Flags
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.7

Field Name : badIpHdrLen
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Invalid Header Length
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.6

Field Name : ipFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.5

Field Name : ipv4Opt
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Option
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.4

Field Name : microFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Micro Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.3

Field Name : emptyFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Empty Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.2

Field Name : landAttack
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Land Attack
OID : 1.3.6.1.4.1.22610.2.4.10.102.63.1.1

Field Name : jumboInTunnelDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Jumbo Packet in Tunnel Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.42

Field Name : ipGreTunnelKeepaliveRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Keep-Alive Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.41

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : ipVxlanTunnelDecapErr
Field Type : CounterBasedGauge64
Field Status : current
Description : IP VxLAN Decap Error
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.40

Field Name : ipVxlanTunnelDecap
Field Type : CounterBasedGauge64
Field Status : current
Description : IP VxLAN Decap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.39

Field Name : ipVxlanTunnelInvalidVni
Field Type : CounterBasedGauge64
Field Status : current
Description : IP VxLAN Invalid VNI
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.38

Field Name : ipVxlanTunnelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : IP VxLAN Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.37

Field Name : ip6EspTunnelInspectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP V6 Tunnel Inspect Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.36

Field Name : ip6EspTunnelInspect
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP V6 Tunnel Inspect
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.35

Field Name : ip6EspTunnelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP V6 Tunnel Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.34

Field Name : ipEspTunnelInspectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Tunnel Inspect Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.33

Field Name : ipEspTunnelInspect
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Tunnel Inspect
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.32

Field Name : ipEspTunnelRcvd
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : ESP Tunnel Received

OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.31

Field Name : ip6GreTunnelDecapDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE V6 Tunnel Decap No Key Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.30

Field Name : ip6GreTunnelDecapKey

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE V6 Tunnel Decap W/ Key

OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.29

Field Name : ip6GreTunnelEncapKey

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE V6 Tunnel Encap W/ Key

OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.28

Field Name : ip6GreTunnelDecapFail

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE V6 Tunnel Decap Failed

OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.27

Field Name : ip6GreTunnelDecap

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE V6 Tunnel Decap

OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.26

Field Name : ip6GreTunnelEncapFail

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE V6 Tunnel Encap Received Failed

OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.25

Field Name : ip6GreTunnelEncap

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE V6 Tunnel Encap

OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.24

Field Name : ip6GreTunnelRateLimitInner

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE V6 Tunnel Rate Limit Inner Pkts

OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.23

Field Name : ip6GreTunnelRcvd

Field Type : CounterBasedGauge64

Field Status : current

Description : GRE V6 Tunnel Received

OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.22

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : ipGreTunnelDecapDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Decap Key Mismatch Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.21

Field Name : ipGreTunnelDecapKey
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Decap W/ Key
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.20

Field Name : ipGreTunnelEncapKey
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Encap W/ Key
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.19

Field Name : ipGreTunnelDecapFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Decap Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.18

Field Name : ipGreTunnelDecap
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Decap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.17

Field Name : ipGreTunnelEncapFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Encap Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.16

Field Name : ipGreTunnelEncap
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Encap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.15

Field Name : ipGreTunnelRateLimitInner
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Rate Limit Inner Pkts
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.14

Field Name : ipGreTunnelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.13

Field Name : ip6TunnelDecapFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : IPv6 Tunnel Decap Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.12

Field Name : ip6TunnelDecap
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Tunnel Decap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.11

Field Name : ip6TunnelEncapFail
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Tunnel Encap Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.10

Field Name : ip6TunnelEncap
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Tunnel Encap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.9

Field Name : ip6TunnelRateLimitInner
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Tunnel Rate Limit Inner Pkts
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.8

Field Name : ip6TunnelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Tunnel Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.7

Field Name : ipTunnelDecapFail
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Tunnel Decap Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.6

Field Name : ipTunnelDecap
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Tunnel Decap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.5

Field Name : ipTunnelEncapFail
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Tunnel Encap Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.4

Field Name : ipTunnelEncap
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Tunnel Encap
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.3

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : ipTunnelRateLimitInner
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Tunnel Rate Limit Inner Pkts
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.2

Field Name : ipTunnelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Tunnel Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.62.1.1

Field Name : dstIpprotoFragRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP-Proto Frag Pkt Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.7

Field Name : dstIpprotoKbitRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP-Proto KiBit Rate Exceeded (KiBit)
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.6

Field Name : dstIpprotoPktRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP-Proto Pkt Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.5

Field Name : dstIpprotoExceedDropAny
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP-Proto Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.4

Field Name : dstIpprotoBl
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP-Proto Blacklist Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.3

Field Name : dstIpprotoDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP-Proto Total Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.2

Field Name : dstIpprotoRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP-Proto Total Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.61.1.1

Field Name : dstPortSameSportDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Dst Port Same Src Port Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.16

Field Name : dstSportConnRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort Conn Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.15

Field Name : dstSportConnLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort Conn Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.14

Field Name : dstSportFragRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort Frag Pkt Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.13

Field Name : dstSportKbitRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort KiBit Rate Exceeded (KiBit)
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.12

Field Name : dstSportPktRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort Pkt Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.11

Field Name : dstSportExceedDropAny
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.10

Field Name : dstSportBl
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst SrcPort Blacklist Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.9

Field Name : dstPortConnRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Conn Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.8

Field Name : dstPortConnLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Conn Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.7

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : dstPortFragRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Frag Pkt Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.6

Field Name : dstPortKbitRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port KiBit Rate Exceeded (KiBit)
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.5

Field Name : dstPortPktRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Pkt Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.4

Field Name : dstPortExceedDropAny
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.3

Field Name : dstPortBl
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Blacklist Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.2

Field Name : dstPortUndefDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Port Undefined Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.60.1.1

Field Name : runtimeDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS Runtime Disable
OID : 1.3.6.1.4.1.22610.2.4.10.102.59.1.4

Field Name : runtimeEnable
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS Runtime Enable
OID : 1.3.6.1.4.1.22610.2.4.10.102.59.1.3

Field Name : dcmsgPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS DCMSG Pkt
OID : 1.3.6.1.4.1.22610.2.4.10.102.59.1.2

Field Name : rrSessLookup
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : DDOS RR Session Lookup
OID : 1.3.6.1.4.1.22610.2.4.10.102.59.1.1

Field Name : acosDdosTable
Field Type : TABLE
Field Status : none
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.102.58

Field Name : acosDdosTableS
Field Type : TABLE
Field Status : none
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1

Field Name : srcZoneServiceClasslistOverflowPolicyAtLearning
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Class-List Overflow Policy Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.72

Field Name : srcDstClasslistOverflowPolicyAtLearning
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Class-List Overflow Policy Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.71

Field Name : entryExtOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Entry Extension Memory
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.70

Field Name : entryOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Entry Memory
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.69

Field Name : srcZoneServiceOverThrePolicyAtLearning
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Overflow Policy Learning Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.68

Field Name : srcZoneServiceOverThrePolicyAtLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Overflow Policy Lookup Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.67

Field Name : srcZoneServiceLearningThreExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Dynamic Entry Count Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.66

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : srcDstOverThrePolicyAtLearning
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Overflow Policy Hit At Learning Stage
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.65

Field Name : srcDstOverThrePolicyAtLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Overflow Policy Hit At Lookup Stage
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.64

Field Name : srcDstLearningThreExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Dynamic Entry Count Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.63

Field Name : srcOverThrePolicyAtLearning
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Overflow Policy Hit At Learning Stage
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.62

Field Name : srcOverThrePolicyAtLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Overflow Policy Hit At Lookup Stage
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.61

Field Name : srcLearningThreExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Dynamic Entry Count Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.60

Field Name : dstOverThrePolicyAtLearning
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Overflow Policy Hit At Learning Stage
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.59

Field Name : dstLearningThreExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Dynamic Entry Count Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.58

Field Name : srcZoneServiceBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Entry Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.57

Field Name : srcDstBlackList
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : SrcDst Entry Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.56

Field Name : srcBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Entry Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.55

Field Name : dstBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Entry Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.54

Field Name : srcZoneServiceWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Entry Whitelisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.53

Field Name : srcDstWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Entry Whitelisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.52

Field Name : srcWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Entry Whitelisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.51

Field Name : dstWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Entry Whitelisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.50

Field Name : srcZoneServiceEntryAged
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Entry Aged
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.49

Field Name : srcZoneServiceMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Entry Missed
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.48

Field Name : srcZoneServiceHit
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Entry Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.47

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : srcZoneServiceLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcZoneService Entry Learned
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.46

Field Name : telemErrFailToDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Zone Entry Delete Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.45

Field Name : telemErrFailToCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Zone Entry Create Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.44

Field Name : telemErrConflictWithStatic
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Conflict with Static Entry
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.43

Field Name : telemErrTelemEntryPreExist
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Zone Entry Pre-exist
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.42

Field Name : telemEntryCleared
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Zone Entry Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.41

Field Name : telemEntryCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Zone Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.40

Field Name : telemRouteDelRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Route-del Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.39

Field Name : telemRouteAddRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : From-l3-peer: Route-add Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.38

Field Name : telemErrMisc
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : From-l3-peer: Misc Error

OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.37

Field Name : srcDstOverLimitOff

Field Type : CounterBasedGauge64

Field Status : current

Description : SrcDst Over Limit Trigger OFF (Deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.36

Field Name : srcOverLimitOff

Field Type : CounterBasedGauge64

Field Status : current

Description : Src Over Limit Trigger OFF (Deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.35

Field Name : dstPortOverLimitOff

Field Type : CounterBasedGauge64

Field Status : current

Description : Dst Port Over Limit Trigger OFF (Deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.34

Field Name : dstOverLimitOff

Field Type : CounterBasedGauge64

Field Status : current

Description : Dst Over Limit Trigger OFF (Deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.33

Field Name : srcDstOverLimitOn

Field Type : CounterBasedGauge64

Field Status : current

Description : SrcDst Over Limit Trigger ON (Deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.32

Field Name : srcOverLimitOn

Field Type : CounterBasedGauge64

Field Status : current

Description : Src Over Limit Trigger ON (Deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.31

Field Name : dstPortOverLimitOn

Field Type : CounterBasedGauge64

Field Status : current

Description : Dst Port Over Limit Trigger ON (Deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.30

Field Name : dstOverLimitOn

Field Type : CounterBasedGauge64

Field Status : current

Description : Dst Over Limit Trigger ON (Deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.29

Field Name : srcDstOtherBlackList

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER SrcDst Blacklist (Deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.28

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : srcDstIcmpBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.27

Field Name : srcDstTcpBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.26

Field Name : srcDstUdpBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.25

Field Name : srcDstOtherWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER SrcDst Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.24

Field Name : srcDstIcmpWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.23

Field Name : srcDstTcpWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.22

Field Name : srcDstUdpWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.21

Field Name : srcOtherBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.20

Field Name : srcIcmpBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.19

Field Name : srcTcpBlackList
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : TCP Src Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.18

Field Name : srcUdpBlackList
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Blacklist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.17

Field Name : srcOtherWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.16

Field Name : srcIcmpWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.15

Field Name : srcTcpWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.14

Field Name : srcUdpWhiteList
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Whitelist (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.13

Field Name : srcDstEntryAged
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Entry Aged
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.12

Field Name : srcDstMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Entry Missed
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.11

Field Name : srcDstHit
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Entry Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.10

Field Name : srcDstLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Entry Learned
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.9

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : srcEntryAged
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Entry Aged
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.8

Field Name : srcMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Entry Missed
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.7

Field Name : srcHit
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Entry Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.6

Field Name : srcLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Entry Learned
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.5

Field Name : dstEntryAged
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Entry Aged
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.4

Field Name : dstMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Entry Missed
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.3

Field Name : dstHit
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Entry Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.2

Field Name : dstLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Entry Learned
OID : 1.3.6.1.4.1.22610.2.4.10.102.58.1.1

Field Name : jumboOutgoingMtuExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Jumbo Outgoing MTU Exceed Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.24

Field Name : outgoingMtuExceedDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Outgoing MTU Exceed Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.23

Field Name : jumboFragDropBeforeSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : Jumbo Fragment Non Data Plane Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.22

Field Name : jumboFragDropByFilter
Field Type : CounterBasedGauge64
Field Status : current
Description : Jumbo Fragment Filter Miss Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.21

Field Name : fragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.20

Field Name : fragRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Received (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.19

Field Name : mplsMalformed
Field Type : CounterBasedGauge64
Field Status : current
Description : MPLS Malformed
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.18

Field Name : mplsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : MPLS Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.17

Field Name : mplsRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : MPLS Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.16

Field Name : dstBlackholeWithdraw
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Blackhole Withdrawn
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.15

Field Name : dstBlackholeInject
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Blackhole Injected
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.14

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : dstIpBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst IP Bypass
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.13

Field Name : srcIpBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Src IP Bypass
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.12

Field Name : egressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.11

Field Name : ingressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.10

Field Name : egressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Outbound Bytes Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.9

Field Name : ingressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Inbound Bytes Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.8

Field Name : pktNotForDdos
Field Type : CounterBasedGauge64
Field Status : current
Description : Not For DDOS
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.7

Field Name : noroute
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4/v6 Out No Route
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.6

Field Name : inStatelessPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Stateless Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.5

Field Name : ipv6Sent
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : IPv6 Sent

OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.4

Field Name : ipv6Rcvd

Field Type : CounterBasedGauge64

Field Status : current

Description : IPv6 Received

OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.3

Field Name : ipSent

Field Type : CounterBasedGauge64

Field Status : current

Description : IPv4 Sent

OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.2

Field Name : ipRcvd

Field Type : CounterBasedGauge64

Field Status : current

Description : IPv4 Received

OID : 1.3.6.1.4.1.22610.2.4.10.102.57.1.1

Field Name : sessSnatFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Session Source NAT Failure

OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.22

Field Name : sessAgedUdpAuth

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Helper Auth Sessions Aged Out

OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.21

Field Name : sessCreateUdpAuth

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Helper Auth Sessions Created

OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.20

Field Name : sessOom

Field Type : CounterBasedGauge64

Field Status : current

Description : Out of Session Memory

OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.19

Field Name : connTcpCreateFromAck

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Conn Created From ACK

OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.18

Field Name : connTcpCreateFromSyn

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Conn Created From SYN

OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.17

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : connEntryMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Entry Mismatch Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.16

Field Name : sessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.15

Field Name : connUdpClose
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Conn Closed
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.14

Field Name : connUdpEst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Conn Established
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.13

Field Name : sessCreateUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.12

Field Name : connTcpClose
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Closed
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.11

Field Name : connTcpCloseWHalfOpen
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Closed With Half Open
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.10

Field Name : connTcpCloseWIdle
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Closed With Idle
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.9

Field Name : connTcpCloseWFin
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Closed With FIN
OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.8

Field Name : connTcpCloseWRst
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : TCP Conn Closed With RST

OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.7

Field Name : connTcpEst

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Conn Established

OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.6

Field Name : connTcpEstWAck

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Conn Established With ACK

OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.5

Field Name : connTcpEstWSyn

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Conn Established With SYN

OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.4

Field Name : sessCreateTcp

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Sessions Created

OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.3

Field Name : sessCreateIp6

Field Type : CounterBasedGauge64

Field Status : current

Description : IPv6 Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.2

Field Name : sessCreateIp

Field Type : CounterBasedGauge64

Field Status : current

Description : IPv4 Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.102.56.1.1

Field Name : sslBadHeaderDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : SSL Traffic Check Bad Header Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.29

Field Name : sslBadHeaderForw

Field Type : CounterBasedGauge64

Field Status : current

Description : SSL Traffic Check Bad Header Forwarded

OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.28

Field Name : sslHeaderBadLen

Field Type : CounterBasedGauge64

Field Status : current

Description : SSL Header Bad Length

OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.27

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : sslHeaderBadVer
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Header Bad Version
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.26

Field Name : sslHeaderInvalidType
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Header Invalid Type
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.25

Field Name : sslNonTls
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Non-TLS Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.24

Field Name : sslL4AuthResp
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Auth Responded
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.23

Field Name : sslL4AuthDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Auth Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.22

Field Name : sslL4RenegotiationIncomplete
Field Type : CounterBasedGauge64
Field Status : current
Description : Renegotiation Incomplete
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.21

Field Name : sslL4AuthHandshakeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Auth Handshake Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.20

Field Name : sslL4AuthHandshakeBl
Field Type : CounterBasedGauge64
Field Status : current
Description : Auth Handshake Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.19

Field Name : sslL4AuthHandshakeOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Auth Handshake Success
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.18

Field Name : sslL4HandshakeTimeout
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Auth Handshake Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.17

Field Name : sslL4ResetForHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : Reset While Others in Handshake
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.16

Field Name : sslL4DoAuthHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : Do Auth Handshake
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.15

Field Name : sslL4IsSrcReqRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Request Rate Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.14

Field Name : sslL4IsDstReqRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.13

Field Name : sslL4RenegotiationExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Renegotiation Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.12

Field Name : sslL4IsRenegotiation
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Renegotiation
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.11

Field Name : sslL4IsTls13
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS v1.2 or higher version
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.10

Field Name : sslL4IsTls12
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS v1.1
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.9

Field Name : sslL4IsTls11
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS v1.0
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.8

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : sslL4IsSsl3
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL v3
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.7

Field Name : sslL4NewSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : New TCP SYN
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.6

Field Name : sslL4Processed
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets Processed
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.5

Field Name : sslL4ErCondition
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Condition
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.4

Field Name : sslL4DropPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.3

Field Name : sslL4PolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.2

Field Name : sslL4PolicyReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy Reset
OID : 1.3.6.1.4.1.22610.2.4.10.102.44.1.1

Field Name : malformReqLineInvalidMethod
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Request Line Invalid Method
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.132

Field Name : malformReqLineTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Request Line Too Small
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.131

Field Name : headerProcessingIncomplete
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Header Process Incomplete

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.130

Field Name : headerProcessingTime3

Field Type : CounterBasedGauge64

Field Status : current

Description : Header Process Time Larger or Equal to 30s

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.129

Field Name : headerProcessingTime2

Field Type : CounterBasedGauge64

Field Status : current

Description : Header Process Time Less Than 30s

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.128

Field Name : headerProcessingTime1

Field Type : CounterBasedGauge64

Field Status : current

Description : Header Process Time Less Than 10s

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.127

Field Name : headerProcessingTime0

Field Type : CounterBasedGauge64

Field Status : current

Description : Header Process Time Less Than 1s

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.126

Field Name : httpAuthResp

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP Auth Responded

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.125

Field Name : httpAuthDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP Auth Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.124

Field Name : uriFilterMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : URI Filter Match

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.123

Field Name : dstFilterActionReset

Field Type : CounterBasedGauge64

Field Status : current

Description : Dst Filter Action Reset

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.122

Field Name : dstFilterActionIgnore

Field Type : CounterBasedGauge64

Field Status : current

Description : Dst Filter Action Ignore

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.121

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : dstFilterRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Rate Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.120

Field Name : srcDstFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.119

Field Name : srcDstFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.118

Field Name : srcDstFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.117

Field Name : srcDstFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.116

Field Name : srcDstFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.115

Field Name : srcDstFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.114

Field Name : srcFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.113

Field Name : srcFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.112

Field Name : srcFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Src Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.111

Field Name : srcFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.110

Field Name : srcFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.109

Field Name : srcFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.108

Field Name : dstFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.107

Field Name : dstRespRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Response Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.106

Field Name : srcPostRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Post Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.105

Field Name : dstPostRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Post Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.104

Field Name : dstFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.103

Field Name : dstFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.102

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : dstFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.101

Field Name : dstFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.100

Field Name : dstFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.99

Field Name : refererFilterBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Referer Filter Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.98

Field Name : refererFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Referer Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.97

Field Name : agentFilterBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Agent Filter Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.96

Field Name : agentFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Agent Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.95

Field Name : useHdrIpAsSource
Field Type : CounterBasedGauge64
Field Status : current
Description : Use IP In Header As Src
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.94

Field Name : allocHdrFail
Field Type : CounterBasedGauge64
Field Status : current
Description : FAIL_ALLOC_HDR (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.93

Field Name : allocFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Alloc Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.92

Field Name : windowSmallDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Window Size Small Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.91

Field Name : windowSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Window Size Small
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.90

Field Name : malformedTooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Too Many Headers
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.89

Field Name : malformedReqLineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Request Line Too Long
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.88

Field Name : malformedLineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Line Too Long
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.87

Field Name : malformedHeaderNameTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Header Name Too Long
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.86

Field Name : malformedContentLenTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Content Length Too Long
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.85

Field Name : malformedBadChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : Malform Bad Chunk
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.84

Field Name : challengeJsFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Challenge Javascript Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.83

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : challengeJsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Challenge Javascript Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.82

Field Name : challengeUdFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Challenge URL Redirect Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.81

Field Name : challengeUdSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Challenge URL Redirect Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.80

Field Name : challengeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Challenge Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.79

Field Name : chunkBad
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad HTTP Chunk
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.78

Field Name : chunkSzGt4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Chunk Size Larger Than 4K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.77

Field Name : chunkSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Chunk Size Less Than or Equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.76

Field Name : chunkSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Chunk Size Less Than or Equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.75

Field Name : chunkSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Chunk Size Less Than or Equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.74

Field Name : chunkSz512
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Payload Chunk Size Less Than or Equal to 512
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.73

Field Name : hpsRspStatusUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code Unknown
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.72

Field Name : hpsRspStatus6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 6XX
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.71

Field Name : hpsRspStatus504AX
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 504 AX-Gen
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.70

Field Name : hpsRspStatus5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 5XX
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.69

Field Name : hpsRspStatus4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 4XX
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.68

Field Name : hpsRspStatus3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 3XX
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.67

Field Name : hpsRspStatus2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 2XX
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.66

Field Name : hpsRspStatus1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Code 1XX
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.65

Field Name : hpsRspSz256kPlus
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Larger Than 256K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.64

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : hpsRspSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 256K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.63

Field Name : hpsRspSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 64K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.62

Field Name : hpsRspSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 32K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.61

Field Name : hpsRspSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 16K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.60

Field Name : hpsRspSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 8K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.59

Field Name : hpsRspSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.58

Field Name : hpsRspSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.57

Field Name : hpsRspSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Payload Size Less Than or Equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.56

Field Name : hpsRsp10
Field Type : CounterBasedGauge64
Field Status : current
Description : Response HTTP 1.0
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.55

Field Name : hpsRsp11
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Response HTTP 1.1

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.54

Field Name : hpsReqSz256kPlus

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Payload Size Larger Than 256K

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.53

Field Name : hpsReqSz256k

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Payload Size Less Than or Equal to 256K

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.52

Field Name : hpsReqSz64k

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Payload Size Less Than or Equal to 64K

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.51

Field Name : hpsReqSz32k

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Payload Size Less Than or Equal to 32K

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.50

Field Name : hpsReqSz16k

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Payload Size Less Than or Equal to 16K

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.49

Field Name : hpsReqSz8k

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Payload Size Less Than or Equal to 8K

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.48

Field Name : hpsReqSz4k

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Payload Size Less Than or Equal to 4K

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.47

Field Name : hpsReqSz2k

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Payload Size Less Than or Equal to 2K

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.46

Field Name : hpsReqSz1k

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Payload Size Less Than or Equal to 1K

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.45

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : httpUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method UNKNOWN
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.44

Field Name : httpDel
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method DELETE
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.43

Field Name : httpConnect
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method CONNECT
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.42

Field Name : httpOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method OPTIONS
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.41

Field Name : httpTrace
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method TRACE
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.40

Field Name : httpPost
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method POST
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.39

Field Name : httpPut
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method PUT
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.38

Field Name : httpHead
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method HEAD
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.37

Field Name : httpGet
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Method GET
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.36

Field Name : rspChunk
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Response Chunk
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.35

Field Name : http10
Field Type : CounterBasedGauge64
Field Status : current
Description : Request HTTP 1.0
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.34

Field Name : http11
Field Type : CounterBasedGauge64
Field Status : current
Description : Request HTTP 1.1
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.33

Field Name : errorCondition
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Condition
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.32

Field Name : policyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.31

Field Name : ddosPolicyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy Violation
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.30

Field Name : hpsServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Server TCP RST Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.29

Field Name : clientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Client TCP RST Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.28

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Line Too Long
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.27

Field Name : invalidHdrVal
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Header Value Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.26

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : invalidHdrName
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Header Name Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.25

Field Name : headerNameTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Header Name Too Long
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.24

Field Name : tooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Header Too Many
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.23

Field Name : invalidHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Header Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.22

Field Name : negRspRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative Response Remain
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.21

Field Name : negReqRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative Request Remain
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.20

Field Name : parsereqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse Request Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.19

Field Name : lowerThanMssExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Min Payload Size Fail Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.18

Field Name : dstReqRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.17

Field Name : srcReqRateExceed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Src Request Rate Exceeded

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.16

Field Name : reqContentLen

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Content-Length Received

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.15

Field Name : request

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Total

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.14

Field Name : reqRetrans

Field Type : CounterBasedGauge64

Field Status : current

Description : Retransmit Request

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.13

Field Name : retransRst

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Retransmit RST

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.12

Field Name : retransPush

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Retransmit PSH

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.11

Field Name : retransFin

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Retransmit FIN

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.10

Field Name : retrans

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Retransmit

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.9

Field Name : newSyn

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP SYN

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.8

Field Name : httpIdleTimeout

Field Type : CounterBasedGauge64

Field Status : current

Description : Http Idle Timeout

OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.7

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : partialHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Partial Header
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.6

Field Name : ofo
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-Of-Order Packets
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.5

Field Name : ofoQueueExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-Of-Order Queue Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.4

Field Name : ofoTimerExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-Of-Order Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.3

Field Name : reqOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-Of-Order Request
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.2

Field Name : reqProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets Processed
OID : 1.3.6.1.4.1.22610.2.4.10.102.43.1.1

Field Name : nonQueryOpcodePassThrough
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Non Query Opcode Pass Through
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.59

Field Name : dnsOutboundQuerySessTimedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Outbound Query Session Timed Out
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.58

Field Name : dnsOutboundQueryResponseSizeExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Outbound Query Resp Size Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.57

Field Name : dnsDgRateExceed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : DNS Domain Group Domain Query Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.56

Field Name : dnsQueryClassAny
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class ANY
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.55

Field Name : dnsQueryClassNone
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class NONE
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.54

Field Name : dnsQueryClassHs
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class HESIOD
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.53

Field Name : dnsQueryClassChaos
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class CHAOS
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.52

Field Name : dnsQueryClassCsnet
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class CSNET
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.51

Field Name : dnsQueryClassIn
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class INTERNET
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.50

Field Name : dnsMalform
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Malform Query (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.49

Field Name : dnsQueryClassWhitelistMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Class Whitelist Miss
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.48

Field Name : dnsNxExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : NXDOMAIN Response Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.47

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : dnsAuthUdpFailBl
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth UDP Fail Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.46

Field Name : forceTcpAuthConnHit
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth Force-TCP With UDP Auth Connection Hit
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.45

Field Name : dnsAuthResp
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth Responded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.44

Field Name : dnsAuthDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.43

Field Name : forceTcpAuthTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth Force-TCP With UDP Auth Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.42

Field Name : dnsRrtypeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Record Type Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.41

Field Name : dnsFqdnLabelCountExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : FQDN Label Count Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.40

Field Name : dnsPolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Policy Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.39

Field Name : dnsUdpAuthRetryGapDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth UDP Retry-Gap Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.38

Field Name : dnsFqdnRateByLabelCountExceed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : FQDN Rate by Label Count Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.37

Field Name : dnsFqdnRateByLabelCountCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : FQDN Rate by Label Count Checked
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.36

Field Name : dnsDgActionDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Domain Group Action Deny
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.35

Field Name : dnsDgActionPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Domain Group Action Permit
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.34

Field Name : dnsQueryTypeOpt
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type OPT
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.33

Field Name : dnsQueryTypeSoa
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type SOA
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.32

Field Name : dnsQueryTypeMx
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type MX
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.31

Field Name : dnsQueryTypeSrv
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type SRV
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.30

Field Name : dnsQueryTypeAny
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type ANY
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.29

Field Name : dnsQueryTypeCname
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type CNAME
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.28

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : dnsQueryTypeNs
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type NS
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.27

Field Name : dnsQueryTypeAaaa
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type AAAA
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.26

Field Name : dnsQueryTypeA
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query Type A
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.25

Field Name : dnsPktProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Packets Processed
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.24

Field Name : dnsFqdnLabelLenExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : FQDN Label Length Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.23

Field Name : dnsAuthUdpTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth UDP Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.22

Field Name : dnsAuthUdpFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth UDP Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.21

Field Name : dnsTcpAuthPass
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth Force-TCP Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.20

Field Name : dnsNxBl
Field Type : CounterBasedGauge64
Field Status : current
Description : NXDOMAIN Query Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.19

Field Name : dnsNxDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : NXDOMAIN Query Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.18

Field Name : dnsIsNx
Field Type : CounterBasedGauge64
Field Status : current
Description : NXDOMAIN Response
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.17

Field Name : dnsFqdnStage2Exceed
Field Type : CounterBasedGauge64
Field Status : current
Description : FQDN Rate Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.16

Field Name : dnsAuthUdpPass
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth UDP Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.15

Field Name : srcRateLimit4
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Request Rate 5 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.14

Field Name : srcRateLimit3
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Request Rate 4 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.13

Field Name : srcRateLimit2
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Request Rate 3 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.12

Field Name : srcRateLimit1
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Request Rate 2 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.11

Field Name : srcRateLimit0
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Request Rate 1 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.10

Field Name : dstRateLimit4
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate 5 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.9

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : dstRateLimit3
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate 4 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.8

Field Name : dstRateLimit2
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate 3 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.7

Field Name : dstRateLimit1
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate 2 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.6

Field Name : dstRateLimit0
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Request Rate 1 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.5

Field Name : dnsQryAnyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Query ANY Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.4

Field Name : dnsMalformDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Malform Query Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.3

Field Name : dnsAuthUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth UDP
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.2

Field Name : forceTcpAuth
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Auth Force-TCP
OID : 1.3.6.1.4.1.22610.2.4.10.102.42.1.1

Field Name : otherTotalBytesDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Total Bytes Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.49

Field Name : otherTotalBytesRcv
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : OTHER Total Bytes Received

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.48

Field Name : otherDropBl

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER Blacklisted Packets Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.47

Field Name : otherAnyExceed

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER Exceeded

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.46

Field Name : srcDstOtherFilterActionWhitelist

Field Type : CounterBasedGauge64

Field Status : current

Description : SrcDst Filter Action WL

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.45

Field Name : srcDstOtherFilterActionDefaultPass

Field Type : CounterBasedGauge64

Field Status : current

Description : SrcDst Filter Action Default Pass

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.44

Field Name : srcDstOtherFilterActionDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : SrcDst Filter Action Drop

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.43

Field Name : srcDstOtherFilterActionBlacklist

Field Type : CounterBasedGauge64

Field Status : current

Description : SrcDst Filter Action Blacklist

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.42

Field Name : srcDstOtherFilterNotMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : SrcDst Filter No Match

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.41

Field Name : srcDstOtherFilterMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : SrcDst Filter Match

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.40

Field Name : srcOtherFilterActionWhitelist

Field Type : CounterBasedGauge64

Field Status : current

Description : Src Filter Action WL

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.39

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : srcOtherFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.38

Field Name : srcOtherFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.37

Field Name : srcOtherFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.36

Field Name : srcOtherFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.35

Field Name : srcOtherFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.34

Field Name : dstOtherFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.33

Field Name : dstOtherFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.32

Field Name : dstOtherFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.31

Field Name : dstOtherFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.30

Field Name : dstOtherFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Dst Filter No Match

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.29

Field Name : dstOtherFilterMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : Dst Filter Match

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.28

Field Name : otherExceedDropBrateSrcDst

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER SrcDst KiBit Rate Drop (KiBit) (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.27

Field Name : otherExceedDropBrateSrc

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER Src KiBit Rate Drop (KiBit) (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.26

Field Name : otherExceedDropBrateDst

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER Dst KiBit Rate Drop (KiBit) (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.25

Field Name : otherDropBlackUserCfgSrcDst

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER SrcDst Blacklist User Packets Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.24

Field Name : otherDropBlackSrcDst

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER SrcDst Blacklist Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.23

Field Name : otherFragExceedDropSrcDst

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER SrcDst Fragment Exceed Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.22

Field Name : otherExceedDropFprateSrcDst

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER SrcDst Fragment Rate Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.21

Field Name : otherExceedDropPrateSrcDst

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER SrcDst Packet Rate Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.20

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : otherExceedDropAnySrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER SrcDst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.19

Field Name : otherSrcDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER SrcDst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.18

Field Name : otherDropBlackUserCfgSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Blacklist User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.17

Field Name : otherDropBlackSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.16

Field Name : otherFragExceedDropSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Fragment Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.15

Field Name : otherExceedDropFprateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Fragment Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.14

Field Name : otherExceedDropPrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.13

Field Name : otherExceedDropAnySrc
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.12

Field Name : otherSrcDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : OTHER Src Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.11

Field Name : otherDropBlackDst
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : OTHER Dst Blacklist Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.10

Field Name : otherFragExceedDropDst

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER Dst Fragment Exceed Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.9

Field Name : otherExceedDropFprateDst

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER Dst Fragment Rate Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.8

Field Name : otherExceedDropPrateDst

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER Dst Packet Rate Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.7

Field Name : otherExceedDropAnyDst

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER Dst Exceed Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.6

Field Name : otherFragDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER Frag Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.5

Field Name : otherDstDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER Dst Packets Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.4

Field Name : otherTotalDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER Total Packets Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.3

Field Name : otherFragRcvd

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER Frag Received

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.2

Field Name : otherReceive

Field Type : CounterBasedGauge64

Field Status : current

Description : OTHER Total Packets Received

OID : 1.3.6.1.4.1.22610.2.4.10.102.41.1.1

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : icmpTotalBytesDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Total Bytes Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.44

Field Name : icmpTotalDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Total Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.43

Field Name : icmpTotalBytesRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Total Bytes Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.42

Field Name : icmpFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Frag Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.41

Field Name : icmpFragRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Frag Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.40

Field Name : icmpDropBl
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Blacklisted Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.39

Field Name : icmpAnyExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.38

Field Name : icmpWildcard
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Wildcard
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.37

Field Name : icmpRateExceed2Bl
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 3 Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.36

Field Name : icmpRateExceed2Drop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : ICMP Type Rate 3 Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.35

Field Name : icmpRateExceed1Bl
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 2 Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.34

Field Name : icmpRateExceed1Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 2 Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.33

Field Name : icmpRateExceed0Bl
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 1 Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.32

Field Name : icmpRateExceed0Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 1 Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.31

Field Name : icmpTypeBl
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.30

Field Name : icmpType
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.29

Field Name : icmpExceedDropBrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst KiBit Rate Drop (KiBit)(deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.28

Field Name : icmpExceedDropBrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.27

Field Name : icmpExceedDropBrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dst KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.26

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : icmpRateExceed2
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 3 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.25

Field Name : icmpRateExceed1
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 2 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.24

Field Name : icmpRateExceed0
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Rate 1 Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.23

Field Name : icmpWildcardDenyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Wildcard Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.22

Field Name : icmpV6RfcUndefDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 RFC Undef Type Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.21

Field Name : icmpV4RfcUndefDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv4 RFC Undef Type Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.20

Field Name : icmpTypeDenyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.19

Field Name : icmpSrcDstBlDropUserCfg
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst Blacklisted User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.18

Field Name : icmpSrcDstBlDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.17

Field Name : icmpSrcDstPktRateExceedDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : ICMP SrcDst Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.16

Field Name : icmpSrcDstAnyExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.15

Field Name : icmpSrcDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP SrcDst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.14

Field Name : icmpDropBlackSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.13

Field Name : icmpSrcPktRateExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.12

Field Name : icmpSrcAnyExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.11

Field Name : icmpDstBlDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dst Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.10

Field Name : icmpExceedDropAnyDst
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.9

Field Name : icmpOtherRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP other Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.8

Field Name : icmpEchoRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Echo Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.7

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : icmpRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Total Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.6

Field Name : srcIcmpBlUserConfig
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Blacklisted User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.5

Field Name : icmpWildcardBl
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Type Wildcard Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.4

Field Name : icmpExceedDropPratedDst
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dst Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.3

Field Name : icmpDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.2

Field Name : icmpSrcDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Src Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.40.1.1

Field Name : udpRetryGapDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry-Gap Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.83

Field Name : udpTotalBytesDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Total Bytes Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.82

Field Name : udpTotalBytesRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Total Bytes Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.81

Field Name : udpAuthDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : UDP Auth Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.80

Field Name : udpFragDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Frag Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.79

Field Name : udpFragRcvd

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Frag Received

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.78

Field Name : udpDropBl

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Blacklist Packets Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.77

Field Name : udpAnyExceed

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Exceeded

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.76

Field Name : udpConnPrateBl

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Conn Pkt Rate Blacklisted

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.75

Field Name : udpConnPrateExceed

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Conn Pkt Rate Exceeded

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.74

Field Name : ntpMonlistRespBl

Field Type : CounterBasedGauge64

Field Status : current

Description : NTP Monlist Response Blacklisted

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.73

Field Name : ntpMonlistResp

Field Type : CounterBasedGauge64

Field Status : current

Description : NTP Monlist Response

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.72

Field Name : ntpMonlistReqBl

Field Type : CounterBasedGauge64

Field Status : current

Description : NTP Monlist Request Blacklisted

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.71

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : ntpMonlistReq
Field Type : CounterBasedGauge64
Field Status : current
Description : NTP Monlist Request
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.70

Field Name : udpPayloadTooSmallBl
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Payload Too Small Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.69

Field Name : udpPayloadTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Payload Too Small
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.68

Field Name : udpPayloadTooBigBl
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Payload Too Large Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.67

Field Name : udpPayloadTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Payload Too Large
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.66

Field Name : udpRetryFailBl
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry Fail Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.65

Field Name : udpRetryPassWl
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry Pass WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.64

Field Name : udpWellknownSrcPortBl
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcPort Wellknown Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.63

Field Name : udpWellknownSrcPort
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcPort Wellknown
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.62

Field Name : srcDstUdpFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : SrcDst Filter Action WL

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.61

Field Name : srcDstUdpFilterActionDefaultPass

Field Type : CounterBasedGauge64

Field Status : current

Description : SrcDst Filter Action Default Pass

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.60

Field Name : srcDstUdpFilterActionDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : SrcDst Filter Action Drop

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.59

Field Name : srcDstUdpFilterActionBlacklist

Field Type : CounterBasedGauge64

Field Status : current

Description : SrcDst Filter Action Blacklist

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.58

Field Name : srcDstUdpFilterNotMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : SrcDst Filter No Match

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.57

Field Name : srcDstUdpFilterMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : SrcDst Filter Match

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.56

Field Name : srcUdpFilterActionWhitelist

Field Type : CounterBasedGauge64

Field Status : current

Description : Src Filter Action WL

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.55

Field Name : srcUdpFilterActionDefaultPass

Field Type : CounterBasedGauge64

Field Status : current

Description : Src Filter Action Default Pass

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.54

Field Name : srcUdpFilterActionDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Src Filter Action Drop

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.53

Field Name : srcUdpFilterActionBlacklist

Field Type : CounterBasedGauge64

Field Status : current

Description : Src Filter Action Blacklist

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.52

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : srcUdpFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.51

Field Name : srcUdpFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.50

Field Name : exceedDropBrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.49

Field Name : exceedDropBrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.48

Field Name : exceedDropBrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.47

Field Name : udpOverLimitAuthSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.46

Field Name : udpOverLimitAuthSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.45

Field Name : udpOverLimitAuthDstPort
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Port Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.44

Field Name : udpOverLimitAuthDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.43

Field Name : udpAuthPass
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : UDP Auth Passed

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.42

Field Name : dstUdpFilterActionWhitelist

Field Type : CounterBasedGauge64

Field Status : current

Description : Dst Filter Action WL

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.41

Field Name : dstUdpFilterActionDefaultPass

Field Type : CounterBasedGauge64

Field Status : current

Description : Dst Filter Action Default Pass

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.40

Field Name : dstUdpFilterActionDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Dst Filter Action Drop

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.39

Field Name : dstUdpFilterActionBlacklist

Field Type : CounterBasedGauge64

Field Status : current

Description : Dst Filter Action Blacklist

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.38

Field Name : dstUdpFilterNotMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : Dst Filter No Match

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.37

Field Name : dstUdpFilterMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : Dst Filter Match

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.36

Field Name : udpConnPrateDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : UDP Conn Pkt Rate Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.35

Field Name : ntpMonlistRespDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : NTP Monlist Response Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.34

Field Name : ntpMonlistReqDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : NTP Monlist Request Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.33

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : udpPayloadTooSmallDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Payload Too Small Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.32

Field Name : udpPayloadTooBigDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Payload Too Large Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.31

Field Name : udpRetryTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.30

Field Name : udpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.29

Field Name : udpRetryPass
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.28

Field Name : udpRetryStart
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Retry Init
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.27

Field Name : udpWellknownSrcPortDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcPort Wellknown Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.26

Field Name : udpPortZeroDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port 0 Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.25

Field Name : udpDropBlackUserCfgSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Blacklist User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.24

Field Name : dropBlackSrcDst
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : UDP SrcDst Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.23

Field Name : exceedDropClimitSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Connection Limit Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.22

Field Name : exceedDropCrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Connection Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.21

Field Name : exceedDropPrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.20

Field Name : exceedAnySrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.19

Field Name : udpSrcDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP SrcDst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.18

Field Name : udpDropBlackUserCfgSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Blacklist User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.17

Field Name : dropBlackSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.16

Field Name : exceedDropClimitSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Connection Limit Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.15

Field Name : exceedDropCrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Connection Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.14

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : exceedDropPrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.13

Field Name : exceedAnySrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.12

Field Name : udpDropSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Src Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.11

Field Name : dropBlackDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.10

Field Name : exceedDropClimitDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Connection Limit Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.9

Field Name : exceedDropCrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Connection Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.8

Field Name : exceedDropPrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.7

Field Name : exceedAnyDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.6

Field Name : udpDropDst
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.5

Field Name : udpTotalDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : UDP Total Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.4

Field Name : instateless
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Stateless Packets
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.3

Field Name : inudp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Total Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.2

Field Name : udpSessCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.102.39.1.1

Field Name : hybridSynAuthAuthNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Auth no match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.148

Field Name : hybridSynAuthEntryAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Entry Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.147

Field Name : tcpSmallWindowDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Small-Window Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.146

Field Name : tcpSmallWindowBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Small-Window Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.145

Field Name : tcpSmallWindow
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Small-Window Total
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.144

Field Name : hybridSynAuthMethodChange
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Method Change
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.143

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : tcpInvalidSynackRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Invalid SYNACK Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.142

Field Name : hybridSynAuthValidFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Valid SYNACK Auth Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.141

Field Name : hybridSynAuthInvalidFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Invalid SYNACK Auth Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.140

Field Name : hybridSynAuthValidPass
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Valid SYNACK Auth Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.139

Field Name : hybridSynAuthInvalidPass
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Invalid SYNACK Auth Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.138

Field Name : hybridSynAuthLookupFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Lookup Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.137

Field Name : hybridSynAuthFilterFull
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Filter Full
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.136

Field Name : hybridSynAuthInvalidSaSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Invalid SYNACK Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.135

Field Name : hybridSynAuthValidSaSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Valid SYNACK Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.134

Field Name : hybridSynAuthUnknownFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : SYN Auth Hybrid Unknown Auth Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.133

Field Name : hybridSynAuthUnknownPass
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Auth Hybrid Unknown Auth Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.132

Field Name : tcpAuthRst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Auth Reset
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.131

Field Name : tcpProgressionViolationExceedReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Progression: Violation Exceeded Reset
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.130

Field Name : tcpProgressionViolationExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Progression: Violation Exceeded Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.129

Field Name : tcpProgressionViolationExceedBl
Field Type : CounterBasedGauge64
Field Status : current
Description : Progression: Violation Exceeded Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.128

Field Name : tcpProgressionViolationExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Progression: Violation Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.127

Field Name : tcpSynTfoRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN TFO Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.126

Field Name : tcpPerConnZwindowRateExceedBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Zero-Window Rate Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.125

Field Name : tcpPerConnZwindowRateExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Zero-Window Rate Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.124

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : tcpPerConnRexmitRateExceedBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Retransmit Rate Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.123

Field Name : tcpPerConnRexmitRateExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Retransmit Rate Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.122

Field Name : tcpPerConnOfRateExceedBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Out-Of-Seq Rate Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.121

Field Name : tcpPerConnOfRateExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Out-Of-Seq Rate Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.120

Field Name : tcpActionOnSynBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Timeout Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.119

Field Name : tcpActionOnAckBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Timeout Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.118

Field Name : tcpTotalBytesDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Total Bytes Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.117

Field Name : tcpTotalBytesRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Total Bytes Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.116

Field Name : tcpAuthResp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Auth Responded
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.115

Field Name : tcpAuthDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : TCP Auth Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.114

Field Name : tcpFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Frag Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.113

Field Name : tcpFragRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Frag Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.112

Field Name : tcpDropBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Blacklist Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.111

Field Name : tcpAnyExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.110

Field Name : tcpPerConnPrateExceedBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Pkt Rate Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.109

Field Name : tcpRetransmitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Retransmit Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.108

Field Name : tcpZeroWindowDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Zero-Window Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.107

Field Name : tcpOutOfSeqDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-Of-Seq Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.106

Field Name : synAuthPassWl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Auth Pass WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.105

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : srcDstTcpFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.104

Field Name : srcDstTcpFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.103

Field Name : srcDstTcpFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.102

Field Name : srcDstTcpFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.101

Field Name : srcDstTcpFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.100

Field Name : srcDstTcpFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SrcDst Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.99

Field Name : srcTcpFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.98

Field Name : srcTcpFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.97

Field Name : srcTcpFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.96

Field Name : srcTcpFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Src Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.95

Field Name : srcTcpFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.94

Field Name : srcTcpFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Src Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.93

Field Name : dstTcpFilterActionWhitelist
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action WL
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.92

Field Name : tcpConcurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Concurrent Port Access
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.91

Field Name : tcpExceedDropBrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.90

Field Name : tcpExceedDropBrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.89

Field Name : tcpExceedDropBrateDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst KiBit Rate Drop (KiBit) (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.88

Field Name : tcpOverLimitSynCookieSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Over Limit Cookie (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.87

Field Name : tcpOverLimitSynCookieSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Over Limit Cookie (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.86

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : tcpOverLimitSynAuthSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.85

Field Name : tcpOverLimitSynAuthSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.84

Field Name : dstTcpFilterActionDefaultPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Default Pass
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.83

Field Name : dstTcpFilterActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.82

Field Name : dstTcpFilterActionBlacklist
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Action Blacklist
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.81

Field Name : dstTcpFilterNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter No Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.80

Field Name : dstTcpFilterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dst Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.79

Field Name : tcpUnauthRstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Unauth RST Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.78

Field Name : tcpActionOnSynGapPass
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Retry-Gap Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.77

Field Name : tcpActionOnSynGapDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : TCP SYN Retry Retry-Gap Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.76

Field Name : tcpActionOnSynReset
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Timeout Reset
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.75

Field Name : tcpActionOnSynTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.74

Field Name : tcpActionOnSynFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.73

Field Name : tcpActionOnSynPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.72

Field Name : tcpActionOnSynStart
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Retry Init
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.71

Field Name : tcpNewConnAckRetryGapDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New-Connection-Ack-Retry-Gap Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.70

Field Name : tcpNewConnAckRetryGapReset
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New-Connection-Ack-Retry-Gap Reset (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.69

Field Name : tcpNewConnAckRetryGapTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New-Connection-Ack-Retry-Gap Timeout (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.68

Field Name : tcpNewConnAckRetryGapFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New-Connection-Ack-Retry-Gap Fail (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.67

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : tcpNewConnAckRetryGapPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New-Connection-Ack-Retry-Gap Pass (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.66

Field Name : tcpNewConnAckRetryGapStart
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP New-Connection-Ack-Retry-Gap Initialize (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.65

Field Name : tcpActionOnAckGapPass
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Retry-Gap Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.64

Field Name : tcpActionOnAckGapDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Retry-Gap Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.63

Field Name : tcpPerConnPrateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Conn Pkt Rate Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.62

Field Name : tcpRexmitSynLimitBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Retransmit SYN Exceed Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.61

Field Name : tcpRetransmitBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Retransmit Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.60

Field Name : tcpOutOfSeqBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-Of-Seq Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.59

Field Name : tcpZeroWindowBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Zero-Window Blacklisted
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.58

Field Name : tcpRexmitSynLimitDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : TCP Retransmit SYN Exceed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.57

Field Name : tcpRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Retransmit Total
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.56

Field Name : tcpZeroWindow
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Zero-Window Total
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.55

Field Name : tcpOutOfSeq
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Out-Of-Seq Total
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.54

Field Name : tcpAckNoSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK No SYN
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.53

Field Name : tcpActionOnAckReset
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Timeout Reset
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.52

Field Name : tcpActionOnAckTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.51

Field Name : tcpActionOnAckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.50

Field Name : tcpActionOnAckPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.49

Field Name : tcpActionOnAckMatched
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Matched
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.48

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : tcpActionOnAckStart
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Retry Init
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.47

Field Name : tcpOverLimitSynCookieDstPort
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Port Over Limit Cookie (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.46

Field Name : tcpOverLimitSynAuthDstPort
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Port Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.45

Field Name : tcpOverLimitSynCookieDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Over Limit Cookie (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.44

Field Name : tcpOverLimitSynAuthDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dst Over Limit Authentication (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.43

Field Name : synAuthSkip
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Auth Skipped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.42

Field Name : synAuthPass
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Auth Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.41

Field Name : tcpSyncookiePass
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Cookie Passed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.40

Field Name : tcpSyncookieFailBl
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Cookie Blacklist Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.39

Field Name : tcpSyncookieHwMissing
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : TCP SYN Cookie HW Missed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.38

Field Name : tcpSyncookieCheckFail
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Cookie Check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.37

Field Name : tcpSyncookieSentFail
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Cookie Send Failed
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.36

Field Name : tcpSyncookieSent
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Cookie Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.35

Field Name : tcpPortZeroDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Port 0 Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.34

Field Name : tcpDropBlackUserCfgSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Blacklist User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.33

Field Name : tcpDropBlackSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.32

Field Name : tcpExceedDropClimitSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Connection Limit Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.31

Field Name : tcpExceedDropCrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Connection Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.30

Field Name : tcpExceedDropPrateSrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.29

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : tcpExceedDropAnySrcDst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.28

Field Name : tcpSrcDstDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SrcDst Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.27

Field Name : tcpDropBlackUserCfgSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Blacklist User Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.26

Field Name : tcpDropBlackSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Blacklist Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.25

Field Name : tcpExceedDropClimitSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Connection Limit Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.24

Field Name : tcpExceedDropCrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Connection Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.23

Field Name : tcpExceedDropPrateSrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Packet Rate Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.22

Field Name : tcpExceedDropAnySrc
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Exceed Drop (deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.21

Field Name : tcpSrcDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Src Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.20

Field Name : tcpDropBlackDst
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : TCP Dst Blacklist Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.19

Field Name : tcpExceedDropClimitDst

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Dst Connection Limit Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.18

Field Name : tcpExceedDropCrateDst

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Dst Connection Rate Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.17

Field Name : tcpExceedDropPrateDst

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Dst Packet Rate Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.16

Field Name : tcpExceedDropAnyDst

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Dst Exceed Drop (deprecated)

OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.15

Field Name : tcpDstDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Dst Packets Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.14

Field Name : tcpTotalDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Total Packets Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.13

Field Name : tcpSynRate

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP SYN Rate Per Sec

OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.12

Field Name : tcpResetServer

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Reset Server

OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.11

Field Name : tcpResetClient

Field Type : CounterBasedGauge64

Field Status : current

Description : TCP Reset Client

OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.10

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : tcpOutrst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Outbound RST
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.9

Field Name : tcpRstRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP RST Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.8

Field Name : tcpFinRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP FIN Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.7

Field Name : tcpAckRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP ACK Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.6

Field Name : tcpSynAckRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN ACK Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.5

Field Name : tcpInvalidSynRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Invalid SYN Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.4

Field Name : tcpSynRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.3

Field Name : intcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Total Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.2

Field Name : tcpSessCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.102.38.1.1

Field Name : filterDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : Extracted Filter Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.81.1.5

Field Name : filterMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Extracted Filter Match
OID : 1.3.6.1.4.1.22610.2.4.10.102.81.1.4

Field Name : genericError
Field Type : CounterBasedGauge64
Field Status : current
Description : Pattern Recognition: Exceptions
OID : 1.3.6.1.4.1.22610.2.4.10.102.81.1.3

Field Name : notFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Pattern Recognition: Pattern Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.102.81.1.2

Field Name : proceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Pattern Recognition: Engine Started
OID : 1.3.6.1.4.1.22610.2.4.10.102.81.1.1

Field Name : quicVersionNoMatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Version No Match Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.31

Field Name : quicCreateConnInitOnly
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Create Connection on Initial Only
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.30

Field Name : quicDcidPktRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC DCID Packet Rate Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.29

Field Name : quicAeadPktRateExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC AEAD Packet Rate Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.28

Field Name : quic0rttDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC 0RTT Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.27

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : quicDecryptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Decrypt Success
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.26

Field Name : quicEncryptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Encrypt Success
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.25

Field Name : quicDecryptFail
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Decrypt Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.24

Field Name : quicEncryptFail
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Encrypt Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.23

Field Name : quicShortHeaderActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Short Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.22

Field Name : quicShortHeaderReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Short Header Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.21

Field Name : quicInvalidRetryToken
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Invalid Retry Token
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.20

Field Name : quicConnectionCloseSent
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Connection Close Sent
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.19

Field Name : quicRetryAuthFail
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Retry Auth Fail
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.18

Field Name : quicRetryAuthPass
Field Type : CounterBasedGauge64
Field Status : current

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Description : QUIC Retry Auth Pass

OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.17

Field Name : quicRetryAuthSent

Field Type : CounterBasedGauge64

Field Status : current

Description : QUIC Retry Auth Sent

OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.16

Field Name : quicFixedBitNotSet

Field Type : CounterBasedGauge64

Field Status : current

Description : QUIC Fixed Bit Not Set

OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.15

Field Name : quicMalformedScidLenMaxExceed

Field Type : CounterBasedGauge64

Field Status : current

Description : QUIC Malformed SCID Len Max Exceed

OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.14

Field Name : quicMalformedDcidLenMaxExceed

Field Type : CounterBasedGauge64

Field Status : current

Description : QUIC Malformed DCID Len Max Exceed

OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.13

Field Name : quicMalformedActionBlacklist

Field Type : CounterBasedGauge64

Field Status : current

Description : QUIC Malformed Action Blacklist

OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.12

Field Name : quicMalformedActionDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : QUIC Malformed Action Drop

OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.11

Field Name : quicMalformedActionTaken

Field Type : CounterBasedGauge64

Field Status : current

Description : QUIC Malformed Action Taken

OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.10

Field Name : quicVersionMatchActionBlacklist

Field Type : CounterBasedGauge64

Field Status : current

Description : QUIC Version Match Action Blacklist

OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.9

Field Name : quicVersionMatchActionDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : QUIC Version Match Action Drop

OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.8

ACOS-DDOS-STATS-MIB_acosDdos_oid_list

Field Name : quicVersionMatchActionTaken
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Version Match Action Taken
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.7

Field Name : quicHandshakeReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Handshake Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.6

Field Name : quic0rttReceivied
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC 0RTT Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.5

Field Name : quicRetryReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Retry Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.4

Field Name : quicVersionNegotiationReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Version Negotiation Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.3

Field Name : quicInitialReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Initial Packet Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.2

Field Name : quicPacketReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC Packet Received
OID : 1.3.6.1.4.1.22610.2.4.10.102.94.1.1

ACOS-EVENT-NOTIFICATION-STATS-MIB_acosEventNotification_oid_list

Field Name : ngwafHcMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : NGWAF A10C metrics export failed
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.86

Field Name : ngwafHcMetricsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : NGWAF A10C metrics export
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.85

Field Name : ngwafHcEpTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : NGWAF A10C PE export failed
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.84

Field Name : ngwafHcEpTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : NGWAF A10C PE export
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.83

Field Name : certPinningListTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert-pinning candidate list dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.82

Field Name : certPinningListTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert-pinning candidate list sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.81

Field Name : avroSystemEnvDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : System Environmet dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.80

Field Name : avroSystemEnvTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : System environment sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.79

Field Name : cgnPortUsageHstgrmAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN Port Usage Histogram A10C Export Failed
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.78

Field Name : cgnPortUsageHstgrmAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current

ACOS-EVENT-NOTIFICATION-STATS-MIB_acosEventNotification_oid_list

Description : CGN Port Usage Histogram A10C Export

OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.77

Field Name : vpnStatsMetricsTopicDequeueErr

Field Type : CounterBasedGauge64

Field Status : current

Description : VPN STATS metrics dropped,enq error analytics qs

OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.76

Field Name : vpnStatsMetricsTopic

Field Type : CounterBasedGauge64

Field Status : current

Description : VPN STATS metrics sent

OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.75

Field Name : vpnIkeGatewayMetricsTopicDequeueErr

Field Type : CounterBasedGauge64

Field Status : current

Description : IKE gateway metrics dropped,enq error analytics qs

OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.74

Field Name : vpnIkeGatewayMetricsTopic

Field Type : CounterBasedGauge64

Field Status : current

Description : IKE gateway metrics sent

OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.73

Field Name : vpnIpsecSaMetricsTopicDequeueErr

Field Type : CounterBasedGauge64

Field Status : current

Description : IPSec SA metrics dropped,enq error analytics qs

OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.72

Field Name : vpnIpsecSaMetricsTopic

Field Type : CounterBasedGauge64

Field Status : current

Description : IPSec SA metrics sent

OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.71

Field Name : peAcosHarmonyTopicDequeueErr

Field Type : CounterBasedGauge64

Field Status : current

Description : L7 PE dropped,enq error analytics queues

OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.70

Field Name : peAcosHarmonyTopicEnqueueErr

Field Type : CounterBasedGauge64

Field Status : current

Description : L7 PE dropped,enq error on acos queues

OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.69

Field Name : peAcosHarmonyTopic

Field Type : CounterBasedGauge64

Field Status : current

Description : L7 PE logs sent

OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.68

ACOS-EVENT-NOTIFICATION-STATS-MIB_acosEventNotification_oid_list

Field Name : hcCountersDroppedFromBlade
Field Type : CounterBasedGauge64
Field Status : current
Description : A10C counters dropped from blade (uuid or size mismatch)
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.67

Field Name : hcCountersReceivedFromBlade
Field Type : CounterBasedGauge64
Field Status : current
Description : A10C counters received from blade
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.66

Field Name : hcCountersSentToMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : A10C counters sent to master
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.65

Field Name : hcOperReceivedFromBlade
Field Type : CounterBasedGauge64
Field Status : current
Description : A10C oper received from blade
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.64

Field Name : hcOperSentToMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : A10C oper to master
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.63

Field Name : hcLogsReceivedFromBlade
Field Type : CounterBasedGauge64
Field Status : current
Description : A10C logs received from blade
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.62

Field Name : hcLogsSentToMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : A10C logs sent to master
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.61

Field Name : visibilityTopnHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Visibility TopN metrics dropped,enq error analytics qs
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.60

Field Name : visibilityTopnHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : Visibility TopN sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.59

Field Name : wafEventsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current

ACOS-EVENT-NOTIFICATION-STATS-MIB_acosEventNotification_oid_list

Description : WAF events metrics dropped,enq error analytics qs
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.58

Field Name : wafEventsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF events topic counter
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.57

Field Name : wafLearnPrTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF learn metrics dropped,enq error analytics qs
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.56

Field Name : wafLearnPrTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF learn topic counter
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.55

Field Name : analyticsBusRestart
Field Type : CounterBasedGauge64
Field Status : current
Description : Analytics bus restart count
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.54

Field Name : ssliPeAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : SSLi PE topic to A10C dequeue error
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.53

Field Name : ssliPeAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : SSLi PE topic counter from acos to A10C
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.52

Field Name : ssliPcAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : SSLi PC topic to A10C dequeue error
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.51

Field Name : ssliPcAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : SSLi PC topic counter from acos to A10C
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.50

Field Name : metricsDroppedPtMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : Metrics dropped,missing partition tenant mapping
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.49

ACOS-EVENT-NOTIFICATION-STATS-MIB_acosEventNotification_oid_list

Field Name : pcThrottleDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 PC logs dropped,throttling
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.48

Field Name : slbServerSslCountersMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL metrics dropped,enq error analytics qs
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.47

Field Name : slbServerSslCountersMetricsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.46

Field Name : slbClientSslCountersMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Cilent SSL metrics dropped,enq error analytics qs
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.45

Field Name : slbClientSslCountersMetricsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.44

Field Name : slbSslStatsMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL metrics dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.43

Field Name : slbSslStatsMetricsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.42

Field Name : ruleSetApplicationMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : AppFW metrics dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.41

Field Name : ruleSetApplicationMetricsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : AppFW metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.40

Field Name : cgnSummaryErrorAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current

ACOS-EVENT-NOTIFICATION-STATS-MIB_acosEventNotification_oid_list

Description : CGN PE logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.39

Field Name : cgnSummaryErrorAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN PE logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.38

Field Name : fwRstPcAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : FW RST PC logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.37

Field Name : fwRstPcAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : FW RST PC logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.36

Field Name : fwDenyPcAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : FW DENY PC logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.35

Field Name : fwDenyPcAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : FW DENY PC logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.34

Field Name : fwPcAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : FW PC logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.33

Field Name : fwPcAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : FW PC logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.32

Field Name : cgnPeAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN PE logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.31

Field Name : cgnPeAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN PE logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.30

ACOS-EVENT-NOTIFICATION-STATS-MIB_acosEventNotification_oid_list

Field Name : cgnPcAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN PC logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.29

Field Name : cgnPcAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN PC logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.28

Field Name : pcAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 PC logs dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.27

Field Name : pcAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 PC logs sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.26

Field Name : pcEncodingFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 PC logs dropped,encoding error
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.25

Field Name : kafkaTopicError
Field Type : CounterBasedGauge64
Field Status : current
Description : Module not supported by analytics
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.24

Field Name : prInLatencyAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR on latency negative
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.23

Field Name : prOutLatencyAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR out latency negative
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.22

Field Name : prOutLatencyThresholdExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR out latency threshold exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.21

Field Name : prInLatencyThresholdExceed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-EVENT-NOTIFICATION-STATS-MIB_acosEventNotification_oid_list

Description : L7 PR on latency threshold exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.20

Field Name : prBeTtlbAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR back-end ttlb is negative
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.19

Field Name : prBeTtfbAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR back-end ttfb is negative
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.18

Field Name : prNotAllowedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR dropped, not allowed to be sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.17

Field Name : prThrottleDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR dropped,log throttling
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.16

Field Name : kafkaQueueFullErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages dropped,acos analytics queue full
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.15

Field Name : kafkaBrokerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Messages dropped,analytics down
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.14

Field Name : kafkaUnknownTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown type dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.13

Field Name : avroPartitionMetricsTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Part metrics dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.12

Field Name : avroPartitionMetricsTopicEnqueueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Part metrics dropped,enq error on acos queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.11

ACOS-EVENT-NOTIFICATION-STATS-MIB_acosEventNotification_oid_list

Field Name : avroDeviceStatusTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Device Status dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.10

Field Name : avroDeviceStatusTopicEnqueueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Device Status dropped,enq error on acos queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.9

Field Name : avroGenericFailedSending
Field Type : CounterBasedGauge64
Field Status : current
Description : Generic Metrics dropped,sending failure
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.8

Field Name : avroGenericFailedEncoding
Field Type : CounterBasedGauge64
Field Status : current
Description : Generic Metrics dropped,encoding error
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.7

Field Name : prAcosHarmonyTopicDequeueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR dropped,enq error analytics queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.6

Field Name : prAcosHarmonyTopicEnqueueErr
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 PR dropped,enq error on acos queues
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.5

Field Name : avroGenericSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Generic Metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.4

Field Name : avroPartitionMetricsTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : Partition Metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.3

Field Name : avroDeviceStatusTopic
Field Type : CounterBasedGauge64
Field Status : current
Description : Device Status Metrics sent
OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.2

Field Name : prAcosHarmonyTopic
Field Type : CounterBasedGauge64
Field Status : current

ACOS-EVENT-NOTIFICATION-STATS-MIB_acosEventNotification_oid_list

Description : L7 PR logs sent

OID : 1.3.6.1.4.1.22610.2.4.10.51.1.1.1.1

ACOS-FW-APP-MIB_oid_list

Field Name : appOperGroupListTable
Field Type : TABLE
Field Status : current
Description : ShowApplicationFirewallSupportedProtocols from object 'fw.app'
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3

Field Name : appOperTable
Field Type : TABLE
Field Status : current
Description : ShowApplicationFirewallSupportedProtocols from object 'fw.app'
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.2

Field Name : appOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The appOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.2.1

Field Name : appOperRelated
Field Type : String
Field Status : current
Description : related
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.2.1.4

Field Name : appOperContains
Field Type : String
Field Status : current
Description : contains
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.2.1.3

Field Name : appOperCategory
Field Type : String
Field Status : current
Description : category
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.2.1.2

Field Name : appOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.2.1.1

Field Name : appStatsTable
Field Type : TABLE
Field Status : current
Description : ShowApplicationFirewallSupportedProtocols from object 'fw.app'
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.1

Field Name : appStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The appStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.477.1.1.1

Field Name : appStatsDummy
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-APP-MIB_oid_list

Description : dummy

OID : 1.3.6.1.4.1.22610.2.4.8.477.1.1.1.2

Field Name : appStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.477.1.1.1.1

Field Name : appOperGroupListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The appOperGroupList entry:group-list

OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3.1

Field Name : appOperGroupListAppDesc

Field Type : String

Field Status : current

Description : app-desc

OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3.1.5

Field Name : appOperGroupListAppName

Field Type : String

Field Status : current

Description : app-name

OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3.1.4

Field Name : appOperGroupListCategoryName

Field Type : String

Field Status : current

Description : category-name

OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3.1.3

Field Name : appOperGroupListGroupListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3.1.2

Field Name : appOperGroupListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.477.1.3.1.1

ACOS-FW-DDOS-PROTECTION-MIB_oid_list

Field Name : ddosProtectionOperEntriesListTable
Field Type : TABLE
Field Status : current
Description : ConfigureFWDDoSProtection from object 'fw.ddos-protection'
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3

Field Name : ddosProtectionOperTable
Field Type : TABLE
Field Status : current
Description : ConfigureFWDDoSProtection from object 'fw.ddos-protection'
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2

Field Name : ddosProtectionOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ddosProtectionOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2.1

Field Name : ddosProtectionOperV6Prefix
Field Type : String
Field Status : current
Description : v6-prefix
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2.1.5

Field Name : ddosProtectionOperV4Netmask
Field Type : String
Field Status : current
Description : v4-netmask
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2.1.4

Field Name : ddosProtectionOperV4Address
Field Type : String
Field Status : current
Description : v4-address
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2.1.3

Field Name : ddosProtectionOperDetails
Field Type : Integer32
Field Status : current
Description : details
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2.1.2

Field Name : ddosProtectionOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.2.1.1

Field Name : ddosProtectionStatsTable
Field Type : TABLE
Field Status : current
Description : ConfigureFWDDoSProtection from object 'fw.ddos-protection'
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1

Field Name : ddosProtectionStatsEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-DDOS-PROTECTION-MIB_oid_list

Description : The ddosProtectionStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1

Field Name : ddosProtectionStatsDdosPacketDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_packet_dropped
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.9

Field Name : ddosProtectionStatsDdosEntryRemoveFromBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entry_remove_from_bgp_failure
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.8

Field Name : ddosProtectionStatsDdosEntryAddToBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entry_add_to_bgp_failure
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.7

Field Name : ddosProtectionStatsDdosEntryRemovedFromBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entry_removed_from_bgp
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.6

Field Name : ddosProtectionStatsDdosEntryAddedToBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entry_added_to_bgp
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.5

Field Name : ddosProtectionStatsDdosEntryRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entry_removed
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.4

Field Name : ddosProtectionStatsDdosEntryAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entry_added
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.3

Field Name : ddosProtectionStatsDdosEntriesTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos_entries_too_many
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.2

Field Name : ddosProtectionStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.1.1.1

ACOS-FW-DDOS-PROTECTION-MIB_oid_list

Field Name : ddosProtectionOperEntriesListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ddosProtectionOperEntriesList entry:entries-list
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1

Field Name : ddosProtectionOperEntriesListRate
Field Type : CounterBasedGauge64
Field Status : current
Description : rate
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.11

Field Name : ddosProtectionOperEntriesListLid
Field Type : CounterBasedGauge64
Field Status : current
Description : lid
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.10

Field Name : ddosProtectionOperEntriesListHash
Field Type : CounterBasedGauge64
Field Status : current
Description : hash
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.9

Field Name : ddosProtectionOperEntriesListHints
Field Type : String
Field Status : current
Description : hints
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.8

Field Name : ddosProtectionOperEntriesListExpiration
Field Type : CounterBasedGauge64
Field Status : current
Description : expiration
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.7

Field Name : ddosProtectionOperEntriesListPps
Field Type : CounterBasedGauge64
Field Status : current
Description : pps
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.6

Field Name : ddosProtectionOperEntriesListRuleName
Field Type : String
Field Status : current
Description : rule-name
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.5

Field Name : ddosProtectionOperEntriesListPrefix
Field Type : CounterBasedGauge64
Field Status : current
Description : prefix
OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.4

Field Name : ddosProtectionOperEntriesListIp
Field Type : String
Field Status : current

ACOS-FW-DDOS-PROTECTION-MIB_oid_list

Description : ip

OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.3

Field Name : ddosProtectionOperEntriesListEntriesListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.2

Field Name : ddosProtectionOperEntriesListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.491.1.3.1.1

ACOS-FW-FULL-CONE-SESSION-MIB_oid_list

Field Name : fullConeSessionOperSessionListTable
Field Type : TABLE
Field Status : current
Description : FullConeSessions from object 'fw.full-cone-session'
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3

Field Name : fullConeSessionOperTable
Field Type : TABLE
Field Status : current
Description : FullConeSessions from object 'fw.full-cone-session'
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.2

Field Name : fullConeSessionOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The fullConeSessionOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.2.1

Field Name : fullConeSessionOperIpv6Addr
Field Type : String
Field Status : current
Description : ipv6-addr
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.2.1.4

Field Name : fullConeSessionOperIpv4Addr
Field Type : String
Field Status : current
Description : ipv4-addr
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.2.1.3

Field Name : fullConeSessionOperTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : total
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.2.1.2

Field Name : fullConeSessionOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.2.1.1

Field Name : fullConeSessionOperSessionListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The fullConeSessionOperSessionList entry:session-list
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1

Field Name : fullConeSessionOperSessionListAge
Field Type : String
Field Status : current
Description : age
OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.9

Field Name : fullConeSessionOperSessionListCpu
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-FULL-CONE-SESSION-MIB_oid_list

Description : cpu

OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.8

Field Name : fullConeSessionOperSessionListInbound

Field Type : CounterBasedGauge64

Field Status : current

Description : inbound

OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.7

Field Name : fullConeSessionOperSessionListOutbound

Field Type : CounterBasedGauge64

Field Status : current

Description : outbound

OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.6

Field Name : fullConeSessionOperSessionListInsidePort

Field Type : CounterBasedGauge64

Field Status : current

Description : inside-port

OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.5

Field Name : fullConeSessionOperSessionListInsideAddress

Field Type : String

Field Status : current

Description : inside-address

OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.4

Field Name : fullConeSessionOperSessionListProtocol

Field Type : String

Field Status : current

Description : protocol

OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.3

Field Name : fullConeSessionOperSessionListSessionListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.2

Field Name : fullConeSessionOperSessionListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.485.1.3.1.1

ACOS-FW-LOGGING-MIB_oid_list

Field Name : loggingStatsTable
Field Type : TABLE
Field Status : current
Description : loggingConfigurationsE.g.FWLoggingTemplateBinding/CEFLogOptions from object
'fw.logging'
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1

Field Name : loggingStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The loggingStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1

Field Name : loggingStatsSessionLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : session-limit-exceeded
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.44

Field Name : loggingStatsIddosBlackholeEntryDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : iddos-blackhole-entry-delete
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.43

Field Name : loggingStatsIddosBlackholeEntryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : iddos-blackhole-entry-create
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.42

Field Name : loggingStatsTcpLoggingPortAllocationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-logging-port-allocation-failed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.41

Field Name : loggingStatsTcpLoggingPortFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-logging-port-freed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.40

Field Name : loggingStatsTcpLoggingPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-logging-port-allocated
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.39

Field Name : loggingStatsLogTypeSctpInnerProtoFilter
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_sctp_inner_proto_filter
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.38

Field Name : loggingStatsSctpSessionDeleted
Field Type : CounterBasedGauge64

ACOS-FW-LOGGING-MIB_oid_list

Field Status : current
Description : sctp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.37

Field Name : loggingStatsSctpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.36

Field Name : loggingStatsHttpAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : http-alloc-failed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.35

Field Name : loggingStatsHttpOutOfOrderDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : http-out-of-order-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.34

Field Name : loggingStatsLogMessageTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : log-message-too-long
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.33

Field Name : loggingStatsTcpLoggingConnDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-logging-conn-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.32

Field Name : loggingStatsTcpLoggingConnCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-logging-conn-create-failed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.31

Field Name : loggingStatsTcpLoggingConnEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-logging-conn-established
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.30

Field Name : loggingStatsAddMsgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : add-msg-failed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.29

Field Name : loggingStatsOutOfBuffers
Field Type : CounterBasedGauge64
Field Status : current
Description : out-of-buffers
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.28

ACOS-FW-LOGGING-MIB_oid_list

Field Name : loggingStatsIpv6FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-frag-failed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.27

Field Name : loggingStatsIpv6FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-frag-applied
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.26

Field Name : loggingStatsIpv4FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-frag-failed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.25

Field Name : loggingStatsIpv4FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-frag-applied
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.24

Field Name : loggingStatsTemplateError
Field Type : CounterBasedGauge64
Field Status : current
Description : template_error
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.23

Field Name : loggingStatsAlgOverridePermit
Field Type : CounterBasedGauge64
Field Status : current
Description : alg_override_permit
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.22

Field Name : loggingStatsDcmsgPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : dcmsg_permit
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.21

Field Name : loggingStatsHttpLoggingInvalidFormat
Field Type : CounterBasedGauge64
Field Status : current
Description : http-logging-invalid-format
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.20

Field Name : loggingStatsHttpRequestLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : http-request-logged
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.19

Field Name : loggingStatsOtherSessionCreated
Field Type : CounterBasedGauge64

ACOS-FW-LOGGING-MIB_oid_list

Field Status : current
Description : other-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.18

Field Name : loggingStatsOtherSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : other-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.17

Field Name : loggingStatsIcmpv6SessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.16

Field Name : loggingStatsIcmpv6SessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : icmpv6-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.15

Field Name : loggingStatsIcmpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.14

Field Name : loggingStatsIcmpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.13

Field Name : loggingStatsUdpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.12

Field Name : loggingStatsUdpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.11

Field Name : loggingStatsTcpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.10

Field Name : loggingStatsTcpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.9

ACOS-FW-LOGGING-MIB_oid_list

Field Name : loggingStatsLogDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : log-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.8

Field Name : loggingStatsRuleNotLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : rule_not_logged
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.7

Field Name : loggingStatsLogTypeSessionOpened
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_session_opened
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.6

Field Name : loggingStatsLogTypeSessionClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_session_closed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.5

Field Name : loggingStatsLogTypeDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_deny
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.4

Field Name : loggingStatsLogTypeReset
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_reset
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.3

Field Name : loggingStatsLogMessageSent
Field Type : CounterBasedGauge64
Field Status : current
Description : log_message_sent
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.2

Field Name : loggingStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.1.1.1

Field Name : gtpStatsTable
Field Type : TABLE
Field Status : current
Description : CountersForGTPLogging from object 'fw.logging.gtp'
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1

Field Name : gtpStatsEntry
Field Type : CounterBasedGauge64

ACOS-FW-LOGGING-MIB_oid_list

Field Status : current
Description : The gtpStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1

Field Name : gtpStatsLogTypeGtpInvalidPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_invalid_ports
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.27

Field Name : gtpStatsLogTypeGtpInvalidVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_invalid_version
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.26

Field Name : gtpStatsLogTypeGtpHdrInvalidPiggyFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_hdr_invalid_piggy_flag
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.25

Field Name : gtpStatsLogTypeGtpHdrInvalidSpareBits
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_hdr_invalid_spare_bits
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.24

Field Name : gtpStatsLogTypeGtpHdrInvalidProtocolFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_hdr_invalid_protocol_flag
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.23

Field Name : gtpStatsLogTypeGtpInvalidMessageLength
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_invalid_message_length
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.22

Field Name : gtpStatsLogTypeGtpRateLimitPeriodic
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_rate_limit_periodic
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.21

Field Name : gtpStatsLogTypeGtpSeqNumMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_seq_num_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.20

Field Name : gtpStatsLogTypeGtpNodeRestart
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_node_restart
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.19

ACOS-FW-LOGGING-MIB_oid_list

Field Name : gtpStatsLogTypeGtpInGtpFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_in_gtp_filtering
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.18

Field Name : gtpStatsLogTypeCountryCodeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_country_code_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.17

Field Name : gtpStatsLogTypeGtpRatTypeFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_rat_type_filtering
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.16

Field Name : gtpStatsLogTypeGtpApnFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_apn_filtering
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.15

Field Name : gtpStatsLogTypeGtpMessageFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_message_filtering
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.14

Field Name : gtpStatsLogTypeMaxMsgLength
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_max_msg_length
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.13

Field Name : gtpStatsLogTypeOutOfState
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_out_of_state
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.12

Field Name : gtpStatsLogTypeMessageNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_message_not_supported
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.11

Field Name : gtpStatsLogTypeCrosslayerCorrelation
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_crosslayer_correlation
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.10

Field Name : gtpStatsLogTypeEnduserIpSpoofed
Field Type : CounterBasedGauge64

ACOS-FW-LOGGING-MIB_oid_list

Field Status : current
Description : log_type_enduser_ip_spoofed
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.9

Field Name : gtpStatsLogTypeGtpOutOfStateIe
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_out_of_state_ie
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.8

Field Name : gtpStatsLogTypeGtpOutOfOrderIe
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_out_of_order_ie
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.7

Field Name : gtpStatsLogTypeGtpMsisdnFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_msisdn_filtering
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.6

Field Name : gtpStatsLogTypeGtpMandatoryIeInsideGroupedIeMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_mandatory_ie_inside_grouped_ie_missing
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.5

Field Name : gtpStatsLogTypeGtpMandatoryIeMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_mandatory_ie_missing
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.4

Field Name : gtpStatsLogGtpTypeReservedIePresent
Field Type : CounterBasedGauge64
Field Status : current
Description : log_gtp_type_reserved_ie_present
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.3

Field Name : gtpStatsLogTypeGtpInvalidTeid
Field Type : CounterBasedGauge64
Field Status : current
Description : log_type_gtp_invalid_teid
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.2

Field Name : gtpStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.480.1.2.1.1.1

ACOS-FW-OPER-MIB_acosFw_oid_list

Field Name : fwFullConeSessionSessionTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1

Field Name : fwFullConeSessionSessionEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1

Field Name : age
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.7

Field Name : cpu
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.6

Field Name : inbound
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.5

Field Name : outbound
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.4

Field Name : insidePort
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.3

Field Name : insideAddress
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.2

Field Name : protocol
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.16.1.1.1

Field Name : fwRateLimitRateLimitTable
Field Type : TABLE
Field Status : current

ACOS-FW-OPER-MIB_acosFw_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1

Field Name : totalEntriesScopeParentRadiusUserid

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.16

Field Name : totalEntriesScopeParentRadiusUsergroup

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.15

Field Name : totalEntriesScopeParentSubscriberPrefix

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.14

Field Name : totalEntriesScopeParentSubscriberIp

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.13

Field Name : totalEntriesScopeParent

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.12

Field Name : totalEntriesScopeRadiusUserid

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.11

Field Name : totalEntriesScopeRadiusUsergroup

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.10

Field Name : totalEntriesScopeSubscriberPrefix

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.9

Field Name : totalEntriesScopeSubscriberIp

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.8

ACOS-FW-OPER-MIB_acosFw_oid_list

Field Name : totalEntriesScopeAggregate
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.7

Field Name : totalNumEntriesFreed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.6

Field Name : totalNumEntriesAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.5

Field Name : totalNumEntries
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.4

Field Name : allocFailures
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.3

Field Name : memUsed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.2

Field Name : fwRateLimitRateLimitEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1

Field Name : memReserved
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1

Field Name : dropCount
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.15

Field Name : totalTrafficAllowed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-OPER-MIB_acosFw_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.14

Field Name : totalTrafficReceived

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.13

Field Name : downlinkTrafficAllowed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.12

Field Name : downlinkTrafficReceived

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.11

Field Name : uplinkTrafficAllowed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.10

Field Name : uplinkTrafficReceived

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.9

Field Name : cpsAllowed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.8

Field Name : cpsReceived

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.7

Field Name : type

Field Type : String

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.6

Field Name : templateId

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.5

ACOS-FW-OPER-MIB_acosFw_oid_list

Field Name : ruleName
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.4

Field Name : prefixLen
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.3

Field Name : address
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.2

Field Name : stringValue
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.30.1.1.1

Field Name : fwLimitEntryLimitEntryTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1

Field Name : fwLimitEntryLimitEntryEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1

Field Name : type
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.7

Field Name : maxCount
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.6

Field Name : currCount
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.5

Field Name : ruleName
Field Type : String
Field Status : current

ACOS-FW-OPER-MIB_acosFw_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.4

Field Name : stringValue

Field Type : String

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.3

Field Name : prefixLen

Field Type : INTEGER

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.2

Field Name : address

Field Type : String

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.20.1.1.1

Field Name : radiusEntriesFree

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.18.6

Field Name : radiusEntriesUsed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.18.5

Field Name : smpSessionsFree

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.18.4

Field Name : smpSessionsUsed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.18.3

Field Name : dataSessionsFree

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.18.2

Field Name : dataSessionsUsed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.139.18.1

ACOS-FW-RATE-LIMIT-MIB_oid_list

Field Name : rateLimitOperRateLimitListTable
Field Type : TABLE
Field Status : current
Description : ViewRateLimitEntries from object 'fw.rate-limit'
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3

Field Name : rateLimitOperRateLimitListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rateLimitOperRateLimitList entry:rate-limit-list
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1

Field Name : rateLimitOperRateLimitListDropCount
Field Type : CounterBasedGauge64
Field Status : current
Description : drop-count
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.16

Field Name : rateLimitOperRateLimitListTotalTrafficAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : total-traffic-allowed
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.15

Field Name : rateLimitOperRateLimitListTotalTrafficReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : total-traffic-received
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.14

Field Name : rateLimitOperRateLimitListDownlinkTrafficAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : downlink-traffic-allowed
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.13

Field Name : rateLimitOperRateLimitListDownlinkTrafficReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : downlink-traffic-received
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.12

Field Name : rateLimitOperRateLimitListUplinkTrafficAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : uplink-traffic-allowed
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.11

Field Name : rateLimitOperRateLimitListUplinkTrafficReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : uplink-traffic-received
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.10

Field Name : rateLimitOperRateLimitListCpsAllowed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-RATE-LIMIT-MIB_oid_list

Description : cps-allowed

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.9

Field Name : rateLimitOperRateLimitListCpsReceived

Field Type : CounterBasedGauge64

Field Status : current

Description : cps-received

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.8

Field Name : rateLimitOperRateLimitListType

Field Type : String

Field Status : current

Description : type

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.7

Field Name : rateLimitOperRateLimitListTemplateId

Field Type : CounterBasedGauge64

Field Status : current

Description : template-id

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.6

Field Name : rateLimitOperRateLimitListRuleName

Field Type : String

Field Status : current

Description : rule-name

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.5

Field Name : rateLimitOperRateLimitListPrefixLen

Field Type : CounterBasedGauge64

Field Status : current

Description : prefix-len

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.4

Field Name : rateLimitOperRateLimitListAddress

Field Type : String

Field Status : current

Description : address

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.3

Field Name : rateLimitOperRateLimitListStringValue

Field Type : String

Field Status : current

Description : string-value

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.17

Field Name : rateLimitOperRateLimitListRateLimitListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.2

Field Name : rateLimitOperRateLimitListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.3.1.1

ACOS-FW-RATE-LIMIT-MIB_oid_list

Field Name : rateLimitOperTable
Field Type : TABLE
Field Status : current
Description : ViewRateLimitEntries from object 'fw.rate-limit'
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2

Field Name : rateLimitOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rateLimitOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1

Field Name : rateLimitOperTemplateId
Field Type : CounterBasedGauge64
Field Status : current
Description : template-id
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1.5

Field Name : rateLimitOperStringValue
Field Type : String
Field Status : current
Description : string-value
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1.6

Field Name : rateLimitOperV6Prefix
Field Type : String
Field Status : current
Description : v6-prefix
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1.4

Field Name : rateLimitOperV4Netmask
Field Type : String
Field Status : current
Description : v4-netmask
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1.3

Field Name : rateLimitOperV4Address
Field Type : String
Field Status : current
Description : v4-address
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1.2

Field Name : rateLimitOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.2.1.1

Field Name : rateLimitStatsTable
Field Type : TABLE
Field Status : current
Description : ViewRateLimitEntries from object 'fw.rate-limit'
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1

Field Name : rateLimitStatsEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-RATE-LIMIT-MIB_oid_list

Description : The rateLimitStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1

Field Name : rateLimitStatsRatelimitEntryCountParentRadiusUserid

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_entry_count_parent_radius_userid

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.29

Field Name : rateLimitStatsRatelimitEntryCountRadiusUserid

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_entry_count_radius_userid

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.28

Field Name : rateLimitStatsRatelimitEntryCountParentRadiusUsergroup

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_entry_count_parent_radius_usergroup

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.27

Field Name : rateLimitStatsRatelimitEntryCountRadiusUsergroup

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_entry_count_radius_usergroup

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.26

Field Name : rateLimitStatsRatelimitEntryCountParentIp

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_entry_count_parent_ip

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.25

Field Name : rateLimitStatsRatelimitEntryCountRuleIp

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_entry_count_rule_ip

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.24

Field Name : rateLimitStatsRatelimitEntryCountFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_entry_count_freed

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.23

Field Name : rateLimitStatsRatelimitEntryCountAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_entry_count_allocated

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.22

Field Name : rateLimitStatsRatelimitInfraGenericErrors

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_infra_generic_errors

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.21

ACOS-FW-RATE-LIMIT-MIB_oid_list

Field Name : rateLimitStatsRatelimitEntryCountParentIpv6Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_parent_ipv6_prefix
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.20

Field Name : rateLimitStatsRatelimitEntryCountParentIpv4Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_parent_ipv4_prefix
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.19

Field Name : rateLimitStatsRatelimitEntryCountParentUid
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_parent_uid
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.18

Field Name : rateLimitStatsRatelimitEntryCountRuleIpv6Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_rule_ipv6_prefix
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.17

Field Name : rateLimitStatsRatelimitEntryCountRuleIpv4Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_rule_ipv4_prefix
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.16

Field Name : rateLimitStatsRatelimitEntryCountSessionId
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_session_id
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.15

Field Name : rateLimitStatsRatelimitEntryCountIp6Addr
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_ip6_addr
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.14

Field Name : rateLimitStatsRatelimitEntryCountIpAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_ip_addr
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.13

Field Name : rateLimitStatsRatelimitEntryCountFwRuleUid
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimit_entry_count_fw_rule_uid
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.12

Field Name : rateLimitStatsRatelimitEntryCountT2Key
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-RATE-LIMIT-MIB_oid_list

Description : ratelimit_entry_count_t2_key

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.11

Field Name : rateLimitStatsRatelimitEntryAllocFailMetricCountGtSupported

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_entry_alloc_fail_metric_count_gt_supported

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.10

Field Name : rateLimitStatsRatelimitEntryAllocFailRateTooHigh

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_entry_alloc_fail_rate_too_high

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.9

Field Name : rateLimitStatsRatelimitHighPerfEntrySecondaryAllocFail

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_high_perf_entry_secondary_alloc_fail

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.8

Field Name : rateLimitStatsRatelimitHighPerfEntryAllocFail

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_high_perf_entry_alloc_fail

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.7

Field Name : rateLimitStatsRatelimitHighAccurateEntryAllocFail

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_high_accurate_entry_alloc_fail

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.6

Field Name : rateLimitStatsRatelimitEntryAllocFrmSpmMem

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_entry_alloc_frm_spm_mem

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.5

Field Name : rateLimitStatsRatelimitUsedHeapMem

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_used_heap_mem

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.4

Field Name : rateLimitStatsRatelimitUsedSpmMem

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_used_spm_mem

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.3

Field Name : rateLimitStatsRatelimitUsedTotalMem

Field Type : CounterBasedGauge64

Field Status : current

Description : ratelimit_used_total_mem

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.2

ACOS-FW-RATE-LIMIT-MIB_oid_list

Field Name : rateLimitStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.1.1.1

Field Name : summaryOperTable

Field Type : TABLE

Field Status : current

Description : ViewASummaryAboutRatelimitEntries from object 'fw.rate-limit.summary'

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2

Field Name : summaryOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The summaryOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1

Field Name : summaryOperTotalEntriesScopeParentRadiusUserid

Field Type : CounterBasedGauge64

Field Status : current

Description : total_entries_scope_parent_radius_userid

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.17

Field Name : summaryOperTotalEntriesScopeParentRadiusUsergroup

Field Type : CounterBasedGauge64

Field Status : current

Description : total_entries_scope_parent_radius_usergroup

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.16

Field Name : summaryOperTotalEntriesScopeParentSubscriberPrefix

Field Type : CounterBasedGauge64

Field Status : current

Description : total_entries_scope_parent_subscriber-prefix

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.13

Field Name : summaryOperTotalEntriesScopeParentSubscriberIp

Field Type : CounterBasedGauge64

Field Status : current

Description : total_entries_scope_parent_subscriber_ip

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.12

Field Name : summaryOperTotalEntriesScopeParent

Field Type : CounterBasedGauge64

Field Status : current

Description : total_entries_scope_parent

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.11

Field Name : summaryOperTotalEntriesScopeRadiusUserid

Field Type : CounterBasedGauge64

Field Status : current

Description : total_entries_scope_radius_userid

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.15

Field Name : summaryOperTotalEntriesScopeRadiusUsergroup

Field Type : CounterBasedGauge64

Field Status : current

ACOS-FW-RATE-LIMIT-MIB_oid_list

Description : total_entries_scope_radius_usergroup
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.14

Field Name : summaryOperTotalEntriesScopeSubscriberPrefix
Field Type : CounterBasedGauge64
Field Status : current
Description : total_entries_scope_subscriber_prefix
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.10

Field Name : summaryOperTotalEntriesScopeSubscriberIp
Field Type : CounterBasedGauge64
Field Status : current
Description : total_entries_scope_subscriber_ip
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.9

Field Name : summaryOperTotalEntriesScopeAggregate
Field Type : CounterBasedGauge64
Field Status : current
Description : total_entries_scope_aggregate
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.8

Field Name : summaryOperTotalNumEntriesFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : total_num_entries_freed
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.7

Field Name : summaryOperTotalNumEntriesAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : total_num_entries_allocated
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.6

Field Name : summaryOperTotalNumEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : total_num_entries
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.5

Field Name : summaryOperAllocFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failures
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.4

Field Name : summaryOperMemUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : mem_used
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.3

Field Name : summaryOperMemReserved
Field Type : CounterBasedGauge64
Field Status : current
Description : mem_reserved
OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.2

ACOS-FW-RATE-LIMIT-MIB_oid_list

Field Name : summaryOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.483.1.4.2.1.1

ACOS-FW-RESOURCE-USAGE-MIB_oid_list

Field Name : resourceUsageOperTable
Field Type : TABLE
Field Status : current
Description : FirewallResourceUsage from object 'fw.resource-usage'
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2

Field Name : resourceUsageOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The resourceUsageOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1

Field Name : resourceUsageOperClausePerObjGrp
Field Type : Integer32
Field Status : current
Description : clause-per-obj-grp
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.28

Field Name : resourceUsageOperRadiusTableSize
Field Type : TABLE
Field Status : current
Description : radius-table-size
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.27

Field Name : resourceUsageOperHelperSessions
Field Type : Integer32
Field Status : current
Description : helper-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.26

Field Name : resourceUsageOperIpRange
Field Type : Integer32
Field Status : current
Description : ip-range
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.25

Field Name : resourceUsageOperZone
Field Type : Integer32
Field Status : current
Description : zone
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.24

Field Name : resourceUsageOperRule
Field Type : Integer32
Field Status : current
Description : rule
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.23

Field Name : resourceUsageOperRuleSet
Field Type : Integer32
Field Status : current
Description : rule-set
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.22

Field Name : resourceUsageOperObjectGroup
Field Type : Integer32
Field Status : current

ACOS-FW-RESOURCE-USAGE-MIB_oid_list

Description : object-group

OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.21

Field Name : resourceUsageOperObject

Field Type : Integer32

Field Status : current

Description : object

OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.20

Field Name : resourceUsageOperClausePerObjGrpTotalCount

Field Type : CounterBasedGauge64

Field Status : current

Description : clause-per-obj-grp-total-count

OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.19

Field Name : resourceUsageOperClausePerObjGrpCurrentCount

Field Type : String

Field Status : current

Description : clause-per-obj-grp-current-count

OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.18

Field Name : resourceUsageOperRadiusTableTotalCount

Field Type : TABLE

Field Status : current

Description : radius-table-total-count

OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.17

Field Name : resourceUsageOperRadiusTableCurrentCount

Field Type : TABLE

Field Status : current

Description : radius-table-current-count

OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.16

Field Name : resourceUsageOperFwHelperSessionsTotalCount

Field Type : CounterBasedGauge64

Field Status : current

Description : fw-helper-sessions-total-count

OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.15

Field Name : resourceUsageOperFwHelperSessionsCurrentCount

Field Type : CounterBasedGauge64

Field Status : current

Description : fw-helper-sessions-current-count

OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.14

Field Name : resourceUsageOperFwIpRangeTotalCount

Field Type : CounterBasedGauge64

Field Status : current

Description : fw-ip-range-total-count

OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.13

Field Name : resourceUsageOperFwIpRangeCurrentCount

Field Type : CounterBasedGauge64

Field Status : current

Description : fw-ip-range-current-count

OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.12

ACOS-FW-RESOURCE-USAGE-MIB_oid_list

Field Name : resourceUsageOperFwZoneTotalCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-zone-total-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.11

Field Name : resourceUsageOperFwZoneCurrentCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-zone-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.10

Field Name : resourceUsageOperFwRuleTotalCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-rule-total-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.9

Field Name : resourceUsageOperFwRuleCurrentCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-rule-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.8

Field Name : resourceUsageOperFwRuleSetTotalCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-rule-set-total-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.7

Field Name : resourceUsageOperFwRuleSetCurrentCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-rule-set-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.6

Field Name : resourceUsageOperFwObjectGroupTotalCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-object-group-total-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.5

Field Name : resourceUsageOperFwObjectGroupCurrentCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-object-group-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.4

Field Name : resourceUsageOperFwObjectTotalCount
Field Type : CounterBasedGauge64
Field Status : current
Description : fw-object-total-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.3

Field Name : resourceUsageOperFwObjectCurrentCount
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-RESOURCE-USAGE-MIB_oid_list

Description : fw-object-current-count
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.2

Field Name : resourceUsageOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.489.1.2.1.1

ACOS-FW-SERVER-MIB_oid_list

Field Name : serverOperTable
Field Type : TABLE
Field Status : current
Description : FirewallLoggingServer from object 'fw.server'
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.2

Field Name : serverOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serverOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.2.1

Field Name : serverOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.2.1.3

Field Name : serverOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.2.1.2

Field Name : serverOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.2.1.1

Field Name : serverStatsTable
Field Type : TABLE
Field Status : current
Description : FirewallLoggingServer from object 'fw.server'
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1

Field Name : serverStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serverStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1

Field Name : serverStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.7

Field Name : serverStatsRevPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : rev-pkt
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.6

Field Name : serverStatsFwdPkt
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-SERVER-MIB_oid_list

Description : fwd-pkt

OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.5

Field Name : serverStatsTotalConn

Field Type : CounterBasedGauge64

Field Status : current

Description : total-conn

OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.4

Field Name : serverStatsCurrConn

Field Type : CounterBasedGauge64

Field Status : current

Description : curr-conn

OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.3

Field Name : serverStatsName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.2

Field Name : serverStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.478.1.1.1.1

Field Name : portOperTable

Field Type : TABLE

Field Status : current

Description : RealServerPort from object 'fw.server.port'

OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2

Field Name : portStatsTable

Field Type : TABLE

Field Status : current

Description : RealServerPort from object 'fw.server.port'

OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1

Field Name : portStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The portStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1

Field Name : portStatsSlowestRspTime

Field Type : CounterBasedGauge64

Field Status : current

Description : slowest_rsp_time

OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.28

Field Name : portStatsFastestRspTime

Field Type : CounterBasedGauge64

Field Status : current

Description : fastest_rsp_time

OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.27

ACOS-FW-SERVER-MIB_oid_list

Field Name : portStatsResponseTime
Field Type : CounterBasedGauge64
Field Status : current
Description : response_time
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.26

Field Name : portStatsTotalRevPktsInspectedGoodStatusCode
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected_good_status_code
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.25

Field Name : portStatsTotalRevPktsInspected
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.24

Field Name : portStatsEsRespInvalidHttp
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_invalid_http
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.23

Field Name : portStatsEsRespCount
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_count
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.22

Field Name : portStatsEsReqCount
Field Type : CounterBasedGauge64
Field Status : current
Description : es_req_count
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.21

Field Name : portStatsEsRespOther
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_other
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.20

Field Name : portStatsEsResp500
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_500
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.19

Field Name : portStatsEsResp400
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_400
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.18

Field Name : portStatsEsResp300
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-SERVER-MIB_oid_list

Description : es_resp_300
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.17

Field Name : portStatsEsResp200
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_200
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.16

Field Name : portStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.15

Field Name : portStatsLastTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : last_total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.14

Field Name : portStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.13

Field Name : portStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.12

Field Name : portStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.11

Field Name : portStatsTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.10

Field Name : portStatsTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.9

Field Name : portStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.8

ACOS-FW-SERVER-MIB_oid_list

Field Name : portStatsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.7

Field Name : portStatsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_req
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.6

Field Name : portStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.5

Field Name : portStatsProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.4

Field Name : portStatsPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.3

Field Name : portStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.2

Field Name : portStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.1.1.1

Field Name : portOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1

Field Name : portOperAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.13

Field Name : portOperPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-SERVER-MIB_oid_list

Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.12

Field Name : portOperPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.11

Field Name : portOperPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.10

Field Name : portOperHaGroupId
Field Type : CounterBasedGauge64
Field Status : current
Description : ha_group_id
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.9

Field Name : portOperVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.8

Field Name : portOperIpv6
Field Type : String
Field Status : current
Description : ipv6
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.7

Field Name : portOperIp
Field Type : String
Field Status : current
Description : ip
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.6

Field Name : portOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.5

Field Name : portOperProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.4

Field Name : portOperPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.3

ACOS-FW-SERVER-MIB_oid_list

Field Name : portOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.2

Field Name : portOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.478.1.3.2.1.1

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : tcamCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flow Count
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.20

Field Name : tcamFree
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flows Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.19

Field Name : tcamCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Flows Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.18

Field Name : entryInvalidateServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Invalidate due to server down
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.17

Field Name : entryForceHwInvalidate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Force HW Invalidate
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.16

Field Name : entryAgeOutInvalidDst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - invalid dst
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.15

Field Name : entryAgeOutTcpRst
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP RST
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.14

Field Name : entryAgeOutTcpFin
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - TCP FIN
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.13

Field Name : entryAgeOutIdle
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Aged Out - idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.12

Field Name : entryAgeOut
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : HW Entries Aged Out

OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.11

Field Name : entryCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entries Count

OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.10

Field Name : entryFreeNoSwEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entry Freed - no software entry

OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.9

Field Name : entryFreeNoConn

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entry Freed - no matched conn

OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.8

Field Name : entryFreeNoHwProg

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entry Freed - no HW prog

OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.7

Field Name : entryFreeOppEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entries Freed - opposite tuple entry aged-out

OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.6

Field Name : entryFree

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entries Freed

OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.5

Field Name : entryCreateFailMaxEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entry Creation Failed - max entries exceeded

OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.4

Field Name : entryCreateFailServerDown

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entry Creation Failed - server down

OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.3

Field Name : entryCreateFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : HW Entry Creation Failed

OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.2

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : entryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.35.1.1

Field Name : ddosPacketDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS Packet Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.8

Field Name : ddosEntryRemoveFromBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS entry BGP remove failures
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.7

Field Name : ddosEntryAddToBgpFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : DDoS Entry BGP add failures
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.6

Field Name : ddosEntryRemovedFromBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : DDoS Entry Removed from BGP
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.5

Field Name : ddosEntryAddedToBgp
Field Type : CounterBasedGauge64
Field Status : current
Description : DDoS Entry added to BGP
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.4

Field Name : ddosEntryRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS entry removed
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.3

Field Name : ddosEntryAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : DDOS entry added
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.2

Field Name : ddosEntriesTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : Too many DDOS entries
OID : 1.3.6.1.4.1.22610.2.4.10.139.31.1.1

Field Name : connSetupFailed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : SYN cookie connection setup failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.19.3.1.4

Field Name : verificationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie verification failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.19.3.1.3

Field Name : verificationPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie verification passed
OID : 1.3.6.1.4.1.22610.2.4.10.139.19.3.1.2

Field Name : synAckSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN cookie SYN ACK sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.19.3.1.1

Field Name : radiusInterCardDupRedir
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packet dropped as redirected by other blade (S0)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.44

Field Name : radiusPacketsDroppedNotLo
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets dropped dest not loopback (S0)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.43

Field Name : radiusPacketsProcessLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets processed locally without redirection (S0)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.42

Field Name : radiusPacketsRedirectFailDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets dropped due to redirect failure (S0)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.41

Field Name : radiusPacketsRedirected
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS packets redirected (S0)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.40

Field Name : interCardMsgFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Inter-Card Message Fail Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.39

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : haSyncNoKeyVapDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync No key dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.38

Field Name : ipAddRaceDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Entry IP Add Race Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.37

Field Name : ipMismatchDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Entry IP Mismatch Delete
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.36

Field Name : acctOnDupRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate RADIUS Acct On Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.35

Field Name : acctOnFiltersFull
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Acct On Request Ignored(Filters Full)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.34

Field Name : haSyncDeleteRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Delete Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.33

Field Name : haSyncCreateRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Create Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.32

Field Name : haSyncDeleteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Delete Sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.31

Field Name : haSyncCreateSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Create Sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.30

Field Name : memFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : RADIUS Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.29

Field Name : memAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.28

Field Name : memAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.27

Field Name : smpDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.26

Field Name : smpInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP in RML
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.25

Field Name : smpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.24

Field Name : smpMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.23

Field Name : smpMemAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.22

Field Name : smpMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS SMP Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.21

Field Name : invalidKey
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Request has Invalid Key Field
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.15

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : ipv6PrefixLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Framed IPV6 Prefix Length Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.14

Field Name : haStandbyDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.13

Field Name : secretNotConfiguredDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Secret Not Configured Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.12

Field Name : radiusTableFull
Field Type : TABLE
Field Status : current
Description : RADIUS Request Dropped (Table Full)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.11

Field Name : requestIgnored
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Table Full Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.10

Field Name : requestMalformedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Malformed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.9

Field Name : requestNoKeyVapDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request No Key Attribute Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.8

Field Name : requestBadSecretDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Bad Secret Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.7

Field Name : radiusRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Dropped (Malformed Packet)
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.6

Field Name : radiusRequestReceived
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : RADIUS Request Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.5

Field Name : customReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom attribute Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.4

Field Name : imsiReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : IMSI Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.3

Field Name : imeiReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : IMEI Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.2

Field Name : msisdNReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : MSISDN Received
OID : 1.3.6.1.4.1.22610.2.4.10.139.17.1.1.1

Field Name : outsideWindow
Field Type : CounterBasedGauge64
Field Status : current
Description : packet dropped counter for outside of tcp window
OID : 1.3.6.1.4.1.22610.2.4.10.139.12.1.1

Field Name : helperFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.40

Field Name : sipHelperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.39

Field Name : sipHelperDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Already Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.38

Field Name : sipHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.37

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : helperFound
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Found
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.36

Field Name : rtpEim
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP EIM
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.35

Field Name : rtpAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.34

Field Name : rtpNew
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.33

Field Name : contactEimSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact EIM Set
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.32

Field Name : contactEim
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact EIM
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.31

Field Name : contactAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.30

Field Name : contactNew
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.29

Field Name : contactPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.28

Field Name : contactPortSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Contact Port Success
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.27

Field Name : contactPortNoOp
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Port No Op
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.26

Field Name : rtcpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RTCP Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.25

Field Name : rtpPortFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Port Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.24

Field Name : rtpRtcpPortSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP RTCP Port Success
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.23

Field Name : rtpPortNoOp
Field Type : CounterBasedGauge64
Field Status : current
Description : RTP Port No Op
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.22

Field Name : sdpError
Field Type : CounterBasedGauge64
Field Status : current
Description : SDP Process Error
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.21

Field Name : contactError
Field Type : CounterBasedGauge64
Field Status : current
Description : Contact Process Error
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.20

Field Name : keepAlive
Field Type : CounterBasedGauge64
Field Status : current
Description : Keep Alive
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.19

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Message Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.18

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : methodUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Method Unknown
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.17

Field Name : methodUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : Method UPDATE
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.16

Field Name : methodMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : Method MESSAGE
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.15

Field Name : methodRefer
Field Type : CounterBasedGauge64
Field Status : current
Description : Method REFER
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.14

Field Name : methodInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Method INFO
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.13

Field Name : methodPublish
Field Type : CounterBasedGauge64
Field Status : current
Description : Method PUBLISH
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.12

Field Name : methodNotify
Field Type : CounterBasedGauge64
Field Status : current
Description : Method NOTIFY
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.11

Field Name : methodSubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description : Method SUBSCRIBE
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.10

Field Name : methodPrack
Field Type : CounterBasedGauge64
Field Status : current
Description : Method PRACK
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.9

Field Name : methodOptions
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Method OPTIONS

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.8

Field Name : methodBye

Field Type : CounterBasedGauge64

Field Status : current

Description : Method BYE

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.7

Field Name : methodCancel

Field Type : CounterBasedGauge64

Field Status : current

Description : Method CANCEL

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.6

Field Name : methodAck

Field Type : CounterBasedGauge64

Field Status : current

Description : Method ACK

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.5

Field Name : methodInvite

Field Type : CounterBasedGauge64

Field Status : current

Description : Method INVITE

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.4

Field Name : methodRegister

Field Type : CounterBasedGauge64

Field Status : current

Description : Method REGISTER

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.3

Field Name : statResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : Response Received

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.2

Field Name : statRequest

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Received

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.6.1.1

Field Name : controlFreeSmpAppTypeMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : Control Free SMP App Type Mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.29

Field Name : controlFreeNoSmp

Field Type : CounterBasedGauge64

Field Status : current

Description : Control Free No SMP

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.28

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : controlFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.27

Field Name : controlFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.26

Field Name : greFreeSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.25

Field Name : greFreeNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free No SMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.24

Field Name : greFreeNoExt
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Free No Ext
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.23

Field Name : greConnAlreadyExists
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Already Exists
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.22

Field Name : greNoControlConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Control Conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.21

Field Name : greNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Rev Route
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.20

Field Name : greNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE No Fwd Route
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.19

Field Name : greConnExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GRE Conn Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.18

Field Name : greConnCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.17

Field Name : smpAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.16

Field Name : smpSessionsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.15

Field Name : smpSessionsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.14

Field Name : smpClientCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Client Call ID Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.13

Field Name : smpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.12

Field Name : callReplyExtExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.11

Field Name : callReplyRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.10

Field Name : callReplyCallIdUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Reply Unknown Client Call ID
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.9

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : callReqExtAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Ext Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.8

Field Name : callReqNew
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request New
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.7

Field Name : callReqRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Call Request Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.6

Field Name : greSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.5

Field Name : greSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.4

Field Name : callReplyPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Reply
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.3

Field Name : callReqPnsCallIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Call ID Mismatch on Call Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.2

Field Name : callsEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : Calls Established
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.5.1.1

Field Name : haDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.35

Field Name : haControlSessionCreated
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : HA Control Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.34

Field Name : haControlExtCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Control Extension Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.33

Field Name : rstpDataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.32

Field Name : rstpDataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.31

Field Name : transportNotFoundOnDataFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Not Found Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.30

Field Name : transportRetryLookupOnDataFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Retry Lookup Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.29

Field Name : transportDoubleReleaseFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Double Release Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.28

Field Name : transportReleasedFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Released Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.27

Field Name : transportAcquireFailureFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquire Failure Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.26

Field Name : transportAcquiredFromData
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquired Data
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.25

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : transportDoubleReleaseFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Double Release Control
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.24

Field Name : transportReleasedFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Released Control
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.23

Field Name : transportAcquireFailureFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquire Failure Control
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.22

Field Name : transportFoundFromPrevControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Found From Prev Control
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.21

Field Name : transportAcquiredFromControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Acquired Control
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.20

Field Name : transportFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Freed Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.19

Field Name : transportPutInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Put in Delete Queue
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.18

Field Name : transportAllocFailureShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Alloc Failure Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.17

Field Name : transportCreationRace
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Create Race
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.16

Field Name : transportInsertedShadow
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Transport Inserted Shadow

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.15

Field Name : transportLinkExtFailureData

Field Type : CounterBasedGauge64

Field Status : current

Description : Transport Link to Extension Failure Data

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.14

Field Name : transportLinkExtData

Field Type : CounterBasedGauge64

Field Status : current

Description : Transport Link to Extension Data

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.13

Field Name : transportLinkExtFailureControl

Field Type : CounterBasedGauge64

Field Status : current

Description : Transport Link to Extension Failure Control

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.12

Field Name : transportExists

Field Type : CounterBasedGauge64

Field Status : current

Description : Transport Already Exists

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.11

Field Name : transportAlreadyInExt

Field Type : CounterBasedGauge64

Field Status : current

Description : Transport Already in Extension

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.10

Field Name : transportTooMany

Field Type : CounterBasedGauge64

Field Status : current

Description : Too Many Transports for Control Conn

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.9

Field Name : transportRemovedFromExt

Field Type : CounterBasedGauge64

Field Status : current

Description : Transport Removed from Extension

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.8

Field Name : transportAddToExt

Field Type : CounterBasedGauge64

Field Status : current

Description : Transport Added to Extension

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.7

Field Name : extCreationFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Extension Creation Failure

OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.6

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : cgnv6StatefullFireWallAlgRtspDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.5

Field Name : cgnv6StatefullFireWallAlgRtspDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.4

Field Name : transportAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.3

Field Name : transportFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.2

Field Name : transportInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Transport Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.4.1.1

Field Name : helperInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session in Remove List
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.7

Field Name : helperAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Session already used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.6

Field Name : helperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.5

Field Name : helperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions freed used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.4

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : TFTP Helper Sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.3

Field Name : helperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Helper Sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.2

Field Name : sessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TFTP Client Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.3.1.1

Field Name : pasvHelperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Freed Unused
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.19

Field Name : pasvHelperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Freed Used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.18

Field Name : portHelperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Freed Unused
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.17

Field Name : portHelperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Freed Used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.16

Field Name : pasvHelperAcquireAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Acquire Already Used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.15

Field Name : pasvHelperAcquireInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Acquire In Del Queue
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.14

Field Name : portHelperAcquireAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Acquire Already Used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.13

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : portHelperAcquireInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Acquire In Del Queue
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.12

Field Name : pasvHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.11

Field Name : portHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.10

Field Name : smpConnAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP Helper Conn Alloc Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.9

Field Name : retransmitSanityCheckFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Retransmit Sanity Check Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.8

Field Name : ftpSmpAppTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SMP App Type Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.7

Field Name : pasvRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.6

Field Name : portRetransmits
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.5

Field Name : serverEpsvReply
Field Type : CounterBasedGauge64
Field Status : current
Description : EPSV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.4

Field Name : serverPasvReply
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : PASV Replies From Server
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.3

Field Name : clientEprtRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : EPRT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.2

Field Name : clientPortRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT Requests From Client
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.2.1.1

Field Name : helperInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Helper Session in Remove List
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.7

Field Name : helperAlreadyUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Helper Session already used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.6

Field Name : helperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Helper Sessions freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.5

Field Name : helperFreedUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Helper Sessions freed used
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.4

Field Name : helperFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Helper Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.3

Field Name : helperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Helper Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.2

Field Name : sessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ESP Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.9.9.1.1

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : ratelimitEntryCountParentRadiusUserid
Field Type : CounterBasedGauge64
Field Status : current
Description : The total number of parent rate-limiting entries with the scope RADIUS user ID.
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.28

Field Name : ratelimitEntryCountRadiusUserid
Field Type : CounterBasedGauge64
Field Status : current
Description : The total number of rate-limiting entries with the scope RADIUS user ID.
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.27

Field Name : ratelimitEntryCountParentRadiusUsergroup
Field Type : CounterBasedGauge64
Field Status : current
Description : The total number of parent rate-limiting entries with the scope RADIUS user group.
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.26

Field Name : ratelimitEntryCountRadiusUsergroup
Field Type : CounterBasedGauge64
Field Status : current
Description : The total number of rate-limiting entries with the scope RADIUS user group.
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.25

Field Name : ratelimitEntryCountParentIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Parent Rate-limit Entries with Scope IP
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.24

Field Name : ratelimitEntryCountRuleIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries with Scope IP
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.23

Field Name : ratelimitEntryCountFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries Freed Totally
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.22

Field Name : ratelimitEntryCountAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries Allocated Totally
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.21

Field Name : ratelimitInfraGenericErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Number of Generic Errors Encountered in Ratelimit Infra
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.20

Field Name : ratelimitEntryCountParentIpv6Prefix

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Parent Rate-limit Entries with Scope IPv6 Prefix
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.19

Field Name : ratelimitEntryCountParentIpv4Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Parent Rate-limit Entries with Scope IPv4 Prefix
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.18

Field Name : ratelimitEntryCountParentUid
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Parent Rate-limit Entries with Scope Aggregate
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.17

Field Name : ratelimitEntryCountRuleIpv6Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries with Scope IPv6 Prefix
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.16

Field Name : ratelimitEntryCountRuleIpv4Prefix
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries with Scope IPv4 Prefix
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.15

Field Name : ratelimitEntryCountSessionId
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries with Scope Session ID
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.14

Field Name : ratelimitEntryCountIp6Addr
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries with Scope IPv6 Address
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.13

Field Name : ratelimitEntryCountIpAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries with Scope IPv4 Address
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.12

Field Name : ratelimitEntryCountFwRuleUid
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Rate-limit Entries with Scope Aggregate
OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.11

Field Name : ratelimitEntryCountT2Key
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Total Rate-limit Entries

ACOS-FW-STATS-MIB_acosFw_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.10

Field Name : ratelimitEntryAllocFailMetricCountGtSupported

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Number of Failures to Create High-Perf Rate-limit Entries Because
of Too Many Metrics

OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.9

Field Name : ratelimitEntryAllocFailRateTooHigh

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Number of Attempts to Configure Too High Rate Limits

OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.8

Field Name : ratelimitHighPerfEntrySecondaryAllocFail

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Number of Failures to Allocate Additional Memory to Existing High-Perf
Rate-limit Entries

OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.7

Field Name : ratelimitHighPerfEntryAllocFail

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Number of Failures to Create High-Perf Rate-limit Entries Due to
Memory Allocation Failures

OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.6

Field Name : ratelimitHighAccurateEntryAllocFail

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Number of Failures to Create Highly Accurate Rate-limit Entries Due
to Memory Allocation Failures

OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.5

Field Name : ratelimitEntryAllocFrmSpmMem

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Number of Rate-limit Entries created using SPM Memory

OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.4

Field Name : ratelimitUsedHeapMem

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Heap Memory Used For Rate-limiting Infra in Bytes

OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.3

Field Name : ratelimitUsedSpmMem

Field Type : CounterBasedGauge64

Field Status : current

Description : Total SPM Memory Used For Rate-limiting Infra in Bytes

OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.2

Field Name : ratelimitUsedTotalMem

Field Type : CounterBasedGauge64

Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Total Memory Used For Rate-limiting (bytes)

OID : 1.3.6.1.4.1.22610.2.4.10.139.30.1.1

Field Name : revEgressPktSizeRange4

Field Type : CounterBasedGauge64

Field Status : current

Description : Reverse Egress Packet size between 1551 and 9000

OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.94

Field Name : revEgressPktSizeRange3

Field Type : CounterBasedGauge64

Field Status : current

Description : Reverse Egress Packet size between 801 and 1550

OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.93

Field Name : revEgressPktSizeRange2

Field Type : CounterBasedGauge64

Field Status : current

Description : Reverse Egress Packet size between 201 and 800

OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.92

Field Name : revEgressPktSizeRange1

Field Type : CounterBasedGauge64

Field Status : current

Description : Reverse Egress Packet size between 0 and 200

OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.91

Field Name : revIngressPktSizeRange4

Field Type : CounterBasedGauge64

Field Status : current

Description : Reverse Ingress Packet size between 1551 and 9000

OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.90

Field Name : revIngressPktSizeRange3

Field Type : CounterBasedGauge64

Field Status : current

Description : Reverse Ingress Packet size between 801 and 1550

OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.89

Field Name : revIngressPktSizeRange2

Field Type : CounterBasedGauge64

Field Status : current

Description : Reverse Ingress Packet size between 201 and 800

OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.88

Field Name : revIngressPktSizeRange1

Field Type : CounterBasedGauge64

Field Status : current

Description : Reverse Ingress Packet size between 0 and 200

OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.87

Field Name : fwdEgressPktSizeRange4

Field Type : CounterBasedGauge64

Field Status : current

Description : Forward Egress Packet size between 1551 and 9000

OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.86

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : fwdEgressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.85

Field Name : fwdEgressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.84

Field Name : fwdEgressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.83

Field Name : fwdIngressPktSizeRange4
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 1551 and 9000
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.82

Field Name : fwdIngressPktSizeRange3
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 801 and 1550
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.81

Field Name : fwdIngressPktSizeRange2
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 201 and 800
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.80

Field Name : fwdIngressPktSizeRange1
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packet size between 0 and 200
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.79

Field Name : revEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.78

Field Name : revIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.77

Field Name : fwdEgressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Forward Egress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.76

Field Name : fwdIngressBytesOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.75

Field Name : revEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.74

Field Name : revIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.73

Field Name : fwdEgressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.72

Field Name : fwdIngressPacketsOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets OTHERS
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.71

Field Name : revEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.70

Field Name : revIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.69

Field Name : fwdEgressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.68

Field Name : fwdIngressBytesIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.67

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : revEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.66

Field Name : revIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.65

Field Name : fwdEgressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.64

Field Name : fwdIngressPacketsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.63

Field Name : revEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.62

Field Name : revIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.61

Field Name : fwdEgressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.60

Field Name : fwdIngressBytesUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.59

Field Name : revEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.58

Field Name : revIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Reverse Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.57

Field Name : fwdEgressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.56

Field Name : fwdIngressPacketsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets UDP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.55

Field Name : revEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.54

Field Name : revIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.53

Field Name : fwdEgressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.52

Field Name : fwdIngressBytesTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Bytes TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.51

Field Name : revEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.50

Field Name : revIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.49

Field Name : fwdEgressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Egress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.48

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : fwdIngressPacketsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Ingress Packets TCP
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.47

Field Name : limitEntryAlreadyAddedToDelQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Added twice to delete queue
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.148

Field Name : fwInsideClIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : fw inside CL ID mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.147

Field Name : fwInsideClTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : fw inside CL TYPE mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.146

Field Name : noFwClassListMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No FW inside Class-List Match
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.145

Field Name : fwInsideClEntryUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : fw inside CL entry update is called
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.144

Field Name : fwInsideEntriesRemovedDmzUntagedFirst
Field Type : CounterBasedGauge64
Field Status : current
Description : lookup entries removed, when CL is bound and dmz intf is untagged
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.143

Field Name : fwInsideEntrieAddClBoundFirst
Field Type : CounterBasedGauge64
Field Status : current
Description : lookup entries added when CL is bound first and intf is dmz tagged later
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.142

Field Name : fwInsideEntriesNotAddedNoDmzIntf
Field Type : CounterBasedGauge64
Field Status : current
Description : no dmz interface found and lookup entries are not added
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.141

Field Name : fwInsideClLoad
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : fw inside CL is loaded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.140

Field Name : fwInsideClResetIdx
Field Type : CounterBasedGauge64
Field Status : current
Description : inside CL index reset
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.139

Field Name : fwInsideRemoveV6Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside remove v6 lookup entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.138

Field Name : fwInsideRemoveV4Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside remove v4 lookup entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.137

Field Name : fwInsideUpdateV6Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside update v6 lookup entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.136

Field Name : fwInsideUpdateV4Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside update v4 lookup entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.135

Field Name : fwInsidePopulateV6Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside populate v6 lookup entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.134

Field Name : fwInsidePopulateV4Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside populate v4 lookup entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.133

Field Name : fwInsideClUnbound
Field Type : CounterBasedGauge64
Field Status : current
Description : FW client CL unbound
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.132

Field Name : fwInsideClBound
Field Type : CounterBasedGauge64
Field Status : current
Description : FW client ips bound via Classlist
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.131

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : fwInsideSubnetEntryDelError
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside error in entry deletion from brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.130

Field Name : fwInsideSubnetEntryCreationError
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside error in entry creation in brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.129

Field Name : fwInsideSubnetV6EntriesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v6 subnet entries are deleted from brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.128

Field Name : fwInsideSingleV6EntriesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v6 single ip entries are deleted from brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.127

Field Name : fwInsideSubnetV4EntriesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v4 subnet entries are deleted from brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.126

Field Name : fwInsideSingleV4EntriesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v4 single ip entries are deleted from brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.125

Field Name : fwInsideSubnetV6EntriesAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v6 subnet entries are added to brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.124

Field Name : fwInsideSingleV6EntriesAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v6 single ip entries are added to brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.123

Field Name : fwInsideSubnetV4EntriesAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : FW inside v4 subnet entries are added to brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.122

Field Name : fwInsideSingleV4EntriesAdded
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : FW inside v4 single ip entries are added to brcm
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.121

Field Name : urpfPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : URPF check packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.46

Field Name : l2VlanChanged
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 forwarding vlan changed after session create
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.110

Field Name : l2DstInOutSame
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 route to same port as received
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.109

Field Name : noRevL2Dst
Field Type : CounterBasedGauge64
Field Status : current
Description : No Reverse Mac Entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.45

Field Name : noFwdL2Dst
Field Type : CounterBasedGauge64
Field Status : current
Description : No Forward Mac Entry
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.44

Field Name : noRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Reverse Route
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.43

Field Name : noFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Forward Route
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.42

Field Name : algDefaultPortDisable
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.41

Field Name : limitEntryPerCpuMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Memory Freed (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.40

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : limitEntryPerCpuMemAllocationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Memory Allocation Failed (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.39

Field Name : limitEntryPerCpuMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Memory Allocated (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.38

Field Name : limitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Per Second Limit Exceeded (Deprecated)
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.37

Field Name : cpsLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Connections Per Second Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.101

Field Name : totalThroughputLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Throughput Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.100

Field Name : downlinkThroughputLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Downlink Throughput Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.99

Field Name : uplinkThroughputLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Uplink Throughput Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.98

Field Name : totalPpsLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total PPS Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.97

Field Name : downlinkPpsLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Downlink PPS Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.96

Field Name : uplinkPpsLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Uplink PPS Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.95

Field Name : srcSessionLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Concurrent Session Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.36

Field Name : invalidLidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Lid Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.35

Field Name : nonSynPktFwdAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : Non-SYN pkt forward allowed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.111

Field Name : undeterminedRuleCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Undetermined rule detected
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.108

Field Name : limitEntryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.34

Field Name : limitEntryNotInBucket
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Not in Bucket
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.33

Field Name : limitEntryFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Found
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.103

Field Name : limitEntryCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.32

Field Name : limitEntryMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.31

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : limitEntryAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.30

Field Name : limitEntryFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit Entry Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.29

Field Name : firewallGlobalActiveFullconeSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Active Full-cone sessions
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.28

Field Name : dataSessionFreedShadowLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : Shadow Data Sessions Freed Local
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.107

Field Name : dataSessionFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Shadow Data Sessions Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.27

Field Name : dataSessionCreatedShadowLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : Shadow Data Sessions Created Local
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.106

Field Name : dataSessionCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Shadow Data Sessions Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.26

Field Name : haFullconeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Full-cone Session Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.25

Field Name : fullconeExtAdded
Field Type : CounterBasedGauge64
Field Status : current
Description : Fullcone Extension Added
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.24

Field Name : fullconeExtMemFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Fullcone Extension Memory Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.23

Field Name : fullconeExtMemAllocInitFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fullcone Extension Initialization Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.22

Field Name : fullconeExtMemAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fullcone Extension Memory Allocate Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.21

Field Name : fullconeExtMemAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : Fullcone Extension Memory Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.20

Field Name : fullconeExtTooMany
Field Type : CounterBasedGauge64
Field Status : current
Description : Fullcone Extension Too Many
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.19

Field Name : fullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.18

Field Name : fullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.17

Field Name : tcpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.16

Field Name : udpFullconeFreedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.15

Field Name : tcpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.14

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : udpFullconeCreatedShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP Full-cone sessions created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.13

Field Name : fullconeOverflowEif
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session EIF Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.12

Field Name : fullconeOverflowEim
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone Session EIM Overflow
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.11

Field Name : fullconeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session not found
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.10

Field Name : fullconeRetryLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session retry look-up
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.9

Field Name : fullconeInDelQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-cone session found in delete queue
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.8

Field Name : fwDefPktDir
Field Type : CounterBasedGauge64
Field Status : current
Description : default direction assigned to packet irrespective of interface tags
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.120

Field Name : firewallGlobalDynBlistNoActivePolicy
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist - No Active Policy
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.119

Field Name : firewallGlobalDynBlistVersionMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist - Version Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.118

Field Name : firewallGlobalDynBlistPktRateHigh
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Dynamic Blacklist - Pkt Rate High
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.116

Field Name : firewallGlobalDynBlistPktRateLow
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist - Pkt Rate Low
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.115

Field Name : firewallGlobalDynBlistPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist - Packet Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.114

Field Name : firewallGlobalDynBlistSessFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.113

Field Name : firewallGlobalDynBlistSessCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.112

Field Name : firewallGlobalDataSessionFreedLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed Local
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.105

Field Name : firewallGlobalDataSessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.7

Field Name : firewallGlobalDynBlistSessSP
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Blacklist Session (Slowpath)
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.117

Field Name : firewallGlobalDataSessionCreatedLocal
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created Local
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.104

Field Name : firewallGlobalDataSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.6

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : firewallGlobalFullconeCreationFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Full-Cone Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.5

Field Name : firewallGlobalUdpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.4

Field Name : firewallGlobalUdpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Full-cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.3

Field Name : firewallGlobalTcpFullconeFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.2

Field Name : firewallGlobalTcpFullconeCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Full-cone Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.7.1.1

Field Name : sessionLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Limit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.45

Field Name : iddosBlackholeEntryDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : iDDoS IP Entry Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.44

Field Name : iddosBlackholeEntryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : iDDoS IP Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.43

Field Name : tcpLoggingPortAllocationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Logging Port Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.42

Field Name : tcpLoggingPortFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : TCP Logging Port Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.41

Field Name : tcpLoggingPortAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Logging Port Allocated
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.40

Field Name : logTypeSctpInnerProtoFilter
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type SCTP Inner Proto Filter
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.37

Field Name : sctpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.36

Field Name : sctpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.35

Field Name : httpAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Request Info Allocation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.34

Field Name : httpOutOfOrderDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP out-of-order dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.33

Field Name : logMessageTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Log message too long
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.32

Field Name : tcpLoggingConnDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Logging Conn Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.31

Field Name : tcpLoggingConnCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Logging Conn Create Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.30

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : tcpLoggingConnEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Logging Conn Established
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.29

Field Name : addMsgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Add Message to Buffer Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.28

Field Name : outOfBuffers
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Buffers
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.27

Field Name : ipv6FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Fragmentation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.26

Field Name : ipv6FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Fragmentation Applied
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.25

Field Name : ipv4FragFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragmentation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.24

Field Name : ipv4FragApplied
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragmentation Applied
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.23

Field Name : templateError
Field Type : CounterBasedGauge64
Field Status : current
Description : Template Error
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.22

Field Name : algOverridePermit
Field Type : CounterBasedGauge64
Field Status : current
Description : Alg Override Permit
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.21

Field Name : dcmsgPermit
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Dcmsg Permit
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.20

Field Name : httpLoggingInvalidFormat
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Logging Invalid Format Error
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.19

Field Name : httpRequestLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Request Logged
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.18

Field Name : otherSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.17

Field Name : otherSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.16

Field Name : icmpv6SessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPV6 Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.15

Field Name : icmpv6SessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPV6 Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.14

Field Name : icmpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.13

Field Name : icmpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.12

Field Name : udpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.11

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : udpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.10

Field Name : tcpSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.9

Field Name : tcpSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.8

Field Name : logDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Packets Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.7

Field Name : ruleNotLogged
Field Type : CounterBasedGauge64
Field Status : current
Description : Firewall Rule Not Logged
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.6

Field Name : logTypeSessionOpened
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type Session Open
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.5

Field Name : logTypeSessionClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type Session Close
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.4

Field Name : logTypeDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type Deny
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.3

Field Name : logTypeReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type Reset
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.2

Field Name : logMessageSent
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Log Packet Sent

OID : 1.3.6.1.4.1.22610.2.4.10.139.6.1.1

Field Name : logTypeGtpInvalidPorts

Field Type : CounterBasedGauge64

Field Status : current

Description : Log Event mismatch of GTP message and ports

OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.26

Field Name : logTypeGtpInvalidVersion

Field Type : CounterBasedGauge64

Field Status : current

Description : Log Event invalid GTP version

OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.25

Field Name : logTypeGtpHdrInvalidPiggyFlag

Field Type : CounterBasedGauge64

Field Status : current

Description : Log Event GTP invalid piggyback flag in header

OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.24

Field Name : logTypeGtpHdrInvalidSpareBits

Field Type : CounterBasedGauge64

Field Status : current

Description : Log Event GTP invalid spare bits in header

OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.23

Field Name : logTypeGtpHdrInvalidProtocolFlag

Field Type : CounterBasedGauge64

Field Status : current

Description : Log Event GTP Protocol flag in header

OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.22

Field Name : logTypeGtpInvalidMessageLength

Field Type : CounterBasedGauge64

Field Status : current

Description : Log Event GTP Invalid message length across layers

OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.21

Field Name : logTypeGtpRateLimitPeriodic

Field Type : CounterBasedGauge64

Field Status : current

Description : Log Event GTP Rate Limit Periodic

OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.20

Field Name : logTypeGtpSeqNumMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : Log Event GTP Response Sequence number Mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.19

Field Name : logTypeGtpNodeRestart

Field Type : CounterBasedGauge64

Field Status : current

Description : Log Event GTP SGW/PGW restarted

OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.18

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : logTypeGtpInGtpFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP in GTP Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.17

Field Name : logTypeCountryCodeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Country Code Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.16

Field Name : logTypeGtpRatTypeFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP RAT Type Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.15

Field Name : logTypeGtpApnFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Apn Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.14

Field Name : logTypeGtpMessageFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Message Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.13

Field Name : logTypeMaxMsgLength
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Message Length Exceeded Max
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.12

Field Name : logTypeOutOfState
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Out of State Message
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.11

Field Name : logTypeMessageNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Reserved Message Found
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.10

Field Name : logTypeCrosslayerCorrelation
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event GTP Crosslayer Correlation
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.9

Field Name : logTypeEnduserIpSpoofed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Log Event Type GTP Enduser IP Spoofed
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.8

Field Name : logTypeGtpOutOfStateIe
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Out of State IE
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.7

Field Name : logTypeGtpOutOfOrderIe
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Out of Order IE V1
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.6

Field Name : logTypeGtpMsisdnFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP MSISDN Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.5

Field Name : logTypeGtpMandatoryIeInsideGroupedIeMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Mandatory IE Missing Inside Grouped IE
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.4

Field Name : logTypeGtpMandatoryIeMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Mandatory IE Missing
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.3

Field Name : logGtpTypeReservedIePresent
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Reserved IE Present
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.2

Field Name : logTypeGtpInvalidTeid
Field Type : CounterBasedGauge64
Field Status : current
Description : Log Event Type GTP Invalid TEID
OID : 1.3.6.1.4.1.22610.2.4.10.139.6.2.1.1

Field Name : fwServiceGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.139.4.1.1

Field Name : fwServiceGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.139.4.1.1.1

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : fwServicePeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Service peak connection
OID : 1.3.6.1.4.1.22610.2.4.10.139.4.1.1.1.4

Field Name : fwServerSelectionFailReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Service selection fail reset
OID : 1.3.6.1.4.1.22610.2.4.10.139.4.1.1.1.3

Field Name : fwServerSelectionFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Service selection fail drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.4.1.1.1.2

Field Name : fwServiceGroupName
Field Type : String
Field Status : current
Description : FW Service Name
OID : 1.3.6.1.4.1.22610.2.4.10.139.4.1.1.1.1

Field Name : fwServerSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1

Field Name : fwServerSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1

Field Name : peakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connections
OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1.6

Field Name : revPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1.5

Field Name : fwdPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1.4

Field Name : totalConn
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Total connections

OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1.3

Field Name : fwServerCurrConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Current connections

OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1.2

Field Name : fwName

Field Type : String

Field Status : current

Description : Server Name

OID : 1.3.6.1.4.1.22610.2.4.10.139.3.1.1.1.1

Field Name : dummy

Field Type : CounterBasedGauge64

Field Status : current

Description : Entry for a10countergen

OID : 1.3.6.1.4.1.22610.2.4.10.139.23.1.1

Field Name : gtpExtHdrIncorrectLength

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP Extension header incorrect length

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.133

Field Name : gtpUInnerIpNotPresent

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP-U inner IP not present

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.132

Field Name : gtpUMonitorForward

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP-U messages forwarded via monitor mode

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.284

Field Name : gtpMonitorForward

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP messages forwarded via monitor mode

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.126

Field Name : gtpL5ConnCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP L5 conn created

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.124

Field Name : gtpL3ConnDeleted

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP L3 conn deleted

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.121

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpStatelessForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Stateless Forward
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.120

Field Name : dropGtpBearerNotFoundInResp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Bearer not found in response
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.119

Field Name : dropGtpMissingCondIeBearerCtx
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing conditional IE in bearer context Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.118

Field Name : gtpPathMessageLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-Path Message Length Mismatch Across Layers
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.117

Field Name : gtpUMessageLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Message Length Mismatch Across Layers
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.116

Field Name : dropGtpIpVersionMismatchHoFteid
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP IP version mismatch in Handover SGW FTEID
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.115

Field Name : dropGtpIpVersionMismatchFteid
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP IP version mismatch for req & response FTEIDs
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.114

Field Name : gtpIpVersionV4V6
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP IP versions of V4&V6 in FTEID
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.113

Field Name : gtpNotEnabledOnStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Not Enabled on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.125

Field Name : gtpSmpPathDelSyncRx
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP SMP path delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.112

Field Name : gtpSmpPathDelSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP path delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.111

Field Name : gtpCL5SyncedBeforeL3
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C L5 conn synced before corresponding L3 GTP-C conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.110

Field Name : gtpUSyncedBeforeControl
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel synced before corresponding GTP-C
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.109

Field Name : dropGtpConnCreationStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Conn creation on Standby Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.108

Field Name : gtpV2CEchoDelSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C-Echo Delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.107

Field Name : gtpV1CEchoDelSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C-Echo Delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.106

Field Name : gtpV0CEchoDelSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C-Echo Delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.105

Field Name : gtpV2CEchoDelSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Echo Delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.104

Field Name : gtpV1CEchoDelSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Echo Delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.103

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpV0CEchoDelSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Echo Delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.102

Field Name : gtpV2CEchoCreateSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C-Echo Create Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.101

Field Name : gtpV1CEchoCreateSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C-Echo Create Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.100

Field Name : gtpV0CEchoCreateSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C-Echo Create Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.99

Field Name : gtpV2CEchoCreateSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Echo Create Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.98

Field Name : gtpV1CEchoCreateSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Echo Create Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.97

Field Name : gtpV0CEchoCreateSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Echo Create Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.96

Field Name : gtpDeleteBearerSyncWithPeriodicUpdateOnStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Bearer Deleted on Standby with Periodic Sync
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.95

Field Name : gtpAddBearerSyncWithPeriodicUpdateOnStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Bearer Added on Standby with Periodic Sync
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.94

Field Name : gtpAddBearerSyncNotRxOnStandby
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP Add Bearer Sync Not Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.93

Field Name : gtpSmpAdditionalBearerSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Additional Bearer Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.123

Field Name : gtpSmpDelBearerSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Del Bearer Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.92

Field Name : gtpSmpAddBearerSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Add Bearer Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.91

Field Name : gtpSmpAdditionalBearerSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Additional Bearer Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.122

Field Name : gtpSmpDelBearerSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Del Bearer Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.90

Field Name : gtpSmpAddBearerSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Add Bearer Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.89

Field Name : gtpHandoverSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Handover Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.88

Field Name : gtpHandoverSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Handover Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.87

Field Name : gtpV2CDeleteSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.86

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpV1CDeleteSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.85

Field Name : gtpV0CDeleteSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Delete Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.84

Field Name : gtpV2CCreateSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Create Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.83

Field Name : gtpV1CCreateSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Create Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.82

Field Name : gtpV0CCreateSyncRx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Create Sync Received on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.81

Field Name : gtpV2CDeleteSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.80

Field Name : gtpV1CDeleteSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.79

Field Name : gtpV0CDeleteSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Delete Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.78

Field Name : gtpV2CCreateSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Create Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.77

Field Name : gtpV1CCreateSynced
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTPv1-C Tunnel Create Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.76

Field Name : gtpV0CCreateSynced
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Create Synced
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.75

Field Name : gtpUDownlinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Downlink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.74

Field Name : gtpUDownlinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Downlink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.73

Field Name : gtpUUplinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Uplink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.72

Field Name : gtpUUplinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Uplink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.71

Field Name : gtpUDownlinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Downlink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.70

Field Name : gtpUDownlinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Downlink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.69

Field Name : gtpUUplinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Uplink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.68

Field Name : gtpUUplinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Uplink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.67

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpV2CDownlinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Downlink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.66

Field Name : gtpV2CDownlinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Downlink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.65

Field Name : gtpV2CUplinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Uplink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.64

Field Name : gtpV2CUplinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Uplink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.63

Field Name : gtpV2CDownlinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Downlink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.62

Field Name : gtpV2CDownlinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Downlink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.61

Field Name : gtpV2CUplinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Uplink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.60

Field Name : gtpV2CUplinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Uplink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.59

Field Name : gtpV1CDownlinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Downlink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.58

Field Name : gtpV1CDownlinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTPv1-C Downlink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.57

Field Name : gtpV1CUplinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Uplink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.56

Field Name : gtpV1CUplinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Uplink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.55

Field Name : gtpV1CDownlinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Downlink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.54

Field Name : gtpV1CDownlinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Downlink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.53

Field Name : gtpV1CUplinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Uplink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.52

Field Name : gtpV1CUplinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Uplink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.51

Field Name : gtpV0CDownlinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Downlink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.50

Field Name : gtpV0CDownlinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Downlink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.49

Field Name : gtpV0CUplinkEgressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Uplink Egress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.48

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpV0CUplinkIngressBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Uplink Ingress Bytes
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.47

Field Name : gtpV0CDownlinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Downlink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.46

Field Name : gtpV0CDownlinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Downlink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.45

Field Name : gtpV0CUplinkEgressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Uplink Egress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.44

Field Name : gtpV0CUplinkIngressPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Uplink Ingress Packets
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.43

Field Name : gtpPathmFailConnCreateSlow
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP path packet failed while creating L4-session in slowpath
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.361

Field Name : gtpUFailConnCreateSlow
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U packet failed while creating L4-session in slowpath
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.360

Field Name : gtpCFailConnCreateSlow
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C packet failed creating L4-session in slowpath
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.359

Field Name : bladeGtpSmpSigCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP signature check Failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.358

Field Name : gtpSmpSigCheckFailed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP SMP signature check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.357

Field Name : bladeGtpUSmpSigCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U SMP signature check Failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.356

Field Name : gtpUSmpSigCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP signature check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.355

Field Name : bladeGtpCSmpSigCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP signature check Failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.354

Field Name : gtpCSmpSigCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP signature check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.353

Field Name : gtpCMatchCSmpWithHoFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C match C-smp with HO flag
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.352

Field Name : gtpCMatchCSmpWithDelFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C match C-smp with deletion flag
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.351

Field Name : gtpSyncRxDelNoSuchEchoSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del ECHO-Conn not Found
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.350

Field Name : gtpSyncRxDelNoSuchUSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del U-Conn not Found
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.349

Field Name : gtpSyncRxDelNoSuchCSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del C-Conn not Found
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.348

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpSyncTxDeleteEchoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync delete Session ECHO sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.347

Field Name : gtpSyncTxDeleteUCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync delete Session GTP-U sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.346

Field Name : gtpSyncTxDeleteCCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync delete Session GTP-C sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.345

Field Name : gtpSyncTxCreateEchoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync create Session ECHO sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.344

Field Name : gtpSyncTxCreateUCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync create Session GTP-U sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.343

Field Name : gtpSyncTxCreateCCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync create Session GTP-C sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.342

Field Name : gtpSyncRxCreateEchoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync create Session ECHO Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.341

Field Name : gtpSyncRxCreateUCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync create Session GTP-U Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.340

Field Name : gtpSyncRxCreateCCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync create Session GTP-C Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.339

Field Name : gtpSyncRxDelEchoCounter
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : Conn Sync Del Session ECHO Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.338

Field Name : gtpSyncRxDelUCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del Session GTP-U Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.337

Field Name : gtpSyncRxDelCCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del Session GTP-C Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.336

Field Name : gtpQueryPktRxCounterGtpEcho
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query GTP-ECHO recv counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.335

Field Name : gtpQueryPktRxCounterGtpU
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query GTP-U recv counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.334

Field Name : gtpQueryPktRxCounterGtpC
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query GTP-C recv counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.333

Field Name : gtpSyncTxFwDropSessionCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync FW gtp Create Session Sent dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.332

Field Name : gtpSyncTxInterPuNoDataError
Field Type : CounterBasedGauge64
Field Status : current
Description : send of inter-pu msg failed with no data to pack
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.331

Field Name : gtpSyncTxInterPuNoMsgHdrError
Field Type : CounterBasedGauge64
Field Status : current
Description : send of inter-pu msg failed as msg header ext failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.330

Field Name : gtpSyncTxInterPuNoUgError
Field Type : CounterBasedGauge64
Field Status : current
Description : send of inter-pu msg failed with no user group error
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.329

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpSyncTxInterPuNoGtpUExt
Field Type : CounterBasedGauge64
Field Status : current
Description : send of inter-pu msg failed with no GTP-U ext
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.328

Field Name : gtpSyncTxInterPuNoVnpError
Field Type : CounterBasedGauge64
Field Status : current
Description : send of inter-pu msg failed with no vnp error
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.327

Field Name : gtpQueryPktTxCounterGtpEcho
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query GTP-ECHO sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.326

Field Name : gtpQueryPktTxCounterGtpU
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query GTP-U sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.325

Field Name : gtpQueryPktTxCounterGtpC
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query GTP-C sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.324

Field Name : gtpSyncRxCreateExtBitCounterInterPu
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create with Ext Received with inter-pu comm counter
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.323

Field Name : gtpCConnWithNoDst
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C created on active with no dst
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.322

Field Name : gtpRevTupleDstUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP REV tuple updated with dst
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.321

Field Name : gtpFwdTupleDstUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP FWD tuple updated with dst
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.320

Field Name : bladeGtpInterPuNoRspToQuery
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP inter-pu No response to query on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.319

Field Name : gtpInterPuNoRspToQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu No response to query
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.318

Field Name : bladeGtpInterPuUDeleteError
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-delete rx drop with error PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.317

Field Name : gtpInterPuUDeleteError
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-delete rx drop with error
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.316

Field Name : bladeGtpInterPuUCreateError
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-create rx drop with error PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.315

Field Name : gtpInterPuUCreateError
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-create rx drop with error
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.314

Field Name : bladeGtpInterPuUDeleteDropNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-delete rx drop no smp PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.313

Field Name : gtpInterPuUDeleteDropNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-delete rx drop no smp
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.312

Field Name : bladeGtpInterPuUCreateDropNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-create rx drop no smp PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.311

Field Name : gtpInterPuUCreateDropNoSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-create rx drop no smp
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.310

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : bladeGtpInterPuCQueryRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu C-mesg recv on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.309

Field Name : bladeGtpInterPuUDeleteRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-deletion recv on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.308

Field Name : bladeGtpInterPuUCreateRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-creation recv on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.307

Field Name : gtpInterPuCQueryRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu C-mesg recv
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.306

Field Name : gtpInterPuUDeleteRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-deletion recv
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.305

Field Name : gtpInterPuUCreateRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-creation recv
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.304

Field Name : bladeGtpInterPuCQueryTxFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu C-query tx fail on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.303

Field Name : bladeGtpInterPuUDeleteTxFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-deletion tx fail on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.302

Field Name : bladeGtpInterPuUCreateTxFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-creation tx fail on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.301

Field Name : gtpInterPuCQueryTxFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP inter-pu C-query tx fail
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.300

Field Name : gtpInterPuUDeleteTxFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-deletion tx fail
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.299

Field Name : gtpInterPuUCreateTxFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-creation tx fail
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.298

Field Name : bladeGtpInterPuCQuerySent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu C-query sync sent on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.297

Field Name : bladeGtpInterPuUDeleteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-deletion sync sent on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.296

Field Name : bladeGtpInterPuUCreateSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-creation sync sent on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.295

Field Name : gtpInterPuCQuerySent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu C-query sync sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.294

Field Name : gtpInterPuUDeleteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-deletion sync sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.293

Field Name : gtpInterPuUCreateSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-pu U-creation sync sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.292

Field Name : bladeGtpSmpNotFoundInterPu
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP smp not found during inter-pu comm on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.291

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpSmpNotFoundInterPu
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP smp not found during inter-pu comm
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.290

Field Name : gtpSyncNewConnCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C sync new conn create
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.289

Field Name : gtpInfoExtNotPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C info not packed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.288

Field Name : bladeGtpSmpNoActionWithUCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP no action with u-create at inter-pu sync on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.287

Field Name : gtpSmpNoActionWithUCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP no action with u-create at inter-pu sync
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.286

Field Name : bladeGtpSmpSessionCountCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U session count is not in range of 0-11 in GTP-C SMP on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.285

Field Name : bladeGtpCSmpClearedByL3WithL5
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp cleared by l3-conn with l5 on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.283

Field Name : bladeGtpCSmpClearedByStandalone
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp cleared by standalone conn on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.282

Field Name : bladeGtpUSmpAccessAfterReuse
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp access after reuse on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.281

Field Name : bladeGtpCSmpAccessAfterReuse
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP-C smp access after reuse on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.280

Field Name : bladeGtpCAttemptForDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp double free attempted on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.279

Field Name : bladeGtpUAttemptForDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp double free attempted on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.278

Field Name : gtpCSmpClearedByL3WithL5
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp cleared by l3-conn with l5
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.223

Field Name : gtpCSmpClearedByStandalone
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp cleared by standalone conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.222

Field Name : gtpUSmpAccessAfterReuse
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp access after reuse
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.221

Field Name : gtpCSmpAccessAfterReuse
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp access after reuse
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.220

Field Name : gtpCAttemptForDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp double free attempted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.219

Field Name : gtpUAttemptForDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp double free attempted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.218

Field Name : gtpUTunnelFragOrJumboPktProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel Fragmented or Jumbo packet processed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.366

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpEchoFragOrJumboPktProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-Echo Fragmented or Jumbo packet processed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.365

Field Name : gtpCFragOrJumboPktProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Fragmented or Jumbo packet processed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.364

Field Name : gtpUFragPktReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Fragmented packet received
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.217

Field Name : gtpCFragPktReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Fragmented packet received
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.216

Field Name : gtpUFragPktProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Fragmented packet processed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.215

Field Name : bladeGtpUPktUSmpValidationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : gtp-u smp ip validation failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.277

Field Name : gtpUPktUSmpValidationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : gtp-u smp ip validation failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.214

Field Name : gtpUSmpNotFoundCProcessing
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-U smp not found in C-processing
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.213

Field Name : gtpEchoStatelessForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-echo Stateless Forward
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.212

Field Name : bladeGtpUMatchCSmpInRml
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP-U match C-smp in rml on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.276

Field Name : bladeGtpUInfoExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-U extension during pkt processing on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.275

Field Name : bladeGtpCSmpExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-C smp during pkt processing on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.274

Field Name : bladeGtpCInfoExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-C extension during pkt processing on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.273

Field Name : gtpUMatchCSmpInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U match C-smp in rml
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.211

Field Name : gtpUInfoExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-U extension during pkt processing
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.210

Field Name : gtpCSmpExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-C smp during pkt processing
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.209

Field Name : gtpCInfoExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract GTP-C extension during pkt processing
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.208

Field Name : gtpUMatchDbrUSmpConnCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U match U-smp with dbr during conn creation
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.207

Field Name : gtpUMatchCSmpWithHoFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U match C-smp with HO flag
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.206

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpUMatchCSmpWithDelFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U match C-smp with deletion flag
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.205

Field Name : gtpUSmpNotFoundConnCreation
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp not found during conn creation
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.204

Field Name : gtpUStatelessForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Stateless Forward
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.203

Field Name : bladeGtpUSmpUnlinkedUConnCreation
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp unlinked from HT while creating U-conn on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.272

Field Name : bladeGtpCSmpDelMaxRefCount
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP with del flag and max ref count during ageout on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.271

Field Name : bladeGtpCRefCountMaxSmpSetForAgeout
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP set for deletion during age out with refcount max on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.270

Field Name : bladeGtpCSmpInRmlCConnAgeUpd
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP in RML during C-conn age update on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.269

Field Name : bladeGtpSmpAlreadyInDLHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP already linked in downlink hash on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.268

Field Name : bladeGtpSmpAlreadyInULHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP already linked in uplink hash on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.267

Field Name : bladeGtpUSmpNotFoundInHash
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP-U SMP not found in hash table to unlink on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.266

Field Name : bladeGtpCSmpNotFoundInHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP not found in hash table to unlink on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.265

Field Name : bladeGtpSmpPathDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP path added twice to del queue on PU2, cannot be added again
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.264

Field Name : bladeGtpSmpDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP added twice to del queue on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.263

Field Name : gtpUSmpUnlinkedUConnCreation
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp unlinked from HT while creating U-conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.202

Field Name : gtpCSmpDelMaxRefCount
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP with del flag and max ref count during ageout
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.201

Field Name : gtpCRefCountMaxSmpSetForAgeout
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP set for deletion during age out with refcount max
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.200

Field Name : gtpCSmpInRmlCConnAgeUpd
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP in RML during C-conn age update
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.199

Field Name : gtpSmpAlreadyInDLHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP already linked in downlink hash
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.198

Field Name : gtpSmpAlreadyInULHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP already linked in uplink hash
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.197

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpUSmpNotFoundInHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U SMP not found in hash table to unlink
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.196

Field Name : gtpCSmpNotFoundInHash
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP not found in hash table to unlink
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.195

Field Name : gtpSmpPathDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP path added twice to del queue, cannot be added again
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.194

Field Name : gtpSmpDoubleFree
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP added twice to del queue
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.193

Field Name : bladeGtpSmpPathAlreadyInDelQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP-PATH already in del queue, cannot be added again on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.262

Field Name : bladeGtpSmpAlreadyInDelQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP already in del queue, cannot be added again on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.261

Field Name : bladeGtpCConnPtrNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C conn ptr not found on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.260

Field Name : bladeGtpSmpLinkToHashInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP smp linked to hash table when in rml on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.259

Field Name : bladeGtpUSmpUnlinkFromHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp unlink from hash table failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.258

Field Name : bladeGtpCSmpUnlinkFromHashFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP-C smp unlink from hash table failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.257

Field Name : bladeGtpInfoExtNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-Info ext not found while freeing C-smp on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.256

Field Name : bladeGtpUSmpAlreadyInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp already in rml on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.255

Field Name : bladeGtpCSmpAlreadyInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp already in rml on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.254

Field Name : bladeGtpUSmpCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP U-SMP check Failed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.253

Field Name : bladeGtpCConnNotInRmlWhenFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C conn not in rml when tuple is freed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.252

Field Name : bladeGtpCFreedConnCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C freed conn accessed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.251

Field Name : bladeGtpSmpDecSessCountCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U session count is 0 in GTP-C SMP on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.250

Field Name : bladeGtpCSmpReferStaleIdx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP referring stale C-conn idx on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.249

Field Name : gtpSmpPathAlreadyInDelQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP-PATH already in del queue, cannot be added again
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.192

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpSmpAlreadyInDelQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP already in del queue, cannot be added again
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.191

Field Name : gtpCConnPtrNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C conn ptr not found
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.190

Field Name : gtpSmpLinkToHashInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP smp linked to hash table when in rml
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.189

Field Name : gtpUSmpUnlinkFromHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp unlink from hash table failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.188

Field Name : gtpCSmpUnlinkFromHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp unlink from hash table failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.187

Field Name : gtpInfoExtNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-Info ext not found while freeing C-smp
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.186

Field Name : gtpUSmpAlreadyInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp already in rml
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.185

Field Name : gtpCSmpAlreadyInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C smp already in rml
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.184

Field Name : gtpUSmpCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP U-SMP check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.183

Field Name : gtpCConnNotInRmlWhenFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP-C conn not in rml when tuple is freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.182

Field Name : gtpCFreedConnCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C freed conn accessed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.181

Field Name : gtpSmpDecSessCountCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U session count is 0 in GTP-C SMP
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.180

Field Name : gtpCSmpReferStaleIdx
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP referring stale C-conn idx
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.179

Field Name : gtpBldToMstrQueryRespFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU dcmsg of query response failed from Blade to Master
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.178

Field Name : gtpMstrToBldQueryRespFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU dcmsg of query response failed from Master to Blade
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.177

Field Name : gtpInterPuBldToMstrQueryRespSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU GTP-C query response sent from Blade to Master
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.176

Field Name : gtpInterPuBldToMstrQueryRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU GTP-C mesg received on Master
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.175

Field Name : gtpInterPuBldToMstrQuerySent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU query sent from Blade to Master
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.174

Field Name : gtpInterPuBldToMstrDcmsgRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU dcmsg received on Master
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.173

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpInterPuBldToMstrDcmsgSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU Blade to Master dcmsg sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.172

Field Name : gtpInterPuBldToMstrDcmsgFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU dcmsg failed from Blade to Master
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.171

Field Name : gtpInterPuMstrToBldQueryRespSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU GTP-C query response sent from Master to Blade
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.170

Field Name : gtpInterPuMstrToBldQueryRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU GTP-C mesg received on Blade
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.169

Field Name : gtpInterPuMstrToBldQuerySent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU query sent from Master to Blade
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.168

Field Name : gtpInterPuMstrToBldDcmsgRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU dcmsg received on blade
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.167

Field Name : gtpInterPuMstrToBldDcmsgSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU Master to Blade dcmsg sent
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.166

Field Name : gtpInterPuMstrToBldDcmsgFail
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP inter-PU dcmsg failed from Master to Blade
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.165

Field Name : gtpCPktFwdConnCreateNoFteid
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C pkt fwded while creating conn when no FTEID
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.164

Field Name : gtpCConnCreatePktDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP-C conn creation drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.163

Field Name : gtpCGoingThruFwLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C mesg going thru fw lookup can be resp or 15 mesg not matching smp
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.162

Field Name : gtpCRevV20ther
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C rev v2 other messages
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.161

Field Name : gtpCRevV10ther
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C rev v1 other messages
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.160

Field Name : gtpCFwdV20ther
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C fwd v2 other messages
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.159

Field Name : gtpCFwdV10ther
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C fwd v1 other messages
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.158

Field Name : gtpCRevPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C rev pkt drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.157

Field Name : gtpCFwdPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C fwd pkt drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.156

Field Name : gtpCProcessPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C process pkt drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.155

Field Name : gtpRefreshConnSetHoFlagLatest
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SGW refresh old conn and set ho flag on latest smp
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.154

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpWrongConnHandoverRequest

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP-C ho mesg matching wrong conn(new teid) with no HO flag

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.153

Field Name : gtpRematchSmpMatchingConn

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP-C rematch smp with packet matching conn

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.152

Field Name : gtpRefreshCConnReuseTeid

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP-C SGW reuse teid with ho and refresh old conn

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.151

Field Name : gtpUnsetHoFlagReuseTeid

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP-C SGW reuse teid with ho and unset ho flag

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.150

Field Name : gtpHoInProgressCMesg

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP-C other than ho mesg matching conn with HO In Progress

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.149

Field Name : gtpHoInProgressHandoverResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP-C ho response matching a conn with HO In Progress

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.148

Field Name : gtpWrongConnHoInProgressHandoverRequest

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP-C ho mesg matching wrong conn(new teid) with HO In Progress

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.147

Field Name : gtpCorrectConnHoInProgressHandoverRequest

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP-C ho mesg matching correct conn(reuse teid) with HO In Progress

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.146

Field Name : gtpHoInProgressHandoverRequest

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP-C ho mesg matching conn with HO In Progress

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.145

Field Name : gtpCHandoverInProgressWithConn

Field Type : CounterBasedGauge64

Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP-C mesg matching conn with HO In Progress
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.144

Field Name : gtpUErrorInd
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Error Indication
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.42

Field Name : gtpV1ExtnHdtNotif
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPV1 Supported Extension header notification
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.41

Field Name : gtpV2CVerNotSupp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Version not supported indication
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.40

Field Name : gtpV1CVerNotSupp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Version not supported indication
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.39

Field Name : gtpV0CVerNotSupp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Version not supported indication
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.38

Field Name : gtpCMessageForwardedWithoutConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Message Forwarded without Conn
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.37

Field Name : responseWithRejectCauseForwarded
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Response with Reject Cause Forwarded
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.36

Field Name : dropGtpFragOrJumboPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Fragmented or JUMBO packet Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.35

Field Name : gtpRrCMessageDcmsg
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Message Sent to home CPU in RR Mode
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.34

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpRrEchoMessageDcmsg
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Echo Message Sent to home CPU in RR Mode
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.33

Field Name : gtpURrMessageDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Message Dropped in RR Mode
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.248

Field Name : gtpRrMessageDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Message Dropped in RR Mode
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.32

Field Name : gtpMultipleHandoverRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Multiple Handover Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.31

Field Name : gtpV2CBearerNotFoundInDeleteResp
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Bearer Not Found in GTP Response
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.30

Field Name : gtpV2CBearerNotFoundInDeleteReq
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Bearer Not Found in GTP Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.29

Field Name : gtpV1CNsapiNotFoundInDeleteReq
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C NSAPI Not Found in GTP Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.28

Field Name : gtpCHandoverRequestOutOfStateDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Handover Request Out of state Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.27

Field Name : gtpUOutOfStateDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Out of state Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.26

Field Name : gtpCreateSessionRequestRetxDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP-C Retransmitted Create Session Request dropped
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.134

Field Name : gtpAddBearerResponseRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Retransmitted Add Bearer Response
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.25

Field Name : gtpDelBearerRequestRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Retransmitted Delete Bearer Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.24

Field Name : gtpHandoverRequestRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Handover Request Retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.23

Field Name : gtpDeleteSessionRequestRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Retransmitted Delete Session Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.22

Field Name : gtpAddBearerRequestRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Retransmitted Add Bearer Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.21

Field Name : gtpCreateSessionRequestRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Retransmitted Create Session Request
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.20

Field Name : dropVldGtpUEchoOutOfState
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Echo Out of State Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.247

Field Name : dropVldGtpEchoIeLenExceedMsgLen
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Echo IE Length Exceeds Message Length
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.135

Field Name : dropVldGtpEchoOutOfState
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Echo Out of State Drop
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.19

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpCEchoPathFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Path Failure due to Echo
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.18

Field Name : gtpNodeRestartEcho
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Node Restoration due to Recovery IE in Echo
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.17

Field Name : gtpEchoConnDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Echo Request conn Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.16

Field Name : gtpEchoConnCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Echo Request Conn Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.15

Field Name : bladeGtpRateLimitEntryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit Entry Create Failure on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.246

Field Name : bladeGtpRateLimitT3CtrCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit Dynamic Counters Create Failure on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.245

Field Name : bladeGtpRateLimitSmpCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit SMP Create Failure on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.244

Field Name : bladeGtpRateLimitSmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit SMP Freed on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.243

Field Name : bladeGtpRateLimitSmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit SMP Created on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.242

Field Name : gtpRateLimitEntryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP Rate Limit Entry Create Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.131

Field Name : gtpRateLimitT3CtrCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit Dynamic Counters Create Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.130

Field Name : gtpRateLimitSmpCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit SMP Create Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.129

Field Name : gtpRateLimitSmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit SMP Freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.128

Field Name : gtpRateLimitSmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Rate Limit SMP Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.127

Field Name : gtpUTunnelRateLimitEntryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel Level Rate Limit Entry Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.241

Field Name : gtpUTunnelRateLimitEntryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel Level Rate Limit Entry Create Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.240

Field Name : gtpUTunnelRateLimitEntryIncRefCount
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel Level Rate Limit Entry Inc ref count
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.363

Field Name : gtpUTunnelRateLimitEntryCreateSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel Level Rate Limit Entry Create Success
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.239

Field Name : gtpTunnelRateLimitEntryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Tunnel Level Rate Limit Entry Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.14

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : gtpTunnelRateLimitEntryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Tunnel Level Rate Limit Entry Create Failure
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.13

Field Name : gtpTunnelRateLimitEntryIncRefCount
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Tunnel Level Rate Limit Entry Inc ref count
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.362

Field Name : gtpTunnelRateLimitEntryCreateSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Tunnel Level Rate Limit Entry Create Success
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.12

Field Name : gtpEchoPktFwdConnCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-ECHO pkt fwded while creating conn with gtp toggling
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.143

Field Name : gtpCPktFwdConnCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C pkt fwded while creating conn with gtp toggling
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.142

Field Name : gtpUPktFwdConnCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U pkt fwded while creating conn with gtp toggling
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.141

Field Name : bladeGtpUSmpInRmlWithSess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp is linked when C-smp is in rml on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.238

Field Name : gtpUSmpInRmlWithSess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U smp is linked when C-smp is in rml
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.140

Field Name : bladeGtpCRefCountSmpExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C session count on C-smp exceeded 2 on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.237

Field Name : gtpCRefCountSmpExceeded
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP-C session count on C-smp exceeded 2

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.139

Field Name : gtpSmpSessionCountCheckFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP-U session count is not in range of 0-11 in GTP-C SMP

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.138

Field Name : bladeGtpSmpCCheckFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP-C SMP check Failed on PU2

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.236

Field Name : bladeGtpSmpPathCheckFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP SMP PATH check Failed on PU2

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.235

Field Name : bladeGtpSmpPathCreationFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP SMP PATH creation Failed on PU2

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.234

Field Name : bladeGtpSmpPathAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP SMP PATH MEM allocated on PU2

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.233

Field Name : bladeGtpSmpPathFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP SMP PATH MEM freed on PU2

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.232

Field Name : bladeGtpSmpPathCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP SMP PATH Created on PU2

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.231

Field Name : bladeSmpCreationFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP SMP Helper Session Creation Failed on PU2

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.230

Field Name : bladeGtpSmpDeleted

Field Type : CounterBasedGauge64

Field Status : current

Description : GTP SMP Deleted on PU2

OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.229

ACOS-FW-STATS-MIB_acosFw_oid_list

Field Name : bladeGtpSmpMarkedDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Marked Deleted on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.228

Field Name : bladeGtpSmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Created on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.227

Field Name : gtpSmpCCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C SMP check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.137

Field Name : gtpSmpPathCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH check Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.136

Field Name : gtpSmpPathCreationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.11

Field Name : gtpSmpPathAllocated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH MEM allocated
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.10

Field Name : gtpSmpPathFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH MEM freed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.9

Field Name : gtpSmpPathCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP PATH Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.8

Field Name : smpCreationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Helper Session Creation Failed
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.7

Field Name : gtpSmpDeleted
Field Type : CounterBasedGauge64
Field Status : current

ACOS-FW-STATS-MIB_acosFw_oid_list

Description : GTP SMP Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.6

Field Name : gtpSmpMarkedDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.5

Field Name : gtpSmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP SMP Created
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.4

Field Name : gtpNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Reverse Route on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.226

Field Name : gtpNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Forward Route on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.225

Field Name : bladeOutOfSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Tunnel Memory on PU2
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.224

Field Name : gtpNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Reverse Route for GTP-C
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.3

Field Name : gtpNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No Forward Route for GTP-C
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.2

Field Name : outOfSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Tunnel Memory for GTP-C
OID : 1.3.6.1.4.1.22610.2.4.10.139.25.1.1

ACOS-FW-STATUS-MIB_oid_list

Field Name : statusOperTable
Field Type : TABLE
Field Status : current
Description : FirewallStatus from object 'fw.status'
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2

Field Name : statusOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statusOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1

Field Name : statusOperInternal
Field Type : Integer32
Field Status : current
Description : internal
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.7

Field Name : statusOperMostRecentCompilationStatus
Field Type : String
Field Status : current
Description : most-recent-compilation-status
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.6

Field Name : statusOperMostRecentCompilationAttempt
Field Type : String
Field Status : current
Description : most-recent-compilation-attempt
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.5

Field Name : statusOperPreviousSuccessfulCompilationDuration
Field Type : String
Field Status : current
Description : previous-successful-compilation-duration
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.4

Field Name : statusOperPreviousSuccessfulCompilationAttempt
Field Type : String
Field Status : current
Description : previous-successful-compilation-attempt
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.3

Field Name : statusOperCurrentActiveRuleSet
Field Type : String
Field Status : current
Description : current-active-rule-set
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.2

Field Name : statusOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.487.1.2.1.1

ACOS-FW-SYSTEM-STATUS-MIB_oid_list

Field Name : systemStatusOperTable
Field Type : TABLE
Field Status : current
Description : FirewallSystemStatus from object 'fw.system-status'
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2

Field Name : systemStatusOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The systemStatusOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1

Field Name : systemStatusOperRadiusEntriesFree
Field Type : CounterBasedGauge64
Field Status : current
Description : radius-entries-free
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.7

Field Name : systemStatusOperRadiusEntriesUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : radius-entries-used
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.6

Field Name : systemStatusOperSmpSessionsFree
Field Type : CounterBasedGauge64
Field Status : current
Description : smp-sessions-free
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.5

Field Name : systemStatusOperSmpSessionsUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : smp-sessions-used
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.4

Field Name : systemStatusOperDataSessionsFree
Field Type : CounterBasedGauge64
Field Status : current
Description : data-sessions-free
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.3

Field Name : systemStatusOperDataSessionsUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : data-sessions-used
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.2

Field Name : systemStatusOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.486.1.2.1.1

ACOS-FW-TCP-WINDOW-CHECK-MIB_oid_list

Field Name : tcpWindowCheckStatsTable
Field Type : TABLE
Field Status : current
Description : ConfigureTCPWindowCheck from object 'fw.tcp-window-check'
OID : 1.3.6.1.4.1.22610.2.4.8.484.1.1

Field Name : tcpWindowCheckStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The tcpWindowCheckStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.484.1.1.1

Field Name : tcpWindowCheckStatsOutsideWindow
Field Type : CounterBasedGauge64
Field Status : current
Description : outside-window
OID : 1.3.6.1.4.1.22610.2.4.8.484.1.1.1.2

Field Name : tcpWindowCheckStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.484.1.1.1.1

ACOS-GSLB-SERVICE-IP-MIB_oid_list

Field Name : portOperTable
Field Type : TABLE
Field Status : current
Description : ServerPort from object 'gslb.service-ip.port'
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2

Field Name : portStatsTable
Field Type : TABLE
Field Status : current
Description : ServerPort from object 'gslb.service-ip.port'
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1

Field Name : portStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1

Field Name : portStatsCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : current
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1.7

Field Name : portStatsActive
Field Type : CounterBasedGauge64
Field Status : current
Description : active
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1.6

Field Name : portStatsPortProto
Field Type : String
Field Status : current
Description : port-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1.4

Field Name : portStatsPortNum
Field Type : Integer32
Field Status : current
Description : port-num
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1.3

Field Name : portStatsNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1.2

Field Name : portStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.1.1.1

Field Name : portOperEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-SERVICE-IP-MIB_oid_list

Description : The portOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1

Field Name : portOperDynamic
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.14

Field Name : portOperUseGslbState
Field Type : CounterBasedGauge64
Field Status : current
Description : use_gslb_state
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.13

Field Name : portOperManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.12

Field Name : portOperTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.11

Field Name : portOperLocalProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.10

Field Name : portOperGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.9

Field Name : portOperDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : disabled
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.8

Field Name : portOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.7

Field Name : portOperServicePort
Field Type : CounterBasedGauge64
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.6

ACOS-GSLB-SERVICE-IP-MIB_oid_list

Field Name : portOperPortProto
Field Type : String
Field Status : current
Description : port-proto
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.4

Field Name : portOperPortNum
Field Type : Integer32
Field Status : current
Description : port-num
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.3

Field Name : portOperNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.2

Field Name : portOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.3.2.1.1

Field Name : serviceIpOperTable
Field Type : TABLE
Field Status : current
Description : ServiceIP from object 'gslb.service-ip'
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2

Field Name : serviceIpOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceIpOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1

Field Name : serviceIpOperDynamic
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.13

Field Name : serviceIpOperUseGslbState
Field Type : CounterBasedGauge64
Field Status : current
Description : use_gslb_state
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.12

Field Name : serviceIpOperManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.11

Field Name : serviceIpOperLocalProtocol
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-SERVICE-IP-MIB_oid_list

Description : local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.10

Field Name : serviceIpOperGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.9

Field Name : serviceIpOperDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : disabled
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.8

Field Name : serviceIpOperVirtualServer
Field Type : CounterBasedGauge64
Field Status : current
Description : virtual-server
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.7

Field Name : serviceIpOperPortCount
Field Type : CounterBasedGauge64
Field Status : current
Description : port-count
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.6

Field Name : serviceIpOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.5

Field Name : serviceIpOperIp
Field Type : String
Field Status : current
Description : ip
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.4

Field Name : serviceIpOperServiceIp
Field Type : String
Field Status : current
Description : service-ip
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.3

Field Name : serviceIpOperNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.2

Field Name : serviceIpOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.2.1.1

ACOS-GSLB-SERVICE-IP-MIB_oid_list

Field Name : serviceIpStatsTable
Field Type : TABLE
Field Status : current
Description : ServiceIP from object 'gslb.service-ip'
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.1

Field Name : serviceIpStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceIpStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.1.1

Field Name : serviceIpStatsRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : recent
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.1.1.4

Field Name : serviceIpStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.1.1.3

Field Name : serviceIpStatsNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.1.1.2

Field Name : serviceIpStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.1.1.1

Field Name : serviceOperTable
Field Type : TABLE
Field Status : current
Description : ServicePort from object 'gslb.service-ip.service'
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2

Field Name : serviceOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1

Field Name : serviceOperDynamic
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.14

Field Name : serviceOperUseGslbState
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-SERVICE-IP-MIB_oid_list

Description : use_gslb_state
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.13

Field Name : serviceOperManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.12

Field Name : serviceOperTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.11

Field Name : serviceOperLocalProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.10

Field Name : serviceOperGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.9

Field Name : serviceOperDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : disabled
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.8

Field Name : serviceOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.7

Field Name : serviceOperServicePort
Field Type : CounterBasedGauge64
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.6

Field Name : serviceOperLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.5

Field Name : serviceOperPortProto
Field Type : String
Field Status : current
Description : port-proto
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.4

ACOS-GSLB-SERVICE-IP-MIB_oid_list

Field Name : serviceOperPortNum
Field Type : Integer32
Field Status : current
Description : port-num
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.3

Field Name : serviceOperNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.2

Field Name : serviceOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.424.1.4.2.1.1

ACOS-GSLB-SERVICE-PORT-MIB_oid_list

Field Name : servicePortOperTable
Field Type : TABLE
Field Status : current
Description : from object 'gslb.service-port'
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2

Field Name : servicePortOperServicePortListTable
Field Type : TABLE
Field Status : current
Description : from object 'gslb.service-port'
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2

Field Name : servicePortOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The servicePortOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1

Field Name : servicePortOperServicePortListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The servicePortOperServicePortList entry:service-port-list
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1

Field Name : servicePortOperServicePortListServiceHcode
Field Type : CounterBasedGauge64
Field Status : current
Description : service-hcode
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.9

Field Name : servicePortOperServicePortListServiceLabel
Field Type : String
Field Status : current
Description : service-label
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.8

Field Name : servicePortOperServicePortListCurrentConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : current-connections
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.7

Field Name : servicePortOperServicePortListActiveRealServer
Field Type : CounterBasedGauge64
Field Status : current
Description : active-real-server
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.6

Field Name : servicePortOperServicePortListState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.5

Field Name : servicePortOperPortCount
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-SERVICE-PORT-MIB_oid_list

Description : port-count

OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.4

Field Name : servicePortOperServicePortListAttributes

Field Type : String

Field Status : current

Description : attributes

OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.4

Field Name : servicePortOperLabel

Field Type : String

Field Status : current

Description : label

OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.3

Field Name : servicePortOperServicePortListServicePortName

Field Type : String

Field Status : current

Description : service-port-name

OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.3

Field Name : servicePortOperServiceHash

Field Type : CounterBasedGauge64

Field Status : current

Description : service-hash

OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.2

Field Name : servicePortOperServicePortListServicePortListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.2

Field Name : servicePortOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.1

Field Name : servicePortOperServicePortListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.434.1.2.1.1

ACOS-GSLB-SITE-MIB_oid_list

Field Name : ipServerOperIpServerPortTable
Field Type : TABLE
Field Status : current
Description : SpecifyARealServerForTheGSLBSite from object 'gslb.site.ip-server'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5

Field Name : ipServerOperDrsListDrsPortTable
Field Type : TABLE
Field Status : current
Description : SpecifyARealServerForTheGSLBSite from object 'gslb.site.ip-server'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4

Field Name : ipServerOperDrsListDrsPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ipServerOperDrsListDrsPort entry:drs-port
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1

Field Name : ipServerOperDrsListDrsPortServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.9

Field Name : ipServerOperDrsListDrsPortVportState
Field Type : String
Field Status : current
Description : vport-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.8

Field Name : ipServerOperDrsListDrsPortVportProtocol
Field Type : String
Field Status : current
Description : vport-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.7

Field Name : ipServerOperDrsListDrsPortVport
Field Type : CounterBasedGauge64
Field Status : current
Description : vport
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.6

Field Name : ipServerOperDrsListDrsPortDrsPortListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.5

Field Name : ipServerOperDrsListDrsPortDrsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.4

Field Name : ipServerOperDrsListDrsPortIpServerName
Field Type : String
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : ip-server-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.3

Field Name : ipServerOperDrsListDrsPortSiteName

Field Type : String

Field Status : current

Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.2

Field Name : ipServerOperDrsListDrsPortSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.4.1.1

Field Name : ipServerOperDrsListTable

Field Type : TABLE

Field Status : current

Description : SpecifyARealServerForTheGSLBSite from object 'gslb.site.ip-server'

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3

Field Name : ipServerOperDrsListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The ipServerOperDrsList entry:drs-list

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1

Field Name : ipServerOperDrsListDrsRecent

Field Type : CounterBasedGauge64

Field Status : current

Description : drs-recent

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.19

Field Name : ipServerOperDrsListDrsHits

Field Type : CounterBasedGauge64

Field Status : current

Description : drs-hits

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.18

Field Name : ipServerOperDrsListDrsDynamic

Field Type : CounterBasedGauge64

Field Status : current

Description : drs-dynamic

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.17

Field Name : ipServerOperDrsListDrsUseGslbState

Field Type : CounterBasedGauge64

Field Status : current

Description : drs-use_gslb_state

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.16

Field Name : ipServerOperDrsListDrsManuallyHealthCheck

Field Type : CounterBasedGauge64

Field Status : current

Description : drs-manually-health-check

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.15

ACOS-GSLB-SITE-MIB_oid_list

Field Name : ipServerOperDrsListDrsLocalProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.14

Field Name : ipServerOperDrsListDrsGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.13

Field Name : ipServerOperDrsListDrsDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-disabled
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.12

Field Name : ipServerOperDrsListDrsVirtualServer
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-virtual-server
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.11

Field Name : ipServerOperDrsListDrsPortCount
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-port-count
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.10

Field Name : ipServerOperDrsListDrsServiceIp
Field Type : String
Field Status : current
Description : drs-service-ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.9

Field Name : ipServerOperDrsListDrsState
Field Type : String
Field Status : current
Description : drs-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.8

Field Name : ipServerOperDrsListDrsFqdnName
Field Type : String
Field Status : current
Description : drs-fqdn-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.7

Field Name : ipServerOperDrsListDrsIpAddress
Field Type : String
Field Status : current
Description : drs-ip-address
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.6

Field Name : ipServerOperDrsListDrsName
Field Type : String
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : drs-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.5

Field Name : ipServerOperDrsListDrsListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.4

Field Name : ipServerOperDrsListIpServerName

Field Type : String

Field Status : current

Description : ip-server-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.3

Field Name : ipServerOperDrsListSiteName

Field Type : String

Field Status : current

Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.2

Field Name : ipServerOperDrsListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.3.1.1

Field Name : ipServerOperTable

Field Type : TABLE

Field Status : current

Description : SpecifyARealServerForTheGSLBSite from object 'gslb.site.ip-server'

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2

Field Name : ipServerOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The ipServerOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1

Field Name : ipServerOperRecent

Field Type : CounterBasedGauge64

Field Status : current

Description : recent

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.18

Field Name : ipServerOperHits

Field Type : CounterBasedGauge64

Field Status : current

Description : hits

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.17

Field Name : ipServerOperDynamic

Field Type : CounterBasedGauge64

Field Status : current

Description : dynamic

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.16

ACOS-GSLB-SITE-MIB_oid_list

Field Name : ipServerOperUseGslbState
Field Type : CounterBasedGauge64
Field Status : current
Description : use_gslb_state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.15

Field Name : ipServerOperManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.14

Field Name : ipServerOperLocalProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.13

Field Name : ipServerOperGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.12

Field Name : ipServerOperDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : disabled
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.11

Field Name : ipServerOperVirtualServer
Field Type : CounterBasedGauge64
Field Status : current
Description : virtual-server
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.10

Field Name : ipServerOperPortCount
Field Type : CounterBasedGauge64
Field Status : current
Description : port-count
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.9

Field Name : ipServerOperServiceIp
Field Type : String
Field Status : current
Description : service-ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.8

Field Name : ipServerOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.7

Field Name : ipServerOperDesc
Field Type : String
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : desc

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.6

Field Name : ipServerOperIpAddress

Field Type : String

Field Status : current

Description : ip-address

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.5

Field Name : ipServerOperIpServer

Field Type : String

Field Status : current

Description : ip-server

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.4

Field Name : ipServerOperIpServerName

Field Type : String

Field Status : current

Description : ip-server-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.3

Field Name : ipServerOperSiteName

Field Type : String

Field Status : current

Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.2

Field Name : ipServerOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.2.1.1

Field Name : ipServerStatsTable

Field Type : TABLE

Field Status : current

Description : SpecifyARealServerForTheGSLBSite from object 'gslb.site.ip-server'

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1

Field Name : ipServerStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The ipServerStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1.1

Field Name : ipServerStatsRecent

Field Type : CounterBasedGauge64

Field Status : current

Description : recent

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1.1.5

Field Name : ipServerStatsHits

Field Type : CounterBasedGauge64

Field Status : current

Description : hits

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1.1.4

ACOS-GSLB-SITE-MIB_oid_list

Field Name : ipServerStatsIpServerName
Field Type : String
Field Status : current
Description : ip-server-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1.1.3

Field Name : ipServerStatsSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1.1.2

Field Name : ipServerStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.1.1.1

Field Name : ipServerOperIpServerPortEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ipServerOperIpServerPort entry:ip-server-port
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1

Field Name : ipServerOperIpServerPortServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.8

Field Name : ipServerOperIpServerPortVportState
Field Type : String
Field Status : current
Description : vport-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.7

Field Name : ipServerOperIpServerPortVportProtocol
Field Type : String
Field Status : current
Description : vport-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.6

Field Name : ipServerOperIpServerPortVport
Field Type : CounterBasedGauge64
Field Status : current
Description : vport
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.5

Field Name : ipServerOperIpServerPortIpServerPortListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.4

Field Name : ipServerOperIpServerPortIpServerName
Field Type : String
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : ip-server-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.3

Field Name : ipServerOperIpServerPortSiteName

Field Type : String

Field Status : current

Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.2

Field Name : ipServerOperIpServerPortSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.5.5.1.1

Field Name : siteOperClientLdnsListTable

Field Type : TABLE

Field Status : current

Description : SpecifyAGSLBsite from object 'gslb.site'

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4

Field Name : siteOperClientLdnsListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The siteOperClientLdnsList entry:client-ldns-list

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1

Field Name : siteOperClientLdnsListRdtSample8

Field Type : CounterBasedGauge64

Field Status : current

Description : rdt-sample8

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.14

Field Name : siteOperClientLdnsListRdtSample7

Field Type : CounterBasedGauge64

Field Status : current

Description : rdt-sample7

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.13

Field Name : siteOperClientLdnsListRdtSample6

Field Type : CounterBasedGauge64

Field Status : current

Description : rdt-sample6

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.12

Field Name : siteOperClientLdnsListRdtSample5

Field Type : CounterBasedGauge64

Field Status : current

Description : rdt-sample5

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.11

Field Name : siteOperClientLdnsListRdtSample4

Field Type : CounterBasedGauge64

Field Status : current

Description : rdt-sample4

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.10

ACOS-GSLB-SITE-MIB_oid_list

Field Name : siteOperClientLdnsListRdtSample3
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample3
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.9

Field Name : siteOperClientLdnsListRdtSample2
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample2
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.8

Field Name : siteOperClientLdnsListRdtSample1
Field Type : CounterBasedGauge64
Field Status : current
Description : rdt-sample1
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.7

Field Name : siteOperClientLdnsListType
Field Type : String
Field Status : current
Description : type
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.6

Field Name : siteOperClientLdnsListAge
Field Type : CounterBasedGauge64
Field Status : current
Description : age
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.5

Field Name : siteOperClientLdnsListClientIp
Field Type : String
Field Status : current
Description : client-ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.4

Field Name : siteOperClientLdnsListClientLdnsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.3

Field Name : siteOperClientLdnsListSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.2

Field Name : siteOperClientLdnsListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.4.1.1

Field Name : siteOperTypeLastTable
Field Type : TABLE
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : SpecifyAGSLBsite from object 'gslb.site'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3

Field Name : siteOperTypeLastEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The siteOperTypeLast entry:type-last
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3.1

Field Name : siteOperTypeLastLast
Field Type : String
Field Status : current
Description : last
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3.1.5

Field Name : siteOperTypeLastType
Field Type : String
Field Status : current
Description : type
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3.1.4

Field Name : siteOperTypeLastTypeLastListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3.1.3

Field Name : siteOperTypeLastSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3.1.2

Field Name : siteOperTypeLastSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.3.1.1

Field Name : siteOperTable
Field Type : TABLE
Field Status : current
Description : SpecifyAGSLBsite from object 'gslb.site'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2

Field Name : siteOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The siteOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1

Field Name : siteOperTotalVipCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total-vip-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.5

ACOS-GSLB-SITE-MIB_oid_list

Field Name : siteOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.4

Field Name : siteOperTime
Field Type : CounterBasedGauge64
Field Status : current
Description : time
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.16

Field Name : siteOperValue
Field Type : CounterBasedGauge64
Field Status : current
Description : value
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.15

Field Name : siteOperLen
Field Type : CounterBasedGauge64
Field Status : current
Description : len
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.14

Field Name : siteOperType
Field Type : String
Field Status : current
Description : type
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.13

Field Name : siteOperUnusable
Field Type : CounterBasedGauge64
Field Status : current
Description : unusable
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.12

Field Name : siteOperLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : limit
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.11

Field Name : siteOperUnlimited
Field Type : CounterBasedGauge64
Field Status : current
Description : unlimited
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.10

Field Name : siteOperHighestCount
Field Type : CounterBasedGauge64
Field Status : current
Description : highest-count
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.9

Field Name : siteOperCurrCount
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : curr-count

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.8

Field Name : siteOperTemplateName

Field Type : String

Field Status : current

Description : template-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.7

Field Name : siteOperGslbSite

Field Type : String

Field Status : current

Description : gslb-site

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.3

Field Name : siteOperBwCost

Field Type : CounterBasedGauge64

Field Status : current

Description : bw-cost

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.6

Field Name : siteOperSiteName

Field Type : String

Field Status : current

Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.2

Field Name : siteOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.2.1.1

Field Name : siteStatsTable

Field Type : TABLE

Field Status : current

Description : SpecifyAGSLBSite from object 'gslb.site'

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.1

Field Name : siteStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The siteStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.1.1

Field Name : siteStatsHits

Field Type : CounterBasedGauge64

Field Status : current

Description : hits

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.1.1.3

Field Name : siteStatsSiteName

Field Type : String

Field Status : current

Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.1.1.2

ACOS-GSLB-SITE-MIB_oid_list

Field Name : siteStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.1.1.1

Field Name : slbDevOperClientLdnsListTable

Field Type : TABLE

Field Status : current

Description : SpecifyASLBDeviceForTheGSLBSite from object 'gslb.site.slb-dev'

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3

Field Name : slbDevOperClientLdnsListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The slbDevOperClientLdnsList entry:client-ldns-list

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1

Field Name : slbDevOperClientLdnsListRdtSample8

Field Type : CounterBasedGauge64

Field Status : current

Description : rdt-sample8

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.15

Field Name : slbDevOperClientLdnsListRdtSample7

Field Type : CounterBasedGauge64

Field Status : current

Description : rdt-sample7

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.14

Field Name : slbDevOperClientLdnsListRdtSample6

Field Type : CounterBasedGauge64

Field Status : current

Description : rdt-sample6

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.13

Field Name : slbDevOperClientLdnsListRdtSample5

Field Type : CounterBasedGauge64

Field Status : current

Description : rdt-sample5

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.12

Field Name : slbDevOperClientLdnsListRdtSample4

Field Type : CounterBasedGauge64

Field Status : current

Description : rdt-sample4

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.11

Field Name : slbDevOperClientLdnsListRdtSample3

Field Type : CounterBasedGauge64

Field Status : current

Description : rdt-sample3

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.10

Field Name : slbDevOperClientLdnsListRdtSample2

Field Type : CounterBasedGauge64

Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : rdt-sample2

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.9

Field Name : slbDevOperClientLdnsListRdtSample1

Field Type : CounterBasedGauge64

Field Status : current

Description : rdt-sample1

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.8

Field Name : slbDevOperClientLdnsListType

Field Type : String

Field Status : current

Description : type

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.7

Field Name : slbDevOperClientLdnsListAge

Field Type : CounterBasedGauge64

Field Status : current

Description : age

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.6

Field Name : slbDevOperClientLdnsListClientIp

Field Type : String

Field Status : current

Description : client-ip

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.5

Field Name : slbDevOperClientLdnsListClientLdnsListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.4

Field Name : slbDevOperClientLdnsListDeviceName

Field Type : String

Field Status : current

Description : device-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.3

Field Name : slbDevOperClientLdnsListSiteName

Field Type : String

Field Status : current

Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.2

Field Name : slbDevOperClientLdnsListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.3.1.1

Field Name : slbDevOperDynamicDevListTable

Field Type : TABLE

Field Status : current

Description : SpecifyASLBDeviceForTheGSLBSite from object 'gslb.site.slb-dev'

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5

ACOS-GSLB-SITE-MIB_oid_list

Field Name : slbDevOperDynVipserverListTable
Field Type : TABLE
Field Status : current
Description : SpecifyASLBDeviceForTheGSLBSite from object 'gslb.site.slb-dev'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5

Field Name : slbDevOperDynVipserverListPortListTable
Field Type : TABLE
Field Status : current
Description : SpecifyASLBDeviceForTheGSLBSite from object 'gslb.site.slb-dev'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5

Field Name : slbDevOperDynamicDevListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slbDevOperDynamicDevList entry:dynamic-dev-list
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1

Field Name : slbDevOperDynVipserverListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slbDevOperDynVipserverList entry:dyn-vipserver-list
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1

Field Name : slbDevOperDynVipserverListPortListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slbDevOperDynVipserverListPortList entry:port-list
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1

Field Name : slbDevOperDynVipserverListPortListPortState
Field Type : String
Field Status : current
Description : port-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.8

Field Name : slbDevOperDynamicDevListDynDevInheritVipserver
Field Type : CounterBasedGauge64
Field Status : current
Description : dyn-dev-inherit-vipserver
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.7

Field Name : slbDevOperDynVipserverListDynSvrHits
Field Type : CounterBasedGauge64
Field Status : current
Description : dyn-svr-hits
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.7

Field Name : slbDevOperDynVipserverListPortListPortProtocol
Field Type : String
Field Status : current
Description : port-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.7

Field Name : slbDevOperDynamicDevListDynDevIp
Field Type : String
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : dyn-dev-ip

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.6

Field Name : slbDevOperDynVipserverListDynSvrState

Field Type : String

Field Status : current

Description : dyn-svr-state

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.6

Field Name : slbDevOperDynVipserverListPortListPortNum

Field Type : CounterBasedGauge64

Field Status : current

Description : port-num

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.6

Field Name : slbDevOperDynamicDevListDynDevName

Field Type : String

Field Status : current

Description : dyn-dev-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.5

Field Name : slbDevOperDynVipserverListDynSvrIp

Field Type : String

Field Status : current

Description : dyn-svr-ip

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.5

Field Name : slbDevOperDynVipserverListPortListPortListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.5

Field Name : slbDevOperDynamicDevListDynamicDevListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.4

Field Name : slbDevOperDynVipserverListDynVipserverListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.4

Field Name : slbDevOperDynVipserverListPortListDynVipserverListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.4

Field Name : slbDevOperDynamicDevListDeviceName

Field Type : String

Field Status : current

Description : device-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.3

ACOS-GSLB-SITE-MIB_oid_list

Field Name : slbDevOperDynVipserverListDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.3

Field Name : slbDevOperDynVipserverListPortListDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.3

Field Name : slbDevOperDynamicDevListSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.2

Field Name : slbDevOperDynVipserverListSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.2

Field Name : slbDevOperDynVipserverListPortListSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.2

Field Name : slbDevOperDynamicDevListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.1

Field Name : slbDevOperDynVipserverListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.1

Field Name : slbDevOperDynVipserverListPortListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.5.1.1

Field Name : slbDevOperTable
Field Type : TABLE
Field Status : current
Description : SpecifyASLBDeviceForTheGSLBSite from object 'gslb.site.slb-dev'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2

Field Name : slbDevOperEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : The slbDevOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1

Field Name : slbDevOperDevCreationType
Field Type : CounterBasedGauge64
Field Status : current
Description : dev-creation-type
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.14

Field Name : slbDevOperDevState
Field Type : String
Field Status : current
Description : dev-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.12

Field Name : slbDevOperDevIpCnt
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_ip_cnt
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.11

Field Name : slbDevOperDevGwState
Field Type : String
Field Status : current
Description : dev_gw_state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.10

Field Name : slbDevOperDevSessionUtil
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_session_util
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.9

Field Name : slbDevOperDevSessionNum
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_session_num
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.8

Field Name : slbDevOperDevAdminPreference
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_admin_preference
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.7

Field Name : slbDevOperDevAttr
Field Type : String
Field Status : current
Description : dev_attr
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.6

Field Name : slbDevOperDevIp
Field Type : String
Field Status : current
Description : dev_ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.5

ACOS-GSLB-SITE-MIB_oid_list

Field Name : slbDevOperDevName
Field Type : String
Field Status : current
Description : dev_name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.4

Field Name : slbDevOperFqdnBased
Field Type : CounterBasedGauge64
Field Status : current
Description : fqdn-based
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.13

Field Name : slbDevOperDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.3

Field Name : slbDevOperSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.2

Field Name : slbDevOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.2.1.1

Field Name : vipServerV6OperDevVipPortListTable
Field Type : TABLE
Field Status : current
Description : SpecifyAVIPForTheSLBDevice from object 'gslb.site.slb-dev.vip-server.vip-server-v6'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3

Field Name : vipServerV6OperTable
Field Type : TABLE
Field Status : current
Description : SpecifyAVIPForTheSLBDevice from object 'gslb.site.slb-dev.vip-server.vip-server-v6'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2

Field Name : vipServerV6OperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vipServerV6Oper entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1

Field Name : vipServerV6OperRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : recent
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.19

Field Name : vipServerV6OperHits
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : hits

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.18

Field Name : vipServerV60perShared

Field Type : CounterBasedGauge64

Field Status : current

Description : shared

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.17

Field Name : vipServerV60perDynamic

Field Type : CounterBasedGauge64

Field Status : current

Description : dynamic

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.16

Field Name : vipServerV60perUseGslbState

Field Type : CounterBasedGauge64

Field Status : current

Description : use_gslb_state

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.15

Field Name : vipServerV60perManuallyHealthCheck

Field Type : CounterBasedGauge64

Field Status : current

Description : manually-health-check

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.14

Field Name : vipServerV60perLocalProtocol

Field Type : CounterBasedGauge64

Field Status : current

Description : local-protocol

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.13

Field Name : vipServerV60perGslbProtocol

Field Type : CounterBasedGauge64

Field Status : current

Description : gslb-protocol

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.12

Field Name : vipServerV60perDisabled

Field Type : CounterBasedGauge64

Field Status : current

Description : disabled

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.11

Field Name : vipServerV60perVirtualServer

Field Type : CounterBasedGauge64

Field Status : current

Description : virtual-server

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.10

Field Name : vipServerV60perPortCount

Field Type : CounterBasedGauge64

Field Status : current

Description : port-count

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.9

ACOS-GSLB-SITE-MIB_oid_list

Field Name : vipServerV6OperServiceIp
Field Type : String
Field Status : current
Description : service-ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.8

Field Name : vipServerV6OperNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.7

Field Name : vipServerV6OperDevVipState
Field Type : String
Field Status : current
Description : dev_vip_state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.6

Field Name : vipServerV6OperDevVipAddr
Field Type : String
Field Status : current
Description : dev_vip_addr
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.5

Field Name : vipServerV6OperIpv6
Field Type : String
Field Status : current
Description : ipv6
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.4

Field Name : vipServerV6OperDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.3

Field Name : vipServerV6OperSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.2

Field Name : vipServerV6OperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.2.1.1

Field Name : vipServerV6StatsTable
Field Type : TABLE
Field Status : current
Description : SpecifyAVIPForTheSLBDevice from object 'gslb.site.slb-dev.vip-server.vip-server-v6'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1

Field Name : vipServerV6StatsEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : The vipServerV6Stats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1

Field Name : vipServerV6StatsDevVipRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_vip_recent
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1.6

Field Name : vipServerV6StatsDevVipHits
Field Type : CounterBasedGauge64
Field Status : current
Description : dev_vip_hits
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1.5

Field Name : vipServerV6StatsIpv6
Field Type : String
Field Status : current
Description : ipv6
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1.4

Field Name : vipServerV6StatsDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1.3

Field Name : vipServerV6StatsSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1.2

Field Name : vipServerV6StatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.1.1.1

Field Name : vipServerV6OperDevVipPortListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vipServerV6OperDevVipPortList entry:dev-vip-port-list
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1

Field Name : vipServerV6OperDevVipPortListDevVipPortServiceName
Field Type : String
Field Status : current
Description : dev-vip-port-service-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.10

Field Name : vipServerV6OperDevVipPortListDevVipPortProtocol
Field Type : String
Field Status : current
Description : dev-vip-port-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.9

ACOS-GSLB-SITE-MIB_oid_list

Field Name : vipServerV60perDevVipPortListDevVipPortDevCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : dev-vip-port-dev-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.8

Field Name : vipServerV60perDevVipPortListDevVipPortState
Field Type : String
Field Status : current
Description : dev-vip-port-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.7

Field Name : vipServerV60perDevVipPortListDevVipPortNum
Field Type : CounterBasedGauge64
Field Status : current
Description : dev-vip-port-num
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.6

Field Name : vipServerV60perDevVipPortListDevVipPortListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.5

Field Name : vipServerV60perDevVipPortListIpv6
Field Type : String
Field Status : current
Description : ipv6
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.4

Field Name : vipServerV60perDevVipPortListDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.3

Field Name : vipServerV60perDevVipPortListSiteName
Field Type : String
Field Status : current
Description : site-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.2

Field Name : vipServerV60perDevVipPortListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.3.3.1.1

Field Name : vipServerV40perDevVipPortListTable
Field Type : TABLE
Field Status : current
Description : SpecifyAVIPForTheSLBDevice from object 'gslb.site.slb-dev.vip-server.vip-server-v4'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3

Field Name : vipServerV40perTable
Field Type : TABLE
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : SpecifyAVIPForTheSLBDevice from object 'gslb.site.slb-dev.vip-server.vip-server-v4'
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2

Field Name : vipServerV40perEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vipServerV40per entry
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1

Field Name : vipServerV40perRecent
Field Type : CounterBasedGauge64
Field Status : current
Description : recent
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.19

Field Name : vipServerV40perHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.18

Field Name : vipServerV40perShared
Field Type : CounterBasedGauge64
Field Status : current
Description : shared
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.17

Field Name : vipServerV40perDynamic
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.16

Field Name : vipServerV40perUseGslbState
Field Type : CounterBasedGauge64
Field Status : current
Description : use_gslb_state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.15

Field Name : vipServerV40perManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.14

Field Name : vipServerV40perLocalProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.13

Field Name : vipServerV40perGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.12

ACOS-GSLB-SITE-MIB_oid_list

Field Name : vipServerV40perDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : disabled
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.11

Field Name : vipServerV40perVirtualServer
Field Type : CounterBasedGauge64
Field Status : current
Description : virtual-server
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.10

Field Name : vipServerV40perPortCount
Field Type : CounterBasedGauge64
Field Status : current
Description : port-count
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.9

Field Name : vipServerV40perServiceIp
Field Type : String
Field Status : current
Description : service-ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.8

Field Name : vipServerV40perNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.7

Field Name : vipServerV40perDevVipState
Field Type : String
Field Status : current
Description : dev_vip_state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.6

Field Name : vipServerV40perDevVipAddr
Field Type : String
Field Status : current
Description : dev_vip_addr
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.5

Field Name : vipServerV40perIpv4
Field Type : String
Field Status : current
Description : ipv4
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.4

Field Name : vipServerV40perDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.3

Field Name : vipServerV40perSiteName
Field Type : String
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.2

Field Name : vipServerV4OperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.2.1.1

Field Name : vipServerV4StatsTable

Field Type : TABLE

Field Status : current

Description : SpecifyAVIPForTheSLBDevice from object 'gslb.site.slb-dev.vip-server.vip-server-v4'

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1

Field Name : vipServerV4StatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The vipServerV4Stats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1

Field Name : vipServerV4StatsDevVipRecent

Field Type : CounterBasedGauge64

Field Status : current

Description : dev_vip_recent

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1.6

Field Name : vipServerV4StatsDevVipHits

Field Type : CounterBasedGauge64

Field Status : current

Description : dev_vip_hits

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1.5

Field Name : vipServerV4StatsIpv4

Field Type : String

Field Status : current

Description : ipv4

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1.4

Field Name : vipServerV4StatsDeviceName

Field Type : String

Field Status : current

Description : device-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1.3

Field Name : vipServerV4StatsSiteName

Field Type : String

Field Status : current

Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1.2

Field Name : vipServerV4StatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.1.1.1

ACOS-GSLB-SITE-MIB_oid_list

Field Name : vipServerV40perDevVipPortListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vipServerV40perDevVipPortList entry:dev-vip-port-list
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1

Field Name : vipServerV40perDevVipPortListDevVipPortServiceName
Field Type : String
Field Status : current
Description : dev-vip-port-service-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.10

Field Name : vipServerV40perDevVipPortListDevVipPortProtocol
Field Type : String
Field Status : current
Description : dev-vip-port-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.9

Field Name : vipServerV40perDevVipPortListDevVipPortDevCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : dev-vip-port-dev-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.8

Field Name : vipServerV40perDevVipPortListDevVipPortState
Field Type : String
Field Status : current
Description : dev-vip-port-state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.7

Field Name : vipServerV40perDevVipPortListDevVipPortNum
Field Type : CounterBasedGauge64
Field Status : current
Description : dev-vip-port-num
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.6

Field Name : vipServerV40perDevVipPortListDevVipPortListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.5

Field Name : vipServerV40perDevVipPortListIpv4
Field Type : String
Field Status : current
Description : ipv4
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.4

Field Name : vipServerV40perDevVipPortListDeviceName
Field Type : String
Field Status : current
Description : device-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.3

Field Name : vipServerV40perDevVipPortListSiteName
Field Type : String
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.2

Field Name : vipServerV4OperDevVipPortListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.2.3.1.1

Field Name : vipServerNameOperDevVipPortListTable

Field Type : TABLE

Field Status : current

Description : SpecifyAVIPForTheSLBDevice from object 'gslb.site.slb-dev.vip-server.vip-server-name'

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3

Field Name : vipServerNameOperTable

Field Type : TABLE

Field Status : current

Description : SpecifyAVIPForTheSLBDevice from object 'gslb.site.slb-dev.vip-server.vip-server-name'

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2

Field Name : vipServerNameOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The vipServerNameOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1

Field Name : vipServerNameOperRecent

Field Type : CounterBasedGauge64

Field Status : current

Description : recent

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.19

Field Name : vipServerNameOperHits

Field Type : CounterBasedGauge64

Field Status : current

Description : hits

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.18

Field Name : vipServerNameOperShared

Field Type : CounterBasedGauge64

Field Status : current

Description : shared

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.17

Field Name : vipServerNameOperDynamic

Field Type : CounterBasedGauge64

Field Status : current

Description : dynamic

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.16

Field Name : vipServerNameOperUseGslbState

Field Type : CounterBasedGauge64

Field Status : current

Description : use_gslb_state

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.15

ACOS-GSLB-SITE-MIB_oid_list

Field Name : vipServerNameOperManuallyHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : manually-health-check
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.14

Field Name : vipServerNameOperLocalProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : local-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.13

Field Name : vipServerNameOperGslbProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : gslb-protocol
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.12

Field Name : vipServerNameOperDisabled
Field Type : CounterBasedGauge64
Field Status : current
Description : disabled
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.11

Field Name : vipServerNameOperVirtualServer
Field Type : CounterBasedGauge64
Field Status : current
Description : virtual-server
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.10

Field Name : vipServerNameOperPortCount
Field Type : CounterBasedGauge64
Field Status : current
Description : port-count
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.9

Field Name : vipServerNameOperServiceIp
Field Type : String
Field Status : current
Description : service-ip
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.8

Field Name : vipServerNameOperNodeName
Field Type : String
Field Status : current
Description : node-name
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.7

Field Name : vipServerNameOperDevVipState
Field Type : String
Field Status : current
Description : dev_vip_state
OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.6

Field Name : vipServerNameOperDevVipAddr
Field Type : String
Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description : dev_vip_addr

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.5

Field Name : vipServerNameOperVipName

Field Type : String

Field Status : current

Description : vip-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.4

Field Name : vipServerNameOperDeviceName

Field Type : String

Field Status : current

Description : device-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.3

Field Name : vipServerNameOperSiteName

Field Type : String

Field Status : current

Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.2

Field Name : vipServerNameOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.2.1.1

Field Name : vipServerNameStatsTable

Field Type : TABLE

Field Status : current

Description : SpecifyAVIPForTheSLBDevice from object 'gslb.site.slb-dev.vip-server.vip-server-name'

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1

Field Name : vipServerNameStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The vipServerNameStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1

Field Name : vipServerNameStatsDevVipRecent

Field Type : CounterBasedGauge64

Field Status : current

Description : dev_vip_recent

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1.6

Field Name : vipServerNameStatsDevVipHits

Field Type : CounterBasedGauge64

Field Status : current

Description : dev_vip_hits

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1.5

Field Name : vipServerNameStatsVipName

Field Type : String

Field Status : current

Description : vip-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1.4

ACOS-GSLB-SITE-MIB_oid_list

Field Name : vipServerNameStatsDeviceName

Field Type : String

Field Status : current

Description : device-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1.3

Field Name : vipServerNameStatsSiteName

Field Type : String

Field Status : current

Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1.2

Field Name : vipServerNameStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.1.1.1

Field Name : vipServerNameOperDevVipPortListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The vipServerNameOperDevVipPortList entry:dev-vip-port-list

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1

Field Name : vipServerNameOperDevVipPortListDevVipPortServiceName

Field Type : String

Field Status : current

Description : dev-vip-port-service-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.10

Field Name : vipServerNameOperDevVipPortListDevVipPortProtocol

Field Type : String

Field Status : current

Description : dev-vip-port-protocol

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.9

Field Name : vipServerNameOperDevVipPortListDevVipPortDevCurrConn

Field Type : CounterBasedGauge64

Field Status : current

Description : dev-vip-port-dev-curr-conn

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.8

Field Name : vipServerNameOperDevVipPortListDevVipPortState

Field Type : String

Field Status : current

Description : dev-vip-port-state

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.7

Field Name : vipServerNameOperDevVipPortListDevVipPortNum

Field Type : CounterBasedGauge64

Field Status : current

Description : dev-vip-port-num

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.6

Field Name : vipServerNameOperDevVipPortListDevVipPortListListId

Field Type : Integer32

Field Status : current

ACOS-GSLB-SITE-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.5

Field Name : vipServerNameOperDevVipPortListVipName

Field Type : String

Field Status : current

Description : vip-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.4

Field Name : vipServerNameOperDevVipPortListDeviceName

Field Type : String

Field Status : current

Description : device-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.3

Field Name : vipServerNameOperDevVipPortListSiteName

Field Type : String

Field Status : current

Description : site-name

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.2

Field Name : vipServerNameOperDevVipPortListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.426.1.8.4.4.3.1.1

ACOS-GSLB-STATISTICS-MIB_oid_list

Field Name : statisticsOperTable
Field Type : TABLE
Field Status : current
Description : GSLBGlobalStats from object 'gslb.statistics'
OID : 1.3.6.1.4.1.22610.2.4.8.422.1.2

Field Name : statisticsOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statisticsOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.422.1.2.1

Field Name : statisticsOperCurrSslCtx
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-ssl-ctx
OID : 1.3.6.1.4.1.22610.2.4.8.422.1.2.1.2

Field Name : statisticsOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.422.1.2.1.1

ACOS-GSLB-STATS-MIB_acosGslb_oid_list

Field Name : gslbSiteSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.119.9.1.1

Field Name : gslbSiteSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.119.9.1.1.1

Field Name : gslbSiteHits

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of times the site was selected

OID : 1.3.6.1.4.1.22610.2.4.10.119.9.1.1.1.2

Field Name : siteName

Field Type : String

Field Status : current

Description : Specify GSLB site name

OID : 1.3.6.1.4.1.22610.2.4.10.119.9.1.1.1.1

Field Name : gslbServiceIpSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.119.4.1.1

Field Name : gslbServiceIpSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.119.4.1.1.1

Field Name : recent

Field Type : CounterBasedGauge64

Field Status : current

Description : Recent hits

OID : 1.3.6.1.4.1.22610.2.4.10.119.4.1.1.1.3

Field Name : gslbServiceIpHits

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of times the service IP has been selected

OID : 1.3.6.1.4.1.22610.2.4.10.119.4.1.1.1.2

Field Name : nodeName

Field Type : String

Field Status : current

Description : Service-IP Name

OID : 1.3.6.1.4.1.22610.2.4.10.119.4.1.1.1.1

Field Name : metricSiteConnectionCount

Field Type : CounterBasedGauge64

Field Status : current

ACOS-GSLB-STATS-MIB_acosGslb_oid_list

Description : Metric Connection Count by Site Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.34

Field Name : metricRoundRobin
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Round Robin Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.33

Field Name : metricAdminIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Admin IP Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.32

Field Name : metricLeastReponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Least Reponse Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.31

Field Name : metricUser
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric User Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.30

Field Name : metricBandwidthCost
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Bandwidth Cost Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.29

Field Name : metricBandwidthQuality
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Bandwidth Quality Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.28

Field Name : metricAdminPreference
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Admin Preference Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.27

Field Name : metricActiveWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Active Weight Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.26

Field Name : metricNumberOfSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Number of Sessions Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.25

ACOS-GSLB-STATS-MIB_acosGslb_oid_list

Field Name : metricConnectionLoad
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Connection Load Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.24

Field Name : metricGeographic
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Geographic Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.23

Field Name : metricActiveRdt
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Active RDT Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.22

Field Name : metricEasyRdt
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Easy RDT Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.21

Field Name : metricActiveServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Active Server Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.20

Field Name : metricCapacity
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Capacity Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.19

Field Name : metricWeightedSite
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Weighted Site Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.18

Field Name : metricWeightedIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Weighted IP Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.17

Field Name : metricHealthCheck
Field Type : CounterBasedGauge64
Field Status : current
Description : Metric Health Check Hit
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.16

Field Name : noAnswer
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-STATS-MIB_acosGslb_oid_list

Description : Number of replies with unknown server IP
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.15

Field Name : badTypeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of replies with incorrect type
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.14

Field Name : badTypeQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries with incorrect type
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.13

Field Name : badClassResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of replies with incorrect class
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.12

Field Name : badClassQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries with incorrect class
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.11

Field Name : badServiceResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of replies with unknown service
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.10

Field Name : badServiceQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries with unknown service
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.9

Field Name : badFormatResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of replies with incorrect format
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.8

Field Name : badFormatQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries with incorrect format
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.7

Field Name : badHeaderResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of replies with incorrect header
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.6

ACOS-GSLB-STATS-MIB_acosGslb_oid_list

Field Name : badHeaderQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries with incorrect header
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.5

Field Name : badPacketResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of replies with incorrect data length
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.4

Field Name : badPacketQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries with incorrect data length
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.3

Field Name : totalResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of DNS replies sent to clients
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.2

Field Name : totalQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of DNS queries received
OID : 1.3.6.1.4.1.22610.2.4.10.119.3.1.1

Field Name : gslbZoneSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1

Field Name : gslbZoneSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1

Field Name : smrRuleRedirFromSvcMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS queries redirected by rule (originally missed service)
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.10

Field Name : smrRuleRedirFromSvcHit
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS queries redirected by rule (originally hit a service)
OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.9

Field Name : backupModeResponse
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-STATS-MIB_acosGslb_oid_list

Description : DNS replies sent by ACOS in backup mode

OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.8

Field Name : stickyModeResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : DNS replies sent by ACOS on same site (if sticky enabled)

OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.7

Field Name : serverModeResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : DNS replies sent by ACOS as DNS server (if DNS server enabled)

OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.6

Field Name : cacheModeResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : Cached DNS replies sent by ACOS (if DNS cache enabled)

OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.5

Field Name : proxyModeResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : DNS replies sent by ACOS as DNS proxy

OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.4

Field Name : sentResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : DNS replies sent to clients for the zone

OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.3

Field Name : receivedQuery

Field Type : CounterBasedGauge64

Field Status : current

Description : DNS queries received for the zone

OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.2

Field Name : name

Field Type : String

Field Status : current

Description : Specify the name for the DNS zone

OID : 1.3.6.1.4.1.22610.2.4.10.119.11.1.1.1.1

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : dnsCaaRecordOperTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSCAAREcord from object 'gslb.zone.dns-caa-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2

Field Name : dnsCaaRecordStatsTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSCAAREcord from object 'gslb.zone.dns-caa-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1

Field Name : dnsCaaRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCaaRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1

Field Name : dnsCaaRecordStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1.6

Field Name : dnsCaaRecordStatsRdata
Field Type : String
Field Status : current
Description : rdata
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1.5

Field Name : dnsCaaRecordStatsPropertyTag
Field Type : String
Field Status : current
Description : property-tag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1.4

Field Name : dnsCaaRecordStatsCriticalFlag
Field Type : Integer32
Field Status : current
Description : critical-flag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1.3

Field Name : dnsCaaRecordStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1.2

Field Name : dnsCaaRecordStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.1.1.1

Field Name : dnsCaaRecordOperEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-ZONE-MIB_oid_list

Description : The dnsCaaRecordOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1

Field Name : dnsCaaRecordOperLastServer
Field Type : String
Field Status : current
Description : last-server
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1.6

Field Name : dnsCaaRecordOperRdata
Field Type : String
Field Status : current
Description : rdata
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1.5

Field Name : dnsCaaRecordOperPropertyTag
Field Type : String
Field Status : current
Description : property-tag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1.4

Field Name : dnsCaaRecordOperCriticalFlag
Field Type : Integer32
Field Status : current
Description : critical-flag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1.3

Field Name : dnsCaaRecordOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1.2

Field Name : dnsCaaRecordOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.6.2.1.1

Field Name : dnsNsRecordOperTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSNSRecord from object 'gslb.zone.dns-ns-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2

Field Name : dnsNsRecordStatsTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSNSRecord from object 'gslb.zone.dns-ns-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.1

Field Name : dnsNsRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsNsRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.1.1

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : dnsNsRecordStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.1.1.4

Field Name : dnsNsRecordStatsNsName
Field Type : String
Field Status : current
Description : ns-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.1.1.3

Field Name : dnsNsRecordStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.1.1.2

Field Name : dnsNsRecordStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.1.1.1

Field Name : dnsNsRecordOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsNsRecordOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2.1

Field Name : dnsNsRecordOperHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2.1.5

Field Name : dnsNsRecordOperLastServer
Field Type : String
Field Status : current
Description : last-server
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2.1.4

Field Name : dnsNsRecordOperNsName
Field Type : String
Field Status : current
Description : ns-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2.1.3

Field Name : dnsNsRecordOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2.1.2

Field Name : dnsNsRecordOperSlotId
Field Type : Integer32
Field Status : current

ACOS-GSLB-ZONE-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.5.2.1.1

Field Name : dnsMxRecordOperTable

Field Type : TABLE

Field Status : current

Description : SpecifyDNSMXRecord from object 'gslb.zone.dns-mx-record'

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2

Field Name : dnsMxRecordStatsTable

Field Type : TABLE

Field Status : current

Description : SpecifyDNSMXRecord from object 'gslb.zone.dns-mx-record'

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.1

Field Name : dnsMxRecordStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The dnsMxRecordStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.1.1

Field Name : dnsMxRecordStatsHits

Field Type : CounterBasedGauge64

Field Status : current

Description : hits

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.1.1.4

Field Name : dnsMxRecordStatsMxName

Field Type : String

Field Status : current

Description : mx-name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.1.1.3

Field Name : dnsMxRecordStatsName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.1.1.2

Field Name : dnsMxRecordStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.1.1.1

Field Name : dnsMxRecordOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The dnsMxRecordOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1

Field Name : dnsMxRecordOperPriority

Field Type : CounterBasedGauge64

Field Status : current

Description : priority

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1.6

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : dnsMxRecordOperHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1.5

Field Name : dnsMxRecordOperLastServer
Field Type : String
Field Status : current
Description : last-server
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1.4

Field Name : dnsMxRecordOperMxName
Field Type : String
Field Status : current
Description : mx-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1.3

Field Name : dnsMxRecordOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1.2

Field Name : dnsMxRecordOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.4.2.1.1

Field Name : zoneOperDnsSoaRecordListTable
Field Type : TABLE
Field Status : current
Description : SpecifyTheDNSZoneNameForWhichGlobalSLBIsProvided from object 'gslb.zone'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3

Field Name : zoneOperDnsSoaRecordListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The zoneOperDnsSoaRecordList entry:dns-soa-record-list
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1

Field Name : zoneOperDnsSoaRecordListMxName
Field Type : String
Field Status : current
Description : mx-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.11

Field Name : zoneOperDnsSoaRecordListTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : ttl
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.10

Field Name : zoneOperDnsSoaRecordListRetry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-ZONE-MIB_oid_list

Description : retry

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.9

Field Name : zoneOperDnsSoaRecordListSerial

Field Type : CounterBasedGauge64

Field Status : current

Description : serial

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.8

Field Name : zoneOperDnsSoaRecordListRefresh

Field Type : CounterBasedGauge64

Field Status : current

Description : refresh

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.7

Field Name : zoneOperDnsSoaRecordListExpire

Field Type : CounterBasedGauge64

Field Status : current

Description : expire

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.6

Field Name : zoneOperDnsSoaRecordListType

Field Type : String

Field Status : current

Description : type

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.5

Field Name : zoneOperDnsSoaRecordListName1

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.4

Field Name : zoneOperDnsSoaRecordListDnsSoaRecordListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.3

Field Name : zoneOperDnsSoaRecordListName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.2

Field Name : zoneOperDnsSoaRecordListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.3.1.1

Field Name : zoneOperTable

Field Type : TABLE

Field Status : current

Description : SpecifyTheDNSZoneNameForWhichGlobalSLBIsProvided from object 'gslb.zone'

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.2

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : zoneOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The zoneOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.2.1

Field Name : zoneOperSmrule
Field Type : Integer32
Field Status : current
Description : smrule
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.2.1.4

Field Name : zoneOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.2.1.3

Field Name : zoneOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.2.1.2

Field Name : zoneOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.2.1.1

Field Name : zoneStatsTable
Field Type : TABLE
Field Status : current
Description : SpecifyTheDNSZoneNameForWhichGlobalSLBIsProvided from object 'gslb.zone'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1

Field Name : zoneStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The zoneStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1

Field Name : zoneStatsSmruleRedirFromSvcMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : smrule-redir-from-svc-miss
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.11

Field Name : zoneStatsSmruleRedirFromSvcHit
Field Type : CounterBasedGauge64
Field Status : current
Description : smrule-redir-from-svc-hit
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.10

Field Name : zoneStatsBackupModeResponse
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-ZONE-MIB_oid_list

Description : backup-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.9

Field Name : zoneStatsStickyModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : sticky-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.8

Field Name : zoneStatsServerModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : server-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.7

Field Name : zoneStatsCacheModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : cache-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.6

Field Name : zoneStatsProxyModeResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy-mode-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.5

Field Name : zoneStatsSentResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : sent-response
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.4

Field Name : zoneStatsReceivedQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : received-query
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.3

Field Name : zoneStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.2

Field Name : zoneStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.1.1.1

Field Name : dnsCaaRecordServiceStatsTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSCAAREcord from object 'gslb.zone.service.dns-caa-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : dnsCaaRecordServiceStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCaaRecordServiceStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1

Field Name : dnsCaaRecordServiceStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.8

Field Name : dnsCaaRecordServiceStatsRdata
Field Type : String
Field Status : current
Description : rdata
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.7

Field Name : dnsCaaRecordServiceStatsPropertyTag
Field Type : String
Field Status : current
Description : property-tag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.6

Field Name : dnsCaaRecordServiceStatsCriticalFlag
Field Type : Integer32
Field Status : current
Description : critical-flag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.5

Field Name : dnsCaaRecordServiceStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.4

Field Name : dnsCaaRecordServiceStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.3

Field Name : dnsCaaRecordServiceStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.2

Field Name : dnsCaaRecordServiceStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.14.1.1.1

Field Name : dnsTxtRecordStatsTable
Field Type : TABLE
Field Status : current

ACOS-GSLB-ZONE-MIB_oid_list

Description : SpecifyDNSTXTRecord from object 'gslb.zone.service.dns-txt-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1

Field Name : dnsTxtRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsTxtRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1

Field Name : dnsTxtRecordStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1.6

Field Name : dnsTxtRecordStatsRecordName
Field Type : String
Field Status : current
Description : record-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1.5

Field Name : dnsTxtRecordStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1.4

Field Name : dnsTxtRecordStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1.3

Field Name : dnsTxtRecordStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1.2

Field Name : dnsTxtRecordStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.13.1.1.1

Field Name : dnsNaptrRecordStatsTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSNAPTRRecord from object 'gslb.zone.service.dns-naptr-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1

Field Name : dnsNaptrRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsNaptrRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : dnsNaptrRecordStatsNaptrHits
Field Type : CounterBasedGauge64
Field Status : current
Description : naptr-hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.8

Field Name : dnsNaptrRecordStatsFlag
Field Type : String
Field Status : current
Description : flag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.7

Field Name : dnsNaptrRecordStatsServiceProto
Field Type : String
Field Status : current
Description : service-proto
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.6

Field Name : dnsNaptrRecordStatsNaptrTarget
Field Type : String
Field Status : current
Description : naptr-target
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.5

Field Name : dnsNaptrRecordStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.4

Field Name : dnsNaptrRecordStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.3

Field Name : dnsNaptrRecordStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.2

Field Name : dnsNaptrRecordStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.12.1.1.1

Field Name : dnsSrvRecordStatsTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSSRVRecord from object 'gslb.zone.service.dns-srv-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1

Field Name : dnsSrvRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-ZONE-MIB_oid_list

Description : The dnsSrvRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1

Field Name : dnsSrvRecordStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.7

Field Name : dnsSrvRecordStatsPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.6

Field Name : dnsSrvRecordStatsSrvName
Field Type : String
Field Status : current
Description : srv-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.5

Field Name : dnsSrvRecordStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.4

Field Name : dnsSrvRecordStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.3

Field Name : dnsSrvRecordStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.2

Field Name : dnsSrvRecordStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.11.1.1.1

Field Name : dnsPtrRecordStatsTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSPTRRecord from object 'gslb.zone.service.dns-ptr-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1

Field Name : dnsPtrRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsPtrRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : dnsPtrRecordStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1.6

Field Name : dnsPtrRecordStatsPtrName
Field Type : String
Field Status : current
Description : ptr-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1.5

Field Name : dnsPtrRecordStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1.4

Field Name : dnsPtrRecordStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1.3

Field Name : dnsPtrRecordStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1.2

Field Name : dnsPtrRecordStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.10.1.1.1

Field Name : dnsNsRecordServiceOperTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSNSRecord from object 'gslb.zone.service.dns-ns-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2

Field Name : dnsNsRecordServiceStatsTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSNSRecord from object 'gslb.zone.service.dns-ns-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1

Field Name : dnsNsRecordServiceStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsNsRecordServiceStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1

Field Name : dnsNsRecordServiceStatsHits
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-ZONE-MIB_oid_list

Description : hits

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1.6

Field Name : dnsNsRecordServiceStatsNsName

Field Type : String

Field Status : current

Description : ns-name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1.5

Field Name : dnsNsRecordServiceStatsServiceName

Field Type : String

Field Status : current

Description : service-name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1.4

Field Name : dnsNsRecordServiceStatsServicePort

Field Type : Integer32

Field Status : current

Description : service-port

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1.3

Field Name : dnsNsRecordServiceStatsName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1.2

Field Name : dnsNsRecordServiceStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.1.1.1

Field Name : dnsNsRecordServiceOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The dnsNsRecordServiceOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1

Field Name : dnsNsRecordServiceOperHits

Field Type : CounterBasedGauge64

Field Status : current

Description : hits

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.7

Field Name : dnsNsRecordServiceOperLastServer

Field Type : String

Field Status : current

Description : last-server

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.6

Field Name : dnsNsRecordServiceOperNsName

Field Type : String

Field Status : current

Description : ns-name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.5

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : dnsNsRecordServiceOperServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.4

Field Name : dnsNsRecordServiceOperServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.3

Field Name : dnsNsRecordServiceOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.2

Field Name : dnsNsRecordServiceOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.9.2.1.1

Field Name : dnsMxRecordServiceOperTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSMXRecord from object 'gslb.zone.service.dns-mx-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2

Field Name : dnsMxRecordServiceStatsTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSMXRecord from object 'gslb.zone.service.dns-mx-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1

Field Name : dnsMxRecordServiceStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsMxRecordServiceStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1

Field Name : dnsMxRecordServiceStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1.6

Field Name : dnsMxRecordServiceStatsMxName
Field Type : String
Field Status : current
Description : mx-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1.5

Field Name : dnsMxRecordServiceStatsServiceName
Field Type : String
Field Status : current

ACOS-GSLB-ZONE-MIB_oid_list

Description : service-name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1.4

Field Name : dnsMxRecordServiceStatsServicePort

Field Type : Integer32

Field Status : current

Description : service-port

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1.3

Field Name : dnsMxRecordServiceStatsName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1.2

Field Name : dnsMxRecordServiceStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.1.1.1

Field Name : dnsMxRecordServiceOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The dnsMxRecordServiceOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1

Field Name : dnsMxRecordServiceOperPriority

Field Type : CounterBasedGauge64

Field Status : current

Description : priority

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.8

Field Name : dnsMxRecordServiceOperHits

Field Type : CounterBasedGauge64

Field Status : current

Description : hits

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.7

Field Name : dnsMxRecordServiceOperLastServer

Field Type : String

Field Status : current

Description : last-server

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.6

Field Name : dnsMxRecordServiceOperMxName

Field Type : String

Field Status : current

Description : mx-name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.5

Field Name : dnsMxRecordServiceOperServiceName

Field Type : String

Field Status : current

Description : service-name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.4

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : dnsMxRecordServiceOperServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.3

Field Name : dnsMxRecordServiceOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.2

Field Name : dnsMxRecordServiceOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.8.2.1.1

Field Name : dnsCNameRecordStatsTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSCNAMERecord from object 'gslb.zone.service.dns-cname-record'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1

Field Name : dnsCNameRecordStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCNameRecordStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1

Field Name : dnsCNameRecordStatsCnameHits
Field Type : CounterBasedGauge64
Field Status : current
Description : cname-hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1.6

Field Name : dnsCNameRecordStatsAliasName
Field Type : String
Field Status : current
Description : alias-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1.5

Field Name : dnsCNameRecordStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1.4

Field Name : dnsCNameRecordStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1.3

Field Name : dnsCNameRecordStatsName
Field Type : String
Field Status : current

ACOS-GSLB-ZONE-MIB_oid_list

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1.2

Field Name : dnsCNameRecordStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.7.1.1.1

Field Name : dnsARecordIpv4StatsTable

Field Type : TABLE

Field Status : current

Description : SpecifyDNSAddressRecord from object 'gslb.zone.service.dns-a-record.dns-a-record-ipv4'

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1

Field Name : dnsARecordIpv4StatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The dnsARecordIpv4Stats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1

Field Name : dnsARecordIpv4StatsHits

Field Type : CounterBasedGauge64

Field Status : current

Description : hits

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1.6

Field Name : dnsARecordIpv4StatsIp

Field Type : String

Field Status : current

Description : dns-a-record-ip

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1.5

Field Name : dnsARecordIpv4StatsServiceName

Field Type : String

Field Status : current

Description : service-name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1.4

Field Name : dnsARecordIpv4StatsServicePort

Field Type : Integer32

Field Status : current

Description : service-port

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1.3

Field Name : dnsARecordIpv4StatsName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1.2

Field Name : dnsARecordIpv4StatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.3.1.1.1

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : dnsARecordSrvStatsTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSAddressRecord from object 'gslb.zone.service.dns-a-record.dns-a-record-srv'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1

Field Name : dnsARecordSrvStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsARecordSrvStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1

Field Name : dnsARecordSrvStatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1.6

Field Name : dnsARecordSrvStatsSvrname
Field Type : String
Field Status : current
Description : svrname
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1.5

Field Name : dnsARecordSrvStatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1.4

Field Name : dnsARecordSrvStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1.3

Field Name : dnsARecordSrvStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1.2

Field Name : dnsARecordSrvStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.2.1.1.1

Field Name : dnsARecordIpv6StatsTable
Field Type : TABLE
Field Status : current
Description : SpecifyDNSAddressRecord from object 'gslb.zone.service.dns-a-record.dns-a-record-ipv6'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1

Field Name : dnsARecordIpv6StatsEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-ZONE-MIB_oid_list

Description : The dnsARecordIpv6Stats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1

Field Name : dnsARecordIpv6StatsHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1.6

Field Name : dnsARecordIpv6StatsIpv6
Field Type : String
Field Status : current
Description : dns-a-record-ipv6
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1.5

Field Name : dnsARecordIpv6StatsServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1.4

Field Name : dnsARecordIpv6StatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1.3

Field Name : dnsARecordIpv6StatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1.2

Field Name : dnsARecordIpv6StatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.6.4.1.1.1

Field Name : serviceOperDnsARecordListTable
Field Type : TABLE
Field Status : current
Description : ServiceInformationForTheGSLBZone from object 'gslb.zone.service'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5

Field Name : serviceOperDnsARecordListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperDnsARecordList entry:dns-a-record-list
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1

Field Name : serviceOperDnsARecordListRecTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : rec-ttl
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.7

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : serviceOperDnsARecordListIp
Field Type : String
Field Status : current
Description : ip
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.6

Field Name : serviceOperDnsARecordListDnsARecordListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.5

Field Name : serviceOperDnsARecordListServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.4

Field Name : serviceOperDnsARecordListServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.3

Field Name : serviceOperDnsARecordListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.2

Field Name : serviceOperDnsARecordListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.5.1.1

Field Name : serviceOperSessionListTable
Field Type : TABLE
Field Status : current
Description : ServiceInformationForTheGSLBZone from object 'gslb.zone.service'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4

Field Name : serviceOperSessionListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperSessionList entry:session-list
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1

Field Name : serviceOperSessionListAging
Field Type : CounterBasedGauge64
Field Status : current
Description : aging
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.13

Field Name : serviceOperSessionListUpdate
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-ZONE-MIB_oid_list

Description : update

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.12

Field Name : serviceOperSessionListTtl

Field Type : String

Field Status : current

Description : ttl

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.11

Field Name : serviceOperSessionListLastSecondHits

Field Type : CounterBasedGauge64

Field Status : current

Description : last-second-hits

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.10

Field Name : serviceOperSessionListHits

Field Type : CounterBasedGauge64

Field Status : current

Description : hits

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.9

Field Name : serviceOperSessionListMode

Field Type : String

Field Status : current

Description : mode

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.8

Field Name : serviceOperSessionListBest

Field Type : String

Field Status : current

Description : best

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.7

Field Name : serviceOperSessionListClient

Field Type : String

Field Status : current

Description : client

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.6

Field Name : serviceOperSessionListSessionListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.5

Field Name : serviceOperSessionListServiceName

Field Type : String

Field Status : current

Description : service-name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.4

Field Name : serviceOperSessionListServicePort

Field Type : Integer32

Field Status : current

Description : service-port

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.3

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : serviceOperSessionListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.2

Field Name : serviceOperSessionListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.4.1.1

Field Name : serviceOperCacheListTable
Field Type : TABLE
Field Status : current
Description : ServiceInformationForTheGSLBZone from object 'gslb.zone.service'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3

Field Name : serviceOperCacheListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperCacheList entry:cache-list
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1

Field Name : serviceOperCacheListAdditionalRecords
Field Type : CounterBasedGauge64
Field Status : current
Description : additional-records
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.13

Field Name : serviceOperCacheListAuthorityRecords
Field Type : CounterBasedGauge64
Field Status : current
Description : authority-records
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.12

Field Name : serviceOperCacheListAnswerRecords
Field Type : CounterBasedGauge64
Field Status : current
Description : answer-records
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.11

Field Name : serviceOperCacheListQuestionRecords
Field Type : CounterBasedGauge64
Field Status : current
Description : question-records
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.10

Field Name : serviceOperCacheListCacheDnsFlag
Field Type : String
Field Status : current
Description : cache-dns-flag
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.9

Field Name : serviceOperCacheListCacheTtl
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-ZONE-MIB_oid_list

Description : cache-ttl

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.8

Field Name : serviceOperCacheListCacheLength

Field Type : CounterBasedGauge64

Field Status : current

Description : cache-length

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.7

Field Name : serviceOperCacheListAlias

Field Type : String

Field Status : current

Description : alias

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.6

Field Name : serviceOperCacheListCacheListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.5

Field Name : serviceOperCacheListServiceName

Field Type : String

Field Status : current

Description : service-name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.4

Field Name : serviceOperCacheListServicePort

Field Type : Integer32

Field Status : current

Description : service-port

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.3

Field Name : serviceOperCacheListName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.2

Field Name : serviceOperCacheListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.3.1.1

Field Name : serviceOperTable

Field Type : TABLE

Field Status : current

Description : ServiceInformationForTheGSLBZone from object 'gslb.zone.service'

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2

Field Name : serviceOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The serviceOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : serviceOperTotalSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : total-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.7

Field Name : serviceOperMatched
Field Type : CounterBasedGauge64
Field Status : current
Description : matched
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.6

Field Name : serviceOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.5

Field Name : serviceOperServiceName
Field Type : String
Field Status : current
Description : service-name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.4

Field Name : serviceOperServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.3

Field Name : serviceOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.2

Field Name : serviceOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.2.1.1

Field Name : serviceStatsTable
Field Type : TABLE
Field Status : current
Description : ServiceInformationForTheGSLBZone from object 'gslb.zone.service'
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1

Field Name : serviceStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1

Field Name : serviceStatsSmruleRedirFromSvcMiss
Field Type : CounterBasedGauge64
Field Status : current

ACOS-GSLB-ZONE-MIB_oid_list

Description : smrule-redir-from-svc-miss

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.13

Field Name : serviceStatsSmruleRedirFromSvcHit

Field Type : CounterBasedGauge64

Field Status : current

Description : smrule-redir-from-svc-hit

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.12

Field Name : serviceStatsBackupModeResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : backup-mode-response

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.11

Field Name : serviceStatsStickyModeResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : sticky-mode-response

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.10

Field Name : serviceStatsServerModeResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : server-mode-response

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.9

Field Name : serviceStatsCacheModeResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : cache-mode-response

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.8

Field Name : serviceStatsProxyModeResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : proxy-mode-response

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.7

Field Name : serviceStatsSentResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : sent-response

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.6

Field Name : serviceStatsReceivedQuery

Field Type : CounterBasedGauge64

Field Status : current

Description : received-query

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.5

Field Name : serviceStatsServiceName

Field Type : String

Field Status : current

Description : service-name

OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.4

ACOS-GSLB-ZONE-MIB_oid_list

Field Name : serviceStatsServicePort
Field Type : Integer32
Field Status : current
Description : service-port
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.3

Field Name : serviceStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.2

Field Name : serviceStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.428.1.7.1.1.1

ACOS-HEALTH-STATS-MIB_acosHealth_oid_list

Field Name : fragErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.17

Field Name : natResourceErr
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT resource error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.16

Field Name : smartNatRserverIpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Smart NAT rserver ip update error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.15

Field Name : smartNatRserverRouteErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Smart NAT rserver route update error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.14

Field Name : smartNatInitInstErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Smart NAT instance initialization error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.13

Field Name : smartNatInitPortErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Smart NAT port initialization error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.12

Field Name : noSlbObject
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB object not found
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.11

Field Name : dcmsgErr
Field Type : CounterBasedGauge64
Field Status : current
Description : DCMSG error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.10

Field Name : sbyNoPeer
Field Type : CounterBasedGauge64
Field Status : current
Description : Peer not found on standby
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.9

Field Name : sendToKernelErr
Field Type : CounterBasedGauge64
Field Status : current

ACOS-HEALTH-STATS-MIB_acosHealth_oid_list

Description : Packets sent to kernel error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.8

Field Name : sendToKernel
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets sent to kernel
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.7

Field Name : recvFromKernel
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets received from kernel
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.6

Field Name : sbyRecvFromActErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets received from active error
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.5

Field Name : sbySendToAct
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets sent to active
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.4

Field Name : sbyRecvFromAct
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets received from active
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.3

Field Name : actSendToSby
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets sent to standby
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.2

Field Name : actRecvFromSby
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets received from standby
OID : 1.3.6.1.4.1.22610.2.4.10.100.4.1.1

ACOS-INTERFACE-AVAILABLE-ETH-LIST-MIB_oid_list

Field Name : availableEthListOperIfListTable
Field Type : TABLE
Field Status : current
Description : ListOfEthernetInterfacesAvailableInAPartition from object 'interface.available-eth-list'
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3

Field Name : availableEthListOperTable
Field Type : TABLE
Field Status : current
Description : ListOfEthernetInterfacesAvailableInAPartition from object 'interface.available-eth-list'
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.2

Field Name : availableEthListOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The availableEthListOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.2.1

Field Name : availableEthListOperTotNumOfPorts
Field Type : CounterBasedGauge64
Field Status : current
Description : tot_num_of_ports
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.2.1.2

Field Name : availableEthListOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.2.1.1

Field Name : availableEthListOperIfListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The availableEthListOperIfList entry:if-list
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1

Field Name : availableEthListOperIfListState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1.6

Field Name : availableEthListOperIfListIFStatus
Field Type : String
Field Status : current
Description : IF-Status
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1.5

Field Name : availableEthListOperIfListIFNum
Field Type : CounterBasedGauge64
Field Status : current
Description : IF-Num
OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1.4

Field Name : availableEthListOperIfListIFType
Field Type : String
Field Status : current

ACOS-INTERFACE-AVAILABLE-ETH-LIST-MIB_oid_list

Description : IF-Type

OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1.3

Field Name : availableEthListOperIfListIfListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1.2

Field Name : availableEthListOperIfListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.190.1.3.1.1

ACOS-INTERFACE-BRIEF-MIB_oid_list

Field Name : briefOperInterfacesTable
Field Type : TABLE
Field Status : current
Description : InterfaceStatisticsInformation from object 'interface.brief'
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2

Field Name : briefOperInterfacesEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The briefOperInterfaces entry:interfaces
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1

Field Name : briefOperInterfacesUnnumberedOper
Field Type : String
Field Status : current
Description : unnumbered_oper
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.18

Field Name : briefOperInterfacesIntfName
Field Type : String
Field Status : current
Description : intf_name
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.17

Field Name : briefOperInterfacesIpv6Prefix
Field Type : String
Field Status : current
Description : ipv6_prefix
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.16

Field Name : briefOperInterfacesIpv6Addr
Field Type : String
Field Status : current
Description : ipv6_addr
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.15

Field Name : briefOperInterfacesIpv6AddrCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_addr_count
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.14

Field Name : briefOperInterfacesIpv4Mask
Field Type : String
Field Status : current
Description : ipv4_mask
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.13

Field Name : briefOperInterfacesIpv4Addr
Field Type : String
Field Status : current
Description : ipv4_addr
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.12

Field Name : briefOperInterfacesIpv4AddrCount
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-BRIEF-MIB_oid_list

Description : ipv4_addr_count
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.11

Field Name : briefOperInterfacesMac
Field Type : String
Field Status : current
Description : mac
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.10

Field Name : briefOperInterfacesState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.9

Field Name : briefOperInterfacesEncapInfo
Field Type : String
Field Status : current
Description : encap_info
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.8

Field Name : briefOperInterfacesVlanInfo
Field Type : String
Field Status : current
Description : vlan_info
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.7

Field Name : briefOperInterfacesTrunkGroup
Field Type : String
Field Status : current
Description : trunk_group
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.6

Field Name : briefOperInterfacesDuplexity
Field Type : String
Field Status : current
Description : duplexity
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.5

Field Name : briefOperInterfacesSpeed
Field Type : String
Field Status : current
Description : speed
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.4

Field Name : briefOperInterfacesPortNum
Field Type : String
Field Status : current
Description : port_num
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.3

Field Name : briefOperInterfacesInterfacesListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.2

ACOS-INTERFACE-BRIEF-MIB_oid_list

Field Name : briefOperInterfacesSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.201.1.2.1.1

ACOS-INTERFACE-COMMON-MIB_oid_list

Field Name : commonOperInterfacesTransceiversInfoTable
Field Type : TABLE
Field Status : current
Description : InterfaceStatisticsInformation from object 'interface.common'
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.4

Field Name : commonOperInterfacesTable
Field Type : TABLE
Field Status : current
Description : InterfaceStatisticsInformation from object 'interface.common'
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3

Field Name : commonOperInterfacesEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The commonOperInterfaces entry:interfaces
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1

Field Name : commonOperInterfacesTotalLane
Field Type : CounterBasedGauge64
Field Status : current
Description : total_lane
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.14

Field Name : commonOperInterfacesTypeVendorPart
Field Type : String
Field Status : current
Description : type_vendor_part
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.13

Field Name : commonOperInterfacesOutputUtilization
Field Type : CounterBasedGauge64
Field Status : current
Description : output-utilization
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.12

Field Name : commonOperInterfacesInputUtilization
Field Type : CounterBasedGauge64
Field Status : current
Description : input-utilization
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.11

Field Name : commonOperInterfacesRateByteRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : rate-byte-rcvd
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.10

Field Name : commonOperInterfacesRatePktRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : rate-pkt-rcvd
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.9

Field Name : commonOperInterfacesRateByteSent
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-COMMON-MIB_oid_list

Description : rate-byte-sent

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.8

Field Name : commonOperInterfacesRatePktSent

Field Type : CounterBasedGauge64

Field Status : current

Description : rate-pkt-sent

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.7

Field Name : commonOperInterfacesSpanTree

Field Type : String

Field Status : current

Description : span-tree

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.6

Field Name : commonOperInterfacesIsPartDefaultVlan

Field Type : String

Field Status : current

Description : is_part_default_vlan

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.5

Field Name : commonOperInterfacesPortType

Field Type : String

Field Status : current

Description : port-type

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.4

Field Name : commonOperInterfacesPortNum

Field Type : String

Field Status : current

Description : port-num

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.3

Field Name : commonOperInterfacesInterfacesListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.2

Field Name : commonOperInterfacesSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.3.1.1

Field Name : commonOperTable

Field Type : TABLE

Field Status : current

Description : InterfaceStatisticsInformation from object 'interface.common'

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.2

Field Name : commonOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The commonOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.2.1

ACOS-INTERFACE-COMMON-MIB_oid_list

Field Name : commonOperTotNumPhyIntf
Field Type : CounterBasedGauge64
Field Status : current
Description : tot_num_phy_intf
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.2.1.5

Field Name : commonOperVnpId
Field Type : CounterBasedGauge64
Field Status : current
Description : vnp_id
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.2.1.4

Field Name : commonOperInterval
Field Type : CounterBasedGauge64
Field Status : current
Description : interval
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.2.1.3

Field Name : commonOperTime
Field Type : String
Field Status : current
Description : time
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.2.1.2

Field Name : commonOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.2.1.1

Field Name : commonOperInterfacesTransceiversInfoEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The commonOperInterfacesTransceiversInfo entry:transceivers_info
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.4.1

Field Name : commonOperInterfacesTransceiversInfoLoAlarm
Field Type : String
Field Status : current
Description : lo_alarm
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.4.1.10

Field Name : commonOperInterfacesTransceiversInfoLoWarn
Field Type : String
Field Status : current
Description : lo_warn
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.4.1.9

Field Name : commonOperInterfacesTransceiversInfoHiWarn
Field Type : String
Field Status : current
Description : hi_warn
OID : 1.3.6.1.4.1.22610.2.4.8.200.1.4.1.8

Field Name : commonOperInterfacesTransceiversInfoHiAlarm
Field Type : String
Field Status : current

ACOS-INTERFACE-COMMON-MIB_oid_list

Description : hi_alarm

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.4.1.7

Field Name : commonOperInterfacesTransceiversInfoCurr

Field Type : String

Field Status : current

Description : curr

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.4.1.6

Field Name : commonOperInterfacesTransceiversInfoLane

Field Type : CounterBasedGauge64

Field Status : current

Description : lane

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.4.1.5

Field Name : commonOperInterfacesTransceiversInfoTransceiverType

Field Type : String

Field Status : current

Description : transceiver-type

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.4.1.4

Field Name : commonOperInterfacesTransceiversInfoTransceiversInfoListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.4.1.3

Field Name : commonOperInterfacesTransceiversInfoInterfacesListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.4.1.2

Field Name : commonOperInterfacesTransceiversInfoSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.200.1.4.1.1

ACOS-INTERFACE-ETHERNET-MIB_oid_list

Field Name : ethernetOperIpv6ListTable
Field Type : TABLE
Field Status : current
Description : EthernetInterface from object 'interface.ethernet'
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4

Field Name : ethernetOperIpv6ListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ethernetOperIpv6List entry:ipv6_list
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1

Field Name : ethernetOperIpv6ListIsAnycast
Field Type : CounterBasedGauge64
Field Status : current
Description : is_anycast
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1.6

Field Name : ethernetOperIpv6ListPrefix
Field Type : String
Field Status : current
Description : prefix
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1.5

Field Name : ethernetOperIpv6ListAddr
Field Type : String
Field Status : current
Description : addr
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1.4

Field Name : ethernetOperIpv6ListIpv6ListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1.3

Field Name : ethernetOperIpv6ListIfnum
Field Type : Integer32
Field Status : current
Description : ifnum
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1.2

Field Name : ethernetOperIpv6ListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.4.1.1

Field Name : ethernetOperIpv4ListTable
Field Type : TABLE
Field Status : current
Description : EthernetInterface from object 'interface.ethernet'
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3

Field Name : ethernetOperIpv4ListEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-ETHERNET-MIB_oid_list

Description : The ethernetOperIpv4List entry:ipv4_list

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3.1

Field Name : ethernetOperIpv4ListMask

Field Type : String

Field Status : current

Description : mask

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3.1.5

Field Name : ethernetOperIpv4ListAddr

Field Type : String

Field Status : current

Description : addr

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3.1.4

Field Name : ethernetOperIpv4ListIpv4ListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3.1.3

Field Name : ethernetOperIpv4ListIfnum

Field Type : Integer32

Field Status : current

Description : ifnum

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3.1.2

Field Name : ethernetOperIpv4ListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.3.1.1

Field Name : ethernetOperTable

Field Type : TABLE

Field Status : current

Description : EthernetInterface from object 'interface.ethernet'

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2

Field Name : ethernetOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The ethernetOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1

Field Name : ethernetOperLastDownEventAt

Field Type : String

Field Status : current

Description : last_down_event_at

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.52

Field Name : ethernetOperLastUpEventAt

Field Type : String

Field Status : current

Description : last_up_event_at

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.51

ACOS-INTERFACE-ETHERNET-MIB_oid_list

Field Name : ethernetOperLastCountClearAt
Field Type : String
Field Status : current
Description : last_count_clear_at
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.50

Field Name : ethernetOperIpUnnumberedPeerLla
Field Type : String
Field Status : current
Description : ip_unnumbered_peer_lls
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.49

Field Name : ethernetOperIpUnnumberedMacLearned
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_unnumbered_mac_learned
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.48

Field Name : ethernetOperIpUnnumberedEnabled
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_unnumbered_enabled
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.47

Field Name : ethernetOperIpUnnumberedOper
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_unnumbered_oper
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.46

Field Name : ethernetOperOutgoingPktsMonitored
Field Type : CounterBasedGauge64
Field Status : current
Description : outgoing_pkts_monitored
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.45

Field Name : ethernetOperIncomingPktsMonitored
Field Type : CounterBasedGauge64
Field Status : current
Description : incoming_pkts_monitored
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.44

Field Name : ethernetOperOutgoingPktsMirrored
Field Type : CounterBasedGauge64
Field Status : current
Description : outgoing_pkts_mirrored
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.43

Field Name : ethernetOperIncomingPktsMirrored
Field Type : CounterBasedGauge64
Field Status : current
Description : incoming_pkts_mirrored
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.42

Field Name : ethernetOperIsDeviceTransparent
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-ETHERNET-MIB_oid_list

Description : is_device_transparent
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.41

Field Name : ethernetOperOutputUtilization
Field Type : CounterBasedGauge64
Field Status : current
Description : output_utilization
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.40

Field Name : ethernetOperInputUtilization
Field Type : CounterBasedGauge64
Field Status : current
Description : input_utilization
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.39

Field Name : ethernetOperRatePktSent
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_pkt_sent
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.38

Field Name : ethernetOperRatePktRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_pkt_rcvd
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.37

Field Name : ethernetOperRateByteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_byte_sent
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.36

Field Name : ethernetOperRateByteRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_byte_rcvd
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.35

Field Name : ethernetOperIsPristine
Field Type : CounterBasedGauge64
Field Status : current
Description : is_pristine
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.34

Field Name : ethernetOperPortVnpId
Field Type : CounterBasedGauge64
Field Status : current
Description : port_vnp_id
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.33

Field Name : ethernetOperCurrentVnpId
Field Type : CounterBasedGauge64
Field Status : current
Description : current_vnp_id
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.32

ACOS-INTERFACE-ETHERNET-MIB_oid_list

Field Name : ethernetOperIsBlocked
Field Type : CounterBasedGauge64
Field Status : current
Description : is_blocked
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.31

Field Name : ethernetOperIsLeadMember
Field Type : CounterBasedGauge64
Field Status : current
Description : is_lead_member
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.30

Field Name : ethernetOperSpanPortState
Field Type : String
Field Status : current
Description : span_port_state
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.29

Field Name : ethernetOperSpanMode
Field Type : String
Field Status : current
Description : span_mode
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.28

Field Name : ethernetOperTaggedVlanList
Field Type : String
Field Status : current
Description : tagged-vlan-list
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.27

Field Name : ethernetOperVlanId
Field Type : CounterBasedGauge64
Field Status : current
Description : vlan-id
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.26

Field Name : ethernetOperIsTagged
Field Type : CounterBasedGauge64
Field Status : current
Description : is-tagged
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.25

Field Name : ethernetOperIcmp6RateOverLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp6-rate-over-limit-drop
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.24

Field Name : ethernetOperIcmp6RateLimitCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp6-rate-limit-current
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.23

Field Name : ethernetOperIcmpRateOverLimitDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-ETHERNET-MIB_oid_list

Description : icmp-rate-over-limit-drop
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.22

Field Name : ethernetOperIcmpRateLimitCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-rate-limit-current
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.21

Field Name : ethernetOperIgmpQuerySent
Field Type : CounterBasedGauge64
Field Status : current
Description : igmp-query-sent
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.20

Field Name : ethernetOperIpv6LinkLocalScope
Field Type : String
Field Status : current
Description : ipv6-link-local-scope
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.19

Field Name : ethernetOperIpv6LinkLocalType
Field Type : String
Field Status : current
Description : ipv6-link-local-type
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.18

Field Name : ethernetOperIpv6LinkLocalPrefix
Field Type : String
Field Status : current
Description : ipv6-link-local-prefix
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.17

Field Name : ethernetOperIpv6LinkLocal
Field Type : String
Field Status : current
Description : ipv6-link-local
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.16

Field Name : ethernetOperIpv6AddrCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_addr_count
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.15

Field Name : ethernetOperIpv4AddrCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4_addr_count
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.14

Field Name : ethernetOperIpv4Netmask
Field Type : String
Field Status : current
Description : ipv4-netmask
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.13

ACOS-INTERFACE-ETHERNET-MIB_oid_list

Field Name : ethernetOperIpv4Address
Field Type : String
Field Status : current
Description : ipv4-address
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.12

Field Name : ethernetOperMediaType
Field Type : String
Field Status : current
Description : media_type
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.11

Field Name : ethernetOperActualDuplexity
Field Type : String
Field Status : current
Description : actual_duplexity
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.10

Field Name : ethernetOperConfigDuplexity
Field Type : String
Field Status : current
Description : config_duplexity
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.9

Field Name : ethernetOperActualSpeed
Field Type : String
Field Status : current
Description : actual_speed
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.8

Field Name : ethernetOperConfigSpeed
Field Type : String
Field Status : current
Description : config_speed
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.7

Field Name : ethernetOperMac
Field Type : String
Field Status : current
Description : mac
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.6

Field Name : ethernetOperLinkType
Field Type : String
Field Status : current
Description : link_type
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.5

Field Name : ethernetOperLineProtocol
Field Type : String
Field Status : current
Description : line_protocol
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.4

Field Name : ethernetOperState
Field Type : String
Field Status : current

ACOS-INTERFACE-ETHERNET-MIB_oid_list

Description : state

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.3

Field Name : ethernetOperIfnum

Field Type : Integer32

Field Status : current

Description : ifnum

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.2

Field Name : ethernetOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.2.1.1

Field Name : ethernetStatsTable

Field Type : TABLE

Field Status : current

Description : EthernetInterface from object 'interface.ethernet'

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1

Field Name : ethernetStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The ethernetStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1

Field Name : ethernetStatsOutputUtilization

Field Type : CounterBasedGauge64

Field Status : current

Description : output_utilization

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.29

Field Name : ethernetStatsInputUtilization

Field Type : CounterBasedGauge64

Field Status : current

Description : input_utilization

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.28

Field Name : ethernetStatsReceiveDrops

Field Type : CounterBasedGauge64

Field Status : current

Description : receive_drops

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.27

Field Name : ethernetStatsTransmitDrops

Field Type : CounterBasedGauge64

Field Status : current

Description : transmit_drops

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.26

Field Name : ethernetStatsLoadInterval

Field Type : CounterBasedGauge64

Field Status : current

Description : load_interval

OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.25

ACOS-INTERFACE-ETHERNET-MIB_oid_list

Field Name : ethernetStatsRateByteRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_byte_rcvd
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.24

Field Name : ethernetStatsRatePktRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_pkt_rcvd
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.23

Field Name : ethernetStatsRateByteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_byte_sent
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.22

Field Name : ethernetStatsRatePktSent
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_pkt_sent
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.21

Field Name : ethernetStatsGiantsOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : giants_output
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.20

Field Name : ethernetStatsCollisions
Field Type : CounterBasedGauge64
Field Status : current
Description : collisions
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.19

Field Name : ethernetStatsOutputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : output_errors
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.18

Field Name : ethernetStatsTransmittedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : transmitted_unicasts
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.17

Field Name : ethernetStatsTransmittedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : transmitted_multicasts
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.16

Field Name : ethernetStatsTransmittedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-ETHERNET-MIB_oid_list

Description : transmitted_broadcasts
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.15

Field Name : ethernetStatsBytesOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : bytes_output
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.14

Field Name : ethernetStatsPacketsOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : packets_output
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.13

Field Name : ethernetStatsGiants
Field Type : CounterBasedGauge64
Field Status : current
Description : giants
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.12

Field Name : ethernetStatsRunts
Field Type : CounterBasedGauge64
Field Status : current
Description : runts
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.11

Field Name : ethernetStatsFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : frame
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.10

Field Name : ethernetStatsCrc
Field Type : CounterBasedGauge64
Field Status : current
Description : crc
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.9

Field Name : ethernetStatsInputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : input_errors
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.8

Field Name : ethernetStatsReceivedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : received_unicasts
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.7

Field Name : ethernetStatsReceivedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : received_multicasts
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.6

ACOS-INTERFACE-ETHERNET-MIB_oid_list

Field Name : ethernetStatsReceivedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : received_broadcasts
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.5

Field Name : ethernetStatsBytesInput
Field Type : CounterBasedGauge64
Field Status : current
Description : bytes_input
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.4

Field Name : ethernetStatsPacketsInput
Field Type : CounterBasedGauge64
Field Status : current
Description : packets_input
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.3

Field Name : ethernetStatsIfnum
Field Type : Integer32
Field Status : current
Description : ifnum
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.2

Field Name : ethernetStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.189.1.1.1.1

ACOS-INTERFACE-MANAGEMENT-MIB_oid_list

Field Name : managementOperTable
Field Type : TABLE
Field Status : current
Description : ManagementInterface from object 'interface.management'
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2

Field Name : managementOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The managementOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1

Field Name : managementOperDhcpEnabled
Field Type : CounterBasedGauge64
Field Status : current
Description : dhcp_enabled
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.21

Field Name : managementOperIpv6Acl
Field Type : String
Field Status : current
Description : ipv6_acl
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.20

Field Name : managementOperIpv4Acl
Field Type : String
Field Status : current
Description : ipv4_acl
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.19

Field Name : managementOperFlowControl
Field Type : CounterBasedGauge64
Field Status : current
Description : flow_control
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.18

Field Name : managementOperMtu
Field Type : CounterBasedGauge64
Field Status : current
Description : mtu
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.17

Field Name : managementOperDuplexity
Field Type : String
Field Status : current
Description : duplexity
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.16

Field Name : managementOperSpeed
Field Type : String
Field Status : current
Description : speed
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.15

Field Name : managementOperIpv6DefaultGateway
Field Type : String
Field Status : current

ACOS-INTERFACE-MANAGEMENT-MIB_oid_list

Description : ipv6-default-gateway
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.14

Field Name : managementOperIpv6LinkLocalPrefix
Field Type : String
Field Status : current
Description : ipv6-link-local-prefix
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.13

Field Name : managementOperIpv6LinkLocal
Field Type : String
Field Status : current
Description : ipv6-link-local
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.12

Field Name : managementOperIpv6Prefix
Field Type : String
Field Status : current
Description : ipv6-prefix
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.11

Field Name : managementOperIpv6Addr
Field Type : String
Field Status : current
Description : ipv6-addr
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.10

Field Name : managementOperIpv4DefaultGateway
Field Type : String
Field Status : current
Description : ipv4-default-gateway
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.9

Field Name : managementOperIpv4Mask
Field Type : String
Field Status : current
Description : ipv4-mask
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.8

Field Name : managementOperIpv4Addr
Field Type : String
Field Status : current
Description : ipv4-addr
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.7

Field Name : managementOperMac
Field Type : String
Field Status : current
Description : mac
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.6

Field Name : managementOperLinkType
Field Type : String
Field Status : current
Description : link_type
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.5

ACOS-INTERFACE-MANAGEMENT-MIB_oid_list

Field Name : managementOperLineProtocol
Field Type : String
Field Status : current
Description : line_protocol
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.4

Field Name : managementOperState
Field Type : CounterBasedGauge64
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.3

Field Name : managementOperInterface
Field Type : String
Field Status : current
Description : interface
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.2

Field Name : managementOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.2.1.1

Field Name : managementStatsTable
Field Type : TABLE
Field Status : current
Description : ManagementInterface from object 'interface.management'
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1

Field Name : managementStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The managementStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1

Field Name : managementStatsCollisions
Field Type : CounterBasedGauge64
Field Status : current
Description : collisions
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.18

Field Name : managementStatsOutputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : output_errors
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.17

Field Name : managementStatsTransmittedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : transmitted_unicasts
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.16

Field Name : managementStatsTransmittedMulticasts
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-MANAGEMENT-MIB_oid_list

Description : transmitted_multicasts
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.15

Field Name : managementStatsTransmittedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : transmitted_broadcasts
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.14

Field Name : managementStatsBytesOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : bytes_output
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.13

Field Name : managementStatsPacketsOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : packets_output
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.12

Field Name : managementStatsInputErrLong
Field Type : CounterBasedGauge64
Field Status : current
Description : input_err_long
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.11

Field Name : managementStatsInputErrShort
Field Type : CounterBasedGauge64
Field Status : current
Description : input_err_short
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.10

Field Name : managementStatsFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : frame
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.9

Field Name : managementStatsCrc
Field Type : CounterBasedGauge64
Field Status : current
Description : crc
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.8

Field Name : managementStatsInputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : input_errors
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.7

Field Name : managementStatsReceivedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : received_unicasts
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.6

ACOS-INTERFACE-MANAGEMENT-MIB_oid_list

Field Name : managementStatsReceivedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : received_multicasts
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.5

Field Name : managementStatsReceivedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : received_broadcasts
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.4

Field Name : managementStatsBytesInput
Field Type : CounterBasedGauge64
Field Status : current
Description : bytes_input
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.3

Field Name : managementStatsPacketsInput
Field Type : CounterBasedGauge64
Field Status : current
Description : packets_input
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.2

Field Name : managementStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.187.1.1.1.1

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Field Name : interfaceLifSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1

Field Name : interfaceLifSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1

Field Name : droppedRxPktsGreKey
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.16

Field Name : droppedTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.15

Field Name : droppedDisTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.14

Field Name : droppedRxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.13

Field Name : droppedDisRxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.12

Field Name : lifNumMulticastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.11

Field Name : lifNumBroadcastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.10

Field Name : lifNumUnicastTxPkts
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.9

Field Name : lifNumTotalTxBytes

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.8

Field Name : lifNumTxPkts

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.7

Field Name : lifNumMulticastPkts

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.6

Field Name : lifNumBroadcastPkts

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.5

Field Name : lifNumUnicastPkts

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.4

Field Name : lifNumTotalBytes

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.3

Field Name : lifNumPkts

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.2

Field Name : lifIfName

Field Type : String

Field Status : current

Description : Lif interface name

OID : 1.3.6.1.4.1.22610.2.4.10.95.7.1.1.1.1

Field Name : interfaceVeSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Field Name : interfaceVeSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1

Field Name : loadInterval
Field Type : CounterBasedGauge64
Field Status : current
Description : Load Interval
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.16

Field Name : rateByteRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Byte received rate bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.15

Field Name : ratePktRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet received rate packets/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.14

Field Name : rateByteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Byte sent rate bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.13

Field Name : ratePktSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet sent rate packets/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.12

Field Name : numMulticastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.11

Field Name : numBroadcastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.10

Field Name : numUnicastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.9

Field Name : numTotalTxBytes
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Description : Transmitted bytes

OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.8

Field Name : numTxPkts

Field Type : CounterBasedGauge64

Field Status : current

Description : Transmitted packets

OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.7

Field Name : numMulticastPkts

Field Type : CounterBasedGauge64

Field Status : current

Description : Received multicasts

OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.6

Field Name : numBroadcastPkts

Field Type : CounterBasedGauge64

Field Status : current

Description : Received broadcasts

OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.5

Field Name : numUnicastPkts

Field Type : CounterBasedGauge64

Field Status : current

Description : Received unicasts

OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.4

Field Name : numTotalBytes

Field Type : CounterBasedGauge64

Field Status : current

Description : Input bytes

OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.3

Field Name : numPkts

Field Type : CounterBasedGauge64

Field Status : current

Description : Input packets

OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.2

Field Name : veIfNum

Field Type : INTEGER

Field Status : current

Description : Virtual ethernet interface number

OID : 1.3.6.1.4.1.22610.2.4.10.95.5.1.1.1.1

Field Name : interfaceTrunkSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1

Field Name : interfaceTrunkSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Field Name : droppedTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.15

Field Name : droppedDisTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.14

Field Name : droppedRxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.13

Field Name : droppedDisRxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.12

Field Name : numMulticastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.11

Field Name : numBroadcastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.10

Field Name : numUnicastTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.9

Field Name : numTotalTxBytes
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.8

Field Name : numTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.7

Field Name : numMulticastPkts
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.6

Field Name : numBroadcastPkts

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.5

Field Name : numUnicastPkts

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.4

Field Name : numTotalBytes

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.3

Field Name : numPkts

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.2

Field Name : ifnum

Field Type : INTEGER

Field Status : current

Description : Trunk interface number

OID : 1.3.6.1.4.1.22610.2.4.10.95.4.1.1.1.1

Field Name : interfaceEthernetSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1

Field Name : interfaceEthernetSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1

Field Name : outputUtilization

Field Type : CounterBasedGauge64

Field Status : current

Description : Output Utilization

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.28

Field Name : inputUtilization

Field Type : CounterBasedGauge64

Field Status : current

Description : Input Utilization

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.27

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Field Name : receiveDrops
Field Type : CounterBasedGauge64
Field Status : current
Description : Receive Drops
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.26

Field Name : transmitDrops
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmit Drops
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.25

Field Name : loadInterval
Field Type : CounterBasedGauge64
Field Status : current
Description : Load Interval
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.24

Field Name : rateByteRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Byte received rate bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.23

Field Name : ratePktRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet received rate packets/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.22

Field Name : rateByteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Byte sent rate bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.21

Field Name : ratePktSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet sent rate packets/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.20

Field Name : giantsOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : Output Giants
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.19

Field Name : collisions
Field Type : CounterBasedGauge64
Field Status : current
Description : Collisions
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.18

Field Name : outputErrors
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Description : Output errors

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.17

Field Name : transmittedUnicasts

Field Type : CounterBasedGauge64

Field Status : current

Description : Transmitted unicasts

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.16

Field Name : transmittedMulticasts

Field Type : CounterBasedGauge64

Field Status : current

Description : Transmitted multicasts

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.15

Field Name : transmittedBroadcasts

Field Type : CounterBasedGauge64

Field Status : current

Description : Transmitted broadcasts

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.14

Field Name : bytesOutput

Field Type : CounterBasedGauge64

Field Status : current

Description : Output bytes

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.13

Field Name : packetsOutput

Field Type : CounterBasedGauge64

Field Status : current

Description : Output packets

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.12

Field Name : giants

Field Type : CounterBasedGauge64

Field Status : current

Description : Giants

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.11

Field Name : runts

Field Type : CounterBasedGauge64

Field Status : current

Description : Runts

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.10

Field Name : frame

Field Type : CounterBasedGauge64

Field Status : current

Description : Frames

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.9

Field Name : crc

Field Type : CounterBasedGauge64

Field Status : current

Description : CRC

OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.8

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Field Name : inputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Input errors
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.7

Field Name : receivedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.6

Field Name : receivedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.5

Field Name : receivedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.4

Field Name : bytesInput
Field Type : CounterBasedGauge64
Field Status : current
Description : Input bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.3

Field Name : packetsInput
Field Type : CounterBasedGauge64
Field Status : current
Description : Input packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.2

Field Name : ifnum
Field Type : String
Field Status : current
Description : Ethernet interface number
OID : 1.3.6.1.4.1.22610.2.4.10.95.2.1.1.1.1

Field Name : collisions
Field Type : CounterBasedGauge64
Field Status : current
Description : Collisions
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.17

Field Name : outputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Output errors
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.16

Field Name : transmittedUnicasts
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Description : Transmitted unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.15

Field Name : transmittedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.14

Field Name : transmittedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.13

Field Name : bytesOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : Output bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.12

Field Name : packetsOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : Output packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.11

Field Name : inputErrLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Giants
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.10

Field Name : inputErrShort
Field Type : CounterBasedGauge64
Field Status : current
Description : Runts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.9

Field Name : frame
Field Type : CounterBasedGauge64
Field Status : current
Description : Frames
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.8

Field Name : crc
Field Type : CounterBasedGauge64
Field Status : current
Description : CRC
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.7

Field Name : inputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Input errors
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.6

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Field Name : receivedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.5

Field Name : receivedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.4

Field Name : receivedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.3

Field Name : bytesInput
Field Type : CounterBasedGauge64
Field Status : current
Description : Input bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.2

Field Name : packetsInput
Field Type : CounterBasedGauge64
Field Status : current
Description : Input packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.15.1.1

Field Name : collisions
Field Type : CounterBasedGauge64
Field Status : current
Description : Collisions
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.17

Field Name : outputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Output errors
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.16

Field Name : transmittedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.15

Field Name : transmittedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Transmitted multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.14

Field Name : transmittedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Description : Transmitted broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.13

Field Name : bytesOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : Output bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.12

Field Name : packetsOutput
Field Type : CounterBasedGauge64
Field Status : current
Description : Output packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.11

Field Name : inputErrLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Giants
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.10

Field Name : inputErrShort
Field Type : CounterBasedGauge64
Field Status : current
Description : Runts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.9

Field Name : frame
Field Type : CounterBasedGauge64
Field Status : current
Description : Frames
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.8

Field Name : crc
Field Type : CounterBasedGauge64
Field Status : current
Description : CRC
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.7

Field Name : inputErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Input errors
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.6

Field Name : receivedUnicasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received unicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.5

Field Name : receivedMulticasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received multicasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.4

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Field Name : receivedBroadcasts
Field Type : CounterBasedGauge64
Field Status : current
Description : Received broadcasts
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.3

Field Name : bytesInput
Field Type : CounterBasedGauge64
Field Status : current
Description : Input bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.2

Field Name : packetsInput
Field Type : CounterBasedGauge64
Field Status : current
Description : Input packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.1.1.1

Field Name : interfaceTunnelSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1

Field Name : interfaceTunnelSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1

Field Name : rateByteRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Byte received rate bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.11

Field Name : ratePktRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet received rate packets/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.10

Field Name : rateByteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Byte sent rate bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.9

Field Name : ratePktSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet sent rate packets/sec
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.8

Field Name : numTxErrPkts
Field Type : CounterBasedGauge64
Field Status : current

ACOS-INTERFACE-STATS-MIB_acosInterface_oid_list

Description : sent error packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.7

Field Name : numRxErrPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : received error packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.6

Field Name : numTotalTxBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : sent bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.5

Field Name : numTxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : sent packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.4

Field Name : numTotalRxBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : received bytes
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.3

Field Name : numRxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : received packets
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.2

Field Name : ifnum
Field Type : INTEGER
Field Status : current
Description : Tunnel interface number
OID : 1.3.6.1.4.1.22610.2.4.10.95.8.1.1.1.1

ACOS-IP-ANOMALY-DROP-MIB_oid_list

Field Name : anomalyDropStatsTable
Field Type : TABLE
Field Status : current
Description : SetIPAnomalyDropPolicy from object 'ip.anomaly-drop'
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1

Field Name : anomalyDropStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The anomalyDropStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1

Field Name : anomalyDropStatsTcpUdpZeroPort
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_udp_zero_port
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.50

Field Name : anomalyDropStatsIpv6EhMalformed
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_malformed
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.49

Field Name : anomalyDropStatsIpv6EhOther
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_other
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.48

Field Name : anomalyDropStatsIpv6EhNone
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_none
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.47

Field Name : anomalyDropStatsIpv6EhMobility
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_mobility
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.46

Field Name : anomalyDropStatsIpv6EhEsp
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_esp
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.45

Field Name : anomalyDropStatsIpv6EhAh
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_ah
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.44

Field Name : anomalyDropStatsIpv6EhFrag
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IP-ANOMALY-DROP-MIB_oid_list

Description : ipv6_eh_frag
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.43

Field Name : anomalyDropStatsIpv6EhRouting
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_routing
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.42

Field Name : anomalyDropStatsIpv6EhDest
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_dest
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.41

Field Name : anomalyDropStatsIpv6EhHbh
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6_eh_hbh
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.40

Field Name : anomalyDropStatsGrePptpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : gre_pptp_err
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.39

Field Name : anomalyDropStatsNvgreErr
Field Type : CounterBasedGauge64
Field Status : current
Description : nvgre_err
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.38

Field Name : anomalyDropStatsVxlanErr
Field Type : CounterBasedGauge64
Field Status : current
Description : vxlan_err
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.37

Field Name : anomalyDropStatsIpipTnlErr
Field Type : CounterBasedGauge64
Field Status : current
Description : ipip_tnl_err
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.36

Field Name : anomalyDropStatsTcpOptErr
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_opt_err
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.35

Field Name : anomalyDropStatsIpipTnlMsmatch
Field Type : CounterBasedGauge64
Field Status : current
Description : ipip_tnl_msmatch
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.34

ACOS-IP-ANOMALY-DROP-MIB_oid_list

Field Name : anomalyDropStatsRuntTcpUdpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : runt_tcp_udp_hdr
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.33

Field Name : anomalyDropStatsRuntIpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : runt_ip_hdr
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.32

Field Name : anomalyDropStatsUdpBadCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_bad_csum
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.31

Field Name : anomalyDropStatsUdpPortLb
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_port_lb
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.30

Field Name : anomalyDropStatsUdpKerbFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_kerb_frg
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.29

Field Name : anomalyDropStatsUdpBadLen
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_bad_len
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.28

Field Name : anomalyDropStatsUdpSrtHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_srt_hdr
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.27

Field Name : anomalyDropStatsTcpBadCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_bad_csum
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.26

Field Name : anomalyDropStatsTcpFrgHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_frg_hdr
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.25

Field Name : anomalyDropStatsTcpSynFrg
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IP-ANOMALY-DROP-MIB_oid_list

Description : tcp_syn_frg
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.24

Field Name : anomalyDropStatsTcpXmasScan
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_xmas_scan
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.23

Field Name : anomalyDropStatsTcpXmas
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_xmas
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.22

Field Name : anomalyDropStatsTcpSynFin
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syn_fin
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.21

Field Name : anomalyDropStatsTcpNullScan
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_null_scan
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.20

Field Name : anomalyDropStatsTcpNullFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_null_frg
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.19

Field Name : anomalyDropStatsTcpBadIplen
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_bad_iplen
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.18

Field Name : anomalyDropStatsTcpShtHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_sht_hdr
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.17

Field Name : anomalyDropStatsBadTcpUrgOffset
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_tcp_urg_offset
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.16

Field Name : anomalyDropStatsPod
Field Type : CounterBasedGauge64
Field Status : current
Description : pod
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.15

ACOS-IP-ANOMALY-DROP-MIB_oid_list

Field Name : anomalyDropStatsCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : csum
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.14

Field Name : anomalyDropStatsBadIpFrgOffset
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_ip_frg_offset
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.13

Field Name : anomalyDropStatsBadIpPayloadLen
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_ip_payload_len
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.12

Field Name : anomalyDropStatsOverIpPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : over_ip_payload
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.11

Field Name : anomalyDropStatsNoIpPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : no_ip_payload
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.10

Field Name : anomalyDropStatsBadIpTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_ip_ttl
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.9

Field Name : anomalyDropStatsBadIpFlg
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_ip_flg
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.8

Field Name : anomalyDropStatsBadIpHdrlen
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_ip_hdrlen
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.7

Field Name : anomalyDropStatsFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : frg
OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.6

Field Name : anomalyDropStatsOpt
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IP-ANOMALY-DROP-MIB_oid_list

Description : opt

OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.5

Field Name : anomalyDropStatsEmpMicFrg

Field Type : CounterBasedGauge64

Field Status : current

Description : emp_mic_frg

OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.4

Field Name : anomalyDropStatsEmpFrg

Field Type : CounterBasedGauge64

Field Status : current

Description : emp_frg

OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.3

Field Name : anomalyDropStatsLand

Field Type : CounterBasedGauge64

Field Status : current

Description : land

OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.2

Field Name : anomalyDropStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.140.1.1.1.1

ACOS-IP-STATS-MIB_acosIp_oid_list

Field Name : ipFragFirstGTPPacketTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First GTP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.47

Field Name : ipFragSctpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.46

Field Name : ipFragSctpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.45

Field Name : fragSessionCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Session Count
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.44

Field Name : ipFragSessionPacketsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Max Packets Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.43

Field Name : ipFragMaxPacketsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Too Many Packets Per Reassembly Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.42

Field Name : ipdEntryDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DDoS Protection Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.41

Field Name : cpuThresholdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : High CPU Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.40

Field Name : lowCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current
Description : Low CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.39

Field Name : highCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IP-STATS-MIB_acosIp_oid_list

Description : High CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.38

Field Name : ipFragErrorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Processing Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.37

Field Name : ipFragPolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : MTU Exceeded Policy Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.36

Field Name : ipFragReassemblyFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Failure
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.35

Field Name : ipFragMaxLenExeeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Max Data Length Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.34

Field Name : ipFragReassemblySucess
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Success
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.33

Field Name : ipFragFramentQueueFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Failure
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.32

Field Name : ipFragTotalFragmentsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Queued Fragments Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.31

Field Name : ipFragDuplicateLastFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate Last Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.30

Field Name : ipFragDuplicateFirstFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate First Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.29

ACOS-IP-STATS-MIB_acosIp_oid_list

Field Name : ipFragExceededLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Out of Bounds
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.28

Field Name : ipFragUnalignedLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Unaligned
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.27

Field Name : ipFragFramentQueueSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Success
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.26

Field Name : ipFragFastAgingUnset
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Unset
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.25

Field Name : ipFragFastAgingSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Set
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.24

Field Name : ipFragNoSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Session Memory
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.23

Field Name : ipFragTotalSessionsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Sessions Exceeded Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.22

Field Name : ipFragFirstL4TooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First L4 Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.21

Field Name : ipFragFirstTcpTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First TCP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.20

Field Name : ipFragTooSmall
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IP-STATS-MIB_acosIp_oid_list

Description : Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.19

Field Name : iipFragBadIpLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Length
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.18

Field Name : ipFragOverlapError
Field Type : CounterBasedGauge64
Field Status : current
Description : Overlapping Fragment Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.17

Field Name : ipFragOtherDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.16

Field Name : ipFragIpv6ipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.15

Field Name : ipFragIpipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.14

Field Name : ipFragTcpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.13

Field Name : ipFragUdpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.12

Field Name : ipFragIcmpv6Dropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.11

Field Name : ipFragIcmpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.10

ACOS-IP-STATS-MIB_acosIp_oid_list

Field Name : ipFragOtherRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.9

Field Name : ipFragIpv6ipRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.8

Field Name : ipFragIpipRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.7

Field Name : ipFragTcpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.6

Field Name : ipFragUdpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.5

Field Name : ipFragIcmpv6Rcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.4

Field Name : ipFragIcmpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.3

Field Name : ipFragSessionExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Expired
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.2

Field Name : ipFragSessionInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.55.7.1.1

Field Name : tcpUdpZeroPort
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IP-STATS-MIB_acosIp_oid_list

Description : TCP UDP Zero Port Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.49

Field Name : ipv6EhMalformed
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Malformed Extension Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.48

Field Name : ipv6EhOther
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Unknown Extension Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.47

Field Name : ipv6EhNone
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 No Next Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.46

Field Name : ipv6EhMobility
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Mobility Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.45

Field Name : ipv6EhEsp
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 ESP Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.44

Field Name : ipv6EhAh
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Authentication Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.43

Field Name : ipv6EhFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Fragmentation Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.42

Field Name : ipv6EhRouting
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Routing Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.41

Field Name : ipv6EhDest
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Destination Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.40

ACOS-IP-STATS-MIB_acosIp_oid_list

Field Name : ipv6EhHbh
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Hop by Hop Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.39

Field Name : grePptpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE PPTP Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.38

Field Name : nvgreErr
Field Type : CounterBasedGauge64
Field Status : current
Description : GRE Tunnel Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.37

Field Name : vxlanErr
Field Type : CounterBasedGauge64
Field Status : current
Description : VXLAN Tunnel Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.36

Field Name : ipipTnlErr
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-over-IP Tunnel Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.35

Field Name : tcpOptErr
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Option Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.34

Field Name : ipipTnlMsmatch
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-over-IP Tunnel Mismatch Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.33

Field Name : runtTcpUdpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Runt TCP/UDP Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.32

Field Name : runtIpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Runt IP Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.31

Field Name : udpBadCsum
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IP-STATS-MIB_acosIp_oid_list

Description : UDP Bad Checksum Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.30

Field Name : udpPortLb
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Port Loopback Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.29

Field Name : udpKerbFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Kerberos Fragment Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.28

Field Name : udpBadLen
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Bad Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.27

Field Name : udpSrtHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Short Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.26

Field Name : tcpBadCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Bad Checksum Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.25

Field Name : tcpFrgHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Fragmented Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.24

Field Name : tcpSynFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Syn Fragment Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.23

Field Name : tcpXmasScan
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP XMAS Scan Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.22

Field Name : tcpXmas
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP XMAS Flags Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.21

ACOS-IP-STATS-MIB_acosIp_oid_list

Field Name : tcpSynFin
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Syn and Fin Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.20

Field Name : tcpNullScan
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Null Scan Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.19

Field Name : tcpNullFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Null Flags Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.18

Field Name : tcpBadIplen
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Bad IP Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.17

Field Name : tcpShtHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Short Header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.16

Field Name : badTcpUrgOffset
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Bad Urgent Offset Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.15

Field Name : pod
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Ping of Death Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.14

Field Name : csum
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Checksum Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.13

Field Name : badIpFrgOffset
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Fragment Offset Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.12

Field Name : badIpPayloadLen
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IP-STATS-MIB_acosIp_oid_list

Description : Bad IP Payload Len Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.11

Field Name : overIpPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : Oversize IP Payload Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.10

Field Name : noIpPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : No IP Payload drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.9

Field Name : badIpTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP TTL Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.8

Field Name : badIpFlg
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Flags Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.7

Field Name : badIpHdrlen
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Header Len Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.6

Field Name : frg
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Fragment Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.5

Field Name : opt
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Options Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.4

Field Name : empMicFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : Micro Fragment Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.3

Field Name : empFrg
Field Type : CounterBasedGauge64
Field Status : current
Description : Empty Fragment Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.2

ACOS-IP-STATS-MIB_acosIp_oid_list

Field Name : land
Field Type : CounterBasedGauge64
Field Status : current
Description : Land Attack Drop
OID : 1.3.6.1.4.1.22610.2.4.10.55.5.1.1

Field Name : ipNatPoolGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.3.1.1

Field Name : ipNatPoolGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.3.1.1.1

Field Name : Failed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.3.1.1.1.2

Field Name : poolGroupName
Field Type : String
Field Status : current
Description : Specify pool group name
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.3.1.1.1.1

Field Name : ipNatPoolSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1

Field Name : ipNatPoolSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1.1

Field Name : ipNatPoolFailed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1.1.5

Field Name : ipNatPoolTotalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1.1.4

Field Name : ipNatPoolTotalUsed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IP-STATS-MIB_acosIp_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1.1.3

Field Name : ipNatPoolPortUsage

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1.1.2

Field Name : ipNatPoolName

Field Type : String

Field Status : current

Description : Specify pool name or pool group

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.2.1.1.1.1

Field Name : crossCpuRrNoConnDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Packets Dropped no conn

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.14

Field Name : crossCpuRrSelfSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Packets Self Sent in CPU RR

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.13

Field Name : crossCpuHelperFreeNotFound

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Free Not Found

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.12

Field Name : crossCpuHelperFreeRetryLookup

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Free Retry Lookup

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.11

Field Name : crossCpuHelperDeleted

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Helper Deleted

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.10

Field Name : crossCpuNoSession

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU No Session Found

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.9

Field Name : crossCpuBadL4

Field Type : CounterBasedGauge64

Field Status : current

Description : Cross CPU Unsupported L4

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.8

ACOS-IP-STATS-MIB_acosIp_oid_list

Field Name : crossCpuBadL3
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Unsupported L3
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.7

Field Name : crossCpuHelperCpuMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper CPU Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.6

Field Name : crossCpuHelperNatPoolStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Standby
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.5

Field Name : crossCpuRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Packets Received
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.4

Field Name : crossCpuSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Packets Sent
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.3

Field Name : crossCpuHelperFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Free
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.2

Field Name : crossCpuHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross CPU Helper Created
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.1.1.1

Field Name : noMatchingGreSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.12

Field Name : unknownGreVersion
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.11

Field Name : truncatedGrePacket
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IP-STATS-MIB_acosIp_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.10

Field Name : retransmittedPacMessage

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.9

Field Name : retransmittedPnsMessage

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.8

Field Name : mismatchedPacCallId

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.7

Field Name : mismatchedPnsCallId

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.6

Field Name : truncatedPacMessage

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.5

Field Name : truncatedPnsMessage

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.4

Field Name : smpSessionCreationFailure

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.3

Field Name : currentGreSessions

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.2

Field Name : currentSmpSessions

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.55.12.9.1.1.1

ACOS-IPV6-IN-IPV4-STATS-MIB_acosIpv6InIpv4_oid_list

Field Name : ipFragFirstGTPPacketTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First GTP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.47

Field Name : sctpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.46

Field Name : sctpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.45

Field Name : fragSessionCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Session Count
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.44

Field Name : sessionPacketsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Max Packets Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.43

Field Name : maxPacketsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Too Many Packets Per Reassembly Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.42

Field Name : ipdEntryDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DDoS Protection Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.41

Field Name : cpuThresholdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : High CPU Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.40

Field Name : lowCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current
Description : Low CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.39

Field Name : highCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IPV6-IN-IPV4-STATS-MIB_acosIpv6InIpv4_oid_list

Description : High CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.38

Field Name : errorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Processing Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.37

Field Name : policyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : MTU Exceeded Policy Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.36

Field Name : reassemblyFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Failure
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.35

Field Name : maxLenExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Max Data Length Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.34

Field Name : reassemblySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Success
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.33

Field Name : fragmentQueueFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Failure
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.32

Field Name : totalFragmentsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Queued Fragments Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.31

Field Name : duplicateLastFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate Last Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.30

Field Name : duplicateFirstFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate First Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.29

ACOS-IPV6-IN-IPV4-STATS-MIB_acosIpv6InIpv4_oid_list

Field Name : exceededLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Out of Bounds
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.28

Field Name : unalignedLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Unaligned
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.27

Field Name : fragmentQueueSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Success
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.26

Field Name : fastAgingUnset
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Unset
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.25

Field Name : ipv6InIpv4FastAgingSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Set
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.24

Field Name : noSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Session Memory
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.23

Field Name : totalSessionsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Sessions Exceeded Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.22

Field Name : firstL4TooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First L4 Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.21

Field Name : firstTcpTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First TCP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.20

Field Name : tooSmall
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IPV6-IN-IPV4-STATS-MIB_acosIpv6InIpv4_oid_list

Description : Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.19

Field Name : badIpLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Length
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.18

Field Name : overlapError
Field Type : CounterBasedGauge64
Field Status : current
Description : Overlapping Fragment Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.17

Field Name : otherDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.16

Field Name : ipv6ipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.15

Field Name : ipipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.14

Field Name : tcpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.13

Field Name : udpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.12

Field Name : icmpv6Dropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.11

Field Name : icmpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.10

ACOS-IPV6-IN-IPV4-STATS-MIB_acosIpv6InIpv4_oid_list

Field Name : otherRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.9

Field Name : ipv6ipRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.8

Field Name : ipipRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.7

Field Name : tcpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.6

Field Name : udpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.5

Field Name : icmpv6Rcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.4

Field Name : icmpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Received
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.3

Field Name : sessionExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Expired
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.2

Field Name : sessionInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.99.1.1.1

ACOS-IPV6-STATS-MIB_acosIpv6_oid_list

Field Name : ipFragFirstGTPPacketTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First GTP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.47

Field Name : ipv6FragSctpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.46

Field Name : ipv6FragSctpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.45

Field Name : fragSessionCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Session Count
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.44

Field Name : ipv6FragSessionPacketsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Max Packets Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.43

Field Name : ipv6FragMaxPacketsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Too Many Packets Per Reassembly Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.42

Field Name : ipdEntryDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DDoS Protection Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.41

Field Name : cpuThresholdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : High CPU Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.40

Field Name : lowCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current
Description : Low CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.39

Field Name : highCpuThreshold
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IPV6-STATS-MIB_acosIpv6_oid_list

Description : High CPU Threshold Reached
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.38

Field Name : ipv6FragErrorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Processing Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.37

Field Name : ipv6FragPolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : MTU Exceeded Policy Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.36

Field Name : ipv6FragReassemblyFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Failure
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.35

Field Name : ipv6FragMaxLenExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Max Data Length Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.34

Field Name : ipv6FragReassemblySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Reassembly Success
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.33

Field Name : ipv6FragFragmentQueueFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Failure
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.32

Field Name : ipv6FragTotalFragmentsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Queued Fragments Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.31

Field Name : ipv6FragDuplicateLastFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate Last Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.30

Field Name : ipv6FragDuplicateFirstFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate First Fragment
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.29

ACOS-IPV6-STATS-MIB_acosIpv6_oid_list

Field Name : ipv6FragExceededLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Out of Bounds
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.28

Field Name : ipv6FragUnalignedLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Payload Length Unaligned
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.27

Field Name : ipv6FragFragmentQueueSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragment Queue Success
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.26

Field Name : ipv6FragFastAgingUnset
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Unset
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.25

Field Name : ipv6FragFastAgingSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Fragmentation Fast Aging Set
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.24

Field Name : ipv6FragNoSessionMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of Session Memory
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.23

Field Name : ipv6FragTotalSessionsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Sessions Exceeded Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.22

Field Name : ipv6FragFirstL4TooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First L4 Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.21

Field Name : ipv6FragFirstTcpTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : First TCP Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.20

Field Name : ipv6FragTooSmall
Field Type : CounterBasedGauge64
Field Status : current

ACOS-IPV6-STATS-MIB_acosIpv6_oid_list

Description : Fragment Too Small Drop
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.19

Field Name : ipv6FragBadIpLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad IP Length
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.18

Field Name : ipv6FragOverlapError
Field Type : CounterBasedGauge64
Field Status : current
Description : Overlapping Fragment Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.17

Field Name : ipv6FragOtherDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.16

Field Name : ipv6FragIpv6ipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.15

Field Name : ipv6FragIpipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-in-IP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.14

Field Name : ipv6FragTcpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.13

Field Name : ipv6FragUdpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.12

Field Name : ipv6FragIcmpv6Dropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.11

Field Name : ipv6FragIcmpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.10

ACOS-IPV6-STATS-MIB_acosIpv6_oid_list

Field Name : ipv6FragOtherRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.9

Field Name : ipv6FragIpv6ipRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.8

Field Name : ipv6FragIpipRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-in-IP Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.7

Field Name : ipv6FragTcpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.6

Field Name : ipv6FragUdpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.5

Field Name : ipv6FragIcmpv6Rcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMPv6 Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.4

Field Name : ipv6FragIcmpRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : ICMP Received
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.3

Field Name : ipv6FragSessionExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Expired
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.2

Field Name : ipv6FragSessionInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.57.4.1.1

Field Name : ipv6NatPoolSTable
Field Type : TABLE
Field Status : current

ACOS-IPV6-STATS-MIB_acosIpv6_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1

Field Name : ipv6NatPoolSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1.1

Field Name : failed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1.1.5

Field Name : totalFreed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1.1.4

Field Name : totalUsed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1.1.3

Field Name : portUsage

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1.1.2

Field Name : poolName

Field Type : String

Field Status : current

Description : Specify pool name

OID : 1.3.6.1.4.1.22610.2.4.10.57.9.1.1.1.1.1

Field Name : ipv6NatPoolGroupSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.57.9.2.1.1

Field Name : ipv6NatPoolGroupSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.57.9.2.1.1.1

Field Name : Failed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.57.9.2.1.1.1.2

ACOS-IPV6-STATS-MIB_acosIpv6_oid_list

Field Name : poolGroupName

Field Type : String

Field Status : current

Description : Specify pool group name

OID : 1.3.6.1.4.1.22610.2.4.10.57.9.2.1.1.1.1

ACOS-JWT-CACHE-MIB_oid_list

Field Name : cacheOperCacheListTable
Field Type : TABLE
Field Status : current
Description : AAMAuthorizationJWTCacheRelatedOperations from object 'aam.authorization.jwt.cache'
OID : 1.3.6.1.4.1.22610.2.4.8.594.1.3

Field Name : cacheOperTable
Field Type : TABLE
Field Status : current
Description : AAMAuthorizationJWTCacheRelatedOperations from object 'aam.authorization.jwt.cache'
OID : 1.3.6.1.4.1.22610.2.4.8.594.1.2

Field Name : cacheOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The cacheOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.594.1.2.1

Field Name : cacheOperAudience
Field Type : String
Field Status : current
Description : audience
OID : 1.3.6.1.4.1.22610.2.4.8.594.1.2.1.5

Field Name : cacheOperMaxTokenCache
Field Type : CounterBasedGauge64
Field Status : current
Description : max_token_cache
OID : 1.3.6.1.4.1.22610.2.4.8.594.1.2.1.4

Field Name : cacheOperTokenCacheHit
Field Type : CounterBasedGauge64
Field Status : current
Description : token_cache_hit
OID : 1.3.6.1.4.1.22610.2.4.8.594.1.2.1.3

Field Name : cacheOperTokenCached
Field Type : CounterBasedGauge64
Field Status : current
Description : token_cached
OID : 1.3.6.1.4.1.22610.2.4.8.594.1.2.1.2

Field Name : cacheOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.594.1.2.1.1

Field Name : cacheOperCacheListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The cacheOperCacheList entry:cache-list
OID : 1.3.6.1.4.1.22610.2.4.8.594.1.3.1

Field Name : cacheOperCacheListTtl
Field Type : CounterBasedGauge64
Field Status : current

ACOS-JWT-CACHE-MIB_oid_list

Description : ttl

OID : 1.3.6.1.4.1.22610.2.4.8.594.1.3.1.8

Field Name : cacheOperCacheListClientIp

Field Type : String

Field Status : current

Description : client-ip

OID : 1.3.6.1.4.1.22610.2.4.8.594.1.3.1.7

Field Name : cacheOperCacheListAudience

Field Type : String

Field Status : current

Description : audience

OID : 1.3.6.1.4.1.22610.2.4.8.594.1.3.1.6

Field Name : cacheOperCacheListSubject

Field Type : String

Field Status : current

Description : subject

OID : 1.3.6.1.4.1.22610.2.4.8.594.1.3.1.5

Field Name : cacheOperCacheListIssuer

Field Type : String

Field Status : current

Description : issuer

OID : 1.3.6.1.4.1.22610.2.4.8.594.1.3.1.4

Field Name : cacheOperCacheListCacheId

Field Type : CounterBasedGauge64

Field Status : current

Description : cache-id

OID : 1.3.6.1.4.1.22610.2.4.8.594.1.3.1.3

Field Name : cacheOperCacheListCacheListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.594.1.3.1.2

Field Name : cacheOperCacheListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.594.1.3.1.1

ACOS-NAT-POOL-MIB_oid_list

Field Name : poolOperNatIpListTable
Field Type : TABLE
Field Status : current
Description : ConfigureCGNv6NATPool from object 'cgnv6.nat.pool'
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3

Field Name : poolStatsTable
Field Type : TABLE
Field Status : current
Description : ConfigureCGNv6NATPool from object 'cgnv6.nat.pool'
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1

Field Name : poolStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The poolStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1

Field Name : poolStatsIpTotalCluster
Field Type : CounterBasedGauge64
Field Status : current
Description : ip-total-cluster
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.37

Field Name : poolStatsUserOccupationPercentage
Field Type : CounterBasedGauge64
Field Status : current
Description : user-occupation-percentage
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.36

Field Name : poolStatsMaxUsersAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : max-users-allowed
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.35

Field Name : poolStatsTcpPortUsagePercentage
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-usage-percentage
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.34

Field Name : poolStatsTcpTotalPort
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-total-port
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.33

Field Name : poolStatsUdpPortUsagePercentage
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-usage-percentage
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.32

Field Name : poolStatsUdpTotalPort
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NAT-POOL-MIB_oid_list

Description : udp-total-port
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.31

Field Name : poolStatsIpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ip-total
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.30

Field Name : poolStatsIpFree
Field Type : CounterBasedGauge64
Field Status : current
Description : ip-free
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.29

Field Name : poolStatsIpUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : ip-used
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.28

Field Name : poolStatsTcpPortOverloadFree
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-overload-free
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.27

Field Name : poolStatsTcpPortOverloadCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-overload-create
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.26

Field Name : poolStatsTcpPortOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-port-overloaded
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.25

Field Name : poolStatsTcpHitFull
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-hit-full
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.24

Field Name : poolStatsTcpPeak
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-peak
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.23

Field Name : poolStatsTcpRsvd
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-rsvd
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.22

ACOS-NAT-POOL-MIB_oid_list

Field Name : poolStatsTcpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-total
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.21

Field Name : poolStatsTcpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-freed
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.20

Field Name : poolStatsTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.19

Field Name : poolStatsUdpPortOverloadFree
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-overload-free
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.18

Field Name : poolStatsUdpPortOverloadCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-overload-create
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.17

Field Name : poolStatsUdpPortOverloaded
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-port-overloaded
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.16

Field Name : poolStatsUdpHitFull
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-hit-full
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.15

Field Name : poolStatsUdpPeak
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-peak
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.14

Field Name : poolStatsUdpRsvd
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-rsvd
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.13

Field Name : poolStatsUdpTotal
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NAT-POOL-MIB_oid_list

Description : udp-total
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.12

Field Name : poolStatsUdpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : udp-freed
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.11

Field Name : poolStatsUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : udp
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.10

Field Name : poolStatsIcmpHitFull
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-hit-full
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.9

Field Name : poolStatsIcmpPeak
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-peak
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.8

Field Name : poolStatsIcmpRsvd
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-rsvd
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.7

Field Name : poolStatsIcmpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-total
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.6

Field Name : poolStatsIcmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-freed
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.5

Field Name : poolStatsIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.4

Field Name : poolStatsUsers
Field Type : CounterBasedGauge64
Field Status : current
Description : users
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.3

ACOS-NAT-POOL-MIB_oid_list

Field Name : poolStatsPoolName

Field Type : String

Field Status : current

Description : pool-name

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.2

Field Name : poolStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.1.1.1

Field Name : poolOperNatIpListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The poolOperNatIpList entry:nat-ip-list

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1

Field Name : poolOperNatIpListObsoleted

Field Type : CounterBasedGauge64

Field Status : current

Description : obsoleted

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.27

Field Name : poolOperNatIpListRtspUsed

Field Type : CounterBasedGauge64

Field Status : current

Description : rtsp-used

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.26

Field Name : poolOperNatIpListTcpPortOverloaded

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp-port-overloaded

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.25

Field Name : poolOperNatIpListTcpHitFull

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp-hit-full

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.24

Field Name : poolOperNatIpListTcpPeak

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp-peak

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.23

Field Name : poolOperNatIpListTcpReserved

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp-reserved

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.22

Field Name : poolOperNatIpListTcpTotal

Field Type : CounterBasedGauge64

Field Status : current

ACOS-NAT-POOL-MIB_oid_list

Description : tcp-total

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.21

Field Name : poolOperNatIpListTcpFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp-freed

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.20

Field Name : poolOperNatIpListTcpUsed

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp-used

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.19

Field Name : poolOperNatIpListUdpPortOverloaded

Field Type : CounterBasedGauge64

Field Status : current

Description : udp-port-overloaded

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.18

Field Name : poolOperNatIpListUdpHitFull

Field Type : CounterBasedGauge64

Field Status : current

Description : udp-hit-full

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.17

Field Name : poolOperNatIpListUdpPeak

Field Type : CounterBasedGauge64

Field Status : current

Description : udp-peak

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.16

Field Name : poolOperNatIpListUdpReserved

Field Type : CounterBasedGauge64

Field Status : current

Description : udp-reserved

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.15

Field Name : poolOperNatIpListUdpTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : udp-total

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.14

Field Name : poolOperNatIpListUdpFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : udp-freed

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.13

Field Name : poolOperNatIpListUdpUsed

Field Type : CounterBasedGauge64

Field Status : current

Description : udp-used

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.12

ACOS-NAT-POOL-MIB_oid_list

Field Name : poolOperNatIpListIcmpHitFull
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-hit-full
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.11

Field Name : poolOperNatIpListIcmpPeak
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-peak
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.10

Field Name : poolOperNatIpListIcmpReserved
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-reserved
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.9

Field Name : poolOperNatIpListIcmpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-total
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.8

Field Name : poolOperNatIpListIcmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-freed
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.7

Field Name : poolOperNatIpListIcmpUsed
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-used
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.6

Field Name : poolOperNatIpListUsers
Field Type : CounterBasedGauge64
Field Status : current
Description : users
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.5

Field Name : poolOperNatIpListIpAddress
Field Type : String
Field Status : current
Description : ip-address
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.4

Field Name : poolOperNatIpListNatIpListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.3

Field Name : poolOperNatIpListPoolName
Field Type : String
Field Status : current

ACOS-NAT-POOL-MIB_oid_list

Description : pool-name

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.2

Field Name : poolOperNatIpListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.717.1.3.1.1

ACOS-NETFLOW-MONITOR-MIB_oid_list

Field Name : monitorOperTable
Field Type : TABLE
Field Status : current
Description : ConfigureNetFlowMonitor from object 'netflow.monitor'
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2

Field Name : monitorOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The monitorOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1

Field Name : monitorOperResendTemplateTimeout
Field Type : String
Field Status : current
Description : resend-template-timeout
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.12

Field Name : monitorOperResendTemplatePerRecords
Field Type : String
Field Status : current
Description : resend-template-per-records
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.11

Field Name : monitorOperCounterPollingInterval
Field Type : String
Field Status : current
Description : counter-polling-interval
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.10

Field Name : monitorOperFlowTimeout
Field Type : String
Field Status : current
Description : flow-timeout
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.9

Field Name : monitorOperSourceIpAddr
Field Type : String
Field Status : current
Description : source-ip-addr
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.8

Field Name : monitorOperSourceIpUseMgmt
Field Type : String
Field Status : current
Description : source-ip-use-mgmt
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.7

Field Name : monitorOperDestination
Field Type : String
Field Status : current
Description : destination
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.6

Field Name : monitorOperFilter
Field Type : String
Field Status : current

ACOS-NETFLOW-MONITOR-MIB_oid_list

Description : filter

OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.5

Field Name : monitorOperStatus

Field Type : String

Field Status : current

Description : status

OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.4

Field Name : monitorOperProtocol

Field Type : String

Field Status : current

Description : protocol

OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.3

Field Name : monitorOperName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.2

Field Name : monitorOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.437.1.2.1.1

Field Name : monitorStatsTable

Field Type : TABLE

Field Status : current

Description : ConfigureNetFlowMonitor from object 'netflow.monitor'

OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1

Field Name : monitorStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The monitorStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1

Field Name : monitorStatsDdosHttpStatRecordsSentFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : ddos-http-stat-records-sent-failure

OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.131

Field Name : monitorStatsDdosHttpStatRecordsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : ddos-http-stat-records-sent

OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.130

Field Name : monitorStatsDdosGeneralStatRecordsSentFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : ddos-general-stat-records-sent-failure

OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.129

ACOS-NETFLOW-MONITOR-MIB_oid_list

Field Name : monitorStatsDdosGeneralStatRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : ddos-general-stat-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.128

Field Name : monitorStatsCustomGtpRateLimitPeriodicRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-rate-limit-periodic-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.127

Field Name : monitorStatsCustomGtpRateLimitPeriodicRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-rate-limit-periodic-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.126

Field Name : monitorStatsCustomNatIddosL4EntryDeletedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l4-entry-deleted-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.125

Field Name : monitorStatsCustomNatIddosL4EntryDeletedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l4-entry-deleted-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.124

Field Name : monitorStatsCustomNatIddosL4EntryCreatedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l4-entry-created-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.123

Field Name : monitorStatsCustomNatIddosL4EntryCreatedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l4-entry-created-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.122

Field Name : monitorStatsCustomNatIddosL3EntryDeletedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l3-entry-deleted-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.121

Field Name : monitorStatsCustomNatIddosL3EntryDeletedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l3-entry-deleted-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.120

Field Name : monitorStatsCustomNatIddosL3EntryCreatedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETFLOW-MONITOR-MIB_oid_list

Description : custom-nat-iddos-l3-entry-created-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.119

Field Name : monitorStatsCustomNatIddosL3EntryCreatedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-nat-iddos-l3-entry-created-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.118

Field Name : monitorStatsCustomFwSesnLimitExceededRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-fw-sesn-limit-exceeded-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.117

Field Name : monitorStatsCustomFwSesnLimitExceededRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-fw-sesn-limit-exceeded-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.116

Field Name : monitorStatsCustomFwIddosEntryDeletedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-fw-iddos-entry-deleted-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.115

Field Name : monitorStatsCustomFwIddosEntryDeletedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-fw-iddos-entry-deleted-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.114

Field Name : monitorStatsCustomFwIddosEntryCreatedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-fw-iddos-entry-created-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.113

Field Name : monitorStatsCustomFwIddosEntryCreatedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-fw-iddos-entry-created-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.112

Field Name : monitorStatsCustomGtpInfoEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-info-event-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.111

Field Name : monitorStatsCustomGtpInfoEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-info-event-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.110

ACOS-NETFLOW-MONITOR-MIB_oid_list

Field Name : monitorStatsCustomGtpDenyEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-deny-event-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.109

Field Name : monitorStatsCustomGtpDenyEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-deny-event-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.108

Field Name : monitorStatsCustomGtpUTunnelEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-u-tunnel-event-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.107

Field Name : monitorStatsCustomGtpUTunnelEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-u-tunnel-event-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.106

Field Name : monitorStatsCustomGtpCTunnelEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-c-tunnel-event-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.105

Field Name : monitorStatsCustomGtpCTunnelEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-gtp-c-tunnel-event-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.104

Field Name : monitorStatsReducedLogsByDestination
Field Type : CounterBasedGauge64
Field Status : current
Description : reduced-logs-by-destination
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.103

Field Name : monitorStatsCustomPortBatchingV2DsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-dslite-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.102

Field Name : monitorStatsCustomPortBatchingV2DsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-dslite-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.101

Field Name : monitorStatsCustomPortBatchingV2Nat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETFLOW-MONITOR-MIB_oid_list

Description : custom-port-batching-v2-nat64-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.100

Field Name : monitorStatsCustomPortBatchingV2Nat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat64-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.99

Field Name : monitorStatsCustomPortBatchingV2Nat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat44-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.98

Field Name : monitorStatsCustomPortBatchingV2Nat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat44-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.97

Field Name : monitorStatsCustomPortBatchingV2DsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-dslite-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.96

Field Name : monitorStatsCustomPortBatchingV2DsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-dslite-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.95

Field Name : monitorStatsCustomPortBatchingV2Nat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat64-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.94

Field Name : monitorStatsCustomPortBatchingV2Nat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat64-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.93

Field Name : monitorStatsCustomPortBatchingV2Nat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat44-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.92

Field Name : monitorStatsCustomPortBatchingV2Nat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-v2-nat44-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.91

ACOS-NETFLOW-MONITOR-MIB_oid_list

Field Name : monitorStatsCustomPortBatchingDsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-dslite-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.90

Field Name : monitorStatsCustomPortBatchingDsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-dslite-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.89

Field Name : monitorStatsCustomPortBatchingNat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat64-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.88

Field Name : monitorStatsCustomPortBatchingNat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat64-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.87

Field Name : monitorStatsCustomPortBatchingNat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat44-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.86

Field Name : monitorStatsCustomPortBatchingNat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat44-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.85

Field Name : monitorStatsCustomPortBatchingDsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-dslite-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.84

Field Name : monitorStatsCustomPortBatchingDsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-dslite-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.83

Field Name : monitorStatsCustomPortBatchingNat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat64-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.82

Field Name : monitorStatsCustomPortBatchingNat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETFLOW-MONITOR-MIB_oid_list

Description : custom-port-batching-nat64-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.81

Field Name : monitorStatsCustomPortBatchingNat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat44-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.80

Field Name : monitorStatsCustomPortBatchingNat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-batching-nat44-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.79

Field Name : monitorStatsCustomPortMappingDsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-dslite-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.78

Field Name : monitorStatsCustomPortMappingDsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-dslite-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.77

Field Name : monitorStatsCustomPortMappingNat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat64-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.76

Field Name : monitorStatsCustomPortMappingNat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat64-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.75

Field Name : monitorStatsCustomPortMappingNat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat44-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.74

Field Name : monitorStatsCustomPortMappingNat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat44-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.73

Field Name : monitorStatsCustomPortMappingDsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-dslite-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.72

ACOS-NETFLOW-MONITOR-MIB_oid_list

Field Name : monitorStatsCustomPortMappingDsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-dslite-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.71

Field Name : monitorStatsCustomPortMappingNat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat64-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.70

Field Name : monitorStatsCustomPortMappingNat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat64-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.69

Field Name : monitorStatsCustomPortMappingNat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat44-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.68

Field Name : monitorStatsCustomPortMappingNat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-port-mapping-nat44-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.67

Field Name : monitorStatsCustomDenyResetEventFw6RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-deny-reset-event-fw6-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.66

Field Name : monitorStatsCustomDenyResetEventFw6RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-deny-reset-event-fw6-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.65

Field Name : monitorStatsCustomDenyResetEventFw4RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-deny-reset-event-fw4-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.64

Field Name : monitorStatsCustomDenyResetEventFw4RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-deny-reset-event-fw4-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.63

Field Name : monitorStatsCustomSessionEventFw6DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETFLOW-MONITOR-MIB_oid_list

Description : custom-session-event-fw6-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.62

Field Name : monitorStatsCustomSessionEventFw6DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw6-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.61

Field Name : monitorStatsCustomSessionEventFw4DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw4-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.60

Field Name : monitorStatsCustomSessionEventFw4DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw4-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.59

Field Name : monitorStatsCustomSessionEventFw6CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw6-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.58

Field Name : monitorStatsCustomSessionEventFw6CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw6-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.57

Field Name : monitorStatsCustomSessionEventFw4CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw4-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.56

Field Name : monitorStatsCustomSessionEventFw4CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-fw4-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.55

Field Name : monitorStatsCustomSessionEventDsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-dslite-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.54

Field Name : monitorStatsCustomSessionEventDsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-dslite-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.53

ACOS-NETFLOW-MONITOR-MIB_oid_list

Field Name : monitorStatsCustomSessionEventNat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat64-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.52

Field Name : monitorStatsCustomSessionEventNat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat64-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.51

Field Name : monitorStatsCustomSessionEventNat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat44-deletion-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.50

Field Name : monitorStatsCustomSessionEventNat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat44-deletion-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.49

Field Name : monitorStatsCustomSessionEventDsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-dslite-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.48

Field Name : monitorStatsCustomSessionEventDsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-dslite-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.47

Field Name : monitorStatsCustomSessionEventNat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat64-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.46

Field Name : monitorStatsCustomSessionEventNat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat64-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.45

Field Name : monitorStatsCustomSessionEventNat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : custom-session-event-nat44-creation-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.44

Field Name : monitorStatsCustomSessionEventNat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETFLOW-MONITOR-MIB_oid_list

Description : custom-session-event-nat44-creation-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.43

Field Name : monitorStatsPortBatchingV2DsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-v2-dslite-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.42

Field Name : monitorStatsPortBatchingV2DsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-v2-dslite-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.41

Field Name : monitorStatsPortBatchingV2Nat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-v2-nat64-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.40

Field Name : monitorStatsPortBatchingV2Nat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-v2-nat64-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.39

Field Name : monitorStatsPortBatchingV2Nat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-v2-nat44-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.38

Field Name : monitorStatsPortBatchingV2Nat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-v2-nat44-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.37

Field Name : monitorStatsPortBatchingDsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-dslite-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.36

Field Name : monitorStatsPortBatchingDsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-dslite-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.35

Field Name : monitorStatsPortBatchingNat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-nat64-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.34

ACOS-NETFLOW-MONITOR-MIB_oid_list

Field Name : monitorStatsPortBatchingNat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-nat64-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.33

Field Name : monitorStatsPortBatchingNat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-nat44-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.32

Field Name : monitorStatsPortBatchingNat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-batching-nat44-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.31

Field Name : monitorStatsNetflowV5ExtRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : netflow-v5-ext-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.30

Field Name : monitorStatsNetflowV5ExtRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : netflow-v5-ext-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.29

Field Name : monitorStatsNetflowV5RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : netflow-v5-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.28

Field Name : monitorStatsNetflowV5RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : netflow-v5-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.27

Field Name : monitorStatsPortMappingDsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-mapping-dslite-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.26

Field Name : monitorStatsPortMappingDsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-mapping-dslite-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.25

Field Name : monitorStatsPortMappingNat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETFLOW-MONITOR-MIB_oid_list

Description : port-mapping-nat64-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.24

Field Name : monitorStatsPortMappingNat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-mapping-nat64-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.23

Field Name : monitorStatsPortMappingNat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : port-mapping-nat44-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.22

Field Name : monitorStatsPortMappingNat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : port-mapping-nat44-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.21

Field Name : monitorStatsSessionEventFw6RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-fw6-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.20

Field Name : monitorStatsSessionEventFw6RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-fw6-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.19

Field Name : monitorStatsSessionEventFw4RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-fw4-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.18

Field Name : monitorStatsSessionEventFw4RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-fw4-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.17

Field Name : monitorStatsSessionEventDsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-dslite-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.16

Field Name : monitorStatsSessionEventDsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-dslite-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.15

ACOS-NETFLOW-MONITOR-MIB_oid_list

Field Name : monitorStatsSessionEventNat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-nat64-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.14

Field Name : monitorStatsSessionEventNat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-nat64-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.13

Field Name : monitorStatsSessionEventNat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-nat44-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.12

Field Name : monitorStatsSessionEventNat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : session-event-nat44-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.11

Field Name : monitorStatsDsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : dslite-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.10

Field Name : monitorStatsDsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : dslite-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.9

Field Name : monitorStatsNat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : nat64-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.8

Field Name : monitorStatsNat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : nat64-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.7

Field Name : monitorStatsNat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : nat44-records-sent-failure
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.6

Field Name : monitorStatsNat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETFLOW-MONITOR-MIB_oid_list

Description : nat44-records-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.5

Field Name : monitorStatsBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : bytes-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.4

Field Name : monitorStatsPacketsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : packets-sent
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.3

Field Name : monitorStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.2

Field Name : monitorStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.437.1.1.1.1

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Field Name : netflowMonitorSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1

Field Name : netflowMonitorSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1

Field Name : ddosHttpStatRecordsSentFailure

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.130

Field Name : ddosHttpStatRecordsSent

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.129

Field Name : ddosGeneralStatRecordsSentFailure

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.128

Field Name : ddosGeneralStatRecordsSent

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.127

Field Name : customGtpRateLimitPeriodicRecordsSentFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Custom GTP Rate Limit Periodic Records Sent Failure

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.126

Field Name : customGtpRateLimitPeriodicRecordsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Custom GTP Rate Limit Periodic Records Sent

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.125

Field Name : customNatIddosL4EntryDeletedRecordsSentFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Custom NAT iDDoS L4 Entry Deleted Records Sent Failure

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.124

Field Name : customNatIddosL4EntryDeletedRecordsSent

Field Type : CounterBasedGauge64

Field Status : current

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Description : Custom NAT iDDoS L4 Entry Deleted Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.123

Field Name : customNatIddosL4EntryCreatedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom NAT iDDoS L4 Entry Created Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.122

Field Name : customNatIddosL4EntryCreatedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom NAT iDDoS L4 Entry Created Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.121

Field Name : customNatIddosL3EntryDeletedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom NAT iDDoS L3 Entry Deleted Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.120

Field Name : customNatIddosL3EntryDeletedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom NAT iDDoS L3 Entry Deleted Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.119

Field Name : customNatIddosL3EntryCreatedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom NAT iDDoS L3 Entry Created Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.118

Field Name : customNatIddosL3EntryCreatedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom NAT iDDoS L3 Entry Created Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.117

Field Name : customFwSesnLimitExceededRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW Session Limit Exceeded Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.116

Field Name : customFwSesnLimitExceededRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW Session Limit Exceeded Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.115

Field Name : customFwIddosEntryDeletedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW iDDoS Entry Deleted Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.114

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Field Name : customFwIddosEntryDeletedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW iDDoS Entry Deleted Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.113

Field Name : customFwIddosEntryCreatedRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW iDDoS Entry Created Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.112

Field Name : customFwIddosEntryCreatedRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW iDDoS Entry Created Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.111

Field Name : customGtpInfoEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP Info Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.110

Field Name : customGtpInfoEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP Info Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.109

Field Name : customGtpDenyEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP Deny Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.108

Field Name : customGtpDenyEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP Deny Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.107

Field Name : customGtpUTunnelEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP U Tunnel Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.106

Field Name : customGtpUTunnelEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP U Tunnel Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.105

Field Name : customGtpCTunnelEventRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Description : Custom GTP C Tunnel Records Sent Failure
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.104

Field Name : customGtpCTunnelEventRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom GTP C Tunnel Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.103

Field Name : reducedLogsByDestination
Field Type : CounterBasedGauge64
Field Status : current
Description : Reduced Logs by Destination Protocol and Port
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.102

Field Name : customPortBatchingV2DsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch V2 Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.101

Field Name : customPortBatchingV2DsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch V2 Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.100

Field Name : customPortBatchingV2Nat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch V2 Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.99

Field Name : customPortBatchingV2Nat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch V2 Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.98

Field Name : customPortBatchingV2Nat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch V2 Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.97

Field Name : customPortBatchingV2Nat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch V2 Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.96

Field Name : customPortBatchingV2DsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch V2 Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.95

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Field Name : customPortBatchingV2DsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch V2 Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.94

Field Name : customPortBatchingV2Nat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch V2 Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.93

Field Name : customPortBatchingV2Nat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch V2 Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.92

Field Name : customPortBatchingV2Nat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch V2 Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.91

Field Name : customPortBatchingV2Nat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch V2 Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.90

Field Name : customPortBatchingDsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.89

Field Name : customPortBatchingDsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.88

Field Name : customPortBatchingNat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.87

Field Name : customPortBatchingNat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.86

Field Name : customPortBatchingNat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Description : Custom Nat44 Port Batch Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.85

Field Name : customPortBatchingNat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.84

Field Name : customPortBatchingDsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.83

Field Name : customPortBatchingDsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Batch Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.82

Field Name : customPortBatchingNat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.81

Field Name : customPortBatchingNat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Batch Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.80

Field Name : customPortBatchingNat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.79

Field Name : customPortBatchingNat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Batch Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.78

Field Name : customPortMappingDsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Map Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.77

Field Name : customPortMappingDsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Map Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.76

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Field Name : customPortMappingNat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Map Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.75

Field Name : customPortMappingNat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Map Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.74

Field Name : customPortMappingNat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Map Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.73

Field Name : customPortMappingNat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Map Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.72

Field Name : customPortMappingDsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Map Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.71

Field Name : customPortMappingDsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Port Map Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.70

Field Name : customPortMappingNat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Map Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.69

Field Name : customPortMappingNat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Port Map Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.68

Field Name : customPortMappingNat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Port Map Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.67

Field Name : customPortMappingNat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Description : Custom Nat44 Port Map Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.66

Field Name : customDenyResetEventFw6RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW6 Deny/Reset Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.65

Field Name : customDenyResetEventFw6RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW6 Deny/Reset Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.64

Field Name : customDenyResetEventFw4RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW4 Deny/Reset Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.63

Field Name : customDenyResetEventFw4RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW4 Deny/Reset Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.62

Field Name : customSessionEventFw6DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW6 Session Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.61

Field Name : customSessionEventFw6DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW6 Session Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.60

Field Name : customSessionEventFw4DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW4 Session Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.59

Field Name : customSessionEventFw4DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW4 Session Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.58

Field Name : customSessionEventFw6CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW6 Session Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.57

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Field Name : customSessionEventFw6CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW6 Session Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.56

Field Name : customSessionEventFw4CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW4 Session Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.55

Field Name : customSessionEventFw4CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom FW4 Session Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.54

Field Name : customSessionEventDsliteDeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Session Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.53

Field Name : customSessionEventDsliteDeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Session Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.52

Field Name : customSessionEventNat64DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Session Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.51

Field Name : customSessionEventNat64DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Session Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.50

Field Name : customSessionEventNat44DeletionRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Session Deletion Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.49

Field Name : customSessionEventNat44DeletionRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Session Deletion Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.48

Field Name : customSessionEventDsliteCreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Description : Custom Dslite Session Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.47

Field Name : customSessionEventDsliteCreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Dslite Session Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.46

Field Name : customSessionEventNat64CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Session Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.45

Field Name : customSessionEventNat64CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat64 Session Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.44

Field Name : customSessionEventNat44CreationRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Session Creation Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.43

Field Name : customSessionEventNat44CreationRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom Nat44 Session Creation Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.42

Field Name : portBatchingV2DsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching V2 Dslite Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.41

Field Name : portBatchingV2DsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching V2 Dslite Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.40

Field Name : portBatchingV2Nat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching V2 Nat64 Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.39

Field Name : portBatchingV2Nat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching V2 Nat64 Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.38

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Field Name : portBatchingV2Nat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching V2 Nat44 Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.37

Field Name : portBatchingV2Nat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching V2 Nat44 Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.36

Field Name : portBatchingDsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching Dslite Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.35

Field Name : portBatchingDsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching Dslite Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.34

Field Name : portBatchingNat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching Nat64 Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.33

Field Name : portBatchingNat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching Nat64 Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.32

Field Name : portBatchingNat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching Nat44 Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.31

Field Name : portBatchingNat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Port Batching Nat44 Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.30

Field Name : netflowV5ExtRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow v5 Ext Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.29

Field Name : netflowV5ExtRecordsSent
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Description : Netflow v5 Ext Records Sent

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.28

Field Name : netflowV5RecordsSentFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Netflow v5 Records Failed

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.27

Field Name : netflowV5RecordsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Netflow v5 Records Sent

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.26

Field Name : portMappingDsliteRecordsSentFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Mapping Dslite Event Records failed

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.25

Field Name : portMappingDsliteRecordsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Mapping Dslite Event Records Sent

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.24

Field Name : portMappingNat64RecordsSentFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Mapping Nat64 Event Records Failed

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.23

Field Name : portMappingNat64RecordsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Mapping Nat64 Event Records Sent

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.22

Field Name : portMappingNat44RecordsSentFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Mapping Nat44 Event Records Failed

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.21

Field Name : portMappingNat44RecordsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Port Mapping Nat44 Event Records Sent

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.20

Field Name : sessionEventFw6RecordsSentFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : FW6 Session Event Records Failed

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.19

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Field Name : sessionEventFw6RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : FW6 Session Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.18

Field Name : sessionEventFw4RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : FW4 Session Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.17

Field Name : sessionEventFw4RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : FW4 Session Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.16

Field Name : sessionEventDsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Dslite Session Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.15

Field Name : sessionEventDsliteRecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Dslite Session Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.14

Field Name : sessionEventNat64RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Nat64 Session Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.13

Field Name : sessionEventNat64RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Nat64 Session Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.12

Field Name : sessionEventNat44RecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Nat44 Session Event Records Failed
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.11

Field Name : sessionEventNat44RecordsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Nat44 Session Event Records Sent
OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.10

Field Name : dsliteRecordsSentFailure
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Description : Dslite Flow Records Failed

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.9

Field Name : dsliteRecordsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Dslite Flow Records Sent

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.8

Field Name : nat64RecordsSentFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : NAT64 Flow Records Failed

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.7

Field Name : nat64RecordsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : NAT64 Flow Records Sent

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.6

Field Name : nat44RecordsSentFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : NAT44 Flow Records Failed

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.5

Field Name : nat44RecordsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : NAT44 Flow Records Sent

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.4

Field Name : bytesSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Sent Bytes Count

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.3

Field Name : packetsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Sent Packets Count

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.2

Field Name : netflowMonitorName

Field Type : String

Field Status : current

Description : Name of netflow monitor

OID : 1.3.6.1.4.1.22610.2.4.10.126.2.1.1.1.1

Field Name : templatesRemovedFromDelq

Field Type : CounterBasedGauge64

Field Status : current

Description : Netflow Templates Removed From Delete Queue

OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.8

ACOS-NETFLOW-STATS-MIB_acosNetflow_oid_list

Field Name : templatesAddedToDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow Templates Added To Delete Queue
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.7

Field Name : templateDropOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow Templates Dropped OOM
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.6

Field Name : templateDropExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow Templates Dropped Maximum Limit Reached
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.5

Field Name : v10TemplatesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow v10(IPFIX) Templates Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.4

Field Name : v10TemplatesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow v10(IPFIX) Templates Created
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.3

Field Name : v9TemplatesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow v9 Templates Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.2

Field Name : v9TemplatesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Netflow v9 Templates Created
OID : 1.3.6.1.4.1.22610.2.4.10.126.3.1.1.1

ACOS-NETWORK-STATS-MIB_acosNetwork_oid_list

Field Name : hcPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet drop due to health check
OID : 1.3.6.1.4.1.22610.2.4.10.56.24.1.4

Field Name : vlanPairUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : VLAN pair update
OID : 1.3.6.1.4.1.22610.2.4.10.56.24.1.3

Field Name : macUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : MAC update
OID : 1.3.6.1.4.1.22610.2.4.10.56.24.1.2

Field Name : vlanUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : VLAN update
OID : 1.3.6.1.4.1.22610.2.4.10.56.24.1.1

Field Name : networkVirtualWireHealthCheckSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.56.28.1.1

Field Name : networkVirtualWireHealthCheckSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.56.28.1.1.1

Field Name : packetCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Count
OID : 1.3.6.1.4.1.22610.2.4.10.56.28.1.1.1.4

Field Name : sbyEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Event Count
OID : 1.3.6.1.4.1.22610.2.4.10.56.28.1.1.1.3

Field Name : actEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Active Event Count
OID : 1.3.6.1.4.1.22610.2.4.10.56.28.1.1.1.2

Field Name : vlan
Field Type : INTEGER
Field Status : current

ACOS-NETWORK-STATS-MIB_acosNetwork_oid_list

Description : VLAN ID, specify 1 for untagged traffic
OID : 1.3.6.1.4.1.22610.2.4.10.56.28.1.1.1.1

Field Name : asymmetricRouteDropErr
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.56.9.1.2

Field Name : xparentVlanListErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Transparent Mode VLAN List Errors
OID : 1.3.6.1.4.1.22610.2.4.10.56.9.1.1

Field Name : networkVlanSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1

Field Name : networkVlanSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1

Field Name : sharedVlanPartitionSwitchedCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : SVLAN Partition switched counter
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.7

Field Name : macMovementCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Mac Movement counter
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.6

Field Name : unknownUnicastCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown Unicast counter
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.5

Field Name : ipMulticastCount
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Multicast counter
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.4

Field Name : multicastCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Multicast counter
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.3

ACOS-NETWORK-STATS-MIB_acosNetwork_oid_list

Field Name : broadcastCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Broadcast counter
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.2

Field Name : vlanNum
Field Type : INTEGER
Field Status : current
Description : VLAN number
OID : 1.3.6.1.4.1.22610.2.4.10.56.4.1.1.1.1

Field Name : otherErr
Field Type : CounterBasedGauge64
Field Status : current
Description : IP other error drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.7

Field Name : noRouteErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Tx IP no route error drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.6

Field Name : twampHdrLenErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx TWAMP hdr length error drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.5

Field Name : rxAcldrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IP client-list drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.4

Field Name : rxDropNotEnabledV4
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IP disabled drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.3

Field Name : txPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Tx IP TWAMP test packets
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.2

Field Name : rxPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IP TWAMP test packets
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.2.1.1

Field Name : otherErrV6
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NETWORK-STATS-MIB_acosNetwork_oid_list

Description : IPv6 Other error drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.14

Field Name : noRouteErrV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Tx IPv6 no route error drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.13

Field Name : twampHdrLenErrV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IPv6 TWAMP hdr length error drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.12

Field Name : rxAcldropV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IPv6 client-list drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.11

Field Name : rxDropNotEnabledV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IPv6 disabled drop
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.10

Field Name : txPktsV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Tx IPv6 TWAMP test packets
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.9

Field Name : rxPktsV6
Field Type : CounterBasedGauge64
Field Status : current
Description : Rx IPv6 TWAMP test packets
OID : 1.3.6.1.4.1.22610.2.4.10.56.20.1.3.1.8

ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list

Field Name : ngWafStatsSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1

Field Name : ngWafStatsSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1

Field Name : custom64

Field Type : CounterBasedGauge64

Field Status : current

Description : Custom signal 64

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.115

Field Name : custom63

Field Type : CounterBasedGauge64

Field Status : current

Description : Custom signal 63

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.114

Field Name : custom62

Field Type : CounterBasedGauge64

Field Status : current

Description : Custom signal 62

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.113

Field Name : custom61

Field Type : CounterBasedGauge64

Field Status : current

Description : Custom signal 61

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.112

Field Name : custom60

Field Type : CounterBasedGauge64

Field Status : current

Description : Custom signal 60

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.111

Field Name : custom59

Field Type : CounterBasedGauge64

Field Status : current

Description : Custom signal 59

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.110

Field Name : custom58

Field Type : CounterBasedGauge64

Field Status : current

Description : Custom signal 58

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.109

Field Name : custom57

Field Type : CounterBasedGauge64

Field Status : current

ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list

Description : Custom signal 57
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.108

Field Name : custom56
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 56
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.107

Field Name : custom55
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 55
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.106

Field Name : custom54
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 54
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.105

Field Name : custom53
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 53
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.104

Field Name : custom52
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 52
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.103

Field Name : custom51
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 51
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.102

Field Name : custom50
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 50
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.101

Field Name : custom49
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 49
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.100

Field Name : custom48
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 48
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.99

ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list

Field Name : custom47
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 47
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.98

Field Name : custom46
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 46
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.97

Field Name : custom45
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 45
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.96

Field Name : custom44
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 44
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.95

Field Name : custom43
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 43
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.94

Field Name : custom42
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 42
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.93

Field Name : custom41
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 41
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.92

Field Name : custom40
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 40
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.91

Field Name : custom39
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 39
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.90

Field Name : custom38
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list

Description : Custom signal 38
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.89

Field Name : custom37
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 37
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.88

Field Name : custom36
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 36
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.87

Field Name : custom35
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 35
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.86

Field Name : custom34
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 34
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.85

Field Name : custom33
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 33
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.84

Field Name : custom32
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 32
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.83

Field Name : custom31
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 31
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.82

Field Name : custom30
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 30
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.81

Field Name : custom29
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 29
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.80

ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list

Field Name : custom28
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 28
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.79

Field Name : custom27
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 27
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.78

Field Name : custom26
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 26
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.77

Field Name : custom25
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 25
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.76

Field Name : custom24
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 24
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.75

Field Name : custom23
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 23
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.74

Field Name : custom22
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 22
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.73

Field Name : custom21
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 21
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.72

Field Name : custom20
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 20
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.71

Field Name : custom19
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list

Description : Custom signal 19
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.70

Field Name : custom18
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 18
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.69

Field Name : custom17
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 17
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.68

Field Name : custom16
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 16
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.67

Field Name : custom15
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 15
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.66

Field Name : custom14
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 14
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.65

Field Name : custom13
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 13
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.64

Field Name : custom12
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 12
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.63

Field Name : custom11
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 11
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.62

Field Name : custom10
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 10
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.61

ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list

Field Name : custom9
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 9
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.60

Field Name : custom8
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 8
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.59

Field Name : custom7
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 7
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.58

Field Name : custom6
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 6
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.57

Field Name : custom5
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 5
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.56

Field Name : custom4
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 4
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.55

Field Name : custom3
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 3
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.54

Field Name : custom2
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 2
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.53

Field Name : custom1
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom signal 1
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.52

Field Name : other
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list

Description : Unknown Attack

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.40

Field Name : xmlError

Field Type : CounterBasedGauge64

Field Status : current

Description : XML Encoding Error

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.51

Field Name : weaktls

Field Type : CounterBasedGauge64

Field Status : current

Description : Weak TLS

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.39

Field Name : tornode

Field Type : CounterBasedGauge64

Field Status : current

Description : Tor Traffic

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.38

Field Name : siteFlaggedIp

Field Type : CounterBasedGauge64

Field Status : current

Description : Site Flagged IP

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.50

Field Name : impostor

Field Type : CounterBasedGauge64

Field Status : current

Description : SearchBot Impostor

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.37

Field Name : scanner

Field Type : CounterBasedGauge64

Field Status : current

Description : Scanner

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.36

Field Name : privatefile

Field Type : CounterBasedGauge64

Field Status : current

Description : Private File

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.35

Field Name : nullbyte

Field Type : CounterBasedGauge64

Field Status : current

Description : Null Byte

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.34

Field Name : noua

Field Type : CounterBasedGauge64

Field Status : current

Description : No User Agent

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.33

ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list

Field Name : noCtype
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing Content-Type Request Header
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.32

Field Name : sigsciIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Network Effect
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.31

Field Name : sans
Field Type : CounterBasedGauge64
Field Status : current
Description : Malicious IP Traffic
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.30

Field Name : malformed
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed Data in the Request Body
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.29

Field Name : jsonError
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Encoding Error
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.49

Field Name : notutf8
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Encoding
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.28

Field Name : respsplit
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Response Splitting
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.27

Field Name : http5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP 5xx Errors
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.26

Field Name : http503
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP 503 Errors
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.25

Field Name : http500
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list

Description : HTTP 500 Errors

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.24

Field Name : http4xx

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP 4xx Errors

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.23

Field Name : http429

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP 429 Errors

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.22

Field Name : http404

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP 404 Errors

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.21

Field Name : http403

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP 403 Errors

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.20

Field Name : graphqlUnusedVariables

Field Type : CounterBasedGauge64

Field Status : current

Description : GRAPHQL-UNUSED-VARIABLES

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.48

Field Name : graphqlIntrospection

Field Type : CounterBasedGauge64

Field Status : current

Description : GraphQL Introspection

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.47

Field Name : graphqlIde

Field Type : CounterBasedGauge64

Field Status : current

Description : GraphQL IDE

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.46

Field Name : fbrowsing

Field Type : CounterBasedGauge64

Field Status : current

Description : Forceful Browsing

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.19

Field Name : duplicateHeaders

Field Type : CounterBasedGauge64

Field Status : current

Description : Duplicate Header Names

OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.45

ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list

Field Name : doubleenc
Field Type : CounterBasedGauge64
Field Status : current
Description : Double Encoding
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.18

Field Name : datacenter
Field Type : CounterBasedGauge64
Field Status : current
Description : Datacenter Traffic
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.17

Field Name : codei
Field Type : CounterBasedGauge64
Field Status : current
Description : Code Injection PHP
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.16

Field Name : block
Field Type : CounterBasedGauge64
Field Status : current
Description : Blocked Requests
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.15

Field Name : bhh
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Hop Headers
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.14

Field Name : abnormalpath
Field Type : CounterBasedGauge64
Field Status : current
Description : Abnormal Path
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.44

Field Name : sqli
Field Type : CounterBasedGauge64
Field Status : current
Description : SQL Injection
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.13

Field Name : log4jJndi
Field Type : CounterBasedGauge64
Field Status : current
Description : Log4J JNDI
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.43

Field Name : graphqlDepth
Field Type : CounterBasedGauge64
Field Status : current
Description : GraphQL Max Depth
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.42

Field Name : traversal
Field Type : CounterBasedGauge64
Field Status : current

ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list

Description : Directory Traversal
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.12

Field Name : xss
Field Type : CounterBasedGauge64
Field Status : current
Description : Cross Site Scripting
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.11

Field Name : cmdexe
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Execution
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.10

Field Name : backdoor
Field Type : CounterBasedGauge64
Field Status : current
Description : Backdoor
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.9

Field Name : awsSsrF
Field Type : CounterBasedGauge64
Field Status : current
Description : AWS SSRF
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.8

Field Name : useragent
Field Type : CounterBasedGauge64
Field Status : current
Description : Attack Tooling
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.7

Field Name : error
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Happened
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.6

Field Name : reqBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Bypassed
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.5

Field Name : reqMarked
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Marked
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.41

Field Name : reqRedirected
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Redirected
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.116

ACOS-NG-WAF-STATS-MIB_acosNgWaf_oid_list

Field Name : reqBlocked
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Blocked
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.4

Field Name : reqForward
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Forwarded
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.3

Field Name : reqReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Received
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : ng-waf name
OID : 1.3.6.1.4.1.22610.2.4.10.202.2.1.1.1.1

ACOS-NGWAF-STATUS-MIB_oid_list

Field Name : statusOperPartitionListTable
Field Type : TABLE
Field Status : current
Description : NGWAFStatus from object 'ng-waf.status'
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3

Field Name : statusOperTable
Field Type : TABLE
Field Status : current
Description : NGWAFStatus from object 'ng-waf.status'
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.2

Field Name : statusOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statusOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.2.1

Field Name : statusOperNgwafVersion
Field Type : String
Field Status : current
Description : ngwaf-version
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.2.1.2

Field Name : statusOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.2.1.1

Field Name : statusOperPartitionListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statusOperPartitionList entry:partition-list
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1

Field Name : statusOperPartitionListTrackedCustomSignal
Field Type : CounterBasedGauge64
Field Status : current
Description : tracked-custom-signal
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.9

Field Name : statusOperPartitionListCacheEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : cache-entries
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.8

Field Name : statusOperPartitionListCpu
Field Type : String
Field Status : current
Description : cpu
OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.10

Field Name : statusOperPartitionListSecretAccessKey
Field Type : String
Field Status : current

ACOS-NGWAF-STATUS-MIB_oid_list

Description : secret-access-key

OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.7

Field Name : statusOperPartitionListAccessKeyId

Field Type : String

Field Status : current

Description : access-key-id

OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.6

Field Name : statusOperPartitionListAgentName

Field Type : String

Field Status : current

Description : agent-name

OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.5

Field Name : statusOperPartitionListStatus

Field Type : String

Field Status : current

Description : status

OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.4

Field Name : statusOperPartitionListPartitionName

Field Type : String

Field Status : current

Description : partition-name

OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.3

Field Name : statusOperPartitionListPartitionListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.2

Field Name : statusOperPartitionListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.386.1.3.1.1

ACOS-OVERLAY-TUNNEL-STATS-MIB_acosOverlayTunnel_oid_list

Field Name : overlayTunnelVtepSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1

Field Name : overlayTunnelVtepSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1

Field Name : lifUnInitRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Lif uninitialized packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.38

Field Name : fragDropPktsTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Frag dropped packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.37

Field Name : badInnerIpv6LenRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad inner ipv6 packet len
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.36

Field Name : badInnerIpv4LenRx
Field Type : CounterBasedGauge64
Field Status : current
Description : bad inner ipv4 packet len
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.35

Field Name : reassembledPktsRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Reassembled packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.34

Field Name : fragPktsTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Frag packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.33

Field Name : dot1qPktsRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Dot1q packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.32

Field Name : largePktsRx
Field Type : CounterBasedGauge64
Field Status : current

ACOS-OVERLAY-TUNNEL-STATS-MIB_acosOverlayTunnel_oid_list

Description : Too large packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.31

Field Name : droppedPktsTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Dropped packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.30

Field Name : mcastPktTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Multicast packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.29

Field Name : bcastPktTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Broadcast packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.28

Field Name : unicastPktTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Unicast packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.27

Field Name : totalBytesTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet bytes out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.26

Field Name : pktsOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.25

Field Name : requeuePktsIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Requeued packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.24

Field Name : badChksumPkRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad checksum in received packets
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.23

Field Name : encapMissPktsRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Encap missed in received packets
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.22

ACOS-OVERLAY-TUNNEL-STATS-MIB_acosOverlayTunnel_oid_list

Field Name : droppedPktRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Dropped received packets
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.21

Field Name : mcastPktRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Total multicast packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.20

Field Name : bcastPktRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Total broadcast packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.19

Field Name : unicastPktRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Total unicast packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.18

Field Name : totalBytesRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packet bytes in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.17

Field Name : totalPktsRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.16

Field Name : unhandledPktTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Unhandled packets out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.15

Field Name : unhandledPktRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Unhandled packets in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.14

Field Name : unknownVtepRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Vtep Unkown rx
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.13

Field Name : unknownVtepTx
Field Type : CounterBasedGauge64
Field Status : current

ACOS-OVERLAY-TUNNEL-STATS-MIB_acosOverlayTunnel_oid_list

Description : Vtep unknown tx
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.12

Field Name : invalidLifTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Lif pkts out
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.11

Field Name : invalidLifRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Lif pkts in
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.10

Field Name : vtepHostLearnError
Field Type : CounterBasedGauge64
Field Status : current
Description : Host learn error
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.9

Field Name : vtepHostLearned
Field Type : CounterBasedGauge64
Field Status : current
Description : Hosts learned
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.8

Field Name : arpReqSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Arp request sent
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.7

Field Name : unknownEncapTxPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Encap miss tx pkts
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.6

Field Name : unknownEncapRxPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Encap miss rx pkts
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.5

Field Name : encapUnresolvedCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Encap unresolved failures
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.4

Field Name : floodedPktCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Flooded packet count
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.3

ACOS-OVERLAY-TUNNEL-STATS-MIB_acosOverlayTunnel_oid_list

Field Name : cfgErrCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Config errors
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.2

Field Name : id
Field Type : INTEGER
Field Status : current
Description : VTEP Identifier
OID : 1.3.6.1.4.1.22610.2.4.10.128.2.1.1.1.1

ACOS-PARTITION-STATS-MIB_acosPartition_oid_list

Field Name : partitionSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.6.1.1

Field Name : partitionSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.6.1.1.1

Field Name : countersCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : dummy counter for infra
OID : 1.3.6.1.4.1.22610.2.4.10.6.1.1.1.2

Field Name : partitionName
Field Type : String
Field Status : current
Description : Object partition name
OID : 1.3.6.1.4.1.22610.2.4.10.6.1.1.1.1

ACOS-PKI-CERT-STATS-MIB_oid_list

Field Name : certStatsOperTable
Field Type : TABLE
Field Status : current
Description : from object 'pki.cert-stats'
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2

Field Name : certStatsOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The certStatsOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2.1

Field Name : certStatsOperPartition
Field Type : String
Field Status : current
Description : partition
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2.1.5

Field Name : certStatsOperCaCertCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ca-cert-count
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2.1.4

Field Name : certStatsOperKeyCount
Field Type : CounterBasedGauge64
Field Status : current
Description : key-count
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2.1.3

Field Name : certStatsOperCertCount
Field Type : CounterBasedGauge64
Field Status : current
Description : cert-count
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2.1.2

Field Name : certStatsOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.273.1.2.1.1

ACOS-RULE-SET-MIB_oid_list

Field Name : ruleSetOperRuleStatsTable
Field Type : TABLE
Field Status : current
Description : ConfigureSecurityPolicyRuleSet from object 'rule-set'
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3

Field Name : ruleSetOperTable
Field Type : TABLE
Field Status : current
Description : ConfigureSecurityPolicyRuleSet from object 'rule-set'
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2

Field Name : ruleSetOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ruleSetOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1

Field Name : ruleSetOperTopnRules
Field Type : String
Field Status : current
Description : topn-rules
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.23

Field Name : ruleSetOperShowTotalStats
Field Type : String
Field Status : current
Description : show-total-stats
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.22

Field Name : ruleSetOperTotalActiveOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : total-active-others
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.21

Field Name : ruleSetOperTotalActiveIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : total-active-icmp
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.20

Field Name : ruleSetOperTotalActiveUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : total-active-udp
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.19

Field Name : ruleSetOperTotalActiveTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : total-active-tcp
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.18

Field Name : ruleSetOperTotalPackets
Field Type : CounterBasedGauge64
Field Status : current

ACOS-RULE-SET-MIB_oid_list

Description : total-packets
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.17

Field Name : ruleSetOperTotalResetPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : total-reset-packets
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.16

Field Name : ruleSetOperTotalDenyPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : total-deny-packets
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.15

Field Name : ruleSetOperTotalPermitPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : total-permit-packets
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.14

Field Name : ruleSetOperTotalBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.13

Field Name : ruleSetOperTotalResetBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total-reset-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.12

Field Name : ruleSetOperTotalDenyBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total-deny-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.11

Field Name : ruleSetOperTotalPermitBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total-permit-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.10

Field Name : ruleSetOperTotalHit
Field Type : CounterBasedGauge64
Field Status : current
Description : total-hit
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.9

Field Name : ruleSetOperPolicyRuleCount
Field Type : CounterBasedGauge64
Field Status : current
Description : policy-rule-count
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.8

ACOS-RULE-SET-MIB_oid_list

Field Name : ruleSetOperPolicyReset
Field Type : CounterBasedGauge64
Field Status : current
Description : policy-reset
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.7

Field Name : ruleSetOperPolicyDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : policy-deny
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.6

Field Name : ruleSetOperPolicyPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : policy-permit
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.5

Field Name : ruleSetOperPolicyUnmatchedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : policy-unmatched-drop
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.4

Field Name : ruleSetOperPolicyStatus
Field Type : String
Field Status : current
Description : policy-status
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.3

Field Name : ruleSetOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.2

Field Name : ruleSetOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.2.1.1

Field Name : ruleSetStatsTable
Field Type : TABLE
Field Status : current
Description : ConfigureSecurityPolicyRuleSet from object 'rule-set'
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1

Field Name : ruleSetStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ruleSetStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1

Field Name : ruleSetStatsReset
Field Type : CounterBasedGauge64
Field Status : current

ACOS-RULE-SET-MIB_oid_list

Description : reset

OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1.6

Field Name : ruleSetStatsDeny

Field Type : CounterBasedGauge64

Field Status : current

Description : deny

OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1.5

Field Name : ruleSetStatsPermit

Field Type : CounterBasedGauge64

Field Status : current

Description : permit

OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1.4

Field Name : ruleSetStatsUnmatchedDrops

Field Type : CounterBasedGauge64

Field Status : current

Description : unmatched-drops

OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1.3

Field Name : ruleSetStatsName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1.2

Field Name : ruleSetStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.470.1.1.1.1

Field Name : ruleSetOperRuleStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The ruleSetOperRuleStats entry:rule-stats

OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1

Field Name : ruleSetOperRuleStatsRuleStatus

Field Type : String

Field Status : current

Description : rule-status

OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.7

Field Name : ruleSetOperRuleStatsRuleAction

Field Type : String

Field Status : current

Description : rule-action

OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.6

Field Name : ruleSetOperRuleStatsRuleHitcount

Field Type : CounterBasedGauge64

Field Status : current

Description : rule-hitcount

OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.5

ACOS-RULE-SET-MIB_oid_list

Field Name : ruleSetOperRuleStatsRuleName
Field Type : String
Field Status : current
Description : rule-name
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.4

Field Name : ruleSetOperRuleStatsRuleStatsListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.3

Field Name : ruleSetOperRuleStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.2

Field Name : ruleSetOperRuleStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.470.1.3.1.1

ACOS-RULESET-RULE-MIB_oid_list

Field Name : ruleOperTable
Field Type : TABLE
Field Status : current
Description : ConfigureRuleSetRule from object 'rule-set.rule'
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2

Field Name : ruleOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ruleOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1

Field Name : ruleOperTcphalfopencount
Field Type : CounterBasedGauge64
Field Status : current
Description : tcphalfopencount
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.33

Field Name : ruleOperVerificationfailed
Field Type : CounterBasedGauge64
Field Status : current
Description : verificationfailed
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.32

Field Name : ruleOperVerificationpassed
Field Type : CounterBasedGauge64
Field Status : current
Description : verificationpassed
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.31

Field Name : ruleOperSynacksent
Field Type : CounterBasedGauge64
Field Status : current
Description : synacksent
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.30

Field Name : ruleOperSyncookieon
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookieon
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.29

Field Name : ruleOperRatelimitdrops
Field Type : CounterBasedGauge64
Field Status : current
Description : ratelimitdrops
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.28

Field Name : ruleOperSessiontotal
Field Type : CounterBasedGauge64
Field Status : current
Description : sessiontotal
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.27

Field Name : ruleOperSessionother
Field Type : CounterBasedGauge64
Field Status : current

ACOS-RULESET-RULE-MIB_oid_list

Description : sessionother
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.26

Field Name : ruleOperSessionsctp
Field Type : CounterBasedGauge64
Field Status : current
Description : sessionsctp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.25

Field Name : ruleOperSessionicmp
Field Type : CounterBasedGauge64
Field Status : current
Description : sessionicmp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.24

Field Name : ruleOperSessionudp
Field Type : CounterBasedGauge64
Field Status : current
Description : sessionudp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.23

Field Name : ruleOperSessiontcp
Field Type : CounterBasedGauge64
Field Status : current
Description : sessiontcp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.22

Field Name : ruleOperActivesessiontotal
Field Type : CounterBasedGauge64
Field Status : current
Description : activesessiontotal
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.21

Field Name : ruleOperActivesessionother
Field Type : CounterBasedGauge64
Field Status : current
Description : activesessionother
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.20

Field Name : ruleOperActivesessionsctp
Field Type : CounterBasedGauge64
Field Status : current
Description : activesessionsctp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.19

Field Name : ruleOperActivesessionicmp
Field Type : CounterBasedGauge64
Field Status : current
Description : activesessionicmp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.18

Field Name : ruleOperActivesessionudp
Field Type : CounterBasedGauge64
Field Status : current
Description : activesessionudp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.17

ACOS-RULESET-RULE-MIB_oid_list

Field Name : ruleOperActivesessiontcp
Field Type : CounterBasedGauge64
Field Status : current
Description : activesessiontcp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.16

Field Name : ruleOperTotalpackets
Field Type : CounterBasedGauge64
Field Status : current
Description : totalpackets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.15

Field Name : ruleOperResetpackets
Field Type : CounterBasedGauge64
Field Status : current
Description : resetpackets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.14

Field Name : ruleOperDenypackets
Field Type : CounterBasedGauge64
Field Status : current
Description : deny packets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.13

Field Name : ruleOperPermitpackets
Field Type : CounterBasedGauge64
Field Status : current
Description : permitpackets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.12

Field Name : ruleOperTotalbytes
Field Type : CounterBasedGauge64
Field Status : current
Description : totalbytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.11

Field Name : ruleOperResetbytes
Field Type : CounterBasedGauge64
Field Status : current
Description : resetbytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.10

Field Name : ruleOperDenybytes
Field Type : CounterBasedGauge64
Field Status : current
Description : denybytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.9

Field Name : ruleOperPermitbytes
Field Type : CounterBasedGauge64
Field Status : current
Description : permitbytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.8

Field Name : ruleOperStatus
Field Type : String
Field Status : current

ACOS-RULESET-RULE-MIB_oid_list

Description : status

OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.7

Field Name : ruleOperAction

Field Type : String

Field Status : current

Description : action

OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.6

Field Name : ruleOperLastHitcountTime

Field Type : String

Field Status : current

Description : last-hitcount-time

OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.5

Field Name : ruleOperHitcount

Field Type : CounterBasedGauge64

Field Status : current

Description : hitcount

OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.4

Field Name : ruleOperName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.3

Field Name : ruleOperRuleSetName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.2

Field Name : ruleOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.471.1.2.1.1

Field Name : ruleStatsTable

Field Type : TABLE

Field Status : current

Description : ConfigureRuleSetRule from object 'rule-set.rule'

OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1

Field Name : ruleStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The ruleStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1

Field Name : ruleStatsTcpHalfOpenCount

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp-half-open-count

OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.27

ACOS-RULESET-RULE-MIB_oid_list

Field Name : ruleStatsSynCookieConnSetupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : syn-cookie-conn-setup-failed
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.26

Field Name : ruleStatsSynCookieVerificationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : syn-cookie-verification-failed
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.25

Field Name : ruleStatsSynCookieVerificationPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : syn-cookie-verification-passed
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.24

Field Name : ruleStatsSynCookieSynAckSent
Field Type : CounterBasedGauge64
Field Status : current
Description : syn-cookie-syn-ack-sent
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.23

Field Name : ruleStatsRateLimitDrops
Field Type : CounterBasedGauge64
Field Status : current
Description : rate-limit-drops
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.22

Field Name : ruleStatsHitcountTimestamp
Field Type : CounterBasedGauge64
Field Status : current
Description : hitcount-timestamp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.21

Field Name : ruleStatsSessionSctp
Field Type : CounterBasedGauge64
Field Status : current
Description : session-sctp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.20

Field Name : ruleStatsActiveSessionSctp
Field Type : CounterBasedGauge64
Field Status : current
Description : active-session-sctp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.19

Field Name : ruleStatsSessionOther
Field Type : CounterBasedGauge64
Field Status : current
Description : session-other
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.18

Field Name : ruleStatsSessionIcmp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-RULESET-RULE-MIB_oid_list

Description : session-icmp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.17

Field Name : ruleStatsSessionUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : session-udp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.16

Field Name : ruleStatsSessionTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : session-tcp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.15

Field Name : ruleStatsActiveSessionOther
Field Type : CounterBasedGauge64
Field Status : current
Description : active-session-other
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.14

Field Name : ruleStatsActiveSessionIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : active-session-icmp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.13

Field Name : ruleStatsActiveSessionUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : active-session-udp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.12

Field Name : ruleStatsActiveSessionTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : active-session-tcp
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.11

Field Name : ruleStatsResetPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : reset-packets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.10

Field Name : ruleStatsDenyPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : deny-packets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.9

Field Name : ruleStatsPermitPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : permit-packets
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.8

ACOS-RULESET-RULE-MIB_oid_list

Field Name : ruleStatsResetBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : reset-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.7

Field Name : ruleStatsDenyBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : deny-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.6

Field Name : ruleStatsPermitBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : permit-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.5

Field Name : ruleStatsHitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : hit-count
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.4

Field Name : ruleStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.3

Field Name : ruleStatsRuleSetName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.2

Field Name : ruleStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.471.1.1.1.1

ACOS-RULESET-RULES-BY-ZONE-MIB_oid_list

Field Name : rulesByZoneOperGroupListRuleListDscpListTable
Field Type : TABLE
Field Status : current
Description : from object 'rule-set.rules-by-zone'
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7

Field Name : rulesByZoneOperGroupListRuleListServiceListTable
Field Type : TABLE
Field Status : current
Description : from object 'rule-set.rules-by-zone'
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6

Field Name : rulesByZoneOperGroupListRuleListServiceListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rulesByZoneOperGroupListRuleListServiceList entry:service-list
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1

Field Name : rulesByZoneOperGroupListRuleListServiceListService
Field Type : String
Field Status : current
Description : service
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1.6

Field Name : rulesByZoneOperGroupListRuleListServiceListServiceListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1.5

Field Name : rulesByZoneOperGroupListRuleListServiceListRuleListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1.4

Field Name : rulesByZoneOperGroupListRuleListServiceListGroupListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1.3

Field Name : rulesByZoneOperGroupListRuleListServiceListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1.2

Field Name : rulesByZoneOperGroupListRuleListServiceListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.6.1.1

Field Name : rulesByZoneOperGroupListRuleListDestListTable
Field Type : TABLE
Field Status : current

ACOS-RULESET-RULES-BY-ZONE-MIB_oid_list

Description : from object 'rule-set.rules-by-zone'

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5

Field Name : rulesByZoneOperGroupListRuleListDestListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The rulesByZoneOperGroupListRuleListDestList entry:dest-list

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1

Field Name : rulesByZoneOperGroupListRuleListDestListDest

Field Type : String

Field Status : current

Description : dest

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1.6

Field Name : rulesByZoneOperGroupListRuleListDestListDestListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1.5

Field Name : rulesByZoneOperGroupListRuleListDestListRuleListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1.4

Field Name : rulesByZoneOperGroupListRuleListDestListGroupListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1.3

Field Name : rulesByZoneOperGroupListRuleListDestListName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1.2

Field Name : rulesByZoneOperGroupListRuleListDestListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.5.1.1

Field Name : rulesByZoneOperGroupListRuleListSourceListTable

Field Type : TABLE

Field Status : current

Description : from object 'rule-set.rules-by-zone'

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4

Field Name : rulesByZoneOperGroupListRuleListSourceListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The rulesByZoneOperGroupListRuleListSourceList entry:source-list

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1

ACOS-RULESET-RULES-BY-ZONE-MIB_oid_list

Field Name : rulesByZoneOperGroupListRuleListSourceListSource
Field Type : String
Field Status : current
Description : source
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1.6

Field Name : rulesByZoneOperGroupListRuleListSourceListSourceListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1.5

Field Name : rulesByZoneOperGroupListRuleListSourceListRuleListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1.4

Field Name : rulesByZoneOperGroupListRuleListSourceListGroupListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1.3

Field Name : rulesByZoneOperGroupListRuleListSourceListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1.2

Field Name : rulesByZoneOperGroupListRuleListSourceListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.4.1.1

Field Name : rulesByZoneOperGroupListRuleListTable
Field Type : TABLE
Field Status : current
Description : from object 'rule-set.rules-by-zone'
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3

Field Name : rulesByZoneOperGroupListRuleListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rulesByZoneOperGroupListRuleList entry:rule-list
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1

Field Name : rulesByZoneOperGroupListRuleListAction
Field Type : String
Field Status : current
Description : action
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1.6

Field Name : rulesByZoneOperGroupListRuleListName1
Field Type : String
Field Status : current

ACOS-RULESET-RULES-BY-ZONE-MIB_oid_list

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1.5

Field Name : rulesByZoneOperGroupListRuleListRuleListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1.4

Field Name : rulesByZoneOperGroupListRuleListGroupListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1.3

Field Name : rulesByZoneOperGroupListRuleListName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1.2

Field Name : rulesByZoneOperGroupListRuleListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.3.1.1

Field Name : rulesByZoneOperGroupListTable

Field Type : TABLE

Field Status : current

Description : from object 'rule-set.rules-by-zone'

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2

Field Name : rulesByZoneOperGroupListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The rulesByZoneOperGroupList entry:group-list

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2.1

Field Name : rulesByZoneOperGroupListTo

Field Type : String

Field Status : current

Description : to

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2.1.5

Field Name : rulesByZoneOperGroupListFrom

Field Type : String

Field Status : current

Description : from

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2.1.4

Field Name : rulesByZoneOperGroupListGroupListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2.1.3

ACOS-RULESET-RULES-BY-ZONE-MIB_oid_list

Field Name : rulesByZoneOperGroupListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2.1.2

Field Name : rulesByZoneOperGroupListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.2.1.1

Field Name : rulesByZoneStatsTable
Field Type : TABLE
Field Status : current
Description : from object 'rule-set.rules-by-zone'
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.1

Field Name : rulesByZoneStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rulesByZoneStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.1.1

Field Name : rulesByZoneStatsDummy
Field Type : CounterBasedGauge64
Field Status : current
Description : dummy
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.1.1.3

Field Name : rulesByZoneStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.1.1.2

Field Name : rulesByZoneStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.1.1.1

Field Name : rulesByZoneOperGroupListRuleListDscpListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The rulesByZoneOperGroupListRuleListDscpList entry:dscp-list
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1

Field Name : rulesByZoneOperGroupListRuleListDscpListDscp
Field Type : String
Field Status : current
Description : dscp
OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1.6

Field Name : rulesByZoneOperGroupListRuleListDscpListDscpListListId
Field Type : Integer32
Field Status : current

ACOS-RULESET-RULES-BY-ZONE-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1.5

Field Name : rulesByZoneOperGroupListRuleListDscpListRuleListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1.4

Field Name : rulesByZoneOperGroupListRuleListDscpListGroupListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1.3

Field Name : rulesByZoneOperGroupListRuleListDscpListName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1.2

Field Name : rulesByZoneOperGroupListRuleListDscpListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.472.1.7.1.1

ACOS-RULE-SET-STATS-MIB_acosRuleSet_oid_list

Field Name : ruleSetSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1

Field Name : ruleSetSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1.1

Field Name : reset
Field Type : CounterBasedGauge64
Field Status : current
Description : Reset counter
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1.1.5

Field Name : deny
Field Type : CounterBasedGauge64
Field Status : current
Description : Denied counter
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1.1.4

Field Name : permit
Field Type : CounterBasedGauge64
Field Status : current
Description : Permitted counter
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1.1.3

Field Name : unmatchedDrops
Field Type : CounterBasedGauge64
Field Status : current
Description : Unmatched drops counter
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Rule set name
OID : 1.3.6.1.4.1.22610.2.4.10.138.1.1.1.1

ACOS-SCTP-GLOBAL-MIB_oid_list

Field Name : globalStatsTable
Field Type : TABLE
Field Status : current
Description : SCTPStatistics from object 'sctp.global'
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1

Field Name : globalStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The globalStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1

Field Name : globalStatsPktAsconfParamLenErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : pkt-asconf-param-len-err-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.67

Field Name : globalStatsPktChunkLenErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : pkt-chunk-len-err-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.66

Field Name : globalStatsPktLenErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : pkt-len-err-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.65

Field Name : globalStatsSctpInitVtagZeroDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-init-vtag-zero-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.64

Field Name : globalStatsSctpAsconfProcessDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-asconf-process-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.63

Field Name : globalStatsSctpRetxInit
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-retx-init
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.62

Field Name : globalStatsSctpRetxInitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-retx-init-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.61

Field Name : globalStatsSctpRetxInitAck
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SCTP-GLOBAL-MIB_oid_list

Description : sctp-retx-init-ack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.60

Field Name : globalStatsSctpNoExtMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-no-ext-match
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.59

Field Name : globalStatsSctpRouteErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-route-err-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.58

Field Name : globalStatsSctpRerouteFailover
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-reroute-failover
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.57

Field Name : globalStatsSctpRouteErrHeartbeatDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-route-err-heartbeat-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.56

Field Name : globalStatsSctpRetxInitAckDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-retx-init-ack-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.55

Field Name : globalStatsSctpChunkHeartBeatClubbed
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-heart-beat-clubbed
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.54

Field Name : globalStatsSctpChunkTypeAbortDataDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-abort-data-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.53

Field Name : globalStatsSctpChunkTypeShutdownCompleteDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-shutdown-complete-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.52

Field Name : globalStatsSctpChunkTypeInitAckDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-init-ack-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.51

ACOS-SCTP-GLOBAL-MIB_oid_list

Field Name : globalStatsSctpChunkTypeInitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-init-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.50

Field Name : globalStatsSctpDataNoExtMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-data-no-ext-match
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.49

Field Name : globalStatsSctpDataNoTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-data-no-tuple
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.48

Field Name : globalStatsSctpHeartbeatNoTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-heartbeat-no-tuple
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.47

Field Name : globalStatsSctpChunkTypeOther
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-other
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.46

Field Name : globalStatsSctpChunkTypeHeartbeatAck
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-heartbeat-ack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.45

Field Name : globalStatsSctpChunkTypeHeartbeat
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-heartbeat
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.44

Field Name : globalStatsSctpChunkTypeErrorOp
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-error-op
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.43

Field Name : globalStatsSctpChunkTypeShutdownComplete
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-shutdown-complete
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.42

Field Name : globalStatsSctpChunkTypeShutdownAck
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SCTP-GLOBAL-MIB_oid_list

Description : sctp-chunk-type-shutdown-ack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.41

Field Name : globalStatsSctpChunkTypeShutdown
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-shutdown
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.40

Field Name : globalStatsSctpChunkTypeAbort
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-abort
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.39

Field Name : globalStatsSctpChunkTypeData
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-data
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.38

Field Name : globalStatsSctpChunkTypeAsconfAck
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-asconf-ack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.37

Field Name : globalStatsSctpChunkTypeAsconf
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-asconf
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.36

Field Name : globalStatsSctpChunkTypeSack
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-sack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.35

Field Name : globalStatsSctpChunkTypeCookieAck
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-cookie-ack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.34

Field Name : globalStatsSctpChunkTypeCookieEcho
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-cookie-echo
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.33

Field Name : globalStatsSctpChunkTypeInitAck
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-init-ack
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.32

ACOS-SCTP-GLOBAL-MIB_oid_list

Field Name : globalStatsSctpChunkTypeInit
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-chunk-type-init
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.31

Field Name : globalStatsBadAlignmentDropShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-alignment-drop-shadow
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.30

Field Name : globalStatsBadPayloadDropShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-payload-drop-shadow
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.29

Field Name : globalStatsBadCsumShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-csum-shadow
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.28

Field Name : globalStatsConnExtSizeMax
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_ext_size_max
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.27

Field Name : globalStatsSctpOutOfSystemMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-out-of-system-memory
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.26

Field Name : globalStatsSbyStaticNatCfgNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : sby-static-nat-cfg-not-found
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.25

Field Name : globalStatsSbySessionUpdateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : sby-session-update-fail
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.24

Field Name : globalStatsSbySessionUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : sby-session-updated
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.23

Field Name : globalStatsSbySessionCreateFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SCTP-GLOBAL-MIB_oid_list

Description : sby-session-create-fail
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.22

Field Name : globalStatsSbySessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : sby-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.21

Field Name : globalStatsRateLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : rate-limit-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.20

Field Name : globalStatsDisallowedPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : disallowed-pkt-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.19

Field Name : globalStatsDisallowedChunkFiltered
Field Type : CounterBasedGauge64
Field Status : current
Description : disallowed-chunk-filtered
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.18

Field Name : globalStatsInvalidFragChunkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid-frag-chunk-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.17

Field Name : globalStatsVrrpStandbyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : vrrp-standby-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.16

Field Name : globalStatsCfgErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : cfg-err-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.15

Field Name : globalStatsStaticNatCfgNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : static-nat-cfg-not-found
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.14

Field Name : globalStatsMultiHomeAddrNotFoundDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : multi-home-addr-not-found-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.13

ACOS-SCTP-GLOBAL-MIB_oid_list

Field Name : globalStatsMultiHomeRemoveIpSkip
Field Type : CounterBasedGauge64
Field Status : current
Description : multi-home-remove-ip-skip
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.12

Field Name : globalStatsMaxMultiHomeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : max-multi-home-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.11

Field Name : globalStatsOosPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : oos-pkt-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.10

Field Name : globalStatsBadAlignmentDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-alignment-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.9

Field Name : globalStatsBadPayloadDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-payload-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.8

Field Name : globalStatsBadCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : bad-csum
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.7

Field Name : globalStatsPktErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : pkt-err-drop
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.6

Field Name : globalStatsSctpFwSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-fw-session-deleted
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.5

Field Name : globalStatsSctpFwSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : sctp-fw-session-created
OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.4

Field Name : globalStatsSctpStaticNatSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SCTP-GLOBAL-MIB_oid_list

Description : sctp-static-nat-session-deleted

OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.3

Field Name : globalStatsSctpStaticNatSessionCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : sctp-static-nat-session-created

OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.2

Field Name : globalStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.495.1.1.1.1

ACOS-SCTP-STATS-MIB_acoSctp_oid_list

Field Name : pktAsconfParamLenErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Parameter Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.66

Field Name : pktChunkLenErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Chunk Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.65

Field Name : pktLenErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Packet Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.64

Field Name : sctpInitVtagZeroDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP INIT VTAG ZERO drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.63

Field Name : sctpAsconfProcessDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP ASCONF process drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.62

Field Name : sctpRetxInit
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Retransmitted INIT
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.61

Field Name : sctpRetxInitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Retransmitted INIT drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.60

Field Name : sctpRetxInitAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type INIT_ACK retransmitted
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.59

Field Name : sctpNoExtMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP no extended match found
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.58

Field Name : sctpRouteErrDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SCTP-STATS-MIB_acosSctp_oid_list

Description : SCTP ROUTE lookup failed for chunks other than HEARTBEAT drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.57

Field Name : sctpRerouteFailover
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP REROUTE lookup for chunks other than HEARTBEAT
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.56

Field Name : sctpRouteErrHeartbeatDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP HEARTBEAT ROUTE lookup failed drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.55

Field Name : sctpRetxInitAckDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type INIT_ACK with retx mismatched vtag drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.54

Field Name : sctpChunkHeartBeatClubbed
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP HEARTBEAT chunk with other chunk
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.53

Field Name : sctpChunkTypeAbortDataDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type with ABORT and DATA drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.52

Field Name : sctpChunkTypeShutdownCompleteDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type SHUTDOWN-COMPLETE drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.51

Field Name : sctpChunkTypeInitAckDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type INIT-ACK drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.50

Field Name : sctpChunkTypeInitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type INIT drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.49

Field Name : sctpDataNoExtMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP DATA no extended match found
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.48

ACOS-SCTP-STATS-MIB_acosSctp_oid_list

Field Name : sctpDataNoTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP DATA chunk no tuple found
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.47

Field Name : sctpHeartbeatNoTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP HEARTBEAT/ACK no tuple found
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.46

Field Name : sctpChunkTypeOther
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type OTHER
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.45

Field Name : sctpChunkTypeHeartbeatAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type HEARTBEAT-ACK
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.44

Field Name : sctpChunkTypeHeartbeat
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type HEARTBEAT
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.43

Field Name : sctpChunkTypeErrorOp
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type ERROR-OP
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.42

Field Name : sctpChunkTypeShutdownComplete
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type SHUTDOWN-COMPLETE
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.41

Field Name : sctpChunkTypeShutdownAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type SHUTDOWN-ACK
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.40

Field Name : sctpChunkTypeShutdown
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type SHUTDOWN
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.39

Field Name : sctpChunkTypeAbort
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SCTP-STATS-MIB_acoSctp_oid_list

Description : SCTP Chunk Type ABORT
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.38

Field Name : sctpChunkTypeData
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type DATA
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.37

Field Name : sctpChunkTypeAsconfAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type ASCONF-ACK
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.36

Field Name : sctpChunkTypeAsconf
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type ASCONF
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.35

Field Name : sctpChunkTypeSack
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type SACK
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.34

Field Name : sctpChunkTypeCookieAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type COOKIE-ACK
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.33

Field Name : sctpChunkTypeCookieEcho
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type COOKIE-ECHO
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.32

Field Name : sctpChunkTypeInitAck
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type INIT-ACK
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.31

Field Name : sctpChunkTypeInit
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Chunk Type INIT
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.30

Field Name : badAlignmentDropShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Packet Alignment Drop Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.29

ACOS-SCTP-STATS-MIB_acosSctp_oid_list

Field Name : badPayloadDropShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Packet Payload Drop Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.28

Field Name : badCsumShadow
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Checksum Shadow
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.27

Field Name : connExtSizeMax
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Conn Extension Size
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.26

Field Name : sctpOutOfSystemMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of System Memory
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.25

Field Name : sbyStaticNatCfgNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Static NAT Config Not Found on Standby
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.24

Field Name : sbySessionUpdateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Session Update Failed
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.23

Field Name : sbySessionUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Session Updated
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.22

Field Name : sbySessionCreateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Session Create Failed
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.21

Field Name : sbySessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Standby Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.20

Field Name : rateLimitDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SCTP-STATS-MIB_acosSctp_oid_list

Description : Rate-limit Drop

OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.19

Field Name : disallowedPktDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Disallowed Packet Drop

OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.18

Field Name : disallowedChunkFiltered

Field Type : CounterBasedGauge64

Field Status : current

Description : Disallowed Chunk Filtered

OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.17

Field Name : invalidFragChunkDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Invalid Fragmented Chunks Drop

OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.16

Field Name : vrrpStandbyDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : NAT Resource VRRP-A Standby Drop

OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.15

Field Name : cfgErrDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Configuration Error Drop

OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.14

Field Name : staticNatCfgNotFound

Field Type : CounterBasedGauge64

Field Status : current

Description : Static NAT Config Not Found Drop

OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.13

Field Name : multiHomeAddrNotFoundDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Multi-homing IP Address Not Found Drop

OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.12

Field Name : multiHomeRemoveIpSkip

Field Type : CounterBasedGauge64

Field Status : current

Description : Multi-homing Remove IP Parameter Skip

OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.11

Field Name : maxMultiHomeDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Maximum Multi-homing IP Addresses Drop

OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.10

ACOS-SCTP-STATS-MIB_acosSctp_oid_list

Field Name : oosPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-of-state Packet Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.9

Field Name : badAlignmentDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Alignment Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.8

Field Name : badPayloadDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Payload Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.7

Field Name : badCsum
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Checksum
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.6

Field Name : pktErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.5

Field Name : sctpFwSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Firewall Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.4

Field Name : sctpFirewallSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Firewall Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.3

Field Name : sctpStaticNatSessionDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Static NAT Session Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.2

Field Name : sctpStaticNatSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Static NAT Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.168.1.1.1

ACOS-SFLOW-STATS-MIB_acosSflow_oid_list

Field Name : totalSflowPacketsDropMgmt
Field Type : CounterBasedGauge64
Field Status : current
Description : sflow packets dropped because of rate limit via Mgmt Interface
OID : 1.3.6.1.4.1.22610.2.4.10.125.7.1.6

Field Name : totalSflowPacketsSentMgmt
Field Type : CounterBasedGauge64
Field Status : current
Description : Total sflow packets sent via Mgmt Interface
OID : 1.3.6.1.4.1.22610.2.4.10.125.7.1.5

Field Name : totalSflowLocalPacketsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total sflow packets sent desc {}
OID : 1.3.6.1.4.1.22610.2.4.10.125.7.1.4

Field Name : totalSflowPacketsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total sflow packets sent
OID : 1.3.6.1.4.1.22610.2.4.10.125.7.1.3

Field Name : totalCounterSampleRecords
Field Type : CounterBasedGauge64
Field Status : current
Description : Total counter sample records
OID : 1.3.6.1.4.1.22610.2.4.10.125.7.1.2

Field Name : totalPacketSampleRecords
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packet sample records
OID : 1.3.6.1.4.1.22610.2.4.10.125.7.1.1

ACOS-SLB-DNS-CACHE-MIB_oid_list

Field Name : dnsCacheOperCacheEntryEntryRecordTable
Field Type : TABLE
Field Status : current
Description : DNSCacheStatistics from object 'slb.dns-cache'
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5

Field Name : dnsCacheOperCacheEntryTable
Field Type : TABLE
Field Status : current
Description : DNSCacheStatistics from object 'slb.dns-cache'
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4

Field Name : dnsCacheOperCacheEntryEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCacheOperCacheEntry entry:cache-entry
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1

Field Name : dnsCacheOperCacheEntryArCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ar_count
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.17

Field Name : dnsCacheOperCacheEntryNsCount
Field Type : CounterBasedGauge64
Field Status : current
Description : ns_count
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.16

Field Name : dnsCacheOperCacheEntryAnCount
Field Type : CounterBasedGauge64
Field Status : current
Description : an_count
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.15

Field Name : dnsCacheOperCacheEntryHits
Field Type : CounterBasedGauge64
Field Status : current
Description : hits
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.14

Field Name : dnsCacheOperCacheEntryWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : weight
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.13

Field Name : dnsCacheOperCacheEntryAge
Field Type : CounterBasedGauge64
Field Status : current
Description : age
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.12

Field Name : dnsCacheOperCacheEntryTtl
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-DNS-CACHE-MIB_oid_list

Description : ttl

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.11

Field Name : dnsCacheOperCacheEntryRLength

Field Type : CounterBasedGauge64

Field Status : current

Description : r_length

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.10

Field Name : dnsCacheOperCacheEntryQLength

Field Type : CounterBasedGauge64

Field Status : current

Description : q_length

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.9

Field Name : dnsCacheOperCacheEntryCacheClass

Field Type : CounterBasedGauge64

Field Status : current

Description : cache_class

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.8

Field Name : dnsCacheOperCacheEntryCacheType

Field Type : CounterBasedGauge64

Field Status : current

Description : cache_type

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.7

Field Name : dnsCacheOperCacheEntryCacheNegative

Field Type : CounterBasedGauge64

Field Status : current

Description : cache_negative

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.6

Field Name : dnsCacheOperCacheEntryDnssec

Field Type : CounterBasedGauge64

Field Status : current

Description : dnssec

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.5

Field Name : dnsCacheOperCacheEntryDomain

Field Type : String

Field Status : current

Description : domain

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.4

Field Name : dnsCacheOperCacheEntryName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.3

Field Name : dnsCacheOperCacheEntryCacheEntryListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.2

ACOS-SLB-DNS-CACHE-MIB_oid_list

Field Name : dnsCacheOperCacheEntrySlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.4.1.1

Field Name : dnsCacheOperCacheClientTable
Field Type : TABLE
Field Status : current
Description : DNSCacheStatistics from object 'slb.dns-cache'
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3

Field Name : dnsCacheOperCacheClientEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsCacheOperCacheClient entry:cache-client
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1

Field Name : dnsCacheOperCacheClientLockupTime
Field Type : CounterBasedGauge64
Field Status : current
Description : lockup_time
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.9

Field Name : dnsCacheOperCacheClientLockup
Field Type : CounterBasedGauge64
Field Status : current
Description : lockup
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.8

Field Name : dnsCacheOperCacheClientOverRateLimitTimes
Field Type : CounterBasedGauge64
Field Status : current
Description : over_rate_limit_times
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.7

Field Name : dnsCacheOperCacheClientCurrRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_rate
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.6

Field Name : dnsCacheOperCacheClientUnitType
Field Type : String
Field Status : current
Description : unit_type
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.5

Field Name : dnsCacheOperCacheClientAddress
Field Type : String
Field Status : current
Description : address
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.4

Field Name : dnsCacheOperCacheClientDomain
Field Type : String
Field Status : current

ACOS-SLB-DNS-CACHE-MIB_oid_list

Description : domain

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.3

Field Name : dnsCacheOperCacheClientCacheClientListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.2

Field Name : dnsCacheOperCacheClientSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.3.1.1

Field Name : dnsCacheOperTable

Field Type : TABLE

Field Status : current

Description : DNSCacheStatistics from object 'slb.dns-cache'

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2

Field Name : dnsCacheOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The dnsCacheOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1

Field Name : dnsCacheOperRecordAll

Field Type : Integer32

Field Status : current

Description : record-all

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.23

Field Name : dnsCacheOperRecordNumValue

Field Type : CounterBasedGauge64

Field Status : current

Description : record-num-value

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.22

Field Name : dnsCacheOperRdataAll

Field Type : Integer32

Field Status : current

Description : rdata-all

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.21

Field Name : dnsCacheOperRdataSizeValue

Field Type : CounterBasedGauge64

Field Status : current

Description : rdata-size-value

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.20

Field Name : dnsCacheOperContentMode

Field Type : String

Field Status : current

Description : content-mode

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.19

ACOS-SLB-DNS-CACHE-MIB_oid_list

Field Name : dnsCacheOperDomainName
Field Type : String
Field Status : current
Description : domain-name
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.18

Field Name : dnsCacheOperTypeString
Field Type : String
Field Status : current
Description : type-string
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.17

Field Name : dnsCacheOperClassValue
Field Type : CounterBasedGauge64
Field Status : current
Description : class-value
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.16

Field Name : dnsCacheOperClassString
Field Type : String
Field Status : current
Description : class-string
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.15

Field Name : dnsCacheOperFqdnDomain
Field Type : String
Field Status : current
Description : fqdn-domain
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.14

Field Name : dnsCacheOperTypeValue
Field Type : CounterBasedGauge64
Field Status : current
Description : type-value
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.13

Field Name : dnsCacheOperPortNum
Field Type : CounterBasedGauge64
Field Status : current
Description : port-num
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.12

Field Name : dnsCacheOperPortType
Field Type : String
Field Status : current
Description : port-type
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.11

Field Name : dnsCacheOperVsName
Field Type : String
Field Status : current
Description : vs-name
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.10

Field Name : dnsCacheOperVport
Field Type : Integer32
Field Status : current

ACOS-SLB-DNS-CACHE-MIB_oid_list

Description : vport

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.9

Field Name : dnsCacheOperCacheContent

Field Type : Integer32

Field Status : current

Description : cache-content

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.8

Field Name : dnsCacheOperTemplate

Field Type : String

Field Status : current

Description : template

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.25

Field Name : dnsCacheOperGlobal

Field Type : Integer32

Field Status : current

Description : global

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.7

Field Name : dnsCacheOperEntry1

Field Type : Integer32

Field Status : current

Description : entry

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.6

Field Name : dnsCacheOperClient

Field Type : Integer32

Field Status : current

Description : client

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.5

Field Name : dnsCacheOperHitRatioPercentagePerSec

Field Type : CounterBasedGauge64

Field Status : current

Description : hit_ratio_percentage_per_sec

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.24

Field Name : dnsCacheOperCacheHitRatio

Field Type : String

Field Status : current

Description : cache_hit_ratio

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.4

Field Name : dnsCacheOperCacheUsage

Field Type : String

Field Status : current

Description : cache_usage

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.3

Field Name : dnsCacheOperTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : total

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.2

ACOS-SLB-DNS-CACHE-MIB_oid_list

Field Name : dnsCacheOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.2.1.1

Field Name : dnsCacheStatsTable

Field Type : TABLE

Field Status : current

Description : DNSCacheStatistics from object 'slb.dns-cache'

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1

Field Name : dnsCacheStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The dnsCacheStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1

Field Name : dnsCacheStatsMultipleAnswerNoCache

Field Type : CounterBasedGauge64

Field Status : current

Description : multiple_answer_no_cache

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.27

Field Name : dnsCacheStatsHitRatePerSec

Field Type : CounterBasedGauge64

Field Status : current

Description : hit_rate_per_sec

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.26

Field Name : dnsCacheStatsQps

Field Type : CounterBasedGauge64

Field Status : current

Description : qps

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.25

Field Name : dnsCacheStatsTruncatedR

Field Type : CounterBasedGauge64

Field Status : current

Description : truncated_r

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.24

Field Name : dnsCacheStatsResolverQueueFull

Field Type : CounterBasedGauge64

Field Status : current

Description : resolver_queue_full

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.23

Field Name : dnsCacheStatsCurrentDataAllocate

Field Type : CounterBasedGauge64

Field Status : current

Description : current_data_allocate

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.22

Field Name : dnsCacheStatsCurrentAllocate

Field Type : CounterBasedGauge64

Field Status : current

ACOS-SLB-DNS-CACHE-MIB_oid_list

Description : current_allocate
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.21

Field Name : dnsCacheStatsTotalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : total_freed
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.20

Field Name : dnsCacheStatsTotalAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_alloc
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.19

Field Name : dnsCacheStatsTotalLog
Field Type : CounterBasedGauge64
Field Status : current
Description : total_log
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.18

Field Name : dnsCacheStatsAgeoutWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : ageout_weight
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.17

Field Name : dnsCacheStatsBadAnswer
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_answer
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.16

Field Name : dnsCacheStatsAgeout
Field Type : CounterBasedGauge64
Field Status : current
Description : ageout
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.15

Field Name : dnsCacheStatsTtlR
Field Type : CounterBasedGauge64
Field Status : current
Description : ttl_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.14

Field Name : dnsCacheStatsAnswerR
Field Type : CounterBasedGauge64
Field Status : current
Description : answer_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.13

Field Name : dnsCacheStatsMultipleR
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.12

ACOS-SLB-DNS-CACHE-MIB_oid_list

Field Name : dnsCacheStatsEncoder
Field Type : CounterBasedGauge64
Field Status : current
Description : encode_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.11

Field Name : dnsCacheStatsOversizeR
Field Type : CounterBasedGauge64
Field Status : current
Description : oversize_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.10

Field Name : dnsCacheStatsBadR
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.9

Field Name : dnsCacheStatsOversizeQ
Field Type : CounterBasedGauge64
Field Status : current
Description : oversize_q
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.8

Field Name : dnsCacheStatsMultipleQ
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple_q
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.7

Field Name : dnsCacheStatsEncodeQ
Field Type : CounterBasedGauge64
Field Status : current
Description : encode_q
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.6

Field Name : dnsCacheStatsBadQ
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_q
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.5

Field Name : dnsCacheStatsHit
Field Type : CounterBasedGauge64
Field Status : current
Description : hit
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.4

Field Name : dnsCacheStatsTotalR
Field Type : CounterBasedGauge64
Field Status : current
Description : total_r
OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.3

Field Name : dnsCacheStatsTotalQ
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-DNS-CACHE-MIB_oid_list

Description : total_q

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.2

Field Name : dnsCacheStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.1.1.1

Field Name : dnsCacheOperCacheEntryEntryRecordEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The dnsCacheOperCacheEntryEntryRecord entry:entry-record

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1

Field Name : dnsCacheOperCacheEntryEntryRecordRecordRdataTc

Field Type : CounterBasedGauge64

Field Status : current

Description : record_rdata_tc

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.9

Field Name : dnsCacheOperCacheEntryEntryRecordRecordRdata

Field Type : String

Field Status : current

Description : record_rdata

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.8

Field Name : dnsCacheOperCacheEntryEntryRecordRecordRdlen

Field Type : CounterBasedGauge64

Field Status : current

Description : record_rdlen

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.7

Field Name : dnsCacheOperCacheEntryEntryRecordRecordTtl

Field Type : CounterBasedGauge64

Field Status : current

Description : record_ttl

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.6

Field Name : dnsCacheOperCacheEntryEntryRecordRecordClass

Field Type : CounterBasedGauge64

Field Status : current

Description : record_class

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.5

Field Name : dnsCacheOperCacheEntryEntryRecordRecordType

Field Type : CounterBasedGauge64

Field Status : current

Description : record_type

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.4

Field Name : dnsCacheOperCacheEntryEntryRecordEntryRecordListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.3

ACOS-SLB-DNS-CACHE-MIB_oid_list

Field Name : dnsCacheOperCacheEntryEntryRecordCacheEntryListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.2

Field Name : dnsCacheOperCacheEntryEntryRecordSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.352.1.5.1.1

ACOS-SLB-DNS-MIB_oid_list

Field Name : dnsStatsTable
Field Type : TABLE
Field Status : current
Description : DNSPacketStatistics from object 'slb.dns'
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1

Field Name : dnsStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dnsStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1

Field Name : dnsStatsSlbDnsEdnsEcsInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_edns_ecs_inserted
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.37

Field Name : dnsStatsSlbDnsEdnsEcsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_edns_ecs_received
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.36

Field Name : dnsStatsInvalidQLenToUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid_q_len_to_udp
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.35

Field Name : dnsStatsNatSlbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_slb_drop
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.34

Field Name : dnsStatsSlbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_drop
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.33

Field Name : dnsStatsRpzActionLocalData
Field Type : CounterBasedGauge64
Field Status : current
Description : rpz_action_local_data
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.32

Field Name : dnsStatsRpzActionNodata
Field Type : CounterBasedGauge64
Field Status : current
Description : rpz_action_nodata
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.31

Field Name : dnsStatsRpzActionNxdomain
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-DNS-MIB_oid_list

Description : rpz_action_nxdomain

OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.30

Field Name : dnsStatsRpzActionTcpOnly

Field Type : CounterBasedGauge64

Field Status : current

Description : rpz_action_tcp_only

OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.29

Field Name : dnsStatsRpzActionPassThru

Field Type : CounterBasedGauge64

Field Status : current

Description : rpz_action_pass_thru

OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.28

Field Name : dnsStatsRpzActionDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : rpz_action_drop

OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.27

Field Name : dnsStatsSlbDnsUdpRetransmitFail

Field Type : CounterBasedGauge64

Field Status : current

Description : slb_dns_udp_retransmit_fail

OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.26

Field Name : dnsStatsSlbDnsUdpRetransmit

Field Type : CounterBasedGauge64

Field Status : current

Description : slb_dns_udp_retransmit

OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.25

Field Name : dnsStatsSlbDnsEdnsSubnetToServerRemoved

Field Type : CounterBasedGauge64

Field Status : current

Description : slb_dns_edns_subnet_to_server_removed

OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.24

Field Name : dnsStatsSlbDnsPaddingToClientAdded

Field Type : CounterBasedGauge64

Field Status : current

Description : slb_dns_padding_to_client_added

OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.23

Field Name : dnsStatsSlbDnsPaddingToServerRemoved

Field Type : CounterBasedGauge64

Field Status : current

Description : slb_dns_padding_to_server_removed

OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.22

Field Name : dnsStatsSlbDnsUdpConnSucc

Field Type : CounterBasedGauge64

Field Status : current

Description : slb_dns_udp_conn_succ

OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.21

ACOS-SLB-DNS-MIB_oid_list

Field Name : dnsStatsSlbDnsUdpConn
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_udp_conn
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.20

Field Name : dnsStatsSlbDnsServerSslSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_server_ssl_succ
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.19

Field Name : dnsStatsSlbDnsClientSslSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_dns_client_ssl_succ
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.18

Field Name : dnsStatsFilterTypeAnyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : filter_type_any_drop
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.17

Field Name : dnsStatsFilterClassDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : filter_class_drop
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.16

Field Name : dnsStatsFilterTypeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : filter_type_drop
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.15

Field Name : dnsStatsNatXidReused
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_xid_reused
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.14

Field Name : dnsStatsNatNoResource
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_no_resource
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.13

Field Name : dnsStatsNatRespNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_resp_no_match
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.12

Field Name : dnsStatsNatReqRexmit
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-DNS-MIB_oid_list

Description : nat_req_rexmit
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.11

Field Name : dnsStatsNatNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_no_resp
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.10

Field Name : dnsStatsNatResp
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_resp
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.9

Field Name : dnsStatsNatReq
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_req
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.8

Field Name : dnsStatsSlbNoResource
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_no_resource
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.7

Field Name : dnsStatsSlbRespNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_resp_no_match
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.6

Field Name : dnsStatsSlbReqRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_req_rexmit
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.5

Field Name : dnsStatsSlbNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_no_resp
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.4

Field Name : dnsStatsSlbResp
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_resp
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.3

Field Name : dnsStatsSlbReq
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_req
OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.2

ACOS-SLB-DNS-MIB_oid_list

Field Name : dnsStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.351.1.1.1.1

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListTable
Field Type : TABLE
Field Status : current
Description : ConfigureHTTPProxyGlobal from object 'slb.http-proxy'
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3

Field Name : httpProxyOperTable
Field Type : TABLE
Field Status : current
Description : ConfigureHTTPProxyGlobal from object 'slb.http-proxy'
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.2

Field Name : httpProxyOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The httpProxyOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.2.1

Field Name : httpProxyOperDebugFields
Field Type : Integer32
Field Status : current
Description : debug_fields
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.2.1.3

Field Name : httpProxyOperCpuCount
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-count
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.2.1.2

Field Name : httpProxyOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.2.1.1

Field Name : httpProxyStatsTable
Field Type : TABLE
Field Status : current
Description : ConfigureHTTPProxyGlobal from object 'slb.http-proxy'
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1

Field Name : httpProxyStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The httpProxyStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1

Field Name : httpProxyStatsTransactionLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : transaction_limited
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.342

Field Name : httpProxyStatsReqHttp11NewProxy
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : req_http11_new_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.341

Field Name : httpProxyStatsDelH2cHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : del_h2c_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.340

Field Name : httpProxyStatsUpgradeToNewProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : upgrade_to_new_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.339

Field Name : httpProxyStatsHttpAllowedMethods
Field Type : CounterBasedGauge64
Field Status : current
Description : http_allowed_methods
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.338

Field Name : httpProxyStatsHttpDisallowedMethods
Field Type : CounterBasedGauge64
Field Status : current
Description : http_disallowed_methods
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.337

Field Name : httpProxyStatsHttp2ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : http2_client_idle_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.336

Field Name : httpProxyStatsHttp1ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : http1_client_idle_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.335

Field Name : httpProxyStatsHeaderFilterRuleHit
Field Type : CounterBasedGauge64
Field Status : current
Description : header_filter_rule_hit
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.334

Field Name : httpProxyStatsResponseHttp3
Field Type : CounterBasedGauge64
Field Status : current
Description : response_http3
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.333

Field Name : httpProxyStatsReqHttp3
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http3
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.332

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsH2upWithHostAndAuth
Field Type : CounterBasedGauge64
Field Status : current
Description : h2up_with_host_and_auth
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.331

Field Name : httpProxyStatsGetAndPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : get_and_payload
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.330

Field Name : httpProxyStatsTransferEncodingAndContentLength
Field Type : CounterBasedGauge64
Field Status : current
Description : transfer_encoding_and_content_length
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.329

Field Name : httpProxyStatsMultipleTransferEncoding
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple_transfer_encoding
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.328

Field Name : httpProxyStatsMultipleContentLength
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple_content_length
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.327

Field Name : httpProxyStatsH2upWithTransferEncoding
Field Type : CounterBasedGauge64
Field Status : current
Description : h2up_with_transfer_encoding
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.326

Field Name : httpProxyStatsMalformedH2upSchemeValue
Field Type : CounterBasedGauge64
Field Status : current
Description : malformed_h2up_scheme_value
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.325

Field Name : httpProxyStatsMalformedH2upHeaderValue
Field Type : CounterBasedGauge64
Field Status : current
Description : malformed_h2up_header_value
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.324

Field Name : httpProxyStatsH2upContentLengthAlias
Field Type : CounterBasedGauge64
Field Status : current
Description : h2up_content_length_alias
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.323

Field Name : httpProxyStatsCompressRspTotal
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : compress_rsp_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.322

Field Name : httpProxyStatsCompressRspBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_rsp_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.321

Field Name : httpProxyStatsDecompressionAfterTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_after_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.320

Field Name : httpProxyStatsDecompressionBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_before_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.319

Field Name : httpProxyStatsDecompressionAfterBr
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_after_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.318

Field Name : httpProxyStatsDecompressionBeforeBr
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_before_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.317

Field Name : httpProxyStatsCompressionAfterTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_after_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.316

Field Name : httpProxyStatsCompressionBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_before_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.315

Field Name : httpProxyStatsCompressionAfterBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_after_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.314

Field Name : httpProxyStatsCompressionBeforeBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_before_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.313

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsDohDnsRespRcodeOther
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_other
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.312

Field Name : httpProxyStatsDohDnsRespRcodeNotzone
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_notzone
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.311

Field Name : httpProxyStatsDohDnsRespRcodeNotauth
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_notauth
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.310

Field Name : httpProxyStatsDohDnsRespRcodeNxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_nxrrset
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.309

Field Name : httpProxyStatsDohDnsRespRcodeYxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_yxrrset
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.308

Field Name : httpProxyStatsDohDnsRespRcodeYxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_yxdomain
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.307

Field Name : httpProxyStatsDohDnsRespRcodeRefuse
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_refuse
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.306

Field Name : httpProxyStatsDohDnsRespRcodeErrType
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_type
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.305

Field Name : httpProxyStatsDohDnsRespRcodeErrName
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_name
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.304

Field Name : httpProxyStatsDohDnsRespRcodeErrServer
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : doh_dns_resp_rcode_err_server
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.303

Field Name : httpProxyStatsDohDnsRespRcodeErrFormat
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_format
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.302

Field Name : httpProxyStatsDohDnsMalformedQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_malformed_query
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.301

Field Name : httpProxyStatsDohPostPayloadTooLarge
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_payload_too_large
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.300

Field Name : httpProxyStatsDohGetUriTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_get_uri_too_long
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.299

Field Name : httpProxyStatsDohRetryWTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_retry_w_tcp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.298

Field Name : httpProxyStatsDohServSelFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_serv_sel_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.297

Field Name : httpProxyStatsDohRespTcpFragments
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_tcp_frags
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.296

Field Name : httpProxyStatsDohRespUdpFragments
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_udp_frags
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.295

Field Name : httpProxyStatsDohRespQueFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_que_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.294

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsDohRespHeaderAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_header_alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.293

Field Name : httpProxyStatsDohRespSetupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_setup_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.292

Field Name : httpProxyStatsDohDnsQueryTypeOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_others
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.291

Field Name : httpProxyStatsDohDnsQueryTypeSoa
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_soa
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.290

Field Name : httpProxyStatsDohDnsQueryTypeMx
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_mx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.289

Field Name : httpProxyStatsDohDnsQueryTypeSrv
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_srv
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.288

Field Name : httpProxyStatsDohDnsQueryTypeAny
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_any
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.287

Field Name : httpProxyStatsDohDnsQueryTypeCname
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_cname
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.286

Field Name : httpProxyStatsDohDnsQueryTypeNs
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_ns
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.285

Field Name : httpProxyStatsDohDnsQueryTypeAaaa
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : doh_dns_query_type_aaaa
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.284

Field Name : httpProxyStatsDohDnsQueryTypeA
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_a
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.283

Field Name : httpProxyStatsDohQueryTimeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_query_time_out
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.282

Field Name : httpProxyStatsDohUdpSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_udp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.281

Field Name : httpProxyStatsDohTcpSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.280

Field Name : httpProxyStatsDohNonDohMethod
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_method
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.279

Field Name : httpProxyStatsDohPostPayloadExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_payload_extract_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.278

Field Name : httpProxyStatsDohPostPayloadNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_payload_not_found
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.277

Field Name : httpProxyStatsDohPostContentTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_post_content_type_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.276

Field Name : httpProxyStatsDohGetBase64DecodeFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_get_base64_decode_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.275

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsDohGetDnsArgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_get_dns_arg_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.274

Field Name : httpProxyStatsDohPathNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_path_not_found
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.273

Field Name : httpProxyStatsDohSnatFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_snat_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.272

Field Name : httpProxyStatsDohReqTcpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_tcp_retry_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.271

Field Name : httpProxyStatsDohReqTcpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_tcp_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.270

Field Name : httpProxyStatsDohReqUdpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_udp_retry_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.269

Field Name : httpProxyStatsDohReqUdpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_udp_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.268

Field Name : httpProxyStatsDohMallocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_malloc_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.267

Field Name : httpProxyStatsDohRespSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.266

Field Name : httpProxyStatsDohReqSendFailed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : doh_req_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.265

Field Name : httpProxyStatsDohTcpDnsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_dns_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.264

Field Name : httpProxyStatsDohTcpDnsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_dns_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.263

Field Name : httpProxyStatsDohUdpDnsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_udp_dns_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.262

Field Name : httpProxyStatsDohUdpDnsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_udp_dns_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.261

Field Name : httpProxyStatsDohTcResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tc_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.260

Field Name : httpProxyStatsDohResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.259

Field Name : httpProxyStatsDohNonDohReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_req_post
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.258

Field Name : httpProxyStatsDohNonDohReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_req_get
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.257

Field Name : httpProxyStatsDohNonDohReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_non_doh_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.256

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsDohReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_post
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.255

Field Name : httpProxyStatsDohReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_get
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.254

Field Name : httpProxyStatsDohReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.253

Field Name : httpProxyStatsReqTimeoutClose
Field Type : CounterBasedGauge64
Field Status : current
Description : req_timeout_close
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.252

Field Name : httpProxyStatsReqTimeoutRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : req_timeout_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.251

Field Name : httpProxyStatsResponseHttp2
Field Type : CounterBasedGauge64
Field Status : current
Description : response_http2
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.250

Field Name : httpProxyStatsReqHttp2
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http2
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.249

Field Name : httpProxyStatsDecompressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_after
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.248

Field Name : httpProxyStatsDecompressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_before
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.247

Field Name : httpProxyStatsNonHttpBypass
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : non_http_bypass
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.246

Field Name : httpProxyStatsReqEnterSsli
Field Type : CounterBasedGauge64
Field Status : current
Description : req_enter_ssli
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.245

Field Name : httpProxyStatsConnectReq
Field Type : CounterBasedGauge64
Field Status : current
Description : connect_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.244

Field Name : httpProxyStatsReqTrack
Field Type : CounterBasedGauge64
Field Status : current
Description : req_track
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.243

Field Name : httpProxyStatsInsertClientPort
Field Type : CounterBasedGauge64
Field Status : current
Description : insert_client_port
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.242

Field Name : httpProxyStatsReqOver5s
Field Type : CounterBasedGauge64
Field Status : current
Description : req_over_5s
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.241

Field Name : httpProxyStatsReq5s
Field Type : CounterBasedGauge64
Field Status : current
Description : req_5s
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.240

Field Name : httpProxyStatsReq2s
Field Type : CounterBasedGauge64
Field Status : current
Description : req_2s
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.239

Field Name : httpProxyStatsReq1s
Field Type : CounterBasedGauge64
Field Status : current
Description : req_1s
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.238

Field Name : httpProxyStatsReq500m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_500m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.237

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsReq200m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_200m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.236

Field Name : httpProxyStatsReq100m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_100m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.235

Field Name : httpProxyStatsReq50m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_50m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.234

Field Name : httpProxyStatsReq20m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_20m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.233

Field Name : httpProxyStatsReq10m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_10m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.232

Field Name : httpProxyStatsReq5m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_5m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.231

Field Name : httpProxyStatsReq2m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_2m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.230

Field Name : httpProxyStatsReq1m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_1m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.229

Field Name : httpProxyStatsReq500u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_500u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.228

Field Name : httpProxyStatsReq200u
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : req_200u

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.227

Field Name : httpProxyStatsReq100u

Field Type : CounterBasedGauge64

Field Status : current

Description : req_100u

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.226

Field Name : httpProxyStatsReq50u

Field Type : CounterBasedGauge64

Field Status : current

Description : req_50u

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.225

Field Name : httpProxyStatsReq20u

Field Type : CounterBasedGauge64

Field Status : current

Description : req_20u

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.224

Field Name : httpProxyStatsReq10u

Field Type : CounterBasedGauge64

Field Status : current

Description : req_10u

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.223

Field Name : httpProxyStatsChunkBad

Field Type : CounterBasedGauge64

Field Status : current

Description : chunk_bad

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.222

Field Name : httpProxyStatsPconnConnectingFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : pconn_connecting_failed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.221

Field Name : httpProxyStatsPconnConnected

Field Type : CounterBasedGauge64

Field Status : current

Description : pconn_connected

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.220

Field Name : httpProxyStatsPconnConnecting

Field Type : CounterBasedGauge64

Field Status : current

Description : pconn_connecting

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.219

Field Name : httpProxyStatsChunkSzGt4k

Field Type : CounterBasedGauge64

Field Status : current

Description : chunk_sz_gt_4k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.218

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsChunkSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.217

Field Name : httpProxyStatsChunkSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.216

Field Name : httpProxyStatsChunkSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.215

Field Name : httpProxyStatsChunkSz512
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_512
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.214

Field Name : httpProxyStatsRspSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_gt_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.213

Field Name : httpProxyStatsRspSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.212

Field Name : httpProxyStatsRspSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_64k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.211

Field Name : httpProxyStatsRspSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_32k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.210

Field Name : httpProxyStatsRspSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_16k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.209

Field Name : httpProxyStatsRspSz8k
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : rsp_sz_8k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.208

Field Name : httpProxyStatsRspSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.207

Field Name : httpProxyStatsRspSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.206

Field Name : httpProxyStatsRspSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.205

Field Name : httpProxyStatsReqSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_gt_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.204

Field Name : httpProxyStatsReqSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.203

Field Name : httpProxyStatsReqSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_64k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.202

Field Name : httpProxyStatsReqSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_32k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.201

Field Name : httpProxyStatsReqSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_16k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.200

Field Name : httpProxyStatsReqSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_8k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.199

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsReqSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.198

Field Name : httpProxyStatsReqSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.197

Field Name : httpProxyStatsReqSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.196

Field Name : httpProxyStatsReqHttp10Keepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http10_keepalive
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.195

Field Name : httpProxyStatsCloseOnDdos
Field Type : CounterBasedGauge64
Field Status : current
Description : close_on_ddos
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.194

Field Name : httpProxyStatsCacheRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : cache_rsp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.193

Field Name : httpProxyStatsCompressRatioTooHigh
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_ratio_too_high
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.192

Field Name : httpProxyStatsCompressRespNoClOrCe
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_resp_no_cl_or_ce
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.191

Field Name : httpProxyStatsCompressRespLtMin
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_resp_lt_min
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.190

Field Name : httpProxyStatsCompressNoContentType
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : compress_no_content_type

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.189

Field Name : httpProxyStatsCompressContentTypeExcluded

Field Type : CounterBasedGauge64

Field Status : current

Description : compress_content_type_excluded

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.188

Field Name : httpProxyStatsCompressRespAlreadyCompressed

Field Type : CounterBasedGauge64

Field Status : current

Description : compress_resp_already_compressed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.187

Field Name : httpProxyStatsCompressDelAcceptEnc

Field Type : CounterBasedGauge64

Field Status : current

Description : compress_del_accept_enc

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.186

Field Name : httpProxyStatsCompressRsp

Field Type : CounterBasedGauge64

Field Status : current

Description : compress_rsp

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.185

Field Name : httpProxyStatsReqChunk

Field Type : CounterBasedGauge64

Field Status : current

Description : req_chunk

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.184

Field Name : httpProxyStatsRspChunk

Field Type : CounterBasedGauge64

Field Status : current

Description : rsp_chunk

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.183

Field Name : httpProxyStatsRspContentLen

Field Type : CounterBasedGauge64

Field Status : current

Description : rsp_content_len

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.182

Field Name : httpProxyStatsReqContentLen

Field Type : CounterBasedGauge64

Field Status : current

Description : req_content_len

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.181

Field Name : httpProxyStatsReqUnknown

Field Type : CounterBasedGauge64

Field Status : current

Description : req_unknown

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.180

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsReqDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : req_delete
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.179

Field Name : httpProxyStatsReqConnect
Field Type : CounterBasedGauge64
Field Status : current
Description : req_connect
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.178

Field Name : httpProxyStatsReqOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : req_options
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.177

Field Name : httpProxyStatsReqTrace
Field Type : CounterBasedGauge64
Field Status : current
Description : req_trace
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.176

Field Name : httpProxyStatsReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : req_post
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.175

Field Name : httpProxyStatsReqPut
Field Type : CounterBasedGauge64
Field Status : current
Description : req_put
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.174

Field Name : httpProxyStatsReqHead
Field Type : CounterBasedGauge64
Field Status : current
Description : req_head
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.173

Field Name : httpProxyStatsReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : req_get
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.172

Field Name : httpProxyStatsResponseHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : response_http11
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.171

Field Name : httpProxyStatsResponseHttp10
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : response_http10
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.170

Field Name : httpProxyStatsReqHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http11
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.169

Field Name : httpProxyStatsReqHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http10
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.168

Field Name : httpProxyStatsResponseUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : response_unknown
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.167

Field Name : httpProxyStatsResponse6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_6xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.166

Field Name : httpProxyStatsResponse510
Field Type : CounterBasedGauge64
Field Status : current
Description : response_510
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.165

Field Name : httpProxyStatsResponse509
Field Type : CounterBasedGauge64
Field Status : current
Description : response_509
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.164

Field Name : httpProxyStatsResponse508
Field Type : CounterBasedGauge64
Field Status : current
Description : response_508
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.163

Field Name : httpProxyStatsResponse507
Field Type : CounterBasedGauge64
Field Status : current
Description : response_507
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.162

Field Name : httpProxyStatsResponse506
Field Type : CounterBasedGauge64
Field Status : current
Description : response_506
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.161

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsResponse505
Field Type : CounterBasedGauge64
Field Status : current
Description : response_505
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.160

Field Name : httpProxyStatsResponse504
Field Type : CounterBasedGauge64
Field Status : current
Description : response_504
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.159

Field Name : httpProxyStatsResponse503
Field Type : CounterBasedGauge64
Field Status : current
Description : response_503
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.158

Field Name : httpProxyStatsResponse502
Field Type : CounterBasedGauge64
Field Status : current
Description : response_502
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.157

Field Name : httpProxyStatsResponse501
Field Type : CounterBasedGauge64
Field Status : current
Description : response_501
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.156

Field Name : httpProxyStatsResponse500
Field Type : CounterBasedGauge64
Field Status : current
Description : response_500
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.155

Field Name : httpProxyStatsResponse5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_5xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.154

Field Name : httpProxyStatsResponse450
Field Type : CounterBasedGauge64
Field Status : current
Description : response_450
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.153

Field Name : httpProxyStatsResponse449
Field Type : CounterBasedGauge64
Field Status : current
Description : response_449
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.152

Field Name : httpProxyStatsResponse426
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : response_426
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.151

Field Name : httpProxyStatsResponse425
Field Type : CounterBasedGauge64
Field Status : current
Description : response_425
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.150

Field Name : httpProxyStatsResponse424
Field Type : CounterBasedGauge64
Field Status : current
Description : response_424
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.149

Field Name : httpProxyStatsResponse423
Field Type : CounterBasedGauge64
Field Status : current
Description : response_423
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.148

Field Name : httpProxyStatsResponse422
Field Type : CounterBasedGauge64
Field Status : current
Description : response_422
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.147

Field Name : httpProxyStatsResponse418
Field Type : CounterBasedGauge64
Field Status : current
Description : response_418
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.146

Field Name : httpProxyStatsResponse417
Field Type : CounterBasedGauge64
Field Status : current
Description : response_417
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.145

Field Name : httpProxyStatsResponse416
Field Type : CounterBasedGauge64
Field Status : current
Description : response_416
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.144

Field Name : httpProxyStatsResponse415
Field Type : CounterBasedGauge64
Field Status : current
Description : response_415
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.143

Field Name : httpProxyStatsResponse414
Field Type : CounterBasedGauge64
Field Status : current
Description : response_414
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.142

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsResponse413
Field Type : CounterBasedGauge64
Field Status : current
Description : response_413
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.141

Field Name : httpProxyStatsResponse412
Field Type : CounterBasedGauge64
Field Status : current
Description : response_412
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.140

Field Name : httpProxyStatsResponse411
Field Type : CounterBasedGauge64
Field Status : current
Description : response_411
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.139

Field Name : httpProxyStatsResponse410
Field Type : CounterBasedGauge64
Field Status : current
Description : response_410
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.138

Field Name : httpProxyStatsResponse409
Field Type : CounterBasedGauge64
Field Status : current
Description : response_409
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.137

Field Name : httpProxyStatsResponse408
Field Type : CounterBasedGauge64
Field Status : current
Description : response_408
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.136

Field Name : httpProxyStatsResponse407
Field Type : CounterBasedGauge64
Field Status : current
Description : response_407
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.135

Field Name : httpProxyStatsResponse406
Field Type : CounterBasedGauge64
Field Status : current
Description : response_406
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.134

Field Name : httpProxyStatsResponse405
Field Type : CounterBasedGauge64
Field Status : current
Description : response_405
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.133

Field Name : httpProxyStatsResponse404
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : response_404
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.132

Field Name : httpProxyStatsResponse403
Field Type : CounterBasedGauge64
Field Status : current
Description : response_403
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.131

Field Name : httpProxyStatsResponse402
Field Type : CounterBasedGauge64
Field Status : current
Description : response_402
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.130

Field Name : httpProxyStatsResponse401
Field Type : CounterBasedGauge64
Field Status : current
Description : response_401
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.129

Field Name : httpProxyStatsResponse400
Field Type : CounterBasedGauge64
Field Status : current
Description : response_400
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.128

Field Name : httpProxyStatsResponse4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_4xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.127

Field Name : httpProxyStatsResponse307
Field Type : CounterBasedGauge64
Field Status : current
Description : response_307
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.126

Field Name : httpProxyStatsResponse306
Field Type : CounterBasedGauge64
Field Status : current
Description : response_306
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.125

Field Name : httpProxyStatsResponse305
Field Type : CounterBasedGauge64
Field Status : current
Description : response_305
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.124

Field Name : httpProxyStatsResponse304
Field Type : CounterBasedGauge64
Field Status : current
Description : response_304
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.123

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsResponse303
Field Type : CounterBasedGauge64
Field Status : current
Description : response_303
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.122

Field Name : httpProxyStatsResponse302
Field Type : CounterBasedGauge64
Field Status : current
Description : response_302
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.121

Field Name : httpProxyStatsResponse301
Field Type : CounterBasedGauge64
Field Status : current
Description : response_301
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.120

Field Name : httpProxyStatsResponse300
Field Type : CounterBasedGauge64
Field Status : current
Description : response_300
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.119

Field Name : httpProxyStatsResponse3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_3xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.118

Field Name : httpProxyStatsResponse207
Field Type : CounterBasedGauge64
Field Status : current
Description : response_207
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.117

Field Name : httpProxyStatsResponse206
Field Type : CounterBasedGauge64
Field Status : current
Description : response_206
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.116

Field Name : httpProxyStatsResponse205
Field Type : CounterBasedGauge64
Field Status : current
Description : response_205
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.115

Field Name : httpProxyStatsResponse204
Field Type : CounterBasedGauge64
Field Status : current
Description : response_204
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.114

Field Name : httpProxyStatsResponse203
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : response_203
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.113

Field Name : httpProxyStatsResponse202
Field Type : CounterBasedGauge64
Field Status : current
Description : response_202
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.112

Field Name : httpProxyStatsResponse201
Field Type : CounterBasedGauge64
Field Status : current
Description : response_201
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.111

Field Name : httpProxyStatsResponse200
Field Type : CounterBasedGauge64
Field Status : current
Description : response_200
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.110

Field Name : httpProxyStatsResponse2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_2xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.109

Field Name : httpProxyStatsResponse102
Field Type : CounterBasedGauge64
Field Status : current
Description : response_102
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.108

Field Name : httpProxyStatsResponse101
Field Type : CounterBasedGauge64
Field Status : current
Description : response_101
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.107

Field Name : httpProxyStatsResponse100
Field Type : CounterBasedGauge64
Field Status : current
Description : response_100
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.106

Field Name : httpProxyStatsResponse1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_1xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.105

Field Name : httpProxyStatsCompressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_after
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.104

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsCompressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_before
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.103

Field Name : httpProxyStatsServerReselFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : server_resel_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.102

Field Name : httpProxyStatsStaleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : stale_sess
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.101

Field Name : httpProxyStatsPktsRetransPush
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_push
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.100

Field Name : httpProxyStatsPktsRetransRst
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.99

Field Name : httpProxyStatsPktsRetransFin
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_fin
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.98

Field Name : httpProxyStatsPktsRetransAckFinwait
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_ack_finwait
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.97

Field Name : httpProxyStatsPktsRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.96

Field Name : httpProxyStatsPktsOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_ofo
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.95

Field Name : httpProxyStatsConnectingAck
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : connecting_ack

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.94

Field Name : httpProxyStatsConnectingRstOfo

Field Type : CounterBasedGauge64

Field Status : current

Description : connecting_rst_ofo

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.93

Field Name : httpProxyStatsConnectingRstRetrans

Field Type : CounterBasedGauge64

Field Status : current

Description : connecting_rst_retrans

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.92

Field Name : httpProxyStatsConnectingRst

Field Type : CounterBasedGauge64

Field Status : current

Description : connecting_rst

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.91

Field Name : httpProxyStatsConnectingFinOfo

Field Type : CounterBasedGauge64

Field Status : current

Description : connecting_fin_ofo

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.90

Field Name : httpProxyStatsConnectingFinRetrans

Field Type : CounterBasedGauge64

Field Status : current

Description : connecting_fin_retrans

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.89

Field Name : httpProxyStatsConnectingFin

Field Type : CounterBasedGauge64

Field Status : current

Description : connecting_fin

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.88

Field Name : httpProxyStatsClientReqUnexpFlag

Field Type : CounterBasedGauge64

Field Status : current

Description : client_req_unexp_flag

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.87

Field Name : httpProxyStatsAsmSetcookieHeaderFail

Field Type : CounterBasedGauge64

Field Status : current

Description : asm_setcookie_header_fail

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.86

Field Name : httpProxyStatsAsmSetcookieFail

Field Type : CounterBasedGauge64

Field Status : current

Description : asm_setcookie_fail

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.85

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsAsmCookieHeaderFail
Field Type : CounterBasedGauge64
Field Status : current
Description : asm_cookie_header_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.84

Field Name : httpProxyStatsAsmCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : asm_cookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.83

Field Name : httpProxyStatsParseSetcookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : parse_setcookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.82

Field Name : httpProxyStatsParseCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : parse_cookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.81

Field Name : httpProxyStatsHugeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : huge_cookie_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.80

Field Name : httpProxyStatsHugeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : huge_cookie
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.79

Field Name : httpProxyStatsLargeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : large_cookie_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.78

Field Name : httpProxyStatsLargeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : large_cookie
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.77

Field Name : httpProxyStatsNegativeRespRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : negative_resp_remain
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.76

Field Name : httpProxyStatsNegativeReqRemain
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : negative_req_remain
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.75

Field Name : httpProxyStatsInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : insert_client_ip
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.74

Field Name : httpProxyStatsHeaderDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : header_delete
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.73

Field Name : httpProxyStatsHeaderInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : header_insert
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.72

Field Name : httpProxyStatsWrongRespHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong_resp_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.71

Field Name : httpProxyStatsHeaderNameTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : header_name_too_long
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.70

Field Name : httpProxyStatsLineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : line_too_long
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.69

Field Name : httpProxyStatsTooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : too_many_headers
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.68

Field Name : httpProxyStatsInvalidHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.67

Field Name : httpProxyStatsServerRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_response
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.66

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsServerRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_connected
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.65

Field Name : httpProxyStatsServerRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.64

Field Name : httpProxyStatsServerRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_request
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.63

Field Name : httpProxyStatsClientRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_response
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.62

Field Name : httpProxyStatsClientRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_connected
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.61

Field Name : httpProxyStatsClientRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.60

Field Name : httpProxyStatsClientRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_request
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.59

Field Name : httpProxyStatsAflexLbReselectOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_lb_reselect_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.58

Field Name : httpProxyStatsAflexLbReselect
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_lb_reselect
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.57

Field Name : httpProxyStatsAflexRetry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : aflex_retry

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.56

Field Name : httpProxyStatsRetry503

Field Type : CounterBasedGauge64

Field Status : current

Description : retry_503

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.55

Field Name : httpProxyStatsLbSwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : lb_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.54

Field Name : httpProxyStatsHostSwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : host_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.53

Field Name : httpProxyStatsUrlSwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : url_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.52

Field Name : httpProxyStatsHttpPolicySwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : http_policy_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.51

Field Name : httpProxyStatsAflexSwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : aflex_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.50

Field Name : httpProxyStatsCookieSwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : cookie_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.49

Field Name : httpProxyStatsL4SwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : l4_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.48

Field Name : httpProxyStatsLbSwitchingOk

Field Type : CounterBasedGauge64

Field Status : current

Description : lb_switching_ok

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.47

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsHostSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : host_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.46

Field Name : httpProxyStatsUrlSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : url_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.45

Field Name : httpProxyStatsHttpPolicySwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : http_policy_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.44

Field Name : httpProxyStatsAflexSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.43

Field Name : httpProxyStatsCookieSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : cookie_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.42

Field Name : httpProxyStatsL4SwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.41

Field Name : httpProxyStatsLbSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : lb_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.40

Field Name : httpProxyStatsHostSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : host_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.39

Field Name : httpProxyStatsUrlSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : url_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.38

Field Name : httpProxyStatsHttpPolicySwitching
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : http_policy_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.37

Field Name : httpProxyStatsAflexSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.36

Field Name : httpProxyStatsCookieSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : cookie_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.35

Field Name : httpProxyStatsL4Switching
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.34

Field Name : httpProxyStatsReqRateOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : req_rate_over_limit
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.33

Field Name : httpProxyStatsReqOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : req_over_limit
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.32

Field Name : httpProxyStatsFullProxyFpgaErr
Field Type : CounterBasedGauge64
Field Status : current
Description : full_proxy_fpga_err
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.31

Field Name : httpProxyStatsFullProxyPipeline
Field Type : CounterBasedGauge64
Field Status : current
Description : full_proxy_pipeline
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.30

Field Name : httpProxyStatsFullProxyPost
Field Type : CounterBasedGauge64
Field Status : current
Description : full_proxy_post
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.29

Field Name : httpProxyStatsFullProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : full_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.28

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsTcpoutrst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcpoutrst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.27

Field Name : httpProxyStatsSnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.26

Field Name : httpProxyStatsNewSvrconn
Field Type : CounterBasedGauge64
Field Status : current
Description : new_svrconn
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.25

Field Name : httpProxyStatsSvrPremClose
Field Type : CounterBasedGauge64
Field Status : current
Description : svr_prem_close
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.24

Field Name : httpProxyStatsServerResel
Field Type : CounterBasedGauge64
Field Status : current
Description : server_resel
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.23

Field Name : httpProxyStatsReqOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : req_ofo
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.22

Field Name : httpProxyStatsReqRetran
Field Type : CounterBasedGauge64
Field Status : current
Description : req_retran
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.21

Field Name : httpProxyStatsFwdreqdataFail
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreqdata_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.20

Field Name : httpProxyStatsFwdreqFailTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_tuple
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.19

Field Name : httpProxyStatsFwdreqFailServer
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : fwdreq_fail_server
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.18

Field Name : httpProxyStatsFwdreqFailPersist
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_persist
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.17

Field Name : httpProxyStatsFwdreqFailRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_route
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.16

Field Name : httpProxyStatsFwdreqFailRport
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_rport
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.15

Field Name : httpProxyStatsFwdreqFailBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail_buff
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.14

Field Name : httpProxyStatsFwdreqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : fwdreq_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.13

Field Name : httpProxyStatsSvrselfFail
Field Type : CounterBasedGauge64
Field Status : current
Description : svrself_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.12

Field Name : httpProxyStatsParsereqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : parsereq_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.11

Field Name : httpProxyStatsNotuple
Field Type : CounterBasedGauge64
Field Status : current
Description : notuple
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.10

Field Name : httpProxyStatsServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.9

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyStatsClientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.8

Field Name : httpProxyStatsNoproxy
Field Type : CounterBasedGauge64
Field Status : current
Description : noproxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.7

Field Name : httpProxyStatsReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.6

Field Name : httpProxyStatsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.5

Field Name : httpProxyStatsTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : total_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.4

Field Name : httpProxyStatsCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.3

Field Name : httpProxyStatsNum
Field Type : CounterBasedGauge64
Field Status : current
Description : num
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.2

Field Name : httpProxyStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.1.1.1

Field Name : httpProxyOperHttpProxyCpuListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The httpProxyOperHttpProxyCpuList entry:http-proxy-cpu-list
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1

Field Name : httpProxyOperHttpProxyCpuListTransactionLimited
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : transaction_limited

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.340

Field Name : httpProxyOperHttpProxyCpuListDelH2cHeader

Field Type : CounterBasedGauge64

Field Status : current

Description : del_h2c_header

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.339

Field Name : httpProxyOperHttpProxyCpuListUpgradeToNewProxy

Field Type : CounterBasedGauge64

Field Status : current

Description : upgrade_to_new_proxy

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.338

Field Name : httpProxyOperHttpProxyCpuListHttpAllowedMethods

Field Type : CounterBasedGauge64

Field Status : current

Description : http_allowed_methods

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.337

Field Name : httpProxyOperHttpProxyCpuListHttpDisallowedMethods

Field Type : CounterBasedGauge64

Field Status : current

Description : http_disallowed_methods

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.336

Field Name : httpProxyOperHttpProxyCpuListHttp2ClientIdleTimeout

Field Type : CounterBasedGauge64

Field Status : current

Description : http2_client_idle_timeout

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.335

Field Name : httpProxyOperHttpProxyCpuListHttp1ClientIdleTimeout

Field Type : CounterBasedGauge64

Field Status : current

Description : http1_client_idle_timeout

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.334

Field Name : httpProxyOperHttpProxyCpuListHeaderFilterRuleHit

Field Type : CounterBasedGauge64

Field Status : current

Description : header_filter_rule_hit

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.333

Field Name : httpProxyOperHttpProxyCpuListH2upWithHostAndAuth

Field Type : CounterBasedGauge64

Field Status : current

Description : h2up_with_host_and_auth

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.332

Field Name : httpProxyOperHttpProxyCpuListGetAndPayload

Field Type : CounterBasedGauge64

Field Status : current

Description : get_and_payload

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.331

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListTransferEncodingAndContentLength
Field Type : CounterBasedGauge64
Field Status : current
Description : transfer_encoding_and_content_length
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.330

Field Name : httpProxyOperHttpProxyCpuListMultipleTransferEncoding
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple_transfer_encoding
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.329

Field Name : httpProxyOperHttpProxyCpuListMultipleContentLength
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple_content_length
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.328

Field Name : httpProxyOperHttpProxyCpuListH2upWithTransferEncoding
Field Type : CounterBasedGauge64
Field Status : current
Description : h2up_with_transfer_encoding
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.327

Field Name : httpProxyOperHttpProxyCpuListMalformedH2upSchemeValue
Field Type : CounterBasedGauge64
Field Status : current
Description : malformed_h2up_scheme_value
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.326

Field Name : httpProxyOperHttpProxyCpuListMalformedH2upHeaderValue
Field Type : CounterBasedGauge64
Field Status : current
Description : malformed_h2up_header_value
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.325

Field Name : httpProxyOperHttpProxyCpuListH2upContentLengthAlias
Field Type : CounterBasedGauge64
Field Status : current
Description : h2up_content_length_alias
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.324

Field Name : httpProxyOperHttpProxyCpuListCompressRspTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_rsp_total
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.323

Field Name : httpProxyOperHttpProxyCpuListCompressRspBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_rsp_br
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.322

Field Name : httpProxyOperHttpProxyCpuListDecompressionAfterTotal
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : decompression_after_total

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.321

Field Name : httpProxyOperHttpProxyCpuListDecompressionBeforeTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : decompression_before_total

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.320

Field Name : httpProxyOperHttpProxyCpuListDecompressionAfterBr

Field Type : CounterBasedGauge64

Field Status : current

Description : decompression_after_br

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.319

Field Name : httpProxyOperHttpProxyCpuListDecompressionBeforeBr

Field Type : CounterBasedGauge64

Field Status : current

Description : decompression_before_br

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.318

Field Name : httpProxyOperHttpProxyCpuListCompressionAfterTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : compression_after_total

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.317

Field Name : httpProxyOperHttpProxyCpuListCompressionBeforeTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : compression_before_total

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.316

Field Name : httpProxyOperHttpProxyCpuListCompressionAfterBr

Field Type : CounterBasedGauge64

Field Status : current

Description : compression_after_br

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.315

Field Name : httpProxyOperHttpProxyCpuListCompressionBeforeBr

Field Type : CounterBasedGauge64

Field Status : current

Description : compression_before_br

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.314

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeOther

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_dns_resp_rcode_other

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.313

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeNotzone

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_dns_resp_rcode_notzone

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.312

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeNotauth
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_notauth
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.311

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeNxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_nxrrset
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.310

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeYxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_yxrrset
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.309

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeYxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_yxdomain
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.308

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeRefuse
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_refuse
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.307

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeErrType
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_type
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.306

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeErrName
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_name
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.305

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeErrServer
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_server
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.304

Field Name : httpProxyOperHttpProxyCpuListDohDnsRespRcodeErrFormat
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_format
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.303

Field Name : httpProxyOperHttpProxyCpuListDohDnsMalformedQuery
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : doh_dns_malformed_query

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.302

Field Name : httpProxyOperHttpProxyCpuListDohPostPayloadTooLarge

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_post_payload_too_large

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.301

Field Name : httpProxyOperHttpProxyCpuListDohGetUriTooLong

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_get_uri_too_long

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.300

Field Name : httpProxyOperHttpProxyCpuListDohRetryWTcp

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_retry_w_tcp

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.299

Field Name : httpProxyOperHttpProxyCpuListDohServSelFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_serv_sel_failed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.298

Field Name : httpProxyOperHttpProxyCpuListDohRespTcpFrgs

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_resp_tcp_frgs

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.297

Field Name : httpProxyOperHttpProxyCpuListDohRespUdpFrgs

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_resp_udp_frgs

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.296

Field Name : httpProxyOperHttpProxyCpuListDohRespQueFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_resp_que_failed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.295

Field Name : httpProxyOperHttpProxyCpuListDohRespHeaderAllocFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_resp_header_alloc_failed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.294

Field Name : httpProxyOperHttpProxyCpuListDohRespSetupFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_resp_setup_failed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.293

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_others
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.292

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeSoa
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_soa
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.291

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeMx
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_mx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.290

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeSrv
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_srv
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.289

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeAny
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_any
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.288

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeCname
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_cname
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.287

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeNs
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_ns
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.286

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeAaaa
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_aaaa
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.285

Field Name : httpProxyOperHttpProxyCpuListDohDnsQueryTypeA
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_a
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.284

Field Name : httpProxyOperHttpProxyCpuListDohQueryTimeOut
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : doh_query_time_out

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.283

Field Name : httpProxyOperHttpProxyCpuListDohUdpSendFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_udp_send_failed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.282

Field Name : httpProxyOperHttpProxyCpuListDohTcpSendFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_tcp_send_failed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.281

Field Name : httpProxyOperHttpProxyCpuListDohNonDohMethod

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_non_doh_method

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.280

Field Name : httpProxyOperHttpProxyCpuListDohPostPayloadExtractFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_post_payload_extract_failed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.279

Field Name : httpProxyOperHttpProxyCpuListDohPostPayloadNotFound

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_post_payload_not_found

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.278

Field Name : httpProxyOperHttpProxyCpuListDohPostContentTypeMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_post_content_type_mismatch

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.277

Field Name : httpProxyOperHttpProxyCpuListDohGetBase64DecodeFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_get_base64_decode_failed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.276

Field Name : httpProxyOperHttpProxyCpuListDohGetDnsArgFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_get_dns_arg_failed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.275

Field Name : httpProxyOperHttpProxyCpuListDohPathNotFound

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_path_not_found

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.274

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListDohSnatFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_snat_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.273

Field Name : httpProxyOperHttpProxyCpuListDohReqTcpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_tcp_retry_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.272

Field Name : httpProxyOperHttpProxyCpuListDohReqTcpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_tcp_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.271

Field Name : httpProxyOperHttpProxyCpuListDohReqUdpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_udp_retry_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.270

Field Name : httpProxyOperHttpProxyCpuListDohReqUdpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_udp_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.269

Field Name : httpProxyOperHttpProxyCpuListDohMallocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_malloc_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.268

Field Name : httpProxyOperHttpProxyCpuListDohRespSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.267

Field Name : httpProxyOperHttpProxyCpuListDohReqSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.266

Field Name : httpProxyOperHttpProxyCpuListDohTcpDnsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_dns_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.265

Field Name : httpProxyOperHttpProxyCpuListDohTcpDnsReq
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : doh_tcp_dns_req

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.264

Field Name : httpProxyOperHttpProxyCpuListDohUdpDnsResp

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_udp_dns_resp

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.263

Field Name : httpProxyOperHttpProxyCpuListDohUdpDnsReq

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_udp_dns_req

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.262

Field Name : httpProxyOperHttpProxyCpuListDohTcResp

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_tc_resp

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.261

Field Name : httpProxyOperHttpProxyCpuListDohResp

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_resp

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.260

Field Name : httpProxyOperHttpProxyCpuListDohNonDohReqPost

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_non_doh_req_post

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.259

Field Name : httpProxyOperHttpProxyCpuListDohNonDohReqGet

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_non_doh_req_get

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.258

Field Name : httpProxyOperHttpProxyCpuListDohNonDohReq

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_non_doh_req

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.257

Field Name : httpProxyOperHttpProxyCpuListDohReqPost

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_req_post

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.256

Field Name : httpProxyOperHttpProxyCpuListDohReqGet

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_req_get

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.255

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListDohReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.254

Field Name : httpProxyOperHttpProxyCpuListReqTimeoutClose
Field Type : CounterBasedGauge64
Field Status : current
Description : req_timeout_close
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.253

Field Name : httpProxyOperHttpProxyCpuListReqTimeoutRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : req_timeout_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.252

Field Name : httpProxyOperHttpProxyCpuListWsServerPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_server_packets
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.251

Field Name : httpProxyOperHttpProxyCpuListWsClientPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_client_packets
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.250

Field Name : httpProxyOperHttpProxyCpuListWsHandshakeResp
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_handshake_resp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.249

Field Name : httpProxyOperHttpProxyCpuListWsHandshakeReq
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_handshake_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.248

Field Name : httpProxyOperHttpProxyCpuListChunkBad
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_bad
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.247

Field Name : httpProxyOperHttpProxyCpuListReqHttp10Keepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : req_http10_keepalive
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.246

Field Name : httpProxyOperHttpProxyCpuListRspChunk
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : rsp_chunk

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.245

Field Name : httpProxyOperHttpProxyCpuListReqContentLen

Field Type : CounterBasedGauge64

Field Status : current

Description : req_content_len

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.244

Field Name : httpProxyOperHttpProxyCpuListRspContentLen

Field Type : CounterBasedGauge64

Field Status : current

Description : rsp_content_len

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.243

Field Name : httpProxyOperHttpProxyCpuListCompressRatioTooHigh

Field Type : CounterBasedGauge64

Field Status : current

Description : compress_ratio_too_high

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.242

Field Name : httpProxyOperHttpProxyCpuListCompressRespNoClOrCe

Field Type : CounterBasedGauge64

Field Status : current

Description : compress_resp_no_cl_or_ce

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.241

Field Name : httpProxyOperHttpProxyCpuListCompressRespLtMin

Field Type : CounterBasedGauge64

Field Status : current

Description : compress_resp_lt_min

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.240

Field Name : httpProxyOperHttpProxyCpuListCompressNoContentType

Field Type : CounterBasedGauge64

Field Status : current

Description : compress_no_content_type

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.239

Field Name : httpProxyOperHttpProxyCpuListCompressContentTypeExcluded

Field Type : CounterBasedGauge64

Field Status : current

Description : compress_content_type_excluded

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.238

Field Name : httpProxyOperHttpProxyCpuListCompressRespAlreadyCompressed

Field Type : CounterBasedGauge64

Field Status : current

Description : compress_resp_already_compressed

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.237

Field Name : httpProxyOperHttpProxyCpuListCompressDelAcceptEnc

Field Type : CounterBasedGauge64

Field Status : current

Description : compress_del_accept_enc

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.236

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListCompressRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : compress_rsp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.235

Field Name : httpProxyOperHttpProxyCpuListPconnConnectingFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn_connecting_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.234

Field Name : httpProxyOperHttpProxyCpuListPconnConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn_connected
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.233

Field Name : httpProxyOperHttpProxyCpuListPconnConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.232

Field Name : httpProxyOperHttpProxyCpuListPktsRetransPush
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_push
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.231

Field Name : httpProxyOperHttpProxyCpuListPktsRetransRst
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.230

Field Name : httpProxyOperHttpProxyCpuListPktsRetransFin
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_fin
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.229

Field Name : httpProxyOperHttpProxyCpuListPktsRetransAckFinwait
Field Type : CounterBasedGauge64
Field Status : current
Description : pkts_retrans_ack_finwait
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.228

Field Name : httpProxyOperHttpProxyCpuListChunkSzGt4k
Field Type : CounterBasedGauge64
Field Status : current
Description : chunk_sz_gt_4k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.227

Field Name : httpProxyOperHttpProxyCpuListChunkSz4k
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : chunk_sz_4k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.226

Field Name : httpProxyOperHttpProxyCpuListChunkSz2k

Field Type : CounterBasedGauge64

Field Status : current

Description : chunk_sz_2k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.225

Field Name : httpProxyOperHttpProxyCpuListChunkSz1k

Field Type : CounterBasedGauge64

Field Status : current

Description : chunk_sz_1k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.224

Field Name : httpProxyOperHttpProxyCpuListChunkSz512

Field Type : CounterBasedGauge64

Field Status : current

Description : chunk_sz_512

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.223

Field Name : httpProxyOperHttpProxyCpuListRspSzGt256k

Field Type : CounterBasedGauge64

Field Status : current

Description : rsp_sz_gt_256k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.222

Field Name : httpProxyOperHttpProxyCpuListRspSz256k

Field Type : CounterBasedGauge64

Field Status : current

Description : rsp_sz_256k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.221

Field Name : httpProxyOperHttpProxyCpuListRspSz64k

Field Type : CounterBasedGauge64

Field Status : current

Description : rsp_sz_64k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.220

Field Name : httpProxyOperHttpProxyCpuListRspSz32k

Field Type : CounterBasedGauge64

Field Status : current

Description : rsp_sz_32k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.219

Field Name : httpProxyOperHttpProxyCpuListRspSz16k

Field Type : CounterBasedGauge64

Field Status : current

Description : rsp_sz_16k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.218

Field Name : httpProxyOperHttpProxyCpuListRspSz8k

Field Type : CounterBasedGauge64

Field Status : current

Description : rsp_sz_8k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.217

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListRspSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.216

Field Name : httpProxyOperHttpProxyCpuListRspSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.215

Field Name : httpProxyOperHttpProxyCpuListRspSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.214

Field Name : httpProxyOperHttpProxyCpuListReqSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_gt_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.213

Field Name : httpProxyOperHttpProxyCpuListReqSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_256k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.212

Field Name : httpProxyOperHttpProxyCpuListReqSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_64k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.211

Field Name : httpProxyOperHttpProxyCpuListReqSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_32k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.210

Field Name : httpProxyOperHttpProxyCpuListReqSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_16k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.209

Field Name : httpProxyOperHttpProxyCpuListReqSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_8k
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.208

Field Name : httpProxyOperHttpProxyCpuListReqSz4k
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : req_sz_4k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.207

Field Name : httpProxyOperHttpProxyCpuListReqSz2k

Field Type : CounterBasedGauge64

Field Status : current

Description : req_sz_2k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.206

Field Name : httpProxyOperHttpProxyCpuListReqSz1k

Field Type : CounterBasedGauge64

Field Status : current

Description : req_sz_1k

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.205

Field Name : httpProxyOperHttpProxyCpuListReqOver5s

Field Type : CounterBasedGauge64

Field Status : current

Description : req_over_5s

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.204

Field Name : httpProxyOperHttpProxyCpuListReq5s

Field Type : CounterBasedGauge64

Field Status : current

Description : req_5s

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.203

Field Name : httpProxyOperHttpProxyCpuListReq2s

Field Type : CounterBasedGauge64

Field Status : current

Description : req_2s

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.202

Field Name : httpProxyOperHttpProxyCpuListReq1s

Field Type : CounterBasedGauge64

Field Status : current

Description : req_1s

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.201

Field Name : httpProxyOperHttpProxyCpuListReq500m

Field Type : CounterBasedGauge64

Field Status : current

Description : req_500m

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.200

Field Name : httpProxyOperHttpProxyCpuListReq200m

Field Type : CounterBasedGauge64

Field Status : current

Description : req_200m

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.199

Field Name : httpProxyOperHttpProxyCpuListReq100m

Field Type : CounterBasedGauge64

Field Status : current

Description : req_100m

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.198

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListReq50m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_50m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.197

Field Name : httpProxyOperHttpProxyCpuListReq20m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_20m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.196

Field Name : httpProxyOperHttpProxyCpuListReq10m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_10m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.195

Field Name : httpProxyOperHttpProxyCpuListReq5m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_5m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.194

Field Name : httpProxyOperHttpProxyCpuListReq2m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_2m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.193

Field Name : httpProxyOperHttpProxyCpuListReq1m
Field Type : CounterBasedGauge64
Field Status : current
Description : req_1m
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.192

Field Name : httpProxyOperHttpProxyCpuListReq500u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_500u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.191

Field Name : httpProxyOperHttpProxyCpuListReq200u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_200u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.190

Field Name : httpProxyOperHttpProxyCpuListReq100u
Field Type : CounterBasedGauge64
Field Status : current
Description : req_100u
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.189

Field Name : httpProxyOperHttpProxyCpuListReq50u
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : req_50u

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.188

Field Name : httpProxyOperHttpProxyCpuListReq20u

Field Type : CounterBasedGauge64

Field Status : current

Description : req_20u

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.187

Field Name : httpProxyOperHttpProxyCpuListReq10u

Field Type : CounterBasedGauge64

Field Status : current

Description : req_10u

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.186

Field Name : httpProxyOperHttpProxyCpuListResponseUnknown

Field Type : CounterBasedGauge64

Field Status : current

Description : response_unknown

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.185

Field Name : httpProxyOperHttpProxyCpuListResponse6xx

Field Type : CounterBasedGauge64

Field Status : current

Description : response_6xx

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.184

Field Name : httpProxyOperHttpProxyCpuListResponse510

Field Type : CounterBasedGauge64

Field Status : current

Description : response_510

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.183

Field Name : httpProxyOperHttpProxyCpuListResponse509

Field Type : CounterBasedGauge64

Field Status : current

Description : response_509

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.182

Field Name : httpProxyOperHttpProxyCpuListResponse508

Field Type : CounterBasedGauge64

Field Status : current

Description : response_508

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.181

Field Name : httpProxyOperHttpProxyCpuListResponse507

Field Type : CounterBasedGauge64

Field Status : current

Description : response_507

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.180

Field Name : httpProxyOperHttpProxyCpuListResponse506

Field Type : CounterBasedGauge64

Field Status : current

Description : response_506

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.179

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListResponse505
Field Type : CounterBasedGauge64
Field Status : current
Description : response_505
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.178

Field Name : httpProxyOperHttpProxyCpuListResponse504Ax
Field Type : CounterBasedGauge64
Field Status : current
Description : response_504_ax
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.177

Field Name : httpProxyOperHttpProxyCpuListResponse504
Field Type : CounterBasedGauge64
Field Status : current
Description : response_504
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.176

Field Name : httpProxyOperHttpProxyCpuListResponse503
Field Type : CounterBasedGauge64
Field Status : current
Description : response_503
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.175

Field Name : httpProxyOperHttpProxyCpuListResponse502
Field Type : CounterBasedGauge64
Field Status : current
Description : response_502
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.174

Field Name : httpProxyOperHttpProxyCpuListResponse501
Field Type : CounterBasedGauge64
Field Status : current
Description : response_501
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.173

Field Name : httpProxyOperHttpProxyCpuListResponse500
Field Type : CounterBasedGauge64
Field Status : current
Description : response_500
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.172

Field Name : httpProxyOperHttpProxyCpuListResponse5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_5xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.171

Field Name : httpProxyOperHttpProxyCpuListResponse450
Field Type : CounterBasedGauge64
Field Status : current
Description : response_450
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.170

Field Name : httpProxyOperHttpProxyCpuListResponse449
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : response_449

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.169

Field Name : httpProxyOperHttpProxyCpuListResponse426

Field Type : CounterBasedGauge64

Field Status : current

Description : response_426

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.168

Field Name : httpProxyOperHttpProxyCpuListResponse425

Field Type : CounterBasedGauge64

Field Status : current

Description : response_425

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.167

Field Name : httpProxyOperHttpProxyCpuListResponse424

Field Type : CounterBasedGauge64

Field Status : current

Description : response_424

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.166

Field Name : httpProxyOperHttpProxyCpuListResponse423

Field Type : CounterBasedGauge64

Field Status : current

Description : response_423

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.165

Field Name : httpProxyOperHttpProxyCpuListResponse422

Field Type : CounterBasedGauge64

Field Status : current

Description : response_422

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.164

Field Name : httpProxyOperHttpProxyCpuListResponse418

Field Type : CounterBasedGauge64

Field Status : current

Description : response_418

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.163

Field Name : httpProxyOperHttpProxyCpuListResponse417

Field Type : CounterBasedGauge64

Field Status : current

Description : response_417

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.162

Field Name : httpProxyOperHttpProxyCpuListResponse416

Field Type : CounterBasedGauge64

Field Status : current

Description : response_416

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.161

Field Name : httpProxyOperHttpProxyCpuListResponse415

Field Type : CounterBasedGauge64

Field Status : current

Description : response_415

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.160

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListResponse414
Field Type : CounterBasedGauge64
Field Status : current
Description : response_414
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.159

Field Name : httpProxyOperHttpProxyCpuListResponse413
Field Type : CounterBasedGauge64
Field Status : current
Description : response_413
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.158

Field Name : httpProxyOperHttpProxyCpuListResponse412
Field Type : CounterBasedGauge64
Field Status : current
Description : response_412
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.157

Field Name : httpProxyOperHttpProxyCpuListResponse411
Field Type : CounterBasedGauge64
Field Status : current
Description : response_411
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.156

Field Name : httpProxyOperHttpProxyCpuListResponse410
Field Type : CounterBasedGauge64
Field Status : current
Description : response_410
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.155

Field Name : httpProxyOperHttpProxyCpuListResponse409
Field Type : CounterBasedGauge64
Field Status : current
Description : response_409
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.154

Field Name : httpProxyOperHttpProxyCpuListResponse408
Field Type : CounterBasedGauge64
Field Status : current
Description : response_408
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.153

Field Name : httpProxyOperHttpProxyCpuListResponse407
Field Type : CounterBasedGauge64
Field Status : current
Description : response_407
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.152

Field Name : httpProxyOperHttpProxyCpuListResponse406
Field Type : CounterBasedGauge64
Field Status : current
Description : response_406
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.151

Field Name : httpProxyOperHttpProxyCpuListResponse405
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : response_405

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.150

Field Name : httpProxyOperHttpProxyCpuListResponse404

Field Type : CounterBasedGauge64

Field Status : current

Description : response_404

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.149

Field Name : httpProxyOperHttpProxyCpuListResponse403

Field Type : CounterBasedGauge64

Field Status : current

Description : response_403

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.148

Field Name : httpProxyOperHttpProxyCpuListResponse402

Field Type : CounterBasedGauge64

Field Status : current

Description : response_402

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.147

Field Name : httpProxyOperHttpProxyCpuListResponse401

Field Type : CounterBasedGauge64

Field Status : current

Description : response_401

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.146

Field Name : httpProxyOperHttpProxyCpuListResponse400

Field Type : CounterBasedGauge64

Field Status : current

Description : response_400

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.145

Field Name : httpProxyOperHttpProxyCpuListResponse4xx

Field Type : CounterBasedGauge64

Field Status : current

Description : response_4xx

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.144

Field Name : httpProxyOperHttpProxyCpuListResponse307

Field Type : CounterBasedGauge64

Field Status : current

Description : response_307

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.143

Field Name : httpProxyOperHttpProxyCpuListResponse306

Field Type : CounterBasedGauge64

Field Status : current

Description : response_306

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.142

Field Name : httpProxyOperHttpProxyCpuListResponse305

Field Type : CounterBasedGauge64

Field Status : current

Description : response_305

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.141

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListResponse304
Field Type : CounterBasedGauge64
Field Status : current
Description : response_304
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.140

Field Name : httpProxyOperHttpProxyCpuListResponse303
Field Type : CounterBasedGauge64
Field Status : current
Description : response_303
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.139

Field Name : httpProxyOperHttpProxyCpuListResponse302
Field Type : CounterBasedGauge64
Field Status : current
Description : response_302
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.138

Field Name : httpProxyOperHttpProxyCpuListResponse301
Field Type : CounterBasedGauge64
Field Status : current
Description : response_301
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.137

Field Name : httpProxyOperHttpProxyCpuListResponse300
Field Type : CounterBasedGauge64
Field Status : current
Description : response_300
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.136

Field Name : httpProxyOperHttpProxyCpuListResponse3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : response_3xx
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.135

Field Name : httpProxyOperHttpProxyCpuListResponse207
Field Type : CounterBasedGauge64
Field Status : current
Description : response_207
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.134

Field Name : httpProxyOperHttpProxyCpuListResponse206
Field Type : CounterBasedGauge64
Field Status : current
Description : response_206
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.133

Field Name : httpProxyOperHttpProxyCpuListResponse205
Field Type : CounterBasedGauge64
Field Status : current
Description : response_205
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.132

Field Name : httpProxyOperHttpProxyCpuListResponse204
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : response_204

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.131

Field Name : httpProxyOperHttpProxyCpuListResponse203

Field Type : CounterBasedGauge64

Field Status : current

Description : response_203

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.130

Field Name : httpProxyOperHttpProxyCpuListResponse202

Field Type : CounterBasedGauge64

Field Status : current

Description : response_202

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.129

Field Name : httpProxyOperHttpProxyCpuListResponse201

Field Type : CounterBasedGauge64

Field Status : current

Description : response_201

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.128

Field Name : httpProxyOperHttpProxyCpuListResponse200

Field Type : CounterBasedGauge64

Field Status : current

Description : response_200

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.127

Field Name : httpProxyOperHttpProxyCpuListResponse2xx

Field Type : CounterBasedGauge64

Field Status : current

Description : response_2xx

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.126

Field Name : httpProxyOperHttpProxyCpuListResponse102

Field Type : CounterBasedGauge64

Field Status : current

Description : response_102

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.125

Field Name : httpProxyOperHttpProxyCpuListResponse101

Field Type : CounterBasedGauge64

Field Status : current

Description : response_101

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.124

Field Name : httpProxyOperHttpProxyCpuListResponse100

Field Type : CounterBasedGauge64

Field Status : current

Description : response_100

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.123

Field Name : httpProxyOperHttpProxyCpuListResponse1xx

Field Type : CounterBasedGauge64

Field Status : current

Description : response_1xx

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.122

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListResponseHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : response_http11
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.121

Field Name : httpProxyOperHttpProxyCpuListResponseHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : response_http10
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.120

Field Name : httpProxyOperHttpProxyCpuListReqUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : req_unknown
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.119

Field Name : httpProxyOperHttpProxyCpuListReqDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : req_delete
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.118

Field Name : httpProxyOperHttpProxyCpuListReqConnect
Field Type : CounterBasedGauge64
Field Status : current
Description : req_connect
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.117

Field Name : httpProxyOperHttpProxyCpuListReqOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : req_options
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.116

Field Name : httpProxyOperHttpProxyCpuListReqTrack
Field Type : CounterBasedGauge64
Field Status : current
Description : req_track
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.115

Field Name : httpProxyOperHttpProxyCpuListReqTrace
Field Type : CounterBasedGauge64
Field Status : current
Description : req_trace
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.114

Field Name : httpProxyOperHttpProxyCpuListReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : req_post
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.113

Field Name : httpProxyOperHttpProxyCpuListReqPut
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : req_put

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.112

Field Name : httpProxyOperHttpProxyCpuListReqHead

Field Type : CounterBasedGauge64

Field Status : current

Description : req_head

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.111

Field Name : httpProxyOperHttpProxyCpuListReqGet

Field Type : CounterBasedGauge64

Field Status : current

Description : req_get

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.110

Field Name : httpProxyOperHttpProxyCpuListResponseHttp3

Field Type : CounterBasedGauge64

Field Status : current

Description : response_http3

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.109

Field Name : httpProxyOperHttpProxyCpuListReqHttp3

Field Type : CounterBasedGauge64

Field Status : current

Description : req_http3

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.108

Field Name : httpProxyOperHttpProxyCpuListResponseHttp2

Field Type : CounterBasedGauge64

Field Status : current

Description : response_http2

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.107

Field Name : httpProxyOperHttpProxyCpuListReqHttp2

Field Type : CounterBasedGauge64

Field Status : current

Description : req_http2

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.106

Field Name : httpProxyOperHttpProxyCpuListReqHttp11NewProxy

Field Type : CounterBasedGauge64

Field Status : current

Description : req_http11_new_proxy

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.105

Field Name : httpProxyOperHttpProxyCpuListReqHttp11

Field Type : CounterBasedGauge64

Field Status : current

Description : req_http11

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.104

Field Name : httpProxyOperHttpProxyCpuListReqHttp10

Field Type : CounterBasedGauge64

Field Status : current

Description : req_http10

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.103

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListAfleXlbReselectOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_lb_reselect_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.102

Field Name : httpProxyOperHttpProxyCpuListAfleXlbReselect
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_lb_reselect
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.101

Field Name : httpProxyOperHttpProxyCpuListAfleXretry
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_retry
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.100

Field Name : httpProxyOperHttpProxyCpuListRetry503
Field Type : CounterBasedGauge64
Field Status : current
Description : retry_503
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.99

Field Name : httpProxyOperHttpProxyCpuListNegativeRespRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : negative_resp_remain
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.98

Field Name : httpProxyOperHttpProxyCpuListNegativeReqRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : negative_req_remain
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.97

Field Name : httpProxyOperHttpProxyCpuListSkipInsertClientPort
Field Type : CounterBasedGauge64
Field Status : current
Description : skip_insert_client_port
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.96

Field Name : httpProxyOperHttpProxyCpuListSkipInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : skip_insert_client_ip
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.95

Field Name : httpProxyOperHttpProxyCpuListInsertClientPort
Field Type : CounterBasedGauge64
Field Status : current
Description : insert_client_port
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.94

Field Name : httpProxyOperHttpProxyCpuListInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : insert_client_ip

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.93

Field Name : httpProxyOperHttpProxyCpuListHeaderDelete

Field Type : CounterBasedGauge64

Field Status : current

Description : header_delete

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.92

Field Name : httpProxyOperHttpProxyCpuListHeaderInsert

Field Type : CounterBasedGauge64

Field Status : current

Description : header_insert

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.91

Field Name : httpProxyOperHttpProxyCpuListWrongRespHeader

Field Type : CounterBasedGauge64

Field Status : current

Description : wrong_resp_header

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.90

Field Name : httpProxyOperHttpProxyCpuListHeaderNameTooLong

Field Type : CounterBasedGauge64

Field Status : current

Description : header_name_too_long

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.89

Field Name : httpProxyOperHttpProxyCpuListLineTooLong

Field Type : CounterBasedGauge64

Field Status : current

Description : line_too_long

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.88

Field Name : httpProxyOperHttpProxyCpuListTooManyHeaders

Field Type : CounterBasedGauge64

Field Status : current

Description : too_many_headers

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.87

Field Name : httpProxyOperHttpProxyCpuListInvalidHeader

Field Type : CounterBasedGauge64

Field Status : current

Description : invalid_header

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.86

Field Name : httpProxyOperHttpProxyCpuListAsmSetcookieHeaderFail

Field Type : CounterBasedGauge64

Field Status : current

Description : asm_setcookie_header_fail

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.85

Field Name : httpProxyOperHttpProxyCpuListAsmSetcookieFail

Field Type : CounterBasedGauge64

Field Status : current

Description : asm_setcookie_fail

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.84

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListAsmCookieHeaderFail
Field Type : CounterBasedGauge64
Field Status : current
Description : asm_cookie_header_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.83

Field Name : httpProxyOperHttpProxyCpuListAsmCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : asm_cookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.82

Field Name : httpProxyOperHttpProxyCpuListParseSetcookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : parse_setcookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.81

Field Name : httpProxyOperHttpProxyCpuListParseCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : parse_cookie_fail
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.80

Field Name : httpProxyOperHttpProxyCpuListHugeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : huge_cookie_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.79

Field Name : httpProxyOperHttpProxyCpuListHugeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : huge_cookie
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.78

Field Name : httpProxyOperHttpProxyCpuListLargeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : large_cookie_header
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.77

Field Name : httpProxyOperHttpProxyCpuListLargeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : large_cookie
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.76

Field Name : httpProxyOperHttpProxyCpuListServerReselFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : server_resel_failed
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.75

Field Name : httpProxyOperHttpProxyCpuListStaleSess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : stale_sess

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.74

Field Name : httpProxyOperHttpProxyCpuListPktsRetrans

Field Type : CounterBasedGauge64

Field Status : current

Description : pkts_retrans

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.73

Field Name : httpProxyOperHttpProxyCpuListPktsOfo

Field Type : CounterBasedGauge64

Field Status : current

Description : pkts_ofo

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.72

Field Name : httpProxyOperHttpProxyCpuListConnectingAck

Field Type : CounterBasedGauge64

Field Status : current

Description : connecting_ack

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.71

Field Name : httpProxyOperHttpProxyCpuListConnectingRstOfo

Field Type : CounterBasedGauge64

Field Status : current

Description : connecting_rst_ofo

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.70

Field Name : httpProxyOperHttpProxyCpuListConnectingRstRetrans

Field Type : CounterBasedGauge64

Field Status : current

Description : connecting_rst_retrans

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.69

Field Name : httpProxyOperHttpProxyCpuListConnectingRst

Field Type : CounterBasedGauge64

Field Status : current

Description : connecting_rst

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.68

Field Name : httpProxyOperHttpProxyCpuListConnectingFinOfo

Field Type : CounterBasedGauge64

Field Status : current

Description : connecting_fin_ofo

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.67

Field Name : httpProxyOperHttpProxyCpuListConnectingFinRetrans

Field Type : CounterBasedGauge64

Field Status : current

Description : connecting_fin_retrans

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.66

Field Name : httpProxyOperHttpProxyCpuListConnectingFin

Field Type : CounterBasedGauge64

Field Status : current

Description : connecting_fin

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.65

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListClientReqUnexpFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : client_req_unexp_flag
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.64

Field Name : httpProxyOperHttpProxyCpuListServerRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_response
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.63

Field Name : httpProxyOperHttpProxyCpuListServerRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_connected
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.62

Field Name : httpProxyOperHttpProxyCpuListServerRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.61

Field Name : httpProxyOperHttpProxyCpuListServerRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_request
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.60

Field Name : httpProxyOperHttpProxyCpuListClientRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_response
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.59

Field Name : httpProxyOperHttpProxyCpuListClientRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_connected
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.58

Field Name : httpProxyOperHttpProxyCpuListClientRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.57

Field Name : httpProxyOperHttpProxyCpuListClientRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_request
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.56

Field Name : httpProxyOperHttpProxyCpuListNonHttpBypass
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : non_http_bypass

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.55

Field Name : httpProxyOperHttpProxyCpuListHttpPolicySwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : http_policy_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.343

Field Name : httpProxyOperHttpProxyCpuListLbSwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : lb_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.54

Field Name : httpProxyOperHttpProxyCpuListHostSwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : host_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.53

Field Name : httpProxyOperHttpProxyCpuListUrlSwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : url_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.52

Field Name : httpProxyOperHttpProxyCpuListAflexSwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : aflex_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.51

Field Name : httpProxyOperHttpProxyCpuListCookieSwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : cookie_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.50

Field Name : httpProxyOperHttpProxyCpuListL4SwitchingEnqueue

Field Type : CounterBasedGauge64

Field Status : current

Description : l4_switching_enqueue

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.49

Field Name : httpProxyOperHttpProxyCpuListHttpPolicySwitchingOk

Field Type : CounterBasedGauge64

Field Status : current

Description : http_policy_switching_ok

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.342

Field Name : httpProxyOperHttpProxyCpuListLbSwitchingOk

Field Type : CounterBasedGauge64

Field Status : current

Description : lb_switching_ok

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.48

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListHostSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : host_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.47

Field Name : httpProxyOperHttpProxyCpuListUrlSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : url_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.46

Field Name : httpProxyOperHttpProxyCpuListAflexSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.45

Field Name : httpProxyOperHttpProxyCpuListCookieSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : cookie_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.44

Field Name : httpProxyOperHttpProxyCpuListL4SwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_switching_ok
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.43

Field Name : httpProxyOperHttpProxyCpuListHttpPolicySwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : http_policy_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.341

Field Name : httpProxyOperHttpProxyCpuListLbSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : lb_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.42

Field Name : httpProxyOperHttpProxyCpuListHostSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : host_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.41

Field Name : httpProxyOperHttpProxyCpuListUrlSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : url_switching
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.40

Field Name : httpProxyOperHttpProxyCpuListAflexSwitching
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : aflex_switching

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.39

Field Name : httpProxyOperHttpProxyCpuListCookieSwitching

Field Type : CounterBasedGauge64

Field Status : current

Description : cookie_switching

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.38

Field Name : httpProxyOperHttpProxyCpuListL4Switching

Field Type : CounterBasedGauge64

Field Status : current

Description : l4_switching

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.37

Field Name : httpProxyOperHttpProxyCpuListFwdreqFailTuple

Field Type : CounterBasedGauge64

Field Status : current

Description : fwdreq_fail_tuple

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.36

Field Name : httpProxyOperHttpProxyCpuListFwdreqFailServer

Field Type : CounterBasedGauge64

Field Status : current

Description : fwdreq_fail_server

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.35

Field Name : httpProxyOperHttpProxyCpuListFwdreqFailPersist

Field Type : CounterBasedGauge64

Field Status : current

Description : fwdreq_fail_persist

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.34

Field Name : httpProxyOperHttpProxyCpuListFwdreqFailRoute

Field Type : CounterBasedGauge64

Field Status : current

Description : fwdreq_fail_route

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.33

Field Name : httpProxyOperHttpProxyCpuListFwdreqFailRport

Field Type : CounterBasedGauge64

Field Status : current

Description : fwdreq_fail_rport

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.32

Field Name : httpProxyOperHttpProxyCpuListFwdreqFailBuff

Field Type : CounterBasedGauge64

Field Status : current

Description : fwdreq_fail_buff

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.31

Field Name : httpProxyOperHttpProxyCpuListFwdreqFail

Field Type : CounterBasedGauge64

Field Status : current

Description : fwdreq_fail

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.30

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.29

Field Name : httpProxyOperHttpProxyCpuListClientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.28

Field Name : httpProxyOperHttpProxyCpuListDecompressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_after
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.27

Field Name : httpProxyOperHttpProxyCpuListDecompressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : decompression_before
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.26

Field Name : httpProxyOperHttpProxyCpuListCloseOnDdos
Field Type : CounterBasedGauge64
Field Status : current
Description : close_on_ddos
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.25

Field Name : httpProxyOperHttpProxyCpuListReqRateOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : req_rate_over_limit
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.24

Field Name : httpProxyOperHttpProxyCpuListReqOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : req_over_limit
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.23

Field Name : httpProxyOperHttpProxyCpuListCompressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_after
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.22

Field Name : httpProxyOperHttpProxyCpuListCompressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_before
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.21

Field Name : httpProxyOperHttpProxyCpuListSnatFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description : snat_fail

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.20

Field Name : httpProxyOperHttpProxyCpuListNewSvrconn

Field Type : CounterBasedGauge64

Field Status : current

Description : new_svrconn

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.19

Field Name : httpProxyOperHttpProxyCpuListSvrPremClose

Field Type : CounterBasedGauge64

Field Status : current

Description : svr_prem_close

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.18

Field Name : httpProxyOperHttpProxyCpuListServerResel

Field Type : CounterBasedGauge64

Field Status : current

Description : server_resel

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.17

Field Name : httpProxyOperHttpProxyCpuListReqOfo

Field Type : CounterBasedGauge64

Field Status : current

Description : req_ofo

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.16

Field Name : httpProxyOperHttpProxyCpuListReqRetran

Field Type : CounterBasedGauge64

Field Status : current

Description : req_retran

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.15

Field Name : httpProxyOperHttpProxyCpuListFwdreqdataFail

Field Type : CounterBasedGauge64

Field Status : current

Description : fwdreqdata_fail

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.14

Field Name : httpProxyOperHttpProxyCpuListSvrselfFail

Field Type : CounterBasedGauge64

Field Status : current

Description : svrsel_fail

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.13

Field Name : httpProxyOperHttpProxyCpuListParsereqFail

Field Type : CounterBasedGauge64

Field Status : current

Description : parsereq_fail

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.12

Field Name : httpProxyOperHttpProxyCpuListNotuple

Field Type : CounterBasedGauge64

Field Status : current

Description : notuple

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.11

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Field Name : httpProxyOperHttpProxyCpuListNoproxy
Field Type : CounterBasedGauge64
Field Status : current
Description : noproxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.10

Field Name : httpProxyOperHttpProxyCpuListCacheRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : cache_rsp
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.9

Field Name : httpProxyOperHttpProxyCpuListReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.8

Field Name : httpProxyOperHttpProxyCpuListReqEnterSsli
Field Type : CounterBasedGauge64
Field Status : current
Description : req_enter_ssli
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.7

Field Name : httpProxyOperHttpProxyCpuListConnectReq
Field Type : CounterBasedGauge64
Field Status : current
Description : connect_req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.6

Field Name : httpProxyOperHttpProxyCpuListReq
Field Type : CounterBasedGauge64
Field Status : current
Description : req
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.5

Field Name : httpProxyOperHttpProxyCpuListTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : total_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.4

Field Name : httpProxyOperHttpProxyCpuListCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.3

Field Name : httpProxyOperHttpProxyCpuListHttpProxyCpuListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.2

Field Name : httpProxyOperHttpProxyCpuListSlotId
Field Type : Integer32
Field Status : current

ACOS-SLB-HTTP-PROXY-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.356.1.3.1.1

ACOS-SLB-L4-MIB_oid_list

Field Name : l40perL4CpuListTable
Field Type : TABLE
Field Status : current
Description : ConfigureL4 from object 'slb.l4'
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3

Field Name : l40perTable
Field Type : TABLE
Field Status : current
Description : ConfigureL4 from object 'slb.l4'
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.2

Field Name : l40perEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The l40per entry
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.2.1

Field Name : l40perCpuCount
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-count
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.2.1.2

Field Name : l40perSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.2.1.1

Field Name : l4StatsTable
Field Type : TABLE
Field Status : current
Description : ConfigureL4 from object 'slb.l4'
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1

Field Name : l4StatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The l4Stats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1

Field Name : l4StatsFastPathL2Reroute
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_path_l2_reroute
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.139

Field Name : l4StatsFastPathReroute
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_path_reroute
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.138

Field Name : l4StatsPbslbEntryLimitExceed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : pbslb_entry_limit_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.137

Field Name : l4StatsSlbGtpProxyRetxRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_retx_requests
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.136

Field Name : l4StatsSlbGtpProxySmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_freed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.135

Field Name : l4StatsSlbGtpProxySmpFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_free_not_found
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.134

Field Name : l4StatsSlbGtpProxySmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_created
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.133

Field Name : l4StatsSlbGtpProxySmpCreationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_creation_failed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.132

Field Name : l4StatsSlbGtpProxyCProcessLocalRr
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_c_process_local_rr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.131

Field Name : l4StatsSlbGtpProxySmpNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_no_match
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.130

Field Name : l4StatsSlbGtpProxySmpMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_match
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.129

Field Name : l4StatsSlbGtpProxyPktRcvRr
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_pkt_rcv_rr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.128

ACOS-SLB-L4-MIB_oid_list

Field Name : l4StatsProxyProtDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_prot_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.127

Field Name : l4StatsProxyProtError
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_prot_error
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.126

Field Name : l4StatsProxyHeaderRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_header_rexmit
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.125

Field Name : l4StatsProxyHeaderInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_header_insert
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.124

Field Name : l4StatsSnatForcePreserveFree
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_force_preserve_free
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.123

Field Name : l4StatsSnatForcePreserveAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_force_preserve_alloc
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.122

Field Name : l4StatsSnatPortOverloadFail
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_port_overload_fail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.121

Field Name : l4StatsReselectSvrselffail
Field Type : CounterBasedGauge64
Field Status : current
Description : reselect_svrselffail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.120

Field Name : l4StatsGtpCInvalidMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : gtp_c_invalid_message
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.119

Field Name : l4StatsGtpCInvalidHeader
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : gtp_c_invalid_header
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.118

Field Name : l4StatsGtpCInvalidPort
Field Type : CounterBasedGauge64
Field Status : current
Description : gtp_c_invalid_port
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.117

Field Name : l4StatsTcpConnectionsClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_connections_closed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.116

Field Name : l4StatsRateDropResetUnkn
Field Type : CounterBasedGauge64
Field Status : current
Description : rate_drop_reset_unkn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.115

Field Name : l4StatsDnssecSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : dnssec_switch
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.114

Field Name : l4StatsServerDownDel
Field Type : CounterBasedGauge64
Field Status : current
Description : server_down_del
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.113

Field Name : l4StatsDnsIdSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_id_switch
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.112

Field Name : l4StatsSynreceivedHw
Field Type : CounterBasedGauge64
Field Status : current
Description : synreceived_hw
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.111

Field Name : l4StatsSkipInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : skip_insert_client_ip
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.110

Field Name : l4StatsSyncookieBuffQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookie_buff_queue
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.109

ACOS-SLB-L4-MIB_oid_list

Field Name : l4StatsSyncookieBuffDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookie_buff_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.108

Field Name : l4StatsSynRate
Field Type : CounterBasedGauge64
Field Status : current
Description : syn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.107

Field Name : l4StatsSynattack
Field Type : CounterBasedGauge64
Field Status : current
Description : synattack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.106

Field Name : l4StatsTcpEst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_est
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.105

Field Name : l4StatsOutSeqAckDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : out_seq_ack_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.104

Field Name : l4StatsUdpRespOneplus
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_resp_oneplus
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.103

Field Name : l4StatsUdpReqOneplus
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_req_oneplus
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.102

Field Name : l4StatsUdpRespMoreReq
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_resp_more_req
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.101

Field Name : l4StatsUdpReqMoreResp
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_req_more_resp
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.100

Field Name : l4StatsUdpReqRespNotmatch
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : udp_req_resp_notmatch
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.99

Field Name : l4StatsUdpReqOneOneplusResp
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_req_one_oneplus_resp
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.98

Field Name : l4StatsUdpReqOneplusNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_req_oneplus_no_resp
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.97

Field Name : l4StatsTcpRevRst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rev_rst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.96

Field Name : l4StatsTcpFwdRst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_fwd_rst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.95

Field Name : l4StatsTcpRevAckfin
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rev_ackfin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.94

Field Name : l4StatsTcpRevFinDup
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rev_fin_dup
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.93

Field Name : l4StatsTcpFwdFinDup
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_fwd_fin_dup
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.92

Field Name : l4StatsTcpRexmitSynackDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rexmit_synack_delq
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.91

Field Name : l4StatsTcpRexmitSynack
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rexmit_synack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.90

ACOS-SLB-L4-MIB_oid_list

Field Name : l4StatsTcpRexmitSynDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rexmit_syn_delq
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.89

Field Name : l4StatsTcpRexmitSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rexmit_syn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.88

Field Name : l4StatsTcpSessNoestSsynXmitAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_sess_noest_ssyn_xmit_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.87

Field Name : l4StatsTcpSessNoestCsynRcvAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_sess_noest_csyn_rcv_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.86

Field Name : l4StatsTcpSessNoestAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_sess_noest_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.85

Field Name : l4StatsTcpSynRcvRst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syn_rcv_rst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.84

Field Name : l4StatsTcpSynRcvAck
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syn_rcv_ack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.83

Field Name : l4StatsTcpAxRexmitSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_ax_rexmit_syn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.82

Field Name : l4StatsStatelessConnTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : stateless_conn_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.81

Field Name : l4StatsSvrSynHandshakeFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : svr_syn_handshake_fail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.80

Field Name : l4StatsConcurrentConnExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : concurrent_conn_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.79

Field Name : l4StatsSslWatermarkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl_watermark_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.78

Field Name : l4StatsSslTptExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl_tpt_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.77

Field Name : l4StatsSslCpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl_cps_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.76

Field Name : l4StatsL7CpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : l7_cps_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.75

Field Name : l4StatsNatCpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_cps_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.74

Field Name : l4StatsL4CpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_cps_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.73

Field Name : l4StatsBwWatermarkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : bw_watermark_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.72

Field Name : l4StatsBwRateLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : bw_rate_limit_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.71

ACOS-SLB-L4-MIB_oid_list

Field Name : l4StatsTcpothterflagsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : tcpothterflags_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.70

Field Name : l4StatsTcpsyndataDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : tcpsyndata_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.69

Field Name : l4StatsPortPreserveSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : port_preserve_succ
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.68

Field Name : l4StatsPortPreserveAttempt
Field Type : CounterBasedGauge64
Field Status : current
Description : port_preserve_attempt
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.67

Field Name : l4StatsL3Dsr
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_dsr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.66

Field Name : l4StatsL2Dsr
Field Type : CounterBasedGauge64
Field Status : current
Description : l2_dsr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.65

Field Name : l4StatsIgnoreMsl
Field Type : CounterBasedGauge64
Field Status : current
Description : ignore_msl
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.64

Field Name : l4StatsResetL7OnFailover
Field Type : CounterBasedGauge64
Field Status : current
Description : reset_l7_on_failover
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.63

Field Name : l4StatsResetUnknownConn
Field Type : CounterBasedGauge64
Field Status : current
Description : reset_unknown_conn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.62

Field Name : l4StatsNoResourceDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : no_resource_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.61

Field Name : l4StatsAnomalyPbslbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_pbslb_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.60

Field Name : l4StatsAnomalyBadContent
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_bad_content
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.59

Field Name : l4StatsAnomalyZeroWin
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_zero_win
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.58

Field Name : l4StatsAnomalyOutSeq
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_out_seq
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.57

Field Name : l4StatsTcpInvalidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_invalid_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.56

Field Name : l4StatsDnsPolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_policy_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.55

Field Name : l4StatsFastAgingReset
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_aging_reset
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.54

Field Name : l4StatsFastAgingSet
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_aging_set
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.53

Field Name : l4StatsAutoReassign
Field Type : CounterBasedGauge64
Field Status : current
Description : auto_reassign
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.52

ACOS-SLB-L4-MIB_oid_list

Field Name : l4StatsInbandHmReassign
Field Type : CounterBasedGauge64
Field Status : current
Description : inband_hm_reassign
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.51

Field Name : l4StatsInbandHmRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : inband_hm_retry
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.50

Field Name : l4StatsDropGslb
Field Type : CounterBasedGauge64
Field Status : current
Description : drop_gslb
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.49

Field Name : l4StatsThrottleSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : throttle_syn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.48

Field Name : l4StatsUdpNoSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_no_slb
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.47

Field Name : l4StatsTcpNoSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_no_slb
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.46

Field Name : l4StatsOtherSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : other_sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.45

Field Name : l4StatsUdpSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.44

Field Name : l4StatsTcpSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.43

Field Name : l4StatsSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.42

Field Name : l4StatsDropAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : drop_aflex
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.41

Field Name : l4StatsProxyNosockDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_nosock_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.40

Field Name : l4StatsConnRateLimitReset
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_rate_limit_reset
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.39

Field Name : l4StatsConnRateLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_rate_limit_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.38

Field Name : l4StatsConnlimitReset
Field Type : CounterBasedGauge64
Field Status : current
Description : connlimit_reset
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.37

Field Name : l4StatsConnlimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : connlimit_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.36

Field Name : l4StatsNosynDropAck
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop_ack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.35

Field Name : l4StatsNosynDropRst
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop_rst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.34

Field Name : l4StatsNosynDropFin
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop_fin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.33

ACOS-SLB-L4-MIB_oid_list

Field Name : l4StatsNosynDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.32

Field Name : l4StatsNoVportDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : no_vport_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.31

Field Name : l4StatsNovportDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : novport_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.30

Field Name : l4StatsSyncookiescheckfailed
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookiescheckfailed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.29

Field Name : l4StatsSmartNatIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : smart_nat_id_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.28

Field Name : l4StatsSnatIcmpNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_icmp_no_match
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.27

Field Name : l4StatsSnatIcmpErrorProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_icmp_error_process
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.26

Field Name : l4StatsSnatNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_no_rev_route
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.25

Field Name : l4StatsSnatNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : snat_no_fwd_route
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.24

Field Name : l4StatsSnatFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : snat_fail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.23

Field Name : l4StatsNoroute
Field Type : CounterBasedGauge64
Field Status : current
Description : noroute
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.22

Field Name : l4StatsSvrselfail
Field Type : CounterBasedGauge64
Field Status : current
Description : svrselfail
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.21

Field Name : l4StatsOutrstTcproxy
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst_tcproxy
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.20

Field Name : l4StatsSynStaleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : syn_stale_sess
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.19

Field Name : l4StatsOutrstStaleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst_stale_sess
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.18

Field Name : l4StatsOutrstAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst_aflex
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.17

Field Name : l4StatsOutrstAckAttack
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst_ack_attack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.16

Field Name : l4StatsOutrstBroker
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst_broker
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.15

Field Name : l4StatsOutrstNosyn
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst_nosyn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.14

ACOS-SLB-L4-MIB_oid_list

Field Name : l4StatsOutrst
Field Type : CounterBasedGauge64
Field Status : current
Description : outrst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.13

Field Name : l4StatsSyncookieissentfailed
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookieissentfailed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.12

Field Name : l4StatsSyncookieissentTs
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookieissent_ts
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.11

Field Name : l4StatsSyncookieissent
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookieissent
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.10

Field Name : l4StatsInudp
Field Type : CounterBasedGauge64
Field Status : current
Description : inudp
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.9

Field Name : l4StatsTcpFwdAckfin
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_fwd_ackfin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.8

Field Name : l4StatsTcpFwdFin
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_fwd_fin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.7

Field Name : l4StatsTcpRevFin
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rev_fin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.6

Field Name : l4StatsTcpRevLastAck
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_rev_last_ack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.5

Field Name : l4StatsTcpFwdLastAck
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : tcp_fwd_last_ack

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.4

Field Name : l4StatsSynreceived

Field Type : CounterBasedGauge64

Field Status : current

Description : synreceived

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.3

Field Name : l4StatsIntcp

Field Type : CounterBasedGauge64

Field Status : current

Description : intcp

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.2

Field Name : l4StatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.1.1.1

Field Name : l40perL4CpuListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The l40perL4CpuList entry:l4-cpu-list

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1

Field Name : l40perL4CpuListFastPathL2Reroute

Field Type : CounterBasedGauge64

Field Status : current

Description : fast_path_l2_reroute

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.137

Field Name : l40perL4CpuListFastPathReroute

Field Type : CounterBasedGauge64

Field Status : current

Description : fast_path_reroute

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.136

Field Name : l40perL4CpuListPbslbEntryLimitExceed

Field Type : CounterBasedGauge64

Field Status : current

Description : pbslb_entry_limit_exceed

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.135

Field Name : l40perL4CpuListSlbGtpProxyRetxRequests

Field Type : CounterBasedGauge64

Field Status : current

Description : slb_gtp_proxy_retx_requests

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.134

Field Name : l40perL4CpuListSlbGtpProxySmpFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : slb_gtp_proxy_smp_freed

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.133

ACOS-SLB-L4-MIB_oid_list

Field Name : 140perL4CpuListSlbGtpProxySmpFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_free_not_found
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.132

Field Name : 140perL4CpuListSlbGtpProxySmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_created
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.131

Field Name : 140perL4CpuListSlbGtpProxySmpCreationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_creation_failed
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.130

Field Name : 140perL4CpuListSlbGtpProxyCProcessLocalRr
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_c_process_local_rr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.129

Field Name : 140perL4CpuListSlbGtpProxySmpNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_no_match
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.128

Field Name : 140perL4CpuListSlbGtpProxySmpMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_smp_match
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.127

Field Name : 140perL4CpuListSlbGtpProxyPktRcvRr
Field Type : CounterBasedGauge64
Field Status : current
Description : slb_gtp_proxy_pkt_rcv_rr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.126

Field Name : 140perL4CpuListProxyProtDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_prot_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.125

Field Name : 140perL4CpuListProxyProtError
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_prot_error
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.124

Field Name : 140perL4CpuListProxyHeaderRexmit
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : proxy_header_rexmit

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.123

Field Name : l40perL4CpuListProxyHeaderInsert

Field Type : CounterBasedGauge64

Field Status : current

Description : proxy_header_insert

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.122

Field Name : l40perL4CpuListSnatForcePreserveFree

Field Type : CounterBasedGauge64

Field Status : current

Description : snat_force_preserve_free

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.121

Field Name : l40perL4CpuListSnatForcePreserveAlloc

Field Type : CounterBasedGauge64

Field Status : current

Description : snat_force_preserve_alloc

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.120

Field Name : l40perL4CpuListSnatPortOverloadFail

Field Type : CounterBasedGauge64

Field Status : current

Description : snat_port_overload_fail

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.119

Field Name : l40perL4CpuListReselectSvrselffail

Field Type : CounterBasedGauge64

Field Status : current

Description : reselect_svrselffail

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.118

Field Name : l40perL4CpuListGtpCInvalidMessage

Field Type : CounterBasedGauge64

Field Status : current

Description : gtp_c_invalid_message

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.117

Field Name : l40perL4CpuListGtpCInvalidHeader

Field Type : CounterBasedGauge64

Field Status : current

Description : gtp_c_invalid_header

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.116

Field Name : l40perL4CpuListGtpCInvalidPort

Field Type : CounterBasedGauge64

Field Status : current

Description : gtp_c_invalid_port

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.115

Field Name : l40perL4CpuListTcpConnectionsClosed

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp_connections_closed

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.114

ACOS-SLB-L4-MIB_oid_list

Field Name : l40perL4CpuListServerDownDel
Field Type : CounterBasedGauge64
Field Status : current
Description : server_down_del
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.113

Field Name : l40perL4CpuListSyncookiesBuffDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookies_buff_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.112

Field Name : l40perL4CpuListSyncookiesBuffQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : syncookies_buff_queue
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.111

Field Name : l40perL4CpuListDnssecSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : dnssec_switch
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.110

Field Name : l40perL4CpuListDnsIdSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_id_switch
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.109

Field Name : l40perL4CpuListSkipInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : skip_insert_client_ip
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.108

Field Name : l40perL4CpuListSynattack
Field Type : CounterBasedGauge64
Field Status : current
Description : synattack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.107

Field Name : l40perL4CpuListTcpEst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_est
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.106

Field Name : l40perL4CpuListRcvUdpRsps
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_udp_rsps
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.105

Field Name : l40perL4CpuListRcvUdpReqs
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : rcv_udp_reqs

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.104

Field Name : l40perL4CpuListRcvRspsMoreethanReqs

Field Type : CounterBasedGauge64

Field Status : current

Description : rcv_rsps_moreethan_reqs

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.103

Field Name : l40perL4CpuListRcvReqMoreethanRsps

Field Type : CounterBasedGauge64

Field Status : current

Description : rcv_req_moreethan_rsps

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.102

Field Name : l40perL4CpuListRcvReqNotMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : rcv_req_not_match

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.101

Field Name : l40perL4CpuListRcvReqRsps

Field Type : CounterBasedGauge64

Field Status : current

Description : rcv_req_rsps

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.100

Field Name : l40perL4CpuListRcvReqsNoRsp

Field Type : CounterBasedGauge64

Field Status : current

Description : rcv_reqs_no_rsp

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.99

Field Name : l40perL4CpuListRcvRevRst

Field Type : CounterBasedGauge64

Field Status : current

Description : rcv_rev_rst

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.98

Field Name : l40perL4CpuListRcvFwdRst

Field Type : CounterBasedGauge64

Field Status : current

Description : rcv_fwd_rst

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.97

Field Name : l40perL4CpuListRcvRevFinack

Field Type : CounterBasedGauge64

Field Status : current

Description : rcv_rev_finack

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.96

Field Name : l40perL4CpuListRcvRevFinDup

Field Type : CounterBasedGauge64

Field Status : current

Description : rcv_rev_fin_dup

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.95

ACOS-SLB-L4-MIB_oid_list

Field Name : l40perL4CpuListRcvRevFin
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rev_fin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.94

Field Name : l40perL4CpuListRcvFwdFinack
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_fwd_finack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.93

Field Name : l40perL4CpuListRcvFwdFinDup
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_fwd_fin_dup
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.92

Field Name : l40perL4CpuListRcvFwdFin
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_fwd_fin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.91

Field Name : l40perL4CpuListRcvRevLastAck
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rev_last_ack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.90

Field Name : l40perL4CpuListRcvFwdLastAck
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_fwd_last_ack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.89

Field Name : l40perL4CpuListRcvRexmitSynackDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rexmit_synack_delq
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.88

Field Name : l40perL4CpuListRcvRexmitSynack
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rexmit_synack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.87

Field Name : l40perL4CpuListRcvRexmitSynDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : rcv_rexmit_syn_delq
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.86

Field Name : l40perL4CpuListRcvRexmitSyn
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : rcv_rexmit_syn

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.85

Field Name : l40perL4CpuListNoestServerSynXmitAgedOut

Field Type : CounterBasedGauge64

Field Status : current

Description : noest_server_syn_xmit_aged_out

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.84

Field Name : l40perL4CpuListNoestClientSynAgedOut

Field Type : CounterBasedGauge64

Field Status : current

Description : noest_client_syn_aged_out

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.83

Field Name : l40perL4CpuListTcpNoestAgedOut

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp_noest_aged_out

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.82

Field Name : l40perL4CpuListRcvRstOnSyn

Field Type : CounterBasedGauge64

Field Status : current

Description : rcv_rst_on_syn

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.81

Field Name : l40perL4CpuListRcvAckOnSyn

Field Type : CounterBasedGauge64

Field Status : current

Description : rcv_ack_on_syn

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.80

Field Name : l40perL4CpuListAxRexmitSyn

Field Type : CounterBasedGauge64

Field Status : current

Description : ax_rexmit_syn

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.79

Field Name : l40perL4CpuListStatelessConnTimeout

Field Type : CounterBasedGauge64

Field Status : current

Description : stateless_conn_timeout

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.78

Field Name : l40perL4CpuListL4SvrHandshakeFail

Field Type : CounterBasedGauge64

Field Status : current

Description : l4_svr_handshake_fail

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.77

Field Name : l40perL4CpuListConnLimitExceedDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : conn_limit_exceed_drop

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.76

ACOS-SLB-L4-MIB_oid_list

Field Name : l40perL4CpuListSslWatermarkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl_watermark_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.75

Field Name : l40perL4CpuListSslTptExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl_tpt_exceed_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.74

Field Name : l40perL4CpuListSslCpsExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl_cps_exceed_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.73

Field Name : l40perL4CpuListL7CpsExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : l7_cps_exceed_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.72

Field Name : l40perL4CpuListNatCpsExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : nat_cps_exceed_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.71

Field Name : l40perL4CpuListL4CpsExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : l4_cps_exceed_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.70

Field Name : l40perL4CpuListBwWatermarkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : bw_watermark_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.69

Field Name : l40perL4CpuListBwRateLimitExceedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : bw_rate_limit_exceed_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.68

Field Name : l40perL4CpuListPortPreserveSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : port_preserve_succ
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.67

Field Name : l40perL4CpuListPortPreserveAttempt
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : port_preserve_attempt
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.66

Field Name : l40perL4CpuListL3Dsr
Field Type : CounterBasedGauge64
Field Status : current
Description : l3_dsr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.65

Field Name : l40perL4CpuListL2Dsr
Field Type : CounterBasedGauge64
Field Status : current
Description : l2_dsr
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.64

Field Name : l40perL4CpuListIgnoreMsl
Field Type : CounterBasedGauge64
Field Status : current
Description : ignore_msl
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.63

Field Name : l40perL4CpuListTcpSynWithdata
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syn_withdata
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.62

Field Name : l40perL4CpuListTcpSynOtherflags
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_syn_otherflags
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.61

Field Name : l40perL4CpuListResetL7OnFailover
Field Type : CounterBasedGauge64
Field Status : current
Description : reset_l7_on_failover
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.60

Field Name : l40perL4CpuListResetUnknownConn
Field Type : CounterBasedGauge64
Field Status : current
Description : reset_unknown_conn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.59

Field Name : l40perL4CpuListNoResourceDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : no_resource_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.58

Field Name : l40perL4CpuListAnomalyPbslbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_pbslb_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.57

ACOS-SLB-L4-MIB_oid_list

Field Name : l40perL4CpuListAnomalyBadContent
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_bad_content
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.56

Field Name : l40perL4CpuListAnomalyZeroWin
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_zero_win
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.55

Field Name : l40perL4CpuListAnomalyOutSeq
Field Type : CounterBasedGauge64
Field Status : current
Description : anomaly_out_seq
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.54

Field Name : l40perL4CpuListOutSeqAckDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : out_seq_ack_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.53

Field Name : l40perL4CpuListTcpInvalidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_invalid_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.52

Field Name : l40perL4CpuListFastAgingReset
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_aging_reset
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.51

Field Name : l40perL4CpuListFastAgingSet
Field Type : CounterBasedGauge64
Field Status : current
Description : fast_aging_set
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.50

Field Name : l40perL4CpuListAutoReassign
Field Type : CounterBasedGauge64
Field Status : current
Description : auto_reassign
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.49

Field Name : l40perL4CpuListInbandHmReassign
Field Type : CounterBasedGauge64
Field Status : current
Description : inband_hm_reassign
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.48

Field Name : l40perL4CpuListInbandHmRetry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : inband_hm_retry
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.47

Field Name : l40perL4CpuListThrottleSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : throttle_syn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.46

Field Name : l40perL4CpuListUdpNoSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_no_slb
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.45

Field Name : l40perL4CpuListTcpNoSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_no_slb
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.44

Field Name : l40perL4CpuListOtherSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : other_sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.43

Field Name : l40perL4CpuListUdpSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.42

Field Name : l40perL4CpuListTcpSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.41

Field Name : l40perL4CpuListSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : sess_aged_out
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.40

Field Name : l40perL4CpuListAflexDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : aflex_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.39

Field Name : l40perL4CpuListProxyNosockDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_nosock_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.38

ACOS-SLB-L4-MIB_oid_list

Field Name : l40perL4CpuListConnRateLimitReset
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_rate_limit_reset
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.37

Field Name : l40perL4CpuListConnRateLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : conn_rate_limit_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.36

Field Name : l40perL4CpuListConnlimitReset
Field Type : CounterBasedGauge64
Field Status : current
Description : connlimit_reset
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.35

Field Name : l40perL4CpuListConnlimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : connlimit_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.34

Field Name : l40perL4CpuListNosynDropAck
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop_ack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.33

Field Name : l40perL4CpuListNosynDropRst
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop_rst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.32

Field Name : l40perL4CpuListNosynDropFin
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop_fin
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.31

Field Name : l40perL4CpuListNosynDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : nosyn_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.30

Field Name : l40perL4CpuListNoVportDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : no_vport_drop
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.29

Field Name : l40perL4CpuListNovportDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : novport_drop

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.28

Field Name : l40perL4CpuListTcpSyncookiescheckfailed

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp_syncookiescheckfailed

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.27

Field Name : l40perL4CpuListSmartNatIdMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : smart_nat_id_mismatch

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.26

Field Name : l40perL4CpuListSnatIcmpNoMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : snat_icmp_no_match

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.25

Field Name : l40perL4CpuListSnatIcmpErrorProcess

Field Type : CounterBasedGauge64

Field Status : current

Description : snat_icmp_error_process

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.24

Field Name : l40perL4CpuListSnatNoRevRoute

Field Type : CounterBasedGauge64

Field Status : current

Description : snat_no_rev_route

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.23

Field Name : l40perL4CpuListSnatNoFwdRoute

Field Type : CounterBasedGauge64

Field Status : current

Description : snat_no_fwd_route

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.22

Field Name : l40perL4CpuListSnatFail

Field Type : CounterBasedGauge64

Field Status : current

Description : snat_fail

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.21

Field Name : l40perL4CpuListSvrSelFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : svr_sel_failed

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.20

Field Name : l40perL4CpuListInudp

Field Type : CounterBasedGauge64

Field Status : current

Description : inudp

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.19

ACOS-SLB-L4-MIB_oid_list

Field Name : l40perL4CpuListIntcp

Field Type : CounterBasedGauge64

Field Status : current

Description : intcp

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.18

Field Name : l40perL4CpuListTcpSyncookiestentfailed

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp_syncookiestentfailed

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.17

Field Name : l40perL4CpuListTcpSyncookiestentTs

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp_syncookiestent_ts

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.16

Field Name : l40perL4CpuListTcpSyncookiestent

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp_syncookiestent

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.15

Field Name : l40perL4CpuListTcpSynRate

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp_syn_rate

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.14

Field Name : l40perL4CpuListTcpSynreceivedHw

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp_synreceived_hw

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.13

Field Name : l40perL4CpuListTcpSynreceived

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp_synreceived

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.12

Field Name : l40perL4CpuListTcpOustrstTcpproxy

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp_oustrst_tcpproxy

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.11

Field Name : l40perL4CpuListTcpSynStaleSess

Field Type : CounterBasedGauge64

Field Status : current

Description : tcp_syn_stale_sess

OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.10

Field Name : l40perL4CpuListTcpOustrstStaleSess

Field Type : CounterBasedGauge64

Field Status : current

ACOS-SLB-L4-MIB_oid_list

Description : tcp_outrst_stale_sess
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.9

Field Name : l40perL4CpuListTcpOutrstAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_outrst_aflex
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.8

Field Name : l40perL4CpuListTcpOutrstAckAttack
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_outrst_ack_attack
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.7

Field Name : l40perL4CpuListTcpOutrstBroker
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_outrst_broker
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.6

Field Name : l40perL4CpuListTcpOutrstNosyn
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_outrst_nosyn
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.5

Field Name : l40perL4CpuListTcpOutrst
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp_outrst
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.4

Field Name : l40perL4CpuListIpOutnoroute
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_outnoroute
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.3

Field Name : l40perL4CpuListL4CpuListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.2

Field Name : l40perL4CpuListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.358.1.3.1.1

ACOS-SLB-L7SESSION-MIB_oid_list

Field Name : l7sessionStatsTable
Field Type : TABLE
Field Status : current
Description : ConfigureL7session from object 'slb.l7session'
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1

Field Name : l7sessionStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The l7sessionStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1

Field Name : l7sessionStatsInvalidServer
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid_server
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.48

Field Name : l7sessionStatsClientNotCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : client_not_cleaned
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.47

Field Name : l7sessionStatsServerNotCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : server_not_cleaned
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.46

Field Name : l7sessionStatsOldServerCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : old_server_cleaned
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.45

Field Name : l7sessionStatsTransactionCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : transaction_cleaned
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.44

Field Name : l7sessionStatsUdpDataEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : udp_data_event
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.43

Field Name : l7sessionStatsHpsFwdreqFailTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : hps_fwdreq_fail_tuple
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.42

Field Name : l7sessionStatsHpsFwdreqFailServer
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L7SESSION-MIB_oid_list

Description : hps_fwdreq_fail_server
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.41

Field Name : l7sessionStatsHpsFwdreqFailPersist
Field Type : CounterBasedGauge64
Field Status : current
Description : hps_fwdreq_fail_persist
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.40

Field Name : l7sessionStatsHpsFwdreqFailRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : hps_fwdreq_fail_route
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.39

Field Name : l7sessionStatsHpsFwdreqFailRport
Field Type : CounterBasedGauge64
Field Status : current
Description : hps_fwdreq_fail_rport
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.38

Field Name : l7sessionStatsHpsFwdreqFailBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : hps_fwdreq_fail_buff
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.37

Field Name : l7sessionStatsHpsFwdreqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : hps_fwdreq_fail
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.36

Field Name : l7sessionStatsDataCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : data_cb_failed
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.35

Field Name : l7sessionStatsEstCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : est_cb_failed
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.34

Field Name : l7sessionStatsEstEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : est_event
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.33

Field Name : l7sessionStatsServerSelectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : server_select_fail
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.32

ACOS-SLB-L7SESSION-MIB_oid_list

Field Name : l7sessionStatsTotalProxyEs
Field Type : CounterBasedGauge64
Field Status : current
Description : total_proxy_es
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.31

Field Name : l7sessionStatsTotalProxyServer
Field Type : CounterBasedGauge64
Field Status : current
Description : total_proxy_server
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.30

Field Name : l7sessionStatsTotalProxyClient
Field Type : CounterBasedGauge64
Field Status : current
Description : total_proxy_client
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.29

Field Name : l7sessionStatsTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : total_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.28

Field Name : l7sessionStatsCurrProxyEs
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_proxy_es
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.27

Field Name : l7sessionStatsCurrProxyServer
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_proxy_server
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.26

Field Name : l7sessionStatsCurrProxyClient
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_proxy_client
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.25

Field Name : l7sessionStatsCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_proxy
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.24

Field Name : l7sessionStatsProxyV2Connection
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy_v2_connection
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.23

Field Name : l7sessionStatsProxyV1Connection
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L7SESSION-MIB_oid_list

Description : proxy_v1_connection
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.22

Field Name : l7sessionStatsServerRstRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_rsp
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.21

Field Name : l7sessionStatsServerRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_connected
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.20

Field Name : l7sessionStatsServerRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.19

Field Name : l7sessionStatsServerRstReq
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst_req
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.18

Field Name : l7sessionStatsClientRstRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_rsp
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.17

Field Name : l7sessionStatsClientRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_connected
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.16

Field Name : l7sessionStatsClientRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_connecting
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.15

Field Name : l7sessionStatsClientRstReq
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst_req
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.14

Field Name : l7sessionStatsServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : server_rst
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.13

ACOS-SLB-L7SESSION-MIB_oid_list

Field Name : l7sessionStatsClientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : client_rst
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.12

Field Name : l7sessionStatsServerConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : server_conn_failed
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.11

Field Name : l7sessionStatsErrCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : err_cb_failed
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.10

Field Name : l7sessionStatsErrEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : err_event
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.9

Field Name : l7sessionStatsWbufCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : wbuf_cb_failed
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.8

Field Name : l7sessionStatsWbufEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : wbuf_event
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.7

Field Name : l7sessionStatsServerFin
Field Type : CounterBasedGauge64
Field Status : current
Description : server_fin
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.6

Field Name : l7sessionStatsClientFin
Field Type : CounterBasedGauge64
Field Status : current
Description : client_fin
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.5

Field Name : l7sessionStatsDataEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : data_event
OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.4

Field Name : l7sessionStatsConnNotExist
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-L7SESSION-MIB_oid_list

Description : conn_not_exist

OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.3

Field Name : l7sessionStatsStartServerConnSucc

Field Type : CounterBasedGauge64

Field Status : current

Description : start_server_conn_succ

OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.2

Field Name : l7sessionStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.329.1.1.1.1

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : utilEnableStatus
Field Type : String
Field Status : current
Description : current module percentage enable Status
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.67

Field Name : fpFailAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex fail
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.66

Field Name : fpFailVerifyCert
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert fetch, validation error
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.65

Field Name : fpFailTcpError
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert fetch, TCP FIN/RST
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.64

Field Name : fpFailHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert fetch, Fatal alert
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.63

Field Name : serverSslUnknownError
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL Unknown Error
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.62

Field Name : serverSslInternalError
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL Internal Error
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.61

Field Name : clientSslUnknownError
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL Unknown Error
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.60

Field Name : clientSslInternalError
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL Internal Error
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.59

Field Name : serverSslFinReset
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : Server SSL, TCP FIN/RST
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.58

Field Name : serverSslFatalAlert
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL, SSL Fatal alert
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.57

Field Name : sslSessionFinReset
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Session, TCP FIN/RST
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.56

Field Name : clientSslFinReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert Fetch, TCP FIN/RST
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.55

Field Name : clientSslFatalAlert
Field Type : CounterBasedGauge64
Field Status : current
Description : Cert Fetch, SSL Fatal Alert
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.54

Field Name : unsupportedSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported SSL Version
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.53

Field Name : revokedOcspResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Revoked OCSP Response
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.52

Field Name : invalidOcspStaplingResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid OCSP Stapling Response
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.51

Field Name : certificateSigningFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in Certificate Signing
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.50

Field Name : certificateVerificationFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in Certificate Verification
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.49

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : tcpFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in TCP
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.48

Field Name : cryptioOperations
Field Type : CounterBasedGauge64
Field Status : current
Description : Crypto operations
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.47

Field Name : sslHandshakeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in SSL handshakes
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.46

Field Name : bypassClientAuthSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Client Auth sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.45

Field Name : dropEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Drop ESNI sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.44

Field Name : bypassEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass ESNI sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.43

Field Name : resetNoSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Reset NO SNI sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.42

Field Name : bypassNoSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass No SNI sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.41

Field Name : bypassCertSanSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Cert SAN sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.40

Field Name : bypassCertIssuerSessions
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : Bypass Cert Issuer sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.39

Field Name : bypassCertSubjectSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Cert Subject sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.38

Field Name : bypassSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass SNI sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.37

Field Name : bypassAdGroupSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass AD-Group sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.36

Field Name : bypassUsernameSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Username sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.35

Field Name : bypassFailsafeSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass failsafe SSL sessions
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.34

Field Name : dynamicSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Dynamic SSL contexts
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.33

Field Name : staticSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Static SSL contexts
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.32

Field Name : currSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : Current SSL contexts in use
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.31

Field Name : maxSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : Maximum SSL contexts
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.30

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : clientsslContextMallocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total client ssl context malloc failures
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.29

Field Name : recordTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : Record too big
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.28

Field Name : hwRingFull
Field Type : CounterBasedGauge64
Field Status : current
Description : HW ring full
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.27

Field Name : hwContextAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Context Memory alloc failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.26

Field Name : hwContextUsage
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Context Memory In Use
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.25

Field Name : hwContextTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Context Memory Total Count
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.24

Field Name : caVerificationFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL fail CA verification
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.23

Field Name : clientCertAuthFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL client certificate authorization failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.22

Field Name : serverCertErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL server certificate errors
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.21

Field Name : sslMemoryUsage
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : SSL memory usage

OID : 1.3.6.1.4.1.22610.2.4.11.108.9.20

Field Name : failedCrypto

Field Type : CounterBasedGauge64

Field Status : current

Description : Failed crypto operations

OID : 1.3.6.1.4.1.22610.2.4.11.108.9.19

Field Name : failedHandshakes

Field Type : CounterBasedGauge64

Field Status : current

Description : Failed SSL handshakes

OID : 1.3.6.1.4.1.22610.2.4.11.108.9.18

Field Name : totalServersideFailedEarlyDataConnections

Field Type : CounterBasedGauge64

Field Status : current

Description : Total serverside failed early data connections

OID : 1.3.6.1.4.1.22610.2.4.11.108.9.17

Field Name : totalClientsideFailedEarlyDataConnections

Field Type : CounterBasedGauge64

Field Status : current

Description : Total clientside failed early data connections

OID : 1.3.6.1.4.1.22610.2.4.11.108.9.16

Field Name : totalServersideEarlyDataConnections

Field Type : CounterBasedGauge64

Field Status : current

Description : Total serverside early data connections

OID : 1.3.6.1.4.1.22610.2.4.11.108.9.15

Field Name : totalClientsideEarlyDataConnections

Field Type : CounterBasedGauge64

Field Status : current

Description : Total clientside early data connections

OID : 1.3.6.1.4.1.22610.2.4.11.108.9.14

Field Name : totalReuseSessionTicketServerSsl

Field Type : CounterBasedGauge64

Field Status : current

Description : Total times of stateless session reuse in server ssl

OID : 1.3.6.1.4.1.22610.2.4.11.108.9.13

Field Name : totalReuseSessionTicketClientSsl

Field Type : CounterBasedGauge64

Field Status : current

Description : Total times of stateless session reuse in client ssl

OID : 1.3.6.1.4.1.22610.2.4.11.108.9.12

Field Name : totalReuseServerSsl

Field Type : CounterBasedGauge64

Field Status : current

Description : Total times of stateful session reuse in server ssl

OID : 1.3.6.1.4.1.22610.2.4.11.108.9.11

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : totalReuseClientSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : Total times of stateful session reuse in client ssl
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.10

Field Name : nonSslBypassConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : NON SSL bypass connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.9

Field Name : totalServersideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total serverside SSL connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.8

Field Name : currentServersideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Current serverside SSL connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.7

Field Name : totalClientsideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total clientside SSL connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.6

Field Name : currentClientsideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Current clientside SSL connections
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.5

Field Name : sslModulesCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SSL modules
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.4

Field Name : thalesHsmStatus
Field Type : String
Field Status : current
Description : Thales HSM Status
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.3

Field Name : configModuleType
Field Type : String
Field Status : current
Description : Config module
OID : 1.3.6.1.4.1.22610.2.4.11.108.9.2

Field Name : sslModuleType
Field Type : String
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : SSL module

OID : 1.3.6.1.4.1.22610.2.4.11.108.9.1

Field Name : badHandshakeLength

Field Type : CounterBasedGauge64

Field Status : current

Description : bad handshake length

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.245

Field Name : unsupportedDigestType

Field Type : CounterBasedGauge64

Field Status : current

Description : unsupported digest type

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.244

Field Name : noRequiredDigest

Field Type : CounterBasedGauge64

Field Status : current

Description : no required digest

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.243

Field Name : unsupportedEllipticCurve

Field Type : CounterBasedGauge64

Field Status : current

Description : unsupported elliptic curve

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.242

Field Name : cookieMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : cookie mismatch

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.241

Field Name : badEcpoint

Field Type : CounterBasedGauge64

Field Status : current

Description : bad ecpoint

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.240

Field Name : badEcdsaSig

Field Type : CounterBasedGauge64

Field Status : current

Description : bad ecdsa sig

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.239

Field Name : badEccCert

Field Type : CounterBasedGauge64

Field Status : current

Description : bad ecc cert

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.238

Field Name : tlsInvalidEcpointformatList

Field Type : CounterBasedGauge64

Field Status : current

Description : tls invalid ecpointformat list

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.237

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : multipleSgcRestarts
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple sgc restarts
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.236

Field Name : ssl3ExtInvalidServernameType
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 ext invalid servername type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.235

Field Name : ssl3ExtInvalidServername
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 ext invalid servername
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.234

Field Name : serverhelloTlsex
Field Type : CounterBasedGauge64
Field Status : current
Description : serverhello tlsex
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.233

Field Name : parseTlsex
Field Type : CounterBasedGauge64
Field Status : current
Description : parse tlsex
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.232

Field Name : clienthelloTlsex
Field Type : CounterBasedGauge64
Field Status : current
Description : clienthello tlsex
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.231

Field Name : x509VerificationSetupProblems
Field Type : CounterBasedGauge64
Field Status : current
Description : x509 verification setup problems
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.230

Field Name : x509Lib
Field Type : CounterBasedGauge64
Field Status : current
Description : x509 lib
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.229

Field Name : wrongVersionNumber
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong version number
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.228

Field Name : wrongSslVersion
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : wrong ssl version
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.227

Field Name : wrongSignatureSize
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong signature size
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.226

Field Name : wrongSignatureLength
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong signature length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.225

Field Name : wrongNumberOfKeyBits
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong number of key bits
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.224

Field Name : wrongMessageType
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong message type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.223

Field Name : wrongCipherReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong cipher returned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.222

Field Name : writeBioNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : write bio not set
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.221

Field Name : unsupportedStatusType
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported status type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.220

Field Name : unsupportedSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported ssl version
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.219

Field Name : unsupportedProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported protocol
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.218

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : unsupportedOption
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported option
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.217

Field Name : unsupportedCompressionAlgorithm
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported compression algorithm
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.216

Field Name : unsupportedCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported cipher
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.215

Field Name : unknownState
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown state
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.214

Field Name : unknownSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown ssl version
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.213

Field Name : unknownRemoteErrorType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown remote error type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.212

Field Name : unknownProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown protocol
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.211

Field Name : unknownPkeyType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown pkey type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.210

Field Name : unknownKeyExchangeType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown key exchange type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.209

Field Name : unknownCipherType
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : unknown cipher type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.208

Field Name : unknownCipherReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown cipher returned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.207

Field Name : unknownCertificateType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown certificate type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.206

Field Name : unknownAlertType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown alert type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.205

Field Name : uninitialized
Field Type : CounterBasedGauge64
Field Status : current
Description : uninitialized
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.204

Field Name : unexpectedRecord
Field Type : CounterBasedGauge64
Field Status : current
Description : unexpected record
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.203

Field Name : unexpectedMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : unexpected message
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.202

Field Name : unableToLoadSsl3Sha1Routines
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to load ssl3 sha1 routines
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.201

Field Name : unableToLoadSsl3Md5Routines
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to load ssl3 md5 routines
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.200

Field Name : unableToLoadSsl2Md5Routines
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to load ssl2 md5 routines
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.199

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : unableToFindSslMethod
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to find ssl method
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.198

Field Name : unableToFindPublicKeyParameters
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to find public key parameters
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.197

Field Name : unableToFindDhParameters
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to find dh parameters
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.196

Field Name : unableToExtractPublicKey
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract public key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.195

Field Name : unableToDecodeDhCerts
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to decode dh certs
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.194

Field Name : triedToUseUnsupportedCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : tried to use unsupported cipher
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.193

Field Name : tlsRsaEncryptedValueLengthIsWrong
Field Type : CounterBasedGauge64
Field Status : current
Description : tls rsa encrypted value length is wrong
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.192

Field Name : tlsPeerDidNotRespondWithCertList
Field Type : CounterBasedGauge64
Field Status : current
Description : tls peer did not respond with cert list
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.191

Field Name : tlsClientCertReqWithAnonCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : tls client cert req with anon cipher
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.190

Field Name : tlsv1AlertUserCancelled
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : tlsv1 alert user cancelled
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.189

Field Name : tlsv1AlertUnknownCa
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert unknown ca
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.188

Field Name : tlsv1AlertRecordOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert record overflow
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.187

Field Name : tlsv1AlertProtocolVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert protocol version
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.186

Field Name : tlsv1AlertNoRenegotiation
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert no renegotiation
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.185

Field Name : tlsv1AlertInternalError
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert internal error
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.184

Field Name : tlsv1AlertInsufficientSecurity
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert insufficient security
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.183

Field Name : tlsv1AlertExportRestriction
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert export restriction
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.182

Field Name : tlsv1AlertDecryptError
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert decrypt error
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.181

Field Name : tlsv1AlertDecryptionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert decryption failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.180

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : tlsv1AlertDecodeError
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert decode error
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.179

Field Name : tlsv1AlertAccessDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert access denied
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.178

Field Name : sslSessionIdIsDifferent
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id is different
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.177

Field Name : sslSessionIdHasBadLength
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id has bad length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.176

Field Name : sslSessionIdContextTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id context too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.175

Field Name : sslSessionIdConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id conflict
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.174

Field Name : sslSessionIdCallbackFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id callback failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.173

Field Name : sslLibraryHasNoCiphers
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl library has no ciphers
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.172

Field Name : sslHandshakeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl handshake failure
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.171

Field Name : sslCtxHasNoDefaultSslVersion
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : ssl ctx has no default ssl version
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.170

Field Name : sslv3AlertUnspportedCert
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert unspported cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.169

Field Name : sslv3AlertUnknownRemoteErrType
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert unknown remote err type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.168

Field Name : sslv3AlertUnexpectedMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert unexpected msg
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.167

Field Name : sslv3AlertPeerErrorUnsuppCertType
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error unsupp cert type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.166

Field Name : sslv3AlertPeerErrorNoCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error no cipher
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.165

Field Name : sslv3AlertPeerErrorNoCert
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error no cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.164

Field Name : sslv3AlertPeerErrorCert
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.163

Field Name : sslv3AlertNoCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert no certificate
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.162

Field Name : sslv3AlertIllegalParameter
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert illegal parameter
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.161

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : sslv3AlertHandshakeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert handshake failure
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.160

Field Name : sslv3AlertDecompressionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert decompression failure
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.159

Field Name : sslv3AlertCertificateUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert certificate unknown
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.158

Field Name : sslv3AlertCertificateRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert certificate revoked
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.157

Field Name : sslv3AlertCertificateExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert certificate expired
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.156

Field Name : sslv3AlertBadRecordMac
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert bad record mac
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.155

Field Name : sslv3AlertBadCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert bad certificate
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.154

Field Name : ssl3SessionIdTooShort
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 session id too short
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.153

Field Name : ssl3SessionIdTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 session id too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.152

Field Name : ssl2ConnectionIdTooLong
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : ssl2 connection id too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.151

Field Name : ssl23DoingSessionIdReuse
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl23 doing session id reuse
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.150

Field Name : signatureForNonSigningCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : signature for non signing certificate
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.149

Field Name : shortRead
Field Type : CounterBasedGauge64
Field Status : current
Description : short read
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.148

Field Name : sessionIdContextUninitialized
Field Type : CounterBasedGauge64
Field Status : current
Description : session id context uninitialized
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.147

Field Name : scsvReceivedWhenRenegotiating
Field Type : CounterBasedGauge64
Field Status : current
Description : scsv received when renegotiating
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.146

Field Name : reuseCipherListNotZero
Field Type : CounterBasedGauge64
Field Status : current
Description : reuse cipher list not zero
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.145

Field Name : reuseCertTypeNotZero
Field Type : CounterBasedGauge64
Field Status : current
Description : reuse cert type not zero
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.144

Field Name : reuseCertLengthNotZero
Field Type : CounterBasedGauge64
Field Status : current
Description : reuse cert length not zero
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.143

Field Name : requiredCipherMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : required cipher missing
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.142

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : recordTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : record too small
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.141

Field Name : recordTooLarge
Field Type : CounterBasedGauge64
Field Status : current
Description : record too large
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.140

Field Name : recordLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : record length mismatch
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.139

Field Name : readWrongPacketType
Field Type : CounterBasedGauge64
Field Status : current
Description : read wrong packet type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.138

Field Name : readBioNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : read bio not set
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.137

Field Name : publicKeyNotRsa
Field Type : CounterBasedGauge64
Field Status : current
Description : public key not rsa
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.136

Field Name : publicKeyIsNotRsa
Field Type : CounterBasedGauge64
Field Status : current
Description : public key is not rsa
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.135

Field Name : publicKeyEncryptError
Field Type : CounterBasedGauge64
Field Status : current
Description : public key encrypt error
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.134

Field Name : protocolIsShutdown
Field Type : CounterBasedGauge64
Field Status : current
Description : protocol is shutdown
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.133

Field Name : problemsMappingCipherFunctions
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : problems mapping cipher functions

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.132

Field Name : preMacLengthTooLong

Field Type : CounterBasedGauge64

Field Status : current

Description : pre mac length too long

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.131

Field Name : peerErrorUnsupportedCertificateType

Field Type : CounterBasedGauge64

Field Status : current

Description : peer error unsupported certificate type

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.130

Field Name : peerErrorNoCipher

Field Type : CounterBasedGauge64

Field Status : current

Description : peer error no cipher

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.129

Field Name : peerErrorNoCertificate

Field Type : CounterBasedGauge64

Field Status : current

Description : peer error no certificate

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.128

Field Name : peerErrorCertificate

Field Type : CounterBasedGauge64

Field Status : current

Description : peer error certificate

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.127

Field Name : peerError

Field Type : CounterBasedGauge64

Field Status : current

Description : peer error

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.126

Field Name : peerDidNotReturnACertificate

Field Type : CounterBasedGauge64

Field Status : current

Description : peer did not return a certificate

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.125

Field Name : pathTooLong

Field Type : CounterBasedGauge64

Field Status : current

Description : path too long

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.124

Field Name : packetLengthTooLong

Field Type : CounterBasedGauge64

Field Status : current

Description : packet length too long

OID : 1.3.6.1.4.1.22610.2.4.11.108.62.123

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : oldSessionCipherNotReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : old session cipher not returned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.122

Field Name : nullSslMethodPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : null ssl method passed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.121

Field Name : nullSslCtx
Field Type : CounterBasedGauge64
Field Status : current
Description : null ssl ctx
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.120

Field Name : noVerifyCallback
Field Type : CounterBasedGauge64
Field Status : current
Description : no verify callback
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.119

Field Name : noSharedCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : no shared cipher
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.118

Field Name : noPublickey
Field Type : CounterBasedGauge64
Field Status : current
Description : no publickey
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.117

Field Name : noProtocolsAvailable
Field Type : CounterBasedGauge64
Field Status : current
Description : no protocols available
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.116

Field Name : noPrivateKeyAssigned
Field Type : CounterBasedGauge64
Field Status : current
Description : no private key assigned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.115

Field Name : noPrivatekey
Field Type : CounterBasedGauge64
Field Status : current
Description : no privatekey
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.114

Field Name : noMethodSpecified
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : no method specified
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.113

Field Name : noCompressionSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no compression specified
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.112

Field Name : noClientCertReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : no client cert received
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.111

Field Name : noCipherMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : no cipher match
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.110

Field Name : noCipherList
Field Type : CounterBasedGauge64
Field Status : current
Description : no cipher list
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.109

Field Name : noCiphersSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no ciphers specified
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.108

Field Name : noCiphersPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : no ciphers passed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.107

Field Name : noCiphersAvailable
Field Type : CounterBasedGauge64
Field Status : current
Description : no ciphers available
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.106

Field Name : noCertificateSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate specified
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.105

Field Name : noCertificateSet
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate set
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.104

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : noCertificateReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate returned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.103

Field Name : noCertificateAssigned
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate assigned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.102

Field Name : noCertificatesReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificates returned
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.101

Field Name : nonSslv2InitialPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : non sslv2 initial packet
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.100

Field Name : missingVerifyMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : missing verify message
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.99

Field Name : missingTmpRsaPkey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing tmp rsa pkey
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.98

Field Name : missingTmpRsaKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing tmp rsa key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.97

Field Name : missingTmpDhKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing tmp dh key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.96

Field Name : missingRsaSigningCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing rsa signing cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.95

Field Name : missingRsaEncryptingCert
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : missing rsa encrypting cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.94

Field Name : missingRsaCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : missing rsa certificate
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.93

Field Name : missingExportTmpRsaKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing export tmp rsa key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.92

Field Name : missingExportTmpDhKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing export tmp dh key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.91

Field Name : missingDsaSigningCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dsa signing cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.90

Field Name : missingDhRsaCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dh rsa cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.89

Field Name : missingDhKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dh key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.88

Field Name : missingDhDsaCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dh dsa cert
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.87

Field Name : messageTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : message too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.86

Field Name : mastKeyTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : mast key too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.85

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : libraryHasNoCiphers
Field Type : CounterBasedGauge64
Field Status : current
Description : library has no ciphers
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.84

Field Name : libraryBug
Field Type : CounterBasedGauge64
Field Status : current
Description : library bug
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.83

Field Name : lengthTooShort
Field Type : CounterBasedGauge64
Field Status : current
Description : length too short
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.82

Field Name : lengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : length mismatch
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.81

Field Name : krb5ServerTktSkew
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server tkt skew
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.80

Field Name : krb5ServerTktNotYetValid
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server tkt not yet valid
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.79

Field Name : krb5ServerTktExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server tkt expired
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.78

Field Name : krb5ServerRdReq
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server rd_req
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.77

Field Name : krb5ServerInit
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server init
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.76

Field Name : krb5ServerBadTicket
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : krb5 server bad ticket
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.75

Field Name : krb5ClientMkReq
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client mk_req
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.74

Field Name : krb5ClientInit
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client init
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.73

Field Name : krb5ClientGetCred
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client get cred
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.72

Field Name : krb5ClientCcPrincipal
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client cc principal
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.71

Field Name : krb5
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.70

Field Name : keyArgTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : key arg too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.69

Field Name : invalidTrust
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid trust
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.68

Field Name : invalidStatusResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid status response
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.67

Field Name : invalidPurpose
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid purpose
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.66

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : invalidCommand
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid command
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.65

Field Name : invalidChallengeLength
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid challenge length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.64

Field Name : inappropriateFallback
Field Type : CounterBasedGauge64
Field Status : current
Description : inappropriate fallback
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.63

Field Name : illegalPadding
Field Type : CounterBasedGauge64
Field Status : current
Description : illegal padding
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.62

Field Name : httpRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : http request
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.61

Field Name : httpsProxyRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : https proxy request
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.60

Field Name : gotAFinBeforeACcs
Field Type : CounterBasedGauge64
Field Status : current
Description : got a fin before a ccs
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.59

Field Name : extraDataInMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : extra data in message
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.58

Field Name : excessiveMessageSize
Field Type : CounterBasedGauge64
Field Status : current
Description : excessive message size
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.57

Field Name : errorInReceivedCipherList
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : error in received cipher list
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.56

Field Name : errorGeneratingTmpRsaKey
Field Type : CounterBasedGauge64
Field Status : current
Description : error generating tmp rsa key
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.55

Field Name : encryptedLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : encrypted length too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.54

Field Name : digestCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : digest check failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.53

Field Name : dhPublicValueLengthIsWrong
Field Type : CounterBasedGauge64
Field Status : current
Description : dh public value length is wrong
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.52

Field Name : decryptionFailedOrBadRecordMac
Field Type : CounterBasedGauge64
Field Status : current
Description : decryption failed or bad record mac
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.51

Field Name : decryptionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : decryption failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.50

Field Name : dataLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : data length too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.49

Field Name : dataBetweenCcsAndFinished
Field Type : CounterBasedGauge64
Field Status : current
Description : data between ccs and finished
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.48

Field Name : connectionTypeNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : connection type not set
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.47

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : connectionIdIsDifferent
Field Type : CounterBasedGauge64
Field Status : current
Description : connection id is different
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.46

Field Name : compressionLibraryError
Field Type : CounterBasedGauge64
Field Status : current
Description : compression library error
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.45

Field Name : compressionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : compression failure
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.44

Field Name : compressedLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : compressed length too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.43

Field Name : cipherTableSrcError
Field Type : TABLE
Field Status : current
Description : cipher table src error
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.42

Field Name : cipherOrHashUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : cipher or hash unavailable
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.41

Field Name : cipherCodeWrongLength
Field Type : CounterBasedGauge64
Field Status : current
Description : cipher code wrong length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.40

Field Name : challengeIsDifferent
Field Type : CounterBasedGauge64
Field Status : current
Description : challenge is different
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.39

Field Name : certLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : cert length mismatch
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.38

Field Name : certificateVerifyFailed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : certificate verify failed
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.37

Field Name : ccsReceivedEarly
Field Type : CounterBasedGauge64
Field Status : current
Description : ccs received early
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.36

Field Name : caDnTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : ca dn too long
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.35

Field Name : caDnLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : ca dn length mismatch
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.34

Field Name : bnLib
Field Type : CounterBasedGauge64
Field Status : current
Description : bn lib
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.33

Field Name : blockCipherPadIsWrong
Field Type : CounterBasedGauge64
Field Status : current
Description : block cipher pad is wrong
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.32

Field Name : bioNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : bio not set
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.31

Field Name : badWriteRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : bad write retry
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.30

Field Name : badState
Field Type : CounterBasedGauge64
Field Status : current
Description : bad state
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.29

Field Name : badSslSessionIdLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ssl session id length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.28

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : badSslFiletype
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ssl filetype
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.27

Field Name : badSignature
Field Type : CounterBasedGauge64
Field Status : current
Description : bad signature
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.26

Field Name : badRsaSignature
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa signature
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.25

Field Name : badRsaModulusLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa modulus length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.24

Field Name : badRsaELength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa e length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.23

Field Name : badRsaEncrypt
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa encrypt
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.22

Field Name : badRsaDecrypt
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa decrypt
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.21

Field Name : badResponseArgument
Field Type : CounterBasedGauge64
Field Status : current
Description : bad response argument
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.20

Field Name : badProtocolVersionNumber
Field Type : CounterBasedGauge64
Field Status : current
Description : bad protocol version number
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.19

Field Name : badPacketLength
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Description : bad packet length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.18

Field Name : badMessageType
Field Type : CounterBasedGauge64
Field Status : current
Description : bad message type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.17

Field Name : badMacDecode
Field Type : CounterBasedGauge64
Field Status : current
Description : bad mac decode
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.16

Field Name : badLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.15

Field Name : badHelloRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : bad hello request
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.14

Field Name : badDsaSignature
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dsa signature
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.13

Field Name : badDigestLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad digest length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.12

Field Name : badDhPLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dh p length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.11

Field Name : badDhPubKeyLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dh pub key length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.10

Field Name : badDhGLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dh g length
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.9

ACOS-SLB-OPER-MIB_acosSlb_oid_list

Field Name : badDecompression
Field Type : CounterBasedGauge64
Field Status : current
Description : bad decompression
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.8

Field Name : badDataReturnedByCallback
Field Type : CounterBasedGauge64
Field Status : current
Description : bad data returned by callback
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.7

Field Name : badChecksum
Field Type : CounterBasedGauge64
Field Status : current
Description : bad checksum
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.6

Field Name : badChangeCipherSpec
Field Type : CounterBasedGauge64
Field Status : current
Description : bad change cipher spec
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.5

Field Name : badAuthenticationType
Field Type : CounterBasedGauge64
Field Status : current
Description : bad authentication type
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.4

Field Name : badAlertRecord
Field Type : CounterBasedGauge64
Field Status : current
Description : bad alert record
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.3

Field Name : attemptToReuseSessInDiffContext
Field Type : CounterBasedGauge64
Field Status : current
Description : attempt to reuse sess in diff context
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.2

Field Name : appDataInHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : app data in handshake
OID : 1.3.6.1.4.1.22610.2.4.11.108.62.1

ACOS-SLB-SERVER-MIB_oid_list

Field Name : portOperDrsIpNatListNatPoolAddrListTable
Field Type : TABLE
Field Status : current
Description : RealServerPort from object 'slb.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8

Field Name : portOperDrsIpNatListTable
Field Type : TABLE
Field Status : current
Description : RealServerPort from object 'slb.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7

Field Name : portOperDrsIpNatListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsIpNatList entry:drs-ip-nat-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1

Field Name : portOperDrsIpNatListPoolName
Field Type : String
Field Status : current
Description : pool_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.8

Field Name : portOperDrsIpNatListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs_port
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.7

Field Name : portOperDrsIpNatListDrsName
Field Type : String
Field Status : current
Description : drs_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.6

Field Name : portOperDrsIpNatListDrsIpNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.5

Field Name : portOperDrsIpNatListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.4

Field Name : portOperDrsIpNatListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.3

Field Name : portOperDrsIpNatListName
Field Type : String
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.2

Field Name : portOperDrsIpNatListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.7.1.1

Field Name : portOperNatPoolAddrListTable

Field Type : TABLE

Field Status : current

Description : RealServerPort from object 'slb.server.port'

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6

Field Name : portOperNatPoolAddrListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The portOperNatPoolAddrList entry:nat-pool-addr-list

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1

Field Name : portOperNatPoolAddrListAllocFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : alloc_failed

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.10

Field Name : portOperNatPoolAddrListPortsFreedTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_freed_total

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.9

Field Name : portOperNatPoolAddrListPortsConsumedTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_consumed_total

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.8

Field Name : portOperNatPoolAddrListPortsConsumed

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_consumed

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.7

Field Name : portOperNatPoolAddrListNatIp

Field Type : String

Field Status : current

Description : nat_ip

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.6

Field Name : portOperNatPoolAddrListNatPoolAddrListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.5

ACOS-SLB-SERVER-MIB_oid_list

Field Name : portOperNatPoolAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.4

Field Name : portOperNatPoolAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.3

Field Name : portOperNatPoolAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.2

Field Name : portOperNatPoolAddrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.6.1.1

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListTable
Field Type : TABLE
Field Status : current
Description : RealServerPort from object 'slb.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsAutoNatListDrsAutoNatAddressList entry:drs-auto-nat-address-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.14

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.13

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.12

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : ports_consumed

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.11

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListIpRr

Field Type : CounterBasedGauge64

Field Status : current

Description : ip_rr

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.10

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListHaGroupId

Field Type : CounterBasedGauge64

Field Status : current

Description : ha_group_id

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.9

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListVrid

Field Type : CounterBasedGauge64

Field Status : current

Description : vrid

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.8

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListAutoNatIp

Field Type : String

Field Status : current

Description : auto_nat_ip

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.7

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListDrsAutoNatAddressListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.6

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListDrsAutoNatListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.5

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListProtocol

Field Type : String

Field Status : current

Description : protocol

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.4

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListPort

Field Type : Integer32

Field Status : current

Description : port-number

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.3

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.2

ACOS-SLB-SERVER-MIB_oid_list

Field Name : portOperDrsAutoNatListDrsAutoNatAddressListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.5.1.1

Field Name : portOperDrsAutoNatListTable
Field Type : TABLE
Field Status : current
Description : RealServerPort from object 'slb.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4

Field Name : portOperDrsAutoNatListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperDrsAutoNatList entry:drs-auto-nat-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1

Field Name : portOperDrsAutoNatListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs_port
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.7

Field Name : portOperDrsAutoNatListDrsName
Field Type : String
Field Status : current
Description : drs_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.6

Field Name : portOperDrsAutoNatListDrsAutoNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.5

Field Name : portOperDrsAutoNatListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.4

Field Name : portOperDrsAutoNatListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.3

Field Name : portOperDrsAutoNatListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.2

Field Name : portOperDrsAutoNatListSlotId
Field Type : Integer32
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.4.1.1

Field Name : portOperAutoNatAddrListTable

Field Type : TABLE

Field Status : current

Description : RealServerPort from object 'slb.server.port'

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3

Field Name : portOperAutoNatAddrListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The portOperAutoNatAddrList entry:auto-nat-addr-list

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1

Field Name : portOperAutoNatAddrListAllocFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : alloc_failed

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.13

Field Name : portOperAutoNatAddrListPortsFreedTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_freed_total

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.12

Field Name : portOperAutoNatAddrListPortsConsumedTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_consumed_total

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.11

Field Name : portOperAutoNatAddrListPortsConsumed

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_consumed

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.10

Field Name : portOperAutoNatAddrListIpRr

Field Type : CounterBasedGauge64

Field Status : current

Description : ip_rr

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.9

Field Name : portOperAutoNatAddrListHaGroupId

Field Type : CounterBasedGauge64

Field Status : current

Description : ha_group_id

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.8

Field Name : portOperAutoNatAddrListVrid

Field Type : CounterBasedGauge64

Field Status : current

Description : vrid

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.7

ACOS-SLB-SERVER-MIB_oid_list

Field Name : portOperAutoNatAddrListAutoNatIp
Field Type : String
Field Status : current
Description : auto_nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.6

Field Name : portOperAutoNatAddrListAutoNatAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.5

Field Name : portOperAutoNatAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.4

Field Name : portOperAutoNatAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.3

Field Name : portOperAutoNatAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.2

Field Name : portOperAutoNatAddrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.3.1.1

Field Name : portOperTable
Field Type : TABLE
Field Status : current
Description : RealServerPort from object 'slb.server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2

Field Name : portOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1

Field Name : portOperPoolName
Field Type : String
Field Status : current
Description : pool_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.23

Field Name : portOperResvConn
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : resv_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.22

Field Name : portOperAflowQueueSize
Field Type : CounterBasedGauge64
Field Status : current
Description : aflow_queue_size
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.21

Field Name : portOperAflowConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : aflow_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.20

Field Name : portOperSoftDownTime
Field Type : CounterBasedGauge64
Field Status : current
Description : soft_down_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.19

Field Name : portOperHmIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-index
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.18

Field Name : portOperHmKey
Field Type : CounterBasedGauge64
Field Status : current
Description : hm-key
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.17

Field Name : portOperDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : disable
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.16

Field Name : portOperInbandHmReassignNum
Field Type : CounterBasedGauge64
Field Status : current
Description : inband_hm_reassign_num
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.15

Field Name : portOperEsRespTime
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.14

Field Name : portOperDiameterEnabled
Field Type : CounterBasedGauge64
Field Status : current
Description : diameter_enabled
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.13

ACOS-SLB-SERVER-MIB_oid_list

Field Name : portOperDownTimeGracePeriod
Field Type : CounterBasedGauge64
Field Status : current
Description : down_time_grace_period
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.12

Field Name : portOperCurrentTime
Field Type : CounterBasedGauge64
Field Status : current
Description : current_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.11

Field Name : portOperDownGracePeriodAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : down_grace_period_allowed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.10

Field Name : portOperCurrObserveRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_observe_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.9

Field Name : portOperSlowStartConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : slow_start_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.8

Field Name : portOperConnRateUnit
Field Type : String
Field Status : current
Description : conn_rate_unit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.7

Field Name : portOperCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.6

Field Name : portOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.5

Field Name : portOperProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.4

Field Name : portOperPort
Field Type : Integer32
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : port-number

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.3

Field Name : portOperName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.2

Field Name : portOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.2.1.1

Field Name : portStatsTable

Field Type : TABLE

Field Status : current

Description : RealServerPort from object 'slb.server.port'

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1

Field Name : portStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The portStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1

Field Name : portStatsCurrPconn

Field Type : CounterBasedGauge64

Field Status : current

Description : curr_pconn

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.39

Field Name : portStatsRespLatency

Field Type : CounterBasedGauge64

Field Status : current

Description : resp-latency

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.38

Field Name : portStatsRespOther

Field Type : CounterBasedGauge64

Field Status : current

Description : resp-other

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.37

Field Name : portStatsResp5xx

Field Type : CounterBasedGauge64

Field Status : current

Description : resp-5xx

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.36

Field Name : portStatsResp4xx

Field Type : CounterBasedGauge64

Field Status : current

Description : resp-4xx

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.35

ACOS-SLB-SERVER-MIB_oid_list

Field Name : portStatsResp3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-3xx
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.34

Field Name : portStatsResp2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-2xx
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.33

Field Name : portStatsResp1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-1xx
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.32

Field Name : portStatsRespCount
Field Type : CounterBasedGauge64
Field Status : current
Description : resp-count
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.31

Field Name : portStatsTotalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.30

Field Name : portStatsCurrSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.29

Field Name : portStatsSlowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : slowest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.28

Field Name : portStatsFastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : fastest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.27

Field Name : portStatsResponseTime
Field Type : CounterBasedGauge64
Field Status : current
Description : response_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.26

Field Name : portStatsTotalRevPktsInspectedGoodStatusCode
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : total_rev_pkts_inspected_good_status_code
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.25

Field Name : portStatsTotalRevPktsInspected
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_inspected
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.24

Field Name : portStatsEsRespInvalidHttp
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_invalid_http
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.23

Field Name : portStatsEsRespCount
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_count
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.22

Field Name : portStatsEsReqCount
Field Type : CounterBasedGauge64
Field Status : current
Description : es_req_count
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.21

Field Name : portStatsEsRespOther
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_other
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.20

Field Name : portStatsEsResp500
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_500
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.19

Field Name : portStatsEsResp400
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_400
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.18

Field Name : portStatsEsResp300
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_300
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.17

Field Name : portStatsEsResp200
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_200
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.16

ACOS-SLB-SERVER-MIB_oid_list

Field Name : portStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.15

Field Name : portStatsLastTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : last_total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.14

Field Name : portStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.13

Field Name : portStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.12

Field Name : portStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.11

Field Name : portStatsTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.10

Field Name : portStatsTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.9

Field Name : portStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req_succ
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.8

Field Name : portStatsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : total_req
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.7

Field Name : portStatsCurrReq
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : curr_req

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.6

Field Name : portStatsCurrConn

Field Type : CounterBasedGauge64

Field Status : current

Description : curr_conn

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.5

Field Name : portStatsProtocol

Field Type : String

Field Status : current

Description : protocol

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.4

Field Name : portStatsPort

Field Type : Integer32

Field Status : current

Description : port-number

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.3

Field Name : portStatsName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.2

Field Name : portStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.1.1.1

Field Name : portOperDrsIpNatListNatPoolAddrListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The portOperDrsIpNatListNatPoolAddrList entry:nat-pool-addr-list

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1

Field Name : portOperDrsIpNatListNatPoolAddrListAllocFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : alloc_failed

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.11

Field Name : portOperDrsIpNatListNatPoolAddrListPortsFreedTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_freed_total

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.10

Field Name : portOperDrsIpNatListNatPoolAddrListPortsConsumedTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_consumed_total

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.9

ACOS-SLB-SERVER-MIB_oid_list

Field Name : portOperDrsIpNatListNatPoolAddrListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.8

Field Name : portOperDrsIpNatListNatPoolAddrListNatIp
Field Type : String
Field Status : current
Description : nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.7

Field Name : portOperDrsIpNatListNatPoolAddrListNatPoolAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.6

Field Name : portOperDrsIpNatListNatPoolAddrListDrsIpNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.5

Field Name : portOperDrsIpNatListNatPoolAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.4

Field Name : portOperDrsIpNatListNatPoolAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.3

Field Name : portOperDrsIpNatListNatPoolAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.2

Field Name : portOperDrsIpNatListNatPoolAddrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.4.8.1.1

Field Name : serverOperDrsListTable
Field Type : TABLE
Field Status : current
Description : Server from object 'slb.server'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3

Field Name : serverOperDrsListEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : The serverOperDrsList entry:drs-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1

Field Name : serverOperDrsListDrsWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-weight
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.28

Field Name : serverOperDrsListDrsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.27

Field Name : serverOperDrsListDrsTotRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-rev-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.26

Field Name : serverOperDrsListDrsTotRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-rev-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.25

Field Name : serverOperDrsListDrsTotFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-fwd-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.24

Field Name : serverOperDrsListDrsTotFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-fwd-bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.23

Field Name : serverOperDrsListDrsTotReqSuc
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-req-suc
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.22

Field Name : serverOperDrsListDrsTotReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-req
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.21

Field Name : serverOperDrsListDrsTotConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-tot-conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.20

ACOS-SLB-SERVER-MIB_oid_list

Field Name : serverOperDrsListDrsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-req
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.19

Field Name : serverOperDrsListDrsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.18

Field Name : serverOperDrsListDrsDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-disable
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.17

Field Name : serverOperDrsListDrsCurrObserveRate
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr_observe_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.16

Field Name : serverOperDrsListDrsConnRateUnit
Field Type : String
Field Status : current
Description : drs-conn_rate_unit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.15

Field Name : serverOperDrsListDrsCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr_conn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.14

Field Name : serverOperDrsListDrsSlowStartConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-slow_start_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.13

Field Name : serverOperDrsListDrsIsAutocreate
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-is_autocreate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.12

Field Name : serverOperDrsListDrsSrvGatewayArp
Field Type : String
Field Status : current
Description : drs-srv_gateway_arp
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.11

Field Name : serverOperDrsListDrsServerTtl
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : drs-server_ttl

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.10

Field Name : serverOperDrsListDrsDnsUpdateTime

Field Type : String

Field Status : current

Description : drs-dns_update_time

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.9

Field Name : serverOperDrsListDrsCreationType

Field Type : String

Field Status : current

Description : drs-creation_type

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.8

Field Name : serverOperDrsListDrsState

Field Type : String

Field Status : current

Description : drs-state

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.7

Field Name : serverOperDrsListDrsServerIpv6Addr

Field Type : String

Field Status : current

Description : drs-server-ipv6-addr

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.6

Field Name : serverOperDrsListDrsHost

Field Type : String

Field Status : current

Description : drs-host

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.5

Field Name : serverOperDrsListDrsName

Field Type : String

Field Status : current

Description : drs-name

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.4

Field Name : serverOperDrsListDrsListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.3

Field Name : serverOperDrsListName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.2

Field Name : serverOperDrsListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.3.1.1

ACOS-SLB-SERVER-MIB_oid_list

Field Name : serverOperTable
Field Type : TABLE
Field Status : current
Description : Server from object 'slb.server'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2

Field Name : serverOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serverOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1

Field Name : serverOperWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : weight
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.14

Field Name : serverOperDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : disable
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.13

Field Name : serverOperCurrObserveRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_observe_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.12

Field Name : serverOperConnRateUnit
Field Type : String
Field Status : current
Description : conn_rate_unit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.11

Field Name : serverOperCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.10

Field Name : serverOperSlowStartConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : slow_start_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.9

Field Name : serverOperIsAutocreate
Field Type : CounterBasedGauge64
Field Status : current
Description : is_autocreate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.8

Field Name : serverOperSrvGatewayArp
Field Type : String
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : srv_gateway_arp
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.7

Field Name : serverOperServerTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : server_ttl
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.6

Field Name : serverOperDnsUpdateTime
Field Type : String
Field Status : current
Description : dns_update_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.5

Field Name : serverOperCreationType
Field Type : String
Field Status : current
Description : creation_type
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.4

Field Name : serverOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.3

Field Name : serverOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.2

Field Name : serverOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.2.1.1

Field Name : serverStatsTable
Field Type : TABLE
Field Status : current
Description : Server from object 'slb.server'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1

Field Name : serverStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serverStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1

Field Name : serverStatsIpOnlyLbRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.19

ACOS-SLB-SERVER-MIB_oid_list

Field Name : serverStatsIpOnlyLbFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.18

Field Name : serverStatsIpOnlyLbRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.17

Field Name : serverStatsIpOnlyLbFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.16

Field Name : serverStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.15

Field Name : serverStatsTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.14

Field Name : serverStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.13

Field Name : serverStatsTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.12

Field Name : serverStatsTotalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.11

Field Name : serverStatsCurrSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.10

Field Name : serverStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : total_req_succ

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.9

Field Name : serverStatsTotalReq

Field Type : CounterBasedGauge64

Field Status : current

Description : total_req

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.8

Field Name : serverStatsPeakConn

Field Type : CounterBasedGauge64

Field Status : current

Description : peak-conn

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.7

Field Name : serverStatsRevPkt

Field Type : CounterBasedGauge64

Field Status : current

Description : rev-pkt

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.6

Field Name : serverStatsFwdPkt

Field Type : CounterBasedGauge64

Field Status : current

Description : fwd-pkt

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.5

Field Name : serverStatsTotalConn

Field Type : CounterBasedGauge64

Field Status : current

Description : total-conn

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.4

Field Name : serverStatsCurrConn

Field Type : CounterBasedGauge64

Field Status : current

Description : curr-conn

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.3

Field Name : serverStatsName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.2

Field Name : serverStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.1.1.1

Field Name : serviceOperDrsIpNatListNatPoolAddrListTable

Field Type : TABLE

Field Status : current

Description : RealServerService from object 'slb.server.service'

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8

ACOS-SLB-SERVER-MIB_oid_list

Field Name : serviceOperDrsIpNatListTable
Field Type : TABLE
Field Status : current
Description : RealServerService from object 'slb.server.service'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.7

Field Name : serviceOperDrsIpNatListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperDrsIpNatList entry:drs-ip-nat-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.7.1

Field Name : serviceOperDrsIpNatListPoolName
Field Type : String
Field Status : current
Description : pool_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.7.1.9

Field Name : serviceOperDrsIpNatListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs_port
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.7.1.8

Field Name : serviceOperDrsIpNatListDrsName
Field Type : String
Field Status : current
Description : drs_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.7.1.7

Field Name : serviceOperDrsIpNatListDrsIpNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.7.1.6

Field Name : serviceOperDrsIpNatListLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.7.1.5

Field Name : serviceOperDrsIpNatListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.7.1.4

Field Name : serviceOperDrsIpNatListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.7.1.3

Field Name : serviceOperDrsIpNatListName
Field Type : String
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.7.1.2

Field Name : serviceOperDrsIpNatListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.7.1.1

Field Name : serviceOperNatPoolAddrListTable

Field Type : TABLE

Field Status : current

Description : RealServerService from object 'slb.server.service'

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.6

Field Name : serviceOperNatPoolAddrListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The serviceOperNatPoolAddrList entry:nat-pool-addr-list

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.6.1

Field Name : serviceOperNatPoolAddrListAllocFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : alloc_failed

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.6.1.11

Field Name : serviceOperNatPoolAddrListPortsFreedTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_freed_total

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.6.1.10

Field Name : serviceOperNatPoolAddrListPortsConsumedTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_consumed_total

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.6.1.9

Field Name : serviceOperNatPoolAddrListPortsConsumed

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_consumed

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.6.1.8

Field Name : serviceOperNatPoolAddrListNatIp

Field Type : String

Field Status : current

Description : nat_ip

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.6.1.7

Field Name : serviceOperNatPoolAddrListNatPoolAddrListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.6.1.6

ACOS-SLB-SERVER-MIB_oid_list

Field Name : serviceOperNatPoolAddrListLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.6.1.5

Field Name : serviceOperNatPoolAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.6.1.4

Field Name : serviceOperNatPoolAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.6.1.3

Field Name : serviceOperNatPoolAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.6.1.2

Field Name : serviceOperNatPoolAddrListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.6.1.1

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListTable
Field Type : TABLE
Field Status : current
Description : RealServerService from object 'slb.server.service'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperDrsAutoNatListDrsAutoNatAddressList entry:drs-auto-nat-address-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : alloc_failed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.15

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.14

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : ports_consumed_total

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.13

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListPortsConsumed

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_consumed

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.12

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListIpRr

Field Type : CounterBasedGauge64

Field Status : current

Description : ip_rr

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.11

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListHaGroupId

Field Type : CounterBasedGauge64

Field Status : current

Description : ha_group_id

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.10

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListVrid

Field Type : CounterBasedGauge64

Field Status : current

Description : vrid

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.9

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListAutoNatIp

Field Type : String

Field Status : current

Description : auto_nat_ip

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.8

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListDrsAutoNatAddressListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.7

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListDrsAutoNatListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.6

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListLabel

Field Type : String

Field Status : current

Description : label

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.5

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListProtocol

Field Type : String

Field Status : current

Description : protocol

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.4

ACOS-SLB-SERVER-MIB_oid_list

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.3

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.2

Field Name : serviceOperDrsAutoNatListDrsAutoNatAddressListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.5.1.1

Field Name : serviceOperDrsAutoNatListTable
Field Type : TABLE
Field Status : current
Description : RealServerService from object 'slb.server.service'
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.4

Field Name : serviceOperDrsAutoNatListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceOperDrsAutoNatList entry:drs-auto-nat-list
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.4.1

Field Name : serviceOperDrsAutoNatListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs_port
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.4.1.8

Field Name : serviceOperDrsAutoNatListDrsName
Field Type : String
Field Status : current
Description : drs_name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.4.1.7

Field Name : serviceOperDrsAutoNatListDrsAutoNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.4.1.6

Field Name : serviceOperDrsAutoNatListLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.4.1.5

Field Name : serviceOperDrsAutoNatListProtocol
Field Type : String
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : protocol

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.4.1.4

Field Name : serviceOperDrsAutoNatListPort

Field Type : Integer32

Field Status : current

Description : port-number

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.4.1.3

Field Name : serviceOperDrsAutoNatListName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.4.1.2

Field Name : serviceOperDrsAutoNatListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.4.1.1

Field Name : serviceOperAutoNatAddrListTable

Field Type : TABLE

Field Status : current

Description : RealServerService from object 'slb.server.service'

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3

Field Name : serviceOperAutoNatAddrListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The serviceOperAutoNatAddrList entry:auto-nat-addr-list

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1

Field Name : serviceOperAutoNatAddrListAllocFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : alloc_failed

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.14

Field Name : serviceOperAutoNatAddrListPortsFreedTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_freed_total

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.13

Field Name : serviceOperAutoNatAddrListPortsConsumedTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_consumed_total

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.12

Field Name : serviceOperAutoNatAddrListPortsConsumed

Field Type : CounterBasedGauge64

Field Status : current

Description : ports_consumed

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.11

ACOS-SLB-SERVER-MIB_oid_list

Field Name : serviceOperAutoNatAddrListIpRr
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_rr
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.10

Field Name : serviceOperAutoNatAddrListHaGroupId
Field Type : CounterBasedGauge64
Field Status : current
Description : ha_group_id
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.9

Field Name : serviceOperAutoNatAddrListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.8

Field Name : serviceOperAutoNatAddrListAutoNatIp
Field Type : String
Field Status : current
Description : auto_nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.7

Field Name : serviceOperAutoNatAddrListAutoNatAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.6

Field Name : serviceOperAutoNatAddrListLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.5

Field Name : serviceOperAutoNatAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.4

Field Name : serviceOperAutoNatAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.3

Field Name : serviceOperAutoNatAddrListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.2

Field Name : serviceOperAutoNatAddrListSlotId
Field Type : Integer32
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.3.1.1

Field Name : serviceOperTable

Field Type : TABLE

Field Status : current

Description : RealServerService from object 'slb.server.service'

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2

Field Name : serviceOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The serviceOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1

Field Name : serviceOperPoolName

Field Type : String

Field Status : current

Description : pool_name

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.24

Field Name : serviceOperResvConn

Field Type : CounterBasedGauge64

Field Status : current

Description : resv_conn

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.23

Field Name : serviceOperAflowQueueSize

Field Type : CounterBasedGauge64

Field Status : current

Description : aflow_queue_size

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.22

Field Name : serviceOperAflowConnLimit

Field Type : CounterBasedGauge64

Field Status : current

Description : aflow_conn_limit

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.21

Field Name : serviceOperSoftDownTime

Field Type : CounterBasedGauge64

Field Status : current

Description : soft_down_time

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.20

Field Name : serviceOperHmIndex

Field Type : CounterBasedGauge64

Field Status : current

Description : hm-index

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.19

Field Name : serviceOperHmKey

Field Type : CounterBasedGauge64

Field Status : current

Description : hm-key

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.18

ACOS-SLB-SERVER-MIB_oid_list

Field Name : serviceOperDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : disable
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.17

Field Name : serviceOperInbandHmReassignNum
Field Type : CounterBasedGauge64
Field Status : current
Description : inband_hm_reassign_num
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.16

Field Name : serviceOperEsRespTime
Field Type : CounterBasedGauge64
Field Status : current
Description : es_resp_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.15

Field Name : serviceOperDiameterEnabled
Field Type : CounterBasedGauge64
Field Status : current
Description : diameter_enabled
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.14

Field Name : serviceOperDownTimeGracePeriod
Field Type : CounterBasedGauge64
Field Status : current
Description : down_time_grace_period
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.13

Field Name : serviceOperCurrentTime
Field Type : CounterBasedGauge64
Field Status : current
Description : current_time
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.12

Field Name : serviceOperDownGracePeriodAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : down_grace_period_allowed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.11

Field Name : serviceOperCurrObserveRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_observe_rate
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.10

Field Name : serviceOperSlowStartConnLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : slow_start_conn_limit
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.9

Field Name : serviceOperConnRateUnit
Field Type : String
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : conn_rate_unit

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.8

Field Name : serviceOperCurrConnRate

Field Type : CounterBasedGauge64

Field Status : current

Description : curr_conn_rate

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.7

Field Name : serviceOperState

Field Type : String

Field Status : current

Description : state

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.6

Field Name : serviceOperLabel

Field Type : String

Field Status : current

Description : label

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.5

Field Name : serviceOperProtocol

Field Type : String

Field Status : current

Description : protocol

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.4

Field Name : serviceOperPort

Field Type : Integer32

Field Status : current

Description : port-number

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.3

Field Name : serviceOperName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.2

Field Name : serviceOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.2.1.1

Field Name : serviceOperDrsIpNatListNatPoolAddrListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The serviceOperDrsIpNatListNatPoolAddrList entry:nat-pool-addr-list

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8.1

Field Name : serviceOperDrsIpNatListNatPoolAddrListAllocFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : alloc_failed

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8.1.12

ACOS-SLB-SERVER-MIB_oid_list

Field Name : serviceOperDrsIpNatListNatPoolAddrListPortsFreedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_freed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8.1.11

Field Name : serviceOperDrsIpNatListNatPoolAddrListPortsConsumedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed_total
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8.1.10

Field Name : serviceOperDrsIpNatListNatPoolAddrListPortsConsumed
Field Type : CounterBasedGauge64
Field Status : current
Description : ports_consumed
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8.1.9

Field Name : serviceOperDrsIpNatListNatPoolAddrListNatIp
Field Type : String
Field Status : current
Description : nat_ip
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8.1.8

Field Name : serviceOperDrsIpNatListNatPoolAddrListNatPoolAddrListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8.1.7

Field Name : serviceOperDrsIpNatListNatPoolAddrListDrsIpNatListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8.1.6

Field Name : serviceOperDrsIpNatListNatPoolAddrListLabel
Field Type : String
Field Status : current
Description : label
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8.1.5

Field Name : serviceOperDrsIpNatListNatPoolAddrListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8.1.4

Field Name : serviceOperDrsIpNatListNatPoolAddrListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8.1.3

Field Name : serviceOperDrsIpNatListNatPoolAddrListName
Field Type : String
Field Status : current

ACOS-SLB-SERVER-MIB_oid_list

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8.1.2

Field Name : serviceOperDrsIpNatListNatPoolAddrListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.318.1.5.8.1.1

ACOS-SLB-SERVICE-GROUP-MIB_oid_list

Field Name : serviceGroupOperSgmListTable
Field Type : TABLE
Field Status : current
Description : ServiceGroup from object 'slb.service-group'
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3

Field Name : serviceGroupOperSgmListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceGroupOperSgmList entry:sgm-list
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3.1

Field Name : serviceGroupOperSgmListSgmPort
Field Type : CounterBasedGauge64
Field Status : current
Description : sgm-port
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3.1.5

Field Name : serviceGroupOperSgmListSgmName
Field Type : String
Field Status : current
Description : sgm-name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3.1.4

Field Name : serviceGroupOperSgmListSgmListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3.1.3

Field Name : serviceGroupOperSgmListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3.1.2

Field Name : serviceGroupOperSgmListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.3.1.1

Field Name : serviceGroupOperTable
Field Type : TABLE
Field Status : current
Description : ServiceGroup from object 'slb.service-group'
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2

Field Name : serviceGroupOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceGroupOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1

Field Name : serviceGroupOperFilter
Field Type : String
Field Status : current

ACOS-SLB-SERVICE-GROUP-MIB_oid_list

Description : filter

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.14

Field Name : serviceGroupOperPriAffinityPriority

Field Type : CounterBasedGauge64

Field Status : current

Description : pri_affinity_priority

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.13

Field Name : serviceGroupOperHmDsrEnableAllVip

Field Type : CounterBasedGauge64

Field Status : current

Description : hm_dsr_enable_all_vip

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.12

Field Name : serviceGroupOperStatelessType

Field Type : CounterBasedGauge64

Field Status : current

Description : stateless_type

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.11

Field Name : serviceGroupOperStatelessState

Field Type : CounterBasedGauge64

Field Status : current

Description : stateless_state

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.10

Field Name : serviceGroupOperStatelessCurrentUsage

Field Type : CounterBasedGauge64

Field Status : current

Description : stateless_current_usage

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.9

Field Name : serviceGroupOperStatelessCurrentRate

Field Type : CounterBasedGauge64

Field Status : current

Description : stateless_current_rate

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.8

Field Name : serviceGroupOperServersTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : servers_total

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.7

Field Name : serviceGroupOperServersDisable

Field Type : CounterBasedGauge64

Field Status : current

Description : servers_disable

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.6

Field Name : serviceGroupOperServersDown

Field Type : CounterBasedGauge64

Field Status : current

Description : servers_down

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.5

ACOS-SLB-SERVICE-GROUP-MIB_oid_list

Field Name : serviceGroupOperServersUp
Field Type : CounterBasedGauge64
Field Status : current
Description : servers_up
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.4

Field Name : serviceGroupOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.3

Field Name : serviceGroupOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.2

Field Name : serviceGroupOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.2.1.1

Field Name : serviceGroupStatsTable
Field Type : TABLE
Field Status : current
Description : ServiceGroup from object 'slb.service-group'
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1

Field Name : serviceGroupStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The serviceGroupStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1

Field Name : serviceGroupStatsServiceCurrConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : service_curr_conn_overflow
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.14

Field Name : serviceGroupStatsServiceResp5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : service_resp_5xx
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.13

Field Name : serviceGroupStatsServiceResp4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : service_resp_4xx
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.12

Field Name : serviceGroupStatsServiceResp3xx
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SERVICE-GROUP-MIB_oid_list

Description : service_resp_3xx

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.11

Field Name : serviceGroupStatsServiceResp2xx

Field Type : CounterBasedGauge64

Field Status : current

Description : service_resp_2xx

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.10

Field Name : serviceGroupStatsServiceRespCount

Field Type : CounterBasedGauge64

Field Status : current

Description : service_resp_count

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.9

Field Name : serviceGroupStatsServiceReqCount

Field Type : CounterBasedGauge64

Field Status : current

Description : service_req_count

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.8

Field Name : serviceGroupStatsServiceUnhealthyHost

Field Type : CounterBasedGauge64

Field Status : current

Description : service_unhealthy_host

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.7

Field Name : serviceGroupStatsServiceHealthyHost

Field Type : CounterBasedGauge64

Field Status : current

Description : service_healthy_host

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.6

Field Name : serviceGroupStatsServicePeakConn

Field Type : CounterBasedGauge64

Field Status : current

Description : service_peak_conn

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.5

Field Name : serviceGroupStatsServerSelectionFailReset

Field Type : CounterBasedGauge64

Field Status : current

Description : server_selection_fail_reset

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.4

Field Name : serviceGroupStatsServerSelectionFailDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : server_selection_fail_drop

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.3

Field Name : serviceGroupStatsName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.2

ACOS-SLB-SERVICE-GROUP-MIB_oid_list

Field Name : serviceGroupStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.1.1.1

Field Name : memberOperAltListTable
Field Type : TABLE
Field Status : current
Description : ServiceGroupMember from object 'slb.service-group.member'
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4

Field Name : memberOperDrsListTable
Field Type : TABLE
Field Status : current
Description : ServiceGroupMember from object 'slb.service-group.member'
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3

Field Name : memberOperDrsListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The memberOperDrsList entry:drs-list
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1

Field Name : memberOperDrsListDrsSrspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-srsp-time
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.25

Field Name : memberOperDrsListDrsFrspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-frsp-time
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.24

Field Name : memberOperDrsListDrsRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-rsp-time
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.23

Field Name : memberOperDrsListDrsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.22

Field Name : memberOperDrsListDrsFwdBts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-fwd-bts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.21

Field Name : memberOperDrsListDrsRevBts
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SERVICE-GROUP-MIB_oid_list

Description : drs-rev-bts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.20

Field Name : memberOperDrsListDrsFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-fwd-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.19

Field Name : memberOperDrsListDrsRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-rev-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.18

Field Name : memberOperDrsListDrsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-total-req-succ
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.17

Field Name : memberOperDrsListDrsTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-total-req
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.16

Field Name : memberOperDrsListDrsCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-req
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.15

Field Name : memberOperDrsListDrsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-total-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.14

Field Name : memberOperDrsListDrsPersConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-pers-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.13

Field Name : memberOperDrsListDrsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.12

Field Name : memberOperDrsListDrsPriority
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-priority
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.11

ACOS-SLB-SERVICE-GROUP-MIB_oid_list

Field Name : memberOperDrsListDrsPort
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-port
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.10

Field Name : memberOperDrsListDrsHmIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-hm-index
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.9

Field Name : memberOperDrsListDrsHmKey
Field Type : CounterBasedGauge64
Field Status : current
Description : drs-hm-key
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.8

Field Name : memberOperDrsListDrsState
Field Type : String
Field Status : current
Description : drs-state
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.7

Field Name : memberOperDrsListDrsName
Field Type : String
Field Status : current
Description : drs-name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.6

Field Name : memberOperDrsListDrsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.5

Field Name : memberOperDrsListPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.4

Field Name : memberOperDrsListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.3

Field Name : memberOperDrsListServiceGroupName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.2

Field Name : memberOperDrsListSlotId
Field Type : Integer32
Field Status : current

ACOS-SLB-SERVICE-GROUP-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.3.1.1

Field Name : memberOperTable

Field Type : TABLE

Field Status : current

Description : ServiceGroupMember from object 'slb.service-group.member'

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2

Field Name : memberOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The memberOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1

Field Name : memberOperHmIndex

Field Type : CounterBasedGauge64

Field Status : current

Description : hm-index

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.7

Field Name : memberOperHmKey

Field Type : CounterBasedGauge64

Field Status : current

Description : hm-key

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.6

Field Name : memberOperState

Field Type : String

Field Status : current

Description : state

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.5

Field Name : memberOperPort

Field Type : Integer32

Field Status : current

Description : port

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.4

Field Name : memberOperName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.3

Field Name : memberOperServiceGroupName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.2

Field Name : memberOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.2.1.1

ACOS-SLB-SERVICE-GROUP-MIB_oid_list

Field Name : memberStatsTable
Field Type : TABLE
Field Status : current
Description : ServiceGroupMember from object 'slb.service-group.member'
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1

Field Name : memberStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The memberStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1

Field Name : memberStatsStateFlaps
Field Type : CounterBasedGauge64
Field Status : current
Description : state_flaps
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.24

Field Name : memberStatsCurrConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_overflow
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.23

Field Name : memberStatsTotalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.22

Field Name : memberStatsCurrSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.21

Field Name : memberStatsSlowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : slowest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.20

Field Name : memberStatsFastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : fastest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.19

Field Name : memberStatsResponseTime
Field Type : CounterBasedGauge64
Field Status : current
Description : response_time
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.18

Field Name : memberStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SERVICE-GROUP-MIB_oid_list

Description : peak_conn

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.17

Field Name : memberStatsTotalReqSucc

Field Type : CounterBasedGauge64

Field Status : current

Description : total_req_succ

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.16

Field Name : memberStatsTotalReq

Field Type : CounterBasedGauge64

Field Status : current

Description : total_req

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.15

Field Name : memberStatsCurrReq

Field Type : CounterBasedGauge64

Field Status : current

Description : curr_req

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.14

Field Name : memberStatsTotalRevPktsInspectedStatusCodeNon5xx

Field Type : CounterBasedGauge64

Field Status : current

Description : total_rev_pkts_inspected_status_code_non_5xx

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.13

Field Name : memberStatsTotalRevPktsInspectedStatusCode2xx

Field Type : CounterBasedGauge64

Field Status : current

Description : total_rev_pkts_inspected_status_code_2xx

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.12

Field Name : memberStatsTotalRevPktsInspected

Field Type : CounterBasedGauge64

Field Status : current

Description : total_rev_pkts_inspected

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.11

Field Name : memberStatsTotalConn

Field Type : CounterBasedGauge64

Field Status : current

Description : total_conn

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.10

Field Name : memberStatsTotalRevPkts

Field Type : CounterBasedGauge64

Field Status : current

Description : total_rev_pkts

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.9

Field Name : memberStatsTotalRevBytes

Field Type : CounterBasedGauge64

Field Status : current

Description : total_rev_bytes

OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.8

ACOS-SLB-SERVICE-GROUP-MIB_oid_list

Field Name : memberStatsTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.7

Field Name : memberStatsTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.6

Field Name : memberStatsCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.5

Field Name : memberStatsPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.4

Field Name : memberStatsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.3

Field Name : memberStatsServiceGroupName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.2

Field Name : memberStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.1.1.1

Field Name : memberOperAltListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The memberOperAltList entry:alt-list
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1

Field Name : memberOperAltListAltPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-peak-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.13

Field Name : memberOperAltListAltFwdPkts
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SERVICE-GROUP-MIB_oid_list

Description : alt-fwd-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.12

Field Name : memberOperAltListAltRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-rev-pkts
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.11

Field Name : memberOperAltListAltTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-total-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.10

Field Name : memberOperAltListAltCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-curr-conn
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.9

Field Name : memberOperAltListAltState
Field Type : String
Field Status : current
Description : alt-state
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.8

Field Name : memberOperAltListAltPort
Field Type : CounterBasedGauge64
Field Status : current
Description : alt-port
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.7

Field Name : memberOperAltListAltName
Field Type : String
Field Status : current
Description : alt-name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.6

Field Name : memberOperAltListAltListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.5

Field Name : memberOperAltListPort
Field Type : Integer32
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.4

Field Name : memberOperAltListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.3

ACOS-SLB-SERVICE-GROUP-MIB_oid_list

Field Name : memberOperAltListServiceGroupName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.2

Field Name : memberOperAltListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.319.1.5.4.1.1

ACOS-SLB-SSL-ACME-CERT-STATUS-MIB_oid_list

Field Name : sslAcmeCertStatusOperAcmeCertsTable
Field Type : TABLE
Field Status : current
Description : from object 'slb.ssl-acme-cert-status'
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2

Field Name : sslAcmeCertStatusOperAcmeCertsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The sslAcmeCertStatusOperAcmeCerts entry:acme-certs
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1

Field Name : sslAcmeCertStatusOperAcmeCertsLastEnrollRenewStatus
Field Type : String
Field Status : current
Description : last-enroll-renew-status
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.7

Field Name : sslAcmeCertStatusOperAcmeCertsRotated
Field Type : CounterBasedGauge64
Field Status : current
Description : rotated
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.6

Field Name : sslAcmeCertStatusOperAcmeCertsRenew
Field Type : String
Field Status : current
Description : renew
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.5

Field Name : sslAcmeCertStatusOperAcmeCertsStatus
Field Type : String
Field Status : current
Description : status
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.4

Field Name : sslAcmeCertStatusOperAcmeCertsName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.3

Field Name : sslAcmeCertStatusOperAcmeCertsAcmeCertsListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.2

Field Name : sslAcmeCertStatusOperAcmeCertsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.297.1.2.1.1

ACOS-SLB-SSL-FORWARD-PROXY-MIB_oid_list

Field Name : sslForwardProxyStatsTable
Field Type : TABLE
Field Status : current
Description : SSLForwardProxyStatsInfo from object 'slb.ssl-forward-proxy'
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1

Field Name : sslForwardProxyStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The sslForwardProxyStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1

Field Name : sslForwardProxyStatsBypassServerIpSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-server-ip-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.37

Field Name : sslForwardProxyStatsBypassClientIpSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-client-ip-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.36

Field Name : sslForwardProxyStatsCertInCache
Field Type : CounterBasedGauge64
Field Status : current
Description : cert_in_cache
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.35

Field Name : sslForwardProxyStatsAsyncConnLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : async_conn_limit_drop
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.34

Field Name : sslForwardProxyStatsAsyncConnTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : async_conn_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.33

Field Name : sslForwardProxyStatsCurrConnInBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_in_buff
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.32

Field Name : sslForwardProxyStatsTotConnInBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : tot_conn_in_buff
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.31

Field Name : sslForwardProxyStatsBypassAdGroupSessions
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SSL-FORWARD-PROXY-MIB_oid_list

Description : bypass-ad-group-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.30

Field Name : sslForwardProxyStatsBypassUsernameSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-username-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.29

Field Name : sslForwardProxyStatsDropEsniSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : drop-esni-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.28

Field Name : sslForwardProxyStatsBypassEsniSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-esni-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.27

Field Name : sslForwardProxyStatsResetNoSniSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : reset-no-sni-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.26

Field Name : sslForwardProxyStatsBypassNoSniSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-no-sni-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.25

Field Name : sslForwardProxyStatsBypassCertSanSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-cert-san-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.24

Field Name : sslForwardProxyStatsBypassCertIssuerSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-cert-issuer-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.23

Field Name : sslForwardProxyStatsBypassCertSubjectSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-cert-subject-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.22

Field Name : sslForwardProxyStatsAflexBypass

Field Type : CounterBasedGauge64

Field Status : current

Description : aflex-bypass

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.21

ACOS-SLB-SSL-FORWARD-PROXY-MIB_oid_list

Field Name : sslForwardProxyStatsConnectionsFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : connections-failed
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.20

Field Name : sslForwardProxyStatsCertificatesInCache
Field Type : CounterBasedGauge64
Field Status : current
Description : certificates-in-cache
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.19

Field Name : sslForwardProxyStatsUnsupportedSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported-ssl-version
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.18

Field Name : sslForwardProxyStatsRevokedOcspResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : revoked-ocsp-response
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.17

Field Name : sslForwardProxyStatsInvalidOcspStaplingResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid-ocsp-stapling-response
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.16

Field Name : sslForwardProxyStatsFailedInCertificateSigning
Field Type : CounterBasedGauge64
Field Status : current
Description : failed-in-certificate-signing
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.15

Field Name : sslForwardProxyStatsFailedInCertificateVerification
Field Type : CounterBasedGauge64
Field Status : current
Description : failed-in-certificate-verification
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.14

Field Name : sslForwardProxyStatsFailedInTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : failed-in-tcp
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.13

Field Name : sslForwardProxyStatsFailedInCryptoOperations
Field Type : CounterBasedGauge64
Field Status : current
Description : failed-in-crypto-operations
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.12

Field Name : sslForwardProxyStatsFailedInSslHandshakes
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SSL-FORWARD-PROXY-MIB_oid_list

Description : failed-in-ssl-handshakes

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.11

Field Name : sslForwardProxyStatsBypassClientAuthSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-client-auth-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.10

Field Name : sslForwardProxyStatsBypassSniSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-sni-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.9

Field Name : sslForwardProxyStatsBypassFailsafeSslSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-failsafe-ssl-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.8

Field Name : sslForwardProxyStatsConnInspect

Field Type : CounterBasedGauge64

Field Status : current

Description : conn_inspect

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.7

Field Name : sslForwardProxyStatsConnBypass

Field Type : CounterBasedGauge64

Field Status : current

Description : conn_bypass

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.6

Field Name : sslForwardProxyStatsCertMiss

Field Type : CounterBasedGauge64

Field Status : current

Description : cert_miss

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.5

Field Name : sslForwardProxyStatsCertHit

Field Type : CounterBasedGauge64

Field Status : current

Description : cert_hit

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.4

Field Name : sslForwardProxyStatsCertExpr

Field Type : CounterBasedGauge64

Field Status : current

Description : cert_expr

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.3

Field Name : sslForwardProxyStatsCertCreate

Field Type : CounterBasedGauge64

Field Status : current

Description : cert_create

OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.2

ACOS-SLB-SSL-FORWARD-PROXY-MIB_oid_list

Field Name : sslForwardProxyStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.312.1.1.1.1

ACOS-SLB-SSL-JA3-MIB_oid_list

Field Name : sslJa3OperRecordTable
Field Type : TABLE
Field Status : current
Description : ShowSSLJA3 from object 'slb.ssl-ja3'
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2

Field Name : sslJa3OperRecordEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The sslJa3OperRecord entry:record
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2.1

Field Name : sslJa3OperRecordAmount
Field Type : CounterBasedGauge64
Field Status : current
Description : amount
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2.1.5

Field Name : sslJa3OperRecordAddrV6
Field Type : String
Field Status : current
Description : addr-v6
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2.1.4

Field Name : sslJa3OperRecordAddrV4
Field Type : String
Field Status : current
Description : addr-v4
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2.1.3

Field Name : sslJa3OperRecordRecordListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2.1.2

Field Name : sslJa3OperRecordSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.314.1.2.1.1

ACOS-SLB-SSL-JA4-MIB_oid_list

Field Name : sslJa40perRecordTable
Field Type : TABLE
Field Status : current
Description : ShowSSLJA4 from object 'slb.ssl-ja4'
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2

Field Name : sslJa40perRecordEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The sslJa40perRecord entry:record
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2.1

Field Name : sslJa40perRecordAmount
Field Type : CounterBasedGauge64
Field Status : current
Description : amount
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2.1.5

Field Name : sslJa40perRecordAddrV6
Field Type : String
Field Status : current
Description : addr-v6
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2.1.4

Field Name : sslJa40perRecordAddrV4
Field Type : String
Field Status : current
Description : addr-v4
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2.1.3

Field Name : sslJa40perRecordRecordListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2.1.2

Field Name : sslJa40perRecordSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.315.1.2.1.1

ACOS-SLB-SSL-STATS-MIB_oid_list

Field Name : sslStatsOperSslModuleStatsTable
Field Type : TABLE
Field Status : current
Description : SSLStatistics from object 'slb.ssl-stats'
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3

Field Name : sslStatsOperTable
Field Type : TABLE
Field Status : current
Description : SSLStatistics from object 'slb.ssl-stats'
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2

Field Name : sslStatsOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The sslStatsOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1

Field Name : sslStatsOperUtilEnableStatus
Field Type : String
Field Status : current
Description : util-enable-status
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.68

Field Name : sslStatsOperFpFailAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : fp-fail-aflex
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.67

Field Name : sslStatsOperFpFailVerifyCert
Field Type : CounterBasedGauge64
Field Status : current
Description : fp-fail-verify-cert
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.66

Field Name : sslStatsOperFpFailTcpError
Field Type : CounterBasedGauge64
Field Status : current
Description : fp-fail-tcp-error
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.65

Field Name : sslStatsOperFpFailHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : fp-fail-handshake
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.64

Field Name : sslStatsOperServerSslUnknownError
Field Type : CounterBasedGauge64
Field Status : current
Description : server-ssl-unknown-error
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.63

Field Name : sslStatsOperServerSslInternalError
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SSL-STATS-MIB_oid_list

Description : server-ssl-internal-error
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.62

Field Name : sslStatsOperClientSslUnknownError
Field Type : CounterBasedGauge64
Field Status : current
Description : client-ssl-unknown-error
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.61

Field Name : sslStatsOperClientSslInternalError
Field Type : CounterBasedGauge64
Field Status : current
Description : client-ssl-internal-error
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.60

Field Name : sslStatsOperServerSslFinReset
Field Type : CounterBasedGauge64
Field Status : current
Description : server-ssl-fin-reset
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.59

Field Name : sslStatsOperServerSslFatalAlert
Field Type : CounterBasedGauge64
Field Status : current
Description : server-ssl-fatal-alert
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.58

Field Name : sslStatsOperSslSessionFinReset
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl-session-fin-reset
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.57

Field Name : sslStatsOperClientSslFinReset
Field Type : CounterBasedGauge64
Field Status : current
Description : client-ssl-fin-reset
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.56

Field Name : sslStatsOperClientSslFatalAlert
Field Type : CounterBasedGauge64
Field Status : current
Description : client-ssl-fatal-alert
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.55

Field Name : sslStatsOperUnsupportedSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported-ssl-version
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.54

Field Name : sslStatsOperRevokedOcspResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : revoked-ocsp-response
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.53

ACOS-SLB-SSL-STATS-MIB_oid_list

Field Name : sslStatsOperInvalidOcspStaplingResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid-ocsp-stapling-response
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.52

Field Name : sslStatsOperCertificateSigningFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : certificate-signing-failures
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.51

Field Name : sslStatsOperCertificateVerificationFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : certificate-verification-failures
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.50

Field Name : sslStatsOperTcpFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : tcp-failures
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.49

Field Name : sslStatsOperCryptioOperations
Field Type : CounterBasedGauge64
Field Status : current
Description : cryptio-operations
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.48

Field Name : sslStatsOperSslHandshakeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl-handshake-failure
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.47

Field Name : sslStatsOperBypassClientAuthSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-client-auth-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.46

Field Name : sslStatsOperDropEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : drop-esni-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.45

Field Name : sslStatsOperBypassEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : bypass-esni-sessions
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.44

Field Name : sslStatsOperResetNoSniSessions
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SSL-STATS-MIB_oid_list

Description : reset-no-sni-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.43

Field Name : sslStatsOperBypassNoSniSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-no-sni-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.42

Field Name : sslStatsOperBypassCertSanSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-cert-san-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.41

Field Name : sslStatsOperBypassCertIssuerSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-cert-issuer-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.40

Field Name : sslStatsOperBypassCertSubjectSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-cert-subject-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.39

Field Name : sslStatsOperBypassSniSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-sni-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.38

Field Name : sslStatsOperBypassAdGroupSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-ad-group-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.37

Field Name : sslStatsOperBypassUsernameSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-username-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.36

Field Name : sslStatsOperBypassFailsafeSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : bypass-failsafe-sessions

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.35

Field Name : sslStatsOperDynamicSslContexts

Field Type : CounterBasedGauge64

Field Status : current

Description : dynamic-ssl-contexts

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.34

ACOS-SLB-SSL-STATS-MIB_oid_list

Field Name : sslStatsOperStaticSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : static-ssl-contexts
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.33

Field Name : sslStatsOperCurrSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-ssl-contexts
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.32

Field Name : sslStatsOperMaxSslContexts
Field Type : CounterBasedGauge64
Field Status : current
Description : max-ssl-contexts
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.31

Field Name : sslStatsOperClientsslContextMallocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : clientssl-context-malloc-fail
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.30

Field Name : sslStatsOperRecordTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : record-too-big
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.29

Field Name : sslStatsOperHwRingFull
Field Type : CounterBasedGauge64
Field Status : current
Description : hw-ring-full
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.28

Field Name : sslStatsOperHwContextAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : hw-context-alloc-fail
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.27

Field Name : sslStatsOperHwContextUsage
Field Type : CounterBasedGauge64
Field Status : current
Description : hw-context-usage
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.26

Field Name : sslStatsOperHwContextTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : hw-context-total
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.25

Field Name : sslStatsOperCaVerificationFailures
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SSL-STATS-MIB_oid_list

Description : ca-verification-failures
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.24

Field Name : sslStatsOperClientCertAuthFail
Field Type : CounterBasedGauge64
Field Status : current
Description : client-cert-auth-fail
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.23

Field Name : sslStatsOperServerCertErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : server-cert-errors
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.22

Field Name : sslStatsOperSslMemoryUsage
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl-memory-usage
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.21

Field Name : sslStatsOperFailedCrypto
Field Type : CounterBasedGauge64
Field Status : current
Description : failed-crypto
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.20

Field Name : sslStatsOperFailedHandshakes
Field Type : CounterBasedGauge64
Field Status : current
Description : failed-handshakes
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.19

Field Name : sslStatsOperTotalServersideFailedEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : total-serverside-failed-early-data-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.18

Field Name : sslStatsOperTotalClientsideFailedEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : total-clientside-failed-early-data-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.17

Field Name : sslStatsOperTotalServersideEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : total-serverside-early-data-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.16

Field Name : sslStatsOperTotalClientsideEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : total-clientside-early-data-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.15

ACOS-SLB-SSL-STATS-MIB_oid_list

Field Name : sslStatsOperTotalReuseSessionTicketServerSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : total-reuse-session-ticket-server-ssl
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.14

Field Name : sslStatsOperTotalReuseSessionTicketClientSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : total-reuse-session-ticket-client-ssl
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.13

Field Name : sslStatsOperTotalReuseServerSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : total-reuse-server-ssl
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.12

Field Name : sslStatsOperTotalReuseClientSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : total-reuse-client-ssl
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.11

Field Name : sslStatsOperNonSslBypassConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : non-ssl-bypass-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.10

Field Name : sslStatsOperTotalServersideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : total-serverside-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.9

Field Name : sslStatsOperCurrentServersideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : current-serverside-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.8

Field Name : sslStatsOperTotalClientsideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : total-clientside-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.7

Field Name : sslStatsOperCurrentClientsideConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : current-clientside-connections
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.6

Field Name : sslStatsOperSslModulesCount
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-SSL-STATS-MIB_oid_list

Description : ssl-modules-count

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.5

Field Name : sslStatsOperThalesHsmStatus

Field Type : String

Field Status : current

Description : thales-hsm-status

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.4

Field Name : sslStatsOperConfigModuleType

Field Type : String

Field Status : current

Description : config-module-type

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.3

Field Name : sslStatsOperSslModuleType

Field Type : String

Field Status : current

Description : ssl-module-type

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.2

Field Name : sslStatsOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.2.1.1

Field Name : sslStatsOperSslModuleStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The sslStatsOperSslModuleStats entry:ssl-module-stats

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1

Field Name : sslStatsOperSslModuleStats60secRate

Field Type : CounterBasedGauge64

Field Status : current

Description : 60sec-rate

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.12

Field Name : sslStatsOperSslModuleStats30secRate

Field Type : CounterBasedGauge64

Field Status : current

Description : 30sec-rate

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.11

Field Name : sslStatsOperSslModuleStats10secRate

Field Type : CounterBasedGauge64

Field Status : current

Description : 10sec-rate

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.10

Field Name : sslStatsOperSslModuleStats5secRate

Field Type : CounterBasedGauge64

Field Status : current

Description : 5sec-rate

OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.9

ACOS-SLB-SSL-STATS-MIB_oid_list

Field Name : sslStatsOperSslModuleStats1secRate
Field Type : CounterBasedGauge64
Field Status : current
Description : 1sec-rate
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.8

Field Name : sslStatsOperSslModuleStatsUtilPercentage
Field Type : CounterBasedGauge64
Field Status : current
Description : util-percentage
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.7

Field Name : sslStatsOperSslModuleStatsRequestsHandled
Field Type : CounterBasedGauge64
Field Status : current
Description : requests-handled
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.6

Field Name : sslStatsOperSslModuleStatsTotalAvailableCryptoEngines
Field Type : CounterBasedGauge64
Field Status : current
Description : total-available-crypto-engines
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.5

Field Name : sslStatsOperSslModuleStatsTotalEnabledCryptoEngines
Field Type : CounterBasedGauge64
Field Status : current
Description : total-enabled-crypto-engines
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.4

Field Name : sslStatsOperSslModuleStatsSslModulesIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl-modules-index
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.3

Field Name : sslStatsOperSslModuleStatsSslModuleStatsListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.2

Field Name : sslStatsOperSslModuleStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.303.1.3.1.1

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RPZ Parse Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.89.1.2

Field Name : setBwError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RPZ Set Class-list Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.89.1.1

Field Name : errEntryCheckSlbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Error in checking HM internal SLB Resource
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.44

Field Name : errEntryMissingVport
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry missing Virtual-Port
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.43

Field Name : errCreateSslCtxFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Error in creating SSL CTX
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.42

Field Name : errMissingServerSslTemplate
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing Server-SSL Template
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.41

Field Name : totalStartServerConnErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total start server connections error
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.40

Field Name : totalServerQuicConnErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total start server QUIC connections error
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.39

Field Name : totalServerQuicConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total start server QUIC connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.38

Field Name : smartNatReleaseFailed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Total smart-nat release failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.37

Field Name : smartNatAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total smart-nat allocation failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.36

Field Name : smartNatRelease
Field Type : CounterBasedGauge64
Field Status : current
Description : Total smart-nat release successful
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.35

Field Name : smartNatAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total smart-nat allocation successful
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.34

Field Name : errHttp2VerMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Error HTTP2 version mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.33

Field Name : errL7SessProcessTcpDataFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 session process TCP data failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.32

Field Name : errL7SessProcessTcpEstabFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 session process TCP established failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.31

Field Name : errHttp2Callback
Field Type : CounterBasedGauge64
Field Status : current
Description : Error HTTP2 callback
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.30

Field Name : errServerSynTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Error SSL server SYN timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.29

Field Name : errSslCertNameMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Error SSL cert name mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.28

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : errNoHmEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Error no HM entry found
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.27

Field Name : totalWrongStatusReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP received response with wrong response code
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.26

Field Name : totalMaintenanceReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Total maintenace response received
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.25

Field Name : totalMatchDefaultRespCode
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP received response with match 200 response code
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.24

Field Name : totalMatchRespCode
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP received response with match response code
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.23

Field Name : errEntryCreateSlbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Error in creating HM internal SLB Resource
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.22

Field Name : entryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry deleted
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.21

Field Name : hmTcpConnSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP connections sent for HM
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.20

Field Name : errHmTcpConnSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Error in initiating TCP connection for HM
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.19

Field Name : errL4SessAlloc
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Error allocating L4 session for HM
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.18

Field Name : errSmartNatPortAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Error obtaining smart-nat source port
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.17

Field Name : errSmartNatAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Error creating smart-nat instance
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.16

Field Name : totalTcpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP errors in health-checks sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.15

Field Name : errEntryInsertFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry insert failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.8

Field Name : errEntryCreateOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry creation out of memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.7

Field Name : errEntryCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.6

Field Name : totalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HM entries freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.5

Field Name : currReadyToFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Current HM entries ready to free
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.4

Field Name : totalInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HM entries inserted
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.3

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : totalCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HM Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.2

Field Name : currEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : Current HM Entries
OID : 1.3.6.1.4.1.22610.2.4.10.108.105.1.1

Field Name : probeTcpConnSent
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP connection sent for probe
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.20

Field Name : errProbeTcpConnSend
Field Type : CounterBasedGauge64
Field Status : current
Description : Error in initiating TCP connection for probe
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.19

Field Name : errL4SessAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Error allocating L4 session for probe
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.18

Field Name : errSmartNatPortAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Error obtaining Smart NAT source port
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.17

Field Name : errSmartNatAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Error creating Smart NAT Instance
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.16

Field Name : totalTcpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP errors in probes sent out
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.15

Field Name : totalHttpResponseBad
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP responses not matching probe template config
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.14

Field Name : totalHttpResponseGood
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Total HTTP responses matching probe template config
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.13

Field Name : totalHttpResponseReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP responses received
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.12

Field Name : totalHttpProbesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP Probes Sent out
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.11

Field Name : errTmplProbeCreateOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Probe Template Creation Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.10

Field Name : errTmplProbeCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Probe Template Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.9

Field Name : errEntryInsertFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Insert Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.8

Field Name : errEntryCreateOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Creation Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.7

Field Name : errEntryCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.6

Field Name : totalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.5

Field Name : totalReadyToFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Ready To Free
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.4

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : totalInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.3

Field Name : totalCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.2

Field Name : currEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Count
OID : 1.3.6.1.4.1.22610.2.4.10.108.78.1.1.1

Field Name : errVportFailMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed to Match Vport
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.16

Field Name : errEntryInsertFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Insert Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.15

Field Name : errEntryExtCreateOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Extension Creation Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.14

Field Name : errEntryCreateOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Creation Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.13

Field Name : errEntryCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Creation Failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.12

Field Name : otherThreadRefill
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Thread Refilling
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.11

Field Name : totalCreditExceeded
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Total Credit Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.10

Field Name : totalRefill
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Refills
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.9

Field Name : totalOverflowEntryHits
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Overflow Entry Hits
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.8

Field Name : totalLogs
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Logs
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.7

Field Name : totalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.6

Field Name : totalReadyToFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Ready To Free
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.5

Field Name : totalWithdrew
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Withdrew
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.4

Field Name : totalInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.3

Field Name : totalCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Entry Created
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.2

Field Name : currEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Count
OID : 1.3.6.1.4.1.22610.2.4.10.108.75.1.1

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : mlbServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Server down
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.18

Field Name : mlbServerProbe
Field Type : CounterBasedGauge64
Field Status : current
Description : Server probe
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.17

Field Name : mlbDcmsgFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Dcmsg free
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.16

Field Name : mlbDcmsgAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Dcmsg alloc
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.15

Field Name : mlbDcmsgError
Field Type : CounterBasedGauge64
Field Status : current
Description : Dcmsg error
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.14

Field Name : mlbDcmsgReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Dcmsg received
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.13

Field Name : mlbDcmsgSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Dcmsg sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.12

Field Name : msgRerouted
Field Type : CounterBasedGauge64
Field Status : current
Description : Message rerouted
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.11

Field Name : msgDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Message dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.10

Field Name : clientConnNotFound
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Client connection not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.9

Field Name : clientConnClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.8

Field Name : clientConnCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection created
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.7

Field Name : serverConnClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.6

Field Name : serverConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.5

Field Name : serverConnRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.4

Field Name : serverConnCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection created
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.3

Field Name : serverMsgReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Server message received
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.2

Field Name : clientMsgSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Client message sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.71.1.1

Field Name : totalLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Total log sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.7

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : totalReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Total rate exceed reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.6

Field Name : totalDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total rate exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.5

Field Name : freedSportip
Field Type : CounterBasedGauge64
Field Status : current
Description : Freed src port-ip entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.4

Field Name : freedSport
Field Type : CounterBasedGauge64
Field Status : current
Description : Freed src port entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.3

Field Name : allocSportip
Field Type : CounterBasedGauge64
Field Status : current
Description : Alloc'd src port-ip entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.2

Field Name : allocSport
Field Type : CounterBasedGauge64
Field Status : current
Description : Alloc'd src port entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.59.1.1

Field Name : totalValidPlayeridPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Valid playerid packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.7

Field Name : totalInvalidPlayeridDrops
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid playerid packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.6

Field Name : totalInvalidPlayeridPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid playerid packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.5

Field Name : totalPktActivityAgeOuts
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Playerid records idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.4

Field Name : totalAbsMaxAgeOuts
Field Type : CounterBasedGauge64
Field Status : current
Description : Playerid records max time aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.3

Field Name : totalPlayeridsDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Playerid records deleted
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.2

Field Name : totalPlayeridsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Playerid records created
OID : 1.3.6.1.4.1.22610.2.4.10.108.57.1.1

Field Name : rspBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from cache 200 OK - Brotli
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.32

Field Name : rspTypeStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from http2 server 200 OK - Stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.31

Field Name : cleanedEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Cleaned
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.30

Field Name : agingEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.29

Field Name : replacedEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Replaced
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.28

Field Name : entryNum
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Cached
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.27

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : memSize
Field Type : CounterBasedGauge64
Field Status : current
Description : Memory Used
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.26

Field Name : entryCreateFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : Entry Create failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.25

Field Name : contentToosmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy Content Too Small
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.24

Field Name : contentToobig
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy Content Too Big
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.23

Field Name : invalidateMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy URI invalidate
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.22

Field Name : match
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy URI cache
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.21

Field Name : nocacheMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy URI nocache
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.20

Field Name : rspOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from cache Other
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.19

Field Name : rspDeflate
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from cache 200 OK - Deflate
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.18

Field Name : rspGzip
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Responses from cache 200 OK - Gzip
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.17

Field Name : rspNoCompress
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from cache 200 OK - No Comp
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.16

Field Name : rspTypeOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from server 200 OK - Other
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.15

Field Name : rspType304
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from server 304 Not Modified
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.14

Field Name : rspTypeCE
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from server 200 OK - Chnk Enc
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.13

Field Name : rspTypeCL
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from server 200 OK - Cont Len
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.12

Field Name : nmResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses from cache 304 Not Modified
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.11

Field Name : imsRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : IMS Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.10

Field Name : rvFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Revalidation Failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.9

Field Name : rvSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Revalidation Successes
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.8

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : ncResHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Not cacheable
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.7

Field Name : ncReqHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : No-cache Request
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.6

Field Name : cachingReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Cacheable Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.5

Field Name : rcCacheGlobalTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.4

Field Name : bytesServed
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes Served
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.3

Field Name : miss
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache Misses
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.2

Field Name : rcCacheGlobalHits
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache Hits
OID : 1.3.6.1.4.1.22610.2.4.10.108.55.1.1

Field Name : slbProxyLineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.31

Field Name : startServerConnFailTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Fail Tuple Issue
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.30

Field Name : startServerConnFailServer
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Fail Server issue
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.29

Field Name : startServerConnFailPersist
Field Type : CounterBasedGauge64
Field Status : current
Description : Fail Persistence
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.28

Field Name : startServerConnFailSnat
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed Source NAT
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.27

Field Name : startServerConnFailMem
Field Type : CounterBasedGauge64
Field Status : current
Description : No memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.26

Field Name : startServerConnNoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No route to server
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.25

Field Name : startServerConnSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Success
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.24

Field Name : startServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Start server conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.23

Field Name : errCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : App ERR callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.22

Field Name : wbufCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : App WBUF callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.21

Field Name : dataCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : App DATA callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.20

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : estCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : App EST callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.19

Field Name : serviceFreeCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Service free callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.18

Field Name : serviceFreeCb
Field Type : CounterBasedGauge64
Field Status : current
Description : Service free callback
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.17

Field Name : serviceAllocCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Service alloc callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.16

Field Name : serviceAllocCb
Field Type : CounterBasedGauge64
Field Status : current
Description : Service alloc callback
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.15

Field Name : connNotExist
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn not exist
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.14

Field Name : eventFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Event failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.13

Field Name : queueDepthOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Queue depth over limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.12

Field Name : slbProxyServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.11

Field Name : slbProxyClientRst
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Client RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.10

Field Name : noMem
Field Type : CounterBasedGauge64
Field Status : current
Description : No memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.9

Field Name : errEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Error occurred
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.8

Field Name : wbufEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Ready to send data
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.7

Field Name : slbProxyServerFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Server FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.6

Field Name : slbProxyClientFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Client FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.5

Field Name : dataEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Data received
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.4

Field Name : estEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Connection established
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.3

Field Name : tcpEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP stack event
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.2

Field Name : num
Field Type : CounterBasedGauge64
Field Status : current
Description : Num
OID : 1.3.6.1.4.1.22610.2.4.10.108.54.1.1

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : macMovement
Field Type : CounterBasedGauge64
Field Status : current
Description : MAC movement
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.117

Field Name : tls12Tls13IgnoreReq
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS12-TLS13-Request-Per-Sec Limit ignored packets count
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.116

Field Name : tls12Tls13DropReq
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS12--TLS13-Request-Per-Sec Limit Drop at ingress
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.115

Field Name : tls12IgnoreReq
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS12-Request-Per-Sec Limit ignored packets count
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.114

Field Name : tls12DropReq
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS12-Request-Per-Sec Limit Drop at ingress
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.113

Field Name : tls13IgnoreReq
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS13-Request-Per-Sec Limit ignored packets count
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.112

Field Name : tls13DropReq
Field Type : CounterBasedGauge64
Field Status : current
Description : TLS13-Request-Per-Sec Limit Drop at ingress
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.111

Field Name : ipIcmpErrorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IP ICMP Error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.110

Field Name : closedPortSynDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Linux Closed Port SYN Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.109

Field Name : ppslIgnoreLimit
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Packet-Per-Sec Limit ignored packets count
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.108

Field Name : ppslDropIng
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet-Per-Sec Limit Drop at ingress
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.107

Field Name : ppslDropEgr
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet-Per-Sec Limit Drop at egress
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.106

Field Name : bwIgnoreLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : BW Limit ignored packets count
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.105

Field Name : ipv6NdiscDadPrefixMismatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 DAD on Advertise drop for prefix mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.104

Field Name : ipv6fragGreDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag gre Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.103

Field Name : unnumberedUnsupportedDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported protocol for unnumbered
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.102

Field Name : unnumberedNatError
Field Type : CounterBasedGauge64
Field Status : current
Description : Unnumbered NAT error
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.101

Field Name : serviceChainRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Chain Packets Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.100

Field Name : serviceChainSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Chain Packets Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.99

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : lacpTxIntfErrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : LACP interface error corrected
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.98

Field Name : devLinkDownArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to interface is down
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.97

Field Name : ipNotFoundArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to IP not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.96

Field Name : selfGratNatIpArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Self generated grat ARP PKT dropped for NAT IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.95

Field Name : selfGratArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Self generated grat ARP PKT dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.94

Field Name : scaleoutHairpinArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to scaleout hairpin checks
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.93

Field Name : inactiveNatPoolArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to inactive nat pool
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.92

Field Name : inactiveStaticNatPoolArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to inactive static nat pool
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.91

Field Name : virtualIpNotFoundArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to virtual IP not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.90

Field Name : scaleoutArpDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : ARP PKT dropped due to scaleout checks
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.89

Field Name : devBasedArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to interface state checks
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.88

Field Name : invalidSenderMacArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP PKT dropped due to invalid sender MAC
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.87

Field Name : invalidRxArpPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid ARP PKT Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.86

Field Name : ipFragSent
Field Type : CounterBasedGauge64
Field Status : current
Description : IP frag sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.85

Field Name : redirectSetupFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect connection setup failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.84

Field Name : redirectRevSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect succeeded in the rev direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.83

Field Name : redirectRevFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect failed in the rev direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.82

Field Name : redirectFwdSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect succeeded in the fwd direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.81

Field Name : redirectFwdFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Redirect failed in the fwd direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.80

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : ipfragIpipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Frag IPIP Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.79

Field Name : ipfragUdpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Frag UDP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.78

Field Name : ipfragTcpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Frag TCP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.77

Field Name : ipfragEsp
Field Type : CounterBasedGauge64
Field Status : current
Description : IP(ESP) Fragment Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.76

Field Name : ipfragOspf
Field Type : CounterBasedGauge64
Field Status : current
Description : IP(OSPF) Fragment Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.75

Field Name : ipfragIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : IP(ICMP) Fragment Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.74

Field Name : ipfragUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : IP(UDP) Fragment Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.73

Field Name : fwSmpZoneMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : FW SMP Zone Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.72

Field Name : urpfPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : URPF check packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.71

Field Name : spNonCtrlPktDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Shared IP mode non ctrl packet to linux drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.70

Field Name : ipv6NdiscOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 DAD Out-of-memory
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.69

Field Name : ipv6NdiscMacChanges
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 DAD MAC Changed
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.68

Field Name : ipv6NdiscDadAdverts
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 DAD on Adverts
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.67

Field Name : ipv6NdiscDadSolicits
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 DAD on Solicits
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.66

Field Name : ipip6JumboFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPIIPv6 Jumbo Frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.65

Field Name : ipv6JumboFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Jumbo Frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.64

Field Name : jumboFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Jumbo Frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.63

Field Name : mgmtSvcDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Management Service Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.62

Field Name : l4InCtrlCpu
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 In Ctrl CPU
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.61

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : ipv6fragEsp
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag ESP
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.60

Field Name : ipv6fragOspf
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag OSPF
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.59

Field Name : ipv6fragIcmp
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag ICMP
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.58

Field Name : ipv6fragTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag TCP
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.57

Field Name : maxArpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Max ARP Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.56

Field Name : fpgaErrorPkt2
Field Type : CounterBasedGauge64
Field Status : current
Description : FPGA Error PKT2
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.55

Field Name : fpgaErrorPkt1
Field Type : CounterBasedGauge64
Field Status : current
Description : FPGA Error PKT1
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.54

Field Name : ipv6NovlanfwdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 No L3 VLAN FWD Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.53

Field Name : ipv4NovlanfwdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 No L3 VLAN FWD Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.52

Field Name : ipFragTooMany
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : IP Fragment too many
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.51

Field Name : ipFragOversize
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Fragment oversize
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.50

Field Name : ipv6fragIpipDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag IPIP Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.49

Field Name : ipv6fragIpipOk
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag IPIP OKs
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.48

Field Name : ipv6fragTcpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag TCP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.47

Field Name : ipv6fragUdpDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag UDP Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.46

Field Name : ipv6fragUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 Frag UDP
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.45

Field Name : noIpDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : No IP Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.44

Field Name : ipv4Frag6rdDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Frag 6RD Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.43

Field Name : ipv4Frag6rdOk
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 Frag 6RD OK
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.42

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : ipDefragInvalidLen
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Invalid Length Frag
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.41

Field Name : ctrlSynRateDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN rate exceeded Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.40

Field Name : bpduSent
Field Type : CounterBasedGauge64
Field Status : current
Description : BPDUs Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.39

Field Name : bpduRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : BPDUs Received
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.38

Field Name : ipsecDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPSec Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.37

Field Name : tcpsynfinDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly TCP SYNFIN Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.36

Field Name : tcpsynfragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly SYN Frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.35

Field Name : tcpnoflagDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly TCP noFlag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.34

Field Name : allfragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly All Frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.33

Field Name : pingofdeathDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Anomaly PingDeath Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.32

Field Name : badpktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Pkt Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.31

Field Name : ipoptionsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly IP OPT Drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.30

Field Name : landDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly Land Attack Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.29

Field Name : ipfragReasmfails
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Fragment Reasm Fails
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.28

Field Name : ipfragReasmoks
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Fragment Reasm OKs
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.27

Field Name : ipfragOverload
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Frag Overload Drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.26

Field Name : ipfragTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Fragment Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.25

Field Name : ipfragOverlap
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Fragment Overlap
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.24

Field Name : ipfragTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : IP(TCP) Fragment Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.23

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : aclDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : ACL Denys
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.22

Field Name : ipDefrag
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Defrag
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.21

Field Name : incorrectLenDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Incorrect Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.20

Field Name : sportDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SPORT Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.19

Field Name : linkdownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Link Down Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.18

Field Name : ttlExceededDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TTL Exceeded Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.17

Field Name : unknownProtDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown Prot Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.16

Field Name : l4Process
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Process
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.15

Field Name : l3ForwardIpv6
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 IPv6 Forward
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.14

Field Name : l3ForwardIp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : L3 IP Forward
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.13

Field Name : l2Forward
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 Forward
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.12

Field Name : protDownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Prot Down Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.11

Field Name : ipv6NorouteDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv6 No Route Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.10

Field Name : ipv4NorouteDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : IPv4 No Route Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.9

Field Name : l2DefVlanDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 Default Vlan FWD Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.8

Field Name : vlanFlood
Field Type : CounterBasedGauge64
Field Status : current
Description : VLAN Flood
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.7

Field Name : rxArpResp
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP RESP Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.6

Field Name : rxArpReq
Field Type : CounterBasedGauge64
Field Status : current
Description : ARP REQ Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.5

Field Name : rxKernel
Field Type : CounterBasedGauge64
Field Status : current
Description : Received kernel
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.4

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : bwlDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : BW Limit Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.3

Field Name : licexpireDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : License Expire Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.2

Field Name : fwlb
Field Type : CounterBasedGauge64
Field Status : current
Description : FWLB
OID : 1.3.6.1.4.1.22610.2.4.10.108.53.1.1

Field Name : controlToSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : Control chn ssl
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.23

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Total POP3 Request
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.22

Field Name : clRequestErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RQ state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.21

Field Name : serverResponseErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv RESP state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.20

Field Name : serConnectingErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv CTNG state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.19

Field Name : clEstErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Client EST state erro
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.18

Field Name : insertTupleFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Serv Sel insert tuple fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.17

Field Name : smpV4Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel SMPv4 fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.16

Field Name : smpV6Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel SMPv6 fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.15

Field Name : rsvPersistConnFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel Persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.14

Field Name : badSequence
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Sequence
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.13

Field Name : unsupportedCommand
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.12

Field Name : requestDontCare
Field Type : CounterBasedGauge64
Field Status : current
Description : other cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.11

Field Name : stls
Field Type : CounterBasedGauge64
Field Status : current
Description : stls cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.10

Field Name : invalidStartLine
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid start line
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.9

Field Name : lineMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : request line freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.8

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.7

Field Name : snatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : source nat failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.6

Field Name : noRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : no route failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.5

Field Name : svrselFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.4

Field Name : total
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.3

Field Name : curr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.2

Field Name : num
Field Type : CounterBasedGauge64
Field Status : current
Description : Num
OID : 1.3.6.1.4.1.22610.2.4.10.108.52.1.1

Field Name : negativeError
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.55

Field Name : boundaryError
Field Type : CounterBasedGauge64
Field Status : current
Description : Boundary error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.54

Field Name : allocError
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Alloc error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.53

Field Name : reallocError
Field Type : CounterBasedGauge64
Field Status : current
Description : Realloc error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.52

Field Name : login
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Login cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.51

Field Name : startTls
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Start TLS cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.50

Field Name : capability
Field Type : CounterBasedGauge64
Field Status : current
Description : Capability cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.49

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Total FTP Request
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.48

Field Name : dataServConnectedErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Serv CTED error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.47

Field Name : dataServConnectingErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Serv CTNG error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.46

Field Name : dataConnStartErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Start state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.45

Field Name : clRequestErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RQ state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.44

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : serverResponseErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv RESP state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.43

Field Name : serConnectingErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv CTNG state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.42

Field Name : clEstErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Client EST state erro
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.41

Field Name : insertTuppleFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel insert tuple fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.40

Field Name : smpV4Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel SMPv4 fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.39

Field Name : smpV6Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel SMPv6 fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.38

Field Name : rsvPersistConnFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel Persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.37

Field Name : badSequence
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Sequence
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.36

Field Name : controlToSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : Control chn ssl
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.35

Field Name : controlToClear
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Control chn clear txt
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.34

Field Name : unsupportedCommand
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.33

Field Name : unsupportedProtValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PROT
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.32

Field Name : unsupportedPbszValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PBSZ
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.31

Field Name : adat
Field Type : CounterBasedGauge64
Field Status : current
Description : adat cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.30

Field Name : authUnsupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported auth
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.29

Field Name : dataTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.28

Field Name : dataCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Data Proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.27

Field Name : cantFindEpsv
Field Type : CounterBasedGauge64
Field Status : current
Description : cant find epsv
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.26

Field Name : epsv
Field Type : CounterBasedGauge64
Field Status : current
Description : epsv command
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.25

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : dataSendFail
Field Type : CounterBasedGauge64
Field Status : current
Description : data send fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.24

Field Name : dataServerConnFail
Field Type : CounterBasedGauge64
Field Status : current
Description : data svr conn fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.23

Field Name : smpCreateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : smp create fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.22

Field Name : pasvAddrNeServer
Field Type : CounterBasedGauge64
Field Status : current
Description : psv addr not equal to svr
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.21

Field Name : cantFindPasv
Field Type : CounterBasedGauge64
Field Status : current
Description : cant find pasv
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.20

Field Name : clientAuthTls
Field Type : CounterBasedGauge64
Field Status : current
Description : client auth tls
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.19

Field Name : requestDontCare
Field Type : CounterBasedGauge64
Field Status : current
Description : other cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.18

Field Name : port
Field Type : CounterBasedGauge64
Field Status : current
Description : port cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.17

Field Name : pasv
Field Type : CounterBasedGauge64
Field Status : current
Description : pasv cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.16

Field Name : pbsz
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : pbsz cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.15

Field Name : prot
Field Type : CounterBasedGauge64
Field Status : current
Description : prot cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.14

Field Name : authTls
Field Type : CounterBasedGauge64
Field Status : current
Description : auth tls cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.13

Field Name : invalidStartLine
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid start line
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.12

Field Name : lineMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : request line freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.11

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.10

Field Name : dataSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : data ssl force
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.9

Field Name : cc
Field Type : CounterBasedGauge64
Field Status : current
Description : clear ctrl port packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.8

Field Name : feat
Field Type : CounterBasedGauge64
Field Status : current
Description : feat packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.7

Field Name : snatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : source nat failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.6

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : noRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : no route failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.5

Field Name : svrselFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.4

Field Name : total
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.3

Field Name : curr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.2

Field Name : num
Field Type : CounterBasedGauge64
Field Status : current
Description : Num
OID : 1.3.6.1.4.1.22610.2.4.10.108.51.1.1

Field Name : cantFindEprt
Field Type : CounterBasedGauge64
Field Status : current
Description : cant find ep rt
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.64

Field Name : cantFindPort
Field Type : CounterBasedGauge64
Field Status : current
Description : cant find port
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.63

Field Name : ep rt
Field Type : CounterBasedGauge64
Field Status : current
Description : ep rt cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.62

Field Name : quit
Field Type : CounterBasedGauge64
Field Status : current
Description : quit cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.61

Field Name : pass
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : pass cmd

OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.60

Field Name : user

Field Type : CounterBasedGauge64

Field Status : current

Description : user cmd

OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.59

Field Name : site

Field Type : CounterBasedGauge64

Field Status : current

Description : site cmd

OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.58

Field Name : open

Field Type : CounterBasedGauge64

Field Status : current

Description : open cmd

OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.57

Field Name : dsFail

Field Type : CounterBasedGauge64

Field Status : current

Description : Host Domain Name isn't resolved

OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.56

Field Name : dsSucc

Field Type : CounterBasedGauge64

Field Status : current

Description : Host Domain Name is resolved

OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.55

Field Name : drop

Field Type : CounterBasedGauge64

Field Status : current

Description : Total FTP Drop

OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.54

Field Name : fwdToSg

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Forward to Service-group

OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.53

Field Name : fwdToInternet

Field Type : CounterBasedGauge64

Field Status : current

Description : Forward to Internet

OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.52

Field Name : authFail

Field Type : CounterBasedGauge64

Field Status : current

Description : Auth Failure

OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.51

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : authSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Auth Success
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.50

Field Name : authReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Auth Request
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.49

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Total FTP Request
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.48

Field Name : dataServConnectedErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Serv CTED error
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.47

Field Name : dataServConnectingErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Serv CTNG error
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.46

Field Name : dataConnStartErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Start state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.45

Field Name : clRequestErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RQ state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.44

Field Name : serverResponseErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv RESP state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.43

Field Name : serConnectingErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv CTNG state error
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.42

Field Name : clEstErr
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Client EST state erro
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.41

Field Name : insertTupleFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel insert tuple fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.40

Field Name : smpV4Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel SMPv4 fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.39

Field Name : smpV6Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel SMPv6 fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.38

Field Name : rsvPersistConnFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Serv Sel Persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.37

Field Name : badSequence
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Sequence
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.36

Field Name : controlToSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : Control chn ssl
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.35

Field Name : controlToClear
Field Type : CounterBasedGauge64
Field Status : current
Description : Control chn clear txt
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.34

Field Name : unsupportedCommand
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.33

Field Name : unsupportedProtValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PROT
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.32

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : unsupportedPbszValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported PBSZ
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.31

Field Name : adat
Field Type : CounterBasedGauge64
Field Status : current
Description : adat cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.30

Field Name : authUnsupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported auth
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.29

Field Name : dataTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.28

Field Name : dataCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Data Proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.27

Field Name : cantFindEpsv
Field Type : CounterBasedGauge64
Field Status : current
Description : cant find epsv
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.26

Field Name : epsv
Field Type : CounterBasedGauge64
Field Status : current
Description : epsv command
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.25

Field Name : dataSendFail
Field Type : CounterBasedGauge64
Field Status : current
Description : data send fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.24

Field Name : dataServerConnFail
Field Type : CounterBasedGauge64
Field Status : current
Description : data svr conn fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.23

Field Name : smpCreateFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : smp create fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.22

Field Name : pasvAddrNeServer
Field Type : CounterBasedGauge64
Field Status : current
Description : psv addr not equal to svr
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.21

Field Name : cantFindPasv
Field Type : CounterBasedGauge64
Field Status : current
Description : cant find pasv
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.20

Field Name : clientAuthTls
Field Type : CounterBasedGauge64
Field Status : current
Description : client auth tls
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.19

Field Name : requestDontCare
Field Type : CounterBasedGauge64
Field Status : current
Description : other cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.18

Field Name : slbFtpProxyPort
Field Type : CounterBasedGauge64
Field Status : current
Description : port cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.17

Field Name : pasv
Field Type : CounterBasedGauge64
Field Status : current
Description : pasv cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.16

Field Name : pbsz
Field Type : CounterBasedGauge64
Field Status : current
Description : pbsz cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.15

Field Name : prot
Field Type : CounterBasedGauge64
Field Status : current
Description : prot cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.14

Field Name : authTls
Field Type : CounterBasedGauge64
Field Status : current
Description : auth tls cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.13

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : invalidStartLine
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid start line
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.12

Field Name : lineMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : request line freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.11

Field Name : slbFtpProxyLineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.10

Field Name : dataSsl
Field Type : CounterBasedGauge64
Field Status : current
Description : data ssl force
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.9

Field Name : cc
Field Type : CounterBasedGauge64
Field Status : current
Description : clear ctrl port packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.8

Field Name : feat
Field Type : CounterBasedGauge64
Field Status : current
Description : feat packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.7

Field Name : slbFtpProxySnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : source nat failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.6

Field Name : slbFtpProxyNoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : no route failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.5

Field Name : slbFtpProxySvrSelFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.4

Field Name : slbFtpProxyTotal
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Total proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.3

Field Name : slbFtpProxyCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.2

Field Name : num
Field Type : CounterBasedGauge64
Field Status : current
Description : Num
OID : 1.3.6.1.4.1.22610.2.4.10.108.50.1.1

Field Name : httpPktsOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : fHTTP Out of Order packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.269

Field Name : httpServerRetx
Field Type : CounterBasedGauge64
Field Status : current
Description : Server Re-Tx fHTTP packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.268

Field Name : httpClientRetx
Field Type : CounterBasedGauge64
Field Status : current
Description : Client Re-Tx fHTTP packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.267

Field Name : httpPktsRetx
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot Re-Tx fHTTP packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.266

Field Name : httpPktsInSeq
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot In-seq fHTTP packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.265

Field Name : decompressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.264

Field Name : decompressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.263

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : skipInsertClientPort
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip Insert Client Port
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.262

Field Name : skipInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip Insert Client IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.261

Field Name : nonHttpBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Non-HTTP bypass
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.260

Field Name : fullProxyPut
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy PUT
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.259

Field Name : reqTrack
Field Type : CounterBasedGauge64
Field Status : current
Description : Method TRACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.258

Field Name : insertClientPort
Field Type : CounterBasedGauge64
Field Status : current
Description : Insert client Port
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.257

Field Name : reqOver5s
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time greater than equal to 5s
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.256

Field Name : req5s
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 5s
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.255

Field Name : req2s
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 2s
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.254

Field Name : req1s
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Rsp time less than 1s
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.253

Field Name : req500m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 500m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.252

Field Name : req200m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 200m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.251

Field Name : req100m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 100m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.250

Field Name : req50m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 50m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.249

Field Name : req20m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 20m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.248

Field Name : req10m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 10m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.247

Field Name : req5m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 5m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.246

Field Name : req2m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 2m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.245

Field Name : req1m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 1m
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.244

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : req500u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 500u
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.243

Field Name : req200u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 200u
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.242

Field Name : req100u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 100u
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.241

Field Name : req50u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 50u
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.240

Field Name : req20u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 20u
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.239

Field Name : req10u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 10u
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.238

Field Name : chunkBad
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Chunk
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.223

Field Name : pconnConnectingFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn conn failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.222

Field Name : pconnConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.221

Field Name : pconnConnecting
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : pconn connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.220

Field Name : chunkSzGt4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk greater than 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.219

Field Name : chunkSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.218

Field Name : chunkSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.217

Field Name : chunkSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.216

Field Name : chunkSz512
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 512
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.215

Field Name : rspSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp greater than 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.214

Field Name : rspSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.213

Field Name : rspSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 64K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.212

Field Name : rspSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 32K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.211

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : rspSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 16K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.210

Field Name : rspSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 8K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.209

Field Name : rspSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.208

Field Name : rspSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.207

Field Name : rspSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.206

Field Name : reqSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req greater than 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.205

Field Name : reqSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.204

Field Name : reqSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 64K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.203

Field Name : reqSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 32K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.202

Field Name : reqSz16k
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Description : Req less than equal to 16K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.201

Field Name : reqSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 8K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.200

Field Name : reqSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.199

Field Name : reqSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.198

Field Name : reqSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.197

Field Name : reqHttp10Keepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : 1.0 Keepalive
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.196

Field Name : closeOnDdos
Field Type : CounterBasedGauge64
Field Status : current
Description : Close on DDoS
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.195

Field Name : cacheRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP req (cache succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.194

Field Name : compressRatioTooHigh
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress ratio too high
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.193

Field Name : compressRespNoClOrCe
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress resp no CL/CE
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.192

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : compressResplTMin
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress resp less than min
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.191

Field Name : compressNoContentType
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress no cont type
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.190

Field Name : compressContentTypeExcluded
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress cont type excl
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.189

Field Name : compressRespAlreadyCompressed
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp already compressed
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.188

Field Name : compressDelAcceptEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress del accept enc
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.187

Field Name : compressRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress req
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.186

Field Name : reqChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : Req chunk encoding
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.185

Field Name : rspChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp chunk encoding
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.184

Field Name : rspContentLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp content len
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.183

Field Name : reqContentLen
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Req content len
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.182

Field Name : reqUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Method UNKNOWN
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.181

Field Name : reqDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Method DELETE
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.180

Field Name : reqConnect
Field Type : CounterBasedGauge64
Field Status : current
Description : Method CONNECT
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.179

Field Name : reqOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : Method OPTIONS
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.178

Field Name : reqTrace
Field Type : CounterBasedGauge64
Field Status : current
Description : Method TRACE
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.177

Field Name : reqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : Method POST
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.176

Field Name : reqPut
Field Type : CounterBasedGauge64
Field Status : current
Description : Method PUT
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.175

Field Name : reqHead
Field Type : CounterBasedGauge64
Field Status : current
Description : Method HEAD
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.174

Field Name : reqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : Method GET
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.173

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : responseHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp 1.1
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.172

Field Name : responseHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp 1.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.171

Field Name : reqHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : Request 1.1
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.170

Field Name : reqHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : Request 1.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.169

Field Name : responseUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.168

Field Name : response6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 6XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.167

Field Name : response510
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 510
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.166

Field Name : response509
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 509
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.165

Field Name : response508
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 508
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.164

Field Name : response507
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Status code 507
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.163

Field Name : response506
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 506
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.162

Field Name : response505
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 505
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.161

Field Name : response504
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 504
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.160

Field Name : response503
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 503
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.159

Field Name : response502
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 502
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.158

Field Name : response501
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 501
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.157

Field Name : response500
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 500
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.156

Field Name : response5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 5XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.155

Field Name : response450
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 450
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.154

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : response449
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 449
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.153

Field Name : response426
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 426
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.152

Field Name : response425
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 425
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.151

Field Name : response424
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 424
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.150

Field Name : response423
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 423
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.149

Field Name : response422
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 422
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.148

Field Name : response418
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 418
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.147

Field Name : response417
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 417
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.146

Field Name : response416
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 416
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.145

Field Name : response415
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Status code 415
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.144

Field Name : response414
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 414
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.143

Field Name : response413
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 413
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.142

Field Name : response412
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 412
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.141

Field Name : response411
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 411
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.140

Field Name : response410
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 410
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.139

Field Name : response409
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 409
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.138

Field Name : response408
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 408
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.137

Field Name : response407
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 407
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.136

Field Name : response406
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 406
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.135

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : response405
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 405
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.134

Field Name : response404
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 404
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.133

Field Name : response403
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 403
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.132

Field Name : response402
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 402
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.131

Field Name : response401
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 401
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.130

Field Name : response400
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 400
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.129

Field Name : response4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 4XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.128

Field Name : response307
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 307
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.127

Field Name : response306
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 306
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.126

Field Name : response305
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Status code 305
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.125

Field Name : response304
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 304
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.124

Field Name : response303
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 303
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.123

Field Name : response302
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 302
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.122

Field Name : response301
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 301
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.121

Field Name : response300
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 300
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.120

Field Name : response3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 3XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.119

Field Name : response207
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 207
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.118

Field Name : response206
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 206
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.117

Field Name : response205
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 205
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.116

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : response204
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 204
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.115

Field Name : response203
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 203
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.114

Field Name : response202
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 202
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.113

Field Name : response201
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 201
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.112

Field Name : response200
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 200
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.111

Field Name : response2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 2XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.110

Field Name : response102
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 102
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.109

Field Name : response101
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 101
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.108

Field Name : response100
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 100
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.107

Field Name : response1xx
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Description : Status code 1XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.106

Field Name : compressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.104

Field Name : compressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.102

Field Name : serverReselFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server re-select failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.101

Field Name : staleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : Stale sess
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.100

Field Name : pktsRetransPush
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans PSH
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.99

Field Name : pktsRetransRst
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.98

Field Name : pktsRetransFin
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.97

Field Name : pktsRetransAckFinwait
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans ACK FWAIT
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.96

Field Name : pktsRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets retrans
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.95

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : pktsOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.94

Field Name : connectingAck
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.93

Field Name : connectingRstOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting RST ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.92

Field Name : connectingRstRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting RST retrans
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.91

Field Name : connectingRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.90

Field Name : connectingFinOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting FIN ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.89

Field Name : connectingFinRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting FIN retrans
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.88

Field Name : connectingFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.87

Field Name : clientReqUnexpFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : Client req unexp flags
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.86

Field Name : asmSetcookieHeaderFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Asm set-cookie hdr fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.85

Field Name : asmSetcookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Assemble set-cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.84

Field Name : asmCookieHeaderFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Asm cookie header fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.83

Field Name : asmCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Assemble cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.82

Field Name : parseSetcookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse set-cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.81

Field Name : parseCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.80

Field Name : hugeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Huge cookie headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.79

Field Name : hugeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : Huge cookies
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.78

Field Name : largeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Large cookie headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.77

Field Name : largeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : Large cookies
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.76

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : negativeRespRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative response remain
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.75

Field Name : negativeReqRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative request remain
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.74

Field Name : insertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Insert client IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.73

Field Name : headerDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Header delete
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.72

Field Name : headerInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : Header insert
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.71

Field Name : wrongRespHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Wrong response header
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.70

Field Name : headerNameTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Header name too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.69

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.68

Field Name : tooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : Too many headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.67

Field Name : invalidHeader
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Invalid header
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.66

Field Name : serverRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - response
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.65

Field Name : serverRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.64

Field Name : serverRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.63

Field Name : serverRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - request
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.62

Field Name : clientRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - response
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.61

Field Name : clientRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.60

Field Name : clientRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.59

Field Name : clientRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - request
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.58

Field Name : aflexLbReselectOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex lb reselect (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.57

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : aflexLbReselect
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex lb reselect
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.56

Field Name : aflexRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex http retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.55

Field Name : retry503
Field Type : CounterBasedGauge64
Field Status : current
Description : Retry on 503
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.54

Field Name : lbSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Normal LB switch. (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.53

Field Name : hostSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Host switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.52

Field Name : urlSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : URL switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.51

Field Name : httpPolicySwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Policy switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.50

Field Name : aflexSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.49

Field Name : cookieSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.48

Field Name : l4SwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : L4 switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.47

Field Name : lbSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Normal LB switch. (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.46

Field Name : hostSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Host switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.45

Field Name : urlSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : URL switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.44

Field Name : httpPolicySwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Policy switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.43

Field Name : aflexSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.42

Field Name : cookieSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.41

Field Name : l4SwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.40

Field Name : lbSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Normal LB switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.39

Field Name : hostSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Host switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.38

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : urlSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : URL switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.37

Field Name : httpPolicySwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Policy switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.36

Field Name : aflexSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.35

Field Name : cookieSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.34

Field Name : l4Switching
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.33

Field Name : reqRateOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Request rate over limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.32

Field Name : reqOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Request over limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.31

Field Name : fullProxyFpgaErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy fpga err
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.30

Field Name : fullProxyPipeline
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy pipeline
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.29

Field Name : fullProxyPost
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Full proxy POST
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.28

Field Name : fullProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy tot
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.27

Field Name : tcpoutrst
Field Type : CounterBasedGauge64
Field Status : current
Description : Out RSTs
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.26

Field Name : slbFastHttpProxySnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.25

Field Name : newSvrconn
Field Type : CounterBasedGauge64
Field Status : current
Description : Server conn made
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.24

Field Name : svrPremClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Server premature close
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.23

Field Name : serverResel
Field Type : CounterBasedGauge64
Field Status : current
Description : Server reselection
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.22

Field Name : slbFastHttpProxyReqOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.21

Field Name : slbFastHttpProxyReqRetran
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets retrans
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.20

Field Name : fwdreqdataFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req data fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.19

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : fwdreqFailTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.18

Field Name : fwdreqFailServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - server
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.17

Field Name : fwdreqFailPersist
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - persist
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.16

Field Name : fwdreqFailRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - route
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.15

Field Name : fwdreqFailRport
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - rport
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.14

Field Name : fwdreqFailBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - buff
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.13

Field Name : fwdreqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.12

Field Name : slbFastHttpProxySrvSelFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.11

Field Name : parsereqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse req fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.10

Field Name : notuple
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : No tuple error
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.9

Field Name : slbFastHttpProxyServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.8

Field Name : slbFastHttpProxyClientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.7

Field Name : noproxy
Field Type : CounterBasedGauge64
Field Status : current
Description : No proxy error
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.6

Field Name : reqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP requests(succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.5

Field Name : slbFastHttpProxyReq
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.4

Field Name : slbFastHttpProxyTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.3

Field Name : slbFastHttpProxyCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.2

Field Name : num
Field Type : CounterBasedGauge64
Field Status : current
Description : Num
OID : 1.3.6.1.4.1.22610.2.4.10.108.49.1.1

Field Name : fastPathL2Reroute
Field Type : CounterBasedGauge64
Field Status : current
Description : Fast Path L2 Reroute
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.138

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : fastPathReroute
Field Type : CounterBasedGauge64
Field Status : current
Description : Fast Path Reroute
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.137

Field Name : pbslbEntryLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : pbslb entry limit Exceed
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.136

Field Name : slbGtpProxyRetxRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy retx requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.135

Field Name : slbGtpProxySmpFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy session helper freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.134

Field Name : slbGtpProxySmpFreeNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy session helper not found during cleanup
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.133

Field Name : slbGtpProxySmpCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy helper session created
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.132

Field Name : slbGtpProxySmpCreationFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy helper session creation failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.131

Field Name : slbGtpProxyCProcessLocalRr
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy messageprocessed locally on RR
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.130

Field Name : slbGtpProxySmpNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy helper session not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.129

Field Name : slbGtpProxySmpMatch
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : SLB GTP proxy helper session found
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.128

Field Name : slbGtpProxyPktRcvRr
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB GTP proxy packet received on RR
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.127

Field Name : proxyProtDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : PROXY protocol drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.126

Field Name : proxyProtError
Field Type : CounterBasedGauge64
Field Status : current
Description : PROXY protocol error
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.125

Field Name : proxyHeaderRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : PROXY protocol header retransmitted
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.124

Field Name : proxyHeaderInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : PROXY protocol header inserted
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.123

Field Name : snatForcePreserveFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Snat port preserve freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.122

Field Name : snatForcePreserveAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Snat port preserve allocated
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.121

Field Name : snatPortOverloadFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Snat port overload fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.120

Field Name : reselectSvrselffail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server reselect failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.119

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : gtpCInvalidMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : Non Create Session/PDP Context Request/Response Received on GTP VIP
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.118

Field Name : gtpCInvalidHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Header Received on GTP VIP
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.117

Field Name : gtpCInvalidPort
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Packet Received on GTP VIP
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.116

Field Name : tcpConnectionsClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Connections Closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.115

Field Name : rateDropResetUnkn
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate Drop reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.114

Field Name : dnssecSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : DNSSEC SG switch
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.113

Field Name : serverDownDel
Field Type : CounterBasedGauge64
Field Status : current
Description : Server Down Del switch
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.112

Field Name : dnsIdSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS query id switch
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.111

Field Name : synreceivedHw
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN (HW SYN cookie)
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.110

Field Name : skipInsertClientIp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Skip Insert-client-ip
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.109

Field Name : syncookieBuffQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN cookie buff queue
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.108

Field Name : syncookieBuffDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN cookie buff drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.107

Field Name : synRate
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN rate per sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.106

Field Name : synattack
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 SYN attack
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.105

Field Name : tcpEst
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 TCP Established
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.104

Field Name : outSeqAckDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of sequence ACK drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.103

Field Name : udpRespOneplus
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP rsps
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.102

Field Name : udpReqOneplus
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP reqs
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.101

Field Name : udpRespMoreReq
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP rsps greater than reqs
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.100

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : udpReqMoreResp
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP req greater than rspi
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.99

Field Name : udpReqRespNotmatch
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP req/rsp not match
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.98

Field Name : udpReqOneOneplusResp
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP req rspi
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.97

Field Name : udpReqOneplusNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 UDP reqs no rsp
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.96

Field Name : tcpRevRst
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rev RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.95

Field Name : tcpFwdRst
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv fwd RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.94

Field Name : tcpRevAckfin
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rev FIN|ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.93

Field Name : tcpRevFinDup
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rev FIN dup
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.92

Field Name : tcpFwdFinDup
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv fwd FIN dup
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.91

Field Name : tcpRexmitSynackDelq
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : L4 rcv rexmit SYN|ACK DQ
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.90

Field Name : tcpRexmitSynack
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rexmit SYN|ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.89

Field Name : tcpRexmitSynDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rexmit SYN (delq)
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.88

Field Name : tcpRexmitSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rexmit SYN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.87

Field Name : tcpSessNoestSsynXmitAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : no-Est SSYN snt aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.86

Field Name : tcpSessNoestCsynRcvAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : no-Est CSYN rcv aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.85

Field Name : tcpSessNoestAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP no-Est Sess aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.84

Field Name : tcpSynRcvRst
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv RST on SYN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.83

Field Name : tcpSynRcvAck
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv ACK on SYN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.82

Field Name : tcpAxRexmitSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 AX re-xmit SYN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.81

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : statelessConnTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 stateless Conn TO
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.80

Field Name : svrSynHandshakeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 server handshake fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.79

Field Name : concurrentConnExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : L3V Conn Limit Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.78

Field Name : sslWatermarkDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL TPT-Watermark drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.77

Field Name : sslTptExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL TPT exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.76

Field Name : sslCpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.75

Field Name : l7CpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.74

Field Name : natCpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.73

Field Name : l4CpsExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 CPS exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.72

Field Name : bwWatermarkDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : BW-Watermark drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.71

Field Name : bwRateLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : BW-Limit Exceed drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.70

Field Name : tcpothersFlagsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Other Flags Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.69

Field Name : tcpsynDataDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN With Data Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.68

Field Name : portPreserveSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Port Preserve Succ
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.67

Field Name : portPreserveAttempt
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT Port Preserve Try
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.66

Field Name : l3Dsr
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 DSR received
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.65

Field Name : l2Dsr
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 DSR received
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.64

Field Name : ignoreMsl
Field Type : CounterBasedGauge64
Field Status : current
Description : ignore msl
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.63

Field Name : resetL7OnFailover
Field Type : CounterBasedGauge64
Field Status : current
Description : RST L7 on failover
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.62

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : resetUnknownConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Reset unknown conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.61

Field Name : noResourceDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : No resource drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.60

Field Name : anomalyPbslbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly pbslb drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.59

Field Name : anomalyBadContent
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly bad content
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.58

Field Name : anomalyZeroWin
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly zero window
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.57

Field Name : anomalyOutSeq
Field Type : CounterBasedGauge64
Field Status : current
Description : Anomaly out of sequence
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.56

Field Name : tcpInvalidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP invalid drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.55

Field Name : dnsPolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Policy Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.54

Field Name : fastAgingReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Fast aging reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.53

Field Name : fastAgingSet
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Fast aging set
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.52

Field Name : autoReassign
Field Type : CounterBasedGauge64
Field Status : current
Description : Auto-reselect server
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.51

Field Name : inbandHmReassign
Field Type : CounterBasedGauge64
Field Status : current
Description : Inband HM reassign
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.50

Field Name : inbandHmRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : Inband HM retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.49

Field Name : dropGslb
Field Type : CounterBasedGauge64
Field Status : current
Description : Drop GSLB
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.48

Field Name : throttleSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN Throttle
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.47

Field Name : udpNoSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP no SLB
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.46

Field Name : tcpNoSlb
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP no SLB
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.45

Field Name : otherSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Other Session aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.44

Field Name : udpSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Session aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.43

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : tcpSessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Session aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.42

Field Name : sessAgedOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Session aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.41

Field Name : dropAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.40

Field Name : proxyNosockDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Proxy no sock drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.39

Field Name : connRateLimitReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn rate limit resets
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.38

Field Name : connRateLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn rate limit drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.37

Field Name : connlimitReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Limit resets
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.36

Field Name : connlimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Limit drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.35

Field Name : nosynDropAck
Field Type : CounterBasedGauge64
Field Status : current
Description : No SYN pkt drops - ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.34

Field Name : nosynDropRst
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : No SYN pkt drops - RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.33

Field Name : nosynDropFin
Field Type : CounterBasedGauge64
Field Status : current
Description : No SYN pkt drops - FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.32

Field Name : nosynDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : No SYN pkt drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.31

Field Name : noVportDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : vport not matching drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.30

Field Name : novportDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : NAT no session drops
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.29

Field Name : syncookiescheckfailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN cookie failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.28

Field Name : smartNatIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Auto NAT id mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.27

Field Name : snatIcmpNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT ICMP No Match
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.26

Field Name : snatIcmpErrorProcess
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT ICMP Process
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.25

Field Name : snatNoRevRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT no rev route
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.24

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : snatNoFwdRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT no fwd route
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.23

Field Name : snatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.22

Field Name : noroute
Field Type : CounterBasedGauge64
Field Status : current
Description : IP out noroute
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.21

Field Name : svrselfail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server sel failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.20

Field Name : outrstTcpproxy
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out RST TCP proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.19

Field Name : synStaleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN stale sess drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.18

Field Name : outrstStaleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out RST stale sess
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.17

Field Name : outrstAflex
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out RST aFlex
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.16

Field Name : outrstAckAttack
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out RST ACK attack
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.15

Field Name : outrstBroker
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : TCP out RST L4 proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.14

Field Name : outrstNosyn
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out RST no SYN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.13

Field Name : outrst
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.12

Field Name : syncookiestentfailed
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN cookie snt fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.11

Field Name : syncookiestentTs
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN cookie snt ts
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.10

Field Name : syncookiestent
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN cookie snt
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.9

Field Name : inudp
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP received
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.8

Field Name : tcpFwdAckfin
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv fwd FIN|ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.7

Field Name : tcpFwdFin
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv fwd FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.6

Field Name : tcpRevFin
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rev FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.5

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : tcpRevLastAck
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv rev last ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.4

Field Name : tcpFwdLastAck
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 rcv fwd last ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.3

Field Name : synreceived
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN received
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.2

Field Name : intcp
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP received
OID : 1.3.6.1.4.1.22610.2.4.10.108.48.1.1

Field Name : localLogDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Local log dropped due to rate-limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.15

Field Name : noRepeatMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : No repeat message
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.14

Field Name : connAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Log-session alloc fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.13

Field Name : freeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Log-session free
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.12

Field Name : allocConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Log-session alloc
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.11

Field Name : buffSendFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Buffer send fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.10

Field Name : slbRateLimitLogNoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : No route
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.9

Field Name : buffAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Buffer alloc fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.8

Field Name : msgTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : Log message too big
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.7

Field Name : remoteLogRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Remote rate (per sec)
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.6

Field Name : localLogRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Local rate (per sec)
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.5

Field Name : remoteLogMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : Remote log messages
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.4

Field Name : localLogMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : Local log messages
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.3

Field Name : totalLogMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : Total log messages
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.2

Field Name : totalLogTimes
Field Type : CounterBasedGauge64
Field Status : current
Description : Total log times
OID : 1.3.6.1.4.1.22610.2.4.10.108.47.1.1

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : transactionLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : Transaction limited
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.359

Field Name : reqHttp11NewProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Request 1.1 (new proxy)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.358

Field Name : delH2cHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : H2C header deletion
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.357

Field Name : upgradeToNewProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : H2C upgrade
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.356

Field Name : httpAllowedMethods
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP allowed methods
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.355

Field Name : httpDisallowedMethods
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP disallowed methods
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.354

Field Name : http2ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP2 client idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.353

Field Name : http1ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP1 client idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.352

Field Name : headerFilterRuleHit
Field Type : CounterBasedGauge64
Field Status : current
Description : Hit header filter rule
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.351

Field Name : responseHttp3
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Resp 3.0

OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.350

Field Name : reqHttp3

Field Type : CounterBasedGauge64

Field Status : current

Description : Request 3.0

OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.349

Field Name : h2upWithHostAndAuth

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP2 with host header and authority header

OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.348

Field Name : getAndPayload

Field Type : CounterBasedGauge64

Field Status : current

Description : GET method with content-length header or transfer-encoding header

OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.347

Field Name : transferEncodingAndContentLength

Field Type : CounterBasedGauge64

Field Status : current

Description : Transfer-encoding header with Content-Length header

OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.346

Field Name : multipleTransferEncoding

Field Type : CounterBasedGauge64

Field Status : current

Description : Multiple transfer-encoding headers

OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.345

Field Name : multipleContentLength

Field Type : CounterBasedGauge64

Field Status : current

Description : Multiple content-length headers

OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.344

Field Name : h2upWithTransferEncoding

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP2 with transfer-encoding header

OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.343

Field Name : malformedH2upSchemeValue

Field Type : CounterBasedGauge64

Field Status : current

Description : Malformed HTTP2 scheme value

OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.342

Field Name : malformedH2upHeaderValue

Field Type : CounterBasedGauge64

Field Status : current

Description : Malformed HTTP2 header value

OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.341

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : h2upContentLengthAlias
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP2 content length alias
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.340

Field Name : compressRspTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress req
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.339

Field Name : compressRspBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress req with brotli
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.338

Field Name : decompressionAfterTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.336

Field Name : decompressionBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.335

Field Name : decompressionAfterBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after brotli decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.334

Field Name : decompressionBeforeBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before brotli decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.333

Field Name : compressionAfterTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.332

Field Name : compressionBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.331

Field Name : compressionAfterBr
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Tot data after brotli compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.330

Field Name : compressionBeforeBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before brotli compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.329

Field Name : dohDnsRespRcodeOther
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode OTHER
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.328

Field Name : dohDnsRespRcodeNotzone
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode NOTZONE
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.327

Field Name : dohDnsRespRcodeNotauth
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode NOTAUTH
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.326

Field Name : dohDnsRespRcodeNxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode NXRRSET
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.325

Field Name : dohDnsRespRcodeYxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode YXRRSET
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.324

Field Name : dohDnsRespRcodeYxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode YXDOMAIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.323

Field Name : dohDnsRespRcodeRefuse
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode REFUSE
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.322

Field Name : dohDnsRespRcodeErrType
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode ERR_TYPE
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.321

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : dohDnsRespRcodeErrName
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode ERR_NAME
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.320

Field Name : dohDnsRespRcodeErrServer
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode ERR_SERVER
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.319

Field Name : dohDnsRespRcodeErrFormat
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Response rcode ERR_FORMAT
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.318

Field Name : dohDnsMalformedQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH DNS Malformed Query
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.317

Field Name : dohPostPayloadTooLarge
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH POST Payload too large
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.316

Field Name : dohGetUriTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH GET URI too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.315

Field Name : dohRetryWTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Retry with TCP SG
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.314

Field Name : dohServSelFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Server Select Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.313

Field Name : dohRespTcpFrgs
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH TCP Frags Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.312

Field Name : dohRespUdpFrgs
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Description : DoH UDP Frags Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.311

Field Name : dohRespQueFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Resp queue failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.310

Field Name : dohRespHeaderAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Resp hdr alloc failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.309

Field Name : dohRespSetupFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Response setup failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.308

Field Name : dohDnsQueryTypeOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type Others
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.307

Field Name : dohDnsQueryTypeSoa
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type SOA
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.306

Field Name : dohDnsQueryTypeMx
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type MX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.305

Field Name : dohDnsQueryTypeSrv
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type SRV
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.304

Field Name : dohDnsQueryTypeAny
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type ANY
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.303

Field Name : dohDnsQueryTypeCname
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type CNAME
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.302

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : dohDnsQueryTypeNs
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type NS
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.301

Field Name : dohDnsQueryTypeAaaa
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type AAAA
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.300

Field Name : dohDnsQueryTypeA
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Query type A
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.299

Field Name : dohQueryTimeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH serv Query timed out
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.298

Field Name : dohUdpSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH serv UDP DNS send failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.297

Field Name : dohTcpSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH serv TCP DNS send failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.296

Field Name : dohNonDohMethod
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Non DoH HTTP request method rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.295

Field Name : dohPostPayloadExtractFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH POST payload extract failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.294

Field Name : dohPostPayloadNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH POST payload not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.293

Field Name : dohPostContentTypeMismatch
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : DoH POST content-type not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.292

Field Name : dohGetBase64DecodeFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH GET base64url decode failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.291

Field Name : dohGetDnsArgFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH GET dns arg not found in uri
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.290

Field Name : dohPathNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH URI Path not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.289

Field Name : dohSnatFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Source NAT failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.288

Field Name : dohReqTcpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH TCP Retry failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.287

Field Name : dohReqTcpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH TCP Retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.286

Field Name : dohReqUdpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH UDP Retry failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.285

Field Name : dohReqUdpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH UDP Retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.284

Field Name : dohMallocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Memory alloc failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.283

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : dohRespSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Response Send Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.282

Field Name : dohReqSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Request Send Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.281

Field Name : dohTcpDnsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH TCP DNS Responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.280

Field Name : dohTcpDnsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH TCP DNS Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.279

Field Name : dohUdpDnsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH UDP DNS Responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.278

Field Name : dohUdpDnsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH UDP DNS Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.277

Field Name : dohTcResp
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH TC Responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.276

Field Name : dohResp
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.275

Field Name : dohNonDohReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH non DoH POST Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.274

Field Name : dohNonDohReqGet
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : DoH non DoH GET Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.273

Field Name : dohNonDohReq
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH non DoH Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.272

Field Name : dohReqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH POST Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.271

Field Name : dohReqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH GET Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.270

Field Name : dohReq
Field Type : CounterBasedGauge64
Field Status : current
Description : DoH Requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.269

Field Name : reqTimeoutClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Close on Req Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.268

Field Name : reqTimeoutRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : Retry on Req Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.267

Field Name : responseHttp2
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp 2.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.266

Field Name : reqHttp2
Field Type : CounterBasedGauge64
Field Status : current
Description : Request 2.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.265

Field Name : decompressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.264

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : decompressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before decompress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.263

Field Name : nonHttpBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Non-HTTP bypass
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.261

Field Name : reqEnterSsli
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP requests enter SSLi
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.260

Field Name : connectReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP CONNECT requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.259

Field Name : reqTrack
Field Type : CounterBasedGauge64
Field Status : current
Description : Method TRACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.258

Field Name : insertClientPort
Field Type : CounterBasedGauge64
Field Status : current
Description : Insert client Port
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.257

Field Name : reqOver5s
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time greater than equal to 5s
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.256

Field Name : req5s
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 5s
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.255

Field Name : req2s
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 2s
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.254

Field Name : req1s
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Rsp time less than 1s
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.253

Field Name : req500m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 500m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.252

Field Name : req200m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 200m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.251

Field Name : req100m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 100m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.250

Field Name : req50m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 50m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.249

Field Name : req20m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 20m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.248

Field Name : req10m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 10m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.247

Field Name : req5m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 5m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.246

Field Name : req2m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 2m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.245

Field Name : req1m
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 1m
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.244

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : req500u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 500u
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.243

Field Name : req200u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 200u
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.242

Field Name : req100u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 100u
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.241

Field Name : req50u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 50u
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.240

Field Name : req20u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 20u
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.239

Field Name : req10u
Field Type : CounterBasedGauge64
Field Status : current
Description : Rsp time less than 10u
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.238

Field Name : chunkBad
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Chunk
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.223

Field Name : pconnConnectingFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn conn failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.222

Field Name : pconnConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : pconn connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.221

Field Name : pconnConnecting
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : pconn connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.220

Field Name : chunkSzGt4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk greater than 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.219

Field Name : chunkSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.218

Field Name : chunkSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.217

Field Name : chunkSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.216

Field Name : chunkSz512
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk less than equal to 512
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.215

Field Name : rspSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp greater than 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.214

Field Name : rspSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.213

Field Name : rspSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 64K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.212

Field Name : rspSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 32K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.211

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : rspSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 16K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.210

Field Name : rspSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 8K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.209

Field Name : rspSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.208

Field Name : rspSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.207

Field Name : rspSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp less than equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.206

Field Name : reqSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req greater than 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.205

Field Name : reqSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 256K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.204

Field Name : reqSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 64K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.203

Field Name : reqSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 32K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.202

Field Name : reqSz16k
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Description : Req less than equal to 16K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.201

Field Name : reqSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 8K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.200

Field Name : reqSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 4K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.199

Field Name : reqSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 2K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.198

Field Name : reqSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : Req less than equal to 1K
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.197

Field Name : reqHttp10Keepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : 1.0 Keepalive
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.196

Field Name : slbHttpProxyCloseOnDdos
Field Type : CounterBasedGauge64
Field Status : current
Description : Close on DDoS
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.195

Field Name : cacheRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP req (cache succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.194

Field Name : compressRatioTooHigh
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress ratio too high
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.193

Field Name : compressRespNoClOrCe
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress resp no CL/CE
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.192

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : compressResplTMin
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress resp less than min
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.191

Field Name : compressNoContentType
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress no cont type
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.190

Field Name : compressContentTypeExcluded
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress cont type excl
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.189

Field Name : compressRespAlreadyCompressed
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp already compressed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.188

Field Name : compressDelAcceptEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress del accept enc
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.187

Field Name : compressRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : Compress req
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.186

Field Name : reqChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : Req chunk encoding
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.185

Field Name : rspChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp chunk encoding
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.184

Field Name : rspContentLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp content len
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.183

Field Name : reqContentLen
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Req content len
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.182

Field Name : reqUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Method UNKNOWN
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.181

Field Name : reqDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Method DELETE
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.180

Field Name : reqConnect
Field Type : CounterBasedGauge64
Field Status : current
Description : Method CONNECT
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.179

Field Name : reqOptions
Field Type : CounterBasedGauge64
Field Status : current
Description : Method OPTIONS
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.178

Field Name : reqTrace
Field Type : CounterBasedGauge64
Field Status : current
Description : Method TRACE
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.177

Field Name : reqPost
Field Type : CounterBasedGauge64
Field Status : current
Description : Method POST
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.176

Field Name : reqPut
Field Type : CounterBasedGauge64
Field Status : current
Description : Method PUT
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.175

Field Name : reqHead
Field Type : CounterBasedGauge64
Field Status : current
Description : Method HEAD
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.174

Field Name : reqGet
Field Type : CounterBasedGauge64
Field Status : current
Description : Method GET
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.173

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : responseHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp 1.1
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.172

Field Name : responseHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp 1.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.171

Field Name : reqHttp11
Field Type : CounterBasedGauge64
Field Status : current
Description : Request 1.1
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.170

Field Name : reqHttp10
Field Type : CounterBasedGauge64
Field Status : current
Description : Request 1.0
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.169

Field Name : responseUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.168

Field Name : response6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 6XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.167

Field Name : response510
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 510
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.166

Field Name : response509
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 509
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.165

Field Name : response508
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 508
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.164

Field Name : response507
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Status code 507
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.163

Field Name : response506
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 506
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.162

Field Name : response505
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 505
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.161

Field Name : response504
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 504
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.160

Field Name : response503
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 503
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.159

Field Name : response502
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 502
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.158

Field Name : response501
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 501
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.157

Field Name : response500
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 500
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.156

Field Name : response5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 5XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.155

Field Name : response450
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 450
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.154

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : response449
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 449
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.153

Field Name : response426
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 426
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.152

Field Name : response425
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 425
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.151

Field Name : response424
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 424
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.150

Field Name : response423
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 423
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.149

Field Name : response422
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 422
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.148

Field Name : response418
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 418
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.147

Field Name : response417
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 417
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.146

Field Name : response416
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 416
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.145

Field Name : response415
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Status code 415
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.144

Field Name : response414
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 414
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.143

Field Name : response413
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 413
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.142

Field Name : response412
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 412
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.141

Field Name : response411
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 411
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.140

Field Name : response410
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 410
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.139

Field Name : response409
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 409
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.138

Field Name : response408
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 408
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.137

Field Name : response407
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 407
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.136

Field Name : response406
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 406
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.135

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : response405
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 405
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.134

Field Name : response404
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 404
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.133

Field Name : response403
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 403
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.132

Field Name : response402
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 402
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.131

Field Name : response401
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 401
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.130

Field Name : response400
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 400
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.129

Field Name : response4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 4XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.128

Field Name : response307
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 307
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.127

Field Name : response306
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 306
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.126

Field Name : response305
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Status code 305
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.125

Field Name : response304
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 304
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.124

Field Name : response303
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 303
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.123

Field Name : response302
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 302
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.122

Field Name : response301
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 301
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.121

Field Name : response300
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 300
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.120

Field Name : response3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 3XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.119

Field Name : response207
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 207
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.118

Field Name : response206
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 206
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.117

Field Name : response205
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 205
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.116

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : response204
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 204
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.115

Field Name : response203
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 203
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.114

Field Name : response202
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 202
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.113

Field Name : response201
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 201
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.112

Field Name : response200
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 200
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.111

Field Name : response2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 2XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.110

Field Name : response102
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 102
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.109

Field Name : response101
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 101
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.108

Field Name : response100
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 100
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.107

Field Name : response1xx
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Description : Status code 1XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.106

Field Name : compressionAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data after compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.104

Field Name : compressionBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : Tot data before compress
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.102

Field Name : serverReselFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server re-select failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.101

Field Name : staleSess
Field Type : CounterBasedGauge64
Field Status : current
Description : Stale sess
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.100

Field Name : pktsRetransPush
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans PSH
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.99

Field Name : pktsRetransRst
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.98

Field Name : pktsRetransFin
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.97

Field Name : pktsRetransAckFinwait
Field Type : CounterBasedGauge64
Field Status : current
Description : retrans ACK FWAIT
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.96

Field Name : pktsRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets retrans
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.95

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : pktsOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.94

Field Name : connectingAck
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.93

Field Name : connectingRstOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting RST ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.92

Field Name : connectingRstRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting RST retrans
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.91

Field Name : connectingRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.90

Field Name : connectingFinOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting FIN ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.89

Field Name : connectingFinRetrans
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting FIN retrans
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.88

Field Name : connectingFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Connecting FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.87

Field Name : clientReqUnexpFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : Client req unexp flags
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.86

Field Name : asmSetcookieHeaderFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Asm set-cookie hdr fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.85

Field Name : asmSetcookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Assemble set-cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.84

Field Name : asmCookieHeaderFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Asm cookie header fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.83

Field Name : asmCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Assemble cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.82

Field Name : parseSetcookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse set-cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.81

Field Name : parseCookieFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse cookie fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.80

Field Name : hugeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Huge cookie headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.79

Field Name : hugeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : Huge cookies
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.78

Field Name : largeCookieHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Large cookie headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.77

Field Name : largeCookie
Field Type : CounterBasedGauge64
Field Status : current
Description : Large cookies
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.76

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : negativeRespRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative response remain
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.75

Field Name : negativeReqRemain
Field Type : CounterBasedGauge64
Field Status : current
Description : Negative request remain
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.74

Field Name : insertClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : Insert client IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.73

Field Name : headerDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Header delete
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.72

Field Name : headerInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : Header insert
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.71

Field Name : wrongRespHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Wrong response header
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.70

Field Name : headerNameTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Header name too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.69

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.68

Field Name : tooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : Too many headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.67

Field Name : invalidHeader
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Invalid header
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.66

Field Name : serverRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - response
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.65

Field Name : serverRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.64

Field Name : serverRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.63

Field Name : serverRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST - request
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.62

Field Name : clientRstResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - response
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.61

Field Name : clientRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.60

Field Name : clientRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.59

Field Name : clientRstRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST - request
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.58

Field Name : aflexLbReselectOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex lb reselect (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.57

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : aflexLbReselect
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex lb reselect
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.56

Field Name : aflexRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex http retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.55

Field Name : retry503
Field Type : CounterBasedGauge64
Field Status : current
Description : Retry on 503
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.54

Field Name : lbSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Normal LB switch. (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.53

Field Name : hostSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Host switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.52

Field Name : urlSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : URL switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.51

Field Name : httpPolicySwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Policy switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.50

Field Name : aflexSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.49

Field Name : cookieSwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.48

Field Name : l4SwitchingEnqueue
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : L4 switching (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.47

Field Name : lbSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Normal LB switch. (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.46

Field Name : hostSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Host switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.45

Field Name : urlSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : URL switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.44

Field Name : httpPolicySwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Policy switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.43

Field Name : aflexSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.42

Field Name : cookieSwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.41

Field Name : l4SwitchingOk
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.40

Field Name : lbSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Normal LB switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.39

Field Name : hostSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Host switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.38

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : urlSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : URL switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.37

Field Name : httpPolicySwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Policy switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.36

Field Name : aflexSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.35

Field Name : cookieSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.34

Field Name : l4Switching
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.33

Field Name : slbHttpProxyReqRateOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Request rate over limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.32

Field Name : slbHttpProxyReqOverLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Request over limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.31

Field Name : fullProxyFpgaErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy fpga err
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.30

Field Name : fullProxyPipeline
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy pipeline
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.29

Field Name : fullProxyPost
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Full proxy POST
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.28

Field Name : fullProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Full proxy tot
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.27

Field Name : tcpoutrst
Field Type : CounterBasedGauge64
Field Status : current
Description : Out RSTs
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.26

Field Name : slbHttpProxySnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.25

Field Name : slbHttpProxyNewSvnConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Server conn made
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.24

Field Name : slbHttpProxySvrPremClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Server premature close
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.23

Field Name : slbHttpProxyServerResel
Field Type : CounterBasedGauge64
Field Status : current
Description : Server reselection
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.22

Field Name : slbHttpProxyReqOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets ofo
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.21

Field Name : slbHttpProxyReqRetran
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets retrans
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.20

Field Name : slbHttpProxyFwdreqdataFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.19

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : fwdreqFailTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.18

Field Name : fwdreqFailServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - server
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.17

Field Name : fwdreqFailPersist
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - persist
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.16

Field Name : fwdreqFailRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - route
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.15

Field Name : fwdreqFailRport
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - rport
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.14

Field Name : fwdreqFailBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - buff
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.13

Field Name : slbHttpProxyFwdreqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.12

Field Name : slbHttpProxySvrSelFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.11

Field Name : slbHttpProxyParseReqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse req fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.10

Field Name : slbHttpProxyNotuple
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : No tuple error
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.9

Field Name : slbHttpProxyServerRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.8

Field Name : slbHttpProxyClientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Client RST
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.7

Field Name : slbHttpProxyNoProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : No proxy error
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.6

Field Name : slbHttpProxyReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP requests(succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.5

Field Name : slbHttpProxyReq
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.4

Field Name : slbHttpProxyTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.3

Field Name : slbHttpProxyCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.2

Field Name : num
Field Type : CounterBasedGauge64
Field Status : current
Description : Num
OID : 1.3.6.1.4.1.22610.2.4.10.108.46.1.1

Field Name : cookieInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid persist cookie
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.53

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : cookiePassThru
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist cookie Pass-thru
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.52

Field Name : cookieNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist cookie not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.51

Field Name : cookiePersistFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.50

Field Name : cookiePersistOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie persist ok
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.49

Field Name : sslSidSessionFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Create SSL SID fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.48

Field Name : sslSidSessionOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Create SSL SID ok
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.47

Field Name : sslSidPersistFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL SID persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.46

Field Name : sslSidPersistOk
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL SID persist ok
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.45

Field Name : ssslSidNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL SID not match
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.44

Field Name : ssslSidMatch
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Server SSL SID match
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.43

Field Name : ssslSidReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL SID reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.42

Field Name : ssslSidNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL SID not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.41

Field Name : csslSidNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL SID not match
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.40

Field Name : csslSidMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL SID match
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.39

Field Name : csslSidNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL SID not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.38

Field Name : dstIpHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP hash persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.37

Field Name : dstIpHashSec
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP hash persist(sec)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.36

Field Name : dstIpHashEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP hash persist(enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.35

Field Name : dstIpHashPri
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP hash persist(pri)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.34

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : dstIpNewSessSelFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP new sess fail (s)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.33

Field Name : dstIpNewSessSel
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP new sess (select)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.32

Field Name : dstIpNewSessCacheFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP new sess fail (c)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.31

Field Name : dstIpNewSessCache
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP new sess (cache)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.30

Field Name : dstIpFail
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.29

Field Name : dstIpEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP persist enqueue
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.28

Field Name : dstIp
Field Type : CounterBasedGauge64
Field Status : current
Description : DST IP persist ok
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.27

Field Name : srcIpEnforce
Field Type : CounterBasedGauge64
Field Status : current
Description : Enforce higher priority
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.26

Field Name : srcIpHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP hash persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.25

Field Name : srcIpHashSec
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : SRC IP hash persist(sec)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.24

Field Name : srcIpHashEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP hash persist(enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.23

Field Name : srcIpHashPri
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP hash persist(pri)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.22

Field Name : srcIpNewSessSelFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP new sess fail (s)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.21

Field Name : srcIpNewSessSel
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP new sess (select)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.20

Field Name : srcIpNewSessCacheFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP new sess fail (c)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.19

Field Name : srcIpNewSessCache
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP new sess (cache)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.18

Field Name : srcIpFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.17

Field Name : srcIpEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP persist enqueue
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.16

Field Name : srcIp
Field Type : CounterBasedGauge64
Field Status : current
Description : SRC IP persist ok
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.15

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : headerHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Header hash persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.14

Field Name : headerHashSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Header hash persist(sec)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.13

Field Name : headerHashEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Header hash persist(enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.12

Field Name : headerHashPri
Field Type : CounterBasedGauge64
Field Status : current
Description : Header hash persist(pri)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.11

Field Name : urlHashFail
Field Type : CounterBasedGauge64
Field Status : current
Description : URL hash persist fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.10

Field Name : urlHashSec
Field Type : CounterBasedGauge64
Field Status : current
Description : URL hash persist (sec)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.9

Field Name : urlHashEnqueue
Field Type : CounterBasedGauge64
Field Status : current
Description : URL hash persist (enQ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.8

Field Name : urlHashPri
Field Type : CounterBasedGauge64
Field Status : current
Description : URL hash persist (pri)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.7

Field Name : hashTblRstAdddel
Field Type : CounterBasedGauge64
Field Status : current
Description : Hash tbl reset (add/del)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.6

Field Name : hashTblRstUpdown
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Hash tbl reset (up/down)
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.5

Field Name : hashTblFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Hash tbl free
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.4

Field Name : hashTblCreateFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Hash tbl create fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.3

Field Name : hashTblCreateOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Hash tbl create ok
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.2

Field Name : hashTblTrylockFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Hash tbl lock fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.45.1.1

Field Name : algPortHelperNatFree
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT helper NAT free
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.8

Field Name : algPasvHelperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : PASV helper freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.7

Field Name : algPortHelperFreedUnused
Field Type : CounterBasedGauge64
Field Status : current
Description : PORT helper freed unused
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.6

Field Name : algPasvHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total PASV helper sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.5

Field Name : algPortHelperCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total PORT helper sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.4

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : algPktsXmittedNum
Field Type : CounterBasedGauge64
Field Status : current
Description : ALG packets rexmitted
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.3

Field Name : algPktsNum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ALG packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.2

Field Name : sessionsNum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Control Sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.44.1.1

Field Name : databaseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Database error
OID : 1.3.6.1.4.1.22610.2.4.10.108.109.1.5

Field Name : databaseBusy
Field Type : CounterBasedGauge64
Field Status : current
Description : Database busy
OID : 1.3.6.1.4.1.22610.2.4.10.108.109.1.4

Field Name : entryDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total deleted cache entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.109.1.3

Field Name : entrySaved
Field Type : CounterBasedGauge64
Field Status : current
Description : Total saved cache entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.109.1.2

Field Name : totalEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Total persistent cache entry
OID : 1.3.6.1.4.1.22610.2.4.10.108.109.1.1

Field Name : multipleAnswerNoCache
Field Type : CounterBasedGauge64
Field Status : current
Description : Response not cached due to multiple answers
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.26

Field Name : hitRatePerSec
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Cache hit rate per second
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.25

Field Name : qps
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache Queries-per-second
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.24

Field Name : truncatedR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response with Truncation bit set
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.23

Field Name : resolverQueueFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Resolver task queue full
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.22

Field Name : currentDataAllocate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current data allocate
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.21

Field Name : currentAllocate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current allocate
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.20

Field Name : dnsTotalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.19

Field Name : totalAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total allocated
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.18

Field Name : totalLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Total stats log sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.17

Field Name : ageoutWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : Total aged for lower weight
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.16

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : badAnswer
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Answer
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.15

Field Name : ageout
Field Type : CounterBasedGauge64
Field Status : current
Description : Total aged out
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.14

Field Name : ttlR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response with short TTL
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.13

Field Name : answerR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response with multiple answers
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.12

Field Name : multipleR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response with multiple questions
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.11

Field Name : encoderR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response encoded
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.10

Field Name : oversizeR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response exceed cache size
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.9

Field Name : badR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response not passed
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.8

Field Name : oversizeQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query exceed cache size
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.7

Field Name : multipleQ
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Query with multiple questions
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.6

Field Name : encodeQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query encoded
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.5

Field Name : badQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query not passed
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.4

Field Name : hit
Field Type : CounterBasedGauge64
Field Status : current
Description : Total cache hit
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.3

Field Name : totalR
Field Type : CounterBasedGauge64
Field Status : current
Description : Total server response
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.2

Field Name : totalQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Total query
OID : 1.3.6.1.4.1.22610.2.4.10.108.43.1.1

Field Name : slbDnsEdnsEcsInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ecs inserted
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.36

Field Name : slbDnsEdnsEcsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ecs from client received
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.35

Field Name : invalidQLenToUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid query length to conver to UDP
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.34

Field Name : natSlbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT)DNS requests drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.33

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS requests drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.32

Field Name : rpzActionLocalData
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action Local Data
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.31

Field Name : rpzActionNodata
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action NODATA
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.30

Field Name : rpzActionNxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action NXDOMAIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.29

Field Name : rpzActionTcpOnly
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action TCP Only
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.28

Field Name : rpzActionPassThru
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action Pass Through
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.27

Field Name : rpzActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.26

Field Name : slbDnsUdpRetransmitFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.25

Field Name : slbDnsUdpRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.24

Field Name : slbDnsEdnsSubnetToServerRemoved
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.23

Field Name : slbDnsPaddingToClientAdded

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.22

Field Name : slbDnsPaddingToServerRemoved

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.21

Field Name : slbDnsUdpConnSucc

Field Type : CounterBasedGauge64

Field Status : current

Description : No. of backend udp conn established

OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.20

Field Name : slbDnsUdpConn

Field Type : CounterBasedGauge64

Field Status : current

Description : No. of backend udp connections

OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.19

Field Name : slbDnsServerSslSucc

Field Type : CounterBasedGauge64

Field Status : current

Description : No. of server ssl success

OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.18

Field Name : slbDnsClientSslSucc

Field Type : CounterBasedGauge64

Field Status : current

Description : No. of client ssl success

OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.17

Field Name : filterTypeAnyDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Query ANY Type Drop

OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.16

Field Name : filterClassDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Query Class Drop

OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.15

Field Name : filterTypeDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Query Type Drop

OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.14

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : natXidReused
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of requests reusing a transaction id
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.13

Field Name : natNoResource
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of resource failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.12

Field Name : natRespNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of requests with no response
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.11

Field Name : natReqRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of request retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.10

Field Name : natNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of resource failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.9

Field Name : natResp
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.8

Field Name : natReq
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT) No. of requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.7

Field Name : slbNoResource
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of resource failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.6

Field Name : slbRespNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests and responses with no match
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.5

Field Name : slbReqRexmit
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : No. of requests retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.4

Field Name : slbNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests with no response
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.3

Field Name : slbResp
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.2

Field Name : slbReq
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.42.1.1

Field Name : slbGenericProxyDiameterTooBusyOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DIAMETER_TOO_BUSY out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.75

Field Name : slbGenericProxyDiameterTooBusyIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DIAMETER_TOO_BUSY in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.74

Field Name : slbGenericProxyDpaIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DPAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.73

Field Name : slbGenericProxyDpaOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DPAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.72

Field Name : slbGenericProxyDprIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DPRs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.71

Field Name : slbGenericProxyDprOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DPRs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.70

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbGenericProxyReplyErrorInfoFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fail to reply error info to peer
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.69

Field Name : slbGenericProxyReplyUnableToDeliver
Field Type : CounterBasedGauge64
Field Status : current
Description : Reply with unable to deliver error info
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.68

Field Name : slbGenericProxyReplyInvalidAVPValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Reply with invalid AVP error info
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.67

Field Name : slbGenericProxyConnClosedByServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Server initiates TCP close/reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.66

Field Name : slbGenericProxyConnClosedByClient
Field Type : CounterBasedGauge64
Field Status : current
Description : Client initiates TCP close/reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.65

Field Name : slbGenericProxyReselectRevTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Original server tuple does not exist so reselect another one
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.64

Field Name : slbGenericProxyReselectFwdTupleOtherCPU
Field Type : CounterBasedGauge64
Field Status : current
Description : Original client tuple does not exist so reselect another one on other CPUs
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.63

Field Name : slbGenericProxyReselectFwdTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Original client tuple does not exist so reselect another one
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.62

Field Name : slbGenericProxyInvalidAVP
Field Type : CounterBasedGauge64
Field Status : current
Description : AVP value contains illegal chars
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.61

Field Name : slbGenericProxyCloseConnWhenVportDown
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Close client conn when virtual port is down
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.60

Field Name : slbGenericProxyClientSelectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fail to select client
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.59

Field Name : slbGenericProxyUpdateLatestServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Update to the latest server that used a session id
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.58

Field Name : slbGenericProxyForwardUnknownSessionID
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward server side message with unknown session id
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.57

Field Name : slbGenericProxyTermCCAT
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter terminate on cca_t
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.56

Field Name : slbGenericProxyCcaT
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCAs terminate
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.55

Field Name : slbGenericProxyCcrT
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCRs terminate
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.54

Field Name : slbGenericProxyCcrU
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCRs update
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.53

Field Name : slbGenericProxyCcrI
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCRs initial
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.52

Field Name : slbGenericProxyCcaIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.51

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbGenericProxyCcaOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.50

Field Name : slbGenericProxyCcrIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCRs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.49

Field Name : slbGenericProxyCcrOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CCRs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.48

Field Name : slbGenericProxyReplyUnknownSessionID
Field Type : CounterBasedGauge64
Field Status : current
Description : Reply with unknown session ID error info
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.47

Field Name : slbGenericProxyDiaRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter retry client request fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.46

Field Name : slbGenericProxyDiaRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter retry client request
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.45

Field Name : slbGenericProxyDiaDcmsgErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter cross cpu error
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.44

Field Name : slbGenericProxyDiaDcmsgRevOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter cross cpu rev out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.43

Field Name : slbGenericProxyDiaDcmsgRevIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter cross cpu rev in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.42

Field Name : slbGenericProxyDiaDcmsgFwdOut
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Diameter cross cpu fwd out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.41

Field Name : slbGenericProxyDiaDcmsgFwdIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter cross cpu fwd in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.40

Field Name : slbGenericProxyDiaNoRev
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter no rev tuple matched
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.39

Field Name : slbGenericProxyDiaNoFwd
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter no fwd tuple matched
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.38

Field Name : slbGenericProxyDiaNoID
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter no session id avp
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.37

Field Name : slbGenericProxyDiaUnkCmd
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter unkown cmd code
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.36

Field Name : slbGenericProxyDiaRevId
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter mismatch rev session id
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.35

Field Name : slbGenericProxyDiaFwdId
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter mismatch fwd session id
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.34

Field Name : totalHttpRequestEnterGen
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of HTTP requests enter generic proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.33

Field Name : slbGenericProxyOtherIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of other messages in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.32

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbGenericProxyOtherOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of other messages out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.31

Field Name : slbGenericProxyAsaIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ASAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.30

Field Name : slbGenericProxyAsaOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ASAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.29

Field Name : slbGenericProxyAsrIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ASRs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.28

Field Name : slbGenericProxyAsrOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ASRs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.27

Field Name : slbGenericProxyStaIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of STAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.26

Field Name : slbGenericProxyStaOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of STAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.25

Field Name : slbGenericProxyStrIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of STRs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.24

Field Name : slbGenericProxyStrOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of STRs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.23

Field Name : slbGenericProxyDwaIn
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Number of DWAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.22

Field Name : slbGenericProxyDwaOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DWAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.21

Field Name : slbGenericProxyDwrIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DWRs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.20

Field Name : slbGenericProxyDwrOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of DWRs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.19

Field Name : slbGenericProxyCerIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CERs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.18

Field Name : slbGenericProxyCerOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CERs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.17

Field Name : slbGenericProxyCeaIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CEAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.16

Field Name : slbGenericProxyCeaOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of CEAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.15

Field Name : slbGenericProxyAcaIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ACAs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.14

Field Name : slbGenericProxyAcaOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ACAs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.13

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbGenericProxyAcrIn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ACRs in
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.12

Field Name : slbGenericProxyAcrOUT
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ACRs out
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.11

Field Name : slbGenericProxyUserSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of user sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.10

Field Name : slbGenericProxyNoSess
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of no sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.9

Field Name : slbGenericProxyServerFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of server failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.8

Field Name : slbGenericProxyClientFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of client failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.7

Field Name : slbGenericProxySnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of snat failures
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.6

Field Name : slbGenericProxyNoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of no routes
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.5

Field Name : slbGenericProxySvrselfFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of server selection failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.4

Field Name : slbGenericProxyTotal
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Total

OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.3

Field Name : slbGenericProxyCurr

Field Type : CounterBasedGauge64

Field Status : current

Description : Current

OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.2

Field Name : slbGenericProxyNum

Field Type : CounterBasedGauge64

Field Status : current

Description : Number

OID : 1.3.6.1.4.1.22610.2.4.10.108.41.1.1

Field Name : logMsgSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Log messages sent

OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.9

Field Name : lockoutDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Lockout drops

OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.8

Field Name : thresholdExceed

Field Type : CounterBasedGauge64

Field Status : current

Description : Threshold exceeded count

OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.7

Field Name : permitted

Field Type : CounterBasedGauge64

Field Status : current

Description : Honor threshold count

OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.6

Field Name : called

Field Type : CounterBasedGauge64

Field Status : current

Description : Threshold check count

OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.5

Field Name : tooManySessions

Field Type : CounterBasedGauge64

Field Status : current

Description : Too many sessions consumed

OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.4

Field Name : outOfSessions

Field Type : CounterBasedGauge64

Field Status : current

Description : Out of sessions

OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.3

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : sessionsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.2

Field Name : sessionsAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Sessions allocated
OID : 1.3.6.1.4.1.22610.2.4.10.108.40.1.1

Field Name : authFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication Failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.13

Field Name : authSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication Success
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.12

Field Name : commands
Field Type : CounterBasedGauge64
Field Status : current
Description : DB commands reply
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.11

Field Name : queries
Field Type : CounterBasedGauge64
Field Status : current
Description : DB Queries
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.10

Field Name : sessionErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Session err
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.9

Field Name : serverFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Server FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.8

Field Name : clientFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Client FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.7

Field Name : totalFeEnc
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Total FE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.6

Field Name : currFeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr FE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.5

Field Name : totalBeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total BE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.4

Field Name : currBeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr BE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.3

Field Name : totalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.2

Field Name : currProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.39.1.1

Field Name : slbMysqlCommands
Field Type : CounterBasedGauge64
Field Status : current
Description : DB commands reply
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.11

Field Name : slbMysqlQueries
Field Type : CounterBasedGauge64
Field Status : current
Description : DB Queries
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.10

Field Name : slbMysqlSessionErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Session err
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.9

Field Name : slbMysqlServerFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Server FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.8

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbMysqlClientFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Client FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.7

Field Name : slbMysqlTotalFeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total FE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.6

Field Name : slbMysqlCurrFeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr FE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.5

Field Name : slbMysqlTotalBeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total BE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.4

Field Name : slbMysqlCurrBeEnc
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr BE Encryption Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.3

Field Name : slbMysqlTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.2

Field Name : slbMysqlCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.38.1.1

Field Name : currPconn
Field Type : CounterBasedGauge64
Field Status : current
Description : Persistent connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.7

Field Name : slbPassthroughTotalRevPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.6

Field Name : slbPassthroughTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Reverse bytes

OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.5

Field Name : slbPassthroughTotalFwdPackets

Field Type : CounterBasedGauge64

Field Status : current

Description : Forward packets

OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.4

Field Name : slbPassthroughTotalFwdBytes

Field Type : CounterBasedGauge64

Field Status : current

Description : Forward bytes

OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.3

Field Name : slbPassthroughTotalConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Total connections

OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.2

Field Name : slbPassthroughCurrConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Current connections

OID : 1.3.6.1.4.1.22610.2.4.10.108.37.1.1

Field Name : totalTimeout

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of Total health-check timeout

OID : 1.3.6.1.4.1.22610.2.4.10.108.36.1.3

Field Name : totalRetrySent

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of Total health-check retry sent

OID : 1.3.6.1.4.1.22610.2.4.10.108.36.1.2

Field Name : totalSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of Total health-check sent

OID : 1.3.6.1.4.1.22610.2.4.10.108.36.1.1

Field Name : timeoutWithPacket

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of pin timeouts while socket has packets

OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.30

Field Name : sslPostHandshakePacket

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of ssl post handshake packets before client sends request

OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.29

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : configHealthRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Config health rate
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.28

Field Name : runningTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Running time
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.27

Field Name : statusOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of other status
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.26

Field Name : statusUnkn
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of status unknowns
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.25

Field Name : statusDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of status downs
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.24

Field Name : statusUp
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of status ups
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.23

Field Name : totalNumber
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.22

Field Name : extHealthRateVal
Field Type : CounterBasedGauge64
Field Status : current
Description : External health rate value
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.21

Field Name : extHealthRate
Field Type : CounterBasedGauge64
Field Status : current
Description : External health rate
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.20

Field Name : currHealthRate
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Current health rate

OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.19

Field Name : sockCloseWithoutNotify

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of sockets closed without notify

OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.18

Field Name : sockCloseBefore17

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of sockets closed before 17

OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.17

Field Name : connImdtSucc

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of connection immediate success

OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.16

Field Name : unexpectedError

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of unexpected errors

OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.15

Field Name : timeout

Field Type : CounterBasedGauge64

Field Status : current

Description : Timeout value

OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.14

Field Name : retryTimes

Field Type : CounterBasedGauge64

Field Status : current

Description : Retry times

OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.13

Field Name : recvPacketFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of failed packet receives

OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.12

Field Name : recvPacket

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of received packets

OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.11

Field Name : sendPacketFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of packet send failures

OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.10

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : sendPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of packets sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.9

Field Name : connectFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of failed connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.8

Field Name : closeSocket
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of closed sockets
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.7

Field Name : openSocketFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of failed open sockets
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.6

Field Name : openSocket
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of open sockets
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.5

Field Name : avgJiffie
Field Type : CounterBasedGauge64
Field Status : current
Description : Average number of jiffies
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.4

Field Name : minJiffie
Field Type : CounterBasedGauge64
Field Status : current
Description : Minimum number of jiffies
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.3

Field Name : maxJiffie
Field Type : CounterBasedGauge64
Field Status : current
Description : Maximum number of jiffies
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.2

Field Name : numBurst
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of burst
OID : 1.3.6.1.4.1.22610.2.4.10.108.35.1.1

Field Name : drop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Dropped

OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.15

Field Name : cache

Field Type : CounterBasedGauge64

Field Status : current

Description : Cache

OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.14

Field Name : adjust

Field Type : CounterBasedGauge64

Field Status : current

Description : Translated

OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.13

Field Name : respLocal

Field Type : CounterBasedGauge64

Field Status : current

Description : Response Local

OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.12

Field Name : respEmpty

Field Type : CounterBasedGauge64

Field Status : current

Description : Response Empty

OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.11

Field Name : respErr

Field Type : CounterBasedGauge64

Field Status : current

Description : Response Error

OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.10

Field Name : respChg

Field Type : CounterBasedGauge64

Field Status : current

Description : Response Changed

OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.9

Field Name : respBadQr

Field Type : CounterBasedGauge64

Field Status : current

Description : Response Bad Query

OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.8

Field Name : respBadPkt

Field Type : CounterBasedGauge64

Field Status : current

Description : Response Bad Packet

OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.7

Field Name : resp

Field Type : CounterBasedGauge64

Field Status : current

Description : Response

OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.6

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : queryPassive
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Passive
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.5

Field Name : queryParallel
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Parallel
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.4

Field Name : queryChg
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Changed
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.3

Field Name : queryBadPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Query Bad Packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.2

Field Name : query
Field Type : CounterBasedGauge64
Field Status : current
Description : Query
OID : 1.3.6.1.4.1.22610.2.4.10.108.104.1.1

Field Name : maxOutstandingSubmitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Max queued submit count
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.8

Field Name : maxOutstandingRequestCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Max queued request count
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.7

Field Name : ringFullCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Compression queue full
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.6

Field Name : failureCode
Field Type : CounterBasedGauge64
Field Status : current
Description : Last failure code
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.5

Field Name : failureCount
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Description : Total failure count
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.4

Field Name : responseCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Total response count
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.3

Field Name : submitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Total submit count
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.2

Field Name : requestCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Total request count
OID : 1.3.6.1.4.1.22610.2.4.10.108.34.1.1

Field Name : processErrorWhenMessageSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.161

Field Name : smpCallIdRtpSessionNotMatch
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.160

Field Name : smpCallIdRtpSessionMatch
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.159

Field Name : updateSmpCallIdRtp
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.158

Field Name : saveSmpCallIdRtp
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.157

Field Name : haFailCloneSipSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.156

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : haFailAllocCallId
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.155

Field Name : haFailAllocSipSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.154

Field Name : haInvalidPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.153

Field Name : haUpdateSipSessionOk
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.152

Field Name : haInsertSipSessionOk
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.151

Field Name : haRecvSipSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.150

Field Name : haFailGetMsgHeader
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.149

Field Name : haSendSipSessionOk
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.148

Field Name : haSendSipSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.147

Field Name : response6XX
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.146

Field Name : response5XX

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.145

Field Name : response4XX

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.144

Field Name : response3XX

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.143

Field Name : response2XX

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.142

Field Name : response1XX

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.141

Field Name : responseUnknown

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.140

Field Name : requestUpdate

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.139

Field Name : requestMessage

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.138

Field Name : requestRefer

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.137

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : requestInfo
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.136

Field Name : requestPublish
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.135

Field Name : requestNotify
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.134

Field Name : requestSubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.133

Field Name : requestPrack
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.132

Field Name : requestOptions
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.131

Field Name : requestBye
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.130

Field Name : requestCancel
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.129

Field Name : requestAck
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.128

Field Name : requestInvite
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.127

Field Name : requestRegister

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.126

Field Name : msgTransBody

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.125

Field Name : msgTransStartHeaders

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.124

Field Name : msgTransStartLine

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.123

Field Name : msgTranslationFail

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.122

Field Name : msgTranslation

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.121

Field Name : saveCallIdOk

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.120

Field Name : saveCallId

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.119

Field Name : saveUriOk

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.118

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : saveUri
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.117

Field Name : concatenateMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.116

Field Name : clientRequestOk
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.115

Field Name : clientRequest
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.114

Field Name : axHealthCheckReceived
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.113

Field Name : serverKeepaliveSend
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.112

Field Name : clientKeepaliveSend
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.111

Field Name : serverKeepaliveReceived
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.110

Field Name : clientKeepaliveReceived
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.109

Field Name : failSplitFragment
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.108

Field Name : sizeTooLarge

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.107

Field Name : wrongIpVersion

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.106

Field Name : assembleFragFailed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.105

Field Name : aclDenied

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.104

Field Name : clientSelectFailed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.103

Field Name : uriSelectClient

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.102

Field Name : callIdSelectClient

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.101

Field Name : xForwardedForClient

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.100

Field Name : selectClientConn

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.99

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : selectServerConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.98

Field Name : selectServerConnByRevTuple
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.97

Field Name : selectServerConnByUri
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.96

Field Name : selectServerConnByCallid
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.95

Field Name : selectServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.94

Field Name : failInsertHeader
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.93

Field Name : failInsertUriSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.92

Field Name : failInsertCallidSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.91

Field Name : deprecatedMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.90

Field Name : noSipRequest
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.89

Field Name : identifyDirFailed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.88

Field Name : msgNoCallId

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.87

Field Name : failGetCounter

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.86

Field Name : bodyTooBig

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.85

Field Name : headerNameTooLong

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.84

Field Name : invalidHeader

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.83

Field Name : tooManyHeaders

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.82

Field Name : failParseHeaders

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.81

Field Name : requestUnknown

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.80

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : responseUnknownVersion
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.79

Field Name : requestUnknownVersion
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.78

Field Name : invalidStartLine
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.77

Field Name : failParseStartLine
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.76

Field Name : failReadStartLine
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.75

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.74

Field Name : msgNoUriSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.73

Field Name : sgNoUriHeader
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.72

Field Name : cmsgNoUriSession
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.71

Field Name : cmsgNoUriHeader
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.70

Field Name : tableMemFreed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.69

Field Name : tableMemAllocd

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.68

Field Name : lineMemFreed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.67

Field Name : lineMemAllocd

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.66

Field Name : sessionCallidFreed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.65

Field Name : sessionCallidAllocd

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.64

Field Name : connFreed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.63

Field Name : connAllocd

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.62

Field Name : sessionInvalid

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.61

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : sessionInRml
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.60

Field Name : sessionFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Session freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.59

Field Name : slbSipSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SIP Session created
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.58

Field Name : msgProxyServerReset
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.57

Field Name : msgProxyClientReset
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.56

Field Name : msgProxyPipelineMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.55

Field Name : msgProxySplitPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.54

Field Name : msgProxyHoldMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.53

Field Name : msgProxyDeprecatedConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.52

Field Name : msgProxyFailDcmsg
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.51

Field Name : msgProxyMagBack

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.50

Field Name : msgProxyL7ToL4

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.49

Field Name : msgProxyL4FromL4Send

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.48

Field Name : msgProxyToL4SendPkt

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.47

Field Name : msgProxyL4FromL7

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.46

Field Name : msgProxyL4ToL7

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.45

Field Name : msgProxyL7CpuFailed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.44

Field Name : msgProxyUnexpectedErr

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.43

Field Name : msgProxyFailAllocMem

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.42

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : msgProxyFailSelectServer
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.41

Field Name : msgProxyNoVport
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.40

Field Name : msgProxyProcessMsgFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.39

Field Name : msgProxyParseMsgFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.38

Field Name : msgProxyFailInsertServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.37

Field Name : msgProxyServerConnAlreadyExists
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.36

Field Name : msgProxyStartServerConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.35

Field Name : msgProxyFailReservePconn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.34

Field Name : msgProxyFailConstructServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.33

Field Name : msgProxyServerConnFailSnat
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.32

Field Name : slbSipMsgProxyFailStartServerConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of server connection create failed

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.31

Field Name : slbSipMsgProxyStartServerConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of server connection created successfully

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.30

Field Name : slbSipMsgProxyCreateServerConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of server connection system tries to create

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.29

Field Name : msgProxyServerFailSendPkt

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.28

Field Name : msgProxyServerExceedTmpBuff

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.27

Field Name : msgProxyServerFailSnat

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.26

Field Name : msgProxyServerFailSelecConnt

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.25

Field Name : msgProxyServerFailProcess

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.24

Field Name : msgProxyServerFailParse

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.23

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : slbSipMsgProxyServerFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SIP messages received from server but failed to forward to client
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.22

Field Name : slbSipMsgProxyServerDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of AX drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.21

Field Name : slbSipMsgProxyServerIncomplete
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of packet which contains incomplete message
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.20

Field Name : slbSipMsgProxyServerSendSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SIP messages received from server and forwarded to client
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.19

Field Name : slbSipMsgProxyServerRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SIP messages received from server
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.18

Field Name : msgProxyClientFailStartServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.17

Field Name : msgProxyClientFailSendPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.16

Field Name : msgProxyClientExceedTmpBuff
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.15

Field Name : msgProxyClientFailSnat
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.14

Field Name : msgProxyClientFailProcess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.13

Field Name : msgProxyClientFailParse

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.12

Field Name : slbSipMsgProxyClientFail

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of SIP messages received from client but failed to forward to server

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.11

Field Name : slbSipMsgProxyClientConnection

Field Type : CounterBasedGauge64

Field Status : current

Description : Connecting server

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.10

Field Name : slbSipMsgProxyClientDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of AX drop

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.9

Field Name : slbSipMsgProxyClientIncomplete

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of packet which contains incomplete message

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.8

Field Name : slbSipMsgProxyClientSendSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of SIP messages received from client and forwarded to server

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.7

Field Name : slbSipMsgProxyClientRecv

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of SIP messages received from client

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.6

Field Name : msgProxyMemFreed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.5

Field Name : msgProxyMemCached

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.4

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : msgProxyMemAllocd
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.3

Field Name : slbSipMsgProxyTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number of sip proxy connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.2

Field Name : slbSipMsgProxyCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of current sip proxy connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.33.1.1

Field Name : statusUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.63

Field Name : status6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status code 6XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.62

Field Name : status5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status code 5XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.61

Field Name : status4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status code 4XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.60

Field Name : status3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status code 3XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.59

Field Name : status2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : status code 2XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.58

Field Name : status1xx
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Description : status code 1XX
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.57

Field Name : status510
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 510
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.56

Field Name : status509
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 509
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.55

Field Name : status508
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 508
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.54

Field Name : status507
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 507
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.53

Field Name : status506
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 506
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.52

Field Name : status505
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 505
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.51

Field Name : status504
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 504
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.50

Field Name : status503
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 503
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.49

Field Name : status502
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 502
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.48

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : status501
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 501
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.47

Field Name : status500
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 500
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.46

Field Name : status450
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 450
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.45

Field Name : status449
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 449
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.44

Field Name : status426
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 426
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.43

Field Name : status425
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 425
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.42

Field Name : status424
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 424
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.41

Field Name : status423
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 423
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.40

Field Name : status422
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 422
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.39

Field Name : status418
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Status code 418
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.38

Field Name : status417
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 417
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.37

Field Name : status416
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 416
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.36

Field Name : status415
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 415
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.35

Field Name : status414
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 414
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.34

Field Name : status413
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 413
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.33

Field Name : status412
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 412
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.32

Field Name : status411
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 411
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.31

Field Name : status410
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 410
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.30

Field Name : status409
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 409
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.29

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : status408
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 408
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.28

Field Name : status407
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 407
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.27

Field Name : status406
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 406
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.26

Field Name : status405
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 405
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.25

Field Name : status404
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 404
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.24

Field Name : status403
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 403
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.23

Field Name : status402
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 402
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.22

Field Name : status401
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 401
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.21

Field Name : status400
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 400
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.20

Field Name : status307
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Description : Status code 307
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.19

Field Name : status306
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 306
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.18

Field Name : status305
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 305
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.17

Field Name : status304
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 304
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.16

Field Name : status303
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 303
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.15

Field Name : status302
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 302
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.14

Field Name : status301
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 301
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.13

Field Name : status300
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 300
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.12

Field Name : status102
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 102
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.11

Field Name : status101
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 101
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.10

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : status100
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 100
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.9

Field Name : status207
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 207
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.8

Field Name : status206
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 206
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.7

Field Name : status205
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 205
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.6

Field Name : status204
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 204
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.5

Field Name : status203
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 203
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.4

Field Name : status202
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 202
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.3

Field Name : status201
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 201
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.2

Field Name : status200
Field Type : CounterBasedGauge64
Field Status : current
Description : Status code 200
OID : 1.3.6.1.4.1.22610.2.4.10.108.32.1.1

Field Name : httpConnectReqmodRequest
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : HTTP CONNECT Reqmod Request Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.105

Field Name : recvOptionResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Send Option Req Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.104

Field Name : httpRespHdrErr
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Resp Hdr Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.103

Field Name : httpRespLineParseErr
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Response Line Parse Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.102

Field Name : httpRespLineReadErr
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Response Line Read Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.101

Field Name : noStatusCodeErr
Field Type : CounterBasedGauge64
Field Status : current
Description : No Status Code Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.100

Field Name : reqHdrIncompleteErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Req Hdr Incomplete Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.99

Field Name : respHdrErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp Hdr Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.98

Field Name : respLineParseErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp Line Parse Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.97

Field Name : respLineReadErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp Line Read Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.96

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : noIcapRespErr
Field Type : CounterBasedGauge64
Field Status : current
Description : No ICAP Resp Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.95

Field Name : encapHdrIncompleteErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Encap HDR Incomplete Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.94

Field Name : icapLineErr
Field Type : CounterBasedGauge64
Field Status : current
Description : ICAP Line Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.93

Field Name : icapVerErr
Field Type : CounterBasedGauge64
Field Status : current
Description : ICAP Ver Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.92

Field Name : prepReqFailErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Prepare ICAP req fail Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.91

Field Name : startIcapConnFailErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Start ICAP conn fail Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.90

Field Name : servSelFailErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Server Select Fail Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.89

Field Name : respHdrIncompleteErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Resp Hdr Incomplete Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.88

Field Name : noPayloadBuffErr
Field Type : CounterBasedGauge64
Field Status : current
Description : No Payload Buff Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.87

Field Name : noPayloadNextBuffErr
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : No Payload In Next Buff Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.86

Field Name : chunkBadTrailErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk Bad Trail Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.85

Field Name : chunk2HdrErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk Hdr Err2 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.84

Field Name : chunk1HdrErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk Hdr Err1 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.83

Field Name : appServConnErr
Field Type : CounterBasedGauge64
Field Status : current
Description : App Server Conn Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.82

Field Name : appServConnNoPcbErr
Field Type : CounterBasedGauge64
Field Status : current
Description : App Server Conn no ES PCB Err Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.81

Field Name : sendOptionReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Send Option Req Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.80

Field Name : statusUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Status Unknown Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.79

Field Name : status6xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 6xx Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.78

Field Name : status510
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 510 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.77

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : status509
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 509 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.76

Field Name : status508
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 508 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.75

Field Name : status507
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 507 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.74

Field Name : status506
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 506 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.73

Field Name : status505
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 505 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.72

Field Name : status504
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 504 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.71

Field Name : status503
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 503 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.70

Field Name : status502
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 502 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.69

Field Name : status501
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 501 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.68

Field Name : status500
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Status 500 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.67

Field Name : status5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 5xx Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.66

Field Name : status450
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 450 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.65

Field Name : status449
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 449 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.64

Field Name : status426
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 426 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.63

Field Name : status425
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 425 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.62

Field Name : status424
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 424 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.61

Field Name : status423
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 423 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.60

Field Name : status422
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 422 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.59

Field Name : status420
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 420 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.58

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : status419
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 419 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.57

Field Name : status418
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 418 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.56

Field Name : status417
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 417 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.55

Field Name : status416
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 416 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.54

Field Name : status415
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 415 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.53

Field Name : status414
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 414 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.52

Field Name : status413
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 413 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.51

Field Name : status412
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 412 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.50

Field Name : status411
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 411 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.49

Field Name : status410
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Status 410 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.48

Field Name : status409
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 409 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.47

Field Name : status408
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 408 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.46

Field Name : status407
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 407 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.45

Field Name : status406
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 406 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.44

Field Name : status405
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 405 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.43

Field Name : status404
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 404 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.42

Field Name : status403
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 403 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.41

Field Name : status402
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 402 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.40

Field Name : status401
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 401 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.39

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : status400
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 400 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.38

Field Name : status4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 4xx Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.37

Field Name : status307
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 307 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.36

Field Name : status306
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 306 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.35

Field Name : status305
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 305 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.34

Field Name : status304
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 304 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.33

Field Name : status303
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 303 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.32

Field Name : status302
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 302 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.31

Field Name : status301
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 301 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.30

Field Name : status300
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Status 300 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.29

Field Name : status3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 3xx Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.28

Field Name : status102
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 102 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.27

Field Name : status101
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 101 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.26

Field Name : status100
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 100 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.25

Field Name : status1xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 1xx Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.24

Field Name : status207
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 207 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.23

Field Name : status206
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 206 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.22

Field Name : status205
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 205 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.21

Field Name : status204
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 204 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.20

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : status203
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 203 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.19

Field Name : status202
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 202 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.18

Field Name : status201
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 201 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.17

Field Name : status200
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 200 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.16

Field Name : status2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Status 2xx Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.15

Field Name : resultOther
Field Type : CounterBasedGauge64
Field Status : current
Description : Result Other Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.14

Field Name : result100Continue
Field Type : CounterBasedGauge64
Field Status : current
Description : Result 100 Continue Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.13

Field Name : resultIcapResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Result ICAP Response Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.12

Field Name : resultContinue
Field Type : CounterBasedGauge64
Field Status : current
Description : Result Continue Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.11

Field Name : lenExceedNoAllow204
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Length Exceeded so no Allow 204 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.10

Field Name : chunkNoAllow204
Field Type : CounterBasedGauge64
Field Status : current
Description : Chunk so no Allow 204 Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.9

Field Name : respmodResponseAfter100
Field Type : CounterBasedGauge64
Field Status : current
Description : Respmod Response After 100 Cont Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.8

Field Name : reqmodResponseAfter100
Field Type : CounterBasedGauge64
Field Status : current
Description : Reqmod Response After 100 Cont Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.7

Field Name : respmodResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Respmod Response Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.6

Field Name : reqmodResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Reqmod Response Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.5

Field Name : respmodRequestAfter100
Field Type : CounterBasedGauge64
Field Status : current
Description : Respmod Request Sent After 100 Cont Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.4

Field Name : reqmodRequestAfter100
Field Type : CounterBasedGauge64
Field Status : current
Description : Reqmod Request Sent After 100 Cont Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.3

Field Name : respmodRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Respmod Request Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.2

Field Name : reqmodRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Reqmod Request Stats
OID : 1.3.6.1.4.1.22610.2.4.10.108.31.1.1

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : insertionSuccessful
Field Type : CounterBasedGauge64
Field Status : current
Description : Insertion successful
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.30

Field Name : insertionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Insertion failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.29

Field Name : sessionExist
Field Type : CounterBasedGauge64
Field Status : current
Description : Session already exist
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.28

Field Name : clientIdNull
Field Type : CounterBasedGauge64
Field Status : current
Description : Null client id
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.27

Field Name : connNull
Field Type : CounterBasedGauge64
Field Status : current
Description : Null conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.26

Field Name : tupleAlreadyLinked
Field Type : CounterBasedGauge64
Field Status : current
Description : tuple-already-linked failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.25

Field Name : tupleNotLinked
Field Type : CounterBasedGauge64
Field Status : current
Description : tuple-not-linked failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.24

Field Name : parseUnsubscribeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse unsubscribe failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.23

Field Name : parseSubscribeFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse subscribe failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.22

Field Name : parsePublishFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Parse publish failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.21

Field Name : parseConnectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse connect failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.20

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Total MQTT Commands
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.19

Field Name : totalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.18

Field Name : currProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Current proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.17

Field Name : recvMqttOther
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.16

Field Name : recvMqttAuth
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Auth
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.15

Field Name : recvMqttDisconnect
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Disconnect
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.14

Field Name : recvMqttPingresp
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Pingresp
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.13

Field Name : recvMqttPingreq
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Pingreq
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.12

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : recvMqttUnsuback
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Unsuback
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.11

Field Name : recvMqttUnsubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Unsubscribe
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.10

Field Name : recvMqttSuback
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Suback
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.9

Field Name : recvMqttSubscribe
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Subscribe
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.8

Field Name : recvMqttPubcomp
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Pubcomp
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.7

Field Name : recvMqttPubrel
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Pubrel
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.6

Field Name : recvMqttPubrec
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Pubrec
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.5

Field Name : recvMqttPuback
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Puback
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.4

Field Name : recvMqttPublish
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Publish
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.3

Field Name : recvMqttConnack
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Description : MQTT Connack
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.2

Field Name : recvMqttConnect
Field Type : CounterBasedGauge64
Field Status : current
Description : MQTT Connect
OID : 1.3.6.1.4.1.22610.2.4.10.108.77.1.1

Field Name : clientEhloSaved
Field Type : CounterBasedGauge64
Field Status : current
Description : Client EHLO saved
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.75

Field Name : dropServerEhloOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Server EHLO_OK dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.74

Field Name : aflexMailFail
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex Mail event failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.73

Field Name : failToSaveClientEhlo
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed to save client EHLO
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.72

Field Name : sendServerEhlo
Field Type : CounterBasedGauge64
Field Status : current
Description : Proxy sends server EHLO
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.71

Field Name : recvClientCommandETRN
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client ETRN
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.70

Field Name : recvClientCommandTURN
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client TURN
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.69

Field Name : rserverSTARTTLSDisable
Field Type : CounterBasedGauge64
Field Status : current
Description : real server not support STARTTLS
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.68

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : serverSTARTTLSFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server side STARTTLS fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.67

Field Name : serverSTARTTLSInit
Field Type : CounterBasedGauge64
Field Status : current
Description : Init server side STARTTLS
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.66

Field Name : aflexLbReselectOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex lb reselect (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.65

Field Name : aflexLbReselect
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex lb reselect
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.64

Field Name : parseResonseLineFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse response line fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.63

Field Name : removeResonseLineFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Del response line fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.62

Field Name : insertResonseLineFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Ins response line fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.61

Field Name : parseRequestLineFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse request line fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.60

Field Name : lineTableExtendFail
Field Type : TABLE
Field Status : current
Description : Table extend fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.59

Field Name : lineTableExtend
Field Type : TABLE
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Table extend
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.58

Field Name : lineExtendFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Line extend fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.57

Field Name : lineExtend
Field Type : CounterBasedGauge64
Field Status : current
Description : Line extend
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.56

Field Name : lineAcrossPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Line across packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.55

Field Name : lineTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Line too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.54

Field Name : tooManyHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : Too many headers
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.53

Field Name : getAllHeadersFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Get all headers fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.52

Field Name : readRequestLineFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Read request line fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.51

Field Name : lbSwitchOk
Field Type : CounterBasedGauge64
Field Status : current
Description : LB switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.50

Field Name : lbSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : LB switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.49

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : clientDomainSwitchOk
Field Type : CounterBasedGauge64
Field Status : current
Description : Client domain sw (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.48

Field Name : clientDomainSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : Client domain switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.47

Field Name : recvServerUnknowReplyCode
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv server unknown-code
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.46

Field Name : recvServerServiceNotReady
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv server serv-not-rdy
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.45

Field Name : l4Switched
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.44

Field Name : tlsEstablished
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL session established
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.43

Field Name : sendServerCmdReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent server RSET
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.42

Field Name : sendClientNoCommand
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent client no-such-cmd
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.41

Field Name : sendClientTLSNotAvailable
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent client TLS-not-aval
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.40

Field Name : sendClientStartTLSFirst
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Sent client STARTTLS-1st
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.39

Field Name : sendClientGoAhead
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent client go-ahead
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.38

Field Name : sendClientCloseConnection
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent client close-conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.37

Field Name : sendClientServiceNotReady
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent client serv-not-rdy
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.36

Field Name : sendClientServiceReady
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent client serv-rdy
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.35

Field Name : recvClientCommandOthers
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client other cmds
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.34

Field Name : recvClientCommandSTARTTLS
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client STARTTLS
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.33

Field Name : recvClientCommandQUIT
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client QUIT
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.32

Field Name : recvClientCommandNOOP
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client NOOP
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.31

Field Name : recvClientCommandHELP
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client HELP
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.30

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : recvClientCommandEXPN
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client EXPN
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.29

Field Name : recvClientCommandVRFY
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client VRFY
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.28

Field Name : recvClientCommandRSET
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client RSET
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.27

Field Name : recvClientCommandDATA
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client DATA
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.26

Field Name : recvClientCommandRCPT
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client RCPT
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.25

Field Name : recvClientCommandMAIL
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client MAIL
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.24

Field Name : recvClientCommandHELO
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client HELO
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.23

Field Name : recvClientCommandEHLO
Field Type : CounterBasedGauge64
Field Status : current
Description : Recv client EHLO
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.22

Field Name : aflexSwitchedOk
Field Type : CounterBasedGauge64
Field Status : current
Description : aFlex switching (succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.21

Field Name : aflexSwitched
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : aFlex switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.20

Field Name : tcpOutReset
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP out reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.19

Field Name : slbSmtPsnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.18

Field Name : newServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection made
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.17

Field Name : serverPremClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Server premature close
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.16

Field Name : serverReselect
Field Type : CounterBasedGauge64
Field Status : current
Description : Server reselection
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.15

Field Name : reqOfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Request pkt out-of-order
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.14

Field Name : reqRetran
Field Type : CounterBasedGauge64
Field Status : current
Description : Request retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.13

Field Name : forwardReqDataFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward REQ data failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.12

Field Name : forwardReqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward request failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.11

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : serverSelectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.10

Field Name : parseReqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse request failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.9

Field Name : noTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : No tuple error
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.8

Field Name : serverReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Server reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.7

Field Name : clientReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Client reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.6

Field Name : noProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : No proxy error
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.5

Field Name : requestSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : SMTP requests (success)
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.4

Field Name : slbSmtRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : SMTP requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.3

Field Name : slbSmtTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.2

Field Name : slbSmtCurrProxy
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Current proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.30.1.1

Field Name : failBindMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.85

Field Name : singleMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.84

Field Name : serverConnFailBind
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.83

Field Name : serverConnGetFromList
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.82

Field Name : serverConnPutInList
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.81

Field Name : clientConnGetFromList
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.80

Field Name : clientConnPutInList
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.79

Field Name : enquireLinkRespSend
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.78

Field Name : enquireLinkSend
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.77

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : enquireLinkRespRecv
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.76

Field Name : enquireLinkRecv
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.75

Field Name : unbindConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.74

Field Name : bindConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.73

Field Name : selectServerFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fail to select server conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.72

Field Name : selectServerByConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Select server conn by client conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.71

Field Name : selectServerFromList
Field Type : CounterBasedGauge64
Field Status : current
Description : Select by roundbin
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.70

Field Name : selectServerByReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Select by request
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.69

Field Name : selectServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Server conn selection
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.68

Field Name : selectClientFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Select failed

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.67

Field Name : selectClientByConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Select by conn

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.66

Field Name : selectClientFromList

Field Type : CounterBasedGauge64

Field Status : current

Description : Select by roundbin

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.65

Field Name : selectClientByReq

Field Type : CounterBasedGauge64

Field Status : current

Description : Select by request

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.64

Field Name : selectClientConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Client conn selection

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.63

Field Name : acosRespDirectly

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of packet which AX responds directly

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.62

Field Name : invalidSeq

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.61

Field Name : pktTooSmall

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.60

Field Name : payloadFreed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.59

Field Name : payloadAllocd

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.58

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : msgProxyServerReset
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.57

Field Name : msgProxyClientReset
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.56

Field Name : msgProxyPipelineMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.55

Field Name : msgProxySplitPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.54

Field Name : msgProxyHoldMsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.53

Field Name : msgProxyDeprecatedConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.52

Field Name : msgProxyFailDcmsg
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.51

Field Name : msgProxyMagBack
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.50

Field Name : msgProxyL7ToL4
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.49

Field Name : msgProxyL4FromL4Send
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.48

Field Name : msgProxyToL4SendPkt

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.47

Field Name : msgProxyL4FromL7

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.46

Field Name : msgProxyL4ToL7

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.45

Field Name : msgProxyL7CpuFailed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.44

Field Name : msgProxyUnexpectedErr

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.43

Field Name : msgProxyFailAllocMem

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.42

Field Name : msgProxyFailSelectServer

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.41

Field Name : msgProxyNoVport

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.40

Field Name : msgProxyProcessMsgFail

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.39

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : msgProxyParseMsgFail

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.38

Field Name : msgProxyFailInsertServerConn

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.37

Field Name : msgProxyServerConnAlreadyExists

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.36

Field Name : msgProxyStartServerConnFailed

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.35

Field Name : msgProxyFailReservePconn

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.34

Field Name : msgProxyFailConstructServerConn

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.33

Field Name : msgProxyServerConnFailSnat

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.32

Field Name : msgProxyFailStartServerConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of server connection created failed

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.31

Field Name : msgProxyStartServerConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of server connection created successfully

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.30

Field Name : msgProxyCreateServerConn

Field Type : CounterBasedGauge64

Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Server conn created

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.29

Field Name : msgProxyServerFailSendPkt

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.28

Field Name : msgProxyServerExceedTmpBuff

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.27

Field Name : msgProxyServerFailSnat

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.26

Field Name : msgProxyServerFailSelecConnt

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.25

Field Name : msgProxyServerFailProcess

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.24

Field Name : msgProxyServerFailParse

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.23

Field Name : msgProxyServerFail

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of SMPP messages received from server but failed to forward to client

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.22

Field Name : msgProxyServerDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of the packet AX drop

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.21

Field Name : msgProxyServerIncomplete

Field Type : CounterBasedGauge64

Field Status : current

Description : Incomplete

OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.20

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : msgProxyServerSendSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent to client
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.19

Field Name : msgProxyServerRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : Server message rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.18

Field Name : msgProxyClientFailStartServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.17

Field Name : msgProxyClientFailSendPkt
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.16

Field Name : msgProxyClientExceedTmpBuff
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.15

Field Name : msgProxyClientFailSnat
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.14

Field Name : msgProxyClientFailProcess
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.13

Field Name : msgProxyClientFailParse
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.12

Field Name : msgProxyClientFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of SMPP messages received from client but failed to forward to server
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.11

Field Name : msgProxyClientConnection
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Connecting server
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.10

Field Name : msgProxyClientDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : AX responds directly
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.9

Field Name : msgProxyClientIncomplete
Field Type : CounterBasedGauge64
Field Status : current
Description : Incomplete
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.8

Field Name : msgProxyClientSendSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent to server
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.7

Field Name : msgProxyClientRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : Client message rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.6

Field Name : msgProxyMemFreed
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.5

Field Name : msgProxyMemCached
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.4

Field Name : msgProxyMemAllocd
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.3

Field Name : msgProxyTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SMPP Proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.2

Field Name : msgProxyCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr SMPP Proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.29.1.1

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : invalidServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid server - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.47

Field Name : clientNotCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : Client not cleaned - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.46

Field Name : serverNotCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : Server not cleaned - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.45

Field Name : oldServerCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : Old server cleaned - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.44

Field Name : transactionCleaned
Field Type : CounterBasedGauge64
Field Status : current
Description : Transaction cleaned - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.43

Field Name : udpDataEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Data event from UDP
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.42

Field Name : hpsFwdreqFailTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.41

Field Name : hpsFwdreqFailServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - server
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.40

Field Name : hpsFwdreqFailPersist
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - persist
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.39

Field Name : hpsFwdreqFailRoute
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Fwd req fail - route
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.38

Field Name : hpsFwdreqFailRport
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - rport
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.37

Field Name : hpsFwdreqFailBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail - buff
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.36

Field Name : hpsFwdreqFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Fwd req fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.35

Field Name : dataCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Data event callback fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.34

Field Name : estCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Est event callback fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.33

Field Name : estEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Est event from TCP
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.32

Field Name : serverSelectFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.31

Field Name : totalProxyEs
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conn - ES
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.30

Field Name : totalProxyServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conn - server
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.29

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : totalProxyClient
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conn - client
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.28

Field Name : totalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.27

Field Name : currProxyEs
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr proxy conn - ES
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.26

Field Name : currProxyServer
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr proxy conn - server
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.25

Field Name : currProxyClient
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr proxy conn - client
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.24

Field Name : currProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr proxy conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.23

Field Name : proxyV2Connection
Field Type : CounterBasedGauge64
Field Status : current
Description : counter for Proxy v2 connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.22

Field Name : proxyV1Connection
Field Type : CounterBasedGauge64
Field Status : current
Description : counter for Proxy v1 connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.21

Field Name : serverRstRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from server - response
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.20

Field Name : serverRstConnected
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : RST from server - connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.19

Field Name : serverRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from server - connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.18

Field Name : serverRstReq
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from server - request
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.17

Field Name : clientRstRsp
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from client - response
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.16

Field Name : clientRstConnected
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from client - connected
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.15

Field Name : clientRstConnecting
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from client - connecting
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.14

Field Name : clientRstReq
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from client - request
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.13

Field Name : serverRst
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from server
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.12

Field Name : clientRst
Field Type : CounterBasedGauge64
Field Status : current
Description : RST from client
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.11

Field Name : serverConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.10

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : errCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Err event callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.9

Field Name : errEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Err event from TCP
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.8

Field Name : wbufCbFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Wbuf event callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.7

Field Name : wbufEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Wbuf event from TCP
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.6

Field Name : serverFin
Field Type : CounterBasedGauge64
Field Status : current
Description : FIN from server
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.5

Field Name : clientFin
Field Type : CounterBasedGauge64
Field Status : current
Description : FIN from client
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.4

Field Name : dataEvent
Field Type : CounterBasedGauge64
Field Status : current
Description : Data event from TCP
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.3

Field Name : connNotExist
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn does not exist
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.2

Field Name : startServerConnSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Start Server Conn Success
OID : 1.3.6.1.4.1.22610.2.4.10.108.64.1.1

Field Name : slbHttp3Rejected
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : HTTP3 Rejected

OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.102

Field Name : allocFailTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : Memory Allocation Failures

OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.101

Field Name : connAllocError

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP/3 Connection Allocation Error

OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.100

Field Name : slbHttp3Fatal

Field Type : CounterBasedGauge64

Field Status : current

Description : Fatal Error

OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.99

Field Name : slbHttp3H3StreamCreationError

Field Type : CounterBasedGauge64

Field Status : current

Description : H3 Stream Creation Error

OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.98

Field Name : slbHttp3H3SettingsError

Field Type : CounterBasedGauge64

Field Status : current

Description : H3 Settings Error

OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.97

Field Name : slbHttp3H3IdError

Field Type : CounterBasedGauge64

Field Status : current

Description : H3 Id Error

OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.96

Field Name : slbHttp3H3GeneralProtocolError

Field Type : CounterBasedGauge64

Field Status : current

Description : H3 General Protocol Error

OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.95

Field Name : slbHttp3H3ClosedCriticalStream

Field Type : CounterBasedGauge64

Field Status : current

Description : H3 Closed Critical Stream

OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.94

Field Name : slbHttp3H3InternalError

Field Type : CounterBasedGauge64

Field Status : current

Description : H3 Internal Error

OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.93

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbHttp3H3MissingSettings
Field Type : CounterBasedGauge64
Field Status : current
Description : H3 Missing Settings
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.92

Field Name : slbHttp3H3FrameError
Field Type : CounterBasedGauge64
Field Status : current
Description : H3 Frame Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.91

Field Name : slbHttp3H3FrameUnexpected
Field Type : CounterBasedGauge64
Field Status : current
Description : H3 Frame Unexpected
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.90

Field Name : slbHttp3QpackDecoderStreamError
Field Type : CounterBasedGauge64
Field Status : current
Description : Qpack Decoder Stream Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.89

Field Name : slbHttp3QpackEncoderStreamError
Field Type : CounterBasedGauge64
Field Status : current
Description : Qpack Encoder Stream Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.88

Field Name : slbHttp3QpackDecompressionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Qpack Decompression Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.87

Field Name : slbHttp3IgnorePushPromise
Field Type : CounterBasedGauge64
Field Status : current
Description : Ignore Push Promise
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.86

Field Name : slbHttp3StreamNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.85

Field Name : slbHttp3IgnoreStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Ignore Stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.84

Field Name : slbHttp3QpackHeaderTooLarge
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Description : Qpack Header Too Large
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.83

Field Name : slbHttp3QpackFatal
Field Type : CounterBasedGauge64
Field Status : current
Description : Qpack Fatal
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.82

Field Name : slbHttp3TooLate
Field Type : CounterBasedGauge64
Field Status : current
Description : Too Late
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.81

Field Name : slbHttp3MalformedHttpMessaging
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed Http Messaging
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.80

Field Name : slbHttp3RemoveHttpHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Http Header
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.79

Field Name : slbHttp3MalformedHttpHeader
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed Http Header
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.78

Field Name : slbHttp3PushIdBlocked
Field Type : CounterBasedGauge64
Field Status : current
Description : Push Id Blocked
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.77

Field Name : slbHttp3StreamInUse
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream In Use
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.76

Field Name : slbHttp3Wouldblock
Field Type : CounterBasedGauge64
Field Status : current
Description : Wouldblock
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.75

Field Name : slbHttp3InvalidState
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid State
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.74

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbHttp3InvalidArgument
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Argument
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.73

Field Name : serverTotalBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bytes sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.72

Field Name : serverTotalBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bytes received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.71

Field Name : serverHeadingBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in HEADERS/DATA frame/stream heading on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.70

Field Name : serverHeadingBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in HEADERS/DATA frame/stream heading on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.69

Field Name : serverOtherFrameBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in other frames (SETTINGS, GOAWAY, PUSH_PROMISE etc) on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.68

Field Name : serverOtherFrameBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in other frames (SETTINGS, GOAWAY, PUSH_PROMISE etc) on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.67

Field Name : serverDataBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in DATA frames on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.66

Field Name : serverDataBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in DATA frames on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.65

Field Name : serverHeaderBytesSent

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in HEADER frames on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.64

Field Name : serverHeaderBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in HEADER frames on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.63

Field Name : serverDataFramesToApp
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frames passed to HTTP layer on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.62

Field Name : serverHeaderFramesToApp
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADER Frames passed to HTTP layer on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.61

Field Name : slbHttpServerFrameTypeUnknownRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.60

Field Name : slbHttpServerFrameTypeMaxPushIdSent
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX PUSH ID Frame sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.59

Field Name : slbHttpServerFrameTypeMaxPushIdRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX PUSH ID Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.58

Field Name : slbHttpServerFrameTypeGoawaySent
Field Type : CounterBasedGauge64
Field Status : current
Description : GOAWAY Frame sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.57

Field Name : slbHttpServerFrameTypeGoawayRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : GOAWAY Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.56

Field Name : slbHttpServerFrameTypePushPromiseSent
Field Type : CounterBasedGauge64
Field Status : current
Description : PUSH PROMISE Frame sent on server side

ACOS-SLB-STATS-MIB_acosSlb_oid_list

OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.55

Field Name : slbHttpServerFrameTypePushPromiseRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : PUSH PROMISE Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.54

Field Name : slbHttpServerFrameTypeSettingsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS Frame sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.53

Field Name : slbHttpServerFrameTypeSettingsRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.52

Field Name : slbHttpServerFrameTypeCancelPushSent
Field Type : CounterBasedGauge64
Field Status : current
Description : CANCEL PUSH Frame sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.51

Field Name : slbHttpServerFrameTypeCancelPushRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : CANCEL PUSH Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.50

Field Name : slbHttpServerFrameTypeDataSent
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.49

Field Name : slbHttpServerFrameTypeDataRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.48

Field Name : slbHttpServerFrameTypeHeadersSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADERS Frame sent on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.47

Field Name : slbHttpServerFrameTypeHeadersRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADERS Frame received on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.46

Field Name : clientTotalBytesSent

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bytes sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.45

Field Name : clientTotalBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bytes received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.44

Field Name : clientHeadingBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in HEADERS/DATA frame/stream heading on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.43

Field Name : clientHeadingBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in HEADERS/DATA frame/stream heading on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.42

Field Name : clientOtherFrameBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in other frames (SETTINGS, GOAWAY, PUSH_PROMISE etc) on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.41

Field Name : clientOtherFrameBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in other frames (SETTINGS, GOAWAY, PUSH_PROMISE etc) on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.40

Field Name : clientDataBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in DATA frames on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.39

Field Name : clientDataBytesRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received in DATA frames on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.38

Field Name : clientHeaderBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes sent in HEADER frames on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.37

Field Name : clientHeaderBytesRcvd
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Bytes received in HEADER frames on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.36

Field Name : clientDataFramesToApp
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frames passed to HTTP layer on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.35

Field Name : clientHeaderFramesToApp
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADER Frames passed to HTTP layer on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.34

Field Name : slbHttpClientFrameTypeUnknownRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.33

Field Name : slbHttpClientFrameTypeMaxPushIdSent
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX PUSH ID Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.32

Field Name : slbHttpClientFrameTypeMaxPushIdRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX PUSH ID Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.31

Field Name : slbHttpClientFrameTypeGoawaySent
Field Type : CounterBasedGauge64
Field Status : current
Description : GOAWAY Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.30

Field Name : slbHttpClientFrameTypeGoawayRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : GOAWAY Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.29

Field Name : slbHttpClientFrameTypePushPromiseSent
Field Type : CounterBasedGauge64
Field Status : current
Description : PUSH PROMISE Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.28

Field Name : slbHttpClientFrameTypePushPromiseRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : PUSH PROMISE Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.27

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbHttpClientFrameTypeSettingsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.26

Field Name : slbHttpClientFrameTypeSettingsRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.25

Field Name : slbHttpClientFrameTypeCancelPushSent
Field Type : CounterBasedGauge64
Field Status : current
Description : CANCEL PUSH Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.24

Field Name : slbHttpClientFrameTypeCancelPushRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : CANCEL PUSH Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.23

Field Name : slbHttpClientFrameTypeDataSent
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.22

Field Name : slbHttpClientFrameTypeDataRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.21

Field Name : slbHttpClientFrameTypeHeadersSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADERS Frame sent on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.20

Field Name : slbHttpClientFrameTypeHeadersRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADERS Frame received on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.19

Field Name : slbHttp3ServerOtherStreamsTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Streams on server side (control, decoder, encoder)
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.18

Field Name : slbHttp3ClientOtherStreamsTotal
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Total Other Streams on client side (control, decoder, encoder)
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.17

Field Name : slbHttp3ServerOtherStreamsCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : urrent Other Streams on server side (control, decoder, encoder)
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.16

Field Name : slbHttp3ClientOtherStreamsCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Other Streams on client side (control, decoder, encoder)
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.15

Field Name : slbHttp3ServerPushStreamsTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Push Streams on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.14

Field Name : slbHttp3ClientPushStreamsTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Push Streams on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.13

Field Name : slbHttp3ServerPushStreamsCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Push Streams on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.12

Field Name : slbHttp3ClientPushStreamsCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Push Streams on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.11

Field Name : slbHttp3ServerRequestStreamsTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request Streams on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.10

Field Name : slbHttp3ClientRequestStreamsTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request Streams on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.9

Field Name : slbHttp3ServerRequestStreamsCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Request Streams on server side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.8

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbHttp3ClientRequestStreamsCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Request Streams on client side
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.7

Field Name : slbHttp3ServerConnPeak
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak HTTP/3 Server Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.6

Field Name : slbHttp3ClientConnPeak
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak HTTP/3 Client Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.5

Field Name : slbHttp3ServerConnTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP/3 Server Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.4

Field Name : slbHttp3ClientConnTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP/3 Client Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.3

Field Name : slbHttp3ServerConnCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current HTTP/3 Server Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.2

Field Name : slbHttp3ClientConnCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current HTTP/3 Client Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.107.1.1

Field Name : streamCancelFloodDetected
Field Type : CounterBasedGauge64
Field Status : current
Description : stream cancel flood detected
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.123

Field Name : frameFloodDetected
Field Type : CounterBasedGauge64
Field Status : current
Description : frame flood detected
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.122

Field Name : transactionLimited
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : transaction_limited
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.121

Field Name : endStreamSent
Field Type : CounterBasedGauge64
Field Status : current
Description : End Stream Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.120

Field Name : endStreamRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : End Stream Recieved
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.119

Field Name : streamFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Free
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.118

Field Name : streamCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream Create
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.117

Field Name : currentStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.116

Field Name : http2Rejected
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP2 Rejected
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.115

Field Name : errSentHttp11Required
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - HTTP_1_1_REQUIRED
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.113

Field Name : errSentInadequateSecurity
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - INADEQUATE_SECURITY
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.112

Field Name : errSentYourCalm
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - ENHANCE_YOUR_CALM
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.111

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : errSentConnectErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - CONNECT_ERROR
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.110

Field Name : errSentCompressionErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - COMPRESSION_ERROR
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.109

Field Name : errSentCancel
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - CANCEL
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.108

Field Name : errSentRefusedStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - REFUSED_STREAM
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.107

Field Name : errSentFrameSizeErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - FRAME_SIZE_ERROR
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.106

Field Name : errSentStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - STREAM_CLOSED
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.105

Field Name : errSentSettingTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - SETTINGS_TIMEOUT
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.104

Field Name : errSentFlowControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - FLOW_CONTROL_ERROR
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.103

Field Name : errSentInternalErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Sent - INTERNAL_ERROR
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.102

Field Name : errSentProtoErr
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Error Sent - PROTOCOL_ERROR
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.101

Field Name : errSentTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Rent - Total
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.100

Field Name : errRcvdTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Rcvd - Total
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.99

Field Name : allocFailTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Alloc Fail - Total
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.98

Field Name : emptySettingsRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Empty SETTINGS Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.97

Field Name : settingsAckRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS ACK Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.96

Field Name : priorityFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : PRIORITY Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.95

Field Name : headersFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADERS Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.94

Field Name : dataFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.93

Field Name : continuationFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : CONTINUATION Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.92

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : controlFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Control Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.91

Field Name : slbHttp2PeakProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.90

Field Name : totalBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 total bytes sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.89

Field Name : totalBytesReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 total bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.88

Field Name : dataBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 data bytes sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.87

Field Name : dataBytesReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 data bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.86

Field Name : headerBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 header bytes sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.85

Field Name : headerBytesReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 header bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.84

Field Name : controlBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP/2 control frame bytes sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.83

Field Name : controlBytesReceived
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : HTTP/2 control frame bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.82

Field Name : frameHeaderBytesSent
Field Type : CounterBasedGauge64
Field Status : current
Description : frame header bytes sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.81

Field Name : frameHeaderBytesReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : frame header bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.80

Field Name : invalidWindowUpdate
Field Type : CounterBasedGauge64
Field Status : current
Description : window-update value out of range
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.79

Field Name : invalidSettingValue
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid setting-frame value
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.78

Field Name : trailersNoEndStream
Field Type : CounterBasedGauge64
Field Status : current
Description : trailers not marked as end-of-stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.77

Field Name : headersInterleaved
Field Type : CounterBasedGauge64
Field Status : current
Description : headers interleaved on streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.76

Field Name : invalidStreamId
Field Type : CounterBasedGauge64
Field Status : current
Description : received invalid stream ID
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.75

Field Name : invalidPushPromise
Field Type : CounterBasedGauge64
Field Status : current
Description : unexpected PUSH_PROMISE frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.74

Field Name : pushPromiseFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Push Promise Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.114

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : headersAfterContinuation
Field Type : CounterBasedGauge64
Field Status : current
Description : headers frame before CONTINUATION was complete
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.73

Field Name : invalidFrameDuringHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : frame before headers were complete
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.72

Field Name : continuationBeforeHeaders
Field Type : CounterBasedGauge64
Field Status : current
Description : CONTINUATION frame with no headers frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.71

Field Name : streamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : stream closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.70

Field Name : exceedsMaxWindowSizeStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Window Update with increment that results in exceeding max window
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.68

Field Name : zeroWindowSizeOnStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Window Update with zero increment rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.66

Field Name : closedStateUnexpectedFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unexpected frame received in closed state
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.65

Field Name : halfClosedRemoteStateUnexpectedFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unexpected frame received in half closed remote state
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.64

Field Name : reservedRemoteStateUnexpectedFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unexpected frame received in reserved remote state
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.63

Field Name : reservedLocalStateUnexpectedFrame
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Unexpected frame received in reserved local state
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.62

Field Name : idleStateUnexpectedFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unexpected frame received in idle state
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.61

Field Name : streamsGtMaxConcurStreams
Field Type : CounterBasedGauge64
Field Status : current
Description : Streams greater than max allowed concurrent streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.60

Field Name : headerPadlenGtFramePayload
Field Type : CounterBasedGauge64
Field Status : current
Description : Header padlen greater than frame payload size
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.59

Field Name : headerNoStream
Field Type : CounterBasedGauge64
Field Status : current
Description : header no stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.58

Field Name : cantAllocateWindowFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate WINDOW_UPDATE frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.57

Field Name : cantAllocateStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.56

Field Name : cantAllocatePingFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate PING frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.55

Field Name : cantAllocateGoawayFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate GOAWAY frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.54

Field Name : cantAllocateRstFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate RST_STREAM frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.53

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : buffAllocError
Field Type : CounterBasedGauge64
Field Status : current
Description : Buff alloc error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.52

Field Name : dataQueueAllocError
Field Type : CounterBasedGauge64
Field Status : current
Description : Data Queue Alloc Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.51

Field Name : wrongStreamState
Field Type : CounterBasedGauge64
Field Status : current
Description : Wrong Stream State
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.50

Field Name : badFrameTypeForStreamState
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad frame type for stream state
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.49

Field Name : cantAllocateSettingsFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate SETTINGS frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.48

Field Name : cantAllocateControlFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Cant allocate control frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.47

Field Name : badConnectionPreface
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad Connection Preface
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.46

Field Name : inflateHeaderFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Inflate Header Fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.45

Field Name : inflateAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : inflate alloc fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.44

Field Name : deflateAllocFail
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : deflate alloc fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.43

Field Name : http11Required
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP1.1 Required
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.42

Field Name : inadequateSecurity
Field Type : CounterBasedGauge64
Field Status : current
Description : inadequate security
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.41

Field Name : enhanceYourCalm
Field Type : CounterBasedGauge64
Field Status : current
Description : enhance your calm error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.40

Field Name : connectError
Field Type : CounterBasedGauge64
Field Status : current
Description : connect error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.39

Field Name : compressionError
Field Type : CounterBasedGauge64
Field Status : current
Description : compression error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.38

Field Name : cancel
Field Type : CounterBasedGauge64
Field Status : current
Description : cancel
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.37

Field Name : refusedStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Refused Stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.36

Field Name : frameSizeError
Field Type : CounterBasedGauge64
Field Status : current
Description : Frame Size Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.35

Field Name : settingsTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Settings Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.34

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : flowControlError
Field Type : CounterBasedGauge64
Field Status : current
Description : Flow Control Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.33

Field Name : dataNoStream
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame Rcvd on non-existent stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.32

Field Name : errorMaxInvalidStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Invalid Stream Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.31

Field Name : invalidFrameSize
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Frame Size Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.29

Field Name : splitBuffFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Splitting Buffer Failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.28

Field Name : proxyAllocError
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP2 Proxy alloc Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.27

Field Name : internalError
Field Type : CounterBasedGauge64
Field Status : current
Description : Internal Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.26

Field Name : protocolError
Field Type : CounterBasedGauge64
Field Status : current
Description : Protocol Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.25

Field Name : dataToApp
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame to HTTP
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.24

Field Name : headerToApp
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : HEADER Frame to HTTP
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.23

Field Name : goawayFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : GOAWAY Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.22

Field Name : rstFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : RST_STREAM Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.21

Field Name : windowUpdateFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : WINDOW_UPDATE Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.20

Field Name : pingFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : PING Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.19

Field Name : emptySettingsSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Empty SETTINGS Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.18

Field Name : settingsAckSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS ACK Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.17

Field Name : settingsFrameSent
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS Frame Sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.16

Field Name : connectionPrefaceSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Connection preface sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.15

Field Name : unknownFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown Frame Recvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.14

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : dataFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : DATA Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.13

Field Name : priorityFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : PRIORITY Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.12

Field Name : goawayFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : GOAWAY Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.11

Field Name : pingFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : PING Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.10

Field Name : windowUpdateFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : WINDOW_UPDATE Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.9

Field Name : settingsFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : SETTINGS Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.8

Field Name : rstFrameRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : RST_STREAM Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.7

Field Name : continuationFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : CONTINUATION Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.6

Field Name : headersFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : HEADERS Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.5

Field Name : controlFrame
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Control Frame Rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.4

Field Name : connectionPrefaceRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Connection preface rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.3

Field Name : slbHttp2TotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.2

Field Name : slbHttp2CurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.63.1.1

Field Name : sessionClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Session close
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.84

Field Name : httpDataStreamClose
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP data stream already closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.83

Field Name : httpHdrStreamClose
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP header stream already closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.82

Field Name : httpErrStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP error stream already closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.81

Field Name : httpCloseStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP close stream already closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.80

Field Name : finStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP FIN stream already closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.79

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : newStreamSessionDel
Field Type : CounterBasedGauge64
Field Status : current
Description : New Stream after Session delete
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.78

Field Name : sessionNeedsRequeue
Field Type : CounterBasedGauge64
Field Status : current
Description : Session needs requeue
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.77

Field Name : closeStreamNotHttpProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Close Stream not http-proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.76

Field Name : httpDataStreamNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP data stream not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.75

Field Name : httpDataSessionClose
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP data session close
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.74

Field Name : headerCompressFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Header compress fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.73

Field Name : compressCtxAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Compression context allocation fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.72

Field Name : headerAfterSessionClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Header after session close
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.71

Field Name : invalidVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid version
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.70

Field Name : invalidFrameSize
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Invalid frame size
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.69

Field Name : dataOnClosedStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Data on closed stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.68

Field Name : unknownControlFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown control frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.67

Field Name : invalidWindowSize
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid window size
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.66

Field Name : windowNoStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Window update no stream found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.65

Field Name : clientRstNoStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Close RST stream not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.64

Field Name : synReplyAlrRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN reply already received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.63

Field Name : synUnidir
Field Type : CounterBasedGauge64
Field Status : current
Description : Unidirectional SYN
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.62

Field Name : synStreamExistOrEven
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream already exists
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.61

Field Name : streamLtPrev
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream id less than previous
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.60

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : synAfterGoaway
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN after goaway
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.59

Field Name : decompressFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Decompress fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.58

Field Name : nameValueNoMustHave
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value no must have
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.57

Field Name : nameValueTrasnferEncod
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value transfer encoding
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.56

Field Name : nameValueProxyConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value proxy-connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.55

Field Name : nameValueKeepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value keep alive
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.54

Field Name : nameValueConnection
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.53

Field Name : nameValueInvalidHttpVer
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value invalid http version
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.52

Field Name : nameValueZeroLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Name value zero name length
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.51

Field Name : nameValueTotalLenEx
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Name value total length exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.50

Field Name : requestHeaderAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Request/Header allocation fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.49

Field Name : httpConnAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP connection allocation fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.48

Field Name : streamAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream alloc fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.47

Field Name : maxConcurrentStreamLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Max concurrent stream limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.46

Field Name : closeSessionAlreadyClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Closing closed session
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.45

Field Name : closeStreamSessionClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream close session close
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.44

Field Name : closeStreamAlreadyClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Closing closed stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.43

Field Name : closeStreamStreamNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Close stream stream not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.42

Field Name : closeStreamSessionNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Close stream session not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.41

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : streamFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.40

Field Name : serverRstCloseStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST close stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.39

Field Name : finCloseSession
Field Type : CounterBasedGauge64
Field Status : current
Description : FIN close session
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.38

Field Name : ctxAllocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Context alloc fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.37

Field Name : dataCbNoTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Data callback no tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.36

Field Name : estCbNoTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Est callback no tuple
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.35

Field Name : dataNoStreamGoawayClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Data no stream and no goaway and close session
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.34

Field Name : dataNoStreamNoGoaway
Field Type : CounterBasedGauge64
Field Status : current
Description : Data no stream and no goaway
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.33

Field Name : dataNoStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Data no stream found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.32

Field Name : dataFrame
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Data frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.31

Field Name : pingFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Ping frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.30

Field Name : windowFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Window update frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.29

Field Name : settingsFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Setting frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.28

Field Name : headersFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Headers frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.27

Field Name : synReplyFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN reply frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.26

Field Name : synFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN stream frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.25

Field Name : controlFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Control frame received
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.24

Field Name : slbSpdyProxySessionErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Session err
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.23

Field Name : streamErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream err
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.22

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : streamClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream close
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.21

Field Name : slbSpdyProxyServerFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Server FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.20

Field Name : slbSpdyProxyClientFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Client FIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.19

Field Name : streamNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : STREAM not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.18

Field Name : pingSent
Field Type : CounterBasedGauge64
Field Status : current
Description : PING sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.17

Field Name : deflateCtx
Field Type : CounterBasedGauge64
Field Status : current
Description : Deflate context
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.16

Field Name : inflateCtx
Field Type : CounterBasedGauge64
Field Status : current
Description : Inflate context
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.15

Field Name : tcpErr
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP sock error
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.14

Field Name : serverGoaway
Field Type : CounterBasedGauge64
Field Status : current
Description : Server GOAWAY sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.13

Field Name : clientGoaway
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.12

Field Name : serverRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Server RST sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.11

Field Name : clientRst
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.10

Field Name : totalStreamSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Streams(succ)
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.9

Field Name : totalStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.8

Field Name : currStream
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.7

Field Name : totalV3Proxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Version 3 Streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.6

Field Name : totalV2Proxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Version 2 Streams
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.5

Field Name : totalHttpProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HTTP Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.4

Field Name : currHttpProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr HTTP Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.3

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : slbSpdyProxyTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.2

Field Name : slbSpdyProxyCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Proxy Conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.28.1.1

Field Name : serverTlsConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Server TLS conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.14

Field Name : clientTlsConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Client TLS conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.13

Field Name : targetSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Target ID switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.12

Field Name : senderSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Sender ID switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.11

Field Name : defaultSwitching
Field Type : CounterBasedGauge64
Field Status : current
Description : Default switching
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.10

Field Name : insertClientip
Field Type : CounterBasedGauge64
Field Status : current
Description : Insert client IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.9

Field Name : serverErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Server fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.7

Field Name : clientErr
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Client fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.6

Field Name : slbFixSnatFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Source NAT failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.5

Field Name : slbFixNoroute
Field Type : CounterBasedGauge64
Field Status : current
Description : No route failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.4

Field Name : slbFixSvrSelFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Server selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.3

Field Name : slbFixTotalProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.2

Field Name : slbFixCurrProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Current proxy conns
OID : 1.3.6.1.4.1.22610.2.4.10.108.27.1.1

Field Name : incAflowLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Inc aFlow limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.11

Field Name : reuseServerIdleConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Reuse idle server conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.10

Field Name : openNewServerConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Open new server conn
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.9

Field Name : errorResumeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Resume conn by error
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.8

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : retryResumeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Resume conn by retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.7

Field Name : tryToResumeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Resume conn by trying
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.6

Field Name : timerResumeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Resume conn by timer
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.5

Field Name : eventResumeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Resume conn by event
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.4

Field Name : resumeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Resume connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.3

Field Name : pauseConnFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Pause connection fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.2

Field Name : pauseConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Pause connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.26.1.1

Field Name : currentHttp2ConnInThePool
Field Type : CounterBasedGauge64
Field Status : current
Description : Current http2 conn in the pool
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.19

Field Name : currentHttp1ConnInThePool
Field Type : CounterBasedGauge64
Field Status : current
Description : Current http1 conn in the pool
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.18

Field Name : zeroPconnBindValue
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Zero current pconn bind counter value
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.17

Field Name : zeroPconnValue
Field Type : CounterBasedGauge64
Field Status : current
Description : Zero current pconn counter value
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.16

Field Name : notRemoveFromRport
Field Type : CounterBasedGauge64
Field Status : current
Description : Not remove from list
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.15

Field Name : slbConnectionReuseResumeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Resume request
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.14

Field Name : slbConnectionReusePauseConnFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Pause request fail
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.13

Field Name : slbConnectionReusePauseConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Pause request
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.12

Field Name : unboundDataRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : Unbound data rcvd
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.11

Field Name : missResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Missed resp
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.10

Field Name : longResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Long resp
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.9

Field Name : delayUnbind
Field Type : CounterBasedGauge64
Field Status : current
Description : Delayed unbind
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.8

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : ntermiErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total terminated by err
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.7

Field Name : ntermi
Field Type : CounterBasedGauge64
Field Status : current
Description : Total terminated
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.6

Field Name : nestab
Field Type : CounterBasedGauge64
Field Status : current
Description : Total established
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.5

Field Name : nunbind
Field Type : CounterBasedGauge64
Field Status : current
Description : Total unbind
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.4

Field Name : nbind
Field Type : CounterBasedGauge64
Field Status : current
Description : Total bind
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.3

Field Name : currentActive
Field Type : CounterBasedGauge64
Field Status : current
Description : Active persist
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.2

Field Name : currentOpen
Field Type : CounterBasedGauge64
Field Status : current
Description : Open persist
OID : 1.3.6.1.4.1.22610.2.4.10.108.25.1.1

Field Name : portOutOfRange
Field Type : CounterBasedGauge64
Field Status : current
Description : Drop Data Port out of range
OID : 1.3.6.1.4.1.22610.2.4.10.108.24.1.2

Field Name : slbFtpDataSessionNum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Data Sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.24.1.1

Field Name : slbVirtualServerPortSTable
Field Type : TABLE

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1

Field Name : slbVirtualServerPortSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1

Field Name : dnsrrlNxExceed

Field Type : CounterBasedGauge64

Field Status : current

Description : DNS Response-Rate-Limiting NX Responses Exceed Limit

OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.101

Field Name : http2ClientIdleTimeout

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP2 Client Idle Timeout

OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.100

Field Name : http1ClientIdleTimeout

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP1 Client Idle Timeout

OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.99

Field Name : dnsrrlTotalTc

Field Type : CounterBasedGauge64

Field Status : current

Description : DNS Response-Rate-Limiting Total Responses Replied With Truncated

OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.98

Field Name : compressionMissTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of requests NOT compressed

OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.97

Field Name : compressionHitTotal

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of requests compressed

OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.96

Field Name : compressionMissBr

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of requests NOT compressed with brotli

OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.95

Field Name : compressionHitBr

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of requests compressed with brotli

OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.94

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : compressionBytesAfterTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Data out of compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.93

Field Name : compressionBytesBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Data into compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.92

Field Name : compressionBytesAfterBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data out of brotli compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.91

Field Name : compressionBytesBeforeBr
Field Type : CounterBasedGauge64
Field Status : current
Description : Data into brotli compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.90

Field Name : dnsRpzTriggerNsName
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Trigger NS Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.89

Field Name : dnsRpzTriggerQname
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Trigger Qname IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.88

Field Name : dnsRpzTriggerNsIp
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Trigger NS IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.87

Field Name : dnsRpzTriggerRespIp
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Trigger Response IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.86

Field Name : dnsRpzTriggerClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Trigger Client IP
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.85

Field Name : dnsRpzActionLocalData
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : DNS RPZ Action Local Data
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.84

Field Name : dnsRpzActionNodata
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Action NODATA
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.83

Field Name : dnsRpzActionNxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Action NXDOMAIN
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.82

Field Name : dnsRpzActionTcpOnly
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Action TCP Only
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.81

Field Name : dnsRpzActionPassThru
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Action Pass Through
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.80

Field Name : dnsRpzActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS RPZ Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.79

Field Name : dnsFilterClassOthersDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Class OTHERS Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.78

Field Name : dnsFilterClassAnyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Class ANY Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.77

Field Name : dnsFilterClassNoneDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Class NONE Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.76

Field Name : dnsFilterClassHesiodDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Class HESIOD Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.75

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : dnsFilterClassChaosDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Class CHAOS Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.74

Field Name : dnsFilterClassInternetDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Class INTERNET Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.73

Field Name : dnsFilterTypeOthersDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type OTHERS Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.72

Field Name : dnsFilterTypeAnyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type Any Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.71

Field Name : dnsFilterTypeTxtDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type TXT Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.70

Field Name : dnsFilterTypeSoaDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type SOA Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.69

Field Name : dnsFilterTypePtrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type PTR Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.68

Field Name : dnsFilterTypeSrvDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type SRV Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.67

Field Name : dnsFilterTypeNsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type NS Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.66

Field Name : dnsFilterTypeMxDrop
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : DNS Filter Type MX Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.65

Field Name : dnsFilterTypeCnameDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type CNAME Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.64

Field Name : dnsFilterTypeAaaaDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type AAAA Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.63

Field Name : dnsFilterTypeADrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Filter Type A Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.62

Field Name : totalDnsFilterClassDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total DNS Filter Class Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.61

Field Name : totalDnsFilterTypeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total DNS Filter Type Drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.60

Field Name : ipOnlyLbRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Packets processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.59

Field Name : ipOnlyLbFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Packets processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.58

Field Name : ipOnlyLbRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Bytes processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.57

Field Name : ipOnlyLbFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Bytes processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.56

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : dynamicMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic memory (bytes) used by the vport(alloc-free)
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.55

Field Name : dynamicMemoryFree
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic memory (bytes) allocated by the vport
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.54

Field Name : dynamicMemoryAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic memory (bytes) allocated by the vport
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.53

Field Name : throughputBitsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Throughput in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.52

Field Name : dnsrrlBadFqdn
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Response-Rate-Limiting Bad FQDN
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.51

Field Name : dnsrrlTotalSlipped
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Response-Rate-Limiting Total Responses Slipped
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.50

Field Name : dnsrrlTotalDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Response-Rate-Limiting Total Responses Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.49

Field Name : dnsrrlTotalAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Response-Rate-Limiting Total Responses Allowed
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.48

Field Name : currRespRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current response rate
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.47

Field Name : totalRespSucc
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Status : current
Description : Total successful responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.46

Field Name : totalResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Total response
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.45

Field Name : currResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Current response
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.44

Field Name : currReqRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current request rate
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.43

Field Name : totalRevPktsOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in reverse direction (outbound)
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.42

Field Name : totalRevBytesOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in reverse direction (outbound)
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.41

Field Name : totalFwdPktsOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in forward direction (outbound)
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.40

Field Name : totalFwdBytesOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in forward direction (outbound)
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.39

Field Name : outLatency
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Latency at Thunder
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.38

Field Name : inLatency
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Latency at Thunder
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.37

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : backendTimeToLastByte
Field Type : CounterBasedGauge64
Field Status : current
Description : Backend Time from Request to Response Last Byte
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.36

Field Name : backendTimeToFirstByte
Field Type : CounterBasedGauge64
Field Status : current
Description : Backend Time from Request to Response First Byte
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.35

Field Name : totalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.34

Field Name : currSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current SSL connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.33

Field Name : locConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Geo-location Connection count
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.32

Field Name : locDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : Geo-location Deny count
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.31

Field Name : locPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : Geo-location Permit count
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.30

Field Name : slowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Slowest response time
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.29

Field Name : fastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Fastest response time
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.28

Field Name : lastRspTime
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Last response time
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.27

Field Name : currConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connection rate
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.26

Field Name : slbSrvPortPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.25

Field Name : totalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total successful requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.24

Field Name : slbSrvPortTotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.23

Field Name : currReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Current requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.22

Field Name : compressionMissTemplateExclusion
Field Type : CounterBasedGauge64
Field Status : current
Description : Compression miss template exclusion
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.21

Field Name : compressionMissNoClient
Field Type : CounterBasedGauge64
Field Status : current
Description : Compression miss no client
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.20

Field Name : compressionMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of requests NOT compressed
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.19

Field Name : compressionHit
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of requests compressed
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.18

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : compressionBytesAfter
Field Type : CounterBasedGauge64
Field Status : current
Description : Data out of gzip compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.17

Field Name : compressionBytesBefore
Field Type : CounterBasedGauge64
Field Status : current
Description : Data into gzip compression engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.16

Field Name : esTotalFailureActions
Field Type : CounterBasedGauge64
Field Status : current
Description : Total failure actions
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.15

Field Name : totalMfDnsPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total MF DNS packets
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.14

Field Name : totalDnsPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total DNS packets processed
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.13

Field Name : totalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.12

Field Name : totalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.11

Field Name : totalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.10

Field Name : totalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.9

Field Name : slbSrvPortTotalConn
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Total connections established
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.8

Field Name : totalTcpConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP connections established
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.7

Field Name : totalL7Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L7 connections established
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.6

Field Name : totalL4Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L4 connections established
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.5

Field Name : slbSrvPortCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.4

Field Name : protocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.3

Field Name : portNumber
Field Type : INTEGER
Field Status : current
Description : Port
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : SLB Virtual Server Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.23.2.1.1.1.1

Field Name : slbServerGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.87.1.1

Field Name : slbServerGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.87.1.1.1

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbServerCurrRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.87.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : server-group name
OID : 1.3.6.1.4.1.22610.2.4.10.108.87.1.1.1.1

Field Name : slbServiceGroupSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1

Field Name : slbServiceGroupSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1

Field Name : serviceCurrConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connection counter overflow count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.13

Field Name : serviceResp5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 5xx count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.12

Field Name : serviceResp4xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 4xx count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.11

Field Name : serviceResp3xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 3xx count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.10

Field Name : serviceResp2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group response 2xx count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.9

Field Name : serviceRespCount
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Service Group response count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.8

Field Name : serviceReqCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group request count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.7

Field Name : serviceUnhealthyHost
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group unhealthy host count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.6

Field Name : serviceHealthyHost
Field Type : CounterBasedGauge64
Field Status : current
Description : Service Group healthy host count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.5

Field Name : servicePeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connection count for the Service Group
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.4

Field Name : serverSelectionFailReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Resets sent out for Service selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.3

Field Name : serverSelectionFailDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Drops due to Service selection failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.2

Field Name : slbServiceGroupName
Field Type : String
Field Status : current
Description : SLB Service Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.1.1.1.1

Field Name : slbServiceGroupMemberSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1

Field Name : slbServiceGroupMemberSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : stateFlaps
Field Type : CounterBasedGauge64
Field Status : current
Description : State flaps count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.23

Field Name : currConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : Current connection counter overflow count
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.22

Field Name : totalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.21

Field Name : currSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current SSL connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.20

Field Name : slbServiceGroupMemberSlowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Slowest response time
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.19

Field Name : slbServiceGroupMemberFastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Fastest response time
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.18

Field Name : slbServiceGroupMemberResponseTime
Field Type : CounterBasedGauge64
Field Status : current
Description : Response time
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.17

Field Name : slbServiceGroupMemberPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.16

Field Name : slbServiceGroupMemberTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total requests successful
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.15

Field Name : slbServiceGroupMemberTotalReq
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Total requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.14

Field Name : slbServiceGroupMemberCurrReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Current requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.13

Field Name : slbServiceGroupMemberTotalRevPktsInspectedStatusCodeNon5xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Total reverse packets inspected status code non 5xx
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.12

Field Name : slbServiceGroupMemberTotalRevPktsInspectedStatusCode2xx
Field Type : CounterBasedGauge64
Field Status : current
Description : Total reverse packets inspected status code 2xx
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.11

Field Name : slbServiceGroupMemberTotalRevPktsInspected
Field Type : CounterBasedGauge64
Field Status : current
Description : Total reverse packets inspected
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.10

Field Name : slbServiceGroupMemberTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.9

Field Name : slbServiceGroupMemberTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.8

Field Name : slbServiceGroupMemberTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.7

Field Name : slbServiceGroupMemberTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.6

Field Name : slbServiceGroupMemberTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.5

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : currConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.4

Field Name : slbServiceGroupMemberPort
Field Type : INTEGER
Field Status : current
Description : Port number
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.3

Field Name : slbServiceGroupMemberName
Field Type : String
Field Status : current
Description : Member name
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.2

Field Name : slbServiceGroupName
Field Type : String
Field Status : current
Description : SLB Service Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.22.3.1.1.1.1

Field Name : slbServerSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1

Field Name : slbServerSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1

Field Name : ipOnlyLbRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Packets processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.18

Field Name : ipOnlyLbFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Packets processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.17

Field Name : ipOnlyLbRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : IP-Only-LB Bytes processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.16

Field Name : ipOnlyLbFwdBytes
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Status : current
Description : IP-Only-LB Bytes processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.15

Field Name : totalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.14

Field Name : totalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.13

Field Name : totalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in reverse direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.12

Field Name : totalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes processed in forward direction
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.11

Field Name : totalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL connections established
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.10

Field Name : currSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Current SSL connections established
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.9

Field Name : totalReqSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Requests succeeded
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.8

Field Name : totalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Requests processed
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.7

Field Name : slbServerPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Peak number of established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.6

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbServerRevPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse Packets Processed
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.5

Field Name : slbServerFwdPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward Packets Processed
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.4

Field Name : slbServerTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.3

Field Name : slbServerCurrRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current established connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.2

Field Name : slbServerName
Field Type : String
Field Status : current
Description : Server Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.21.1.1.1.1

Field Name : slbTemplateLinkCostSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1

Field Name : slbTemplateLinkCostSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1

Field Name : intervalMaxThroughput
Field Type : CounterBasedGauge64
Field Status : current
Description : Link Cost max throughput per interval
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1.6

Field Name : intervalAvgThroughput
Field Type : CounterBasedGauge64
Field Status : current
Description : Link Cost average throughput per interval
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1.5

Field Name : linkTotalConn
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Link Cost total connection
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1.4

Field Name : intervalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Link Cost bytes processed in forward direction per interval
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1.3

Field Name : linkTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : Total bytes fwd for link
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Server Link-Cost Template Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.39.1.1.1.1

Field Name : slbTemplateServerSshSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.17.1.1

Field Name : slbTemplateServerSshSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.17.1.1.1

Field Name : forwardingErrors
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.17.1.1.1.4

Field Name : failedHandshakes
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.17.1.1.1.3

Field Name : successfulHandshakes
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.17.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Server SSH Template Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.17.1.1.1.1

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbTemplatePolicySTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1

Field Name : slbTemplatePolicySEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1

Field Name : expClientHelloNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Expected Client HELLO requests not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.11

Field Name : fwdPolicySourceMatchNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward-policy requests without matching source rule
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.10

Field Name : fwdPolicyPolicyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of forward-policy requests dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.9

Field Name : fwdPolicyForwardToProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of forward-policy requests forwarded to proxy
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.8

Field Name : fwdPolicyForwardToServiceGroup
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of forward-policy requests forwarded to service group
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.7

Field Name : fwdPolicyForwardToInternet
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of forward-policy requests forwarded to internet
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.6

Field Name : fwdPolicyHits
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of forward-policy requests for this policy template
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.5

Field Name : fwdPolicySnatFail
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Forward-policy source-nat translation failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.4

Field Name : fwdPolicyDnsOutstanding
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward-policy current DNS outstanding requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.3

Field Name : fwdPolicyDnsUnresolved
Field Type : CounterBasedGauge64
Field Status : current
Description : Forward-policy unresolved DNS queries
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Policy template name
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.13.1.1.1.1

Field Name : slbTemplateClientSshSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.5.1.1

Field Name : slbTemplateClientSshSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.5.1.1.1

Field Name : forwardingErrors
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.5.1.1.1.4

Field Name : failedHandshakes
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.5.1.1.1.3

Field Name : successfulHandshakes
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.5.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Client SSH Template Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.5.1.1.1.1

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbTemplateClientSslSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1

Field Name : slbTemplateClientSslSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1

Field Name : malicious
Field Type : CounterBasedGauge64
Field Status : current
Description : Malicious level(1-20)
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.98

Field Name : suspicious
Field Type : CounterBasedGauge64
Field Status : current
Description : Suspicious level(21-40)
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.97

Field Name : moderateRisk
Field Type : CounterBasedGauge64
Field Status : current
Description : Moderate-risk level(41-60)
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.96

Field Name : lowRisk
Field Type : CounterBasedGauge64
Field Status : current
Description : Low-risk level(61-80)
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.95

Field Name : trustworthy
Field Type : CounterBasedGauge64
Field Status : current
Description : Trustworthy level(81-100)
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.94

Field Name : otherCategory
Field Type : CounterBasedGauge64
Field Status : current
Description : other category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.93

Field Name : uncategorised
Field Type : CounterBasedGauge64
Field Status : current
Description : uncategorised
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.92

Field Name : illegalPornography
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : illegal pornography eg. child sexual abuse
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.91

Field Name : nudityArtistic
Field Type : CounterBasedGauge64
Field Status : current
Description : artistic nudity
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.90

Field Name : generativeAi
Field Type : CounterBasedGauge64
Field Status : current
Description : generative ai category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.89

Field Name : lowThcCannabisProducts
Field Type : CounterBasedGauge64
Field Status : current
Description : low-thc cannabis products
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.88

Field Name : dnsOverHttps
Field Type : CounterBasedGauge64
Field Status : current
Description : dns over https category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.87

Field Name : selfHarm
Field Type : CounterBasedGauge64
Field Status : current
Description : self harm category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.86

Field Name : dummyItem
Field Type : CounterBasedGauge64
Field Status : current
Description : dummy item category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.85

Field Name : foodAndDining
Field Type : CounterBasedGauge64
Field Status : current
Description : food and dining category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.84

Field Name : webHostingSites
Field Type : CounterBasedGauge64
Field Status : current
Description : web hosting sites category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.83

Field Name : motorVehicles
Field Type : CounterBasedGauge64
Field Status : current
Description : motor vehicles category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.82

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : recreationAndHobbies
Field Type : CounterBasedGauge64
Field Status : current
Description : recreation and hobbies category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.81

Field Name : fashionAndBeauty
Field Type : CounterBasedGauge64
Field Status : current
Description : fashion and beauty category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.80

Field Name : imageAndVideoSearch
Field Type : CounterBasedGauge64
Field Status : current
Description : image and video search category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.79

Field Name : privateIPAddresses
Field Type : CounterBasedGauge64
Field Status : current
Description : private IP addresses category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.78

Field Name : alcoholAndTobacco
Field Type : CounterBasedGauge64
Field Status : current
Description : alcohol and tobacco category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.77

Field Name : parkedDomains
Field Type : CounterBasedGauge64
Field Status : current
Description : parked domains category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.76

Field Name : dynamicallyGeneratedContent
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamically generated content category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.75

Field Name : openHTTPProxies
Field Type : CounterBasedGauge64
Field Status : current
Description : open HTTP proxies category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.74

Field Name : unconfirmedSPAMSources
Field Type : CounterBasedGauge64
Field Status : current
Description : unconfirmed SPAM sources category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.73

Field Name : spamUrlHits
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : SPAM URLs category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.72

Field Name : confirmedSPAMSources
Field Type : CounterBasedGauge64
Field Status : current
Description : confirmed SPAM sources category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.71

Field Name : healthAndMedicine
Field Type : CounterBasedGauge64
Field Status : current
Description : health and medicine category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.70

Field Name : abortion
Field Type : CounterBasedGauge64
Field Status : current
Description : abortion category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.69

Field Name : botNets
Field Type : CounterBasedGauge64
Field Status : current
Description : bot nets category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.68

Field Name : internetCommunications
Field Type : CounterBasedGauge64
Field Status : current
Description : internet communications category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.67

Field Name : cdnHits
Field Type : CounterBasedGauge64
Field Status : current
Description : content delivery networks category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.66

Field Name : illegal
Field Type : CounterBasedGauge64
Field Status : current
Description : illegal category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.65

Field Name : newsAndMedia
Field Type : CounterBasedGauge64
Field Status : current
Description : news and media category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.64

Field Name : nudity
Field Type : CounterBasedGauge64
Field Status : current
Description : nudity category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.63

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : government
Field Type : CounterBasedGauge64
Field Status : current
Description : government category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.62

Field Name : music
Field Type : CounterBasedGauge64
Field Status : current
Description : music category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.61

Field Name : spywareAndAdware
Field Type : CounterBasedGauge64
Field Status : current
Description : spyware and adware category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.60

Field Name : proxyAvoidAndAnonymizers
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy avoid and anonymizers category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.59

Field Name : phishingAndOtherFraud
Field Type : CounterBasedGauge64
Field Status : current
Description : phishing and other fraud category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.58

Field Name : malwareSites
Field Type : CounterBasedGauge64
Field Status : current
Description : malware sites category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.57

Field Name : webBasedEmail
Field Type : CounterBasedGauge64
Field Status : current
Description : web based email category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.56

Field Name : gross
Field Type : CounterBasedGauge64
Field Status : current
Description : gross category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.55

Field Name : cheating
Field Type : CounterBasedGauge64
Field Status : current
Description : cheating category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.54

Field Name : webAdvertisements
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : web advertisements category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.53

Field Name : internetPortals
Field Type : CounterBasedGauge64
Field Status : current
Description : internet portals category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.52

Field Name : searchEngines
Field Type : CounterBasedGauge64
Field Status : current
Description : search engines category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.51

Field Name : keyloggersAndMonitoring
Field Type : CounterBasedGauge64
Field Status : current
Description : keyloggers and monitoring category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.50

Field Name : violence
Field Type : CounterBasedGauge64
Field Status : current
Description : violence category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.49

Field Name : personalStorage
Field Type : CounterBasedGauge64
Field Status : current
Description : personal storage category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.48

Field Name : hateAndRacism
Field Type : CounterBasedGauge64
Field Status : current
Description : hate and racism category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.47

Field Name : kids
Field Type : CounterBasedGauge64
Field Status : current
Description : kids category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.46

Field Name : questionable
Field Type : CounterBasedGauge64
Field Status : current
Description : questionable category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.45

Field Name : swimsuitsAndIntimateApparel
Field Type : CounterBasedGauge64
Field Status : current
Description : swimsuits and intimate apparel category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.44

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : sports
Field Type : CounterBasedGauge64
Field Status : current
Description : sports category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.43

Field Name : onlineGreetingCards
Field Type : CounterBasedGauge64
Field Status : current
Description : online greeting cards category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.42

Field Name : educationalInstitutions
Field Type : CounterBasedGauge64
Field Status : current
Description : educational institutions category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.41

Field Name : society
Field Type : CounterBasedGauge64
Field Status : current
Description : society category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.40

Field Name : huntingAndFishing
Field Type : CounterBasedGauge64
Field Status : current
Description : hunting and fishing category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.39

Field Name : payToSurf
Field Type : CounterBasedGauge64
Field Status : current
Description : pay to surf category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.38

Field Name : weapons
Field Type : CounterBasedGauge64
Field Status : current
Description : weapons category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.37

Field Name : philosophyAndPolitics
Field Type : CounterBasedGauge64
Field Status : current
Description : philosophy and politics category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.36

Field Name : games
Field Type : CounterBasedGauge64
Field Status : current
Description : games category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.35

Field Name : hacking
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : hacking category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.34

Field Name : marijuana
Field Type : CounterBasedGauge64
Field Status : current
Description : marijuana category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.33

Field Name : peerToPeer
Field Type : CounterBasedGauge64
Field Status : current
Description : peer to peer category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.32

Field Name : sharewareAndFreeware
Field Type : CounterBasedGauge64
Field Status : current
Description : shareware and freeware category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.31

Field Name : referenceAndResearch
Field Type : CounterBasedGauge64
Field Status : current
Description : reference and research category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.30

Field Name : translation
Field Type : CounterBasedGauge64
Field Status : current
Description : translation category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.29

Field Name : gambling
Field Type : CounterBasedGauge64
Field Status : current
Description : gambling category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.28

Field Name : jobSearch
Field Type : CounterBasedGauge64
Field Status : current
Description : job search category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.27

Field Name : streamingMedia
Field Type : CounterBasedGauge64
Field Status : current
Description : streaming media category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.26

Field Name : localInformation
Field Type : CounterBasedGauge64
Field Status : current
Description : local information category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.25

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : legal
Field Type : CounterBasedGauge64
Field Status : current
Description : legal category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.24

Field Name : personalSitesAndBlogs
Field Type : CounterBasedGauge64
Field Status : current
Description : personal sites and blogs category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.23

Field Name : entertainmentAndArts
Field Type : CounterBasedGauge64
Field Status : current
Description : entertainment and arts category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.22

Field Name : religion
Field Type : CounterBasedGauge64
Field Status : current
Description : religion category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.21

Field Name : sexEducation
Field Type : CounterBasedGauge64
Field Status : current
Description : sex education category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.20

Field Name : dating
Field Type : CounterBasedGauge64
Field Status : current
Description : dating category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.19

Field Name : trainingAndTools
Field Type : CounterBasedGauge64
Field Status : current
Description : training and tools category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.18

Field Name : stockAdviceAndTools
Field Type : CounterBasedGauge64
Field Status : current
Description : stock advice and tools category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.17

Field Name : deadSites
Field Type : CounterBasedGauge64
Field Status : current
Description : dead sites category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.16

Field Name : socialNetwork
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : social network category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.15

Field Name : military
Field Type : CounterBasedGauge64
Field Status : current
Description : military category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.14

Field Name : homeAndGarden
Field Type : CounterBasedGauge64
Field Status : current
Description : home and garden category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.13

Field Name : adultAndPornography
Field Type : CounterBasedGauge64
Field Status : current
Description : adult and pornography category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.12

Field Name : drugs
Field Type : CounterBasedGauge64
Field Status : current
Description : drugs category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.11

Field Name : travel
Field Type : CounterBasedGauge64
Field Status : current
Description : travel category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.10

Field Name : cultAndOccult
Field Type : CounterBasedGauge64
Field Status : current
Description : cult and occult category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.9

Field Name : shopping
Field Type : CounterBasedGauge64
Field Status : current
Description : shopping category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.8

Field Name : auctions
Field Type : CounterBasedGauge64
Field Status : current
Description : auctions category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.7

Field Name : computerAndInternetInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : computer and internet info category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.6

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : businessAndEconomy
Field Type : CounterBasedGauge64
Field Status : current
Description : business and economy category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.5

Field Name : financialServices
Field Type : CounterBasedGauge64
Field Status : current
Description : financial services category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.4

Field Name : computerAndInternetSecurity
Field Type : CounterBasedGauge64
Field Status : current
Description : computer and internet security category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.3

Field Name : realEstate
Field Type : CounterBasedGauge64
Field Status : current
Description : real estate category
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.2

Field Name : slbTemplateClientSslName
Field Type : String
Field Status : current
Description : Client SSL Template Name
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.4.1.1.1.1

Field Name : slbTemplateCacheSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1

Field Name : slbTemplateCacheSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1

Field Name : slbTemplateCacheRspBr
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.34

Field Name : slbTemplateCacheHeaderSaveError
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.33

Field Name : slbTemplateCacheRspTypeStream
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.32

Field Name : slbTemplateCacheCleanedEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.31

Field Name : slbTemplateCacheAgingEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.30

Field Name : slbTemplateCacheReplacedEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.29

Field Name : slbTemplateCacheEntryNum

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.28

Field Name : slbTemplateCacheMemSize

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.27

Field Name : entryCreateFailures

Field Type : CounterBasedGauge64

Field Status : current

Description : slbTemplateCacheEntryCreateFailures, help entry_create_failures

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.26

Field Name : contentToosmall

Field Type : CounterBasedGauge64

Field Status : current

Description : slbTemplateCacheContentToosmall, help content_toosmall

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.25

Field Name : contentToobig

Field Type : CounterBasedGauge64

Field Status : current

Description : slbTemplateCacheContentToobig, help content_toobig

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.24

Field Name : slbTemplateCacheInvalidateMatch

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.23

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbTemplateCacheMatch
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.22

Field Name : slbTemplateCacheNocacheMatch
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.21

Field Name : slbTemplateCacheRspOther
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.20

Field Name : slbTemplateCacheRspDeflate
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.19

Field Name : slbTemplateCacheRspGzip
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.18

Field Name : slbTemplateCacheRspNoCompress
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.17

Field Name : slbTemplateCacheRspTypeOther
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.16

Field Name : slbTemplateCacheRspType304
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.15

Field Name : slbTemplateCacheRspTypeCE
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.14

Field Name : slbTemplateCacheRspTypeCL
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.13

Field Name : slbTemplateCacheNmResponse

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.12

Field Name : slbTemplateCacheImsRequest

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.11

Field Name : rvFailure

Field Type : CounterBasedGauge64

Field Status : current

Description : slbTemplateCacheRvFailure, help rv_failure

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.10

Field Name : slbTemplateCacheRvSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.9

Field Name : ncResHeader

Field Type : CounterBasedGauge64

Field Status : current

Description : slbTemplateCacheNcResHeader, help nc_res_header

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.8

Field Name : ncReqHeader

Field Type : CounterBasedGauge64

Field Status : current

Description : slbTemplateCacheNcReqHeader, help nc_req_header

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.7

Field Name : slbTemplateCacheCachingReq

Field Type : CounterBasedGauge64

Field Status : current

Description : Total requests to cache

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.6

Field Name : slbTemplateCacheTotalReq

Field Type : CounterBasedGauge64

Field Status : current

Description : Total requests received

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.5

Field Name : slbTemplateCacheBytesServed

Field Type : CounterBasedGauge64

Field Status : current

Description : Bytes served from cache

OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.4

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : slbTemplateCacheMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache misses
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.3

Field Name : slbTemplateCacheHits
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache hits
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.2

Field Name : slbTemplateCache
Field Type : String
Field Status : current
Description : Specify cache template name
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.2.1.1.1.1

Field Name : slbTemplateCaptchaInstanceSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.42.2.1.1

Field Name : slbTemplateCaptchaInstanceSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.42.2.1.1.1

Field Name : otherError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Other Error
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.42.2.1.1.1.8

Field Name : timeoutError
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.42.2.1.1.1.7

Field Name : jsonFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Failure JSON Response
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.42.2.1.1.1.5

Field Name : parseFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total JSON Response Parse Failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.42.2.1.1.1.4

Field Name : verifySucc
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Total Verification Success Response
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.42.2.1.1.1.3

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Request
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.42.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Specify captcha template name
OID : 1.3.6.1.4.1.22610.2.4.10.108.18.42.2.1.1.1.1

Field Name : nRespFInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with invalid rcode
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.25

Field Name : nRespFBadcookie
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADCOOKIE
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.24

Field Name : nRespFBadtrunc
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADTRUNC
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.23

Field Name : nRespFBadalg
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADALG
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.22

Field Name : nRespFBadname
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADNAME
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.21

Field Name : nRespFBadmode
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADMODE
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.20

Field Name : nRespFBadtime
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADTIME
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.19

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : nRespFBadkey
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADKEY
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.18

Field Name : nRespFBadvers
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode BADVERS
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.17

Field Name : nRespFDsotypeni
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode DSOTYPENI
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.16

Field Name : nRespFNotzone
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode NotZone
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.15

Field Name : nRespFNotauth
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode NotAuth
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.14

Field Name : nRespFNxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode NXRRSet
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.13

Field Name : nRespFYxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode YXRRSet
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.12

Field Name : nRespFYxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode YXDomain
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.11

Field Name : nRespFRefused
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode Refused
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.10

Field Name : nRespFNotimp
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Number of response failure with rcode NotImp
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.9

Field Name : nRespFNxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode NXDomain
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.8

Field Name : nRespFServfail
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode ServFail
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.7

Field Name : nRespFFormerr
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response failure with rcode FormErr
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.6

Field Name : nRespErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of response errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.5

Field Name : nResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.4

Field Name : nQueryDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries dropped due to full queue
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.3

Field Name : nQueryErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of query errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.2

Field Name : nQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of queries
OID : 1.3.6.1.4.1.22610.2.4.10.108.112.1.1

Field Name : secureGamingDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Secure Gaming dropped
OID : 1.3.6.1.4.1.22610.2.4.10.108.92.1.2

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : secureGamingPass
Field Type : CounterBasedGauge64
Field Status : current
Description : Secure Gaming passed
OID : 1.3.6.1.4.1.22610.2.4.10.108.92.1.1

Field Name : bypassServerIpSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Server IP sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.36

Field Name : bypassClientIpSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Client IP sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.35

Field Name : certInCache
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificates in cache used by HC SSLi App
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.34

Field Name : asyncConnLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : SSLi Async connections failures due to limit
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.33

Field Name : asyncConnTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : SSLi Async connections failures due to timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.32

Field Name : currConnInBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : Current buffered async connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.31

Field Name : totConnInBuff
Field Type : CounterBasedGauge64
Field Status : current
Description : Total buffered async connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.30

Field Name : bypassAdGroupSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass AD-group sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.29

Field Name : bypassUsernameSessions
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Bypass Username sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.28

Field Name : dropEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Drop ESNI sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.27

Field Name : bypassEsniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass ESNI sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.26

Field Name : resetNoSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Reset No SNI sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.25

Field Name : bypassNoSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass NO SNI sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.24

Field Name : bypassCertSanSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Cert SAN sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.23

Field Name : bypassCertIssuerSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Cert issuer sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.22

Field Name : bypassCertSubjectSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Cert Subject sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.21

Field Name : aflexBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass triggered by aFlex
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.20

Field Name : connectionsFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Connections failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.19

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : certificatesInCache
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificates in cache
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.18

Field Name : unsupportedSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : Unsupported SSL version
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.17

Field Name : revokedOcspResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Revoked OCSP Response
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.16

Field Name : invalidOcspStaplingResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid OCSP Stapling Response
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.15

Field Name : failedInCertificateSigning
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in Certificate signing
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.14

Field Name : failedInCertificateVerification
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in Certificate verification
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.13

Field Name : failedInTcp
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in TCP
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.12

Field Name : failedInCryptoOperations
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in crypto operations
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.11

Field Name : failedInSslHandshakes
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed in SSL handshakes
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.10

Field Name : bypassClientAuthSessions
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Bypass Client Auth sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.9

Field Name : bypassSniSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass SNI sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.8

Field Name : bypassFailsafeSslSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Bypass Failsafe SSL sessions
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.7

Field Name : connInspect
Field Type : CounterBasedGauge64
Field Status : current
Description : Connections inspected
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.6

Field Name : connBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : Connections bypassed
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.5

Field Name : certMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificate cache miss
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.4

Field Name : certHit
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificate cache hits
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.3

Field Name : certExpr
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificates expired
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.2

Field Name : certCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificates created
OID : 1.3.6.1.4.1.22610.2.4.10.108.17.1.1

Field Name : l7ProxyTransPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Proxy Transactions/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.15

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : l7ProxyConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Proxy Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.14

Field Name : gifwConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : GiFW Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.13

Field Name : fwConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : FW Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.12

Field Name : servSslConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Server SSL Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.11

Field Name : l7Bandwidth
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Bandwidth in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.10

Field Name : l4Bandwidth
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Bandwidth in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.9

Field Name : totalCurrConns
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Current Established Connections
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.8

Field Name : totalNewConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Total New Connections Established/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.7

Field Name : ipNatConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : IP NAT Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.6

Field Name : sslConnsPerSec
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : SSL Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.5

Field Name : l7TransPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Transactions/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.4

Field Name : l7ConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.3

Field Name : l4ConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.2

Field Name : totalThroughputBitsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Throughput in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.108.13.1.1

Field Name : crlOtherError
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL other errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.32

Field Name : crlCacheStatusRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL cache status revoked
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.31

Field Name : crlCacheStatusGood
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL cache status good
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.30

Field Name : crlResponseStatusUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL response status unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.29

Field Name : crlResponseStatusRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL response status revoked
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.28

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : crlResponseStatusGood
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL response status good
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.27

Field Name : crlUriUnsupported
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL URI unsupported
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.26

Field Name : crlUriHttps
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL URI https
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.25

Field Name : crlUriNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL URI not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.24

Field Name : crlConnectionError
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL connection errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.23

Field Name : crlResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.22

Field Name : crlRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : CRL requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.21

Field Name : ocspResponseNonceError
Field Type : CounterBasedGauge64
Field Status : current
Description : Log OCSP other errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.20

Field Name : ocspResponseNoNonce
Field Type : CounterBasedGauge64
Field Status : current
Description : Log OCSP other errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.19

Field Name : ocspOtherError
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Log OCSP other errors
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.18

Field Name : ocsCacheExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP cache expired
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.17

Field Name : ocsCacheMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP cache miss
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.16

Field Name : ocsCacheStatusRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP cache status revoked
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.15

Field Name : ocsCacheStatusGood
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP cache status good
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.14

Field Name : ocsResponseStatusUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP response status unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.13

Field Name : ocsResponseStatusRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP response status revoked
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.12

Field Name : ocsResponseStatusGood
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP response status good
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.11

Field Name : ocsUriUnsupported
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP URI unsupported
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.10

Field Name : ocsUriHttps
Field Type : CounterBasedGauge64
Field Status : current
Description : Log OCSP URI https
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.9

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : ocsUriNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP URI not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.8

Field Name : ocsConnectionError
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP connection error
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.7

Field Name : ocsResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP responses
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.6

Field Name : ocsRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP requests
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.5

Field Name : ocsChainStatusUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificate chain status unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.4

Field Name : ocsChainStatusRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificate chain status revoked
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.3

Field Name : ocsChainStatusGood
Field Type : CounterBasedGauge64
Field Status : current
Description : Certificate chain status good
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.2

Field Name : ocsStaplingResponseGood
Field Type : CounterBasedGauge64
Field Status : current
Description : OCSP stapling response good
OID : 1.3.6.1.4.1.22610.2.4.10.108.12.1.1

Field Name : badHandshakeLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad handshake length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.245

Field Name : unsupportedDigestType
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : unsupported digest type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.244

Field Name : noRequiredDigest
Field Type : CounterBasedGauge64
Field Status : current
Description : no required digest
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.243

Field Name : unsupportedEllipticCurve
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported elliptic curve
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.242

Field Name : cookieMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : cookie mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.241

Field Name : badEcpoint
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ecpoint
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.240

Field Name : badEcdsaSig
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ecdsa sig
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.239

Field Name : badEccCert
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ecc cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.238

Field Name : tlsInvalidEcpointformatList
Field Type : CounterBasedGauge64
Field Status : current
Description : tls invalid ecpointformat list
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.237

Field Name : multipleSgcRestarts
Field Type : CounterBasedGauge64
Field Status : current
Description : multiple sgc restarts
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.236

Field Name : ssl3ExtInvalidServernameType
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 ext invalid servername type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.235

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : ssl3ExtInvalidServername
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 ext invalid servername
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.234

Field Name : serverhelloTlsex
Field Type : CounterBasedGauge64
Field Status : current
Description : serverhello tlsex
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.233

Field Name : parseTlsex
Field Type : CounterBasedGauge64
Field Status : current
Description : parse tlsex
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.232

Field Name : clienthelloTlsex
Field Type : CounterBasedGauge64
Field Status : current
Description : clienthello tlsex
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.231

Field Name : x509VerificationSetupProblems
Field Type : CounterBasedGauge64
Field Status : current
Description : x509 verification setup problems
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.230

Field Name : x509Lib
Field Type : CounterBasedGauge64
Field Status : current
Description : x509 lib
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.229

Field Name : wrongVersionCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong version counter
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.228

Field Name : wrongSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong ssl version
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.227

Field Name : wrongSignatureSize
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong signature size
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.226

Field Name : wrongSignatureLength
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : wrong signature length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.225

Field Name : wrongCounterOfKeyBits
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong counter of key bits
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.224

Field Name : wrongMessageType
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong message type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.223

Field Name : wrongCipherReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : wrong cipher returned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.222

Field Name : writeBioNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : write bio not set
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.221

Field Name : unsupportedStatusType
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported status type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.220

Field Name : unsupportedSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported ssl version
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.219

Field Name : unsupportedProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported protocol
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.218

Field Name : unsupportedOption
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported option
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.217

Field Name : unsupportedCompressionAlgorithm
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported compression algorithm
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.216

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : unsupportedCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : unsupported cipher
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.215

Field Name : unknownState
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown state
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.214

Field Name : unknownSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown ssl version
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.213

Field Name : unknownRemoteErrorType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown remote error type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.212

Field Name : unknownProtocol
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown protocol
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.211

Field Name : unknownPkeyType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown pkey type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.210

Field Name : unknownKeyExchangeType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown key exchange type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.209

Field Name : unknownCipherType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown cipher type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.208

Field Name : unknownCipherReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown cipher returned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.207

Field Name : unknownCertificateType
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : unknown certificate type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.206

Field Name : unknownAlertType
Field Type : CounterBasedGauge64
Field Status : current
Description : unknown alert type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.205

Field Name : uninitialized
Field Type : CounterBasedGauge64
Field Status : current
Description : uninitialized
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.204

Field Name : unexpectedRecord
Field Type : CounterBasedGauge64
Field Status : current
Description : unexpected record
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.203

Field Name : unexpectedMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : unexpected message
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.202

Field Name : unableToLoadSsl3Sha1Routines
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to load ssl3 sha1 routines
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.201

Field Name : unableToLoadSsl3Md5Routines
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to load ssl3 md5 routines
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.200

Field Name : unableToLoadSsl2Md5Routines
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to load ssl2 md5 routines
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.199

Field Name : unableToFindSslMethod
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to find ssl method
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.198

Field Name : unableToFindPublicKeyParameters
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to find public key parameters
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.197

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : unableToFindDhParameters
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to find dh parameters
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.196

Field Name : unableToExtractPublicKey
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to extract public key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.195

Field Name : unableToDecodeDhCerts
Field Type : CounterBasedGauge64
Field Status : current
Description : unable to decode dh certs
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.194

Field Name : triedToUseUnsupportedCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : tried to use unsupported cipher
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.193

Field Name : tlsRsaEncryptedValueLengthIsWrong
Field Type : CounterBasedGauge64
Field Status : current
Description : tls rsa encrypted value length is wrong
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.192

Field Name : tlsPeerDidNotRespondWithCertList
Field Type : CounterBasedGauge64
Field Status : current
Description : tls peer did not respond with cert list
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.191

Field Name : tlsClientCertReqWithAnonCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : tls client cert req with anon cipher
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.190

Field Name : tlsv1AlertUserCancelled
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert user cancelled
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.189

Field Name : tlsv1AlertUnknownCa
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert unknown ca
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.188

Field Name : tlsv1AlertRecordOverflow
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : tlsv1 alert record overflow
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.187

Field Name : tlsv1AlertProtocolVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert protocol version
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.186

Field Name : tlsv1AlertNoRenegotiation
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert no renegotiation
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.185

Field Name : tlsv1AlertInternalError
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert internal error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.184

Field Name : tlsv1AlertInsufficientSecurity
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert insufficient security
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.183

Field Name : tlsv1AlertExportRestriction
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert export restriction
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.182

Field Name : tlsv1AlertDecryptError
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert decrypt error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.181

Field Name : tlsv1AlertDecryptionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert decryption failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.180

Field Name : tlsv1AlertDecodeError
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert decode error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.179

Field Name : tlsv1AlertAccessDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : tlsv1 alert access denied
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.178

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : sslSessionIdIsDifferent
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id is different
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.177

Field Name : sslSessionIdHasBadLength
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id has bad length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.176

Field Name : sslSessionIdContextTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id context too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.175

Field Name : sslSessionIdConflict
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id conflict
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.174

Field Name : sslSessionIdCallbackFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl session id callback failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.173

Field Name : sslLibraryHasNoCiphers
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl library has no ciphers
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.172

Field Name : sslHandshakeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl handshake failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.171

Field Name : sslCtxHasNoDefaultSslVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl ctx has no default ssl version
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.170

Field Name : sslv3AlertUnspportedCert
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert unspported cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.169

Field Name : sslv3AlertUnknownRemoteErrType
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Status : current
Description : sslv3 alert unknown remote err type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.168

Field Name : sslv3AlertUnexpectedMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert unexpected msg
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.167

Field Name : sslv3AlertPeerErrorUnsuppCertType
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error unsupp cert type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.166

Field Name : sslv3AlertPeerErrorNoCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error no cipher
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.165

Field Name : sslv3AlertPeerErrorNoCert
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error no cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.164

Field Name : sslv3AlertPeerErrorCert
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert peer error cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.163

Field Name : sslv3AlertNoCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert no certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.162

Field Name : sslv3AlertIllegalParameter
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert illegal parameter
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.161

Field Name : sslv3AlertHandshakeFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert handshake failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.160

Field Name : sslv3AlertDecompressionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert decompression failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.159

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : sslv3AlertCertificateUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert certificate unknown
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.158

Field Name : sslv3AlertCertificateRevoked
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert certificate revoked
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.157

Field Name : sslv3AlertCertificateExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert certificate expired
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.156

Field Name : sslv3AlertBadRecordMac
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert bad record mac
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.155

Field Name : sslv3AlertBadCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : sslv3 alert bad certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.154

Field Name : ssl3SessionIdTooShort
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 session id too short
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.153

Field Name : ssl3SessionIdTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl3 session id too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.152

Field Name : ssl2ConnectionIdTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl2 connection id too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.151

Field Name : ssl23DoingSessionIdReuse
Field Type : CounterBasedGauge64
Field Status : current
Description : ssl23 doing session id reuse
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.150

Field Name : signatureForNonSigningCertificate
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : signature for non signing certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.149

Field Name : shortRead
Field Type : CounterBasedGauge64
Field Status : current
Description : short read
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.148

Field Name : sessionIdContextUninitialized
Field Type : CounterBasedGauge64
Field Status : current
Description : session id context uninitialized
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.147

Field Name : scsvReceivedWhenRenegotiating
Field Type : CounterBasedGauge64
Field Status : current
Description : scsv received when renegotiating
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.146

Field Name : reuseCipherListNotZero
Field Type : CounterBasedGauge64
Field Status : current
Description : reuse cipher list not zero
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.145

Field Name : reuseCertTypeNotZero
Field Type : CounterBasedGauge64
Field Status : current
Description : reuse cert type not zero
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.144

Field Name : reuseCertLengthNotZero
Field Type : CounterBasedGauge64
Field Status : current
Description : reuse cert length not zero
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.143

Field Name : requiredCipherMissing
Field Type : CounterBasedGauge64
Field Status : current
Description : required cipher missing
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.142

Field Name : recordTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : record too small
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.141

Field Name : recordTooLarge
Field Type : CounterBasedGauge64
Field Status : current
Description : record too large
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.140

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : recordLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : record length mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.139

Field Name : readWrongPacketType
Field Type : CounterBasedGauge64
Field Status : current
Description : read wrong packet type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.138

Field Name : readBioNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : read bio not set
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.137

Field Name : publicKeyNotRsa
Field Type : CounterBasedGauge64
Field Status : current
Description : public key not rsa
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.136

Field Name : publicKeyIsNotRsa
Field Type : CounterBasedGauge64
Field Status : current
Description : public key is not rsa
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.135

Field Name : publicKeyEncryptError
Field Type : CounterBasedGauge64
Field Status : current
Description : public key encrypt error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.134

Field Name : protocolIsShutdown
Field Type : CounterBasedGauge64
Field Status : current
Description : protocol is shutdown
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.133

Field Name : problemsMappingCipherFunctions
Field Type : CounterBasedGauge64
Field Status : current
Description : problems mapping cipher functions
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.132

Field Name : preMacLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : pre mac length too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.131

Field Name : peerErrorUnsupportedCertificateType
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : peer error unsupported certificate type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.130

Field Name : peerErrorNoCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : peer error no cipher
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.129

Field Name : peerErrorNoCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : peer error no certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.128

Field Name : peerErrorCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : peer error certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.127

Field Name : peerError
Field Type : CounterBasedGauge64
Field Status : current
Description : peer error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.126

Field Name : peerDidNotReturnACertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : peer did not return a certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.125

Field Name : pathTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : path too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.124

Field Name : packetLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : packet length too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.123

Field Name : oldSessionCipherNotReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : old session cipher not returned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.122

Field Name : nullSslMethodPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : null ssl method passed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.121

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : nullSslCtx
Field Type : CounterBasedGauge64
Field Status : current
Description : null ssl ctx
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.120

Field Name : noVerifyCallback
Field Type : CounterBasedGauge64
Field Status : current
Description : no verify callback
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.119

Field Name : noSharedCipher
Field Type : CounterBasedGauge64
Field Status : current
Description : no shared cipher
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.118

Field Name : noPublickey
Field Type : CounterBasedGauge64
Field Status : current
Description : no publickey
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.117

Field Name : noProtocolsAvailable
Field Type : CounterBasedGauge64
Field Status : current
Description : no protocols available
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.116

Field Name : noPrivateKeyAssigned
Field Type : CounterBasedGauge64
Field Status : current
Description : no private key assigned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.115

Field Name : noPrivatekey
Field Type : CounterBasedGauge64
Field Status : current
Description : no privatekey
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.114

Field Name : noMethodSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no method specified
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.113

Field Name : noCompressionSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no compression specified
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.112

Field Name : noClientCertReceived
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : no client cert received
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.111

Field Name : noCipherMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : no cipher match
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.110

Field Name : noCipherList
Field Type : CounterBasedGauge64
Field Status : current
Description : no cipher list
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.109

Field Name : noCiphersSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no ciphers specified
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.108

Field Name : noCiphersPassed
Field Type : CounterBasedGauge64
Field Status : current
Description : no ciphers passed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.107

Field Name : noCiphersAvailable
Field Type : CounterBasedGauge64
Field Status : current
Description : no ciphers available
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.106

Field Name : noCertificateSpecified
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate specified
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.105

Field Name : noCertificateSet
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate set
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.104

Field Name : noCertificateReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate returned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.103

Field Name : noCertificateAssigned
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificate assigned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.102

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Name : noCertificatesReturned
Field Type : CounterBasedGauge64
Field Status : current
Description : no certificates returned
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.101

Field Name : nonSslv2InitialPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : non sslv2 initial packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.100

Field Name : missingVerifyMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : missing verify message
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.99

Field Name : missingTmpRsaPkey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing tmp rsa pkey
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.98

Field Name : missingTmpRsaKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing tmp rsa key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.97

Field Name : missingTmpDhKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing tmp dh key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.96

Field Name : missingRsaSigningCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing rsa signing cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.95

Field Name : missingRsaEncryptingCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing rsa encrypting cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.94

Field Name : missingRsaCertificate
Field Type : CounterBasedGauge64
Field Status : current
Description : missing rsa certificate
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.93

Field Name : missingExportTmpRsaKey
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : missing export tmp rsa key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.92

Field Name : missingExportTmpDhKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing export tmp dh key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.91

Field Name : missingDsaSigningCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dsa signing cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.90

Field Name : missingDhRsaCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dh rsa cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.89

Field Name : missingDhKey
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dh key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.88

Field Name : missingDhDsaCert
Field Type : CounterBasedGauge64
Field Status : current
Description : missing dh dsa cert
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.87

Field Name : messageTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : message too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.86

Field Name : mastKeyTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : mast key too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.85

Field Name : libraryHasNoCiphers
Field Type : CounterBasedGauge64
Field Status : current
Description : library has no ciphers
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.84

Field Name : libraryBug
Field Type : CounterBasedGauge64
Field Status : current
Description : library bug
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.83

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : lengthTooShort
Field Type : CounterBasedGauge64
Field Status : current
Description : length too short
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.82

Field Name : lengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : length mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.81

Field Name : krb5ServerTktSkew
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server tkt skew
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.80

Field Name : krb5ServerTktNotYetValid
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server tkt not yet valid
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.79

Field Name : krb5ServerTktExpired
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server tkt expired
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.78

Field Name : krb5ServerRdReq
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server rd_req
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.77

Field Name : krb5ServerInit
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server init
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.76

Field Name : krb5ServerBadTicket
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 server bad ticket
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.75

Field Name : krb5ClientMkReq
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client mk_req
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.74

Field Name : krb5ClientInit
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : krb5 client init
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.73

Field Name : krb5ClientGetCred
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client get cred
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.72

Field Name : krb5ClientCcPrincipal
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5 client cc principal
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.71

Field Name : krb5
Field Type : CounterBasedGauge64
Field Status : current
Description : krb5
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.70

Field Name : keyArgTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : key arg too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.69

Field Name : invalidTrust
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid trust
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.68

Field Name : invalidStatusResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid status response
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.67

Field Name : invalidPurpose
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid purpose
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.66

Field Name : invalidCommand
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid command
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.65

Field Name : invalidChallengeLength
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid challenge length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : inappropriateFallback
Field Type : CounterBasedGauge64
Field Status : current
Description : inappropriate fallback
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.63

Field Name : illegalPadding
Field Type : CounterBasedGauge64
Field Status : current
Description : illegal padding
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.62

Field Name : httpRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : http request
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.61

Field Name : httpsProxyRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : https proxy request
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.60

Field Name : gotAFinBeforeACcs
Field Type : CounterBasedGauge64
Field Status : current
Description : got a fin before a ccs
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.59

Field Name : extraDataInMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : extra data in message
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.58

Field Name : excessiveMessageSize
Field Type : CounterBasedGauge64
Field Status : current
Description : excessive message size
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.57

Field Name : errorInReceivedCipherList
Field Type : CounterBasedGauge64
Field Status : current
Description : error in received cipher list
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.56

Field Name : errorGeneratingTmpRsaKey
Field Type : CounterBasedGauge64
Field Status : current
Description : error generating tmp rsa key
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.55

Field Name : encryptedLengthTooLong
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : encrypted length too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.54

Field Name : digestCheckFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : digest check failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.53

Field Name : dhPublicValueLengthIsWrong
Field Type : CounterBasedGauge64
Field Status : current
Description : dh public value length is wrong
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.52

Field Name : decryptionFailedOrBadRecordMac
Field Type : CounterBasedGauge64
Field Status : current
Description : decryption failed or bad record mac
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.51

Field Name : decryptionFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : decryption failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.50

Field Name : dataLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : data length too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.49

Field Name : dataBetweenCcsAndFinished
Field Type : CounterBasedGauge64
Field Status : current
Description : data between ccs and finished
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.48

Field Name : connectionTypeNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : connection type not set
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.47

Field Name : connectionIdIsDifferent
Field Type : CounterBasedGauge64
Field Status : current
Description : connection id is different
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.46

Field Name : compressionLibraryError
Field Type : CounterBasedGauge64
Field Status : current
Description : compression library error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.45

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : compressionFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : compression failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.44

Field Name : compressedLengthTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : compressed length too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.43

Field Name : cipherTableSrcError
Field Type : TABLE
Field Status : current
Description : cipher table src error
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.42

Field Name : cipherOrHashUnavailable
Field Type : CounterBasedGauge64
Field Status : current
Description : cipher or hash unavailable
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.41

Field Name : cipherCodeWrongLength
Field Type : CounterBasedGauge64
Field Status : current
Description : cipher code wrong length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.40

Field Name : challengeIsDifferent
Field Type : CounterBasedGauge64
Field Status : current
Description : challenge is different
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.39

Field Name : certLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : cert length mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.38

Field Name : certificateVerifyFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : certificate verify failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.37

Field Name : ccsReceivedEarly
Field Type : CounterBasedGauge64
Field Status : current
Description : ccs received early
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.36

Field Name : caDnTooLong
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Status : current
Description : ca dn too long
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.35

Field Name : caDnLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : ca dn length mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.34

Field Name : bnLib
Field Type : CounterBasedGauge64
Field Status : current
Description : bn lib
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.33

Field Name : blockCipherPadIsWrong
Field Type : CounterBasedGauge64
Field Status : current
Description : block cipher pad is wrong
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.32

Field Name : bioNotSet
Field Type : CounterBasedGauge64
Field Status : current
Description : bio not set
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.31

Field Name : badWriteRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : bad write retry
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.30

Field Name : badState
Field Type : CounterBasedGauge64
Field Status : current
Description : bad state
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.29

Field Name : badSslSessionIdLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ssl session id length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.28

Field Name : badSslFiletype
Field Type : CounterBasedGauge64
Field Status : current
Description : bad ssl filetype
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.27

Field Name : badSignature
Field Type : CounterBasedGauge64
Field Status : current
Description : bad signature
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.26

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : badRsaSignature
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa signature
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.25

Field Name : badRsaModulusLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa modulus length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.24

Field Name : badRsaELength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa e length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.23

Field Name : badRsaEncrypt
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa encrypt
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.22

Field Name : badRsaDecrypt
Field Type : CounterBasedGauge64
Field Status : current
Description : bad rsa decrypt
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.21

Field Name : badResponseArgument
Field Type : CounterBasedGauge64
Field Status : current
Description : bad response argument
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.20

Field Name : badProtocolVersionCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : bad protocol version counter
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.19

Field Name : badPacketLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad packet length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.18

Field Name : badMessageType
Field Type : CounterBasedGauge64
Field Status : current
Description : bad message type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.17

Field Name : badMacDecode
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : bad mac decode
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.16

Field Name : badLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.15

Field Name : badHelloRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : bad hello request
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.14

Field Name : badDsaSignature
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dsa signature
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.13

Field Name : badDigestLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad digest length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.12

Field Name : badDhPLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dh p length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.11

Field Name : badDhPubKeyLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dh pub key length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.10

Field Name : badDhGLength
Field Type : CounterBasedGauge64
Field Status : current
Description : bad dh g length
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.9

Field Name : badDecompression
Field Type : CounterBasedGauge64
Field Status : current
Description : bad decompression
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.8

Field Name : badDataReturnedByCallback
Field Type : CounterBasedGauge64
Field Status : current
Description : bad data returned by callback
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.7

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : badChecksum
Field Type : CounterBasedGauge64
Field Status : current
Description : bad checksum
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.6

Field Name : badChangeCipherSpec
Field Type : CounterBasedGauge64
Field Status : current
Description : bad change cipher spec
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.5

Field Name : badAuthenticationType
Field Type : CounterBasedGauge64
Field Status : current
Description : bad authentication type
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.4

Field Name : badAlertRecord
Field Type : CounterBasedGauge64
Field Status : current
Description : bad alert record
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.3

Field Name : attemptToReuseSessInDiffContext
Field Type : CounterBasedGauge64
Field Status : current
Description : attempt to reuse sess in diff context
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.2

Field Name : appDataInHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : app data in handshake
OID : 1.3.6.1.4.1.22610.2.4.10.108.62.1.1

Field Name : keyUpdateTx
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC TLS key update sent
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.165

Field Name : keyUpdateRx
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC TLS key update received
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.164

Field Name : invalidCidSig
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid CID Signature
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.163

Field Name : cidCpuHash
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : CID CPU Hash
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.162

Field Name : cidZero
Field Type : CounterBasedGauge64
Field Status : current
Description : CID Zero
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.161

Field Name : quicLb
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC LB
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.160

Field Name : quickMallocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : quick malloc failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.153

Field Name : quicMallocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC malloc failure
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.152

Field Name : quicFree
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC free
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.151

Field Name : quicMalloc
Field Type : CounterBasedGauge64
Field Status : current
Description : QUIC malloc
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.150

Field Name : delayAlarm
Field Type : CounterBasedGauge64
Field Status : current
Description : delay timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.222

Field Name : closeAlarm
Field Type : CounterBasedGauge64
Field Status : current
Description : close timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.221

Field Name : ackAlarm
Field Type : CounterBasedGauge64
Field Status : current
Description : ack timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.148

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : idleAlarm
Field Type : CounterBasedGauge64
Field Status : current
Description : conn idle timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.147

Field Name : onLdTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : lost detection timeout
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.146

Field Name : noWSocket
Field Type : CounterBasedGauge64
Field Status : current
Description : no w socket
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.220

Field Name : noWEngine
Field Type : CounterBasedGauge64
Field Status : current
Description : no w engine
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.184

Field Name : noOtherSideSocket
Field Type : CounterBasedGauge64
Field Status : current
Description : no other side socket
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.180

Field Name : noA10Socket
Field Type : CounterBasedGauge64
Field Status : current
Description : no a10 socket
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.179

Field Name : a10SocketClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : a10 socket closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.143

Field Name : a10SocketCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : a10 socket created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.142

Field Name : wsocketClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : wsocket closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.141

Field Name : wsocketCreated
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : wsocket created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.140

Field Name : noTxQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : No tx queue
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.178

Field Name : iovSystem
Field Type : CounterBasedGauge64
Field Status : current
Description : Iov System
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.224

Field Name : iovIO
Field Type : CounterBasedGauge64
Field Status : current
Description : Iov IO
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.223

Field Name : iovAllocLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Iov alloc len
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.175

Field Name : iovBufferDup
Field Type : CounterBasedGauge64
Field Status : current
Description : Iov buffer dup
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.174

Field Name : iovBufferUnbind
Field Type : CounterBasedGauge64
Field Status : current
Description : Iov buffer unbind
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.167

Field Name : iovBufferBind
Field Type : CounterBasedGauge64
Field Status : current
Description : Iov buffer bind
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.166

Field Name : appBufferQueueFull
Field Type : CounterBasedGauge64
Field Status : current
Description : App buffer queue full
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.136

Field Name : appBufferDeq
Field Type : CounterBasedGauge64
Field Status : current
Description : App buffer dequeued
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.135

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : appBufferEnq
Field Type : CounterBasedGauge64
Field Status : current
Description : App buffer enqueued
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.134

Field Name : txBufferDeq
Field Type : CounterBasedGauge64
Field Status : current
Description : Tx buffer dequeued
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.133

Field Name : txBufferEnq
Field Type : CounterBasedGauge64
Field Status : current
Description : Tx buffer enqueued
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.132

Field Name : ackedPacketFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Acked packet freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.225

Field Name : pnDeleteFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Pn delete failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.219

Field Name : pnInsertFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Pn insert failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.218

Field Name : pktAckedFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Pkt_acked_failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.217

Field Name : serverRxHandshakeDone
Field Type : CounterBasedGauge64
Field Status : current
Description : Server_rx_handshake_done
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.216

Field Name : errProtocolViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Err_protocol_violation
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.215

Field Name : errFlowControl
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Err_flow_control
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.214

Field Name : errFrameFinalSize
Field Type : CounterBasedGauge64
Field Status : current
Description : Err_frame_final_size
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.213

Field Name : errFrameDecb
Field Type : CounterBasedGauge64
Field Status : current
Description : Err_frame_decb
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.212

Field Name : errFrameDec
Field Type : CounterBasedGauge64
Field Status : current
Description : Err_frame_dec
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.211

Field Name : errFrameDec1
Field Type : CounterBasedGauge64
Field Status : current
Description : Err_frame_dec1
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.210

Field Name : zeroFramePacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Zero_frame_packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.209

Field Name : serverReceiveNewToken
Field Type : CounterBasedGauge64
Field Status : current
Description : Server_receive_new_token
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.207

Field Name : tokenLenTooLong
Field Type : CounterBasedGauge64
Field Status : current
Description : Token_len_too_long
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.206

Field Name : noNextScid
Field Type : CounterBasedGauge64
Field Status : current
Description : No_next_scid
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.205

Field Name : cannotRetireCid
Field Type : CounterBasedGauge64
Field Status : current
Description : Cannot_retire_cid
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.204

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : cannotInsertSrt
Field Type : CounterBasedGauge64
Field Status : current
Description : Cannot_insert_srt
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.203

Field Name : cannotInsertCid
Field Type : CounterBasedGauge64
Field Status : current
Description : Cannot_insert_cid
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.202

Field Name : illegalTokenLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Illegal_token_len
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.208

Field Name : illegalLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Illegal_len
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.201

Field Name : illegalRpt
Field Type : CounterBasedGauge64
Field Status : current
Description : Illegal_rpt
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.200

Field Name : illegalSeq
Field Type : CounterBasedGauge64
Field Status : current
Description : Illegal_seq
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.199

Field Name : illegalReasonLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Illegal_reason_len
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.194

Field Name : illegalStreamLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Illegal_stream_len
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.186

Field Name : newConnIdLenNonZero
Field Type : CounterBasedGauge64
Field Status : current
Description : New_conn_id_len_non_zero
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.198

Field Name : newConnIdLenZero
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : New_conn_id_len_zero
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.197

Field Name : streamBlocked
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream_blocked
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.196

Field Name : maxStreamTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : Max_stream_too_big
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.195

Field Name : tooNoisyFuzzing
Field Type : CounterBasedGauge64
Field Status : current
Description : Too_noisy_fuzzing
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.192

Field Name : ackRngHuge3
Field Type : CounterBasedGauge64
Field Status : current
Description : Ack_rng_huge_3
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.193

Field Name : ackRngHuge2
Field Type : CounterBasedGauge64
Field Status : current
Description : Ack_rng_huge_2
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.191

Field Name : ackRngHuge1
Field Type : CounterBasedGauge64
Field Status : current
Description : Ack_rng_huge_1
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.190

Field Name : ackDelayHuge
Field Type : CounterBasedGauge64
Field Status : current
Description : Ack_delay_huge
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.189

Field Name : streamIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream_id_mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.188

Field Name : exceedMaxStreamId
Field Type : CounterBasedGauge64
Field Status : current
Description : Exceed_max_stream_id
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.187

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : cryptoStreamNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Crypto stream not found
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.185

Field Name : exceedFlowControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Exceed flow control
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.181

Field Name : decodeStreamError
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode stream error
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.177

Field Name : decodeFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.176

Field Name : encodeError
Field Type : CounterBasedGauge64
Field Status : current
Description : Encode error
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.171

Field Name : quicPacketDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Quic packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.170

Field Name : packetOutOfOrder
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet out of order
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.131

Field Name : packetRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.130

Field Name : packetDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.129

Field Name : packetLost
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Packet lost
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.128

Field Name : statelessReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Stateless reset
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.127

Field Name : invalidSessionPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid session packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.149

Field Name : invalidConnMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid conn match
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.145

Field Name : invalidPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid packet
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.126

Field Name : invalidVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid version
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.125

Field Name : packetTooShort
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet_too_short
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.124

Field Name : dcidMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Dcid mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.123

Field Name : unknownScid
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown scid
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.122

Field Name : errorClose
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn closed of error
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.121

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : parseError
Field Type : CounterBasedGauge64
Field Status : current
Description : Parse error
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.120

Field Name : receiveWndLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : Receive window limited
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.144

Field Name : packetLoopLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet loop limited
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.137

Field Name : burstLimited
Field Type : CounterBasedGauge64
Field Status : current
Description : Burst limited
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.119

Field Name : noCongestWnd
Field Type : CounterBasedGauge64
Field Status : current
Description : No congestion window
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.118

Field Name : congestWndDec
Field Type : CounterBasedGauge64
Field Status : current
Description : Congestion window decrease
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.117

Field Name : congestWndInc
Field Type : CounterBasedGauge64
Field Status : current
Description : Congestion window increase
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.116

Field Name : packetTxFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet send failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.115

Field Name : packetTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.114

Field Name : packetRx
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acoSslb_oid_list

Field Status : current
Description : Packet receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.113

Field Name : delayedAck
Field Type : CounterBasedGauge64
Field Status : current
Description : Delayed ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.112

Field Name : needsAck
Field Type : CounterBasedGauge64
Field Status : current
Description : Needs ACK
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.111

Field Name : rTTUpdated
Field Type : CounterBasedGauge64
Field Status : current
Description : RTT updated
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.110

Field Name : vERTx
Field Type : CounterBasedGauge64
Field Status : current
Description : Version send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.109

Field Name : vERRx
Field Type : CounterBasedGauge64
Field Status : current
Description : Version receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.108

Field Name : rETRYTx
Field Type : CounterBasedGauge64
Field Status : current
Description : RETRY send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.107

Field Name : rETRYRx
Field Type : CounterBasedGauge64
Field Status : current
Description : RETRY receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.106

Field Name : hANDSHAKETx
Field Type : CounterBasedGauge64
Field Status : current
Description : HANDSHAKE send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.105

Field Name : hANDSHAKERx
Field Type : CounterBasedGauge64
Field Status : current
Description : HANDSHAKE receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.104

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : rTT0Tx
Field Type : CounterBasedGauge64
Field Status : current
Description : RTT_0 send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.103

Field Name : rTT0Rx
Field Type : CounterBasedGauge64
Field Status : current
Description : RTT_0 receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.102

Field Name : iINITIALTx
Field Type : CounterBasedGauge64
Field Status : current
Description : INITIAL send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.101

Field Name : iINITIALRx
Field Type : CounterBasedGauge64
Field Status : current
Description : INITIAL receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.100

Field Name : streamFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.173

Field Name : streamCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.172

Field Name : streamStopSend
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream stop send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.231

Field Name : streamNotSend
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream not send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.99

Field Name : streamResumeData
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream resume data
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.98

Field Name : streamPauseData
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Stream pause data
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.97

Field Name : streamOpen
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream open
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.96

Field Name : streamCongest
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream congest
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.95

Field Name : streamFinSend
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream FIN send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.94

Field Name : streamFinDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream FIN down
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.139

Field Name : streamFinUp
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream FIN up
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.138

Field Name : streamFinReceive
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream FIN receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.93

Field Name : unknownFrame
Field Type : CounterBasedGauge64
Field Status : current
Description : Unknown frame
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.92

Field Name : handshakeDoneFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : handshake done frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.91

Field Name : handshakeDoneFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : handshake done frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.90

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : appConnCloseFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : app conn close frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.89

Field Name : appConnCloseFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : app conn close frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.88

Field Name : connCloseFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : conn close frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.87

Field Name : connCloseFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : conn close frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.86

Field Name : pathResponseFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : path response frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.85

Field Name : pathResponseFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : path response frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.84

Field Name : pathChallengeFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : path challenge frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.83

Field Name : pathChallengeFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : path challenge frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.82

Field Name : retireConnIdFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : retire conn id frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.81

Field Name : retireConnIdFrameRx
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : retire conn id frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.80

Field Name : newConnIdFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : new conn id frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.79

Field Name : newConnIdFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : new conn id frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.78

Field Name : uniStreamDataBlockedFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : uni stream data blocked frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.77

Field Name : uniStreamDataBlockedFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : uni stream data blocked frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.76

Field Name : biStreamDataBlockedFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : bi stream data blocked frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.75

Field Name : biStreamDataBlockedFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : bi stream data blocked frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.74

Field Name : streamDataBlockedFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream data blocked frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.73

Field Name : streamDataBlockedFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream data blocked frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.72

Field Name : dataBlockedFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : data blocked frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.71

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : dataBlockedFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : data blocked frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.70

Field Name : maxUniStreamFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : max uni stream frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.69

Field Name : maxUniStreamFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : max uni stream frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.68

Field Name : maxBiStreamFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : max bi stream frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.67

Field Name : maxBiStreamFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : max bi stream frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.66

Field Name : maxStreamDataFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : max stream data frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.65

Field Name : maxStreamDataFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : max stream data frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.64

Field Name : maxDataFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : max data frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.63

Field Name : maxDataFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : max data frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.62

Field Name : streamOffFrameTx
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : stream 0f frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.61

Field Name : stream0fFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0f frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.60

Field Name : stream0eFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0e frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.59

Field Name : stream0eFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0e frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.58

Field Name : stream0dFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0d frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.57

Field Name : stream0dFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0d frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.56

Field Name : stream0cFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0c frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.55

Field Name : stream0cFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0c frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.54

Field Name : stream0bFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0b frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.53

Field Name : stream0bFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0b frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.52

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : stream0aFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0a frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.51

Field Name : stream0aFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 0a frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.50

Field Name : stream09FrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 09 frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.49

Field Name : stream09FrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream 09 frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.48

Field Name : streamFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.47

Field Name : streamFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.46

Field Name : newTokenFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : new token frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.45

Field Name : newTokenFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : new token frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.44

Field Name : cryptoFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : crypto frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.43

Field Name : cryptoFrameRx
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : crypto frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.42

Field Name : streamStopFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream stop frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.41

Field Name : streamStopFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream stop frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.40

Field Name : streamRstFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream reset frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.39

Field Name : streamRstFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : stream reset frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.38

Field Name : ackEcnFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : ack enc frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.37

Field Name : ackEcnFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : ack enc frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.36

Field Name : ackFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : ack frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.35

Field Name : ackFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : ack frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.34

Field Name : pingFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : ping frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.33

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : pingFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : ping frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.32

Field Name : paddingFrameTx
Field Type : CounterBasedGauge64
Field Status : current
Description : padding frame send
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.31

Field Name : paddingFrameRx
Field Type : CounterBasedGauge64
Field Status : current
Description : padding frame receive
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.30

Field Name : streamFailToInsert
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream fail to insert
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.226

Field Name : streamError
Field Type : CounterBasedGauge64
Field Status : current
Description : Stream error
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.26

Field Name : remoteUniStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Remote uni-stream closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.183

Field Name : localUniStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Local uni-stream closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.25

Field Name : remoteUniStreamCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Remote uni-stream created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.24

Field Name : localUniStreamCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Local uni-stream created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.23

Field Name : remoteUniStreamCurrent
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Current remote uni-stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.230

Field Name : localUniStreamCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : Current local uni-stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.229

Field Name : remoteBiStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Remote bi-stream closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.182

Field Name : localBiStreamClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Local bi-stream closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.22

Field Name : remoteBiStreamCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Remote bi-stream created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.21

Field Name : localBiStreamCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Local bi-stream created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.20

Field Name : remoteBiStreamCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : Current remote bi-stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.228

Field Name : localBiStreamCurrent
Field Type : CounterBasedGauge64
Field Status : current
Description : Current local bi-stream
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.227

Field Name : qConnFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Q connection freed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.169

Field Name : qConnCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Q connection created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.168

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Name : serverConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.12

Field Name : serverConnRemoteClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection remote closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.11

Field Name : serverConnLocalClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection local closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.10

Field Name : serverConnCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.9

Field Name : serverConnHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection handshake
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.8

Field Name : serverConnAttempted
Field Type : CounterBasedGauge64
Field Status : current
Description : Server connection attempted
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.7

Field Name : clientConnFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection failed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.6

Field Name : clientConnRemoteClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection remote closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.5

Field Name : clientConnLocalClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection local closed
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.4

Field Name : clientConnCreated
Field Type : CounterBasedGauge64

ACOS-SLB-STATS-MIB_acosSlb_oid_list

Field Status : current
Description : Client connection created
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.3

Field Name : clientConnHandshake
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection handshake
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.2

Field Name : clientConnAttempted
Field Type : CounterBasedGauge64
Field Status : current
Description : Client connection attempted
OID : 1.3.6.1.4.1.22610.2.4.10.108.108.1.1

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : migrateVipOperTable
Field Type : TABLE
Field Status : current
Description : MigrateThisVirtualServer from object 'slb.virtual-server.migrate-vip'
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.3.2

Field Name : migrateVipOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The migrateVipOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.3.2.1

Field Name : migrateVipOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.3.2.1.3

Field Name : migrateVipOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.3.2.1.2

Field Name : migrateVipOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.3.2.1.1

Field Name : virtualServerOperTable
Field Type : TABLE
Field Status : current
Description : CreateAVirtualServer from object 'slb.virtual-server'
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2

Field Name : virtualServerOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The virtualServerOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1

Field Name : virtualServerOperIpOnlyLbRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.21

Field Name : virtualServerOperIpOnlyLbFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.20

Field Name : virtualServerOperIpOnlyLbRevBytes
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : ip_only_lb_rev_bytes

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.19

Field Name : virtualServerOperIpOnlyLbFwdBytes

Field Type : CounterBasedGauge64

Field Status : current

Description : ip_only_lb_fwd_bytes

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.18

Field Name : virtualServerOperCurrConnOverflow

Field Type : CounterBasedGauge64

Field Status : current

Description : curr-conn-overflow

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.17

Field Name : virtualServerOperIpv6Address

Field Type : String

Field Status : current

Description : ipv6-address

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.16

Field Name : virtualServerOperIpAddress

Field Type : String

Field Status : current

Description : ip-address

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.15

Field Name : virtualServerOperPeakConn

Field Type : CounterBasedGauge64

Field Status : current

Description : peak-conn

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.14

Field Name : virtualServerOperMigrationStatus

Field Type : String

Field Status : current

Description : migration-status

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.13

Field Name : virtualServerOperIcmpv6RateOverLimitDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : icmpv6-rate-over-limit-drop

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.12

Field Name : virtualServerOperIcmpv6LockupTimeLeft

Field Type : CounterBasedGauge64

Field Status : current

Description : icmpv6-lockup-time-left

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.11

Field Name : virtualServerOperCurrIcmpv6Rate

Field Type : CounterBasedGauge64

Field Status : current

Description : curr-icmpv6-rate

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.10

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : virtualServerOperIcmpRateOverLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-rate-over-limit-drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.9

Field Name : virtualServerOperIcmpLockupTimeLeft
Field Type : CounterBasedGauge64
Field Status : current
Description : icmp-lockup-time-left
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.8

Field Name : virtualServerOperCurrIcmpRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-icmp-rate
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.7

Field Name : virtualServerOperConnRateUnit
Field Type : String
Field Status : current
Description : conn-rate-unit
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.6

Field Name : virtualServerOperCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr-conn-rate
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.5

Field Name : virtualServerOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.4

Field Name : virtualServerOperMac
Field Type : String
Field Status : current
Description : mac
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.3

Field Name : virtualServerOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.2

Field Name : virtualServerOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.2.1.1

Field Name : portOperHttpVportCpuListTable
Field Type : TABLE
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : VirtualPort from object 'slb.virtual-server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4

Field Name : portOperHttpHitsListTable
Field Type : TABLE
Field Status : current
Description : VirtualPort from object 'slb.virtual-server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3

Field Name : portOperHttpHitsListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOperHttpHitsList entry:http-hits-list
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1

Field Name : portOperHttpHitsListHitsCount
Field Type : CounterBasedGauge64
Field Status : current
Description : hits-count
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.7

Field Name : portOperHttpHitsListName1
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.6

Field Name : portOperHttpHitsListHttpHitsListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.5

Field Name : portOperHttpHitsListProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.4

Field Name : portOperHttpHitsListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.3

Field Name : portOperHttpHitsListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.2

Field Name : portOperHttpHitsListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.3.1.1

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperTable
Field Type : TABLE
Field Status : current
Description : VirtualPort from object 'slb.virtual-server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2

Field Name : portOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1

Field Name : portOperClearCurrConn
Field Type : Integer32
Field Status : current
Description : clear_curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.23

Field Name : portOperHttpVport
Field Type : Integer32
Field Status : current
Description : http_vport
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.22

Field Name : portOperHttpUrlHits
Field Type : Integer32
Field Status : current
Description : http_url_hits
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.21

Field Name : portOperHttpHostHits
Field Type : Integer32
Field Status : current
Description : http_host_hits
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.20

Field Name : portOperCpuCount
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-count
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.19

Field Name : portOperLocLast
Field Type : String
Field Status : current
Description : loc_last
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.18

Field Name : portOperLocOverride
Field Type : CounterBasedGauge64
Field Status : current
Description : loc_override
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.17

Field Name : portOperLocError
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : loc_error
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.16

Field Name : portOperLocSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : loc_success
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.15

Field Name : portOperLocMaxDepth
Field Type : CounterBasedGauge64
Field Status : current
Description : loc_max_depth
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.14

Field Name : portOperGroupId
Field Type : CounterBasedGauge64
Field Status : current
Description : group_id
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.13

Field Name : portOperLevelStr
Field Type : String
Field Status : current
Description : level_str
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.12

Field Name : portOperGeoLocation
Field Type : String
Field Status : current
Description : geo_location
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.11

Field Name : portOperLocList
Field Type : String
Field Status : current
Description : loc_list
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.10

Field Name : portOperPrintExtendedStats
Field Type : CounterBasedGauge64
Field Status : current
Description : print_extended_stats
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.9

Field Name : portOperCurrConnOverflow
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_overflow
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.8

Field Name : portOperIntCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : int_curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.7

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperRealCurrConn
Field Type : CounterBasedGauge64
Field Status : current
Description : real_curr_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.6

Field Name : portOperState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.5

Field Name : portOperProtocol
Field Type : String
Field Status : current
Description : protocol
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.4

Field Name : portOperPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.3

Field Name : portOperName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.2

Field Name : portOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.2.1.1

Field Name : portStatsTable
Field Type : TABLE
Field Status : current
Description : VirtualPort from object 'slb.virtual-server.port'
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1

Field Name : portStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The portStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1

Field Name : portStatsDnsrrlNxExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : dnsrrl_nx_exceed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.102

Field Name : portStatsHttp2ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : http2_client_idle_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.101

Field Name : portStatsHttp1ClientIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : http1_client_idle_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.100

Field Name : portStatsDnsrrlTotalTc
Field Type : CounterBasedGauge64
Field Status : current
Description : dnsrrl_total_tc
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.99

Field Name : portStatsCompressionMissTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_miss_total
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.98

Field Name : portStatsCompressionHitTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_hit_total
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.97

Field Name : portStatsCompressionMissBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_miss_br
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.96

Field Name : portStatsCompressionHitBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_hit_br
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.95

Field Name : portStatsCompressionBytesAfterTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_bytes_after_total
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.94

Field Name : portStatsCompressionBytesBeforeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_bytes_before_total
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.93

Field Name : portStatsCompressionBytesAfterBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_bytes_after_br
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.92

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portStatsCompressionBytesBeforeBr
Field Type : CounterBasedGauge64
Field Status : current
Description : compression_bytes_before_br
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.91

Field Name : portStatsDnsRpzTriggerNsName
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_trigger_ns_name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.90

Field Name : portStatsDnsRpzTriggerQname
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_trigger_qname
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.89

Field Name : portStatsDnsRpzTriggerNsIp
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_trigger_ns_ip
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.88

Field Name : portStatsDnsRpzTriggerRespIp
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_trigger_resp_ip
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.87

Field Name : portStatsDnsRpzTriggerClientIp
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_trigger_client_ip
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.86

Field Name : portStatsDnsRpzActionLocalData
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_action_local_data
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.85

Field Name : portStatsDnsRpzActionNodata
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_action_nodata
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.84

Field Name : portStatsDnsRpzActionNxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_rpz_action_nxdomain
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.83

Field Name : portStatsDnsRpzActionTcpOnly
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : dns_rpz_action_tcp_only

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.82

Field Name : portStatsDnsRpzActionPassThru

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_rpz_action_pass_thru

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.81

Field Name : portStatsDnsRpzActionDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_rpz_action_drop

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.80

Field Name : portStatsDnsFilterClassOthersDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_filter_class_others_drop

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.79

Field Name : portStatsDnsFilterClassAnyDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_filter_class_any_drop

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.78

Field Name : portStatsDnsFilterClassNoneDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_filter_class_none_drop

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.77

Field Name : portStatsDnsFilterClassHesiodDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_filter_class_hesiod_drop

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.76

Field Name : portStatsDnsFilterClassChaosDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_filter_class_chaos_drop

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.75

Field Name : portStatsDnsFilterClassInternetDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_filter_class_internet_drop

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.74

Field Name : portStatsDnsFilterTypeOthersDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_filter_type_others_drop

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.73

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portStatsDnsFilterTypeAnyDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_any_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.72

Field Name : portStatsDnsFilterTypeTxtDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_txt_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.71

Field Name : portStatsDnsFilterTypeSoaDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_soa_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.70

Field Name : portStatsDnsFilterTypePtrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_ptr_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.69

Field Name : portStatsDnsFilterTypeSrvDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_srv_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.68

Field Name : portStatsDnsFilterTypeNsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_ns_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.67

Field Name : portStatsDnsFilterTypeMxDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_mx_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.66

Field Name : portStatsDnsFilterTypeCnameDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_cname_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.65

Field Name : portStatsDnsFilterTypeAaaaDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : dns_filter_type_aaaa_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.64

Field Name : portStatsDnsFilterTypeADrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : dns_filter_type_a_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.63

Field Name : portStatsTotalDnsFilterClassDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : total_dns_filter_class_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.62

Field Name : portStatsTotalDnsFilterTypeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : total_dns_filter_type_drop
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.61

Field Name : portStatsIpOnlyLbRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.60

Field Name : portStatsIpOnlyLbFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.59

Field Name : portStatsIpOnlyLbRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.58

Field Name : portStatsIpOnlyLbFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_only_lb_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.57

Field Name : portStatsDynamicMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic-memory
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.56

Field Name : portStatsDynamicMemoryFree
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic-memory-free
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.55

Field Name : portStatsDynamicMemoryAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamic-memory-alloc
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.54

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portStatsThroughputBitsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : throughput-bits-per-sec
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.53

Field Name : portStatsDnsrrlBadFqdn
Field Type : CounterBasedGauge64
Field Status : current
Description : dnsrrl_bad_fqdn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.52

Field Name : portStatsDnsrrlTotalSlipped
Field Type : CounterBasedGauge64
Field Status : current
Description : dnsrrl_total_slipped
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.51

Field Name : portStatsDnsrrlTotalDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : dnsrrl_total_dropped
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.50

Field Name : portStatsDnsrrlTotalAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : dnsrrl_total_allowed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.49

Field Name : portStatsCurrRespRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_resp_rate
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.48

Field Name : portStatsTotalRespSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : total_resp_succ
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.47

Field Name : portStatsTotalResp
Field Type : CounterBasedGauge64
Field Status : current
Description : total_resp
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.46

Field Name : portStatsCurrResp
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_resp
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.45

Field Name : portStatsCurrReqRate
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : curr_req_rate
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.44

Field Name : portStatsTotalRevPktsOut
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts_out
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.43

Field Name : portStatsTotalRevBytesOut
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes_out
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.42

Field Name : portStatsTotalFwdPktsOut
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts_out
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.41

Field Name : portStatsTotalFwdBytesOut
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes_out
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.40

Field Name : portStatsOutLatency
Field Type : CounterBasedGauge64
Field Status : current
Description : out-latency
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.39

Field Name : portStatsInLatency
Field Type : CounterBasedGauge64
Field Status : current
Description : in-latency
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.38

Field Name : portStatsBackendTimeToLastByte
Field Type : CounterBasedGauge64
Field Status : current
Description : backend-time-to-last-byte
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.37

Field Name : portStatsBackendTimeToFirstByte
Field Type : CounterBasedGauge64
Field Status : current
Description : backend-time-to-first-byte
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.36

Field Name : portStatsTotalSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.35

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portStatsCurrSslConn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_ssl_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.34

Field Name : portStatsLocConn
Field Type : CounterBasedGauge64
Field Status : current
Description : loc_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.33

Field Name : portStatsLocDeny
Field Type : CounterBasedGauge64
Field Status : current
Description : loc_deny
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.32

Field Name : portStatsLocPermit
Field Type : CounterBasedGauge64
Field Status : current
Description : loc_permit
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.31

Field Name : portStatsSlowestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : slowest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.30

Field Name : portStatsFastestRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : fastest_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.29

Field Name : portStatsLastRspTime
Field Type : CounterBasedGauge64
Field Status : current
Description : last_rsp_time
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.28

Field Name : portStatsCurrConnRate
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_conn_rate
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.27

Field Name : portStatsPeakConn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.26

Field Name : portStatsTotalReqSucc
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : total_req_succ

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.25

Field Name : portStatsTotalReq

Field Type : CounterBasedGauge64

Field Status : current

Description : total_req

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.24

Field Name : portStatsCurrReq

Field Type : CounterBasedGauge64

Field Status : current

Description : curr_req

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.23

Field Name : portStatsCompressionMissTemplateExclusion

Field Type : CounterBasedGauge64

Field Status : current

Description : compression_miss_template_exclusion

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.22

Field Name : portStatsCompressionMissNoClient

Field Type : CounterBasedGauge64

Field Status : current

Description : compression_miss_no_client

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.21

Field Name : portStatsCompressionMiss

Field Type : CounterBasedGauge64

Field Status : current

Description : compression_miss

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.20

Field Name : portStatsCompressionHit

Field Type : CounterBasedGauge64

Field Status : current

Description : compression_hit

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.19

Field Name : portStatsCompressionBytesAfter

Field Type : CounterBasedGauge64

Field Status : current

Description : compression_bytes_after

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.18

Field Name : portStatsCompressionBytesBefore

Field Type : CounterBasedGauge64

Field Status : current

Description : compression_bytes_before

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.17

Field Name : portStatsEsTotalFailureActions

Field Type : CounterBasedGauge64

Field Status : current

Description : es_total_failure_actions

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.16

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portStatsTotalMfDnsPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_mf_dns_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.15

Field Name : portStatsTotalDnsPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_dns_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.14

Field Name : portStatsTotalRevPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.13

Field Name : portStatsTotalRevBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_rev_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.12

Field Name : portStatsTotalFwdPkts
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_pkts
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.11

Field Name : portStatsTotalFwdBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_fwd_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.10

Field Name : portStatsTotalConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.9

Field Name : portStatsTotalTcpConn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_tcp_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.8

Field Name : portStatsTotalL7Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_l7_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.7

Field Name : portStatsTotalL4Conn
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : total_l4_conn

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.6

Field Name : portStatsCurrConn

Field Type : CounterBasedGauge64

Field Status : current

Description : curr_conn

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.5

Field Name : portStatsProtocol

Field Type : String

Field Status : current

Description : protocol

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.4

Field Name : portStatsPort

Field Type : Integer32

Field Status : current

Description : port-number

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.3

Field Name : portStatsName

Field Type : String

Field Status : current

Description : name

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.2

Field Name : portStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.1.1.1

Field Name : portOperHttpVportCpuListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The portOperHttpVportCpuList entry:http-vport-cpu-list

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1

Field Name : portOperHttpVportCpuListDohDnsRespRcodeOther

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_dns_resp_rcode_other

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.213

Field Name : portOperHttpVportCpuListDohDnsRespRcodeNotzone

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_dns_resp_rcode_notzone

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.212

Field Name : portOperHttpVportCpuListDohDnsRespRcodeNotauth

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_dns_resp_rcode_notauth

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.211

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperHttpVportCpuListDohDnsRespRcodeNxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_nxrrset
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.210

Field Name : portOperHttpVportCpuListDohDnsRespRcodeYxrrset
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_yxrrset
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.209

Field Name : portOperHttpVportCpuListDohDnsRespRcodeYxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_yxdomain
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.208

Field Name : portOperHttpVportCpuListDohDnsRespRcodeRefuse
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_refuse
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.207

Field Name : portOperHttpVportCpuListDohDnsRespRcodeErrType
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_type
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.206

Field Name : portOperHttpVportCpuListDohDnsRespRcodeErrName
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.205

Field Name : portOperHttpVportCpuListDohDnsRespRcodeErrServer
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_server
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.204

Field Name : portOperHttpVportCpuListDohDnsRespRcodeErrFormat
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_resp_rcode_err_format
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.203

Field Name : portOperHttpVportCpuListDohDnsMalformedQuery
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_malformed_query
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.202

Field Name : portOperHttpVportCpuListDohPostPayloadTooLarge
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : doh_post_payload_too_large

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.201

Field Name : portOperHttpVportCpuListDohGetUriTooLong

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_get_uri_too_long

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.200

Field Name : portOperHttpVportCpuListDohRetryWTcp

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_retry_w_tcp

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.199

Field Name : portOperHttpVportCpuListDohServSelFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_serv_sel_failed

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.198

Field Name : portOperHttpVportCpuListDohRespTcpFrag

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_resp_tcp_frags

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.197

Field Name : portOperHttpVportCpuListDohRespUdpFrag

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_resp_udp_frags

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.196

Field Name : portOperHttpVportCpuListDohRespQueFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_resp_que_failed

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.195

Field Name : portOperHttpVportCpuListDohRespHeaderAllocFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_resp_header_alloc_failed

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.194

Field Name : portOperHttpVportCpuListDohRespSetupFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_resp_setup_failed

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.193

Field Name : portOperHttpVportCpuListDohDnsQueryTypeOthers

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_dns_query_type_others

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.192

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperHttpVportCpuListDohDnsQueryTypeSoa
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_soa
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.191

Field Name : portOperHttpVportCpuListDohDnsQueryTypeMx
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_mx
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.190

Field Name : portOperHttpVportCpuListDohDnsQueryTypeSrv
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_srv
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.189

Field Name : portOperHttpVportCpuListDohDnsQueryTypeAny
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_any
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.188

Field Name : portOperHttpVportCpuListDohDnsQueryTypeCname
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_cname
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.187

Field Name : portOperHttpVportCpuListDohDnsQueryTypeNs
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_ns
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.186

Field Name : portOperHttpVportCpuListDohDnsQueryTypeAaaa
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_aaaa
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.185

Field Name : portOperHttpVportCpuListDohDnsQueryTypeA
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_dns_query_type_a
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.184

Field Name : portOperHttpVportCpuListDohQueryTimeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_query_time_out
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.183

Field Name : portOperHttpVportCpuListDohUdpSendFailed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : doh_udp_send_failed

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.182

Field Name : portOperHttpVportCpuListDohTcpSendFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_tcp_send_failed

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.181

Field Name : portOperHttpVportCpuListDohNonDohMethod

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_non_doh_method

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.180

Field Name : portOperHttpVportCpuListDohPostPayloadExtractFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_post_payload_extract_failed

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.179

Field Name : portOperHttpVportCpuListDohPostPayloadNotFound

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_post_payload_not_found

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.178

Field Name : portOperHttpVportCpuListDohPostContentTypeMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_post_content_type_mismatch

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.177

Field Name : portOperHttpVportCpuListDohGetBase64DecodeFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_get_base64_decode_failed

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.176

Field Name : portOperHttpVportCpuListDohGetDnsArgFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_get_dns_arg_failed

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.175

Field Name : portOperHttpVportCpuListDohPathNotFound

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_path_not_found

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.174

Field Name : portOperHttpVportCpuListDohSnatFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_snat_failed

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.173

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperHttpVportCpuListDohReqTcpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_tcp_retry_fail
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.172

Field Name : portOperHttpVportCpuListDohReqTcpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_tcp_retry
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.171

Field Name : portOperHttpVportCpuListDohReqUdpRetryFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_udp_retry_fail
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.170

Field Name : portOperHttpVportCpuListDohReqUdpRetry
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_udp_retry
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.169

Field Name : portOperHttpVportCpuListDohMallocFail
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_malloc_fail
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.168

Field Name : portOperHttpVportCpuListDohRespSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_resp_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.167

Field Name : portOperHttpVportCpuListDohReqSendFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_req_send_failed
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.166

Field Name : portOperHttpVportCpuListDohTcpDnsResp
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_dns_resp
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.165

Field Name : portOperHttpVportCpuListDohTcpDnsReq
Field Type : CounterBasedGauge64
Field Status : current
Description : doh_tcp_dns_req
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.164

Field Name : portOperHttpVportCpuListDohUdpDnsResp
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : doh_udp_dns_resp

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.163

Field Name : portOperHttpVportCpuListDohUdpDnsReq

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_udp_dns_req

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.162

Field Name : portOperHttpVportCpuListDohTcResp

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_tc_resp

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.161

Field Name : portOperHttpVportCpuListDohResp

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_resp

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.160

Field Name : portOperHttpVportCpuListDohNonDohReqPost

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_non_doh_req_post

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.159

Field Name : portOperHttpVportCpuListDohNonDohReqGet

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_non_doh_req_get

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.158

Field Name : portOperHttpVportCpuListDohNonDohReq

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_non_doh_req

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.157

Field Name : portOperHttpVportCpuListDohReqPost

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_req_post

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.156

Field Name : portOperHttpVportCpuListDohReqGet

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_req_get

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.155

Field Name : portOperHttpVportCpuListDohReq

Field Type : CounterBasedGauge64

Field Status : current

Description : doh_req

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.154

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperHttpVportCpuListRspChunk
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_chunk
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.153

Field Name : portOperHttpVportCpuListReqContentLen
Field Type : CounterBasedGauge64
Field Status : current
Description : req_content_len
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.152

Field Name : portOperHttpVportCpuListReqSzGt256k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_gt_256k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.151

Field Name : portOperHttpVportCpuListReqSz256k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_256k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.150

Field Name : portOperHttpVportCpuListReqSz64k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_64k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.149

Field Name : portOperHttpVportCpuListReqSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_32k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.148

Field Name : portOperHttpVportCpuListReqSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_16k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.147

Field Name : portOperHttpVportCpuListReqSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_8k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.146

Field Name : portOperHttpVportCpuListReqSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : req_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.145

Field Name : portOperHttpVportCpuListReqSz2k
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : req_sz_2k

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.144

Field Name : portOperHttpVportCpuListReqSz1k

Field Type : CounterBasedGauge64

Field Status : current

Description : req_sz_1k

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.143

Field Name : portOperHttpVportCpuListChunkSzGt4k

Field Type : CounterBasedGauge64

Field Status : current

Description : chunk_sz_gt_4k

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.142

Field Name : portOperHttpVportCpuListChunkSz4k

Field Type : CounterBasedGauge64

Field Status : current

Description : chunk_sz_4k

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.141

Field Name : portOperHttpVportCpuListChunkSz2k

Field Type : CounterBasedGauge64

Field Status : current

Description : chunk_sz_2k

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.140

Field Name : portOperHttpVportCpuListChunkSz1k

Field Type : CounterBasedGauge64

Field Status : current

Description : chunk_sz_1k

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.139

Field Name : portOperHttpVportCpuListChunkSz512

Field Type : CounterBasedGauge64

Field Status : current

Description : chunk_sz_512

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.138

Field Name : portOperHttpVportCpuListRspSzGt256k

Field Type : CounterBasedGauge64

Field Status : current

Description : rsp_sz_gt_256k

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.137

Field Name : portOperHttpVportCpuListRspSz256k

Field Type : CounterBasedGauge64

Field Status : current

Description : rsp_sz_256k

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.136

Field Name : portOperHttpVportCpuListRspSz64k

Field Type : CounterBasedGauge64

Field Status : current

Description : rsp_sz_64k

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.135

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperHttpVportCpuListRspSz32k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_32k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.134

Field Name : portOperHttpVportCpuListRspSz16k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_16k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.133

Field Name : portOperHttpVportCpuListRspSz8k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_8k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.132

Field Name : portOperHttpVportCpuListRspSz4k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_4k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.131

Field Name : portOperHttpVportCpuListRspSz2k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_2k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.130

Field Name : portOperHttpVportCpuListRspSz1k
Field Type : CounterBasedGauge64
Field Status : current
Description : rsp_sz_1k
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.129

Field Name : portOperHttpVportCpuListReqTrack
Field Type : CounterBasedGauge64
Field Status : current
Description : req_track
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.128

Field Name : portOperHttpVportCpuListReqUnknown
Field Type : CounterBasedGauge64
Field Status : current
Description : req_unknown
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.127

Field Name : portOperHttpVportCpuListReqDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : req_delete
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.126

Field Name : portOperHttpVportCpuListReqConnect
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : req_connect

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.125

Field Name : portOperHttpVportCpuListReqOptions

Field Type : CounterBasedGauge64

Field Status : current

Description : req_options

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.124

Field Name : portOperHttpVportCpuListReqTrace

Field Type : CounterBasedGauge64

Field Status : current

Description : req_trace

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.123

Field Name : portOperHttpVportCpuListReqPost

Field Type : CounterBasedGauge64

Field Status : current

Description : req_post

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.122

Field Name : portOperHttpVportCpuListReqPut

Field Type : CounterBasedGauge64

Field Status : current

Description : req_put

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.121

Field Name : portOperHttpVportCpuListReqHead

Field Type : CounterBasedGauge64

Field Status : current

Description : req_head

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.120

Field Name : portOperHttpVportCpuListReqGet

Field Type : CounterBasedGauge64

Field Status : current

Description : req_get

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.119

Field Name : portOperHttpVportCpuListHeaderLengthLong

Field Type : CounterBasedGauge64

Field Status : current

Description : header_length_long

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.118

Field Name : portOperHttpVportCpuListJsiHashLookupFails

Field Type : CounterBasedGauge64

Field Status : current

Description : jsi_hash_lookup_fails

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.117

Field Name : portOperHttpVportCpuListJsiHashAddFails

Field Type : CounterBasedGauge64

Field Status : current

Description : jsi_hash_add_fails

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.116

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperHttpVportCpuListJsiSkipNotBrowser
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_skip_not_browser
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.115

Field Name : portOperHttpVportCpuListJsiSkipNoUa
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_skip_no_ua
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.114

Field Name : portOperHttpVportCpuListJsiSkipNoFi
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_skip_no_fi
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.113

Field Name : portOperHttpVportCpuListJsiApiNoToken
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_api_no_token
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.112

Field Name : portOperHttpVportCpuListJsiApiNoAuthHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_api_no_auth_hdr
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.111

Field Name : portOperHttpVportCpuListJsiApiResponseResponses
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_api_responses
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.110

Field Name : portOperHttpVportCpuListJsiApiRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_api_requests
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.109

Field Name : portOperHttpVportCpuListJsiPriRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_pri_requests
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.108

Field Name : portOperHttpVportCpuListJsiResponses
Field Type : CounterBasedGauge64
Field Status : current
Description : jsi_responses
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.107

Field Name : portOperHttpVportCpuListJsiRequests
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : jsi_requests

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.106

Field Name : portOperHttpVportCpuListTransactionLimited

Field Type : CounterBasedGauge64

Field Status : current

Description : transaction_limited

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.105

Field Name : portOperHttpVportCpuListStreamClosed

Field Type : CounterBasedGauge64

Field Status : current

Description : stream_closed

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.104

Field Name : portOperHttpVportCpuListHttp2GoawaySent

Field Type : CounterBasedGauge64

Field Status : current

Description : http2_goaway_sent

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.103

Field Name : portOperHttpVportCpuListHttp2GoawayReceived

Field Type : CounterBasedGauge64

Field Status : current

Description : http2_goaway_received

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.102

Field Name : portOperHttpVportCpuListHttp2ResetSent

Field Type : CounterBasedGauge64

Field Status : current

Description : http2_reset_sent

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.101

Field Name : portOperHttpVportCpuListHttp2ResetReceived

Field Type : CounterBasedGauge64

Field Status : current

Description : http2_reset_received

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.100

Field Name : portOperHttpVportCpuListHttp2DataBytes

Field Type : CounterBasedGauge64

Field Status : current

Description : http2_data_bytes

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.99

Field Name : portOperHttpVportCpuListHttp2HeaderBytes

Field Type : CounterBasedGauge64

Field Status : current

Description : http2_header_bytes

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.98

Field Name : portOperHttpVportCpuListHttp2ControlBytes

Field Type : CounterBasedGauge64

Field Status : current

Description : http2_control_bytes

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.97

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperHttpVportCpuListTotalHttp2Bytes
Field Type : CounterBasedGauge64
Field Status : current
Description : total_http2_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.96

Field Name : portOperHttpVportCpuListPeakHttp2Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : peak_http2_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.95

Field Name : portOperHttpVportCpuListTotalHttp2Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : total_http2_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.94

Field Name : portOperHttpVportCpuListCurrHttp2Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : curr_http2_conn
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.93

Field Name : portOperHttpVportCpuListTotalRequests
Field Type : CounterBasedGauge64
Field Status : current
Description : total_requests
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.215

Field Name : portOperHttpVportCpuListREQOVER5s
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_OVER_5s
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.92

Field Name : portOperHttpVportCpuListREQ5s
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_5s
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.91

Field Name : portOperHttpVportCpuListREQ2s
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_2s
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.90

Field Name : portOperHttpVportCpuListREQ1s
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_1s
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.89

Field Name : portOperHttpVportCpuListREQ500m
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : REQ_500m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.88

Field Name : portOperHttpVportCpuListREQ200m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_200m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.87

Field Name : portOperHttpVportCpuListREQ100m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_100m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.86

Field Name : portOperHttpVportCpuListREQ50m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_50m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.85

Field Name : portOperHttpVportCpuListREQ20m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_20m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.84

Field Name : portOperHttpVportCpuListREQ10m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_10m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.83

Field Name : portOperHttpVportCpuListREQ5m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_5m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.82

Field Name : portOperHttpVportCpuListREQ2m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_2m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.81

Field Name : portOperHttpVportCpuListREQ1m
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_1m
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.80

Field Name : portOperHttpVportCpuListREQ500u
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_500u
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.79

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperHttpVportCpuListREQ200u
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_200u
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.78

Field Name : portOperHttpVportCpuListREQ100u
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_100u
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.77

Field Name : portOperHttpVportCpuListREQ50u
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_50u
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.76

Field Name : portOperHttpVportCpuListREQ20u
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_20u
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.75

Field Name : portOperHttpVportCpuListREQ10u
Field Type : CounterBasedGauge64
Field Status : current
Description : REQ_10u
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.74

Field Name : portOperHttpVportCpuListWsServerSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_server_switch
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.73

Field Name : portOperHttpVportCpuListWsClientSwitch
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_client_switch
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.72

Field Name : portOperHttpVportCpuListWsHandshakeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_handshake_success
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.71

Field Name : portOperHttpVportCpuListWsHandshakeRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : ws_handshake_request
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.70

Field Name : portOperHttpVportCpuListStatusUnknown
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : status_unknown

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.69

Field Name : portOperHttpVportCpuListStatus6xx

Field Type : CounterBasedGauge64

Field Status : current

Description : status_6xx

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.68

Field Name : portOperHttpVportCpuListStatus5xx

Field Type : CounterBasedGauge64

Field Status : current

Description : status_5xx

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.67

Field Name : portOperHttpVportCpuListStatus4xx

Field Type : CounterBasedGauge64

Field Status : current

Description : status_4xx

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.66

Field Name : portOperHttpVportCpuListStatus3xx

Field Type : CounterBasedGauge64

Field Status : current

Description : status_3xx

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.65

Field Name : portOperHttpVportCpuListStatus2xx

Field Type : CounterBasedGauge64

Field Status : current

Description : status_2xx

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.64

Field Name : portOperHttpVportCpuListStatus1xx

Field Type : CounterBasedGauge64

Field Status : current

Description : status_1xx

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.63

Field Name : portOperHttpVportCpuListStatus510

Field Type : CounterBasedGauge64

Field Status : current

Description : status_510

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.62

Field Name : portOperHttpVportCpuListStatus509

Field Type : CounterBasedGauge64

Field Status : current

Description : status_509

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.61

Field Name : portOperHttpVportCpuListStatus508

Field Type : CounterBasedGauge64

Field Status : current

Description : status_508

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.60

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperHttpVportCpuListStatus507
Field Type : CounterBasedGauge64
Field Status : current
Description : status_507
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.59

Field Name : portOperHttpVportCpuListStatus506
Field Type : CounterBasedGauge64
Field Status : current
Description : status_506
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.58

Field Name : portOperHttpVportCpuListStatus505
Field Type : CounterBasedGauge64
Field Status : current
Description : status_505
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.57

Field Name : portOperHttpVportCpuListStatus504Ax
Field Type : CounterBasedGauge64
Field Status : current
Description : status_504_ax
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.56

Field Name : portOperHttpVportCpuListStatus504
Field Type : CounterBasedGauge64
Field Status : current
Description : status_504
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.55

Field Name : portOperHttpVportCpuListStatus503
Field Type : CounterBasedGauge64
Field Status : current
Description : status_503
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.54

Field Name : portOperHttpVportCpuListStatus502
Field Type : CounterBasedGauge64
Field Status : current
Description : status_502
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.53

Field Name : portOperHttpVportCpuListStatus501
Field Type : CounterBasedGauge64
Field Status : current
Description : status_501
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.52

Field Name : portOperHttpVportCpuListStatus500
Field Type : CounterBasedGauge64
Field Status : current
Description : status_500
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.51

Field Name : portOperHttpVportCpuListStatus450
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : status_450

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.50

Field Name : portOperHttpVportCpuListStatus449

Field Type : CounterBasedGauge64

Field Status : current

Description : status_449

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.49

Field Name : portOperHttpVportCpuListStatus426

Field Type : CounterBasedGauge64

Field Status : current

Description : status_426

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.48

Field Name : portOperHttpVportCpuListStatus425

Field Type : CounterBasedGauge64

Field Status : current

Description : status_425

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.47

Field Name : portOperHttpVportCpuListStatus424

Field Type : CounterBasedGauge64

Field Status : current

Description : status_424

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.46

Field Name : portOperHttpVportCpuListStatus423

Field Type : CounterBasedGauge64

Field Status : current

Description : status_423

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.45

Field Name : portOperHttpVportCpuListStatus422

Field Type : CounterBasedGauge64

Field Status : current

Description : status_422

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.44

Field Name : portOperHttpVportCpuListStatus418

Field Type : CounterBasedGauge64

Field Status : current

Description : status_418

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.43

Field Name : portOperHttpVportCpuListStatus417

Field Type : CounterBasedGauge64

Field Status : current

Description : status_417

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.42

Field Name : portOperHttpVportCpuListStatus416

Field Type : CounterBasedGauge64

Field Status : current

Description : status_416

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.41

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperHttpVportCpuListStatus415
Field Type : CounterBasedGauge64
Field Status : current
Description : status_415
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.40

Field Name : portOperHttpVportCpuListStatus414
Field Type : CounterBasedGauge64
Field Status : current
Description : status_414
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.39

Field Name : portOperHttpVportCpuListStatus413
Field Type : CounterBasedGauge64
Field Status : current
Description : status_413
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.38

Field Name : portOperHttpVportCpuListStatus412
Field Type : CounterBasedGauge64
Field Status : current
Description : status_412
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.37

Field Name : portOperHttpVportCpuListStatus411
Field Type : CounterBasedGauge64
Field Status : current
Description : status_411
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.36

Field Name : portOperHttpVportCpuListStatus410
Field Type : CounterBasedGauge64
Field Status : current
Description : status_410
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.35

Field Name : portOperHttpVportCpuListStatus409
Field Type : CounterBasedGauge64
Field Status : current
Description : status_409
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.34

Field Name : portOperHttpVportCpuListStatus408
Field Type : CounterBasedGauge64
Field Status : current
Description : status_408
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.33

Field Name : portOperHttpVportCpuListStatus407
Field Type : CounterBasedGauge64
Field Status : current
Description : status_407
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.32

Field Name : portOperHttpVportCpuListStatus406
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : status_406

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.31

Field Name : portOperHttpVportCpuListStatus405

Field Type : CounterBasedGauge64

Field Status : current

Description : status_405

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.30

Field Name : portOperHttpVportCpuListStatus404

Field Type : CounterBasedGauge64

Field Status : current

Description : status_404

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.29

Field Name : portOperHttpVportCpuListStatus403

Field Type : CounterBasedGauge64

Field Status : current

Description : status_403

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.28

Field Name : portOperHttpVportCpuListStatus402

Field Type : CounterBasedGauge64

Field Status : current

Description : status_402

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.27

Field Name : portOperHttpVportCpuListStatus401

Field Type : CounterBasedGauge64

Field Status : current

Description : status_401

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.26

Field Name : portOperHttpVportCpuListStatus400

Field Type : CounterBasedGauge64

Field Status : current

Description : status_400

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.25

Field Name : portOperHttpVportCpuListStatus307

Field Type : CounterBasedGauge64

Field Status : current

Description : status_307

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.24

Field Name : portOperHttpVportCpuListStatus306

Field Type : CounterBasedGauge64

Field Status : current

Description : status_306

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.23

Field Name : portOperHttpVportCpuListStatus305

Field Type : CounterBasedGauge64

Field Status : current

Description : status_305

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.22

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperHttpVportCpuListStatus304
Field Type : CounterBasedGauge64
Field Status : current
Description : status_304
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.21

Field Name : portOperHttpVportCpuListStatus303
Field Type : CounterBasedGauge64
Field Status : current
Description : status_303
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.20

Field Name : portOperHttpVportCpuListStatus302
Field Type : CounterBasedGauge64
Field Status : current
Description : status_302
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.19

Field Name : portOperHttpVportCpuListStatus301
Field Type : CounterBasedGauge64
Field Status : current
Description : status_301
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.18

Field Name : portOperHttpVportCpuListStatus300
Field Type : CounterBasedGauge64
Field Status : current
Description : status_300
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.17

Field Name : portOperHttpVportCpuListStatus103
Field Type : CounterBasedGauge64
Field Status : current
Description : status_103
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.214

Field Name : portOperHttpVportCpuListStatus102
Field Type : CounterBasedGauge64
Field Status : current
Description : status_102
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.16

Field Name : portOperHttpVportCpuListStatus101
Field Type : CounterBasedGauge64
Field Status : current
Description : status_101
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.15

Field Name : portOperHttpVportCpuListStatus100
Field Type : CounterBasedGauge64
Field Status : current
Description : status_100
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.14

Field Name : portOperHttpVportCpuListStatus207
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Description : status_207

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.13

Field Name : portOperHttpVportCpuListStatus206

Field Type : CounterBasedGauge64

Field Status : current

Description : status_206

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.12

Field Name : portOperHttpVportCpuListStatus205

Field Type : CounterBasedGauge64

Field Status : current

Description : status_205

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.11

Field Name : portOperHttpVportCpuListStatus204

Field Type : CounterBasedGauge64

Field Status : current

Description : status_204

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.10

Field Name : portOperHttpVportCpuListStatus203

Field Type : CounterBasedGauge64

Field Status : current

Description : status_203

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.9

Field Name : portOperHttpVportCpuListStatus202

Field Type : CounterBasedGauge64

Field Status : current

Description : status_202

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.8

Field Name : portOperHttpVportCpuListStatus201

Field Type : CounterBasedGauge64

Field Status : current

Description : status_201

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.7

Field Name : portOperHttpVportCpuListStatus200

Field Type : CounterBasedGauge64

Field Status : current

Description : status_200

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.6

Field Name : portOperHttpVportCpuListHttpVportCpuListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.5

Field Name : portOperHttpVportCpuListProtocol

Field Type : String

Field Status : current

Description : protocol

OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.4

ACOS-SLB-VIRTUAL-SERVER-MIB_oid_list

Field Name : portOperHttpVportCpuListPort
Field Type : Integer32
Field Status : current
Description : port-number
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.3

Field Name : portOperHttpVportCpuListName
Field Type : String
Field Status : current
Description : name
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.2

Field Name : portOperHttpVportCpuListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.321.1.4.4.1.1

ACOS-SO-COUNTERS-STATS-MIB_acosSoCounters_oid_list

Field Name : soHairpinConnSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin connection success
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.56

Field Name : soHairpinIntfWrongTag
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin wrong hairpin interface tag
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.55

Field Name : soHairpinNoHairpinIntf
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin no hairpin interface
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.54

Field Name : soHairpinConnExtFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin connection extension failed
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.53

Field Name : soHairpinNoFwdDev
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin no fwd device
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.52

Field Name : soHairpinMissingPktHash
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin missing pkt hash
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.51

Field Name : soHairpinInboundNoDstChange
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin inbound conn no dest change
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.50

Field Name : soHairpinIncorrectIntfTag
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin incorrect interface tag
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.49

Field Name : soHairpinInboundCheckNoRoute
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout hairpin inbound check no route
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.48

Field Name : soPktsL2redirectTxFragVlanAddFail
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SO-COUNTERS-STATS-MIB_acosSoCounters_oid_list

Description : L2 redirect tx pkt failed to add vlan
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.47

Field Name : soPktsL2redirectFragVlanRetrievalError
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 redirect pkt frag vlan not retrieved
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.46

Field Name : soPktsRedirectionLoopDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets redirection loop drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.45

Field Name : soPktsCgnTrafficMapMismatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : CGN packets traffic map mismatch drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.44

Field Name : soSyncSlbShadowSessionDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent Sync message for SLB Shadow session deletion
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.43

Field Name : soSyncSlbShadowSessionCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent Sync message for SLB Shadow session creation
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.42

Field Name : soSlbShadowSessionCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : SLB Shadow Session created
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.41

Field Name : soPktsL2redirectSamePktMultipleTimes
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 redirect same pkt multiple times
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.40

Field Name : soPktsL2redirectLoopDetectDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 redirect pkt loop detected and dropped
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.39

Field Name : soPktsL2redirectPortRetrievalError
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 redirect pkt port not retrieved
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.38

ACOS-SO-COUNTERS-STATS-MIB_acosSoCounters_oid_list

Field Name : soPktsL2redirectVlanRetrievalError
Field Type : CounterBasedGauge64
Field Status : current
Description : L2 redirect pkt vlan not retrieved
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.37

Field Name : soHcDeregistrationDone
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout stats block de-registered with HC
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.36

Field Name : soHcRegistrationDone
Field Type : CounterBasedGauge64
Field Status : current
Description : Scaleout stats block registered with HC
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.35

Field Name : soFwInternalRuleCount
Field Type : CounterBasedGauge64
Field Status : current
Description : FW internal rule count
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.34

Field Name : soSyncShadowStatsToActive
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Shadow session stats from shadow to active
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.33

Field Name : soSyncFwShadowExt
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync FW Shadow extension creation/updation
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.32

Field Name : soSyncFwShadowSessionDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent Sync message for FW Shadow session deletion
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.31

Field Name : soSyncFwShadowSessionCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Sent Sync message for FW Shadow session creation
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.30

Field Name : soPktsL3RedirectEncapMtuErrorDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Received L3 Redirected MTU not enough to add encap
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.29

Field Name : soPktsL3RedirectTooLargePktsInDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SO-COUNTERS-STATS-MIB_acosSoCounters_oid_list

Description : Received L3 Redirected fragmented packets too large
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.28

Field Name : soPktsL3RedirectEncapIpv6JumboFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Redirect tx ipv6 packet after encap more than max jumbo size
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.27

Field Name : soPktsL3RedirectEncapIpv4JumboFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Redirect ipv4 packet after encap more than max jumbo size
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.26

Field Name : soPktsL3RedirectChassisDestMacError
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Redirect RX multi-slot Destination MAC Error
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.25

Field Name : soPktsL3RedirectInvalidDevDir
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Redirect Invalid Device direction during transmission
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.24

Field Name : soPktsL3RedirectTableNoEntryFound
Field Type : TABLE
Field Status : current
Description : L3 redirect Table no redirect entry found error
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.23

Field Name : soPktsL3RedirectFragmentationError
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 redirect encap Fragmentation error
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.22

Field Name : soPktsL3RedirectRcvdInL2ModeDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Received l3 redirect packets in L2 mode Drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.21

Field Name : soPktsL3RedirectTableError
Field Type : TABLE
Field Status : current
Description : L3 Redirect Table error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.20

Field Name : soPktsL3RedirectDecapRxEncapParamsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : L3 Redirect decap Rx encap params error Drop
OID : 1.3.6.1.4.1.22610.2.4.10.143.1.19

ACOS-SO-COUNTERS-STATS-MIB_acosSoCounters_oid_list

Field Name : soPktsL3RedirectDecapNonIpv4VxlanDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : L3 Redirect received non ipv4 VXLAN packet

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.18

Field Name : soPktsL3RedirectDecapVlanSanityDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : L3 Redirect Decap VLAN Sanity Drop during receipt

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.17

Field Name : soPktsL3RedirectInnerMacZeroDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : L3 Redirect inner mac zero drop during transmission

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.16

Field Name : soPktsL3RedirectEncapErrorDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : L3 Redirect encap error drop during transmission

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.15

Field Name : soPktsL2redirectInvalidRedirectInfoError

Field Type : CounterBasedGauge64

Field Status : current

Description : Redirect Table Error due to invalid redirect info

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.14

Field Name : soPktsL2redirectInterfaceNotUp

Field Type : CounterBasedGauge64

Field Status : current

Description : L2redirect Intf is not UP

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.13

Field Name : soPktsL2redirectDestMacZeroDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Destination MAC Address zero Drop

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.12

Field Name : soPktsDestMacMismatchDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Destination MAC Mismatch Drop

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.11

Field Name : soPktsSlbNatReleaseFail

Field Type : CounterBasedGauge64

Field Status : current

Description : Total SLB NAT release failures

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.10

Field Name : soPktsSlbNatReserveFail

Field Type : CounterBasedGauge64

Field Status : current

ACOS-SO-COUNTERS-STATS-MIB_acosSoCounters_oid_list

Description : Total SLB NAT reserve failures

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.9

Field Name : soPktsScaleoutNotActiveDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Scaleout Not Active Drop

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.8

Field Name : soSlbPktsRedirectConnAgedOut

Field Type : CounterBasedGauge64

Field Status : current

Description : Total SLB redirect conns aged out

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.7

Field Name : soPktsTrafficMapNotFoundDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Traffic MAP Not Found Drop

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.6

Field Name : soFwShadowSessionCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : FW Shadow Session created

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.5

Field Name : soRedirectedPktsRcvd

Field Type : CounterBasedGauge64

Field Status : current

Description : Total redirected packets received on node

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.4

Field Name : soPktsDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : Total packets dropped

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.3

Field Name : soRedirectPktsSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Total packets redirected out of node

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.2

Field Name : soPktsRcvd

Field Type : CounterBasedGauge64

Field Status : current

Description : Total data packets received

OID : 1.3.6.1.4.1.22610.2.4.10.143.1.1

ACOS-SYSTEM-CONTROL-CPU-MIB_oid_list

Field Name : controlCpuStatsTable
Field Type : TABLE
Field Status : current
Description : SystemControlCpuInformation from object 'system.control-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1

Field Name : controlCpuStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The controlCpuStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1

Field Name : controlCpuStatsCpu64
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-64
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.66

Field Name : controlCpuStatsCpu63
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-63
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.65

Field Name : controlCpuStatsCpu62
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-62
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.64

Field Name : controlCpuStatsCpu61
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-61
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.63

Field Name : controlCpuStatsCpu60
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-60
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.62

Field Name : controlCpuStatsCpu59
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-59
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.61

Field Name : controlCpuStatsCpu58
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-58
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.60

Field Name : controlCpuStatsCpu57
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-CONTROL-CPU-MIB_oid_list

Description : cpu-57

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.59

Field Name : controlCpuStatsCpu56

Field Type : CounterBasedGauge64

Field Status : current

Description : cpu-56

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.58

Field Name : controlCpuStatsCpu55

Field Type : CounterBasedGauge64

Field Status : current

Description : cpu-55

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.57

Field Name : controlCpuStatsCpu54

Field Type : CounterBasedGauge64

Field Status : current

Description : cpu-54

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.56

Field Name : controlCpuStatsCpu53

Field Type : CounterBasedGauge64

Field Status : current

Description : cpu-53

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.55

Field Name : controlCpuStatsCpu52

Field Type : CounterBasedGauge64

Field Status : current

Description : cpu-52

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.54

Field Name : controlCpuStatsCpu51

Field Type : CounterBasedGauge64

Field Status : current

Description : cpu-51

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.53

Field Name : controlCpuStatsCpu50

Field Type : CounterBasedGauge64

Field Status : current

Description : cpu-50

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.52

Field Name : controlCpuStatsCpu49

Field Type : CounterBasedGauge64

Field Status : current

Description : cpu-49

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.51

Field Name : controlCpuStatsCpu48

Field Type : CounterBasedGauge64

Field Status : current

Description : cpu-48

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.50

ACOS-SYSTEM-CONTROL-CPU-MIB_oid_list

Field Name : controlCpuStatsCpu47
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-47
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.49

Field Name : controlCpuStatsCpu46
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-46
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.48

Field Name : controlCpuStatsCpu45
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-45
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.47

Field Name : controlCpuStatsCpu44
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-44
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.46

Field Name : controlCpuStatsCpu43
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-43
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.45

Field Name : controlCpuStatsCpu42
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-42
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.44

Field Name : controlCpuStatsCpu41
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-41
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.43

Field Name : controlCpuStatsCpu40
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-40
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.42

Field Name : controlCpuStatsCpu39
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-39
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.41

Field Name : controlCpuStatsCpu38
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-CONTROL-CPU-MIB_oid_list

Description : cpu-38
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.40

Field Name : controlCpuStatsCpu37
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-37
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.39

Field Name : controlCpuStatsCpu36
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-36
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.38

Field Name : controlCpuStatsCpu35
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-35
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.37

Field Name : controlCpuStatsCpu34
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-34
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.36

Field Name : controlCpuStatsCpu33
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-33
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.35

Field Name : controlCpuStatsCpu32
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-32
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.34

Field Name : controlCpuStatsCpu31
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-31
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.33

Field Name : controlCpuStatsCpu30
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-30
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.32

Field Name : controlCpuStatsCpu29
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-29
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.31

ACOS-SYSTEM-CONTROL-CPU-MIB_oid_list

Field Name : controlCpuStatsCpu28
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-28
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.30

Field Name : controlCpuStatsCpu27
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-27
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.29

Field Name : controlCpuStatsCpu26
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-26
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.28

Field Name : controlCpuStatsCpu25
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-25
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.27

Field Name : controlCpuStatsCpu24
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-24
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.26

Field Name : controlCpuStatsCpu23
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-23
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.25

Field Name : controlCpuStatsCpu22
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-22
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.24

Field Name : controlCpuStatsCpu21
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-21
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.23

Field Name : controlCpuStatsCpu20
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-20
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.22

Field Name : controlCpuStatsCpu19
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-CONTROL-CPU-MIB_oid_list

Description : cpu-19
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.21

Field Name : controlCpuStatsCpu18
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-18
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.20

Field Name : controlCpuStatsCpu17
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-17
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.19

Field Name : controlCpuStatsCpu16
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-16
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.18

Field Name : controlCpuStatsCpu15
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-15
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.17

Field Name : controlCpuStatsCpu14
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-14
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.16

Field Name : controlCpuStatsCpu13
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-13
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.15

Field Name : controlCpuStatsCpu12
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-12
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.14

Field Name : controlCpuStatsCpu11
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-11
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.13

Field Name : controlCpuStatsCpu10
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-10
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.12

ACOS-SYSTEM-CONTROL-CPU-MIB_oid_list

Field Name : controlCpuStatsCpu9
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-9
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.11

Field Name : controlCpuStatsCpu8
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-8
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.10

Field Name : controlCpuStatsCpu7
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-7
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.9

Field Name : controlCpuStatsCpu6
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-6
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.8

Field Name : controlCpuStatsCpu5
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-5
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.7

Field Name : controlCpuStatsCpu4
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-4
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.6

Field Name : controlCpuStatsCpu3
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-3
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.5

Field Name : controlCpuStatsCpu2
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-2
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.4

Field Name : controlCpuStatsCpu1
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-1
OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.3

Field Name : controlCpuStatsCtrlCpuNumber
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-CONTROL-CPU-MIB_oid_list

Description : ctrl-cpu-number

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.2

Field Name : controlCpuStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.47.1.1.1.1

ACOS-SYSTEMCPU-CTRL-CPU-MIB_oid_list

Field Name : ctrlCpuOperCpuUsageTable
Field Type : TABLE
Field Status : current
Description : ControlCPUUsage from object 'system-cpu.ctrl-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3

Field Name : ctrlCpuOperTable
Field Type : TABLE
Field Status : current
Description : ControlCPUUsage from object 'system-cpu.ctrl-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.2

Field Name : ctrlCpuOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ctrlCpuOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.2.1

Field Name : ctrlCpuOperNumberOfCpu
Field Type : CounterBasedGauge64
Field Status : current
Description : number-of-cpu
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.2.1.3

Field Name : ctrlCpuOperCurrentTime
Field Type : String
Field Status : current
Description : current-time
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.2.1.2

Field Name : ctrlCpuOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.2.1.1

Field Name : ctrlCpuOperCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The ctrlCpuOperCpuUsage entry:cpu-usage
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1

Field Name : ctrlCpuOperCpuUsage60Sec
Field Type : CounterBasedGauge64
Field Status : current
Description : 60-sec
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.8

Field Name : ctrlCpuOperCpuUsage30Sec
Field Type : CounterBasedGauge64
Field Status : current
Description : 30-sec
OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.7

Field Name : ctrlCpuOperCpuUsage10Sec
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEMCPU-CTRL-CPU-MIB_oid_list

Description : 10-sec

OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.6

Field Name : ctrlCpuOperCpuUsage5Sec

Field Type : CounterBasedGauge64

Field Status : current

Description : 5-sec

OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.5

Field Name : ctrlCpuOperCpuUsage1Sec

Field Type : CounterBasedGauge64

Field Status : current

Description : 1-sec

OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.4

Field Name : ctrlCpuOperCpuUsageCpuId

Field Type : CounterBasedGauge64

Field Status : current

Description : cpu-id

OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.3

Field Name : ctrlCpuOperCpuUsageCpuUsageListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.2

Field Name : ctrlCpuOperCpuUsageSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.112.1.3.1.1

ACOS-SYSTEMCPU-DATA-CPU-MIB_oid_list

Field Name : dataCpuOperCpuUsageTable
Field Type : TABLE
Field Status : current
Description : DataCPUUsage from object 'system-cpu.data-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3

Field Name : dataCpuOperTable
Field Type : TABLE
Field Status : current
Description : DataCPUUsage from object 'system-cpu.data-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.2

Field Name : dataCpuOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dataCpuOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.2.1

Field Name : dataCpuOperNumberOfDataCpu
Field Type : CounterBasedGauge64
Field Status : current
Description : number-of-data-cpu
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.2.1.3

Field Name : dataCpuOperNumberOfCpu
Field Type : CounterBasedGauge64
Field Status : current
Description : number-of-cpu
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.2.1.2

Field Name : dataCpuOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.2.1.1

Field Name : dataCpuOperCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dataCpuOperCpuUsage entry:cpu-usage
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1

Field Name : dataCpuOperCpuUsageDcpuStr
Field Type : String
Field Status : current
Description : dcpu-str
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.9

Field Name : dataCpuOperCpuUsage60Sec
Field Type : CounterBasedGauge64
Field Status : current
Description : 60-sec
OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.8

Field Name : dataCpuOperCpuUsage30Sec
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEMCPU-DATA-CPU-MIB_oid_list

Description : 30-sec

OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.7

Field Name : dataCpuOperCpuUsage10Sec

Field Type : CounterBasedGauge64

Field Status : current

Description : 10-sec

OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.6

Field Name : dataCpuOperCpuUsage5Sec

Field Type : CounterBasedGauge64

Field Status : current

Description : 5-sec

OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.5

Field Name : dataCpuOperCpuUsage1Sec

Field Type : CounterBasedGauge64

Field Status : current

Description : 1-sec

OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.4

Field Name : dataCpuOperCpuUsageCpuId

Field Type : CounterBasedGauge64

Field Status : current

Description : cpu-id

OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.3

Field Name : dataCpuOperCpuUsageCpuUsageListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.2

Field Name : dataCpuOperCpuUsageSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.111.1.3.1.1

ACOS-SYSTEM-CPU-OPER-MIB_acosSystemCpu_oid_list

Field Name : systemCpuCtrlCpuCpuUsageTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1

Field Name : systemCpuCtrlCpuCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1

Field Name : ctrlSixtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1.6

Field Name : ctrlThirtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1.5

Field Name : ctrlTenSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1.4

Field Name : ctrlFiveSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1.3

Field Name : ctrlOneSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1.2

Field Name : ctrlCpuId
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.2.1.1.1

Field Name : systemCpuDataCpuCpuUsageTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1

Field Name : systemCpuDataCpuCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-CPU-OPER-MIB_acosSystemCpu_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1

Field Name : dcpuStr

Field Type : String

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.7

Field Name : sixtySec

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.6

Field Name : thirtySec

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.5

Field Name : tenSec

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.4

Field Name : fiveSec

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.3

Field Name : oneSec

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.2

Field Name : cpuId

Field Type : INTEGER

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.1.1.1.1

Field Name : systemCpuVportDataCpuVportCpuUsageTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1

Field Name : systemCpuVportDataCpuVportCpuUsageEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1

ACOS-SYSTEM-CPU-OPER-MIB_acosSystemCpu_oid_list

Field Name : sixtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.11

Field Name : thirtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.10

Field Name : tenSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.9

Field Name : fiveSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.8

Field Name : oneSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.7

Field Name : dcpuStr
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.6

Field Name : vportType
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.5

Field Name : cpuId
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.4

Field Name : protocol
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.3

Field Name : portNumber
Field Type : INTEGER
Field Status : current

ACOS-SYSTEM-CPU-OPER-MIB_acosSystemCpu_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.2

Field Name : vserverName

Field Type : String

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.5.1.1.1

Field Name : systemCpuVserverDataCpuVserverCpuUsageTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1

Field Name : systemCpuVserverDataCpuVserverCpuUsageEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1

Field Name : sixtySec

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.8

Field Name : thirtySec

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.7

Field Name : tenSec

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.6

Field Name : fiveSec

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.5

Field Name : oneSec

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.4

Field Name : dcpuStr

Field Type : String

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.3

ACOS-SYSTEM-CPU-OPER-MIB_acosSystemCpu_oid_list

Field Name : cpuId
Field Type : INTEGER
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.2

Field Name : vserverName
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.4.1.1.1

Field Name : systemCpuDataCpuOverallCpuUsageTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1

Field Name : systemCpuDataCpuOverallCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1

Field Name : allDcpuStr
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.7

Field Name : allSixtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.6

Field Name : allThirtySec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.5

Field Name : allTenSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.4

Field Name : allFiveSec
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.3

Field Name : allOneSec
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-CPU-OPER-MIB_acosSystemCpu_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.2

Field Name : allCpuId

Field Type : INTEGER

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.11.40.3.1.1.1

ACOS-SYSTEM-DATA-CPU-MIB_oid_list

Field Name : dataCpuStatsTable
Field Type : TABLE
Field Status : current
Description : SystemDataCpuInformation from object 'system.data-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1

Field Name : dataCpuStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The dataCpuStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1

Field Name : dataCpuStatsCpu100
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-100
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.102

Field Name : dataCpuStatsCpu99
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-99
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.101

Field Name : dataCpuStatsCpu98
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-98
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.100

Field Name : dataCpuStatsCpu97
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-97
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.99

Field Name : dataCpuStatsCpu96
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-96
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.98

Field Name : dataCpuStatsCpu95
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-95
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.97

Field Name : dataCpuStatsCpu94
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-94
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.96

Field Name : dataCpuStatsCpu93
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-DATA-CPU-MIB_oid_list

Description : cpu-93
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.95

Field Name : dataCpuStatsCpu92
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-92
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.94

Field Name : dataCpuStatsCpu91
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-91
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.93

Field Name : dataCpuStatsCpu90
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-90
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.92

Field Name : dataCpuStatsCpu89
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-89
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.91

Field Name : dataCpuStatsCpu88
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-88
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.90

Field Name : dataCpuStatsCpu87
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-87
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.89

Field Name : dataCpuStatsCpu86
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-86
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.88

Field Name : dataCpuStatsCpu85
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-85
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.87

Field Name : dataCpuStatsCpu84
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-84
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.86

ACOS-SYSTEM-DATA-CPU-MIB_oid_list

Field Name : dataCpuStatsCpu83
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-83
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.85

Field Name : dataCpuStatsCpu82
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-82
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.84

Field Name : dataCpuStatsCpu81
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-81
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.83

Field Name : dataCpuStatsCpu80
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-80
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.82

Field Name : dataCpuStatsCpu79
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-79
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.81

Field Name : dataCpuStatsCpu78
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-78
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.80

Field Name : dataCpuStatsCpu77
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-77
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.79

Field Name : dataCpuStatsCpu76
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-76
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.78

Field Name : dataCpuStatsCpu75
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-75
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.77

Field Name : dataCpuStatsCpu74
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-DATA-CPU-MIB_oid_list

Description : cpu-74
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.76

Field Name : dataCpuStatsCpu73
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-73
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.75

Field Name : dataCpuStatsCpu72
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-72
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.74

Field Name : dataCpuStatsCpu71
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-71
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.73

Field Name : dataCpuStatsCpu70
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-70
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.72

Field Name : dataCpuStatsCpu69
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-69
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.71

Field Name : dataCpuStatsCpu68
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-68
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.70

Field Name : dataCpuStatsCpu67
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-67
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.69

Field Name : dataCpuStatsCpu66
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-66
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.68

Field Name : dataCpuStatsCpu65
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-65
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.67

ACOS-SYSTEM-DATA-CPU-MIB_oid_list

Field Name : dataCpuStatsCpu64
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-64
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.66

Field Name : dataCpuStatsCpu63
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-63
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.65

Field Name : dataCpuStatsCpu62
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-62
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.64

Field Name : dataCpuStatsCpu61
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-61
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.63

Field Name : dataCpuStatsCpu60
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-60
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.62

Field Name : dataCpuStatsCpu59
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-59
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.61

Field Name : dataCpuStatsCpu58
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-58
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.60

Field Name : dataCpuStatsCpu57
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-57
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.59

Field Name : dataCpuStatsCpu56
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-56
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.58

Field Name : dataCpuStatsCpu55
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-DATA-CPU-MIB_oid_list

Description : cpu-55
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.57

Field Name : dataCpuStatsCpu54
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-54
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.56

Field Name : dataCpuStatsCpu53
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-53
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.55

Field Name : dataCpuStatsCpu52
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-52
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.54

Field Name : dataCpuStatsCpu51
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-51
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.53

Field Name : dataCpuStatsCpu50
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-50
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.52

Field Name : dataCpuStatsCpu49
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-49
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.51

Field Name : dataCpuStatsCpu48
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-48
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.50

Field Name : dataCpuStatsCpu47
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-47
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.49

Field Name : dataCpuStatsCpu46
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-46
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.48

ACOS-SYSTEM-DATA-CPU-MIB_oid_list

Field Name : dataCpuStatsCpu45
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-45
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.47

Field Name : dataCpuStatsCpu44
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-44
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.46

Field Name : dataCpuStatsCpu43
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-43
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.45

Field Name : dataCpuStatsCpu42
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-42
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.44

Field Name : dataCpuStatsCpu41
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-41
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.43

Field Name : dataCpuStatsCpu40
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-40
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.42

Field Name : dataCpuStatsCpu39
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-39
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.41

Field Name : dataCpuStatsCpu38
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-38
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.40

Field Name : dataCpuStatsCpu37
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-37
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.39

Field Name : dataCpuStatsCpu36
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-DATA-CPU-MIB_oid_list

Description : cpu-36
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.38

Field Name : dataCpuStatsCpu35
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-35
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.37

Field Name : dataCpuStatsCpu34
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-34
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.36

Field Name : dataCpuStatsCpu33
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-33
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.35

Field Name : dataCpuStatsCpu32
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-32
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.34

Field Name : dataCpuStatsCpu31
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-31
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.33

Field Name : dataCpuStatsCpu30
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-30
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.32

Field Name : dataCpuStatsCpu29
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-29
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.31

Field Name : dataCpuStatsCpu28
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-28
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.30

Field Name : dataCpuStatsCpu27
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-27
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.29

ACOS-SYSTEM-DATA-CPU-MIB_oid_list

Field Name : dataCpuStatsCpu26
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-26
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.28

Field Name : dataCpuStatsCpu25
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-25
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.27

Field Name : dataCpuStatsCpu24
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-24
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.26

Field Name : dataCpuStatsCpu23
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-23
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.25

Field Name : dataCpuStatsCpu22
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-22
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.24

Field Name : dataCpuStatsCpu21
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-21
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.23

Field Name : dataCpuStatsCpu20
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-20
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.22

Field Name : dataCpuStatsCpu19
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-19
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.21

Field Name : dataCpuStatsCpu18
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-18
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.20

Field Name : dataCpuStatsCpu17
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-DATA-CPU-MIB_oid_list

Description : cpu-17
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.19

Field Name : dataCpuStatsCpu16
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-16
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.18

Field Name : dataCpuStatsCpu15
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-15
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.17

Field Name : dataCpuStatsCpu14
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-14
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.16

Field Name : dataCpuStatsCpu13
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-13
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.15

Field Name : dataCpuStatsCpu12
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-12
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.14

Field Name : dataCpuStatsCpu11
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-11
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.13

Field Name : dataCpuStatsCpu10
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-10
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.12

Field Name : dataCpuStatsCpu9
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-9
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.11

Field Name : dataCpuStatsCpu8
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-8
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.10

ACOS-SYSTEM-DATA-CPU-MIB_oid_list

Field Name : dataCpuStatsCpu7
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-7
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.9

Field Name : dataCpuStatsCpu6
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-6
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.8

Field Name : dataCpuStatsCpu5
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-5
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.7

Field Name : dataCpuStatsCpu4
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-4
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.6

Field Name : dataCpuStatsCpu3
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-3
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.5

Field Name : dataCpuStatsCpu2
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-2
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.4

Field Name : dataCpuStatsCpu1
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-1
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.3

Field Name : dataCpuStatsDataCpuNumber
Field Type : CounterBasedGauge64
Field Status : current
Description : data-cpu-number
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.2

Field Name : dataCpuStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.48.1.1.1.1

ACOS-SYSTEM-OPER-MIB_acosSystem_oid_list

Field Name : Total
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.22.1

Field Name : memory
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.7

Field Name : storage
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.6

Field Name : cpuStepping
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.5

Field Name : cpuCores
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.4

Field Name : cpu
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.3

Field Name : serial
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.2

Field Name : platformDescription
Field Type : String
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.11.39.32.1

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : cpurrdrop
Field Type : CounterBasedGauge64
Field Status : current
Description : CPU round robin packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.98

Field Name : proxyheaderv2
Field Type : CounterBasedGauge64
Field Status : current
Description : Proxy header v2
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.97

Field Name : proxyheaderv1
Field Type : CounterBasedGauge64
Field Status : current
Description : Proxy header v1
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.96

Field Name : a2bsndwnd
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP send window
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.95

Field Name : mburstlim
Field Type : CounterBasedGauge64
Field Status : current
Description : Maxburst limited tx
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.94

Field Name : earlyrexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Early Retransmission sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.93

Field Name : atcpsendfail
Field Type : CounterBasedGauge64
Field Status : current
Description : Adaptive TCP sent fails
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.91

Field Name : a2bappbuffering
Field Type : CounterBasedGauge64
Field Status : current
Description : Transition to full stack on when application buffers too much data
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.90

Field Name : atcpbuffallocfail
Field Type : CounterBasedGauge64
Field Status : current
Description : Adaptive TCP buffer allocation fails
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.89

Field Name : atcprexmit
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Adaptive TCP retransmits
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.88

Field Name : atcpsendbackack
Field Type : CounterBasedGauge64
Field Status : current
Description : Adaptive TCP sendback ACK
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.87

Field Name : atcprexmitsadrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Adaptive TCP transmit SA drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.86

Field Name : atcpsent
Field Type : CounterBasedGauge64
Field Status : current
Description : Adaptive TCP sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.85

Field Name : atcpforward
Field Type : CounterBasedGauge64
Field Status : current
Description : Adaptive TCP forward
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.84

Field Name : badIoChan
Field Type : CounterBasedGauge64
Field Status : current
Description : IO Channel Modified
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.83

Field Name : b2atrtransitionnum
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP total transitions
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.82

Field Name : a2btransitionnum
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP total transitions
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.81

Field Name : a2bfsmtransition
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP state machine transition
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.76

Field Name : a2bpartialack
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP partial ack received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.75

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : a2boodata
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP oo data received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.74

Field Name : a2btcpoptions
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP unsupported TCP options
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.73

Field Name : a2brxdata
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP Rxmitted data
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.72

Field Name : a2bdupack
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP Dup/00 ACK
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.71

Field Name : a2bsackpresent
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP SACK options present
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.70

Field Name : a2brcvwnd
Field Type : CounterBasedGauge64
Field Status : current
Description : ATCP to BTCP receive window
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.69

Field Name : rcvdsack
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcvd DSACK packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.68

Field Name : ccReduce
Field Type : CounterBasedGauge64
Field Status : current
Description : Congestion control window reduced by event
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.67

Field Name : ccIdle
Field Type : CounterBasedGauge64
Field Status : current
Description : Congestion control window set do to idle
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.66

Field Name : reasstimeout
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Reassembly Time Out

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.92

Field Name : reassmemdrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Packet dropped during reassembly

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.65

Field Name : cacklim

Field Type : CounterBasedGauge64

Field Status : current

Description : Challenge ACK limited

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.64

Field Name : sndcack

Field Type : CounterBasedGauge64

Field Status : current

Description : Challenge ACK sent

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.63

Field Name : sackSendBlocks

Field Type : CounterBasedGauge64

Field Status : current

Description : SACK sent

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.60

Field Name : sackRcvBlocks

Field Type : CounterBasedGauge64

Field Status : current

Description : SACK received

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.59

Field Name : sackRexmitBytes

Field Type : CounterBasedGauge64

Field Status : current

Description : SACK rexmit bytes

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.58

Field Name : sackRexmits

Field Type : CounterBasedGauge64

Field Status : current

Description : SACK rexmit segments

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.57

Field Name : sackRecoveryEpisode

Field Type : CounterBasedGauge64

Field Status : current

Description : SACK recovery episodes

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.56

Field Name : finwait2Drops

Field Type : CounterBasedGauge64

Field Status : current

Description : Drop FIN_WAIT_2 connection after time limit

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.55

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : badrst
Field Type : CounterBasedGauge64
Field Status : current
Description : Ignored RST
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.54

Field Name : persistdrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Timeout in persist state
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.52

Field Name : preddat
Field Type : CounterBasedGauge64
Field Status : current
Description : Hdr predict for data pkts
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.51

Field Name : predack
Field Type : CounterBasedGauge64
Field Status : current
Description : Hdr predict for acks
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.50

Field Name : pawsdrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Segments dropped due to PAWS
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.49

Field Name : rcvwinupd
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcvd window update packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.48

Field Name : rcvackbyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes acked by rcvd acks
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.47

Field Name : rcvackpack
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcvd ack packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.46

Field Name : rcvacktoomuch
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcvd acks for unsent data
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.45

Field Name : rcvdupack
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Rcvd duplicate acks
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.44

Field Name : rcvwinprobe
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcvd window probe packet
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.43

Field Name : rcvbyteafterwin
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes rcvd after window
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.42

Field Name : rcvpackafterwin
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets with data after window
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.41

Field Name : rcvoobyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-of-order bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.40

Field Name : rcvoopack
Field Type : CounterBasedGauge64
Field Status : current
Description : Out-of-order packet received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.39

Field Name : rcvpartdupbyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Dup. bytes in part-dup. packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.38

Field Name : rcvpartduppack
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet with some duplicate data
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.37

Field Name : rcvdupbyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.36

Field Name : rcvduppack
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate packet received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.35

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : rcvmemdrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet dropped for lack of memory
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.33

Field Name : rcvbadoff
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet received with bad offset
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.32

Field Name : rcvbyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Bytes received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.31

Field Name : rcvpack
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.30

Field Name : rcvtotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packet received
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.29

Field Name : sndsyn
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.28

Field Name : sndfin
Field Type : CounterBasedGauge64
Field Status : current
Description : FIN packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.27

Field Name : sndrst
Field Type : CounterBasedGauge64
Field Status : current
Description : RST packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.26

Field Name : sndctrl
Field Type : CounterBasedGauge64
Field Status : current
Description : SYN|FIN|RST packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.25

Field Name : sndwinup
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Window update packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.24

Field Name : sndurg
Field Type : CounterBasedGauge64
Field Status : current
Description : URG packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.23

Field Name : sndprobe
Field Type : CounterBasedGauge64
Field Status : current
Description : Window probe sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.22

Field Name : sndacks
Field Type : CounterBasedGauge64
Field Status : current
Description : Ack packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.21

Field Name : sndrexmitbad
Field Type : CounterBasedGauge64
Field Status : current
Description : Unnecessary packet retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.20

Field Name : sndrexmitbyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Data byte retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.19

Field Name : sndrexmitpack
Field Type : CounterBasedGauge64
Field Status : current
Description : Data packet retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.18

Field Name : sndbyte
Field Type : CounterBasedGauge64
Field Status : current
Description : Data bytes sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.17

Field Name : sndpack
Field Type : CounterBasedGauge64
Field Status : current
Description : Data packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.16

Field Name : sndtotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packet sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.15

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : keepdrops
Field Type : CounterBasedGauge64
Field Status : current
Description : Connect dropped in keepalive
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.14

Field Name : keepprobe
Field Type : CounterBasedGauge64
Field Status : current
Description : Keepalive probe sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.13

Field Name : keeptimeo
Field Type : CounterBasedGauge64
Field Status : current
Description : Keepalive timeout
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.12

Field Name : persisttimeo
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist timeout
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.11

Field Name : rexmttimeo
Field Type : CounterBasedGauge64
Field Status : current
Description : Retransmit timeout
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.10

Field Name : timeoutdrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn dropped in rxmt timeout
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.9

Field Name : delack
Field Type : CounterBasedGauge64
Field Status : current
Description : Delayed acks sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.8

Field Name : rttupdated
Field Type : CounterBasedGauge64
Field Status : current
Description : Update RTT
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.7

Field Name : segstimed
Field Type : CounterBasedGauge64
Field Status : current
Description : Segs to get RTT
OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.6

Field Name : closed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Connect closed

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.5

Field Name : conndrops

Field Type : CounterBasedGauge64

Field Status : current

Description : Embryonic connect dropped

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.4

Field Name : drops

Field Type : CounterBasedGauge64

Field Status : current

Description : Connect dropped

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.3

Field Name : connects

Field Type : CounterBasedGauge64

Field Status : current

Description : Connect established

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.2

Field Name : connattempt

Field Type : CounterBasedGauge64

Field Status : current

Description : Connect initiated

OID : 1.3.6.1.4.1.22610.2.4.10.39.57.1.1

Field Name : noFreeBuffers

Field Type : CounterBasedGauge64

Field Status : current

Description : No Free Buffers to send R.A.

OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.10

Field Name : l2AddrAndUnspec

Field Type : CounterBasedGauge64

Field Status : current

Description : R.S. Src Link-Layer Option and Unspecified Address

OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.9

Field Name : badIcmpv6Option

Field Type : CounterBasedGauge64

Field Status : current

Description : R.S. Bad ICMPv6 Option

OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.8

Field Name : badIcmpv6Code

Field Type : CounterBasedGauge64

Field Status : current

Description : R.S. Unknown ICMPv6 Code

OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.7

Field Name : badIcmpv6Csum

Field Type : CounterBasedGauge64

Field Status : current

Description : R.S. Bad ICMPv6 Checksum

OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.6

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : truncated
Field Type : CounterBasedGauge64
Field Status : current
Description : R.S. Truncated
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.5

Field Name : badHopLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : R.S. Bad Hop Limit
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.4

Field Name : rateLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : R.S. Rate Limited
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.3

Field Name : periodicSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Periodic Router Advertisements (R.A.) Sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.2

Field Name : goodRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : Good Router Solicitations (R.S.) Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.56.1.1

Field Name : totalSystemSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Total system-wide sessions
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.110

Field Name : freeConnNotInSp
Field Type : CounterBasedGauge64
Field Status : current
Description : Attempt to Free a Conn Whoes Address Not in Session Pool
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.109

Field Name : schedConnWithWrongNextIdxToRml
Field Type : CounterBasedGauge64
Field Status : current
Description : Attempt to Put a Conn to RML Whose next_idx is NOT Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.108

Field Name : serverTcpHalfOpenCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Server TCP Half Open
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.107

Field Name : serverTcpEstCounter
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Server TCP Established
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.106

Field Name : fwBlacklistSessFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Blacklist Session Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.105

Field Name : fwBlacklistSessCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Blacklist Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.104

Field Name : fwBlacklistSess
Field Type : CounterBasedGauge64
Field Status : current
Description : Blacklist Sessions
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.103

Field Name : gtpCumConnFreedCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP cumulative Conn Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.102

Field Name : gtpCumConnCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP cumulative Conn Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.101

Field Name : gtpCurrFreeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Current Available Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.100

Field Name : gtpUEchoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Echo Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.99

Field Name : gtpCEchoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Echo Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.98

Field Name : gtpUCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.97

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : gtpCHalfOpenCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Half Open
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.96

Field Name : gtpCEstCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Established
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.95

Field Name : totalLoggingConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Logging Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.94

Field Name : sslForwardProxyEsniResetTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy ESNI Drop Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.93

Field Name : sslForwardProxyEsniBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy ESNI Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.92

Field Name : totalServersideFailedEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total serverside failed early data connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.91

Field Name : totalClientsideFailedEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total clientside failed early data connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.90

Field Name : totalServersideEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total serverside early data connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.89

Field Name : totalClientsideEarlyDataConnections
Field Type : CounterBasedGauge64
Field Status : current
Description : Total clientside early data connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.88

Field Name : serverSslSessionTicketReuseTotal
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Total SSL Server Session Ticket Reuse
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.87

Field Name : clientSslSessionTicketReuseTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Client Session Ticket Reuse
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.86

Field Name : diameterConcurrentUserSessionsCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Diameter Concurrent User-Sessions
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.85

Field Name : sslForwardProxyAdGrpupBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy AD-Group Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.84

Field Name : sslForwardProxyUsernameBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Username Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.83

Field Name : sslForwardProxyNoSniResetTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy No SNI reset Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.82

Field Name : sslForwardProxyNoSniBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy No SNI Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.81

Field Name : sslForwardProxyCertSanBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Certificate SAN Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.80

Field Name : sslForwardProxyCertIssuerBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Certificate Issuer Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.79

Field Name : sslForwardProxyCertSubjectBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Certificate Subject Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.78

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : sslForwardProxyFailedAflexTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy AFLEX Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.77

Field Name : totalDebugConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Debug Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.76

Field Name : serverTemplateUnknownErr
Field Type : CounterBasedGauge64
Field Status : current
Description : server template unknown error
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.75

Field Name : serverTemplateIntErr
Field Type : CounterBasedGauge64
Field Status : current
Description : server template int error
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.74

Field Name : clientTemplateUnknownErr
Field Type : CounterBasedGauge64
Field Status : current
Description : client template unknown error
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.73

Field Name : clientTemplateIntErr
Field Type : CounterBasedGauge64
Field Status : current
Description : client template internal error
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.72

Field Name : serverSslFinRst
Field Type : CounterBasedGauge64
Field Status : current
Description : server ssl fin rst
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.71

Field Name : serverSslFatalAlert
Field Type : CounterBasedGauge64
Field Status : current
Description : server ssl fatal alert
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.70

Field Name : fpSessionFinRst
Field Type : CounterBasedGauge64
Field Status : current
Description : FP Session FIN/RST
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.69

Field Name : clientSslFinRst
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : client ssl fin rst

OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.68

Field Name : clientSslFatalAlert

Field Type : CounterBasedGauge64

Field Status : current

Description : client ssl fatal alert

OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.67

Field Name : totalCurrConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Curr Conn

OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.66

Field Name : totalLocalConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Local Conn

OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.65

Field Name : totalFwConn

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Firewall Conn

OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.64

Field Name : debugUdpCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Hidden UDP sessions for CGNv6 Stateless Technologies

OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.63

Field Name : debugTcpCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Hidden TCP sessions for CGNv6 Stateless Technologies

OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.62

Field Name : diameterConnFreedCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Diameter Conn Freed

OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.61

Field Name : diameterConnCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Diameter Conn Count

OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.60

Field Name : connAppSmpAllocCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn APP SMP Alloc

OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.59

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : sslForwardProxyClientAuthBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Client Auth Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.58

Field Name : sslForwardProxySniBypassTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy SNI Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.57

Field Name : sslForwardProxyFailedSslVersionTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Unsupported version Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.56

Field Name : sslForwardProxyFailedCertSigningTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Failed Certificate Signing Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.55

Field Name : sslForwardProxyRevokedOcspTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Revoked OCSP Response Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.54

Field Name : sslForwardProxyInvalidOcspStaplingTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Invalid OCSP Stapling Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.53

Field Name : sslForwardProxyFailedCertVerifyTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Failed Certificate Verification Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.52

Field Name : sslForwardProxyFailedCryptoTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Failed Crypto Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.51

Field Name : sslForwardProxyFailedTcpTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Forward Proxy Failed TCP Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.50

Field Name : sslForwardProxyFailedHandshakeTotal
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Total SSL Forward Proxy Failed Handshake Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.49

Field Name : sslFailsafeTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Failsafe Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.48

Field Name : nonsslBypass
Field Type : CounterBasedGauge64
Field Status : current
Description : NON SSL Bypass Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.47

Field Name : sctpEstCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Established
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.46

Field Name : sctpHalfOpenCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : SCTP Half Open
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.45

Field Name : connSmpType4Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Type 4 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.44

Field Name : connSmpType3Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Type 3 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.43

Field Name : connSmpType2Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Type 2 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.42

Field Name : connSmpType1Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Type 1 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.41

Field Name : connSmpType0Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Type 0 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.40

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : connType4Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Type 4 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.39

Field Name : connType3Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Type 3 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.38

Field Name : connType2Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Type 2 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.37

Field Name : connType1Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Type 1 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.36

Field Name : connType0Available
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Type 0 Available
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.35

Field Name : clientSslCtxMallocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Client SSL Ctx malloc Failures
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.34

Field Name : totalL2L3Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Totl L2/L3 Connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.33

Field Name : totalIpNatConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IP Nat Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.32

Field Name : sslClientCertAuthFail
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Client Cert Auth Failures
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.31

Field Name : sslServerCertError
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : SSL Server Cert Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.30

Field Name : sslFailedCaVerification
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Cert Auth Verification Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.29

Field Name : sslFailedTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Failures
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.28

Field Name : serverSslReuseTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Server Reuse
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.27

Field Name : clientSslReuseTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Client Reuse
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.26

Field Name : serverSslCountTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Server Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.25

Field Name : serverSslCountCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Current SSL Server Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.24

Field Name : sslCountTotal
Field Type : CounterBasedGauge64
Field Status : current
Description : Total SSL Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.23

Field Name : sslCountCurr
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr SSL Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.22

Field Name : connSmpAgedCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Aged
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.21

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : connSmpFreeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Free
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.20

Field Name : connSmpAllocCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn SMP Alloc
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.19

Field Name : tcpSynHalfOpenCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP SYN Half Open
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.18

Field Name : reverseNatUdpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse NAT UDP
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.17

Field Name : reverseNatTcpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Reverse NAT TCP
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.16

Field Name : otherCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Non TCP/UDP IP sessions
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.15

Field Name : ipCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : IP Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.14

Field Name : udpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.13

Field Name : tcpHalfCloseCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Half Closed
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.12

Field Name : tcpHalfOpenCounter
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : TCP Half Open
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.11

Field Name : tcpEstCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP Established
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.10

Field Name : currFreeConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Curr Free Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.9

Field Name : systemSessionTotalTcpConn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.8

Field Name : systemSessionTotalL7Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L7 Conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.7

Field Name : totalL4ConnProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L4 Conn Proxy Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.6

Field Name : totalL7PacketCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L7 Packet Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.5

Field Name : totalL4PacketCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L4 Packet Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.4

Field Name : connFreedCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.3

Field Name : connCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.2

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : systemSessionTotalL4Conn
Field Type : CounterBasedGauge64
Field Status : current
Description : Total L4 Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.55.1.1

Field Name : multipleAnswerNoCache
Field Type : CounterBasedGauge64
Field Status : current
Description : Response not cached due to multiple answers
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.26

Field Name : hitRatePerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache hit rate per second
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.25

Field Name : qps
Field Type : CounterBasedGauge64
Field Status : current
Description : Cache Queries-per-second
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.24

Field Name : truncatedR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response with Truncation bit set
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.23

Field Name : resolverQueueFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Resolver task queue full
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.22

Field Name : currentDataAllocate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current data allocate
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.21

Field Name : currentAllocate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current allocate
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.20

Field Name : dnsTotalFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.19

Field Name : totalAlloc
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Total allocated

OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.18

Field Name : totalLog

Field Type : CounterBasedGauge64

Field Status : current

Description : Total stats log sent

OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.17

Field Name : ageoutWeight

Field Type : CounterBasedGauge64

Field Status : current

Description : Total aged for lower weight

OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.16

Field Name : badAnswer

Field Type : CounterBasedGauge64

Field Status : current

Description : Bad Answer

OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.15

Field Name : ageout

Field Type : CounterBasedGauge64

Field Status : current

Description : Total aged out

OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.14

Field Name : ttlR

Field Type : CounterBasedGauge64

Field Status : current

Description : Response with short TTL

OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.13

Field Name : answerR

Field Type : CounterBasedGauge64

Field Status : current

Description : Response with multiple answers

OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.12

Field Name : multipleR

Field Type : CounterBasedGauge64

Field Status : current

Description : Response with multiple questions

OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.11

Field Name : encoderR

Field Type : CounterBasedGauge64

Field Status : current

Description : Response encoded

OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.10

Field Name : oversizeR

Field Type : CounterBasedGauge64

Field Status : current

Description : Response exceed cache size

OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.9

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : badR
Field Type : CounterBasedGauge64
Field Status : current
Description : Response not passed
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.8

Field Name : oversizeQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query exceed cache size
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.7

Field Name : multipleQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query with multiple questions
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.6

Field Name : encodeQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query encoded
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.5

Field Name : badQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Query not passed
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.4

Field Name : hit
Field Type : CounterBasedGauge64
Field Status : current
Description : Total cache hit
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.3

Field Name : totalR
Field Type : CounterBasedGauge64
Field Status : current
Description : Total server response
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.2

Field Name : totalQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Total query
OID : 1.3.6.1.4.1.22610.2.4.10.39.93.1.1

Field Name : slbDnsEdnsEcsInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of ecs inserted
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.36

Field Name : slbDnsEdnsEcsReceived
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Number of ecs from client received
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.35

Field Name : invalidQLenToUdp
Field Type : CounterBasedGauge64
Field Status : current
Description : invalid query length to conver to UDP
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.34

Field Name : natSlbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : (NAT)DNS requests drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.33

Field Name : slbDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS requests drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.32

Field Name : rpzActionLocalData
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action Local Data
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.31

Field Name : rpzActionNodata
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action NODATA
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.30

Field Name : rpzActionNxdomain
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action NXDOMAIN
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.29

Field Name : rpzActionTcpOnly
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action TCP Only
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.28

Field Name : rpzActionPassThru
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action Pass Through
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.27

Field Name : rpzActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : RPZ Action Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.26

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : slbDnsUdpRetransmitFail
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.25

Field Name : slbDnsUdpRetransmit
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.24

Field Name : slbDnsEdnsSubnetToServerRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.23

Field Name : slbDnsPaddingToClientAdded
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.22

Field Name : slbDnsPaddingToServerRemoved
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.21

Field Name : slbDnsUdpConnSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of backend udp conn established
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.20

Field Name : slbDnsUdpConn
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of backend udp connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.19

Field Name : slbDnsServerSslSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of server ssl success
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.18

Field Name : slbDnsClientSslSucc
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of client ssl success
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.17

Field Name : filterTypeAnyDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Total Query ANY Type Drop

OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.16

Field Name : filterClassDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Query Class Drop

OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.15

Field Name : filterTypeDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Query Type Drop

OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.14

Field Name : natXidReused

Field Type : CounterBasedGauge64

Field Status : current

Description : (NAT) No. of requests reusing a transaction id

OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.13

Field Name : natNoResource

Field Type : CounterBasedGauge64

Field Status : current

Description : (NAT) No. of resource failures

OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.12

Field Name : natRespNoMatch

Field Type : CounterBasedGauge64

Field Status : current

Description : (NAT) No. of requests with no response

OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.11

Field Name : natReqRexmit

Field Type : CounterBasedGauge64

Field Status : current

Description : (NAT) No. of request retransmits

OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.10

Field Name : natNoResp

Field Type : CounterBasedGauge64

Field Status : current

Description : (NAT) No. of resource failures

OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.9

Field Name : natResp

Field Type : CounterBasedGauge64

Field Status : current

Description : (NAT) No. of responses

OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.8

Field Name : natReq

Field Type : CounterBasedGauge64

Field Status : current

Description : (NAT) No. of requests

OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.7

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : slbNoResource
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of resource failures
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.6

Field Name : slbRespNoMatch
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests and responses with no match
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.5

Field Name : slbReqRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests retransmit
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.4

Field Name : slbNoResp
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests with no response
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.3

Field Name : slbResp
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of responses
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.2

Field Name : slbReq
Field Type : CounterBasedGauge64
Field Status : current
Description : No. of requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.92.1.1

Field Name : failComplete
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed to Complete Job
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.11

Field Name : failExecute
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed to Execute Job
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.10

Field Name : qNoSpace
Field Type : CounterBasedGauge64
Field Status : current
Description : No More Space in Q
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.9

Field Name : failSubmit
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Jobs Failed to Submit
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.8

Field Name : complete
Field Type : CounterBasedGauge64
Field Status : current
Description : Jobs Completed
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.7

Field Name : rcvHome
Field Type : CounterBasedGauge64
Field Status : current
Description : Jobs Received Home
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.6

Field Name : sntHome
Field Type : CounterBasedGauge64
Field Status : current
Description : Jobs Sent Back Home
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.5

Field Name : execute
Field Type : CounterBasedGauge64
Field Status : current
Description : Jobs Executed
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.4

Field Name : receive
Field Type : CounterBasedGauge64
Field Status : current
Description : Jobs Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.3

Field Name : submit
Field Type : CounterBasedGauge64
Field Status : current
Description : Jobs Submitted
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.2

Field Name : jobs
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Jobs
OID : 1.3.6.1.4.1.22610.2.4.10.39.131.1.1

Field Name : v6CurrRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current rate (v6)
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.12

Field Name : v6LockupTimeLeft
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockup time left (v6)
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.11

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : v6LimitTotalDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total rate limit drops (v6)
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.10

Field Name : v6LimitVserverDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Virtual Server rate limit drops (v6)
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.9

Field Name : v6LimitIntfDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Interfaces rate limit drops (v6)
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.8

Field Name : v6OverLimitDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Over limit drops (v6)
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.7

Field Name : currRate
Field Type : CounterBasedGauge64
Field Status : current
Description : Current rate
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.6

Field Name : lockupTimeLeft
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockup time left
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.5

Field Name : limitTotalDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total rate limit drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.4

Field Name : limitVserverDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Virtual Server rate limit drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.3

Field Name : limitIntfDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Interfaces rate limit drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.2

Field Name : overLimitDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Over limit drops

OID : 1.3.6.1.4.1.22610.2.4.10.39.54.1.1

Field Name : systemBfdOtherError

Field Type : CounterBasedGauge64

Field Status : current

Description : Other errors

OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.22

Field Name : noIpv6Enable

Field Type : CounterBasedGauge64

Field Status : current

Description : No IPv6 enable

OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.21

Field Name : destUnreachable

Field Type : CounterBasedGauge64

Field Status : current

Description : Destination unreachable

OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.20

Field Name : localStateAdminDown

Field Type : CounterBasedGauge64

Field Status : current

Description : Local admin down session state

OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.19

Field Name : authFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Authentication failures

OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.18

Field Name : authSeqnumInvalid

Field Type : CounterBasedGauge64

Field Status : current

Description : Invalid authentication sequence number

OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.17

Field Name : authKeyMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : Authentication key mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.16

Field Name : authKeyIdMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : Authentication key-id mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.15

Field Name : authTypeMismatch

Field Type : CounterBasedGauge64

Field Status : current

Description : Authentication type mismatch

OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.14

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : authMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Authentication mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.13

Field Name : authLengthInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid authentication length
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.12

Field Name : invalidTtl
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid TTL
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.11

Field Name : invalidMyDisc
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid my descriptor
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.10

Field Name : invalidMultipoint
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid multipoint setting
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.9

Field Name : invalidDetectMult
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid detect multiplier
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.8

Field Name : dataIsShort
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet data length too short
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.7

Field Name : lengthTooSmall
Field Type : CounterBasedGauge64
Field Status : current
Description : Packets too small
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.6

Field Name : versionMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : BFD version mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.5

Field Name : multihopMismatch
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Multihop session or packet mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.4

Field Name : sessionNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : Session not found
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.3

Field Name : udpChecksumError
Field Type : CounterBasedGauge64
Field Status : current
Description : UDP packet checksum errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.2

Field Name : ipChecksumError
Field Type : CounterBasedGauge64
Field Status : current
Description : IP packet checksum errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.53.1.1

Field Name : outmcastpkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing multicast packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.22

Field Name : inmcastpkts
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming multicast packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.21

Field Name : fragcreates
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing fragmented packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.20

Field Name : fragfails
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets fragmentation failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.19

Field Name : fragoks
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets fragmented
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.18

Field Name : reasmfails
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming reassembly requests failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.17

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : reasmoks
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming reassembled packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.16

Field Name : reasmreqds
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming reassembly requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.15

Field Name : reasmtimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Reassembly timed out packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.14

Field Name : outnoroutes
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing no route packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.13

Field Name : outdiscards
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets discarded
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.12

Field Name : outrequests
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.11

Field Name : outforwdatagrams
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing forwarded datagrams
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.10

Field Name : indelivers
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packets delivered
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.9

Field Name : indiscards
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming packets discarded
OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.8

Field Name : intruncatedpkts
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Incoming truncated packets

OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.7

Field Name : inunknownprotos

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming unknown protocol packet drops

OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.6

Field Name : inaddrerrors

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming packet address errors

OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.5

Field Name : innoroutes

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming no route packet drops

OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.4

Field Name : intoobigerrors

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming packet too big errors

OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.3

Field Name : inhdrerrors

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming packet header errors

OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.2

Field Name : inreceives

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming packets received

OID : 1.3.6.1.4.1.22610.2.4.10.39.52.1.1

Field Name : systemIpStatsOutmcastpkts

Field Type : CounterBasedGauge64

Field Status : current

Description : Outgoing multicast packets

OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.22

Field Name : systemIpStatsInmcastpkts

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming multicast packets

OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.21

Field Name : systemIpStatsFragcreate

Field Type : CounterBasedGauge64

Field Status : current

Description : Outgoing fragmented packets

OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.20

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : systemIpStatsFragfails
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets fragmentation failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.19

Field Name : systemIpStatsFragoks
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets fragmented
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.18

Field Name : systemIpStatsReasmfails
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming reassembly requests failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.17

Field Name : systemIpStatsReasmoks
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming reassembled packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.16

Field Name : systemIpStatsReasmreqds
Field Type : CounterBasedGauge64
Field Status : current
Description : Incoming reassembly requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.15

Field Name : systemIpStatsReasmtimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Reassembly timed out packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.14

Field Name : systemIpStatsOutnoroutes
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing no route packet drops
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.13

Field Name : systemIpStatsOutdiscards
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets discarded
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.12

Field Name : systemIpStatsOutrequests
Field Type : CounterBasedGauge64
Field Status : current
Description : Outgoing packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.11

Field Name : systemIpStatsOutforwdatagrams
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Outgoing forwarded datagrams

OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.10

Field Name : systemIpStatsIndelivers

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming packets delivered

OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.9

Field Name : systemIpStatsIndiscards

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming packets discarded

OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.8

Field Name : systemIpStatsIntruncatedpkts

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming truncated packets

OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.7

Field Name : systemIpStatsInunknownprotos

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming unknown protocol packet drops

OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.6

Field Name : systemIpStatsInhdrerrors

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming packet address errors

OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.5

Field Name : systemIpStatsInnoroutes

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming no route packet drops

OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.4

Field Name : systemIpStatsIntoobigerrors

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming packet too big errors

OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.3

Field Name : systemIpStatsInhdrerrors

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming packet header errors

OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.2

Field Name : systemIpStatsInreceives

Field Type : CounterBasedGauge64

Field Status : current

Description : Incoming packets received

OID : 1.3.6.1.4.1.22610.2.4.10.39.51.1.1

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : errEchoReplies
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Echo replies
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.37

Field Name : errEchoes
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Echo requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.36

Field Name : errRedirects
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Redirects
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.35

Field Name : errNa
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Neighbor advertisement
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.34

Field Name : errNs
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Neighbor solicitation
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.33

Field Name : errRa
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Router advertisement
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.32

Field Name : errRs
Field Type : CounterBasedGauge64
Field Status : current
Description : Error Router solicitation
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.31

Field Name : outMemReductions
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Group member reduction
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.30

Field Name : outMemResp
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Group member reply
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.29

Field Name : outRedirects
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Out Redirects

OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.28

Field Name : outNa

Field Type : CounterBasedGauge64

Field Status : current

Description : Out neighbor advertisement

OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.27

Field Name : outNs

Field Type : CounterBasedGauge64

Field Status : current

Description : Out neighbor solicitation

OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.26

Field Name : outRa

Field Type : CounterBasedGauge64

Field Status : current

Description : Out Router advertisement

OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.25

Field Name : outRs

Field Type : CounterBasedGauge64

Field Status : current

Description : Out Router solicitation

OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.24

Field Name : outEchoReplies

Field Type : CounterBasedGauge64

Field Status : current

Description : Out Echo replies

OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.23

Field Name : outEchoReq

Field Type : CounterBasedGauge64

Field Status : current

Description : Out Echo requests

OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.22

Field Name : outParamProb

Field Type : CounterBasedGauge64

Field Status : current

Description : Out Parameter Problem

OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.21

Field Name : outTimeExceeds

Field Type : CounterBasedGauge64

Field Status : current

Description : Out TTL Exceeds

OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.20

Field Name : outPktTooBig

Field Type : CounterBasedGauge64

Field Status : current

Description : Out Packet too big

OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.19

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : outDstUnReach
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Destination Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.18

Field Name : outMsg
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Messages
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.17

Field Name : inRedirect
Field Type : CounterBasedGauge64
Field Status : current
Description : In Redirects
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.16

Field Name : inNa
Field Type : CounterBasedGauge64
Field Status : current
Description : In neighbor advertisement
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.15

Field Name : inNs
Field Type : CounterBasedGauge64
Field Status : current
Description : In neighbor solicitation
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.14

Field Name : inRa
Field Type : CounterBasedGauge64
Field Status : current
Description : In Router advertisement
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.13

Field Name : inRouterSol
Field Type : CounterBasedGauge64
Field Status : current
Description : In Router solicitation
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.12

Field Name : inGrpMemReduction
Field Type : CounterBasedGauge64
Field Status : current
Description : In Group member reduction
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.11

Field Name : inGrpMemResp
Field Type : CounterBasedGauge64
Field Status : current
Description : In Group member reply
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.10

Field Name : inGrpMemQuery
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : In Group member query
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.9

Field Name : inExhoReply
Field Type : CounterBasedGauge64
Field Status : current
Description : In Echo replies
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.8

Field Name : inEchoes
Field Type : CounterBasedGauge64
Field Status : current
Description : In Echo requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.7

Field Name : inParamProb
Field Type : CounterBasedGauge64
Field Status : current
Description : In Parameter Problem
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.6

Field Name : inTimeExceeds
Field Type : CounterBasedGauge64
Field Status : current
Description : In TTL Exceeds
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.5

Field Name : inPktTooBig
Field Type : CounterBasedGauge64
Field Status : current
Description : In Packet too big
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.4

Field Name : inDestUnReach
Field Type : CounterBasedGauge64
Field Status : current
Description : In Destination Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.3

Field Name : inErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : In Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.2

Field Name : inMsgs
Field Type : CounterBasedGauge64
Field Status : current
Description : In messages
OID : 1.3.6.1.4.1.22610.2.4.10.39.50.1.1

Field Name : outaddrmaskreps
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Address Mask Rep
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.27

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : outaddrmask
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Address Mask
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.26

Field Name : outtimestampreps
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Time Stamp Rep
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.25

Field Name : outtimestamps
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Time Stamp
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.24

Field Name : outechoreps
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Echo Replies
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.23

Field Name : outechos
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Echo Requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.22

Field Name : outredirects
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Redirects
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.21

Field Name : outsrcquenchs
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Source Quench Error
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.20

Field Name : outparmprobs
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Parameter Problem
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.19

Field Name : outtimeexcdis
Field Type : CounterBasedGauge64
Field Status : current
Description : Out TTL Exceeds
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.18

Field Name : outdestunreaches
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Out Destination Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.17

Field Name : outerrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.16

Field Name : outmsgs
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Message
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.15

Field Name : inaddrmaskreps
Field Type : CounterBasedGauge64
Field Status : current
Description : In Address Mask Rep
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.14

Field Name : inaddrmasks
Field Type : CounterBasedGauge64
Field Status : current
Description : In Address Masks
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.13

Field Name : intimestampreps
Field Type : CounterBasedGauge64
Field Status : current
Description : In Timestamp Rep
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.12

Field Name : intimestamps
Field Type : CounterBasedGauge64
Field Status : current
Description : In Timestamp
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.11

Field Name : inechoreps
Field Type : CounterBasedGauge64
Field Status : current
Description : In Echo replies
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.10

Field Name : inechos
Field Type : CounterBasedGauge64
Field Status : current
Description : In Echo requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.9

Field Name : inredirects
Field Type : CounterBasedGauge64
Field Status : current
Description : In Redirects
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.8

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : insrcquenchs
Field Type : CounterBasedGauge64
Field Status : current
Description : In Source Quench Error
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.7

Field Name : inparmprobs
Field Type : CounterBasedGauge64
Field Status : current
Description : In Parameter Problem
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.6

Field Name : intimeexcds
Field Type : CounterBasedGauge64
Field Status : current
Description : In TTL Exceeds
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.5

Field Name : indestunreachs
Field Type : CounterBasedGauge64
Field Status : current
Description : In Destination Unreachable
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.4

Field Name : inerrors
Field Type : CounterBasedGauge64
Field Status : current
Description : In Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.3

Field Name : inmsgs
Field Type : CounterBasedGauge64
Field Status : current
Description : In Messages
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.2

Field Name : systemIcmpNum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total number
OID : 1.3.6.1.4.1.22610.2.4.10.39.49.1.1

Field Name : delayedFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Delayed free return
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.40

Field Name : invalidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.39

Field Name : sockInit
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Socket init
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.38

Field Name : synRcvRexmit
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcv SYN rexmit
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.37

Field Name : tfoDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : TFO Denied
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.36

Field Name : tfoActives
Field Type : CounterBasedGauge64
Field Status : current
Description : TFO Current Actives
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.35

Field Name : tfoConns
Field Type : CounterBasedGauge64
Field Status : current
Description : TFO Total Connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.34

Field Name : exceedmss
Field Type : CounterBasedGauge64
Field Status : current
Description : MSS exceeded pkt dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.33

Field Name : noroute
Field Type : CounterBasedGauge64
Field Status : current
Description : TCPIP out noroute
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.32

Field Name : tcpabortontimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP abort on timeout
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.31

Field Name : axRexmitSyn
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP rexmit SYN
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.30

Field Name : synRcvAck
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcv ACK on SYN
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.29

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : synRcvRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcv RST on SYN
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.28

Field Name : synRcvRstack
Field Type : CounterBasedGauge64
Field Status : current
Description : Rcv RST|ACK on SYN
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.27

Field Name : pawsactiverejected
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP paw active rej
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.26

Field Name : currclsg
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in Closing state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.25

Field Name : currlstn
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in Listen state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.24

Field Name : currlack
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in LastACK state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.23

Field Name : currclsw
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in CloseW state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.22

Field Name : currclose
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in Close state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.21

Field Name : currtimew
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP TimeW state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.20

Field Name : currfinw2
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : TCP FIN-W2 state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.19

Field Name : currfinw1
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in FIN-W1 state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.18

Field Name : currsynrcv
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in SYN-RCV state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.17

Field Name : currsysnt
Field Type : CounterBasedGauge64
Field Status : current
Description : TCP in SYN-SNT state
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.16

Field Name : currestab
Field Type : CounterBasedGauge64
Field Status : current
Description : Currently EST conns
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.15

Field Name : sendMem
Field Type : CounterBasedGauge64
Field Status : current
Description : Total tx buffer
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.14

Field Name : recvMem
Field Type : CounterBasedGauge64
Field Status : current
Description : Total rx buffer
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.13

Field Name : memAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Memory alloc
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.12

Field Name : orphanCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Orphan sockets
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.11

Field Name : sockAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Sockets allocated
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.10

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : outrsts
Field Type : CounterBasedGauge64
Field Status : current
Description : Reset Sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.9

Field Name : inerrs
Field Type : CounterBasedGauge64
Field Status : current
Description : Input errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.8

Field Name : retranssegs
Field Type : CounterBasedGauge64
Field Status : current
Description : Retransmitted packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.7

Field Name : outsegs
Field Type : CounterBasedGauge64
Field Status : current
Description : Total out TCP packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.6

Field Name : insegs
Field Type : CounterBasedGauge64
Field Status : current
Description : Total in TCP packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.5

Field Name : estabresets
Field Type : CounterBasedGauge64
Field Status : current
Description : Resets rcvd on EST conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.4

Field Name : attemptfails
Field Type : CounterBasedGauge64
Field Status : current
Description : Connect attemp failures
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.3

Field Name : passiveopens
Field Type : CounterBasedGauge64
Field Status : current
Description : Passive open conns
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.2

Field Name : activeopens
Field Type : CounterBasedGauge64
Field Status : current
Description : Active open conns
OID : 1.3.6.1.4.1.22610.2.4.10.39.48.1.1

Field Name : sslHwQInuseTot
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.39.94.1.5

Field Name : sslHwQDepthTot

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.39.94.1.4

Field Name : sslReqQInuseTot

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.39.94.1.3

Field Name : sslReqQDepthTot

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.39.94.1.2

Field Name : numSslQueues

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.39.94.1.1

Field Name : gifwConnsPerSec

Field Type : CounterBasedGauge64

Field Status : current

Description : GiFW Connections/sec

OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.13

Field Name : fwConnsPerSec

Field Type : CounterBasedGauge64

Field Status : current

Description : FW Connections/sec

OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.12

Field Name : servSslConnsPerSec

Field Type : CounterBasedGauge64

Field Status : current

Description : Server SSL Connections/sec

OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.11

Field Name : l7Bandwidth

Field Type : CounterBasedGauge64

Field Status : current

Description : L7 Bandwidth in bits/sec

OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.10

Field Name : l4Bandwidth

Field Type : CounterBasedGauge64

Field Status : current

Description : L4 Bandwidth in bits/sec

OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.9

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : totalCurrConns
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Current Established Connections
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.8

Field Name : totalNewConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Total New Connections Established/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.7

Field Name : ipNatConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : IP NAT Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.6

Field Name : sslConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : SSL Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.5

Field Name : l7TransPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Transactions/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.4

Field Name : l7ConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L7 Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.3

Field Name : l4ConnsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : L4 Connections/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.2

Field Name : totalThroughputBitsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Throughput in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.71.1.1

Field Name : wRingDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total worker core ring drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.27

Field Name : wLinkDownDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Total worker core link down drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.26

Field Name : wTxQueDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total worker core queue drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.25

Field Name : ioRingDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IO core ring drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.24

Field Name : ioTxQueDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IO core TX queue drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.23

Field Name : ioRxQueDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IO core Rx queue drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.22

Field Name : rxCsumOffloadErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Rx packet check-sum offload error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.21

Field Name : rxAlignErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet align error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.20

Field Name : rxShortLenErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet short length error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.19

Field Name : rxLongLenErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet long length error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.18

Field Name : txWindowsErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX windows error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.17

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : txHbeatErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX packet HBEAT error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.16

Field Name : txFifoErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX packet fifo error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.15

Field Name : txCarrierErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX packert carrier error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.14

Field Name : txAbortErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX packet abort error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.13

Field Name : rxMissErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet miss error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.12

Field Name : rxNoBuffErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet no buffer error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.11

Field Name : rxFrameErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet frame error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.10

Field Name : rxCrcErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet CRC error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.9

Field Name : rxOverErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet over error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.8

Field Name : rxLenErr
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Total RX packet length error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.7

Field Name : txDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.6

Field Name : txErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TX packet error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.5

Field Name : rxErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total RX packet error
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.4

Field Name : errPktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total error packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.3

Field Name : pktLnkDownDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packets link down drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.2

Field Name : pktDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packet drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.114.1.1

Field Name : qdrDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total QDR Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.38

Field Name : tunMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Tun mismatch Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.37

Field Name : runtTcpudpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Runt TCPUDP hdr Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.36

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : runtIpHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Runt IP hdr Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.35

Field Name : udpBadChksum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP bad csum Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.34

Field Name : udpPortLb
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP port LB Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.33

Field Name : udpKbFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP KB frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.32

Field Name : udpBadIpLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP bad leng Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.31

Field Name : udpShortHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total UDP short hdr Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.30

Field Name : tcpBadChksum
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP bad csum Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.29

Field Name : tcpFragHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP frag header Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.28

Field Name : tcpSynFrag
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP SYN frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.27

Field Name : tcpXmasScan
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Total TCP XMAS scan Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.26

Field Name : tcpXmasFlags
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP XMAS FLAGS Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.25

Field Name : tcpFinSin
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP SYN&FIN Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.24

Field Name : tcpNullScan
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP null scan Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.23

Field Name : tcpNullFlags
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP null flags Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.22

Field Name : tcpBadIpLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP Bad IP Len Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.21

Field Name : tcpShortHdr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP short hdr Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.20

Field Name : tcpBadUrgOffset
Field Type : CounterBasedGauge64
Field Status : current
Description : Total TCP bad urg off Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.19

Field Name : icmpPodDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total ICMP POD Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.18

Field Name : badIpChksumDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bad IP csum Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.17

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : badIpFragOffset
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bad IP frag off Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.16

Field Name : badIpPayloadLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bad IP PL len Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.15

Field Name : oversizeIpPayload
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Oversize IP PL Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.14

Field Name : noIpPayloadDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total No IP Payload Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.13

Field Name : badIpTtlDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bad IP TTL Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.12

Field Name : badIpFlagsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bad IP Flags Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.11

Field Name : badIpHdrLen
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Bad IP hdr len Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.10

Field Name : ipv4Frag
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IP frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.9

Field Name : ipv4OptDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IPv4 opt Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.8

Field Name : micFragDrop
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Total Micro frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.7

Field Name : emptyFragDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Empty frag Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.6

Field Name : landDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total LAND Attack Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.5

Field Name : fcsDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total FCS Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.4

Field Name : sizDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Size Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.3

Field Name : hrxDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total HRX Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.2

Field Name : mrxDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Total MRX Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.113.1.1

Field Name : errorOutOfSpeEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of SPE Entries Error
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.8

Field Name : errorOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of memory Error
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.7

Field Name : entriesRemovedFromSpe
Field Type : CounterBasedGauge64
Field Status : current
Description : Entries Removed from SPE
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.6

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : entriesAddedInSpe
Field Type : CounterBasedGauge64
Field Status : current
Description : Entries Added in SPE
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.5

Field Name : entriesRemovedFromSw
Field Type : CounterBasedGauge64
Field Status : current
Description : Entries Removed from SW
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.4

Field Name : entriesAddedInSw
Field Type : CounterBasedGauge64
Field Status : current
Description : Entries Added in SW
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.3

Field Name : packetHitCountInSpe
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Hit Count in SPE
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.2

Field Name : packetHitCountInSw
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet Hit Count in SW
OID : 1.3.6.1.4.1.22610.2.4.10.39.103.1.1

Field Name : placeHolder
Field Type : CounterBasedGauge64
Field Status : current
Description : place-holder
OID : 1.3.6.1.4.1.22610.2.4.10.39.87.1.1

Field Name : placeHolder
Field Type : CounterBasedGauge64
Field Status : current
Description : place-holder
OID : 1.3.6.1.4.1.22610.2.4.10.39.85.1.1

Field Name : systemGeolocListSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.84.1.1

Field Name : systemGeolocListSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.84.1.1.1

Field Name : totalActive
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.39.84.1.1.1.4

Field Name : totalGeoloc

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.39.84.1.1.1.3

Field Name : hitCount

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.39.84.1.1.1.2

Field Name : name

Field Type : String

Field Status : current

Description : Specify name of Geolocation list

OID : 1.3.6.1.4.1.22610.2.4.10.39.84.1.1.1.1

Field Name : radiusInterCardDupRedir

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS packet dropped as redirected by other blade (S0)

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.39

Field Name : radiusPacketsDroppedNotLo

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS packets dropped dest not loopback (S0)

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.38

Field Name : radiusPacketsProcessLocal

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS packets processed locally without redirection (S0)

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.37

Field Name : radiusPacketsRedirectFailDropped

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS packets dropped due to redirect failure (S0)

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.36

Field Name : radiusPacketsRedirected

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS packets redirected (S0)

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.35

Field Name : interCardMsgFailDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Inter-Card Message Fail Drop

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.34

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : haSyncNoKeyVapDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync No key dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.33

Field Name : ipAddRaceDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Entry IP Add Race Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.32

Field Name : ipMismatchDelete
Field Type : CounterBasedGauge64
Field Status : current
Description : Radius Entry IP Mismatch Delete
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.31

Field Name : acctOnDupRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Duplicate RADIUS Acct On Request
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.30

Field Name : acctOnFiltersFull
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Acct On Request Ignored(Filters Full)
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.29

Field Name : haSyncDeleteRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Delete Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.28

Field Name : haSyncCreateRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Create Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.27

Field Name : haSyncDeleteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Delete Sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.26

Field Name : haSyncCreateSent
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Record Sync Create Sent
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.25

Field Name : memFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : RADIUS Memory Freed

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.24

Field Name : memAllocFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS Memory Allocation Failed

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.23

Field Name : memAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS Memory Allocated

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.22

Field Name : smpInRml

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS SMP in RML

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.21

Field Name : smpMemFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS SMP Memory Freed

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.20

Field Name : smpMemAllocFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS SMP Memory Allocation Failed

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.19

Field Name : smpMemAllocated

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS SMP Memory Allocated

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.18

Field Name : smpDeleted

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS SMP Deleted

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.17

Field Name : smpCreated

Field Type : CounterBasedGauge64

Field Status : current

Description : RADIUS SMP Created

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.16

Field Name : invalidKey

Field Type : CounterBasedGauge64

Field Status : current

Description : Radius Request has Invalid Key Field

OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.15

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : ipv6PrefixLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Framed IPV6 Prefix Length Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.14

Field Name : haStandbyDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : HA Standby Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.13

Field Name : secretNotConfiguredDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Secret Not Configured Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.12

Field Name : radiusTableFull
Field Type : TABLE
Field Status : current
Description : RADIUS Request Dropped (Table Full)
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.11

Field Name : requestIgnored
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Ignored
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.10

Field Name : requestMalformedDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Malformed Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.9

Field Name : requestNoKeyVapDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request No Key Attribute Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.8

Field Name : requestBadSecretDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Bad Secret Dropped
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.7

Field Name : radiusRequestDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : RADIUS Request Dropped (Malformed Packet)
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.6

Field Name : radiusRequestReceived
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : RADIUS Request Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.5

Field Name : customReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Custom attribute Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.4

Field Name : imsiReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : IMSI Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.3

Field Name : imeiReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : IMEI Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.2

Field Name : msisdNReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : MSISDN Received
OID : 1.3.6.1.4.1.22610.2.4.10.39.78.1.1.1

Field Name : globalServerSslConnectionsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : global server ssl conneciton
OID : 1.3.6.1.4.1.22610.2.4.10.39.38.1.7

Field Name : globalClientSslConnectionsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : global ssl conneciton per sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.38.1.6

Field Name : globalServerSslCount
Field Type : CounterBasedGauge64
Field Status : current
Description : global server ssl count
OID : 1.3.6.1.4.1.22610.2.4.10.39.38.1.5

Field Name : globalClientSslCount
Field Type : CounterBasedGauge64
Field Status : current
Description : global ssl count
OID : 1.3.6.1.4.1.22610.2.4.10.39.38.1.4

Field Name : perPartThroughputBitsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Partition throughput in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.38.1.3

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : globalSystemIngressThroughputBitsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Global System ingress throughput in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.38.1.2

Field Name : globalSystemThroughputBitsPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Global System egress throughput in bits/sec
OID : 1.3.6.1.4.1.22610.2.4.10.39.38.1.1

Field Name : hwFwdFlowSflowCount
Field Type : CounterBasedGauge64
Field Status : current
Description : hardware forward rate drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.33

Field Name : hwFwdStatsUpdateRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward entry stats update count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.32

Field Name : hwFwdLookupFailRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward entry lookup fail count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.31

Field Name : hwFwdTcpRstAgeoutRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward tcp RST ageout received count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.30

Field Name : hwFwdTcpFinAgeoutRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward tcp FIN ageout received count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.29

Field Name : hwFwdNormalAgeoutRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward normal ageout received count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.28

Field Name : hwFwdRateDropCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward rate drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.27

Field Name : hwFwdAvailIpv6Entry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Hardware forward available ipv6 entries count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.26

Field Name : hwFwdAvailIpv4Entry
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward available ipv4 entries count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.25

Field Name : hwFwdProtocolMismatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward protocol mismatch count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.24

Field Name : hwFwdVmidDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward vmid mismatch count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.23

Field Name : hwFwdVlanidMismatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward vlanid mismatch count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.22

Field Name : hwFwdPhyportMismatchDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward phyport mismatch count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.21

Field Name : hwFwdFlowQdrFullDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow qdr full drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.20

Field Name : hwFwdFlowTxFullDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow tx full drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.19

Field Name : hwFwdFlowUnderflowCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow underflow count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.18

Field Name : hwFwdFlowUnalignCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow unalign count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.17

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : hwFwdFlowErrorCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow error count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.16

Field Name : hwFwdFlowDropCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.15

Field Name : hwFwdFlowReasonFlags
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow reason flags
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.14

Field Name : hwFwdFlowHitIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward flow hit index
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.13

Field Name : hwFwdInvalidationDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward invalid drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.12

Field Name : hwFwdAgeoutDropCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward ageout drop count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.11

Field Name : hwFwdFlowSeqMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward sequence mismatch errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.10

Field Name : hwFwdFlowTagMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward tag mismatch errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.9

Field Name : hwFwdFlowSinglebitErrors
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward singlebit Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.8

Field Name : hwFwdProgErrors
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Hardware forward programming Errors
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.7

Field Name : hwFwdProgReqs
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forward programming requests
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.6

Field Name : hwFwdModuleStatus
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware forwarder status flags
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.5

Field Name : ipv6ForwardCounts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IPv6 hardware forwarded packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.4

Field Name : ipv4ForwardCounts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total IPv4 hardware forwarded packets
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.3

Field Name : hitIndex
Field Type : CounterBasedGauge64
Field Status : current
Description : HW Fwd hit index
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.2

Field Name : hitCounts
Field Type : CounterBasedGauge64
Field Status : current
Description : Total packets hit counts
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.1.1

Field Name : tcamCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Entry Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.20

Field Name : tcamFree
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Entries Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.19

Field Name : tcamCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : TCAM Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.18

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : entryInvalidateServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Invalidate due to server down
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.17

Field Name : entryForceHwInvalidate
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Force HW Invalidate
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.16

Field Name : entryAgeOutInvalidDst
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Aged Out invalid dst
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.15

Field Name : entryAgeOutTcpRst
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Aged Out TCP RST
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.14

Field Name : entryAgeOutTcpFin
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Aged Out TCP FIN
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.13

Field Name : entryAgeOutIdle
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Aged Out Idle
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.12

Field Name : entryAgeOut
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Aged Out
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.11

Field Name : entryCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entry Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.10

Field Name : entryFreeNoSwEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entry Free no software entry
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.9

Field Name : entryFreeNoConn
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Hardware Entry Free no matched conn
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.8

Field Name : entryFreeNoHwProg
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entry Free no hw prog
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.7

Field Name : entryFreeOppEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Free due to opposite tuple entry ageout event
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.6

Field Name : entryFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.5

Field Name : entryCreateFailMaxEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.4

Field Name : entryCreateFailServerDown
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.3

Field Name : entryCreateFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.2

Field Name : entryCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Hardware Entries Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.153.2.1.1

Field Name : acosSystemTableIntegrity
Field Type : TABLE
Field Status : none
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.129

Field Name : acosSystemTableIntegrityS
Field Type : TABLE
Field Status : none
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : macTblCksumCancelM
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table checksum cancelled count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.230

Field Name : ipv6FibTblCksumCancelM
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table checksum cancelled count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.229

Field Name : ipv4FibTblCksumCancelM
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table checksum cancelled count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.228

Field Name : nd6TblCksumCancelM
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table checksum cancelled count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.227

Field Name : arpTblCksumCancelM
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table checksum cancelled count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.226

Field Name : macTblCksumMismatchB
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table checksum mismatch count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.225

Field Name : ipv6FibTblCksumMismatchB
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table checksum mismatch count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.224

Field Name : ipv4FibTblCksumMismatchB
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table checksum mismatch count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.223

Field Name : nd6TblCksumMismatchB
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table checksum mismatch count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.222

Field Name : arpTblCksumMismatchB
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : arp table checksum mismatch count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.221

Field Name : macTblCksumB
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table checksum count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.220

Field Name : ipv6FibTblCksumB
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table checksum count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.219

Field Name : ipv4FibTblCksumB
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table checksum count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.218

Field Name : nd6TblCksumB
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table checksum count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.217

Field Name : arpTblCksumB
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table checksum count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.216

Field Name : macTblCksumM
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table checksum count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.215

Field Name : ipv6FibTblCksumM
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table checksum count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.214

Field Name : ipv4FibTblCksumM
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table checksum count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.213

Field Name : nd6TblCksumM
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table checksum count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.212

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : arpTblCksumM
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table checksum count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.211

Field Name : macTblSyncB
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.210

Field Name : ipv6FibTblSyncB
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.209

Field Name : ipv4FibTblSyncB
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.208

Field Name : nd6TblSyncB
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.207

Field Name : arpTblSyncB
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync count in blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.206

Field Name : macTblSyncM
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.205

Field Name : ipv6FibTblSyncM
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.204

Field Name : ipv4FibTblSyncM
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.203

Field Name : nd6TblSyncM
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : nd6 table sync count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.202

Field Name : arpTblSyncM
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync count in master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.201

Field Name : macTblSyncEndTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.200

Field Name : ipv6FibTblSyncEndTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.199

Field Name : ipv4FibTblSyncEndTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.198

Field Name : nd6TblSyncEndTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.197

Field Name : arpTblSyncEndTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.196

Field Name : macTblSyncEndTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.195

Field Name : ipv6FibTblSyncEndTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.194

Field Name : ipv4FibTblSyncEndTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.193

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : nd6TblSyncEndTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.192

Field Name : arpTblSyncEndTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.191

Field Name : macTblSyncEntriesRemovedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries removed in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.190

Field Name : ipv6FibTblSyncEntriesRemovedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries removed in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.189

Field Name : ipv4FibTblSyncEntriesRemovedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries removed in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.188

Field Name : nd6TblSyncEntriesRemovedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries removed in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.187

Field Name : arpTblSyncEntriesRemovedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.186

Field Name : macTblSyncEntriesAddedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries added in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.185

Field Name : ipv6FibTblSyncEntriesAddedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries added in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.184

Field Name : ipv4FibTblSyncEntriesAddedB5th
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : ipv4-fib table entries added in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.183

Field Name : nd6TblSyncEntriesAddedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries added in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.182

Field Name : arpTblSyncEntriesAddedB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries added in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.181

Field Name : macTblSyncEntriesRcvdB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries received in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.180

Field Name : ipv6FibTblSyncEntriesRcvdB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries received in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.179

Field Name : ipv4FibTblSyncEntriesRcvdB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries received in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.178

Field Name : nd6TblSyncEntriesRcvdB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries received in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.177

Field Name : arpTblSyncEntriesRcvdB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries received in blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.176

Field Name : macTblSyncEntriesSentM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.175

Field Name : ipv6FibTblSyncEntriesSentM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.174

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : ipv4FibTblSyncEntriesSentM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.173

Field Name : nd6TblSyncEntriesSentM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.172

Field Name : arpTblSyncEntriesSentM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.171

Field Name : macTblSyncStartTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.170

Field Name : ipv6FibTblSyncStartTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.169

Field Name : ipv4FibTblSyncStartTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.168

Field Name : nd6TblSyncStartTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.167

Field Name : arpTblSyncStartTsB5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp blade for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.166

Field Name : macTblSyncStartTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.165

Field Name : ipv6FibTblSyncStartTsM5th
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : ipv6-fib table sync start time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.164

Field Name : ipv4FibTblSyncStartTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.163

Field Name : nd6TblSyncStartTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.162

Field Name : arpTblSyncStartTsM5th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp master for T-4 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.161

Field Name : macTblSyncEndTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.160

Field Name : ipv6FibTblSyncEndTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.159

Field Name : ipv4FibTblSyncEndTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.158

Field Name : nd6TblSyncEndTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.157

Field Name : arpTblSyncEndTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.156

Field Name : macTblSyncEndTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.155

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : ipv6FibTblSyncEndTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.154

Field Name : ipv4FibTblSyncEndTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.153

Field Name : nd6TblSyncEndTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.152

Field Name : arpTblSyncEndTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.151

Field Name : macTblSyncEntriesRemovedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries removed in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.150

Field Name : ipv6FibTblSyncEntriesRemovedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries removed in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.149

Field Name : ipv4FibTblSyncEntriesRemovedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries removed in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.148

Field Name : nd6TblSyncEntriesRemovedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries removed in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.147

Field Name : arpTblSyncEntriesRemovedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.146

Field Name : macTblSyncEntriesAddedB4th
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : mac table entries added in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.145

Field Name : ipv6FibTblSyncEntriesAddedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries added in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.144

Field Name : ipv4FibTblSyncEntriesAddedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries added in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.143

Field Name : nd6TblSyncEntriesAddedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries added in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.142

Field Name : arpTblSyncEntriesAddedB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries added in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.141

Field Name : macTblSyncEntriesRcvdB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries received in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.140

Field Name : ipv6FibTblSyncEntriesRcvdB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries received in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.139

Field Name : ipv4FibTblSyncEntriesRcvdB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries received in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.138

Field Name : nd6TblSyncEntriesRcvdB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries received in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.137

Field Name : arpTblSyncEntriesRcvdB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries received in blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.136

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : macTblSyncEntriesSentM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries sent from master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.135

Field Name : ipv6FibTblSyncEntriesSentM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries sent from master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.134

Field Name : ipv4FibTblSyncEntriesSentM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries sent from master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.133

Field Name : nd6TblSyncEntriesSentM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries sent from master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.132

Field Name : arpTblSyncEntriesSentM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries sent from master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.131

Field Name : macTblSyncStartTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.130

Field Name : ipv6FibTblSyncStartTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.129

Field Name : ipv4FibTblSyncStartTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.128

Field Name : nd6TblSyncStartTsB4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.127

Field Name : arpTblSyncStartTsB4th
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : arp table sync start time stamp blade for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.126

Field Name : macTblSyncStartTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.125

Field Name : ipv6FibTblSyncStartTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.124

Field Name : ipv4FibTblSyncStartTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.123

Field Name : nd6TblSyncStartTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.122

Field Name : arpTblSyncStartTsM4th
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp master for T-3 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.121

Field Name : macTblSyncEndTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.120

Field Name : ipv6FibTblSyncEndTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.119

Field Name : ipv4FibTblSyncEndTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.118

Field Name : nd6TblSyncEndTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.117

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : arpTblSyncEndTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.116

Field Name : macTblSyncEndTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.115

Field Name : ipv6FibTblSyncEndTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.114

Field Name : ipv4FibTblSyncEndTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.113

Field Name : nd6TblSyncEndTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.112

Field Name : arpTblSyncEndTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.111

Field Name : macTblSyncEntriesRemovedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries removed in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.110

Field Name : ipv6FibTblSyncEntriesRemovedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries removed in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.109

Field Name : ipv4FibTblSyncEntriesRemovedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries removed in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.108

Field Name : nd6TblSyncEntriesRemovedB3rd
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : nd6 table entries removed in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.107

Field Name : arpTblSyncEntriesRemovedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.106

Field Name : macTblSyncEntriesAddedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries added in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.105

Field Name : ipv6FibTblSyncEntriesAddedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries added in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.104

Field Name : ipv4FibTblSyncEntriesAddedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries added in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.103

Field Name : nd6TblSyncEntriesAddedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries added in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.102

Field Name : arpTblSyncEntriesAddedB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries added in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.101

Field Name : macTblSyncEntriesRcvdB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries received in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.100

Field Name : ipv6FibTblSyncEntriesRcvdB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries received in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.99

Field Name : ipv4FibTblSyncEntriesRcvdB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries received in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.98

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : nd6TblSyncEntriesRcvdB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries received in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.97

Field Name : arpTblSyncEntriesRcvdB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries received in blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.96

Field Name : macTblSyncEntriesSentM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries sent from master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.95

Field Name : ipv6FibTblSyncEntriesSentM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries sent from master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.94

Field Name : ipv4FibTblSyncEntriesSentM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries sent from master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.93

Field Name : nd6TblSyncEntriesSentM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries sent from master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.92

Field Name : arpTblSyncEntriesSentM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries sent from master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.91

Field Name : macTblSyncStartTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.90

Field Name : ipv6FibTblSyncStartTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.89

Field Name : ipv4FibTblSyncStartTsB3rd
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : ipv4-fib table sync start time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.88

Field Name : nd6TblSyncStartTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.87

Field Name : arpTblSyncStartTsB3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp blade for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.86

Field Name : macTblSyncStartTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.85

Field Name : ipv6FibTblSyncStartTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.84

Field Name : ipv4FibTblSyncStartTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.83

Field Name : nd6TblSyncStartTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.82

Field Name : arpTblSyncStartTsM3rd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp master for T-2 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.81

Field Name : macTblSyncEndTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.80

Field Name : ipv6FibTblSyncEndTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.79

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : ipv4FibTblSyncEndTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.78

Field Name : nd6TblSyncEndTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.77

Field Name : arpTblSyncEndTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.76

Field Name : macTblSyncEndTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.75

Field Name : ipv6FibTblSyncEndTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.74

Field Name : ipv4FibTblSyncEndTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.73

Field Name : nd6TblSyncEndTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.72

Field Name : arpTblSyncEndTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.71

Field Name : macTblSyncEntriesRemovedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries removed in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.70

Field Name : ipv6FibTblSyncEntriesRemovedB2nd
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : ipv6-fib table entries removed in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.69

Field Name : ipv4FibTblSyncEntriesRemovedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries removed in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.68

Field Name : nd6TblSyncEntriesRemovedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries removed in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.67

Field Name : arpTblSyncEntriesRemovedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.66

Field Name : macTblSyncEntriesAddedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries added in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.65

Field Name : ipv6FibTblSyncEntriesAddedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries added in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.64

Field Name : ipv4FibTblSyncEntriesAddedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries added in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.63

Field Name : nd6TblSyncEntriesAddedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries added in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.62

Field Name : arpTblSyncEntriesAddedB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries added in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.61

Field Name : macTblSyncEntriesRcvdB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries received in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.60

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : ipv6FibTblSyncEntriesRcvdB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries received in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.59

Field Name : ipv4FibTblSyncEntriesRcvdB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries received in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.58

Field Name : nd6TblSyncEntriesRcvdB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries received in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.57

Field Name : arpTblSyncEntriesRcvdB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries received in blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.56

Field Name : macTblSyncEntriesSentM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries sent from master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.55

Field Name : ipv6FibTblSyncEntriesSentM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries sent from master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.54

Field Name : ipv4FibTblSyncEntriesSentM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries sent from master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.53

Field Name : nd6TblSyncEntriesSentM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries sent from master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.52

Field Name : arpTblSyncEntriesSentM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries sent from master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.51

Field Name : macTblSyncStartTsB2nd
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : mac table sync start time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.50

Field Name : ipv6FibTblSyncStartTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.49

Field Name : ipv4FibTblSyncStartTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.48

Field Name : nd6TblSyncStartTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.47

Field Name : arpTblSyncStartTsB2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp blade for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.46

Field Name : macTblSyncStartTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.45

Field Name : ipv6FibTblSyncStartTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.44

Field Name : ipv4FibTblSyncStartTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.43

Field Name : nd6TblSyncStartTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.42

Field Name : arpTblSyncStartTsM2nd
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp master for T-1 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.41

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : macTblSyncEndTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.40

Field Name : ipv6FibTblSyncEndTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.39

Field Name : ipv4FibTblSyncEndTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.38

Field Name : nd6TblSyncEndTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.37

Field Name : arpTblSyncEndTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync end time stamp blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.36

Field Name : macTblSyncEndTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync end time stamp master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.35

Field Name : ipv6FibTblSyncEndTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync end time stamp master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.34

Field Name : ipv4FibTblSyncEndTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync end time stamp master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.33

Field Name : nd6TblSyncEndTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync end time stamp master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.32

Field Name : arpTblSyncEndTsM1st
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : arp table sync end time stamp master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.31

Field Name : macTblSyncEntriesRemovedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.30

Field Name : ipv6FibTblSyncEntriesRemovedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.29

Field Name : ipv4FibTblSyncEntriesRemovedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.28

Field Name : nd6TblSyncEntriesRemovedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.27

Field Name : arpTblSyncEntriesRemovedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries removed on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.26

Field Name : macTblSyncEntriesAddedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries added on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.25

Field Name : ipv6FibTblSyncEntriesAddedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries added on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.24

Field Name : ipv4FibTblSyncEntriesAddedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries added on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.23

Field Name : nd6TblSyncEntriesAddedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries added on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.22

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : arpTblSyncEntriesAddedB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries added on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.21

Field Name : macTblSyncEntriesRcvdB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries received on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.20

Field Name : ipv6FibTblSyncEntriesRcvdB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries received on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.19

Field Name : ipv4FibTblSyncEntriesRcvdB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries received on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.18

Field Name : nd6TblSyncEntriesRcvdB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table entries received on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.17

Field Name : arpTblSyncEntriesRcvdB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries received on blade for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.16

Field Name : macTblSyncEntriesSentM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table entries sent from master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.15

Field Name : ipv6FibTblSyncEntriesSentM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table entries sent from master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.14

Field Name : ipv4FibTblSyncEntriesSentM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table entries sent from master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.13

Field Name : nd6TblSyncEntriesSentM1st
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : nd6 table entries sent from master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.12

Field Name : arpTblSyncEntriesSentM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table entries sent from master for T0 synchronization
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.11

Field Name : macTblSyncStartTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.10

Field Name : ipv6FibTblSyncStartTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.9

Field Name : ipv4FibTblSyncStartTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.8

Field Name : nd6TblSyncStartTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.7

Field Name : arpTblSyncStartTsB1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp blade
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.6

Field Name : macTblSyncStartTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : mac table sync start time stamp master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.5

Field Name : ipv6FibTblSyncStartTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv6-fib table sync start time stamp master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.4

Field Name : ipv4FibTblSyncStartTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : ipv4-fib table sync start time stamp master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.3

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : nd6TblSyncStartTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : nd6 table sync start time stamp master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.2

Field Name : arpTblSyncStartTsM1st
Field Type : CounterBasedGauge64
Field Status : current
Description : arp table sync start time stamp master
OID : 1.3.6.1.4.1.22610.2.4.10.39.129.1.1

Field Name : usagePercentage
Field Type : CounterBasedGauge64
Field Status : current
Description : Memory Usage percentage
OID : 1.3.6.1.4.1.22610.2.4.10.39.23.1.1

Field Name : cpu100
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-100
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.101

Field Name : cpu99
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-99
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.100

Field Name : cpu98
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-98
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.99

Field Name : cpu97
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-97
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.98

Field Name : cpu96
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-96
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.97

Field Name : cpu95
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-95
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.96

Field Name : cpu94
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Data CPU-94
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.95

Field Name : cpu93
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-93
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.94

Field Name : cpu92
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-92
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.93

Field Name : cpu91
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-91
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.92

Field Name : cpu90
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-90
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.91

Field Name : cpu89
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-89
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.90

Field Name : cpu88
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-88
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.89

Field Name : cpu87
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-87
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.88

Field Name : cpu86
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-86
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.87

Field Name : cpu85
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-85
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.86

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : cpu84
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-84
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.85

Field Name : cpu83
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-83
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.84

Field Name : cpu82
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-82
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.83

Field Name : cpu81
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-81
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.82

Field Name : cpu80
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-80
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.81

Field Name : cpu79
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-79
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.80

Field Name : cpu78
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-78
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.79

Field Name : cpu77
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-77
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.78

Field Name : cpu76
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-76
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.77

Field Name : cpu75
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Data CPU-75
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.76

Field Name : cpu74
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-74
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.75

Field Name : cpu73
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-73
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.74

Field Name : cpu72
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-72
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.73

Field Name : cpu71
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-71
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.72

Field Name : cpu70
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-70
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.71

Field Name : cpu69
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-69
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.70

Field Name : cpu68
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-68
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.69

Field Name : cpu67
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-67
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.68

Field Name : cpu66
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-66
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.67

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : cpu65
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-65
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.66

Field Name : cpu64
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-64
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.65

Field Name : cpu63
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-63
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.64

Field Name : cpu62
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-62
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.63

Field Name : cpu61
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-61
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.62

Field Name : cpu60
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-60
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.61

Field Name : cpu59
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-59
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.60

Field Name : cpu58
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-58
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.59

Field Name : cpu57
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-57
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.58

Field Name : cpu56
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Data CPU-56
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.57

Field Name : cpu55
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-55
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.56

Field Name : cpu54
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-54
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.55

Field Name : cpu53
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-53
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.54

Field Name : cpu52
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-52
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.53

Field Name : cpu51
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-51
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.52

Field Name : cpu50
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-50
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.51

Field Name : cpu49
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-49
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.50

Field Name : cpu48
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-48
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.49

Field Name : cpu47
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-47
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.48

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : cpu46
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-46
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.47

Field Name : cpu45
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-45
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.46

Field Name : cpu44
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-44
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.45

Field Name : cpu43
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-43
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.44

Field Name : cpu42
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-42
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.43

Field Name : cpu41
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-41
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.42

Field Name : cpu40
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-40
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.41

Field Name : cpu39
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-39
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.40

Field Name : cpu38
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-38
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.39

Field Name : cpu37
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Data CPU-37

OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.38

Field Name : cpu36

Field Type : CounterBasedGauge64

Field Status : current

Description : Data CPU-36

OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.37

Field Name : cpu35

Field Type : CounterBasedGauge64

Field Status : current

Description : Data CPU-35

OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.36

Field Name : cpu34

Field Type : CounterBasedGauge64

Field Status : current

Description : Data CPU-34

OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.35

Field Name : cpu33

Field Type : CounterBasedGauge64

Field Status : current

Description : Data CPU-33

OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.34

Field Name : cpu32

Field Type : CounterBasedGauge64

Field Status : current

Description : Data CPU-32

OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.33

Field Name : cpu31

Field Type : CounterBasedGauge64

Field Status : current

Description : Data CPU-31

OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.32

Field Name : cpu30

Field Type : CounterBasedGauge64

Field Status : current

Description : Data CPU-30

OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.31

Field Name : cpu29

Field Type : CounterBasedGauge64

Field Status : current

Description : Data CPU-29

OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.30

Field Name : cpu28

Field Type : CounterBasedGauge64

Field Status : current

Description : Data CPU-28

OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.29

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : cpu27
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-27
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.28

Field Name : cpu26
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-26
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.27

Field Name : cpu25
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-25
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.26

Field Name : cpu24
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-24
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.25

Field Name : cpu23
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-23
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.24

Field Name : cpu22
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-22
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.23

Field Name : cpu21
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-21
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.22

Field Name : cpu20
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-20
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.21

Field Name : cpu19
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-19
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.20

Field Name : cpu18
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Data CPU-18
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.19

Field Name : cpu17
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-17
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.18

Field Name : cpu16
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-16
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.17

Field Name : cpu15
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-15
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.16

Field Name : cpu14
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-14
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.15

Field Name : cpu13
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-13
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.14

Field Name : cpu12
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-12
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.13

Field Name : cpu11
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-11
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.12

Field Name : cpu10
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-10
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.11

Field Name : cpu9
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-9
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.10

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : cpu8
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-8
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.9

Field Name : cpu7
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-7
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.8

Field Name : cpu6
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-6
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.7

Field Name : cpu5
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-5
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.6

Field Name : cpu4
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-4
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.5

Field Name : cpu3
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-3
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.4

Field Name : cpu2
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-2
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.3

Field Name : cpu1
Field Type : CounterBasedGauge64
Field Status : current
Description : Data CPU-1
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.2

Field Name : dataCpuNumber
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of data cpus
OID : 1.3.6.1.4.1.22610.2.4.10.39.6.1.1

Field Name : cpu64
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Control CPU-64
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.65

Field Name : cpu63
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-63
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.64

Field Name : cpu62
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-62
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.63

Field Name : cpu61
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-61
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.62

Field Name : cpu60
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-60
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.61

Field Name : cpu59
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-59
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.60

Field Name : cpu58
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-58
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.59

Field Name : cpu57
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-57
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.58

Field Name : cpu56
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-56
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.57

Field Name : cpu55
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-55
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.56

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : cpu54
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-54
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.55

Field Name : cpu53
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-53
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.54

Field Name : cpu52
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-52
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.53

Field Name : cpu51
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-51
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.52

Field Name : cpu50
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-50
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.51

Field Name : cpu49
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-49
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.50

Field Name : cpu48
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-48
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.49

Field Name : cpu47
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-47
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.48

Field Name : cpu46
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-46
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.47

Field Name : cpu45
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Control CPU-45
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.46

Field Name : cpu44
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-44
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.45

Field Name : cpu43
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-43
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.44

Field Name : cpu42
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-42
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.43

Field Name : cpu41
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-41
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.42

Field Name : cpu40
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-40
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.41

Field Name : cpu39
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-39
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.40

Field Name : cpu38
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-38
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.39

Field Name : cpu37
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-37
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.38

Field Name : cpu36
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-36
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.37

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : cpu35
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-35
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.36

Field Name : cpu34
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-34
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.35

Field Name : cpu33
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-33
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.34

Field Name : cpu32
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-32
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.33

Field Name : cpu31
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-31
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.32

Field Name : cpu30
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-30
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.31

Field Name : cpu29
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-29
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.30

Field Name : cpu28
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-28
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.29

Field Name : cpu27
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-27
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.28

Field Name : cpu26
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Control CPU-26
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.27

Field Name : cpu25
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-25
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.26

Field Name : cpu24
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-24
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.25

Field Name : cpu23
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-23
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.24

Field Name : cpu22
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-22
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.23

Field Name : cpu21
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-21
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.22

Field Name : cpu20
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-20
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.21

Field Name : cpu19
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-19
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.20

Field Name : cpu18
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-18
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.19

Field Name : cpu17
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-17
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.18

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : cpu16
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-16
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.17

Field Name : cpu15
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-15
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.16

Field Name : cpu14
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-14
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.15

Field Name : cpu13
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-13
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.14

Field Name : cpu12
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-12
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.13

Field Name : cpu11
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-11
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.12

Field Name : cpu10
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-10
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.11

Field Name : cpu9
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-9
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.10

Field Name : cpu8
Field Type : CounterBasedGauge64
Field Status : current
Description : Control CPU-8
OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.9

Field Name : cpu7
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Control CPU-7

OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.8

Field Name : cpu6

Field Type : CounterBasedGauge64

Field Status : current

Description : Control CPU-6

OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.7

Field Name : cpu5

Field Type : CounterBasedGauge64

Field Status : current

Description : Control CPU-5

OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.6

Field Name : cpu4

Field Type : CounterBasedGauge64

Field Status : current

Description : Control CPU-4

OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.5

Field Name : cpu3

Field Type : CounterBasedGauge64

Field Status : current

Description : Control CPU-3

OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.4

Field Name : cpu2

Field Type : CounterBasedGauge64

Field Status : current

Description : Control CPU-2

OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.3

Field Name : cpu1

Field Type : CounterBasedGauge64

Field Status : current

Description : Control CPU-1

OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.2

Field Name : ctrlCpuNumber

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of ctrl cpus

OID : 1.3.6.1.4.1.22610.2.4.10.39.5.1.1

Field Name : totalMemblocksReallocAvro

Field Type : CounterBasedGauge64

Field Status : current

Description : Total memory blocks realloc by avro lib

OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.17

Field Name : totalMemblocksFreeAvro

Field Type : CounterBasedGauge64

Field Status : current

Description : Total memory blocks freed by avro lib

OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.16

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : totalMemblocksAllocAvro
Field Type : CounterBasedGauge64
Field Status : current
Description : Total memory blocks allocated by avro lib
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.15

Field Name : totalNodesInSystem
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nodes currently allocated in system
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.14

Field Name : totalNodesUnlinkFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nodes unlink failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.13

Field Name : totalNodesFreeFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nodes free failed
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.12

Field Name : totalNodesFree
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nodes freed(sflow/history/telemetry/cpu-compute)
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.11

Field Name : totalNodesInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nodes put in rml queue
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.10

Field Name : totalNodesAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nodes allocated(sflow/history/telemetry/cpu-compute)
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.9

Field Name : totalBlocksInRmlHash
Field Type : CounterBasedGauge64
Field Status : current
Description : Total blocks in rml in hash table
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.8

Field Name : totalBlocksInHash
Field Type : CounterBasedGauge64
Field Status : current
Description : Total blocks in hash table
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.7

Field Name : totalOperFree
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Total oper blocks freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.6

Field Name : totalOperAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total oper blocks allocated
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.5

Field Name : totalCtrInSystem
Field Type : CounterBasedGauge64
Field Status : current
Description : Total counters currently allocated in system
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.4

Field Name : totalCtrFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total counters actually freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.3

Field Name : totalCtrInRml
Field Type : CounterBasedGauge64
Field Status : current
Description : Total counters put in rml queue
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.2

Field Name : totalCtrAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Total counters allocated
OID : 1.3.6.1.4.1.22610.2.4.10.39.99.1.1

Field Name : bwlDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : BW Limit Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.7

Field Name : licexpireDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : License Expire Drop
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.6

Field Name : ppslIgnoreLimit
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet-Per-Sec Limit ignored packets count
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.5

Field Name : ppslDropIng
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet-Per-Sec Limit Drop at ingress
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.4

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : ppslDropEgr
Field Type : CounterBasedGauge64
Field Status : current
Description : Packet-Per-Sec Limit Drop at egress
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.3

Field Name : outputBytesPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : Out Bytes per second
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.2

Field Name : inputBytesPerSec
Field Type : CounterBasedGauge64
Field Status : current
Description : In Bytes per second
OID : 1.3.6.1.4.1.22610.2.4.10.39.4.1.1

Field Name : currEntriesTargetGlobalDnsCache
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target Global DNS Cache
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.18

Field Name : currEntriesStats
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Stats Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.17

Field Name : currEntriesTargetService
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target Service
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.16

Field Name : currEntriesTargetRport
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target Rport
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.15

Field Name : currEntriesTargetRserver
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target Rserver
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.14

Field Name : currEntriesTargetLOC
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target LOC
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.13

Field Name : currEntriesTargetVport
Field Type : CounterBasedGauge64
Field Status : current

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Description : Current Entry Target Vport
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.12

Field Name : currEntriesTargetVserver
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target Vserver
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.11

Field Name : currEntriesTargetGlobal
Field Type : CounterBasedGauge64
Field Status : current
Description : Current Entry Target Global
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.10

Field Name : totalDirectActionEntriesFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Direct Action Entry Count Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.9

Field Name : totalDirectActionEntriesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Direct Action Entry Count Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.8

Field Name : totalDomainEntriesFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Domain Entry Count Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.7

Field Name : totalDomainEntriesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Domain Entry Count Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.6

Field Name : totalV6EntriesFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total V6 Entry Count Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.5

Field Name : totalV6EntriesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total V6 Entry Count Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.4

Field Name : totalV4EntriesFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total V4 Entry Count Freed
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.3

ACOS-SYSTEM-STATS-MIB_acosSystem_oid_list

Field Name : totalV4EntriesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total V4 Entry Count Created
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.2

Field Name : currEntries
Field Type : CounterBasedGauge64
Field Status : current
Description : Current PBSLB Entry Count
OID : 1.3.6.1.4.1.22610.2.4.10.39.137.1.1

ACOS-SYSTEM-VIEW-STATS-MIB_acosSystemView_oid_list

Field Name : usagePercentage
Field Type : CounterBasedGauge64
Field Status : current
Description : Usage percentage
OID : 1.3.6.1.4.1.22610.2.4.10.38.1.1.1

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Field Name : templateGtpPolicySTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1

Field Name : templateGtpPolicySEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1

Field Name : rlMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Message forwarded via monitor mode at rate-limit policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.124

Field Name : dropRlGtpUMaxConcurrentTunnels
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Concurrent Tunnels
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.95

Field Name : dropRlGtpUTotalPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Total packet rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.94

Field Name : dropRlGtpUTotalByte
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Total byte rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.93

Field Name : dropRlGtpUDownlinkPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Downlink packet rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.92

Field Name : dropRlGtpUDownlinkByte
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Downlink byte rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.91

Field Name : dropRlGtpUUpLinkPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Uplink packet rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.90

Field Name : dropRlGtpUUpLinkByte
Field Type : CounterBasedGauge64
Field Status : current

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Description : Rate-limit Drop: GTP-U Uplink byte rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.89

Field Name : dropRlGtpUTunnelCreate
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTP-U Tunnel Creation rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.88

Field Name : dropRlGtpV2CModifyBearerRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTPv2-C Modify Bearer Request rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.87

Field Name : dropRlGtpV1CUpdatePdpRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTPv1-C Update PDP Request rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.86

Field Name : dropRlGtpV2CCreateSessionRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTPv2-C Create Session Request rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.85

Field Name : dropRlGtpV1CCreatePdpRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: GTPv1-C Create PDP Request rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.84

Field Name : dropRlGtpV2CAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: Maximum GTPv2-C Message rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.83

Field Name : dropRlGtpV1CAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: Maximum GTPv1-C Message rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.82

Field Name : dropRlGtpV0CAgg
Field Type : CounterBasedGauge64
Field Status : current
Description : Rate-limit Drop: Maximum GTPv0-C Message rate
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.81

Field Name : gtpInGtpFltMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Message forwarded via monitor mode at GTP-IN_GTP filtering policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.123

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Field Name : msisdnFltMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Message forwarded via monitor mode at Msisdn filtering policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.122

Field Name : apnImsiFltMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Message forwarded via monitor mode at APN-IMSI filtering policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.121

Field Name : ratFltMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Message forwarded via monitor mode at rat filtering policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.120

Field Name : fltMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C Message forwarded via monitor mode at message filtering policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.119

Field Name : dropFltGtpInGtp
Field Type : CounterBasedGauge64
Field Status : current
Description : Filtering Drop: GTP in GTP Tunnel Present
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.80

Field Name : dropFltRatTypeFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Filtering Drop: RAT Type Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.79

Field Name : dropFltMsisdnFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Filtering Drop: MSISDN Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.78

Field Name : dropFltApnFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Filtering Drop: APN IMSI Filtering
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.77

Field Name : dropFltMessageFiltering
Field Type : CounterBasedGauge64
Field Status : current
Description : Filtering Drop: Message Type Not Permitted on Interface
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.76

Field Name : dropVldGtpV2CMessageSkippedApnFilteringNoApn
Field Type : CounterBasedGauge64
Field Status : current

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Description : Validation Drop: GTPv2-C APN/IMSI Filtering Dropped (No APN)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.107

Field Name : dropVldGtpV1CMessageSkippedApnFilteringNoApn
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv1-C APN/IMSI Filtering Dropped (No APN)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.106

Field Name : dropVldGtpV0CMessageSkippedApnFilteringNoApn
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv0-C APN/IMSI Filtering Dropped (No APN)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.105

Field Name : genMessageLengthMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Message forwarded via monitor mode at validation policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.118

Field Name : vldMessageMonitor
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Message forwarded via monitor mode at validation policy
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.117

Field Name : dropVldGtpV2CMessageLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Message Length Mismatch Across Layers
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.101

Field Name : dropVldGtpV1CMessageLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Message Length Mismatch Across Layers
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.100

Field Name : dropVldGtpV0CMessageLengthMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Message Length Mismatch Across Layers
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.99

Field Name : dropVldGtpV2CIELenExceedMsgLen
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C IE Length Exceeds Message Length
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.98

Field Name : dropVldGtpV1CIELenExceedMsgLen
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C IE Length Exceeds Message Length
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.97

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Field Name : dropVldGtpV0CIELenExceedMsgLen
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C IE Length Exceeds Message Length
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.96

Field Name : dropVldGtpv2SubscriberAttrMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPV2-c Subscriber Attributes Missing
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.104

Field Name : dropVldGtpv1SubscriberAttrMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPV1-c Subscriber Attributes Missing
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.103

Field Name : dropVldGtpv0SubscriberAttrMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPV0-c Subscriber Attributes Missing
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.102

Field Name : dropVldProtocolFlagUnset
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Protocol flag in Header Field not Set
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.75

Field Name : dropVldGtpInvalidApnLenDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTP-C Invalid APN Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.74

Field Name : dropVldGtpInvalidImsiLenDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTP-C Invalid IMSI Length Drop
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.73

Field Name : dropVldGtpv2SeqnumBufferFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPV2-C conn Sequence number Buffer Full
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.72

Field Name : dropVldGtpv1SeqnumBufferFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPV1-C conn Sequence number Buffer Full
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.71

Field Name : dropVldGtpv0SeqnumBufferFull
Field Type : CounterBasedGauge64
Field Status : current

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Description : Validation Drop: GTPV0-C conn Sequence number Buffer Full
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.70

Field Name : dropVldSequenceNumCorrelation
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTP-C Sequence number Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.69

Field Name : dropVldSanityFailedPiggyback
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: piggyback message anomaly failed
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.68

Field Name : dropVldInvalidPktLenPiggyback
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Piggyback message invalid packet length
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.67

Field Name : dropVldV2ReservedMessageDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv2-C Reserved Message Drop
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.66

Field Name : dropVldV1ReservedMessageDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv1-C Reserved Message Drop
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.65

Field Name : dropVldV0ReservedMessageDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv0-C Reserved Message Drop
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.64

Field Name : gtpCHandoverInProgressWithConn
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-C matching a conn with Handover In Progress
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.62

Field Name : dropVldGtpV2WrongLbiCreateBearerReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPV2-C Wrong LBI in Create Bearer Request
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.61

Field Name : dropVldGtpBearerCountExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTP Bearer count exceeded max (11)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.60

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Field Name : dropVldGtpUSpoofedSourceAddress
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTP-U IP Address Spoofed
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.59

Field Name : dropVldCountryCodeMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Country Code Mismatch in IMSI and MSISDN
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.58

Field Name : dropVldCrossLayerCorrelation
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Cross Layer IP Address Mismatch
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.57

Field Name : dropVldMessageLength
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Message Length Exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.56

Field Name : dropVldVersionNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Invalid GTP version
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.55

Field Name : dropVldReservedInformationElement
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Reserved IE Field Present
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.54

Field Name : dropVldOutOfStateIe
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Unexpected IE Present in Message
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.53

Field Name : dropVldOutOfOrderIe
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv1-C Message Out of Order IE
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.52

Field Name : dropVldMandatoryIeInGroupedIe
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Mandatory IE in Grouped IE Not Present
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.51

Field Name : dropVldMandatoryInformationElement
Field Type : CounterBasedGauge64
Field Status : current

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Description : Validation Drop: Mandatory IE Not Present
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.50

Field Name : dropVldOutOfState
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Out Of State GTP Message
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.49

Field Name : dropVldInvalidTeid
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Invalid TEID Value
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.48

Field Name : dropVldInvalidFlowLabelV0
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Invalid Flow Label in GTPv0-C Header
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.47

Field Name : dropVldTunnelIdFlag
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Tunnel Header Flag Not Set
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.46

Field Name : dropVldReservedFieldSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: Reserved Header Field Set
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.45

Field Name : dropVldGtpIeRepeatCountExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTP repeated IE count exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.44

Field Name : dropVldSanityGtpV0CMessageWithTeidZeroExpected
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv0-C PDU Notification Request with TEID
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.43

Field Name : dropVldSanityGtpV1CMessageWithTeidZeroExpected
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv1-C PDU Notification Request with TEID
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.42

Field Name : dropVldSanityGtpV2CMessageWithTeidZeroExpected
Field Type : CounterBasedGauge64
Field Status : current
Description : Validation Drop: GTPv2-C Create Session Request with TEID
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.41

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Field Name : gtpV2CPacketDummyMsisdn
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Packet With Dummy MSISDN Forwarded
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.116

Field Name : gtpV1CPacketDummyMsisdn
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Packet With Dummy MSISDN Forwarded
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.115

Field Name : gtpV0CPacketDummyMsisdn
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Packet With Dummy MSISDN Forwarded
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.114

Field Name : gtpV2CMessageSkippedMsisdnFilteringNoImsi
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C MSISDN Filtering Skipped (No MSISDN)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.113

Field Name : gtpV1CMessageSkippedMsisdnFilteringNoImsi
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C MSISDN Filtering Skipped (No MSISDN)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.112

Field Name : gtpV0CMessageSkippedMsisdnFilteringNoImsi
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C MSISDN Filtering Skipped (No MSISDN)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.111

Field Name : gtpV2CMessageSkippedApnFilteringNoImsi
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C APN/IMSI Filtering Skipped (No IMSI)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.110

Field Name : gtpV1CMessageSkippedApnFilteringNoImsi
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C APN/IMSI Filtering Skipped (No IMSI)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.109

Field Name : gtpV0CMessageSkippedApnFilteringNoImsi
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C APN/IMSI Filtering Skipped (No IMSI)
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.108

Field Name : gtpV0CPduNotificationRejectRequestForward
Field Type : CounterBasedGauge64
Field Status : current

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Description : GTPv0-C PDU Notification Reject Request Forward
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.40

Field Name : gtpV0CPduNotificationRequestForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C PDU Notification Request Forward
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.39

Field Name : gtpV1CPduNotificationRejectRequestForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C PDU Notification Reject Request Forward
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.38

Field Name : gtpV1CPduNotificationRequestForward
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C PDU Notification Request Forward
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.37

Field Name : gtpV2CLoadContrInfoExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Load Control Info IEs in message exceeded 2
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.36

Field Name : gtpV2CReservedMessageAllow
Field Type : CounterBasedGauge64
Field Status : current
Description : Permit GTPv2-C Reserved Messages
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.35

Field Name : gtpV1CReservedMessageAllow
Field Type : CounterBasedGauge64
Field Status : current
Description : Permit GTPv1-C Reserved Messages
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.34

Field Name : gtpV0CReservedMessageAllow
Field Type : CounterBasedGauge64
Field Status : current
Description : Permit GTPv0-C Reserved Messages
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.33

Field Name : gtpV2CTunnelDeletedRestart
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Deleted with Restart/failure
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.32

Field Name : gtpV1CTunnelDeletedRestart
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Deleted with Restart/failure
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.31

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Field Name : gtpV0CTunnelDeletedRestart
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Deleted with Restart/failure
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.30

Field Name : gtpPathManagementMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP Path Management Messages Received
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.29

Field Name : gtpV2CPiggybackMessage
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Piggyback Message
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.28

Field Name : gtpV2CCreateSessRespUnsuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Create Session Response Unsuccessful
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.27

Field Name : gtpV1CCreatePdpRespUnsuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Create PDP Context Response Unsuccessful
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.26

Field Name : gtpV0CCreatePdpRespUnsuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Create PDP Context Response Unsuccessful
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.25

Field Name : gtpV2CModBearerRespUnsuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Modify Bearer Response Unsuccessful
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.24

Field Name : gtpV1CUpdatePdpRespUnsuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Update PDP Context Response Unsuccessful
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.23

Field Name : gtpV0CUpdatePdpRespUnsuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Update PDP Context Response Unsuccessful
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.22

Field Name : gtpUTunnelDeleted
Field Type : CounterBasedGauge64
Field Status : current

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Description : GTP-U Tunnel Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.21

Field Name : gtpUTunnelCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTP-U Tunnel Created
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.20

Field Name : gtpV2CHalfOpenTunnelClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Half open tunnel closed
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.19

Field Name : gtpV2CTunnelDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.18

Field Name : gtpV2CTunnelClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.17

Field Name : gtpV2CTunnelHalfClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Delete Request
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.16

Field Name : gtpV2CTunnelHalfOpen
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Half open tunnel created
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.15

Field Name : gtpV2CTunnelCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv2-C Tunnel Created
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.14

Field Name : gtpV1CHalfOpenTunnelClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Half open tunnel closed
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.13

Field Name : gtpV1CTunnelDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.12

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Field Name : gtpV1CTunnelClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.11

Field Name : gtpV1CTunnelHalfClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Delete Request
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.10

Field Name : gtpV1CTunnelHalfOpen
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Half open tunnel created
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.9

Field Name : gtpV1CTunnelCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv1-C Tunnel Created
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.8

Field Name : gtpV0CHalfOpenTunnelClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Half open tunnel closed
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.7

Field Name : gtpV0CTunnelDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.6

Field Name : gtpV0CTunnelClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Marked Deleted
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.5

Field Name : gtpV0CTunnelHalfClosed
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Tunnel Delete Request
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.4

Field Name : gtpV0CTunnelHalfOpen
Field Type : CounterBasedGauge64
Field Status : current
Description : GTPv0-C Half open tunnel created
OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.3

Field Name : gtpV0CTunnelCreated
Field Type : CounterBasedGauge64
Field Status : current

ACOS-TEMPLATE-STATS-MIB_acosTemplate_oid_list

Description : GTPv0-C Tunnel Created

OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.2

Field Name : name

Field Type : String

Field Status : current

Description : Configure the GTP Policy Name

OID : 1.3.6.1.4.1.22610.2.4.10.160.6.1.1.1.1

ACOS-THREAT-INTEL-STATS-MIB_acosThreatIntel_oid_list

Field Name : threatIntelThreatListSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1

Field Name : threatIntelThreatListSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1

Field Name : totalHits
Field Type : CounterBasedGauge64
Field Status : current
Description : Total hits for threat-list
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.13

Field Name : torProxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for tor-proxy
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.12

Field Name : mobileThreats
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for mobile threats
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.11

Field Name : proxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for proxy
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.10

Field Name : phishing
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for phishing
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.9

Field Name : reputation
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for reputation
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.8

Field Name : dosAttacks
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for dos attacks
OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.7

Field Name : scanners
Field Type : CounterBasedGauge64
Field Status : current

ACOS-THREAT-INTEL-STATS-MIB_acosThreatIntel_oid_list

Description : Hits for scanners

OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.6

Field Name : botnets

Field Type : CounterBasedGauge64

Field Status : current

Description : Hits for botnets

OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.5

Field Name : webAttacks

Field Type : CounterBasedGauge64

Field Status : current

Description : Hits for web attacks

OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.4

Field Name : windowsExploits

Field Type : CounterBasedGauge64

Field Status : current

Description : Hits for windows exploits

OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.3

Field Name : spamSources

Field Type : CounterBasedGauge64

Field Status : current

Description : Hits for spam sources

OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.2

Field Name : name

Field Type : String

Field Status : current

Description : Threat category List name

OID : 1.3.6.1.4.1.22610.2.4.10.164.2.1.1.1.1

Field Name : nonMaliciousIps

Field Type : CounterBasedGauge64

Field Status : current

Description : IP's not found in database or RTU cache

OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.14

Field Name : databaseLookup

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of lookups in database

OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.13

Field Name : rtuLookup

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of lookups in RTU cache

OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.12

Field Name : torProxy

Field Type : CounterBasedGauge64

Field Status : current

Description : Hits for tor-proxy

OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.11

ACOS-THREAT-INTEL-STATS-MIB_acosThreatIntel_oid_list

Field Name : mobileThreats
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for mobile threats
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.10

Field Name : proxy
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for proxy
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.9

Field Name : phishing
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for phishing
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.8

Field Name : reputation
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for reputation
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.7

Field Name : dosAttacks
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for dos attacks
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.6

Field Name : scanners
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for scanners
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.5

Field Name : botnets
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for botnets
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.4

Field Name : webAttacks
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for web attacks
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.3

Field Name : windowsExploits
Field Type : CounterBasedGauge64
Field Status : current
Description : Hits for windows exploits
OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.2

Field Name : spamSources
Field Type : CounterBasedGauge64
Field Status : current

ACOS-THREAT-INTEL-STATS-MIB_acosThreatIntel_oid_list

Description : Hits for spam sources

OID : 1.3.6.1.4.1.22610.2.4.10.164.3.1.1

ACOS-TRAFFIC-CONTROL-STATS-MIB_acosTrafficControl_oid_list

Field Name : trafficControlRuleSetSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.197.2.1.1

Field Name : trafficControlRuleSetSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.197.2.1.1.1

Field Name : hitCount
Field Type : CounterBasedGauge64
Field Status : current
Description : Hit counts
OID : 1.3.6.1.4.1.22610.2.4.10.197.2.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Rule set name
OID : 1.3.6.1.4.1.22610.2.4.10.197.2.1.1.1.1

ACOS-VCSSCHASSIS-SLOT-SUMMARY-MIB_oid_list

Field Name : slotSummaryOperMemberListIpListTable
Field Type : TABLE
Field Status : current
Description : ChassisSummaryInformation from object 'vcs-chassis.slot-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.7

Field Name : slotSummaryOperMemberListTable
Field Type : TABLE
Field Status : current
Description : ChassisSummaryInformation from object 'vcs-chassis.slot-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6

Field Name : slotSummaryOperMemberListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slotSummaryOperMemberList entry:member-list
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1

Field Name : slotSummaryOperMemberListLocation
Field Type : String
Field Status : current
Description : location
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.7

Field Name : slotSummaryOperMemberListPort
Field Type : CounterBasedGauge64
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.6

Field Name : slotSummaryOperMemberListPriority
Field Type : CounterBasedGauge64
Field Status : current
Description : priority
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.5

Field Name : slotSummaryOperMemberListState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.4

Field Name : slotSummaryOperMemberListId
Field Type : CounterBasedGauge64
Field Status : current
Description : id
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.3

Field Name : slotSummaryOperMemberListMemberListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.2

Field Name : slotSummaryOperMemberListSlotId
Field Type : Integer32
Field Status : current

ACOS-VCSSCHASSIS-SLOT-SUMMARY-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.19.1.6.1.1

Field Name : slotSummaryOperFloatingIpv6ListTable

Field Type : TABLE

Field Status : current

Description : ChassisSummaryInformation from object 'vcs-chassis.slot-summary'

OID : 1.3.6.1.4.1.22610.2.4.8.19.1.5

Field Name : slotSummaryOperFloatingIpv6ListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The slotSummaryOperFloatingIpv6List entry:floating-ipv6-list

OID : 1.3.6.1.4.1.22610.2.4.8.19.1.5.1

Field Name : slotSummaryOperFloatingIpv6ListFloatingIpv6Prefix

Field Type : CounterBasedGauge64

Field Status : current

Description : floating-ipv6-prefix

OID : 1.3.6.1.4.1.22610.2.4.8.19.1.5.1.4

Field Name : slotSummaryOperFloatingIpv6ListFloatingIpv6

Field Type : String

Field Status : current

Description : floating-ipv6

OID : 1.3.6.1.4.1.22610.2.4.8.19.1.5.1.3

Field Name : slotSummaryOperFloatingIpv6ListFloatingIpv6ListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.19.1.5.1.2

Field Name : slotSummaryOperFloatingIpv6ListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.19.1.5.1.1

Field Name : slotSummaryOperFloatingIpv4ListTable

Field Type : TABLE

Field Status : current

Description : ChassisSummaryInformation from object 'vcs-chassis.slot-summary'

OID : 1.3.6.1.4.1.22610.2.4.8.19.1.4

Field Name : slotSummaryOperFloatingIpv4ListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The slotSummaryOperFloatingIpv4List entry:floating-ipv4-list

OID : 1.3.6.1.4.1.22610.2.4.8.19.1.4.1

Field Name : slotSummaryOperFloatingIpv4ListFloatingIpv4Mask

Field Type : String

Field Status : current

Description : floating-ipv4-mask

OID : 1.3.6.1.4.1.22610.2.4.8.19.1.4.1.4

ACOS-VCSSCHASSIS-SLOT-SUMMARY-MIB_oid_list

Field Name : slotSummaryOperFloatingIpv4ListFloatingIpv4
Field Type : String
Field Status : current
Description : floating-ipv4
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.4.1.3

Field Name : slotSummaryOperFloatingIpv4ListFloatingIpv4ListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.4.1.2

Field Name : slotSummaryOperFloatingIpv4ListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.4.1.1

Field Name : slotSummaryOperVcsHandshakeCompletedListTable
Field Type : TABLE
Field Status : current
Description : ChassisSummaryInformation from object 'vcs-chassis.slot-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.3

Field Name : slotSummaryOperVcsHandshakeCompletedListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slotSummaryOperVcsHandshakeCompletedList entry:vcs-handshake-completed-list
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.3.1

Field Name : slotSummaryOperVcsHandshakeCompletedListVcsHandshakeCompleted
Field Type : CounterBasedGauge64
Field Status : current
Description : vcs-handshake-completed
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.3.1.4

Field Name : slotSummaryOperVcsHandshakeCompletedListVcsHandshakeCompletedId
Field Type : CounterBasedGauge64
Field Status : current
Description : vcs-handshake-completed-id
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.3.1.3

Field Name : slotSummaryOperVcsHandshakeCompletedListVcsHandshakeCompletedListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.3.1.2

Field Name : slotSummaryOperVcsHandshakeCompletedListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.3.1.1

Field Name : slotSummaryOperTable
Field Type : TABLE
Field Status : current

ACOS-VCSSCHASSIS-SLOT-SUMMARY-MIB_oid_list

Description : ChassisSummaryInformation from object 'vcs-chassis.slot-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2

Field Name : slotSummaryOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slotSummaryOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1

Field Name : slotSummaryOperVmasterMaintenanceLeft
Field Type : CounterBasedGauge64
Field Status : current
Description : vmaster-maintenance-left
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.8

Field Name : slotSummaryOperVmasterMaintenanceInterval
Field Type : CounterBasedGauge64
Field Status : current
Description : vmaster-maintenance-interval
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.7

Field Name : slotSummaryOperVersion
Field Type : String
Field Status : current
Description : version
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.6

Field Name : slotSummaryOperMulticastPort
Field Type : CounterBasedGauge64
Field Status : current
Description : multicast-port
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.5

Field Name : slotSummaryOperMulticastAddr
Field Type : String
Field Status : current
Description : multicast-addr
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.4

Field Name : slotSummaryOperChassisId
Field Type : CounterBasedGauge64
Field Status : current
Description : chassis-id
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.3

Field Name : slotSummaryOperVcsEnabled
Field Type : String
Field Status : current
Description : vcs-enabled
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.2

Field Name : slotSummaryOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.2.1.1

ACOS-VCSSCHASSIS-SLOT-SUMMARY-MIB_oid_list

Field Name : slotSummaryOperMemberListIpListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The slotSummaryOperMemberListIpList entry:ip-list
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.7.1

Field Name : slotSummaryOperMemberListIpListIp
Field Type : String
Field Status : current
Description : ip
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.7.1.4

Field Name : slotSummaryOperMemberListIpListIpListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.7.1.3

Field Name : slotSummaryOperMemberListIpListMemberListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.7.1.2

Field Name : slotSummaryOperMemberListIpListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.19.1.7.1.1

ACOS-VCS-IMAGES-MIB_oid_list

Field Name : imagesOperImagesListTable
Field Type : TABLE
Field Status : current
Description : VCSImagesInformation from object 'vcs.images'
OID : 1.3.6.1.4.1.22610.2.4.8.16.1.2

Field Name : imagesOperImagesListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The imagesOperImagesList entry:images-list
OID : 1.3.6.1.4.1.22610.2.4.8.16.1.2.1

Field Name : imagesOperImagesListImagesName
Field Type : String
Field Status : current
Description : images-name
OID : 1.3.6.1.4.1.22610.2.4.8.16.1.2.1.4

Field Name : imagesOperImagesListType
Field Type : String
Field Status : current
Description : type
OID : 1.3.6.1.4.1.22610.2.4.8.16.1.2.1.3

Field Name : imagesOperImagesListImagesListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.16.1.2.1.2

Field Name : imagesOperImagesListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.16.1.2.1.1

ACOS-VCS-STAT-MIB_oid_list

Field Name : statStatsTable
Field Type : TABLE
Field Status : current
Description : ShowAVCSStatisticsInformation from object 'vcs.stat'
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1

Field Name : statStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1

Field Name : statStatsDaemonMsgHandleFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_msg_handle_failure
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.74

Field Name : statStatsDaemonMsgInval
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_msg_inval
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.73

Field Name : statStatsDaemonNSent
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_n_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.72

Field Name : statStatsDaemonNRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_n_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.71

Field Name : statStatsDaemonSentBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_sent_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.70

Field Name : statStatsDaemonRecvBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_recv_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.69

Field Name : statStatsDaemonSendErr
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_send_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.68

Field Name : statStatsDaemonRecvErr
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VCS-STAT-MIB_oid_list

Description : daemon_recv_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.67

Field Name : statStatsDaemonNElecStop
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_n_elec_stop
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.66

Field Name : statStatsDaemonNElecStart
Field Type : CounterBasedGauge64
Field Status : current
Description : daemon_n_elec_start
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.65

Field Name : statStatsSlaveCfgUpdFail
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd_fail
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.64

Field Name : statStatsSlaveCfgUpd
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.63

Field Name : statStatsSlaveKeepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_keepalive
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.62

Field Name : statStatsSlaveMsgInval
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_msg_inval
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.61

Field Name : statStatsSlaveNSent
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_n_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.60

Field Name : statStatsSlaveNRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_n_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.59

Field Name : statStatsSlaveSentBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_sent_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.58

ACOS-VCS-STAT-MIB_oid_list

Field Name : statStatsSlaveRecvBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_recv_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.57

Field Name : statStatsSlaveSendErr
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_send_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.56

Field Name : statStatsSlaveRecvErr
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_recv_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.55

Field Name : statStatsMasterCfgUpdResultErr
Field Type : CounterBasedGauge64
Field Status : current
Description : master_cfg_upd_result_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.54

Field Name : statStatsMasterCfgUpdNotifErr
Field Type : CounterBasedGauge64
Field Status : current
Description : master_cfg_upd_notif_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.53

Field Name : statStatsMasterCfgUpdRFail
Field Type : CounterBasedGauge64
Field Status : current
Description : master_cfg_upd_r_fail
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.52

Field Name : statStatsMasterCfgUpdLFail
Field Type : CounterBasedGauge64
Field Status : current
Description : master_cfg_upd_l_fail
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.51

Field Name : statStatsMasterCfgUpd
Field Type : CounterBasedGauge64
Field Status : current
Description : master_cfg_upd
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.50

Field Name : statStatsMasterSlaveStop
Field Type : CounterBasedGauge64
Field Status : current
Description : master_slave_stop
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.49

Field Name : statStatsMasterSlaveStart
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VCS-STAT-MIB_oid_list

Description : master_slave_start
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.48

Field Name : statStatsMasterSlaveStartErr
Field Type : CounterBasedGauge64
Field Status : current
Description : master_slave_start_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.47

Field Name : statStatsElectLeaveMasterTakeOver
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_leave_master_take_over
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.46

Field Name : statStatsElectLeaveMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_leave_master
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.45

Field Name : statStatsElectLeaveSlave
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_leave_slave
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.44

Field Name : statStatsElectLeaveMasterCand
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_leave_master_cand
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.43

Field Name : statStatsElectEnterMasterTakeOver
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_enter_master_take_over
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.42

Field Name : statStatsElectEnterMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_enter_master
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.41

Field Name : statStatsElectEnterSlave
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_enter_slave
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.40

Field Name : statStatsElectEnterMasterCandStat
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_enter_master_cand_stat
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.39

ACOS-VCS-STAT-MIB_oid_list

Field Name : statStatsElectMasterDupNeighbour
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_dup_neighbour
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.38

Field Name : statStatsElectMasterTooManyNeighbour
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_too_many_neighbour
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.37

Field Name : statStatsElectMasterDiscardNeighbour
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_discard_neighbour
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.36

Field Name : statStatsElectMasterDupChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_dup_challenger
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.35

Field Name : statStatsElectMasterReplaceChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_replace_challenger
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.34

Field Name : statStatsElectMasterNewChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_new_challenger
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.33

Field Name : statStatsElectMasterDiscardChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_master_discard_challenger
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.32

Field Name : statStatsElectSlaveDupNeighbour
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_slave_dup_neighbour
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.31

Field Name : statStatsElectSlaveTooManyNeighbour
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_slave_too_many_neighbour
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.30

Field Name : statStatsElectSlaveDiscardNeighbour
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VCS-STAT-MIB_oid_list

Description : elect_slave_discard_neighbour
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.29

Field Name : statStatsElectSlaveDupChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_slave_dup_challenger
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.28

Field Name : statStatsElectSlaveReplaceChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_slave_replace_challenger
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.27

Field Name : statStatsElectSlaveDiscardChallenger
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_slave_discard_challenger
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.26

Field Name : statStatsElectSlaveDupMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_slave_dup_master
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.25

Field Name : statStatsElectMcResetTimerByMto
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_mc_reset_timer_by_mto
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.24

Field Name : statStatsElectMcResetTimerByMc
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_mc_reset_timer_by_mc
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.23

Field Name : statStatsElectMcDupMasterr
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_mc_dup_masterr
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.22

Field Name : statStatsElectMcReplaceMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_mc_replace_master
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.21

Field Name : statStatsElectMcDiscardMaster
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_mc_discard_master
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.20

ACOS-VCS-STAT-MIB_oid_list

Field Name : statStatsElectPduDevIdCollision
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_dev_id_collision
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.19

Field Name : statStatsElectPduClusterMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_cluster_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.18

Field Name : statStatsElectPduHwMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_hw_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.17

Field Name : statStatsElectPduInval
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_inval
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.16

Field Name : statStatsElectPduUnknownSent
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_unknown_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.15

Field Name : statStatsElectPduMasterTakeOverSent
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_master_take_over_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.14

Field Name : statStatsElectPduSlaveSent
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_slave_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.13

Field Name : statStatsElectPduMasterCandSent
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_master_cand_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.12

Field Name : statStatsElectPduMasterSent
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_master_sent
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.11

Field Name : statStatsElectPduUnknownRecv
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VCS-STAT-MIB_oid_list

Description : elect_pdu_unknown_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.10

Field Name : statStatsElectPduMasterTakeOverRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_master_take_over_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.9

Field Name : statStatsElectPduSlaveRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_slave_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.8

Field Name : statStatsElectPduMasterCandRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_master_cand_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.7

Field Name : statStatsElectPduMasterRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_pdu_master_recv
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.6

Field Name : statStatsElectSendByte
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_send_byte
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.5

Field Name : statStatsElectRecvByte
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_recv_byte
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.4

Field Name : statStatsElectSendErr
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_send_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.3

Field Name : statStatsElectRecvErr
Field Type : CounterBasedGauge64
Field Status : current
Description : elect_recv_err
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.2

Field Name : statStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.18.1.1.1.1

ACOS-VCSVBLADES-STAT-MIB_oid_list

Field Name : statStatsTable
Field Type : TABLE
Field Status : current
Description : ShowAVCSVBladeBoxStatisticsInformation from object 'vcs-vblades.stat'
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1

Field Name : statStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1

Field Name : statStatsSlaveCfgUpdResultErr
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd_result_err
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.16

Field Name : statStatsSlaveCfgUpdNotifErr
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd_notif_err
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.15

Field Name : statStatsSlaveCfgUpdL2Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd_l2_fail
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.14

Field Name : statStatsSlaveCfgUpdRFail
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd_r_fail
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.13

Field Name : statStatsSlaveCfgUpdL1Fail
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd_l1_fail
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.12

Field Name : statStatsSlaveCfgUpd
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_cfg_upd
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.11

Field Name : statStatsSlaveKeepalive
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_keepalive
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.10

Field Name : statStatsSlaveMsgInval
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VCSVBLADES-STAT-MIB_oid_list

Description : slave_msg_inval
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.9

Field Name : statStatsSlaveNSent
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_n_sent
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.8

Field Name : statStatsSlaveNRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_n_recv
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.7

Field Name : statStatsSlaveSentBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_sent_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.6

Field Name : statStatsSlaveRecvBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_recv_bytes
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.5

Field Name : statStatsSlaveSendErr
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_send_err
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.4

Field Name : statStatsSlaveRecvErr
Field Type : CounterBasedGauge64
Field Status : current
Description : slave_recv_err
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.3

Field Name : statStatsVbladeId
Field Type : Integer32
Field Status : current
Description : vblade-id
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.2

Field Name : statStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.497.1.1.1.1

ACOS-VCS-VBLADES-STATS-MIB_acosVcsVblades_oid_list

Field Name : vcsVbladesStatSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1

Field Name : vcsVbladesStatSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1

Field Name : vcsVbladesSlaveCfgUpdResultErr

Field Type : CounterBasedGauge64

Field Status : current

Description : vBlade Configuration Update Result Errors counter of aVCS election

OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.15

Field Name : vcsVbladesSlaveCfgUpdNotifErr

Field Type : CounterBasedGauge64

Field Status : current

Description : vBlade Configuration Update Notif Errors counter of aVCS election

OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.14

Field Name : vcsVbladesSlaveCfgUpdL2Fail

Field Type : CounterBasedGauge64

Field Status : current

Description : vBlade Local Configuration Update Errors (2) counter of aVCS election

OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.13

Field Name : vcsVbladesSlaveCfgUpdRFail

Field Type : CounterBasedGauge64

Field Status : current

Description : vBlade Remote Configuration Update Errors counter of aVCS election

OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.12

Field Name : vcsVbladesSlaveCfgUpdL1Fail

Field Type : CounterBasedGauge64

Field Status : current

Description : vBlade Local Configuration Update Errors (1) counter of aVCS election

OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.11

Field Name : vcsVbladesSlaveCfgUpd

Field Type : CounterBasedGauge64

Field Status : current

Description : vBlade Received Configuration Updates counter of aVCS election

OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.10

Field Name : vcsVbladesSlaveKeepAlive

Field Type : CounterBasedGauge64

Field Status : current

Description : vBlade Received Keepalives counter of aVCS election

OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.9

Field Name : vcsVbladesSlaveMsgInval

Field Type : CounterBasedGauge64

Field Status : current

ACOS-VCS-VBLADES-STATS-MIB_acosVcsVblades_oid_list

Description : vBlade Invalid Messages counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.8

Field Name : vcsVbladesSlaveNSent
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Sent Messages counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.7

Field Name : vcsVbladesSlaveNRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Received Messages counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.6

Field Name : vcsVbladesSlaveSentBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Sent Bytes counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.5

Field Name : vcsVbladesSlaveRecvBytes
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Received Bytes counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.4

Field Name : vcsVbladesSlaveSendErr
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Send Errors counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.3

Field Name : vcsVbladesSlaveRecvErr
Field Type : CounterBasedGauge64
Field Status : current
Description : vBlade Receive Errors counter of aVCS election
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.2

Field Name : vbladeId
Field Type : INTEGER
Field Status : current
Description : vBlade-id
OID : 1.3.6.1.4.1.22610.2.4.10.144.1.1.1.1.1

ACOS-VCS-VCS-SUMMARY-MIB_oid_list

Field Name : vcsSummaryOperMemberListIpListTable
Field Type : TABLE
Field Status : current
Description : VCSSummaryInformation from object 'vcs.vcs-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.7

Field Name : vcsSummaryOperMemberListTable
Field Type : TABLE
Field Status : current
Description : VCSSummaryInformation from object 'vcs.vcs-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6

Field Name : vcsSummaryOperMemberListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vcsSummaryOperMemberList entry:member-list
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1

Field Name : vcsSummaryOperMemberListLocation
Field Type : String
Field Status : current
Description : location
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.7

Field Name : vcsSummaryOperMemberListPort
Field Type : CounterBasedGauge64
Field Status : current
Description : port
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.6

Field Name : vcsSummaryOperMemberListPriority
Field Type : CounterBasedGauge64
Field Status : current
Description : priority
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.5

Field Name : vcsSummaryOperMemberListState
Field Type : String
Field Status : current
Description : state
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.4

Field Name : vcsSummaryOperMemberListId
Field Type : CounterBasedGauge64
Field Status : current
Description : id
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.3

Field Name : vcsSummaryOperMemberListMemberListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.2

Field Name : vcsSummaryOperMemberListSlotId
Field Type : Integer32
Field Status : current

ACOS-VCS-VCS-SUMMARY-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.15.1.6.1.1

Field Name : vcsSummaryOperFloatingIpv6ListTable

Field Type : TABLE

Field Status : current

Description : VCSSummaryInformation from object 'vcs.vcs-summary'

OID : 1.3.6.1.4.1.22610.2.4.8.15.1.5

Field Name : vcsSummaryOperFloatingIpv6ListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The vcsSummaryOperFloatingIpv6List entry:floating-ipv6-list

OID : 1.3.6.1.4.1.22610.2.4.8.15.1.5.1

Field Name : vcsSummaryOperFloatingIpv6ListFloatingIpv6Prefix

Field Type : CounterBasedGauge64

Field Status : current

Description : floating-ipv6-prefix

OID : 1.3.6.1.4.1.22610.2.4.8.15.1.5.1.4

Field Name : vcsSummaryOperFloatingIpv6ListFloatingIpv6

Field Type : String

Field Status : current

Description : floating-ipv6

OID : 1.3.6.1.4.1.22610.2.4.8.15.1.5.1.3

Field Name : vcsSummaryOperFloatingIpv6ListFloatingIpv6ListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.15.1.5.1.2

Field Name : vcsSummaryOperFloatingIpv6ListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.15.1.5.1.1

Field Name : vcsSummaryOperFloatingIpv4ListTable

Field Type : TABLE

Field Status : current

Description : VCSSummaryInformation from object 'vcs.vcs-summary'

OID : 1.3.6.1.4.1.22610.2.4.8.15.1.4

Field Name : vcsSummaryOperFloatingIpv4ListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The vcsSummaryOperFloatingIpv4List entry:floating-ipv4-list

OID : 1.3.6.1.4.1.22610.2.4.8.15.1.4.1

Field Name : vcsSummaryOperFloatingIpv4ListFloatingIpv4Mask

Field Type : String

Field Status : current

Description : floating-ipv4-mask

OID : 1.3.6.1.4.1.22610.2.4.8.15.1.4.1.4

ACOS-VCS-VCS-SUMMARY-MIB_oid_list

Field Name : vcsSummaryOperFloatingIpv4ListFloatingIpv4
Field Type : String
Field Status : current
Description : floating-ipv4
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.4.1.3

Field Name : vcsSummaryOperFloatingIpv4ListFloatingIpv4ListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.4.1.2

Field Name : vcsSummaryOperFloatingIpv4ListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.4.1.1

Field Name : vcsSummaryOperVcsHandshakeCompletedListTable
Field Type : TABLE
Field Status : current
Description : VCSSummaryInformation from object 'vcs.vcs-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.3

Field Name : vcsSummaryOperVcsHandshakeCompletedListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vcsSummaryOperVcsHandshakeCompletedList entry:vcs-handshake-completed-list
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.3.1

Field Name : vcsSummaryOperVcsHandshakeCompletedListVcsHandshakeCompleted
Field Type : CounterBasedGauge64
Field Status : current
Description : vcs-handshake-completed
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.3.1.4

Field Name : vcsSummaryOperVcsHandshakeCompletedListVcsHandshakeCompletedId
Field Type : CounterBasedGauge64
Field Status : current
Description : vcs-handshake-completed-id
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.3.1.3

Field Name : vcsSummaryOperVcsHandshakeCompletedListVcsHandshakeCompletedListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.3.1.2

Field Name : vcsSummaryOperVcsHandshakeCompletedListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.3.1.1

Field Name : vcsSummaryOperTable
Field Type : TABLE
Field Status : current

ACOS-VCS-VCS-SUMMARY-MIB_oid_list

Description : VCSSummaryInformation from object 'vcs.vcs-summary'
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2

Field Name : vcsSummaryOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vcsSummaryOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1

Field Name : vcsSummaryOperVmasterMaintenanceLeft
Field Type : CounterBasedGauge64
Field Status : current
Description : vmaster-maintenance-left
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.8

Field Name : vcsSummaryOperVmasterMaintenanceInterval
Field Type : CounterBasedGauge64
Field Status : current
Description : vmaster-maintenance-interval
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.7

Field Name : vcsSummaryOperVersion
Field Type : String
Field Status : current
Description : version
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.6

Field Name : vcsSummaryOperMulticastPort
Field Type : CounterBasedGauge64
Field Status : current
Description : multicast-port
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.5

Field Name : vcsSummaryOperMulticastAddr
Field Type : String
Field Status : current
Description : multicast-addr
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.4

Field Name : vcsSummaryOperChassisId
Field Type : CounterBasedGauge64
Field Status : current
Description : chassis-id
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.3

Field Name : vcsSummaryOperVcsEnabled
Field Type : String
Field Status : current
Description : vcs-enabled
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.2

Field Name : vcsSummaryOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.2.1.1

ACOS-VCS-VCS-SUMMARY-MIB_oid_list

Field Name : vcsSummaryOperMemberListIpListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The vcsSummaryOperMemberListIpList entry:ip-list
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.7.1

Field Name : vcsSummaryOperMemberListIpListIp
Field Type : String
Field Status : current
Description : ip
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.7.1.4

Field Name : vcsSummaryOperMemberListIpListIpListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.7.1.3

Field Name : vcsSummaryOperMemberListIpListMemberListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.7.1.2

Field Name : vcsSummaryOperMemberListIpListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.15.1.7.1.1

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Field Name : hcObjAllocFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Send failed to HC, Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.17

Field Name : objMetricDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Object metric node deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.16

Field Name : objMoveToDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total object node moved to delq
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.15

Field Name : objMetricRegOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Total object Metric node alloc failed Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.14

Field Name : objMetricRegSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total object Metric node allocated
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.13

Field Name : heapMetricDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Heap metric node deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.12

Field Name : heapMoveToDelq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total heap node moved to delq
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.11

Field Name : heapMetricAllocOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Total heap metric node alloc failed Out of Memory
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.10

Field Name : heapMetricAllocSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Total heap metric node allocated
OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.9

Field Name : objDeleted
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Description : Total Object node deleted

OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.8

Field Name : heapDeleted

Field Type : CounterBasedGauge64

Field Status : current

Description : Total Heap node deleted

OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.7

Field Name : objRegOom

Field Type : CounterBasedGauge64

Field Status : current

Description : Total object node alloc failed Out of Memory

OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.6

Field Name : objRegFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Total object node alloc failed

OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.5

Field Name : objRegSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Total object node allocated

OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.4

Field Name : heapAllocOom

Field Type : CounterBasedGauge64

Field Status : current

Description : Total heap node alloc failed Out of Memory

OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.3

Field Name : heapAllocFailed

Field Type : CounterBasedGauge64

Field Status : current

Description : Total heap node alloc failed

OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.2

Field Name : heapAllocSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Total heap node allocated

OID : 1.3.6.1.4.1.22610.2.4.10.169.14.1.1

Field Name : unknownDir

Field Type : CounterBasedGauge64

Field Status : current

Description : sflow sample direction is unknown

OID : 1.3.6.1.4.1.22610.2.4.10.169.6.1.1.5

Field Name : versionNotSupported

Field Type : CounterBasedGauge64

Field Status : current

Description : sflow version not supported

OID : 1.3.6.1.4.1.22610.2.4.10.169.6.1.1.4

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Field Name : agentNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : sflow pkts from not configured agents
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.1.1.3

Field Name : fragDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total sflow fragment packets droppped
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.1.1.2

Field Name : pktsReceived
Field Type : CounterBasedGauge64
Field Status : current
Description : Total sflow pkts received
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.1.1.1

Field Name : unknownDir
Field Type : CounterBasedGauge64
Field Status : current
Description : nflow sample direction is unknown
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.11

Field Name : versionNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : nflow version not supported
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.10

Field Name : agentNotFound
Field Type : CounterBasedGauge64
Field Status : current
Description : nflow pkts from not configured agents
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.9

Field Name : fragDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nflow fragment packets dropped
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.8

Field Name : templateDropOutOfMemory
Field Type : CounterBasedGauge64
Field Status : current
Description : Total templates dropped becuase of out of memory
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.7

Field Name : templateDropExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Total templates dropped because of maximum limit
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.6

Field Name : v10TemplatesDeleted
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Description : Total v10(IPFIX) templates deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.5

Field Name : v10TemplatesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total v10(IPFIX) templates created
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.4

Field Name : v9TemplatesDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Total v9 templates deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.3

Field Name : v9TemplatesCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total v9 templates created
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.2

Field Name : pktsRcvd
Field Type : CounterBasedGauge64
Field Status : current
Description : Total nflow packets received
OID : 1.3.6.1.4.1.22610.2.4.10.169.6.2.1.1

Field Name : dequeued
Field Type : CounterBasedGauge64
Field Status : current
Description : Total jobs dequeued
OID : 1.3.6.1.4.1.22610.2.4.10.169.4.1.6

Field Name : enqueuePass
Field Type : CounterBasedGauge64
Field Status : current
Description : Total enqueue jobs passed
OID : 1.3.6.1.4.1.22610.2.4.10.169.4.1.5

Field Name : enqueueFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Total enqueue jobs failed
OID : 1.3.6.1.4.1.22610.2.4.10.169.4.1.4

Field Name : notifJobsInQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : Total notification jobs in queue
OID : 1.3.6.1.4.1.22610.2.4.10.169.4.1.3

Field Name : bufferAllocFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total reporting buffer allocation failures
OID : 1.3.6.1.4.1.22610.2.4.10.169.4.1.2

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Field Name : logTransmitFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Total log transmit failures
OID : 1.3.6.1.4.1.22610.2.4.10.169.4.1.1

Field Name : monEntityRrdFileCreateErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity rrd file create error
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.17

Field Name : monEntityRrdOutOfMemoryErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity rrd load failed, out of memory error
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.16

Field Name : monEntityRrdTuneErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity rrd tune error
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.15

Field Name : monEntityRrdLastUpdateFetchFailedErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity rrd last update fetch failed error
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.14

Field Name : monEntityRrdUpdateErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity rrd update error
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.13

Field Name : monEntityRrdFileTimestampErr
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity rrd file timestamp errors
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.12

Field Name : lwOutOfMemoryAllocFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : Light Weight Out-of-memory allocation failures
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.11

Field Name : lwMonEntityLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Light weight limit exceeded errors
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.10

Field Name : lwMonEntityDeleted
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Description : Total Light-weight entities deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.9

Field Name : lwMonEntityCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Light-weight entities created
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.8

Field Name : outOfMemoryAllocFailures
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of memory allocation failures
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.7

Field Name : haEntityPeriodicSyncSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity periodic sync messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.6

Field Name : haEntityAnomalyOffSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total anomaly off HA messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.5

Field Name : haEntityAnomalyOnSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total anomaly on HA messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.4

Field Name : haEntityDeleteSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity HA delete messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.3

Field Name : haEntityCreateSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity HA create messages sent
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.2

Field Name : monEntityLimitExceed
Field Type : CounterBasedGauge64
Field Status : current
Description : Total monitor entity limit exceed failures
OID : 1.3.6.1.4.1.22610.2.4.10.169.1.1

Field Name : failureMisc
Field Type : CounterBasedGauge64
Field Status : current
Description : Failed, other
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.81

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Field Name : smpExists
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic Capture(3 tuple based/SMP) already exists
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.80

Field Name : numPerObjectCountersDeregistered
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of per instance objects deregistered
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.79

Field Name : numPerObjectCountersRegistered
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of per instance objects registered
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.78

Field Name : numGlobalCountersDeregistered
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of global objects deregistered
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.77

Field Name : numGlobalCountersRegistered
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of global objects registered
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.76

Field Name : numDynamicCaptureConfigUnlinked
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times dynamic capture-config unlinked from template
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.75

Field Name : numCaptureConfigUnlinked
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times capture-config unlinked from template
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.74

Field Name : numDynamicCaptureConfigLinked
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times dynamic capture-config linked to template
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.73

Field Name : numCaptureConfigLinked
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times capture-config linked to template
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.72

Field Name : numDynamicCaptureConfigDeleteQ
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Description : Number of dynamic capture-config set for deletion
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.71

Field Name : numCaptureConfigDeleteQ
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of capture-config set for deletion
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.70

Field Name : numDynamicCaptureConfigDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of dynamic capture-config deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.69

Field Name : numCaptureConfigDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of capture-config deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.68

Field Name : numDynamicCaptureConfigCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of dynamic capture-config created
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.67

Field Name : numCaptureConfigCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of capture-config created
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.66

Field Name : numObjectTplDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of object templates deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.65

Field Name : numGlobalTplDeleted
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of global templates deleted
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.64

Field Name : numObjectTplCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of object templates created
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.63

Field Name : numGlobalTplCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of global templates created
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.62

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Field Name : autoPcapFileMergedFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Auto pcapng files merged failed
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.61

Field Name : autoPcapFileMerged
Field Type : CounterBasedGauge64
Field Status : current
Description : Auto pcapng files merged
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.60

Field Name : wrongCtrIncremented
Field Type : CounterBasedGauge64
Field Status : current
Description : Counter increment issue
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.59

Field Name : pktAlreadyCaptured
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip capturing, packet already captured
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.58

Field Name : nonPktPath
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip capturing, not packet processing path
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.57

Field Name : failedAsReturnCompletedSet
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip capturing, capture-config marked completed
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.56

Field Name : skipCaptureAsConnCreatedBeforeSmp
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip capturing, conn was created before the capture started
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.55

Field Name : skipAsConnAlreadyRecapture
Field Type : CounterBasedGauge64
Field Status : current
Description : Skip creating capture, conn was already captured
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.54

Field Name : connExtFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Error, Conn extension creation fail
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.53

Field Name : failedDiskFull
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Description : Error, Capture fail, Disk limit reached
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.52

Field Name : pktpcapOom
Field Type : CounterBasedGauge64
Field Status : current
Description : Error, Automated Packet capture infra OOM
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.51

Field Name : numPcapsCreateFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Error, Number of pcapng files creation failed
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.50

Field Name : numTmpPcapsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of temporary pcapng files created
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.49

Field Name : numPcapsCreated
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of pcapng files created
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.48

Field Name : numOfAnomaliesCleared
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times ctr Anomaly cleared
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.47

Field Name : numOfAnomaliesDetected
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of times ctr Anomaly detected
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.46

Field Name : pktpcaptureTriggeredByOtherFeature
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture triggered by Other feature
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.45

Field Name : pktpcaptureTriggeredByAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture triggered by counter anomaly
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.44

Field Name : pktpcaptureTriggeredByIncrement
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture triggered by counter increment
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.43

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Field Name : numConnsUntagged
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of conns untagged (done with conn limit or capture)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.42

Field Name : numConnsTaggedOtherFeatureMaxed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail, reached limit (based on Other feature, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.41

Field Name : numConnsTaggedAnomalyMaxed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail, reached limit (based on ctr anomaly, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.40

Field Name : numConnsTaggedIncrementMaxed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail, reached limit (based on ctr increment, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.39

Field Name : numConnsTaggedOtherFeatureFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail (based on Other feature, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.38

Field Name : numConnsTaggedAnomalyFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail (based on ctr anomaly, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.37

Field Name : numConnsTaggedIncrementFail
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag fail (based on ctr increment, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.36

Field Name : numConnsTaggedOtherFeature
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag success (based on Other feature, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.35

Field Name : numConnsTaggedAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn tag success (based on ctr anomaly, dynamic)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.34

Field Name : numConnsTaggedIncrement
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Description : Conn tag success (based on ctr increment, dynamic)

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.33

Field Name : numConnsTaggedGlobalOtherFeatureMaxed

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn tag fail, reached limit (based on Other feature, Global)

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.32

Field Name : numConnsTaggedGlobalAnomalyMaxed

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn tag fail, reached limit (based on ctr anomaly, Global)

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.31

Field Name : numConnsTaggedGlobalIncrementMaxed

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn tag fail, reached limit (based on ctr increment, Global)

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.30

Field Name : numConnsTaggedGlobalOtherFeatureFail

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn tag fail (based on Other feature, Global)

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.29

Field Name : numConnsTaggedGlobalAnomalyFail

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn tag fail (based on ctr anomaly, Global)

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.28

Field Name : numConnsTaggedGlobalIncrementFail

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn tag fail (based on ctr increment, Global)

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.27

Field Name : numConnsTaggedGlobalOtherFeature

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn tag success (based on Other feature, Global)

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.26

Field Name : numConnsTaggedGlobalAnomaly

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn tag success (based on ctr anomaly, Global)

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.25

Field Name : numConnsTaggedGlobalIncrement

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn tag success (based on ctr increment, Global)

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.24

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Field Name : pktcaptureFailureFileSizeRchd
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture fail, file size reached
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.23

Field Name : pktcaptureFailureWaitForBlock
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture fail, waiting to get free buffer
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.22

Field Name : pktcaptureWithConnFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture fail, Packets with tagged conn (dynamic capture)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.21

Field Name : pktcaptureWithConnFailureGlobal
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture fail, Packets with tagged conn (global capture)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.20

Field Name : pktcaptureWithConnSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture success, Packets with tagged conn (dynamic capture)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.19

Field Name : pktcaptureWithConnSuccessGlobal
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture success, Packets with tagged conn (global capture)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.18

Field Name : pktcaptureWithConnButNotTaggedFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture fail, Packets with untagged conn
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.17

Field Name : pktcaptureWithConnButNotTaggedSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture success, Packets with untagged conn
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.16

Field Name : pktcaptureWithNoConnFailure
Field Type : CounterBasedGauge64
Field Status : current
Description : Capture fail, Packets without conn
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.15

Field Name : pktcaptureWithNoConnSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Description : Capture success, Packets without conn

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.14

Field Name : concurrentCaptureFinished

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of Dynamic captures(3 tuple based) finished capturing

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.13

Field Name : globalCaptureFinished

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of times global capture finished capturing

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.12

Field Name : concurrentCaptureByCtrOtherFeatureFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : Dynamic Capture(Other feature based) freed

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.11

Field Name : concurrentCaptureByCtrAnomalyFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : Dynamic Capture(ctr anomaly based) freed

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.10

Field Name : concurrentCaptureByCtrIncrementFreed

Field Type : CounterBasedGauge64

Field Status : current

Description : Dynamic Capture(ctr increment based) freed

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.9

Field Name : concurrentCaptureLimitReached

Field Type : CounterBasedGauge64

Field Status : current

Description : Dynamic Capture configured concurrent limit reached

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.8

Field Name : concurrentCaptureCreateFailedOom

Field Type : CounterBasedGauge64

Field Status : current

Description : Error, Dynamic Capture create failed, OOM

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.7

Field Name : concurrentCaptureCreateFailedByOtherFeature

Field Type : CounterBasedGauge64

Field Status : current

Description : Error, Dynamic Capture(Other feature based) create failed

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.6

Field Name : concurrentCaptureCreateFailedByCtrAnomaly

Field Type : CounterBasedGauge64

Field Status : current

Description : Error, Dynamic Capture(ctr anomaly based) create failed

OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.5

ACOS-VISIBILITY-STATS-MIB_acosVisibility_oid_list

Field Name : concurrentCaptureCreateFailedByCtrIncrement
Field Type : CounterBasedGauge64
Field Status : current
Description : Error, Dynamic Capture(ctr increment based) create failed
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.4

Field Name : concurrentCaptureCreatedByOtherFeature
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic 3 tuple based capture created (Other feature based)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.3

Field Name : concurrentCaptureCreatedByCtrAnomaly
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic 3 tuple based capture created (ctr anomaly based)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.2

Field Name : concurrentCaptureCreatedByCtrIncrement
Field Type : CounterBasedGauge64
Field Status : current
Description : Dynamic 3 tuple based capture created (ctr increment based)
OID : 1.3.6.1.4.1.22610.2.4.10.169.18.1.1

ACOS-VRRPA-COMMON-MIB_oid_list

Field Name : commonStatsTable
Field Type : TABLE
Field Status : current
Description : HAVRRPAGlobalCommands from object 'vrrp-a.common'
OID : 1.3.6.1.4.1.22610.2.4.8.6.1.1

Field Name : commonStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The commonStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.6.1.1.1

Field Name : commonStatsVrrpCommonDummy
Field Type : CounterBasedGauge64
Field Status : current
Description : vrrp_common_dummy
OID : 1.3.6.1.4.1.22610.2.4.8.6.1.1.1.2

Field Name : commonStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.6.1.1.1.1

ACOS-VRRPA-DETAIL-MIB_oid_list

Field Name : detailOperLocalInfoListLocalEthSendListTable
Field Type : TABLE
Field Status : current
Description : displayVrrpAPeerDetailStatus from object 'vrrp-a.detail'
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7

Field Name : detailOperLocalInfoListTable
Field Type : TABLE
Field Status : current
Description : displayVrrpAPeerDetailStatus from object 'vrrp-a.detail'
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6

Field Name : detailOperLocalInfoListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The detailOperLocalInfoList entry:local_info_list
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1

Field Name : detailOperLocalInfoListVrrpPktSend
Field Type : CounterBasedGauge64
Field Status : current
Description : vrrp_pkt_send
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1.6

Field Name : detailOperLocalInfoListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1.5

Field Name : detailOperLocalInfoListSwitchToStandby
Field Type : CounterBasedGauge64
Field Status : current
Description : switch_to_standby
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1.4

Field Name : detailOperLocalInfoListSwitchToActive
Field Type : CounterBasedGauge64
Field Status : current
Description : switch_to_active
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1.3

Field Name : detailOperLocalInfoListLocalInfoListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1.2

Field Name : detailOperLocalInfoListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.6.1.1

Field Name : detailOperPeerInfoListPeerListPeerPortListTable
Field Type : TABLE
Field Status : current

ACOS-VRRPA-DETAIL-MIB_oid_list

Description : displayVrrpAPeerDetailStatus from object 'vrrp-a.detail'
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5

Field Name : detailOperPeerInfoListPeerListPeerPortListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The detailOperPeerInfoListPeerListPeerPortList entry:peer_port_list
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1

Field Name : detailOperPeerInfoListPeerListPeerPortListEthMiss
Field Type : CounterBasedGauge64
Field Status : current
Description : eth_miss
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.7

Field Name : detailOperPeerInfoListPeerListPeerPortListVrrpPktRecv
Field Type : CounterBasedGauge64
Field Status : current
Description : vrrp_pkt_recv
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.6

Field Name : detailOperPeerInfoListPeerListPeerPortListEth
Field Type : CounterBasedGauge64
Field Status : current
Description : eth
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.5

Field Name : detailOperPeerInfoListPeerListPeerPortListPeerPortListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.4

Field Name : detailOperPeerInfoListPeerListPeerPortListPeerListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.3

Field Name : detailOperPeerInfoListPeerListPeerPortListPeerInfoListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.2

Field Name : detailOperPeerInfoListPeerListPeerPortListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.5.1.1

Field Name : detailOperPeerInfoListPeerListTable
Field Type : TABLE
Field Status : current
Description : displayVrrpAPeerDetailStatus from object 'vrrp-a.detail'
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4

ACOS-VRRPA-DETAIL-MIB_oid_list

Field Name : detailOperPeerInfoListPeerListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The detailOperPeerInfoListPeerList entry:peer_list
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1

Field Name : detailOperPeerInfoListPeerListMissingHeartbeat
Field Type : CounterBasedGauge64
Field Status : current
Description : missing_heartbeat
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1.6

Field Name : detailOperPeerInfoListPeerListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1.5

Field Name : detailOperPeerInfoListPeerListPeerId
Field Type : CounterBasedGauge64
Field Status : current
Description : peer_id
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1.4

Field Name : detailOperPeerInfoListPeerListPeerListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1.3

Field Name : detailOperPeerInfoListPeerListPeerInfoListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1.2

Field Name : detailOperPeerInfoListPeerListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.4.1.1

Field Name : detailOperPeerInfoListTable
Field Type : TABLE
Field Status : current
Description : displayVrrpAPeerDetailStatus from object 'vrrp-a.detail'
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.3

Field Name : detailOperPeerInfoListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The detailOperPeerInfoList entry:peer_info_list
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.3.1

Field Name : detailOperPeerInfoListPeerPktRecv
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRPA-DETAIL-MIB_oid_list

Description : peer_pkt_recv

OID : 1.3.6.1.4.1.22610.2.4.8.14.1.3.1.4

Field Name : detailOperPeerInfoListPeerIp

Field Type : String

Field Status : current

Description : peer_ip

OID : 1.3.6.1.4.1.22610.2.4.8.14.1.3.1.3

Field Name : detailOperPeerInfoListPeerInfoListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.14.1.3.1.2

Field Name : detailOperPeerInfoListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.14.1.3.1.1

Field Name : detailOperTable

Field Type : TABLE

Field Status : current

Description : displayVrrpAPeerDetailStatus from object 'vrrp-a.detail'

OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2

Field Name : detailOperEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The detailOper entry

OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1

Field Name : detailOperL2NoRoute

Field Type : CounterBasedGauge64

Field Status : current

Description : l2_no_route

OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.13

Field Name : detailOperLockTry

Field Type : CounterBasedGauge64

Field Status : current

Description : lock_try

OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.12

Field Name : detailOperErrParid

Field Type : CounterBasedGauge64

Field Status : current

Description : err_parid

OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.11

Field Name : detailOperErrDevid

Field Type : CounterBasedGauge64

Field Status : current

Description : err_devid

OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.10

ACOS-VRRPA-DETAIL-MIB_oid_list

Field Name : detailOperErrPort
Field Type : CounterBasedGauge64
Field Status : current
Description : err_port
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.9

Field Name : detailOperIp6PoolsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ip6_pools_exceeded
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.8

Field Name : detailOperIpPoolsExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : ip_pools_exceeded
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.7

Field Name : detailOperTimeInaccurateCount
Field Type : CounterBasedGauge64
Field Status : current
Description : time_inaccurate_count
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.6

Field Name : detailOperVrrpVersionMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : vrrp_version_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.5

Field Name : detailOperSetIdMismatch
Field Type : CounterBasedGauge64
Field Status : current
Description : set_id_mismatch
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.4

Field Name : detailOperBadGroupRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : bad_group_rcv
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.3

Field Name : detailOperDupIdRcv
Field Type : CounterBasedGauge64
Field Status : current
Description : dup_id_rcv
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.2

Field Name : detailOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.2.1.1

Field Name : detailOperLocalInfoListLocalEthSendListEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRPA-DETAIL-MIB_oid_list

Description : The detailOperLocalInfoListLocalEthSendList entry:local_eth_send_list
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7.1

Field Name : detailOperLocalInfoListLocalEthSendListEthPktSend
Field Type : CounterBasedGauge64
Field Status : current
Description : eth_pkt_send
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7.1.5

Field Name : detailOperLocalInfoListLocalEthSendListEthPort
Field Type : CounterBasedGauge64
Field Status : current
Description : eth_port
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7.1.4

Field Name : detailOperLocalInfoListLocalEthSendListLocalEthSendListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7.1.3

Field Name : detailOperLocalInfoListLocalEthSendListLocalInfoListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7.1.2

Field Name : detailOperLocalInfoListLocalEthSendListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.14.1.7.1.1

ACOS-VRRPA-HOSTID-MIB_oid_list

Field Name : hostidOperHostidListTable
Field Type : TABLE
Field Status : current
Description : vrrpADeviceSerialNumberOrSoftaxUUID from object 'vrrp-a.hostid'
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.3

Field Name : hostidOperTable
Field Type : TABLE
Field Status : current
Description : vrrpADeviceSerialNumberOrSoftaxUUID from object 'vrrp-a.hostid'
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.2

Field Name : hostidOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The hostidOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.2.1

Field Name : hostidOperSetID
Field Type : CounterBasedGauge64
Field Status : current
Description : set_ID
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.2.1.2

Field Name : hostidOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.2.1.1

Field Name : hostidOperHostidListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The hostidOperHostidList entry:hostid-list
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.3.1

Field Name : hostidOperHostidListSN
Field Type : String
Field Status : current
Description : SN
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.3.1.4

Field Name : hostidOperHostidListDeviceID
Field Type : CounterBasedGauge64
Field Status : current
Description : device_ID
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.3.1.3

Field Name : hostidOperHostidListHostidListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.10.1.3.1.2

Field Name : hostidOperHostidListSlotId
Field Type : Integer32
Field Status : current

ACOS-VRRPA-HOSTID-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.10.1.3.1.1

ACOS-VRRPA-MAC-MIB_oid_list

Field Name : macOperVridMacListTable
Field Type : TABLE
Field Status : current
Description : correspondingVirtualMac from object 'vrrp-a.mac'
OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2

Field Name : macOperVridMacListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The macOperVridMacList entry:vrid-mac-list
OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2.1

Field Name : macOperVridMacListMacWithSynCookie
Field Type : String
Field Status : current
Description : mac_with_syn_cookie
OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2.1.5

Field Name : macOperVridMacListMacAddress
Field Type : String
Field Status : current
Description : mac_address
OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2.1.4

Field Name : macOperVridMacListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2.1.3

Field Name : macOperVridMacListVridMacListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2.1.2

Field Name : macOperVridMacListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.11.1.2.1.1

ACOS-VRRPA-PARTITION-VRID-ALL-STATUS-MIB_oid_list

Field Name : partitionVridAllStatusOperAllPartitionListTable
Field Type : TABLE
Field Status : current
Description : displayVridAllStatusForAllPartitions from object 'vrrp-a.partition-vrid-all-status'
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2

Field Name : partitionVridAllStatusOperAllPartitionListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The partitionVridAllStatusOperAllPartitionList entry:all-partition-list
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1

Field Name : partitionVridAllStatusOperAllPartitionListStandbyWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : standby_weight
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.11

Field Name : partitionVridAllStatusOperAllPartitionListStandbyPriority
Field Type : CounterBasedGauge64
Field Status : current
Description : standby_priority
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.10

Field Name : partitionVridAllStatusOperAllPartitionListStandbyDeviceId
Field Type : CounterBasedGauge64
Field Status : current
Description : standby_device_id
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.9

Field Name : partitionVridAllStatusOperAllPartitionListActiveWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : active_weight
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.8

Field Name : partitionVridAllStatusOperAllPartitionListActivePriority
Field Type : CounterBasedGauge64
Field Status : current
Description : active_priority
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.7

Field Name : partitionVridAllStatusOperAllPartitionListActiveDeviceId
Field Type : CounterBasedGauge64
Field Status : current
Description : active_device_id
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.6

Field Name : partitionVridAllStatusOperAllPartitionListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.5

Field Name : partitionVridAllStatusOperAllPartitionListPartitionName
Field Type : String
Field Status : current

ACOS-VRRPA-PARTITION-VRID-ALL-STATUS-MIB_oid_list

Description : partition-name

OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.4

Field Name : partitionVridAllStatusOperAllPartitionListLocalDeviceID

Field Type : CounterBasedGauge64

Field Status : current

Description : local_device_ID

OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.3

Field Name : partitionVridAllStatusOperAllPartitionListAllPartitionListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.2

Field Name : partitionVridAllStatusOperAllPartitionListSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.9.1.2.1.1

ACOS-VRRPA-PARTITION-VRID-STATUS-MIB_oid_list

Field Name : partitionVridStatusOperAllPartitionListTable
Field Type : TABLE
Field Status : current
Description : displayVrrpAStatusForAllPartitions from object 'vrrp-a.partition-vrid-status'
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2

Field Name : partitionVridStatusOperAllPartitionListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The partitionVridStatusOperAllPartitionList entry:all-partition-list
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1

Field Name : partitionVridStatusOperAllPartitionListActiveWeight
Field Type : CounterBasedGauge64
Field Status : current
Description : active_weight
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.8

Field Name : partitionVridStatusOperAllPartitionListActivePriority
Field Type : CounterBasedGauge64
Field Status : current
Description : active_priority
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.7

Field Name : partitionVridStatusOperAllPartitionListActiveDeviceId
Field Type : CounterBasedGauge64
Field Status : current
Description : active_device_id
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.6

Field Name : partitionVridStatusOperAllPartitionListVrid
Field Type : CounterBasedGauge64
Field Status : current
Description : vrid
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.5

Field Name : partitionVridStatusOperAllPartitionListPartitionName
Field Type : String
Field Status : current
Description : partition-name
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.4

Field Name : partitionVridStatusOperAllPartitionListLocalDeviceID
Field Type : CounterBasedGauge64
Field Status : current
Description : local_device_ID
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.3

Field Name : partitionVridStatusOperAllPartitionListAllPartitionListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.2

Field Name : partitionVridStatusOperAllPartitionListSlotId
Field Type : Integer32
Field Status : current

ACOS-VRRPA-PARTITION-VRID-STATUS-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.8.1.2.1.1

ACOS-VRRPA-SETID-MONITOR-MIB_oid_list

Field Name : setidMonitorOperSetidListIpListTable
Field Type : TABLE
Field Status : current
Description : monitorSetIdThatHasBeenUsed from object 'vrrp-a.setid-monitor'
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4

Field Name : setidMonitorOperSetidListTable
Field Type : TABLE
Field Status : current
Description : monitorSetIdThatHasBeenUsed from object 'vrrp-a.setid-monitor'
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.3

Field Name : setidMonitorOperSetidListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The setidMonitorOperSetidList entry:setid-list
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.3.1

Field Name : setidMonitorOperSetidListLif
Field Type : CounterBasedGauge64
Field Status : current
Description : lif
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.3.1.4

Field Name : setidMonitorOperSetidListInterfaceType
Field Type : String
Field Status : current
Description : interface_type
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.3.1.3

Field Name : setidMonitorOperSetidListSetidListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.3.1.2

Field Name : setidMonitorOperSetidListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.3.1.1

Field Name : setidMonitorOperTable
Field Type : TABLE
Field Status : current
Description : monitorSetIdThatHasBeenUsed from object 'vrrp-a.setid-monitor'
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.2

Field Name : setidMonitorOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The setidMonitorOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.2.1

Field Name : setidMonitorOperSetId
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRPA-SETID-MONITOR-MIB_oid_list

Description : set-id

OID : 1.3.6.1.4.1.22610.2.4.8.13.1.2.1.2

Field Name : setidMonitorOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.13.1.2.1.1

Field Name : setidMonitorOperSetidListIpListEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The setidMonitorOperSetidListIpList entry:ip-list

OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1

Field Name : setidMonitorOperSetidListIpListLastObserved

Field Type : CounterBasedGauge64

Field Status : current

Description : last_observed

OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.9

Field Name : setidMonitorOperSetidListIpListVlan

Field Type : CounterBasedGauge64

Field Status : current

Description : vlan

OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.8

Field Name : setidMonitorOperSetidListIpListMac

Field Type : String

Field Status : current

Description : mac

OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.7

Field Name : setidMonitorOperSetidListIpListIpv6

Field Type : String

Field Status : current

Description : ipv6

OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.6

Field Name : setidMonitorOperSetidListIpListIpAddress

Field Type : String

Field Status : current

Description : ipaddress

OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.5

Field Name : setidMonitorOperSetidListIpListDeviceId

Field Type : CounterBasedGauge64

Field Status : current

Description : device-id

OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.4

Field Name : setidMonitorOperSetidListIpListIpListListId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.3

ACOS-VRRPA-SETID-MONITOR-MIB_oid_list

Field Name : setidMonitorOperSetidListIpListSetidListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.2

Field Name : setidMonitorOperSetidListIpListSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.13.1.4.1.1

ACOS-VRRPA-STATE-CPU-MIB_oid_list

Field Name : stateCpuOperCpuUsageTable
Field Type : TABLE
Field Status : current
Description : HAVRRPAGlobalCommands from object 'vrrp-a.state-cpu'
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2

Field Name : stateCpuOperCpuUsageEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The stateCpuOperCpuUsage entry:cpu-usage
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1

Field Name : stateCpuOperCpuUsageMinQueryMsgPerPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Min-Query-Msg-Per-Packet
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.7

Field Name : stateCpuOperCpuUsageMaxQueryMsgPerPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Max-Query-Msg-Per-Packet
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.6

Field Name : stateCpuOperCpuUsageMinSyncMsgPerPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Min-Sync-Msg-Per-Packet
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.5

Field Name : stateCpuOperCpuUsageMaxSyncMsgPerPacket
Field Type : CounterBasedGauge64
Field Status : current
Description : Max-Sync-Msg-Per-Packet
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.4

Field Name : stateCpuOperCpuUsageCpuId
Field Type : CounterBasedGauge64
Field Status : current
Description : cpu-id
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.3

Field Name : stateCpuOperCpuUsageCpuUsageListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.2

Field Name : stateCpuOperCpuUsageSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.5.1.2.1.1

ACOS-VRRPA-STATE-MIB_oid_list

Field Name : stateStatsTable
Field Type : TABLE
Field Status : current
Description : HAVRRPAGlobalCommands from object 'vrrp-a.state'
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1

Field Name : stateStatsEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The stateStats stats entry
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1

Field Name : stateStatsQueryPktRxError
Field Type : CounterBasedGauge64
Field Status : current
Description : query_pkt_rx_error
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.180

Field Name : stateStatsSyncTxUpdateMiscCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_update_misc_counter_act
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.179

Field Name : stateStatsSyncTxUpdateAgeCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_update_age_counter_act
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.178

Field Name : stateStatsSyncTxDelCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_del_counter_act
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.177

Field Name : stateStatsSyncTxCreateCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_create_counter_act
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.176

Field Name : stateStatsSyncTxUpdateMiscBearer
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_update_misc_bearer
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.175

Field Name : stateStatsSyncPktRcvDcMsgDir
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_rcv_dc_msg_dir
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.174

Field Name : stateStatsSyncRxDropSyncPackets
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRPA-STATE-MIB_oid_list

Description : sync_rx_drop_sync_packets

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.173

Field Name : stateStatsSyncRxDcmsgCounterInterPu

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_rx_dcmsg_counter_inter_pu

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.172

Field Name : stateStatsDnsCacheSyncRxErrorCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_cache_sync_rx_error_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.171

Field Name : stateStatsDnsCacheSyncTxErrorCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_cache_sync_tx_error_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.170

Field Name : stateStatsDnsCacheSyncRxFragCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_cache_sync_rx_frag_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.169

Field Name : stateStatsDnsCacheSyncTxFragCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_cache_sync_tx_frag_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.168

Field Name : stateStatsDnsCacheSyncRxDelCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_cache_sync_rx_del_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.167

Field Name : stateStatsDnsCacheSyncTxDelCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_cache_sync_tx_del_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.166

Field Name : stateStatsDnsCacheSyncRxCreateCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_cache_sync_rx_create_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.165

Field Name : stateStatsDnsCacheSyncTxCreateCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : dns_cache_sync_tx_create_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.164

ACOS-VRRPA-STATE-MIB_oid_list

Field Name : stateStatsSyncRxFwSetDscpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_fw_set_dscp_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.163

Field Name : stateStatsSyncTxFwSetDscpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_fw_set_dscp_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.162

Field Name : stateStatsSyncRxExtFwLimitEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_limit_entry
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.161

Field Name : stateStatsSyncTxAflexTableEntryNotEligibleCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_not_eligible_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.160

Field Name : stateStatsSyncTxAflexTableEntryErrorCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_error_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.159

Field Name : stateStatsSyncRxAflexTableEntryFastsyncCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_fastsync_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.158

Field Name : stateStatsSyncTxAflexTableEntryFastsyncCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_fastsync_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.157

Field Name : stateStatsSyncRxAflexTableEntryTimeoutCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_timeout_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.156

Field Name : stateStatsSyncTxAflexTableEntryTimeoutCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_timeout_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.155

Field Name : stateStatsSyncRxAflexTableEntrySetCounter
Field Type : TABLE
Field Status : current

ACOS-VRRPA-STATE-MIB_oid_list

Description : sync_rx_aflex_table_entry_set_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.154

Field Name : stateStatsSyncTxAflexTableEntrySetCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_set_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.153

Field Name : stateStatsSyncRxAflexTableEntryReplaceCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_replace_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.152

Field Name : stateStatsSyncTxAflexTableEntryReplaceCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_replace_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.151

Field Name : stateStatsSyncRxAflexTableEntryLifetimeCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_lifetime_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.150

Field Name : stateStatsSyncTxAflexTableEntryLifetimeCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_lifetime_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.149

Field Name : stateStatsSyncRxAflexTableEntryLookupCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_lookup_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.148

Field Name : stateStatsSyncTxAflexTableEntryLookupCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_lookup_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.147

Field Name : stateStatsSyncRxAflexTableEntryIncrCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_incr_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.146

Field Name : stateStatsSyncTxAflexTableEntryIncrCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_incr_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.145

ACOS-VRRPA-STATE-MIB_oid_list

Field Name : stateStatsSyncRxAflexTableEntryDeleteCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_delete_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.144

Field Name : stateStatsSyncTxAflexTableEntryDeleteCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_delete_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.143

Field Name : stateStatsSyncRxAflexTableEntryAppendCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_append_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.142

Field Name : stateStatsSyncTxAflexTableEntryAppendCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_append_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.141

Field Name : stateStatsSyncRxAflexTableEntryAddCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_aflex_table_entry_add_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.140

Field Name : stateStatsSyncTxAflexTableEntryAddCounter
Field Type : TABLE
Field Status : current
Description : sync_tx_aflex_table_entry_add_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.139

Field Name : stateStatsSyncRxExtFwSoShadowExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_so_shadow_ext_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.138

Field Name : stateStatsSyncTxSmpClearCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_smp_clear_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.137

Field Name : stateStatsSyncRxSmpClearCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_smp_clear_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.136

Field Name : stateStatsSyncTxSmpUpdateCounter
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRPA-STATE-MIB_oid_list

Description : sync_tx_smp_update_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.135

Field Name : stateStatsSyncTxSmpDeleteCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_smp_delete_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.134

Field Name : stateStatsSyncTxSmpCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_smp_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.133

Field Name : stateStatsSyncRxSmpUpdateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_smp_update_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.132

Field Name : stateStatsSyncRxSmpDeleteCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_smp_delete_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.131

Field Name : stateStatsSyncRxSmpCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_smp_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.130

Field Name : stateStatsSyncRxExtFwGtpEchoExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_gtp_echo_ext_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.129

Field Name : stateStatsSyncRxUnreachedPktCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_unreached_pkt_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.128

Field Name : stateStatsSyncRxOutOfOrderPktCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_out_of_order_pkt_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.127

Field Name : stateStatsQueryRxInvalidMsgDirCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_invalid_msg_dir_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.126

ACOS-VRRPA-STATE-MIB_oid_list

Field Name : stateStatsQueryRxInvalidSyncVersionCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_invalid_sync_version_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.125

Field Name : stateStatsQueryRxInvalidHaGroupCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_invalid_ha_group_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.124

Field Name : stateStatsQueryRxInvalidPartitionCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_invalid_partition_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.123

Field Name : stateStatsSyncRxAflegFragCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_afleg_frag_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.122

Field Name : stateStatsSyncRxAflegDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_afleg_del_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.121

Field Name : stateStatsSyncRxAflegCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_afleg_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.120

Field Name : stateStatsSyncRxAflegUpdateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_afleg_update_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.119

Field Name : stateStatsSyncRxTableEntryDelCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_table_entry_del_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.118

Field Name : stateStatsSyncRxTableEntryCreateCounter
Field Type : TABLE
Field Status : current
Description : sync_rx_table_entry_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.117

Field Name : stateStatsSyncRxTableEntryUpdateCounter
Field Type : TABLE
Field Status : current

ACOS-VRRPA-STATE-MIB_oid_list

Description : sync_rx_table_entry_update_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.116

Field Name : stateStatsSyncRxByInactivePeerCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_by_inactive_peer_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.115

Field Name : stateStatsSyncRxNoVgrpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_no_vgrp_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.114

Field Name : stateStatsSyncRxBadProtocolCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_bad_protocol_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.113

Field Name : stateStatsSyncPktFailedBuffCopyCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_failed_buff_copy_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.112

Field Name : stateStatsQueryPktNoReceivingIpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_pkt_no_receiving_ip_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.111

Field Name : stateStatsSyncPktNoReceivingVgrpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_no_receiving_vgrp_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.110

Field Name : stateStatsSyncPktNoSendingVgrpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_no_sending_vgrp_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.109

Field Name : stateStatsSyncPktEmptyBuffCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_empty_buff_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.108

Field Name : stateStatsSyncRxInvalidSyncPacketCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_invalid_sync_packet_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.107

ACOS-VRRPA-STATE-MIB_oid_list

Field Name : stateStatsSyncRxDdosDropCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ddos_drop_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.106

Field Name : stateStatsSyncRxExtFwGtpLogExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_gtp_log_ext_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.105

Field Name : stateStatsSyncRxExtFwGtpExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_gtp_ext_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.104

Field Name : stateStatsSyncRxExtFwGtpUInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_gtp_u_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.103

Field Name : stateStatsSyncRxExtFwGtpLogInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_gtp_log_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.102

Field Name : stateStatsSyncRxMonEntity
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_mon_entity
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.101

Field Name : stateStatsSyncTxMonEntity
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_mon_entity
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.100

Field Name : stateStatsSyncRxExtFwApps
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_fw_apps
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.99

Field Name : stateStatsSyncRxNotExpectSyncPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_not_expect_sync_pkt
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.98

Field Name : stateStatsSyncRxExtFwGtpInfo
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRPA-STATE-MIB_oid_list

Description : sync_rx_ext_fw_gtp_info

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.97

Field Name : stateStatsSyncRxExtDcfwRuleIdleTimeout

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_rx_ext_dcfw_rule_idle_timeout

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.96

Field Name : stateStatsSyncRxExtFwHttpLogging

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_rx_ext_fw_http_logging

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.95

Field Name : stateStatsSyncRxZoneFailureCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_rx_zone_failure_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.94

Field Name : stateStatsSyncTxEstabCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_tx_estab_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.93

Field Name : stateStatsSyncRxEstabCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_rx_estab_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.92

Field Name : stateStatsSyncRxExtDcfwLog

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_rx_ext_dcfw_log

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.91

Field Name : stateStatsSyncRxExtDcfwRuleId

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_rx_ext_dcfw_rule_id

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.90

Field Name : stateStatsSyncRxExtNatAlgTcpInfo

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_rx_ext_nat_alg_tcp_info

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.89

Field Name : stateStatsSyncRxUpdateSctpConnAddr

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_rx_update_sctp_conn_addr

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.88

ACOS-VRRPA-STATE-MIB_oid_list

Field Name : stateStatsSyncTxUpdateSctpConnAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_update_sctp_conn_addr
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.87

Field Name : stateStatsSyncErrLsnFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_err_lsn_fullcone
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.86

Field Name : stateStatsSyncRxLsnFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_lsn_fullcone
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.85

Field Name : stateStatsSyncTxLsnFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_lsn_fullcone
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.84

Field Name : stateStatsSyncRxExtNatMac
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_nat_mac
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.83

Field Name : stateStatsSyncRxExtH323Alg
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_h323_alg
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.82

Field Name : stateStatsSyncRxExtSipAlg
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_sip_alg
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.81

Field Name : stateStatsSyncRxExtLsnAcIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_lsn_ac_idle_timeout
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.80

Field Name : stateStatsSyncRxExtLsnAc1
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_lsn_ac1
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.79

Field Name : stateStatsSyncRxFtpControl
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRPA-STATE-MIB_oid_list

Description : sync_rx_ftp_control
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.78

Field Name : stateStatsSyncRxSeqDeltas
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_seq_deltas
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.77

Field Name : stateStatsSyncRxReserveHa
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_reserve_ha
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.76

Field Name : stateStatsSyncRxExtRtsp
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_rtsp
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.75

Field Name : stateStatsSyncRxExtPptp
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_pptp
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.74

Field Name : stateStatsSyncRxCreateStaticSby
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_create_static_sby
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.73

Field Name : stateStatsSyncRxSfw
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_sfw
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.72

Field Name : stateStatsSyncRxInsertTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_insert_tuple
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.71

Field Name : stateStatsSyncRxNatAllocSby
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_nat_alloc_sby
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.70

Field Name : stateStatsSyncRxNatCreateSby
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_nat_create_sby
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.69

ACOS-VRRPA-STATE-MIB_oid_list

Field Name : stateStatsSyncRxLsnCreateSby
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_lsn_create_sby
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.68

Field Name : stateStatsSyncGetBuffFailedPort
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_get_buff_failed_port
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.67

Field Name : stateStatsSyncGetBuffFailedRt
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_get_buff_failed_rt
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.66

Field Name : stateStatsSyncQueryDcmsgCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_query_dcmsg_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.65

Field Name : stateStatsSyncRxApptypeNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_apptype_not_supported
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.64

Field Name : stateStatsSyncRxUnkCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_unk_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.63

Field Name : stateStatsSyncRxUpdateSeqnosCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_update_seqnos_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.62

Field Name : stateStatsSyncRxTotalInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_total_info_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.61

Field Name : stateStatsSyncRxDcmsgCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_dcmsg_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.60

Field Name : stateStatsSyncRxZeroInfoCounter
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRPA-STATE-MIB_oid_list

Description : sync_rx_zero_info_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.59

Field Name : stateStatsSyncRxTypeInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_type_invalid
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.58

Field Name : stateStatsSyncRxDelNoSuchSession
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_del_no_such_session
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.57

Field Name : stateStatsSyncRxNoSuchSgNode
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_no_such_sg_node
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.56

Field Name : stateStatsSyncRxNoSuchNatPool
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_no_such_nat_pool
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.55

Field Name : stateStatsSyncRxNoDstForVportInline
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_no_dst_for_vport_inline
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.54

Field Name : stateStatsSyncRxProtoNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_proto_not_supported
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.53

Field Name : stateStatsSyncRxConnGetFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_conn_get_failed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.52

Field Name : stateStatsSyncRxConnExists
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_conn_exists
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.51

Field Name : stateStatsSyncRxCreateExtBitCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_create_ext_bit_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.50

ACOS-VRRPA-STATE-MIB_oid_list

Field Name : stateStatsSyncRxExtBitProcessError
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_ext_bit_process_error
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.49

Field Name : stateStatsSyncRxCannotProcessMandatory
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_cannot_process_mandatory
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.48

Field Name : stateStatsSyncRxNoSuchRport
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_no_such_rport
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.47

Field Name : stateStatsSyncRxNoSuchVport
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_no_such_vport
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.46

Field Name : stateStatsSyncPersistRxConnGetFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_conn_get_failed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.45

Field Name : stateStatsSyncPersistRxNoSgGroupInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_no_sg_group_info
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.44

Field Name : stateStatsSyncPersistRxNoSuchSgGroup
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_no_such_sg_group
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.43

Field Name : stateStatsSyncPersistRxNoSuchRport
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_no_such_rport
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.42

Field Name : stateStatsSyncPersistRxVporttypeNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_vporttype_not_supported
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.41

Field Name : stateStatsSyncPersistRxNoSuchVport
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRPA-STATE-MIB_oid_list

Description : sync_persist_rx_no_such_vport
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.40

Field Name : stateStatsSyncPersistRxExtBitProcessError
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_ext_bit_process_error
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.39

Field Name : stateStatsSyncPersistRxCannotProcessMandatory
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_cannot_process_mandatory
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.38

Field Name : stateStatsSyncPersistRxTypeInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_type_invalid
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.37

Field Name : stateStatsSyncPersistRxProtoNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_proto_not_supported
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.36

Field Name : stateStatsSyncPersistRxLenInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_persist_rx_len_invalid
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.35

Field Name : stateStatsSyncRxLenInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_len_invalid
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.34

Field Name : stateStatsSyncTxMaxPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_max_packed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.33

Field Name : stateStatsSyncTxMinPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_min_packed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.32

Field Name : stateStatsSyncTxUpdateSeqnosCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_update_seqnos_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.31

ACOS-VRRPA-STATE-MIB_oid_list

Field Name : stateStatsSyncTxCreateExtBitCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_create_ext_bit_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.30

Field Name : stateStatsSyncTxTotalInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_total_info_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.29

Field Name : stateStatsSyncTxGetBuffFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_get_buff_failed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.28

Field Name : stateStatsSyncPktInvalidIdxCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_invalid_idx_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.27

Field Name : stateStatsQueryRxUnkCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_unk_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.26

Field Name : stateStatsQueryRxFullInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_full_info_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.25

Field Name : stateStatsQueryRxZeroInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_rx_zero_info_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.24

Field Name : stateStatsQueryTxGetBuffFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : query_tx_get_buff_failed
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.23

Field Name : stateStatsQueryPktInvalidIdxCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : query_pkt_invalid_idx_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.22

Field Name : stateStatsQueryTxMinPacked
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRPA-STATE-MIB_oid_list

Description : query_tx_min_packed

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.21

Field Name : stateStatsQueryTxMaxPacked

Field Type : CounterBasedGauge64

Field Status : current

Description : query_tx_max_packed

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.20

Field Name : stateStatsSyncRxSmpRadiusTableCounter

Field Type : TABLE

Field Status : current

Description : sync_rx_smp_radius_table_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.19

Field Name : stateStatsSyncTxSmpRadiusTableCounter

Field Type : TABLE

Field Status : current

Description : sync_tx_smp_radius_table_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.18

Field Name : stateStatsQueryPktRcvCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : query_pkt_rcv_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.17

Field Name : stateStatsQueryPktTxCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : query_pkt_tx_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.16

Field Name : stateStatsSyncTxPersistUpdateAgeCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_tx_persist_update_age_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.15

Field Name : stateStatsSyncTxPersistDelCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_tx_persist_del_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.14

Field Name : stateStatsSyncTxPersistCreateCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_tx_persist_create_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.13

Field Name : stateStatsSyncRxPersistUpdateAgeCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : sync_rx_persist_update_age_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.12

ACOS-VRRPA-STATE-MIB_oid_list

Field Name : stateStatsSyncRxPersistDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_persist_del_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.11

Field Name : stateStatsSyncRxPersistCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_persist_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.10

Field Name : stateStatsSyncTxUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_update_age_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.9

Field Name : stateStatsSyncTxDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_del_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.8

Field Name : stateStatsSyncTxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_tx_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.7

Field Name : stateStatsSyncRxUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_update_age_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.6

Field Name : stateStatsSyncRxDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_del_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.5

Field Name : stateStatsSyncRxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_rx_create_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.4

Field Name : stateStatsSyncPktRcvCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : sync_pkt_rcv_counter
OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.3

Field Name : stateStatsSyncPktTxCounter
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRPA-STATE-MIB_oid_list

Description : sync_pkt_tx_counter

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.2

Field Name : stateStatsSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.4.1.1.1.1

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Field Name : vrrpCommonDummy
Field Type : CounterBasedGauge64
Field Status : current
Description : dummy counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.3.1.1

Field Name : queryPktRxError
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query recv error
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.180

Field Name : syncTxUpdateMiscCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update misc Sent counter actual
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.179

Field Name : syncTxUpdateAgeCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Age Sent counter actual
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.178

Field Name : syncTxDelCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del Session Sent counter actual
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.177

Field Name : syncTxCreateCounterAct
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Session Sent counter actual
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.176

Field Name : syncTxUpdateMiscBearer
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync update misc bearer sent
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.175

Field Name : syncPktRcvDcMsgDir
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync pkt recv with DCMSG dir
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.174

Field Name : syncRxDropSyncPackets
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync drop all packets
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.173

Field Name : syncRxDcmsgCounterInterPu
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Description : Conn Sync forward CPU with inter-pu comm
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.172

Field Name : dnsCacheSyncRxErrorCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Error Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.171

Field Name : dnsCacheSyncTxErrorCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Error Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.170

Field Name : dnsCacheSyncRxFragCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Frag Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.169

Field Name : dnsCacheSyncTxFragCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Frag Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.168

Field Name : dnsCacheSyncRxDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Del Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.167

Field Name : dnsCacheSyncTxDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Del Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.166

Field Name : dnsCacheSyncRxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Create Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.165

Field Name : dnsCacheSyncTxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : DNS Cache Sync Create Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.164

Field Name : syncRxFwSetDscpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive fw set dscp counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.163

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Field Name : syncTxFwSetDscpCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync send fw set dscp counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.162

Field Name : syncRxExtFwLimitEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync FW Limit Entry Info Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.161

Field Name : syncTxAflexTableEntryNotEligibleCounter
Field Type : TABLE
Field Status : current
Description : send of aflex table entry not eligible
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.160

Field Name : syncTxAflexTableEntryErrorCounter
Field Type : TABLE
Field Status : current
Description : Error on send packet with aflex table entry
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.159

Field Name : syncRxAflexTableEntryFastsyncCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry fast sync
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.158

Field Name : syncTxAflexTableEntryFastsyncCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry fast sync
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.157

Field Name : syncRxAflexTableEntryTimeoutCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry timeout
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.156

Field Name : syncTxAflexTableEntryTimeoutCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry timeout
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.155

Field Name : syncRxAflexTableEntrySetCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry set
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.154

Field Name : syncTxAflexTableEntrySetCounter
Field Type : TABLE
Field Status : current

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Description : Sync send packet with aflex table entry set

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.153

Field Name : syncRxAfexTableEntryReplaceCounter

Field Type : TABLE

Field Status : current

Description : Sync receive packet with aflex table entry replace

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.152

Field Name : syncTxAfexTableEntryReplaceCounter

Field Type : TABLE

Field Status : current

Description : Sync send packet with aflex table entry replace

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.151

Field Name : syncRxAfexTableEntryLifetimeCounter

Field Type : TABLE

Field Status : current

Description : Sync receive packet with aflex table entry lifetime

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.150

Field Name : syncTxAfexTableEntryLifetimeCounter

Field Type : TABLE

Field Status : current

Description : Sync send packet with aflex table entry lifetime

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.149

Field Name : syncRxAfexTableEntryLookupCounter

Field Type : TABLE

Field Status : current

Description : Sync receive packet with aflex table entry lookup

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.148

Field Name : syncTxAfexTableEntryLookupCounter

Field Type : TABLE

Field Status : current

Description : Sync send packet with aflex table entry lookup

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.147

Field Name : syncRxAfexTableEntryIncrCounter

Field Type : TABLE

Field Status : current

Description : Sync receive packet with aflex table entry incr

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.146

Field Name : syncTxAfexTableEntryIncrCounter

Field Type : TABLE

Field Status : current

Description : Sync send packet with aflex table entry incr

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.145

Field Name : syncRxAfexTableEntryDeleteCounter

Field Type : TABLE

Field Status : current

Description : Sync receive packet with aflex table entry delete

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.144

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Field Name : syncTxAflexTableEntryDeleteCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry delete
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.143

Field Name : syncRxAflexTableEntryAppendCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry append
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.142

Field Name : syncTxAflexTableEntryAppendCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry append
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.141

Field Name : syncRxAflexTableEntryAddCounter
Field Type : TABLE
Field Status : current
Description : Sync receive packet with aflex table entry add
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.140

Field Name : syncTxAflexTableEntryAddCounter
Field Type : TABLE
Field Status : current
Description : Sync send packet with aflex table entry add
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.139

Field Name : syncRxExtFwSoShadowExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : FW Scaleout Shadow Ext Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.138

Field Name : syncTxSmpClearCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Clear SMP Session Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.137

Field Name : syncRxSmpClearCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Clear SMP Session Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.136

Field Name : syncTxSmpUpdateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Update SMP Session Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.135

Field Name : syncTxSmpDeleteCounter
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Description : Sync Delete SMP Session Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.134

Field Name : syncTxSmpCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Create SMP Session Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.133

Field Name : syncRxSmpUpdateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Update SMP Session Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.132

Field Name : syncRxSmpDeleteCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Delete SMP Session Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.131

Field Name : syncRxSmpCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Sync Create SMP Session Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.130

Field Name : syncRxExtFwGtpEchoExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : FW GTP Echo Ext Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.129

Field Name : syncRxUnreachedPktCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : total number of unreached packets
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.128

Field Name : syncRxOutOfOrderPktCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : total number of out of order packets received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.127

Field Name : queryRxInvalidMsgDirCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive query packet with invalid message dir
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.126

Field Name : queryRxInvalidSyncVersionCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive query packet with invalid sync version
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.125

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Field Name : queryRxInvalidHaGroupCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive query packet with invalid ha group
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.124

Field Name : queryRxInvalidPartitionCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive query packet with invalid partition
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.123

Field Name : syncRxAflexFragCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive packet with aflex fragment
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.122

Field Name : syncRxAflexDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive packet with aflex delete
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.121

Field Name : syncRxAflexCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive packet with aflex create
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.120

Field Name : syncRxAflexUpdateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync receive packet with aflex update
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.119

Field Name : syncRxTableEntryDelCounter
Field Type : TABLE
Field Status : current
Description : Conn Sync receive packet with table entry delete
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.118

Field Name : syncRxTableEntryCreateCounter
Field Type : TABLE
Field Status : current
Description : Conn Sync receive packet with table entry create
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.117

Field Name : syncRxTableEntryUpdateCounter
Field Type : TABLE
Field Status : current
Description : Conn Sync receive packet with table entry update
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.116

Field Name : syncRxByInactivePeerCounter
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Description : Conn Sync receive packet by inactive peer

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.115

Field Name : syncRxNoVgrpCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn Sync receive packet with no virtual group

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.114

Field Name : syncRxBadProtocolCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn Sync receive packet with bad protocol

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.113

Field Name : syncPktFailedBuffCopyCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn Sync drop sending packet for failure in sending buffer copy

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.112

Field Name : queryPktNoReceivingIpCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn Sync drop sending packet for invalid receiving ip

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.111

Field Name : syncPktNoReceivingVgrpCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn Sync drop sending packet for invalid receiving virtual group

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.110

Field Name : syncPktNoSendingVgrpCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn Sync drop sending packet for invalid sending virtual group

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.109

Field Name : syncPktEmptyBuffCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn Sync drop sending packet for empty buffer

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.108

Field Name : syncRxInvalidSyncPacketCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn Sync receive invalid packet

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.106

Field Name : syncRxDdosDropCounter

Field Type : CounterBasedGauge64

Field Status : current

Description : Conn Sync receive ddos protect packet

OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.105

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Field Name : syncRxExtFwGtpLogExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : FW GTP Ext Log Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.104

Field Name : syncRxExtFwGtpExtInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : FW GTP Ext Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.103

Field Name : syncRxExtFwGtpUInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : FW GTP U Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.102

Field Name : syncRxExtFwGtpLogInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : FW GTP Log Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.101

Field Name : syncRxMonEntity
Field Type : CounterBasedGauge64
Field Status : current
Description : Acos monitoring Entities Sync Messages Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.100

Field Name : syncTxMonEntity
Field Type : CounterBasedGauge64
Field Status : current
Description : Acos Monitoring Entities Sync Messages Sent
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.99

Field Name : syncRxExtFwApps
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync FIREWALL application information Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.98

Field Name : syncRxNotExpectSyncPkt
Field Type : CounterBasedGauge64
Field Status : current
Description : unexpected session sync packets
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.97

Field Name : syncRxExtFwGtpInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : FW GTP Info Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.96

Field Name : syncRxExtDcfwRuleIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Description : Conn Sync FIREWALL session rule idle timeout information Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.95

Field Name : syncRxExtFwHttpLogging
Field Type : CounterBasedGauge64
Field Status : current
Description : FW HTTP Logging Sync Failures
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.94

Field Name : syncRxZoneFailureCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Zone Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.93

Field Name : syncTxEstabCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync send established state
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.92

Field Name : syncRxEstabCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync rcv established state
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.91

Field Name : syncRxExtDcfwLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync FIREWALL session logging information Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.90

Field Name : syncRxExtDcfwRuleId
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync FIREWALL session rule ID information Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.89

Field Name : syncRxExtNatAlgTcpInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync NAT ALG TCP Information
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.88

Field Name : syncRxUpdateSctpConnAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : Update SCTP Addresses Received
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.87

Field Name : syncTxUpdateSctpConnAddr
Field Type : CounterBasedGauge64
Field Status : current
Description : Update SCTP Addresses Sent
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.86

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Field Name : syncErrLsnFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync LSN Fullcone Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.85

Field Name : syncRxLsnFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update LSN Fullcone Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.84

Field Name : syncTxLsnFullcone
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update LSN Fullcone Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.83

Field Name : syncRxExtNatMac
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync NAT MAC Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.82

Field Name : syncRxExtH323Alg
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync H323 TCP ALG Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.81

Field Name : syncRxExtSipAlg
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync SIP TCP ALG Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.80

Field Name : syncRxExtLsnAcIdleTimeout
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync LSN ACL Idle Timeout Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.79

Field Name : syncRxExtLsnAc1
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync LSN ACL Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.78

Field Name : syncRxFtpControl
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync FTP Control Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.77

Field Name : syncRxSeqDeltas
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Description : Conn Sync Seq Deltas Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.76

Field Name : syncRxReserveHa
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Reserve HA Conn
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.75

Field Name : syncRxExtRtsp
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Ext RTSP
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.74

Field Name : syncRxExtPtp
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Ext PTP
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.73

Field Name : syncRxCreateStaticSby
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Static Standby
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.72

Field Name : syncRxSfw
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync SFW
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.71

Field Name : syncRxInsertTuple
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Insert Tuple
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.70

Field Name : syncRxNatAllocSby
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync NAT Alloc Standby
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.69

Field Name : syncRxNatCreateSby
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync NAT Create Standby
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.68

Field Name : syncRxLsnCreateSby
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync LSN Create Standby
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.67

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Field Name : syncGetBuffFailedPort
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Get Buff Failure Wrong Port
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.66

Field Name : syncGetBuffFailedRt
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Get Buff Failure No Route
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.65

Field Name : syncQueryDcmsgCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync query forward CPU
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.64

Field Name : syncRxApptypeNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync App Type Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.63

Field Name : syncRxUnkCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Unknown Type
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.62

Field Name : syncRxUpdateSeqnosCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Seq Num Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.61

Field Name : syncRxTotalInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Total Info Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.60

Field Name : syncRxDcmsgCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync forward CPU
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.59

Field Name : syncRxZeroInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Packet Empty
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.58

Field Name : syncRxTypeInvalid
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Description : Conn Sync Type Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.57

Field Name : syncRxDelNoSuchSession
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del Conn not Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.56

Field Name : syncRxNoSuchSgNode
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync no SG node found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.55

Field Name : syncRxNoSuchNatPool
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync NAT Pool Error
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.54

Field Name : syncRxNoDstForVportInline
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync 'dst' not found for vport inline
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.53

Field Name : syncRxProtoNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Protocol Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.52

Field Name : syncRxConnGetFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Get Conn Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.51

Field Name : syncRxConnExists
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Conn Exists
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.50

Field Name : syncRxCreateExtBitCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create with Ext Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.49

Field Name : syncRxExtBitProcessError
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Proc Ext Bit Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.48

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Field Name : syncRxCannotProcessMandatory
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Process Mandatory Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.47

Field Name : syncRxNoSuchRport
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Real Port Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.46

Field Name : syncRxNoSuchVport
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Virt Port Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.45

Field Name : syncPersistRxConnGetFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Get Conn Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.44

Field Name : syncPersistRxNoSgGroupInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync No Service Group Info Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.43

Field Name : syncPersistRxNoSuchSgGroup
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync No Service Group Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.42

Field Name : syncPersistRxNoSuchRport
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Real Port Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.41

Field Name : syncPersistRxVporttypeNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Virt Port Type Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.40

Field Name : syncPersistRxNoSuchVport
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Virt Port Not Found
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.39

Field Name : syncPersistRxExtBitProcessError
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Description : Persist Conn Sync Proc Ext Bit Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.38

Field Name : syncPersistRxCannotProcessMandatory
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Process Mandatory Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.37

Field Name : syncPersistRxTypeInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Type Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.36

Field Name : syncPersistRxProtoNotSupported
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Protocol Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.35

Field Name : syncPersistRxLenInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Persist Conn Sync Length Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.34

Field Name : syncRxLenInvalid
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Length Invalid
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.33

Field Name : syncTxMaxPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : Min Sync Msg Per Packet
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.32

Field Name : syncTxMinPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Sync Msg Per Packet
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.31

Field Name : syncTxUpdateSeqnosCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Seq Num Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.30

Field Name : syncTxCreateExtBitCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create with Ext Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.29

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Field Name : syncTxTotalInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Total Info Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.28

Field Name : syncTxGetBuffFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Get Buff Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.27

Field Name : syncPktInvalidIdxCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Invalid Interface
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.26

Field Name : queryRxUnkCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query Unknown Type
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.25

Field Name : queryRxFullInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query Packet Full
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.24

Field Name : queryRxZeroInfoCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query Packet Empty
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.23

Field Name : queryTxGetBuffFailed
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query Get Buff Failure
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.22

Field Name : queryPktInvalidIdxCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query Invalid Interface
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.21

Field Name : queryTxMinPacked
Field Type : CounterBasedGauge64
Field Status : current
Description : Min Query Msg Per Packet
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.20

Field Name : queryTxMaxPacked
Field Type : CounterBasedGauge64
Field Status : current

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Description : Max Query Msg Per Packet
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.19

Field Name : syncRxSmpRadiusTableCounter
Field Type : TABLE
Field Status : current
Description : Conn Sync Update LSN RADIUS Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.18

Field Name : syncTxSmpRadiusTableCounter
Field Type : TABLE
Field Status : current
Description : Conn Sync Update LSN RADIUS Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.17

Field Name : queryPktRcvCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.16

Field Name : queryPktTxCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Query sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.15

Field Name : syncTxPersistUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Persist Age Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.14

Field Name : syncTxPersistDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Delete Persist Session Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.13

Field Name : syncTxPersistCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Persist Session Pkts Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.12

Field Name : syncRxPersistUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Persist Age Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.11

Field Name : syncRxPersistDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Delete Persist Session Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.10

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Field Name : syncRxPersistCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Persist Session Pkts Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.9

Field Name : syncTxUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Age Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.8

Field Name : syncTxDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del Session Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.7

Field Name : syncTxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Session Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.6

Field Name : syncRxUpdateAgeCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Update Age Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.5

Field Name : syncRxDelCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Del Session Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.4

Field Name : syncRxCreateCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Create Session Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.3

Field Name : syncPktRcvCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Received counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.2

Field Name : syncPktTxCounter
Field Type : CounterBasedGauge64
Field Status : current
Description : Conn Sync Sent counter
OID : 1.3.6.1.4.1.22610.2.4.10.13.1.1.1

Field Name : vrrpAVridSTable
Field Type : TABLE
Field Status : current

ACOS-VRRP-A-STATS-MIB_acosVrrpA_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.13.11.1.1

Field Name : vrrpAVridSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.13.11.1.1.1

Field Name : associatedNatpoolCount

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of nat pools associated to vrid

OID : 1.3.6.1.4.1.22610.2.4.10.13.11.1.1.1.4

Field Name : associatedVportCount

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of vports associated to vrid

OID : 1.3.6.1.4.1.22610.2.4.10.13.11.1.1.1.3

Field Name : associatedVipCount

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of vips associated to vrid

OID : 1.3.6.1.4.1.22610.2.4.10.13.11.1.1.1.2

Field Name : vridVal

Field Type : INTEGER

Field Status : current

Description : Specify ha VRRP-A vrid

OID : 1.3.6.1.4.1.22610.2.4.10.13.11.1.1.1.1

ACOS-WAF-RULE-SET-STATS-MIB_acosWafRuleSet_oid_list

Field Name : wafRuleSetSTable

Field Type : TABLE

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1

Field Name : wafRuleSetSEntry

Field Type : CounterBasedGauge64

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1

Field Name : phase4Other

Field Type : CounterBasedGauge64

Field Status : current

Description : WAF rule set other hits in phase 4

OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.27

Field Name : phase4Redirect

Field Type : CounterBasedGauge64

Field Status : current

Description : WAF rule set redirect hits in phase 4

OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.26

Field Name : phase4Drop

Field Type : CounterBasedGauge64

Field Status : current

Description : WAF rule set drop hits in phase 4

OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.25

Field Name : phase4Deny

Field Type : CounterBasedGauge64

Field Status : current

Description : WAF rule set deny hits in phase 4

OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.24

Field Name : phase4Allow

Field Type : CounterBasedGauge64

Field Status : current

Description : WAF rule set allow hits in phase 4

OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.23

Field Name : phase4Pass

Field Type : CounterBasedGauge64

Field Status : current

Description : WAF rule set pass hits in phase 4

OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.22

Field Name : phase3Other

Field Type : CounterBasedGauge64

Field Status : current

Description : WAF rule set other hits in phase 3

OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.21

Field Name : phase3Redirect

Field Type : CounterBasedGauge64

Field Status : current

ACOS-WAF-RULE-SET-STATS-MIB_acosWafRuleSet_oid_list

Description : WAF rule set redirect hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.20

Field Name : phase3Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.19

Field Name : phase3Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.18

Field Name : phase3Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.17

Field Name : phase3Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.16

Field Name : phase2Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.15

Field Name : phase2Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.14

Field Name : phase2Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.13

Field Name : phase2Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.12

Field Name : phase2Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.11

ACOS-WAF-RULE-SET-STATS-MIB_acosWafRuleSet_oid_list

Field Name : phase2Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.10

Field Name : phase10ther
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.9

Field Name : phase1Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.8

Field Name : phase1Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.7

Field Name : phase1Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.6

Field Name : phase1Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.5

Field Name : phase1Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.4

Field Name : response
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses hanlded by WAF rule set
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.3

Field Name : request
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests hanlded by WAF rule set
OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.2

Field Name : name
Field Type : String
Field Status : current

ACOS-WAF-RULE-SET-STATS-MIB_acosWafRuleSet_oid_list

Description : WAF Rule set name

OID : 1.3.6.1.4.1.22610.2.4.10.194.1.1.1.1

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : phase4Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.363

Field Name : phase4Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.362

Field Name : phase4Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.361

Field Name : phase4Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.360

Field Name : phase4Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.359

Field Name : phase4Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.358

Field Name : phase3Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.357

Field Name : phase3Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.356

Field Name : phase3Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.355

Field Name : phase3Deny
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : WAF rule set deny hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.354

Field Name : phase3Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.353

Field Name : phase3Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.352

Field Name : phase2Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.351

Field Name : phase2Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.350

Field Name : phase2Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.349

Field Name : phase2Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.348

Field Name : phase2Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.347

Field Name : phase2Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.346

Field Name : phase1Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.345

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : phase1Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.344

Field Name : phase1Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.343

Field Name : phase1Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.342

Field Name : phase1Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.341

Field Name : phase1Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.340

Field Name : ruleSetResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses handled by WAF rule set
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.339

Field Name : ruleSetRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests handled by WAF rule set
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.338

Field Name : cookieSecurityAddSamesiteViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - samesite attribute violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.337

Field Name : cookieSecurityAddSamesiteSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - samesite attribute added successfully
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.336

Field Name : httpProtocolNonSslCookiePrefixViolation
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Cookie Name Prefix check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.335

Field Name : httpProtocolNonSslCookiePrefixSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Name Prefix check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.334

Field Name : httpProtocolBodyWithoutContentTypeViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Body without content type check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.333

Field Name : httpProtocolBodyWithoutContentTypeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Body without content type check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.332

Field Name : httpProtocolPostWithoutContentTypeViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : POST without content type check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.331

Field Name : httpProtocolPostWithoutContentTypeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : POST without content type check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.330

Field Name : actionResponseLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Log response violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.329

Field Name : actionResponseLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Learning Updates
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.328

Field Name : actionResponseDenyCustomResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with custom response
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.327

Field Name : actionResponseDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Dropped Responses
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.326

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : actionResponseDenyReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Deny with Resets
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.325

Field Name : actionResponseDenyRedirect
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with Redirect
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.324

Field Name : actionResponseDeny403
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with 403
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.323

Field Name : actionResponseDeny200
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with 200
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.322

Field Name : actionResponseAllow
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Action allowed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.321

Field Name : xmlCheckMaxEntityDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.320

Field Name : xmlCheckMaxEntityDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.319

Field Name : xmlCheckMaxEntityDeclViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Decl violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.318

Field Name : xmlCheckMaxEntityDeclSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Decl check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.317

Field Name : formResponseNonPostSanitize
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Changed response form method to POST
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.316

Field Name : formResponseNonPostViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Response form method was not POST
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.315

Field Name : formResponseNonPostSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Response form method was POST
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.314

Field Name : cookieSecurityDecryptInGracePeriodViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Decrypt violation but in grace period
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.313

Field Name : requestCheckCommandInjectionFormBodyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check form body arguments violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.312

Field Name : requestCheckCommandInjectionFormBodySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check form body arguments passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.311

Field Name : requestCheckCommandInjectionUriQueryViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check url query arguments violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.310

Field Name : requestCheckCommandInjectionUriQuerySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check url query arguments passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.309

Field Name : requestCheckCommandInjectionHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check headers violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.308

Field Name : requestCheckCommandInjectionHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check headers passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.307

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : requestCheckCommandInjectionCookiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check cookies violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.306

Field Name : requestCheckCommandInjectionCookiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check cookies passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.305

Field Name : regexViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Regular expression failure
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.304

Field Name : tooManySessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Too many sessions consumed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.303

Field Name : outOfSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of sessions
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.302

Field Name : sessionsFreed
Field Type : CounterBasedGauge64
Field Status : current
Description : Sessions freed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.301

Field Name : sessionsAlloc
Field Type : CounterBasedGauge64
Field Status : current
Description : Sessions allocated
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.300

Field Name : policyLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Policy limit exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.299

Field Name : actionLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Log request violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.298

Field Name : actionLearn
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Request Learning Updates

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.297

Field Name : actionDenyCustomResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Deny with custom response

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.296

Field Name : actionDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of Dropped Requests

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.295

Field Name : actionDenyReset

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Deny with Resets

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.294

Field Name : actionDenyRedirect

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Deny with Redirect

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.293

Field Name : actionDeny403

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Deny with 403

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.292

Field Name : actionDeny200

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Deny with 200

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.291

Field Name : actionAllow

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Action allowed

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.290

Field Name : learningListFull

Field Type : CounterBasedGauge64

Field Status : current

Description : Learning list is full

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.289

Field Name : xmlContentCheckWsdlViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : WSDL violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.288

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : xmlContentCheckWsd1Success
Field Type : CounterBasedGauge64
Field Status : current
Description : WSDL passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.287

Field Name : xmlContentCheckSchemaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Schema violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.286

Field Name : xmlContentCheckSchemaSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Schema passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.285

Field Name : xmlCheckXssViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML XSS Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.284

Field Name : xmlCheckXssSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML XSS Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.283

Field Name : xmlCheckSqliaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Sqlia Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.282

Field Name : xmlCheckSqliaSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Sqlia Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.281

Field Name : xmlCheckNamespaceUriLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Namespace URI Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.280

Field Name : xmlCheckNamespaceUriLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Namespace URI Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.279

Field Name : xmlCheckMaxNamespaceViolation
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : XML Limit Namespace violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.278

Field Name : xmlCheckMaxNamespaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Namespace check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.277

Field Name : xmlCheckMaxEntityExpDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entities Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.276

Field Name : xmlCheckMaxEntityExpDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entities Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.275

Field Name : xmlCheckMaxEntityExpViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Expansions violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.274

Field Name : xmlCheckMaxEntityExpSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Expansions check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.273

Field Name : xmlCheckMaxElemNameLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Name Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.272

Field Name : xmlCheckMaxElemNameLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Name Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.271

Field Name : xmlCheckMaxElemDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.270

Field Name : xmlCheckMaxElemDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.269

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : xmlCheckMaxElemChildViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Child violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.268

Field Name : xmlCheckMaxElemChildSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Child check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.267

Field Name : xmlCheckMaxElemViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.266

Field Name : xmlCheckMaxElemSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.265

Field Name : xmlCheckMaxCdataLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit CData Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.264

Field Name : xmlCheckMaxCdataLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit CData Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.263

Field Name : xmlCheckMaxAttrValueLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Value Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.262

Field Name : xmlCheckMaxAttrValueLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Value Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.261

Field Name : xmlCheckMaxAttrNameLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Name Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.260

Field Name : xmlCheckMaxAttrNameLenSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : XML Limit Name Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.259

Field Name : xmlCheckMaxAttrViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Attribute violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.258

Field Name : xmlCheckMaxAttrSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Attribute check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.257

Field Name : xmlCheckFormatViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.256

Field Name : xmlCheckFormatSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.255

Field Name : soapCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Soap Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.254

Field Name : soapCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Soap Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.253

Field Name : responseCloakingFilterHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Headers Filter violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.252

Field Name : responseCloakingFilterHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Headers Filter check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.251

Field Name : responseCloakingHideStatusCodeViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Hide Code violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.250

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : responseCloakingHideStatusCodeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Hide Code check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.249

Field Name : requestCheckXssPostBodySanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Post Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.248

Field Name : requestCheckXssPostBodyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Post violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.247

Field Name : requestCheckXssPostBodySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Post passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.246

Field Name : requestCheckXssUrlSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check URL Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.245

Field Name : requestCheckXssUrlViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check URL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.244

Field Name : requestCheckXssUrlSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check URL passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.243

Field Name : requestCheckXssCookieSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Cookie Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.242

Field Name : requestCheckXssCookieViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Cookie violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.241

Field Name : requestCheckXssCookieSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : XSS Check Cookie passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.240

Field Name : requestCheckUrlBlacklistViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : URI Black List violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.239

Field Name : requestCheckUrlBlacklistSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : URI Black List passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.238

Field Name : requestCheckUrlWhitelistViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : URI White List violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.237

Field Name : requestCheckUrlWhitelistSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : URI White List passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.236

Field Name : requestCheckUrlListLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : URL Check Learn
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.235

Field Name : requestCheckUrlListViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : URL Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.234

Field Name : requestCheckUrlListSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : URL Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.233

Field Name : requestCheckSqliaPostBodySanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check Post Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.232

Field Name : requestCheckSqliaPostBodyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check Post violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.231

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : requestCheckSqliaPostBodySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check Post passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.230

Field Name : requestCheckSqliaUrlSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check URL Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.229

Field Name : requestCheckSqliaUrlViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check URL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.228

Field Name : requestCheckSqliaUrlSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check URL passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.227

Field Name : requestCheckSessionCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.226

Field Name : requestCheckSessionCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.225

Field Name : requestCheckSessionCheckNone
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Created
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.224

Field Name : requestCheckRefererRedirect
Field Type : CounterBasedGauge64
Field Status : current
Description : Referer Check Redirect
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.223

Field Name : requestCheckRefererViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Referer Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.222

Field Name : requestCheckRefererSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Referer Check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.221

Field Name : requestCheckRedirectWlistLearn

Field Type : CounterBasedGauge64

Field Status : current

Description : Redirect Whitelist Learn

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.220

Field Name : requestCheckRedirectWlistViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Redirect Whitelist violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.219

Field Name : requestCheckRedirectWlistSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Redirect Whitelist passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.218

Field Name : requestCheckBotViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Bot check violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.217

Field Name : requestCheckBotSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Bot check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.216

Field Name : jsonCheckMaxStringViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : JSON Limit String violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.215

Field Name : jsonCheckMaxStringSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : JSON Limit String check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.214

Field Name : jsonCheckMaxObjectMemberCountViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : JSON Limit Object Number Count violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.213

Field Name : jsonCheckMaxObjectMemberCountSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : JSON Limit Object Number Count check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.212

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : jsonCheckMaxDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.211

Field Name : jsonCheckMaxDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.210

Field Name : jsonCheckMaxArrayValueCountViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Array Value Count violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.209

Field Name : jsonCheckMaxArrayValueCountSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Array Value Count check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.208

Field Name : jsonCheckFormatViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.207

Field Name : jsonCheckFormatSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.206

Field Name : httpProtocolViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.205

Field Name : httpProtocolSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.204

Field Name : httpProtocolPostWithoutContentViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : POST without content check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.203

Field Name : httpProtocolPostWithoutContentSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : POST without content check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.202

Field Name : httpProtocolPostWith0ContentViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : POST with 0 content check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.201

Field Name : httpProtocolPostWith0ContentSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : POST with 0 content check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.200

Field Name : httpProtocolMultipleContentLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple content-length headers check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.199

Field Name : httpProtocolMultipleContentLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple content-length headers check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.198

Field Name : httpProtocolMissingHostHeaderViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing host header check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.197

Field Name : httpProtocolMissingHostHeaderSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing host header check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.196

Field Name : httpProtocolMissingHeaderValueViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing header value check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.195

Field Name : httpProtocolMissingHeaderValueSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing header value check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.194

Field Name : httpProtocolMalformedRequestLineViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request line check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.193

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : httpProtocolMalformedRequestLineSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request line check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.192

Field Name : httpProtocolMalformedRequestViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.191

Field Name : httpProtocolMalformedRequestSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.190

Field Name : httpProtocolMalformedParameterViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed parameter check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.189

Field Name : httpProtocolMalformedParameterSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed parameter check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.188

Field Name : httpProtocolMalformedHeaderViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed header check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.187

Field Name : httpProtocolMalformedHeaderSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed header check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.186

Field Name : httpProtocolMalformedContentLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed content-length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.185

Field Name : httpProtocolMalformedContentLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed content-length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.184

Field Name : httpProtocolInvalidUrlEncodingViolation
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Invalid url encoding check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.183

Field Name : httpProtocolInvalidUrlEncodingSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid url encoding check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.182

Field Name : httpProtocolHostHeaderWithIpViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Host header with IP check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.181

Field Name : httpProtocolHostHeaderWithIpSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Host header with IP check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.180

Field Name : httpProtocolHeadWithContentViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HEAD with content check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.179

Field Name : httpProtocolHeadWithContentSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HEAD with content check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.178

Field Name : httpProtocolGetWithContentViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : GET with content check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.177

Field Name : httpProtocolGetWithContentSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GET with content check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.176

Field Name : httpProtocolBadMultipartRequestViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad multi-part request check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.175

Field Name : httpProtocolBadMultipartRequestSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad multi-part request check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.174

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : httpProtocolAllowedMethodCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Method Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.173

Field Name : httpProtocolAllowedMethodCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Method Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.172

Field Name : httpProtocolAllowedVersionsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP versions check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.171

Field Name : httpProtocolAllowedVersionsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP versions check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.170

Field Name : httpProtocolAllowedHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP headers check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.169

Field Name : httpProtocolAllowedHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP headers check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.168

Field Name : maxUrlLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX URL length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.167

Field Name : maxUrlLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX URL length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.166

Field Name : httpLimitMaxRequestLineLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX request line length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.165

Field Name : httpLimitMaxRequestLineLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Limit check - MAX request line length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.164

Field Name : httpLimitMaxRequestLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX request length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.163

Field Name : httpLimitMaxRequestLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX request length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.162

Field Name : httpLimitMaxQueryLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX query length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.161

Field Name : httpLimitMaxQueryLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX query length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.160

Field Name : httpLimitMaxPostLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX POST length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.159

Field Name : httpLimitMaxPostLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX POST length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.158

Field Name : httpLimitMaxParamsLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters total length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.157

Field Name : httpLimitMaxParamsLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters total length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.156

Field Name : httpLimitMaxParamsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.155

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : httpLimitMaxParamsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.154

Field Name : httpLimitMaxParamValueLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter value length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.153

Field Name : httpLimitMaxParamValueLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter value length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.152

Field Name : httpLimitMaxParamNameLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter name length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.151

Field Name : httpLimitMaxParamNameLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter name length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.150

Field Name : httpLimitMaxHeadersLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX headers length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.149

Field Name : httpLimitMaxHeadersLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX headers length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.148

Field Name : httpLimitMaxHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Headers violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.147

Field Name : httpLimitMaxHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX headers count check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.146

Field Name : httpLimitMaxHeaderValueLengthViolation
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : MAX header value length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.145

Field Name : httpLimitMaxHeaderValueLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header value length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.144

Field Name : httpLimitMaxHeaderNameLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header name length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.143

Field Name : httpLimitMaxHeaderNameLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header name length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.142

Field Name : httpLimitMaxHeaderLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.141

Field Name : httpLimitMaxHeaderLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.140

Field Name : httpLimitMaxEntitiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Entities violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.139

Field Name : httpLimitMaxEntitiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Entities check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.138

Field Name : httpLimitMaxDataParseViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Buffer Overflow - Max Data Parse violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.137

Field Name : httpLimitMaxDataParseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Buffer Overflow - Max Data Parse check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.136

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : httpLimitMaxCookiesLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookies length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.135

Field Name : httpLimitMaxCookiesLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookies length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.134

Field Name : httpLimitMaxCookiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Cookies violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.133

Field Name : httpLimitMaxCookiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Cookies check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.132

Field Name : httpLimitMaxCookieValueLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie value length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.131

Field Name : httpLimitMaxCookieValueLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie value length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.130

Field Name : httpLimitMaxCookieNameLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie name length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.129

Field Name : httpLimitMaxCookieNameLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie name length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.128

Field Name : httpLimitMaxCookieHeaderLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie header length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.127

Field Name : httpLimitMaxCookieHeaderLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : MAX cookie header length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.126

Field Name : httpLimitMaxContentLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX content-length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.125

Field Name : httpLimitMaxContentLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX content-length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.124

Field Name : evasionCheckRemoveSpacesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Spaces check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.123

Field Name : evasionCheckRemoveSpacesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Spaces check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.122

Field Name : evasionCheckRemoveCommentsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Comments check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.121

Field Name : evasionCheckRemoveCommentsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Comments check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.120

Field Name : evasionCheckMaxLevelsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Levels check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.119

Field Name : evasionCheckMaxLevelsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Levels check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.118

Field Name : evasionCheckMultipleSlashesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Slashes check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.117

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : evasionCheckMultipleSlashesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Slashes check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.116

Field Name : evasionCheckMultipleEncodingLevelsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Encoding Levels check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.115

Field Name : evasionCheckMultipleEncodingLevelsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Encoding Levels check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.114

Field Name : evasionCheckInvalidHexEncodingViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Hex Encoding check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.113

Field Name : evasionCheckInvalidHexEncodingSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Hex Encoding check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.112

Field Name : evasionCheckHighAsciiBytesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : High Ascii Bytes check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.111

Field Name : evasionCheckHighAsciiBytesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : High Ascii Bytes check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.110

Field Name : evasionCheckDirTraversalViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Dir traversal check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.109

Field Name : evasionCheckDirTraversalSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Dir traversal check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.108

Field Name : evasionCheckDecodeUnicodeCharsViolation
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Decode Unicode Chars check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.107

Field Name : evasionCheckDecodeUnicodeCharsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Unicode Chars check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.106

Field Name : evasionCheckDecodeEscapedCharsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Escaped Chars check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.105

Field Name : evasionCheckDecodeEscapedCharsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Escaped Chars check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.104

Field Name : evasionCheckDecodeEntitiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Entities check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.103

Field Name : evasionCheckDecodeEntitiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Entities check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.102

Field Name : evasionCheckApacheWhitespaceViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Apache Whitespace check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.101

Field Name : evasionCheckApacheWhitespaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Apache Whitespace check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.100

Field Name : dlpPcreMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : PCRE Mask violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.99

Field Name : dlpPcreViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : PCRE Mask violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.98

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : dlpPcreSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : PCRE Mask check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.97

Field Name : dlpSsnViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Social Security Number Mask violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.96

Field Name : dlpSsnSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Social Security Number Mask check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.95

Field Name : dlpCcnJcbMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : JCB Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.94

Field Name : dlpCcnJcbViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JCB Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.93

Field Name : dlpCcnDiscoverMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : Discover Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.92

Field Name : dlpCcnDiscoverViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Discover Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.91

Field Name : dlpCcnMastercardMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : MasterCard Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.90

Field Name : dlpCcnMastercardViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MasterCard Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.89

Field Name : dlpCcnVisaMasked
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Visa Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.88

Field Name : dlpCcnVisaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Visa Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.87

Field Name : dlpCcnDinersMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : Diners Club Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.86

Field Name : dlpCcnDinersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Diners Club Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.85

Field Name : dlpCcnAmexMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : Amex Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.84

Field Name : dlpCcnAmexViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Amex Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.83

Field Name : dlpCcnSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Credit Card Number check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.82

Field Name : formSetNoCache
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Set No Cache violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.81

Field Name : formSetNoCacheSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Set No Cache check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.80

Field Name : formPasswordAutocompleteViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Password Autocomplete violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.79

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : formPasswordAutocompleteSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Password Autocomplete check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.78

Field Name : formNonSslPasswordViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL Password violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.77

Field Name : formNonSslPasswordSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL Password check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.76

Field Name : formNonMaskedPasswordViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non Masked Password violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.75

Field Name : formNonMaskedPasswordSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non Masked Password check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.74

Field Name : formCheckSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : Post Form Check Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.73

Field Name : formCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Post Form Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.72

Field Name : formCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Post Form Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.71

Field Name : formRequestNonPostViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Method being Non Post in Request violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.70

Field Name : formRequestNonPostSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Form Method being Non Post in Request passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.69

Field Name : formNonSslViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.68

Field Name : formNonSslSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.67

Field Name : formTagInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Form A10 Tag Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.66

Field Name : formConsistencyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Consistency violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.65

Field Name : formConsistencySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Consistency passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.64

Field Name : formCsrftagViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form CSRF tag violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.63

Field Name : formCsrftagSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form CSRF tag passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.62

Field Name : cspHeaderInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : CSP header Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.61

Field Name : cspHeaderSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : CSP header found
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.60

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : cspHeaderViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : CSP header_missing
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.59

Field Name : cookieSecurityDisallowedPersistentSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed persistent Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.58

Field Name : cookieSecurityDisallowedSessionSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed session Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.57

Field Name : cookieSecurityAllowedPersistentSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - allowed persistent Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.56

Field Name : cookieSecurityAllowedSessionSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - allowed session Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.55

Field Name : cookieSecurityDisallowedPersistentCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.54

Field Name : cookieSecurityDisallowedSessionCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.53

Field Name : cookieSecurityAllowedPersistentCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - allowed persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.52

Field Name : cookieSecurityAllowedSessionCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - allowed session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.51

Field Name : cookieSecuritySessionCookiesSigned
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Cookie Security - signed session cookies

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.50

Field Name : cookieSecuritySessionCookiesEncrypted

Field Type : CounterBasedGauge64

Field Status : current

Description : Cookie Security - encrypted session cookies

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.49

Field Name : cookieSecuritySessionCookies

Field Type : CounterBasedGauge64

Field Status : current

Description : Cookie Security - session cookies

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.48

Field Name : cookieSecurityPersistentCookiesSigned

Field Type : CounterBasedGauge64

Field Status : current

Description : Cookie Security - signed persistent cookies

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.47

Field Name : cookieSecurityPersistentCookiesEncrypted

Field Type : CounterBasedGauge64

Field Status : current

Description : Cookie Security - encrypted persistent cookies

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.46

Field Name : cookieSecurityPersistentCookies

Field Type : CounterBasedGauge64

Field Status : current

Description : Cookie Security - persistent cookies

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.45

Field Name : cookieSecurityCookiePolicyViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Cookie Security - cookie policy violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.44

Field Name : cookieSecurityCookiePolicySuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Cookie Security - cookie policy passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.43

Field Name : cookieSecurityUnrecognizedCookieViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Cookie Security - unrecognized cookie violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.42

Field Name : cookieSecurityUnrecognizedCookieSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Cookie Security - request with unrecognized cookie

OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.41

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : cookieSecurityMissingCookieViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - missing cookie violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.40

Field Name : cookieSecurityMissingCookieSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - request with missing cookie
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.39

Field Name : cookieSecurityAddSecureViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - secure flag violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.38

Field Name : cookieSecurityAddSecureSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - secure flag added successfully
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.37

Field Name : cookieSecurityAddHttpOnlyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - http-only flag violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.36

Field Name : cookieSecurityAddHttpOnlySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - http-only flag added successfully
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.35

Field Name : cookieSecuritySignatureCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signature check failed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.34

Field Name : cookieSecuritySignatureCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signature check successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.33

Field Name : cookieSecuritySignSkipRcache
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing skipped - RAM cache
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.32

Field Name : cookieSecuritySignLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Cookie Security - signing limit exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.31

Field Name : cookieSecuritySignViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.30

Field Name : cookieSecuritySignSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.29

Field Name : cookieSecurityDecryptViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - decrypt violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.28

Field Name : cookieSecurityDecryptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - decrypt successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.27

Field Name : cookieSecurityEncryptSkipRcache
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt skipped - RAM cache
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.26

Field Name : cookieSecurityEncryptLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt limit exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.25

Field Name : cookieSecurityEncryptViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.24

Field Name : cookieSecurityEncryptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.23

Field Name : bruteForceResponseStringTriggered
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute Force Response string Triggered
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.22

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : bruteForceResponseHeadersTriggered
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute Force Response Headers Triggered
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.21

Field Name : bruteForceResponseCodesTriggered
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Codes Triggered
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.20

Field Name : bruteForceChallengeLimitViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.19

Field Name : bruteForceChallengeLimitSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.18

Field Name : bruteForceLockoutLimitViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.17

Field Name : bruteForceLockoutLimitSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.16

Field Name : bruteForceChallengeCaptchaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Captcha challenge violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.15

Field Name : bruteForceChallengeCaptchaSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Captcha challenge check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.14

Field Name : bruteForceChallengeCaptchaSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Captcha challenge sent
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.13

Field Name : bruteForceChallengeJavascriptViolation
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : JavaScript challenge violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.12

Field Name : bruteForceChallengeJavascriptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JavaScript challenge check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.11

Field Name : bruteForceChallengeJavascriptSent
Field Type : CounterBasedGauge64
Field Status : current
Description : JavaScript challenge sent
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.10

Field Name : bruteForceChallengeCookieViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie challenge violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.9

Field Name : bruteForceChallengeCookieSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Challenge check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.8

Field Name : bruteForceChallengeCookieSent
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Challenge Sent
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.7

Field Name : bruteForceViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute-Force checks violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.6

Field Name : bruteForceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute-Force checks passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.5

Field Name : respDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses Denied
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.4

Field Name : reqDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Denied
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.3

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : reqAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Allowed
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.2

Field Name : totalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Requests
OID : 1.3.6.1.4.1.22610.2.4.10.111.1.1.1

Field Name : wafTemplateSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1

Field Name : wafTemplateSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1

Field Name : phase4Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.364

Field Name : phase4Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.363

Field Name : phase4Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.362

Field Name : phase4Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.361

Field Name : phase4Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.360

Field Name : phase4Pass
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : WAF rule set pass hits in phase 4
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.359

Field Name : phase3Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.358

Field Name : phase3Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.357

Field Name : phase3Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.356

Field Name : phase3Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.355

Field Name : phase3Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.354

Field Name : phase3Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 3
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.353

Field Name : phase2Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.352

Field Name : phase2Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.351

Field Name : phase2Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.350

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : phase2Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.349

Field Name : phase2Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.348

Field Name : phase2Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 2
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.347

Field Name : phase1Other
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set other hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.346

Field Name : phase1Redirect
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set redirect hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.345

Field Name : phase1Drop
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set drop hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.344

Field Name : phase1Deny
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set deny hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.343

Field Name : phase1Allow
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set allow hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.342

Field Name : phase1Pass
Field Type : CounterBasedGauge64
Field Status : current
Description : WAF rule set pass hits in phase 1
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.341

Field Name : ruleSetResponse
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Responses hanlded by WAF rule set
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.340

Field Name : ruleSetRequest
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests hanlded by WAF rule set
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.339

Field Name : wafTemplatecookieSecurityAddSamesiteViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - samesite attribute violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.338

Field Name : wafTemplatecookieSecurityAddSamesiteSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - samesite attribute added successfully
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.337

Field Name : wafTemplatehttpProtocolNonSslCookiePrefixViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Name Prefix check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.336

Field Name : wafTemplatehttpProtocolNonSslCookiePrefixSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Name Prefix check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.335

Field Name : wafTemplatehttpProtocolBodyWithoutContentTypeViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Body without content type check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.334

Field Name : wafTemplatehttpProtocolBodyWithoutContentTypeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Body without content type check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.333

Field Name : wafTemplatehttpProtocolPostWithoutContentTypeViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : POST without content type check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.332

Field Name : wafTemplatehttpProtocolPostWithoutContentTypeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : POST without content type check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.331

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplateResponseActionLog
Field Type : CounterBasedGauge64
Field Status : current
Description : Log response violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.330

Field Name : wafTemplateResponseActionLearn
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Learning Updates
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.329

Field Name : wafTemplateResponseActionDenyCustomResponse
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with custom response
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.328

Field Name : wafTemplateResponseActionDrop
Field Type : CounterBasedGauge64
Field Status : current
Description : Number of Dropped Responses
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.327

Field Name : wafTemplateResponseActionDenyReset
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with Resets
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.326

Field Name : wafTemplateResponseActionDenyRedirect
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with Redirect
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.325

Field Name : wafTemplateResponseActionDeny403
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with 403
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.324

Field Name : wafTemplateResponseActionDeny200
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Deny with 200
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.323

Field Name : wafTemplateResponseActionAllow
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Action allowed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.322

Field Name : wafTemplatexmlCheckMaxEntityDepthViolation
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : XML Limit Entity Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.321

Field Name : wafTemplatexmlCheckMaxEntityDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.320

Field Name : wafTemplatexmlCheckMaxEntityDeclViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Decl violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.319

Field Name : wafTemplatexmlCheckMaxEntityDeclSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Entity Decl check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.318

Field Name : wafTemplateformResponseNonPostSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : Changed response form method to POST
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.317

Field Name : wafTemplateformResponseNonPostViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Response form method was not POST
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.316

Field Name : wafTemplateformResponseNonPostSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Response form method was POST
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.315

Field Name : wafTemplatecookieSecurityDecryptInGracePeriodViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Decrypt violation but in grace period
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.314

Field Name : wafTemplateRequestCheckCommandInjectionFormBodyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check form body arguments violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.313

Field Name : wafTemplateRequestCheckCommandInjectionFormBodySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check form body arguments passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.312

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplateRequestCheckCommandInjectionUrlQueryViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check url query arguments violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.311

Field Name : wafTemplateRequestCheckCommandInjectionUrlQuerySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check url query arguments passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.310

Field Name : wafTemplateRequestCheckCommandInjectionHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check headers violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.309

Field Name : wafTemplateRequestCheckCommandInjectionHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check headers passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.308

Field Name : wafTemplateRequestCheckCommandInjectionCookiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check cookies violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.307

Field Name : wafTemplateRequestCheckCommandInjectionCookiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Command Injection Check cookies passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.306

Field Name : wafTemplateregexViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Regular expression failure
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.305

Field Name : wafTemplatetooManySessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Too many sessions consumed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.304

Field Name : wafTemplateoutOfSessions
Field Type : CounterBasedGauge64
Field Status : current
Description : Out of sessions
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.303

Field Name : wafTemplatesessionsFreed
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Sessions freed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.302

Field Name : wafTemplatesessionsAlloc

Field Type : CounterBasedGauge64

Field Status : current

Description : Sessions allocated

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.301

Field Name : wafTemplatepolicyLimitExceeded

Field Type : CounterBasedGauge64

Field Status : current

Description : Policy limit exceeded

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.300

Field Name : wafTemplateactionLog

Field Type : CounterBasedGauge64

Field Status : current

Description : Log request violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.299

Field Name : wafTemplateactionLearn

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Learning Updates

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.298

Field Name : wafTemplateactionDenyCustomResponse

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Deny with custom response

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.297

Field Name : wafTemplateactionDrop

Field Type : CounterBasedGauge64

Field Status : current

Description : Number of Dropped Requests

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.296

Field Name : wafTemplateactionDenyReset

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Deny with Resets

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.295

Field Name : wafTemplateactionDenyRedirect

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Deny with Redirect

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.294

Field Name : wafTemplateactionDeny403

Field Type : CounterBasedGauge64

Field Status : current

Description : Request Deny with 403

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.293

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplateactionDeny200
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Deny with 200
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.292

Field Name : wafTemplateactionAllow
Field Type : CounterBasedGauge64
Field Status : current
Description : Request Action allowed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.291

Field Name : wafTemplatelearningListFull
Field Type : CounterBasedGauge64
Field Status : current
Description : Learning list is full
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.290

Field Name : wafTemplatexmlContentCheckWsdLViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : WSDL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.289

Field Name : wafTemplatexmlContentCheckWsdLSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : WSDL passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.288

Field Name : wafTemplatexmlContentCheckSchemaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Schema violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.287

Field Name : wafTemplatexmlContentCheckSchemaSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Schema passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.286

Field Name : wafTemplatexmlCheckXssViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML XSS Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.285

Field Name : wafTemplatexmlCheckXssSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML XSS Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.284

Field Name : wafTemplatexmlCheckSqliaViolation
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : XML Sqlia Check violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.283

Field Name : wafTemplatexmlCheckSqliaSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : XML Sqlia Check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.282

Field Name : wafTemplatexmlCheckNamespaceUriLenViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : XML Limit Namespace URI Length violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.281

Field Name : wafTemplatexmlCheckNamespaceUriLenSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : XML Limit Namespace URI Length check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.280

Field Name : wafTemplatexmlCheckMaxNamespaceViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : XML Limit Namespace violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.279

Field Name : wafTemplatexmlCheckMaxNamespaceSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : XML Limit Namespace check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.278

Field Name : wafTemplatexmlCheckMaxEntityExpDepthViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : XML Limit Entities Depth violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.277

Field Name : wafTemplatexmlCheckMaxEntityExpDepthSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : XML Limit Entities Depth check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.276

Field Name : wafTemplatexmlCheckMaxEntityExpViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : XML Limit Entity Decl violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.275

Field Name : wafTemplatexmlCheckMaxEntityExpSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : XML Limit Entity Decl check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.274

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplatexmlCheckMaxElemNameLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Name Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.273

Field Name : wafTemplatexmlCheckMaxElemNameLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Name Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.272

Field Name : wafTemplatexmlCheckMaxElemDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.271

Field Name : wafTemplatexmlCheckMaxElemDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.270

Field Name : wafTemplatexmlCheckMaxElemChildViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Child violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.269

Field Name : wafTemplatexmlCheckMaxElemChildSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element Child check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.268

Field Name : wafTemplatexmlCheckMaxElemViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.267

Field Name : wafTemplatexmlCheckMaxElemSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Element check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.266

Field Name : wafTemplatexmlCheckMaxCdataLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit CData Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.265

Field Name : wafTemplatexmlCheckMaxCdataLenSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : XML Limit CData Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.264

Field Name : wafTemplatexmlCheckMaxAttrValueLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Value Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.263

Field Name : wafTemplatexmlCheckMaxAttrValueLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Value Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.262

Field Name : wafTemplatexmlCheckMaxAttrNameLenViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Name Length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.261

Field Name : wafTemplatexmlCheckMaxAttrNameLenSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Name Length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.260

Field Name : wafTemplatexmlCheckMaxAttrViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Attribute violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.259

Field Name : wafTemplatexmlCheckMaxAttrSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Limit Attribute check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.258

Field Name : wafTemplatexmlCheckFormatViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.257

Field Name : wafTemplatexmlCheckFormatSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XML Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.256

Field Name : wafTemplatesoapCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Soap Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.255

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplatesoapCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Soap Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.254

Field Name : wafTemplateresponseCloakingFilterHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Headers Filter violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.253

Field Name : wafTemplateresponseCloakingFilterHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Headers Filter check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.252

Field Name : wafTemplateresponseCloakingHideStatusCodeViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Hide Code violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.251

Field Name : wafTemplateresponseCloakingHideStatusCodeSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Hide Code check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.250

Field Name : wafTemplaterequestCheckXssPostBodySanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Post Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.249

Field Name : wafTemplaterequestCheckXssPostBodyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Post violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.248

Field Name : wafTemplaterequestCheckXssPostBodySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check Post passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.247

Field Name : wafTemplaterequestCheckXssUrlSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : XSS Check URL Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.246

Field Name : wafTemplaterequestCheckXssUrlViolation
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : XSS Check URL violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.245

Field Name : wafTemplaterequestCheckXssUrlSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : XSS Check URL passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.244

Field Name : wafTemplaterequestCheckXssCookieSanitize

Field Type : CounterBasedGauge64

Field Status : current

Description : XSS Check Cookie Sanitized

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.243

Field Name : wafTemplaterequestCheckXssCookieViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : XSS Check Cookie violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.242

Field Name : wafTemplaterequestCheckXssCookieSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : XSS Check Cookie passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.241

Field Name : wafTemplaterequestCheckUrlBlacklistViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : URI Black List violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.240

Field Name : wafTemplaterequestCheckUrlBlacklistSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : URI Black List passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.239

Field Name : wafTemplaterequestCheckUrlWhitelistViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : URI White List violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.238

Field Name : wafTemplaterequestCheckUrlWhitelistSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : URI White List passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.237

Field Name : wafTemplaterequestCheckUrlListLearn

Field Type : CounterBasedGauge64

Field Status : current

Description : URL Check Learn

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.236

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplaterequestCheckUrllistViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : URL Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.235

Field Name : wafTemplaterequestCheckUrllistSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : URL Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.234

Field Name : wafTemplaterequestCheckSqliaPostBodySanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check Post Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.233

Field Name : wafTemplaterequestCheckSqliaPostBodyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check Post violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.232

Field Name : wafTemplaterequestCheckSqliaPostBodySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check Post passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.231

Field Name : wafTemplaterequestCheckSqliaUrlSanitize
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check URL Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.230

Field Name : wafTemplaterequestCheckSqliaUrlViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check URL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.229

Field Name : wafTemplaterequestCheckSqliaUrlSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : SQLIA Check URL passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.228

Field Name : wafTemplaterequestCheckSessionCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Session Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.227

Field Name : wafTemplaterequestCheckSessionCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Session Check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.226

Field Name : wafTemplaterequestCheckSessionCheckNone

Field Type : CounterBasedGauge64

Field Status : current

Description : Session Created

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.225

Field Name : wafTemplaterequestCheckRefererRedirect

Field Type : CounterBasedGauge64

Field Status : current

Description : Referer Check Redirect

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.224

Field Name : wafTemplaterequestCheckRefererViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Referer Check violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.223

Field Name : wafTemplaterequestCheckRefererSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Referer Check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.222

Field Name : wafTemplaterequestCheckRedirectWlistLearn

Field Type : CounterBasedGauge64

Field Status : current

Description : Redirect Whitelist Learn

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.221

Field Name : wafTemplaterequestCheckRedirectWlistViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Redirect Whitelist violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.220

Field Name : wafTemplaterequestCheckRedirectWlistSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Redirect Whitelist passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.219

Field Name : wafTemplaterequestCheckBotViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Bot check violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.218

Field Name : wafTemplaterequestCheckBotSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Bot check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.217

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplatejsonCheckMaxStringViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit String violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.216

Field Name : wafTemplatejsonCheckMaxStringSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit String check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.215

Field Name : wafTemplatejsonCheckMaxObjectMemberCountViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Object Number Count violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.214

Field Name : wafTemplatejsonCheckMaxObjectMemberCountSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Object Number Count check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.213

Field Name : wafTemplatejsonCheckMaxDepthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Depth violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.212

Field Name : wafTemplatejsonCheckMaxDepthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Depth check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.211

Field Name : wafTemplatejsonCheckMaxArrayValueCountViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Array Value Count violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.210

Field Name : wafTemplatejsonCheckMaxArrayValueCountSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Limit Array Value Count check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.209

Field Name : wafTemplatejsonCheckFormatViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JSON Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.208

Field Name : wafTemplatejsonCheckFormatSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : JSON Check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.207

Field Name : wafTemplatehttpProtocolViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP Check violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.206

Field Name : wafTemplatehttpProtocolSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : HTTP Check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.205

Field Name : wafTemplatehttpProtocolPostWithoutContentViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : POST without content check violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.204

Field Name : wafTemplatehttpProtocolPostWithoutContentSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : POST without content check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.203

Field Name : wafTemplatehttpProtocolPostWith0ContentViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : POST with 0 content check violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.202

Field Name : wafTemplatehttpProtocolPostWith0ContentSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : POST with 0 content check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.201

Field Name : wafTemplatehttpProtocolMultipleContentLengthViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Multiple content-length headers check violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.200

Field Name : wafTemplatehttpProtocolMultipleContentLengthSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Multiple content-length headers check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.199

Field Name : wafTemplatehttpProtocolMissingHostHeaderViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Missing host header check violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.198

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplatehttpProtocolMissingHostHeaderSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing host header check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.197

Field Name : wafTemplatehttpProtocolMissingHeaderValueViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing header value check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.196

Field Name : wafTemplatehttpProtocolMissingHeaderValueSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Missing header value check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.195

Field Name : wafTemplatehttpProtocolMalformedRequestLineViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request line check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.194

Field Name : wafTemplatehttpProtocolMalformedRequestLineSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request line check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.193

Field Name : wafTemplatehttpProtocolMalformedRequestViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.192

Field Name : wafTemplatehttpProtocolMalformedRequestSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed request check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.191

Field Name : wafTemplatehttpProtocolMalformedParameterViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed parameter check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.190

Field Name : wafTemplatehttpProtocolMalformedParameterSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Malformed parameter check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.189

Field Name : wafTemplatehttpProtocolMalformedHeaderViolation
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Malformed header check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.188

Field Name : wafTemplatehttpProtocolMalformedHeaderSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Malformed header check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.187

Field Name : wafTemplatehttpProtocolMalformedContentLengthViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Malformed content-length check violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.186

Field Name : wafTemplatehttpProtocolMalformedContentLengthSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Malformed content-length check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.185

Field Name : wafTemplatehttpProtocolInvalidUrlEncodingViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Invalid url encoding check violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.184

Field Name : wafTemplatehttpProtocolInvalidUrlEncodingSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Invalid url encoding check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.183

Field Name : wafTemplatehttpProtocolHostHeaderWithIpViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Host header with IP check violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.182

Field Name : wafTemplatehttpProtocolHostHeaderWithIpSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Host header with IP check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.181

Field Name : wafTemplatehttpProtocolHeadWithContentViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : HEAD with content check violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.180

Field Name : wafTemplatehttpProtocolHeadWithContentSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : HEAD with content check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.179

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplatehttpProtocolGetWithContentViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : GET with content check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.178

Field Name : wafTemplatehttpProtocolGetWithContentSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : GET with content check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.177

Field Name : wafTemplatehttpProtocolBadMultipartRequestViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad multi-part request check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.176

Field Name : wafTemplatehttpProtocolBadMultipartRequestSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Bad multi-part request check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.175

Field Name : wafTemplatehttpProtocolAllowedMethodCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Method Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.174

Field Name : wafTemplatehttpProtocolAllowedMethodCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP Method Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.173

Field Name : wafTemplatehttpProtocolAllowedVersionsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP versions check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.172

Field Name : wafTemplatehttpProtocolAllowedVersionsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP versions check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.171

Field Name : wafTemplatehttpProtocolAllowedHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : HTTP headers check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.170

Field Name : wafTemplatehttpProtocolAllowedHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : HTTP headers check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.169

Field Name : wafTemplatemaxUrlLengthViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Limit check - MAX URL length violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.168

Field Name : wafTemplatemaxUrlLengthSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Limit check - MAX URL length check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.167

Field Name : wafTemplatehttpLimitMaxRequestLineLengthViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Limit check - MAX request line length violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.166

Field Name : wafTemplatehttpLimitMaxRequestLineLengthSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Limit check - MAX request line length check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.165

Field Name : wafTemplatehttpLimitMaxRequestLengthViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Limit check - MAX request length violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.164

Field Name : wafTemplatehttpLimitMaxRequestLengthSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Limit check - MAX request length check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.163

Field Name : wafTemplatehttpLimitMaxQueryLengthViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Limit check - MAX query length violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.162

Field Name : wafTemplatehttpLimitMaxQueryLengthSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Limit check - MAX query length check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.161

Field Name : wafTemplatehttpLimitMaxPostLengthViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : MAX POST length violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.160

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplatehttpLimitMaxPostLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX POST length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.159

Field Name : wafTemplatehttpLimitMaxParamsLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters total length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.158

Field Name : wafTemplatehttpLimitMaxParamsLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters total length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.157

Field Name : wafTemplatehttpLimitMaxParamsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.156

Field Name : wafTemplatehttpLimitMaxParamsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameters check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.155

Field Name : wafTemplatehttpLimitMaxParamValueLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter value length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.154

Field Name : wafTemplatehttpLimitMaxParamValueLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter value length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.153

Field Name : wafTemplatehttpLimitMaxParamNameLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter name length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.152

Field Name : wafTemplatehttpLimitMaxParamNameLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Limit check - MAX parameter name length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.151

Field Name : wafTemplatehttpLimitMaxHeadersLengthViolation
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : MAX headers length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.150

Field Name : wafTemplatehttpLimitMaxHeadersLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX headers length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.149

Field Name : wafTemplatehttpLimitMaxHeadersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Headers violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.148

Field Name : wafTemplatehttpLimitMaxHeadersSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX headers count check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.147

Field Name : wafTemplatehttpLimitMaxHeaderValueLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header value length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.146

Field Name : wafTemplatehttpLimitMaxHeaderValueLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header value length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.145

Field Name : wafTemplatehttpLimitMaxHeaderNameLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header name length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.144

Field Name : wafTemplatehttpLimitMaxHeaderNameLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header name length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.143

Field Name : wafTemplatehttpLimitMaxHeaderLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.142

Field Name : wafTemplatehttpLimitMaxHeaderLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX header length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.141

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplatehttpLimitMaxEntitiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Entities violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.140

Field Name : wafTemplatehttpLimitMaxEntitiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Entities check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.139

Field Name : wafTemplatehttpLimitMaxDataParseViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Buffer Overflow - Max Data Parse violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.138

Field Name : wafTemplatehttpLimitMaxDataParseSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Buffer Overflow - Max Data Parse check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.137

Field Name : wafTemplatehttpLimitMaxCookiesLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookies length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.136

Field Name : wafTemplatehttpLimitMaxCookiesLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookies length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.135

Field Name : wafTemplatehttpLimitMaxCookiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Cookies violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.134

Field Name : wafTemplatehttpLimitMaxCookiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Cookies check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.133

Field Name : wafTemplatehttpLimitMaxCookieValueLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie value length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.132

Field Name : wafTemplatehttpLimitMaxCookieValueLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : MAX cookie value length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.131

Field Name : wafTemplatehttpLimitMaxCookieNameLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie name length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.130

Field Name : wafTemplatehttpLimitMaxCookieNameLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie name length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.129

Field Name : wafTemplatehttpLimitMaxCookieHeaderLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie header length violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.128

Field Name : wafTemplatehttpLimitMaxCookieHeaderLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX cookie header length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.127

Field Name : wafTemplatehttpLimitMaxContentLengthViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX content-length check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.126

Field Name : wafTemplatehttpLimitMaxContentLengthSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : MAX content-length check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.125

Field Name : wafTemplateevasionCheckRemoveSpacesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Spaces check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.124

Field Name : wafTemplateevasionCheckRemoveSpacesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Spaces check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.123

Field Name : wafTemplateevasionCheckRemoveCommentsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Comments check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.122

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplateevasionCheckRemoveCommentsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Remove Comments check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.121

Field Name : wafTemplateevasionCheckMaxLevelsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Levels check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.120

Field Name : wafTemplateevasionCheckMaxLevelsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Max Levels check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.119

Field Name : wafTemplateevasionCheckMultipleSlashesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Slashes check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.118

Field Name : wafTemplateevasionCheckMultipleSlashesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Slashes check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.117

Field Name : wafTemplateevasionCheckMultipleEncodingLevelsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Encoding Levels check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.116

Field Name : wafTemplateevasionCheckMultipleEncodingLevelsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Multiple Encoding Levels check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.115

Field Name : wafTemplateevasionCheckInvalidHexEncodingViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Hex Encoding check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.114

Field Name : wafTemplateevasionCheckInvalidHexEncodingSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Invalid Hex Encoding check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.113

Field Name : wafTemplateevasionCheckHighAsciiBytesViolation
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : High Ascii Bytes check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.112

Field Name : wafTemplateevasionCheckHighAsciiBytesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : High Ascii Bytes check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.111

Field Name : wafTemplateevasionCheckDirTraversalViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Dir traversal check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.110

Field Name : wafTemplateevasionCheckDirTraversalSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Dir traversal check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.109

Field Name : wafTemplateevasionCheckDecodeUnicodeCharsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Unicode Chars check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.108

Field Name : wafTemplateevasionCheckDecodeUnicodeCharsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Unicode Chars check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.107

Field Name : wafTemplateevasionCheckDecodeEscapedCharsViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Escaped Chars check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.106

Field Name : wafTemplateevasionCheckDecodeEscapedCharsSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Escaped Chars check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.105

Field Name : wafTemplateevasionCheckDecodeEntitiesViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Entities check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.104

Field Name : wafTemplateevasionCheckDecodeEntitiesSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Decode Entities check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.103

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplateevasionCheckApacheWhitespaceViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Apache Whitespace check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.102

Field Name : wafTemplateevasionCheckApacheWhitespaceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Apache Whitespace check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.101

Field Name : wafTemplatedlpPcreMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : PCRE Mask violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.100

Field Name : wafTemplatedlpPcreViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : PCRE Mask violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.99

Field Name : wafTemplatedlpPcreSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : PCRE Mask check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.98

Field Name : wafTemplatedlpSsnViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Social Security Number Mask violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.97

Field Name : wafTemplatedlpSsnSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Social Security Number Mask check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.96

Field Name : wafTemplatedlpCcnJcbMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : JCB Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.95

Field Name : wafTemplatedlpCcnJcbViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : JCB Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.94

Field Name : wafTemplatedlpCcnDiscoverMasked
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Discover Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.93

Field Name : wafTemplatedlpCcnDiscoverViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Discover Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.92

Field Name : wafTemplatedlpCcnMastercardMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : MasterCard Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.91

Field Name : wafTemplatedlpCcnMastercardViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : MasterCard Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.90

Field Name : wafTemplatedlpCcnVisaMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : Visa Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.89

Field Name : wafTemplatedlpCcnVisaViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Visa Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.88

Field Name : wafTemplatedlpCcnDinersMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : Diners Club Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.87

Field Name : wafTemplatedlpCcnDinersViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Diners Club Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.86

Field Name : wafTemplatedlpCcnAmexMasked
Field Type : CounterBasedGauge64
Field Status : current
Description : Amex Credit Card Number Masked
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.85

Field Name : wafTemplatedlpCcnAmexViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Amex Credit Card Number Detected
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.84

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplatedlpCcnSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Credit Card Number check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.83

Field Name : wafTemplateformSetNoCache
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Set No Cache violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.82

Field Name : wafTemplateformSetNoCacheSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Set No Cache check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.81

Field Name : wafTemplateformPasswordAutocompleteViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Password Autocomplete violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.80

Field Name : wafTemplateformPasswordAutocompleteSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Password Autocomplete check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.79

Field Name : wafTemplateformNonSslPasswordViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL Password violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.78

Field Name : wafTemplateformNonSslPasswordSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL Password check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.77

Field Name : wafTemplateformNonMaskedPasswordViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non Masked Password violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.76

Field Name : wafTemplateformNonMaskedPasswordSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non Masked Password check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.75

Field Name : wafTemplateformCheckSanitize
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Post Form Check Sanitized
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.74

Field Name : wafTemplateformCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Post Form Check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.73

Field Name : wafTemplateformCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Post Form Check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.72

Field Name : wafTemplateformNonPostViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Method being Non Post in Request violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.71

Field Name : wafTemplateformNonPostSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Method being Non Post in Request passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.70

Field Name : wafTemplateformNonSslViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.69

Field Name : wafTemplateformNonSslSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Non SSL check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.68

Field Name : wafTemplateformTagInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : Form A10 Tag Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.67

Field Name : wafTemplateformConsistencyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Consistency violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.66

Field Name : wafTemplateformConsistencySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form Consistency passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.65

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplateformCsrftagViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Form CSRF tag violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.64

Field Name : wafTemplateformCsrftagSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Form CSRF tag passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.63

Field Name : wafTemplatecspHeaderInserted
Field Type : CounterBasedGauge64
Field Status : current
Description : CSP header Inserted
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.62

Field Name : wafTemplatecspHeaderSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : CSP header found
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.61

Field Name : wafTemplatecspHeaderViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : CSP header missing
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.60

Field Name : wafTemplatecookieSecurityDisallowedPersistentSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed persistent Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.59

Field Name : wafTemplatecookieSecurityDisallowedSessionSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed session Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.58

Field Name : wafTemplatecookieSecurityAllowedPersistentSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed persistent Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.57

Field Name : wafTemplatecookieSecurityAllowedSessionSetCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed session Set-Cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.56

Field Name : wafTemplatecookieSecurityDisallowedPersistentCookies
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Cookie Security - disallowed persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.55

Field Name : wafTemplatecookieSecurityDisallowedSessionCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - disallowed session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.54

Field Name : wafTemplatecookieSecurityAllowedPersistentCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - allowed persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.53

Field Name : wafTemplatecookieSecurityAllowedSessionCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - allowed session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.52

Field Name : wafTemplatecookieSecuritySessionCookiesSigned
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signed session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.51

Field Name : wafTemplatecookieSecuritySessionCookiesEncrypted
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypted session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.50

Field Name : wafTemplatecookieSecuritySessionCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - session cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.49

Field Name : wafTemplatecookieSecurityPersistentCookiesSigned
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signed persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.48

Field Name : wafTemplatecookieSecurityPersistentCookiesEncrypted
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypted persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.47

Field Name : wafTemplatecookieSecurityPersistentCookies
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - persistent cookies
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.46

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplatecookieSecurityCookiePolicyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - cookie policy violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.45

Field Name : wafTemplatecookieSecurityCookiePolicySuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - cookie policy passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.44

Field Name : wafTemplatecookieSecurityUnrecognizedCookieViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - unrecognized cookie violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.43

Field Name : wafTemplatecookieSecurityUnrecognizedCookieSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - request with unrecognized cookie
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.42

Field Name : wafTemplatecookieSecurityMissingCookieViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - missing cookie violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.41

Field Name : wafTemplatecookieSecurityMissingCookieSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - request with missing cookie
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.40

Field Name : wafTemplatecookieSecurityAddSecureViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - secure flag violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.39

Field Name : wafTemplatecookieSecurityAddSecureSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - secure flag added
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.38

Field Name : wafTemplatecookieSecurityAddHttpOnlyViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - http-only flag violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.37

Field Name : wafTemplatecookieSecurityAddHttpOnlySuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Cookie Security - http-only flag added
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.36

Field Name : wafTemplatecookieSecuritySignatureCheckViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signature check violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.35

Field Name : wafTemplatecookieSecuritySignatureCheckSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signature check successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.34

Field Name : wafTemplatecookieSecuritySignSkipRcache
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing skipped - RAM Cache
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.33

Field Name : wafTemplatecookieSecuritySignLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing limit exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.32

Field Name : wafTemplatecookieSecuritySignViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.31

Field Name : wafTemplatecookieSecuritySignSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - signing successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.30

Field Name : wafTemplatecookieSecurityDecryptViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - decrypt violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.29

Field Name : wafTemplatecookieSecurityDecryptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - decrypt successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.28

Field Name : wafTemplatecookieSecurityEncryptSkipRcache
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt skipped - RAM cache
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.27

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplatecookieSecurityEncryptLimitExceeded
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt limit exceeded
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.26

Field Name : wafTemplatecookieSecurityEncryptViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.25

Field Name : wafTemplatecookieSecurityEncryptSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Cookie Security - encrypt successful
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.24

Field Name : wafTemplatebruteForceResponseStringTriggered
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute Force Response string Triggered
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.23

Field Name : wafTemplatebruteForceResponseHeadersTriggered
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute Force Response Headers Triggered
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.22

Field Name : wafTemplatebruteForceResponseCodesTriggered
Field Type : CounterBasedGauge64
Field Status : current
Description : Response Codes Triggered
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.21

Field Name : wafTemplatebruteForceChallengeLimitViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.20

Field Name : wafTemplatebruteForceChallengeLimitSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit check passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.19

Field Name : wafTemplatebruteForceLockoutLimitViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Lockout limit violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.18

Field Name : wafTemplatebruteForceLockoutLimitSuccess
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Description : Lockout limit check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.17

Field Name : wafTemplatebruteForceChallengeCaptchaViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Captcha challenge violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.16

Field Name : wafTemplatebruteForceChallengeCaptchaSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Captcha challenge check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.15

Field Name : wafTemplatebruteForceChallengeCaptchaSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Captcha challenge sent

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.14

Field Name : wafTemplatebruteForceChallengeJavascriptViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : JavaScript challenge violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.13

Field Name : wafTemplatebruteForceChallengeJavascriptSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : JavaScript challenge check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.12

Field Name : wafTemplatebruteForceChallengeJavascriptSent

Field Type : CounterBasedGauge64

Field Status : current

Description : JavaScript challenge sent

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.11

Field Name : wafTemplatebruteForceChallengeCookieViolation

Field Type : CounterBasedGauge64

Field Status : current

Description : Cookie challenge violation

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.10

Field Name : wafTemplatebruteForceChallengeCookieSuccess

Field Type : CounterBasedGauge64

Field Status : current

Description : Cookie Challenge check passed

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.9

Field Name : wafTemplatebruteForceChallengeCookieSent

Field Type : CounterBasedGauge64

Field Status : current

Description : Cookie Challenge Sent

OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.8

ACOS-WAF-STATS-MIB_acosWaf_oid_list

Field Name : wafTemplatebruteForceViolation
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute-Force checks violation
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.7

Field Name : wafTemplatebruteForceSuccess
Field Type : CounterBasedGauge64
Field Status : current
Description : Brute-Force checks passed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.6

Field Name : wafTemplaterespDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : Responses Denied
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.5

Field Name : wafTemplatereqDenied
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Denied
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.4

Field Name : wafTemplatereqAllowed
Field Type : CounterBasedGauge64
Field Status : current
Description : Requests Allowed
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.3

Field Name : wafTemplatetotalReq
Field Type : CounterBasedGauge64
Field Status : current
Description : Total Requests
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.2

Field Name : wafTemplateName
Field Type : String
Field Status : current
Description : WAF Template Name
OID : 1.3.6.1.4.1.22610.2.4.10.111.5.1.1.1.1

ACOS-WEBCATEGORY-LICENSE-MIB_oid_list

Field Name : licenseOperTable
Field Type : TABLE
Field Status : current
Description : LicenseInformation from object 'web-category.license'
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2

Field Name : licenseOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The licenseOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1

Field Name : licenseOperSerialNumber
Field Type : String
Field Status : current
Description : serial-number
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.9

Field Name : licenseOperGracePeriod
Field Type : String
Field Status : current
Description : grace-period
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.8

Field Name : licenseOperIsGrace
Field Type : String
Field Status : current
Description : is-grace
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.7

Field Name : licenseOperRemainingPeriod
Field Type : String
Field Status : current
Description : remaining-period
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.6

Field Name : licenseOperLicenseExpiry
Field Type : String
Field Status : current
Description : license-expiry
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.5

Field Name : licenseOperLicenseType
Field Type : String
Field Status : current
Description : license-type
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.4

Field Name : licenseOperLicenseStatus
Field Type : String
Field Status : current
Description : license-status
OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.3

Field Name : licenseOperModuleStatus
Field Type : String
Field Status : current

ACOS-WEBCATEGORY-LICENSE-MIB_oid_list

Description : module-status

OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.2

Field Name : licenseOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.278.1.2.1.1

ACOS-WEB-CATEGORY-MIB_oid_list

Field Name : webCategoryOperTable
Field Type : TABLE
Field Status : current
Description : WebCategoryCommands from object 'web-category'
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2

Field Name : webCategoryOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The webCategoryOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1

Field Name : webCategoryOperWebCatLastSuccessfulConnection
Field Type : String
Field Status : current
Description : web-cat-last-successful-connection
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.11

Field Name : webCategoryOperWebCatFailureReason
Field Type : String
Field Status : current
Description : web-cat-failure-reason
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.10

Field Name : webCategoryOperWebCatConnectionStatus
Field Type : String
Field Status : current
Description : web-cat-connection-status
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.9

Field Name : webCategoryOperWebCatNextUpdateTime
Field Type : String
Field Status : current
Description : web-cat-next-update-time
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.8

Field Name : webCategoryOperWebCatLastUpdateTime
Field Type : String
Field Status : current
Description : web-cat-last-update-time
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.7

Field Name : webCategoryOperWebCatDatabaseVersion
Field Type : CounterBasedGauge64
Field Status : current
Description : web-cat-database-version
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.6

Field Name : webCategoryOperWebCatDatabaseSize
Field Type : String
Field Status : current
Description : web-cat-database-size
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.5

Field Name : webCategoryOperWebCatDatabaseStatus
Field Type : String
Field Status : current

ACOS-WEB-CATEGORY-MIB_oid_list

Description : web-cat-database-status
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.4

Field Name : webCategoryOperWebCatDatabaseName
Field Type : String
Field Status : current
Description : web-cat-database-name
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.3

Field Name : webCategoryOperWebCatVersion
Field Type : String
Field Status : current
Description : web-cat-version
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.2

Field Name : webCategoryOperSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.274.1.2.1.1

ACOS-WEBCATEGORY-STATISTICS-MIB_oid_list

Field Name : statisticsOperPerCpuListTable
Field Type : TABLE
Field Status : current
Description : Statistics from object 'web-category.statistics'
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3

Field Name : statisticsOperTable
Field Type : TABLE
Field Status : current
Description : Statistics from object 'web-category.statistics'
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2

Field Name : statisticsOperEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statisticsOper entry
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1

Field Name : statisticsOperClearCache
Field Type : String
Field Status : current
Description : clear-cache
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.8

Field Name : statisticsOperTotalReqLookupProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : total-req-lookup-processed
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.7

Field Name : statisticsOperTotalReqProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : total-req-processed
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.6

Field Name : statisticsOperTotalReqDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : total-req-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.5

Field Name : statisticsOperTotalReqQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : total-req-queue
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.4

Field Name : statisticsOperNumLookupThreads
Field Type : CounterBasedGauge64
Field Status : current
Description : num-lookup-threads
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.3

Field Name : statisticsOperNumDplaneThreads
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WEBCATEGORY-STATISTICS-MIB_oid_list

Description : num-dplane-threads

OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.2

Field Name : statisticsOperSlotId

Field Type : Integer32

Field Status : current

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.280.1.2.1.1

Field Name : statisticsStatsTable

Field Type : TABLE

Field Status : current

Description : Statistics from object 'web-category.statistics'

OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1

Field Name : statisticsStatsEntry

Field Type : CounterBasedGauge64

Field Status : current

Description : The statisticsStats stats entry

OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1

Field Name : statisticsStatsLookupCacheMem

Field Type : CounterBasedGauge64

Field Status : current

Description : lookup-cache-mem

OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.9

Field Name : statisticsStatsRtuCacheMem

Field Type : CounterBasedGauge64

Field Status : current

Description : rtu-cache-mem

OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.8

Field Name : statisticsStatsDbMem

Field Type : CounterBasedGauge64

Field Status : current

Description : db-mem

OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.7

Field Name : statisticsStatsLookupLatency

Field Type : CounterBasedGauge64

Field Status : current

Description : lookup-latency

OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.6

Field Name : statisticsStatsRtuLookup

Field Type : CounterBasedGauge64

Field Status : current

Description : rtu-lookup

OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.5

Field Name : statisticsStatsCloudLookup

Field Type : CounterBasedGauge64

Field Status : current

Description : cloud-lookup

OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.4

ACOS-WEBCATEGORY-STATISTICS-MIB_oid_list

Field Name : statisticsStatsCloudCacheLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : cloud-cache-lookup
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.3

Field Name : statisticsStatsDbLookup
Field Type : CounterBasedGauge64
Field Status : current
Description : db-lookup
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.2

Field Name : statisticsStatsSlotId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.1.1.1

Field Name : statisticsOperPerCpuListEntry
Field Type : CounterBasedGauge64
Field Status : current
Description : The statisticsOperPerCpuList entry:per-cpu-list
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1

Field Name : statisticsOperPerCpuListReqLookupProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : req-lookup-processed
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1.6

Field Name : statisticsOperPerCpuListReqProcessed
Field Type : CounterBasedGauge64
Field Status : current
Description : req-processed
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1.5

Field Name : statisticsOperPerCpuListReqDropped
Field Type : CounterBasedGauge64
Field Status : current
Description : req-dropped
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1.4

Field Name : statisticsOperPerCpuListReqQueue
Field Type : CounterBasedGauge64
Field Status : current
Description : req-queue
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1.3

Field Name : statisticsOperPerCpuListPerCpuListListId
Field Type : Integer32
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1.2

Field Name : statisticsOperPerCpuListSlotId
Field Type : Integer32
Field Status : current

ACOS-WEBCATEGORY-STATISTICS-MIB_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.8.280.1.3.1.1

ACOS-WEB-CATEGORY-STATS-MIB_acosWebCategory_oid_list

Field Name : lookupCacheMem
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.8

Field Name : rtuCacheMem
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.7

Field Name : dbMem
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.6

Field Name : lookupLatency
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.5

Field Name : rtuLookup
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.4

Field Name : cloudLookup
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.3

Field Name : cloudCacheLookup
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.2

Field Name : dbLookup
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.8.1.1

Field Name : webCategoryCategoryListSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1

Field Name : webCategoryCategoryListSEntry
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WEB-CATEGORY-STATS-MIB_acosWebCategory_oid_list

Description :

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1

Field Name : illegalPornography

Field Type : CounterBasedGauge64

Field Status : current

Description : illegal pornography eg. child sexual abuse

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.92

Field Name : nudityArtistic

Field Type : CounterBasedGauge64

Field Status : current

Description : artistic nudity

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.91

Field Name : generativeAi

Field Type : CounterBasedGauge64

Field Status : current

Description : generative ai

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.90

Field Name : lowThcCannabisProducts

Field Type : CounterBasedGauge64

Field Status : current

Description : low-thc cannabis products category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.89

Field Name : dnsOverHttps

Field Type : CounterBasedGauge64

Field Status : current

Description : dns over https category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.88

Field Name : selfHarm

Field Type : CounterBasedGauge64

Field Status : current

Description : self harm category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.87

Field Name : dummyItem

Field Type : CounterBasedGauge64

Field Status : current

Description : dummy item category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.86

Field Name : foodAndDining

Field Type : CounterBasedGauge64

Field Status : current

Description : food and dining category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.85

Field Name : webHostingSites

Field Type : CounterBasedGauge64

Field Status : current

Description : web hosting sites category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.84

ACOS-WEB-CATEGORY-STATS-MIB_acosWebCategory_oid_list

Field Name : motorVehicles
Field Type : CounterBasedGauge64
Field Status : current
Description : motor vehicles category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.83

Field Name : recreationAndHobbies
Field Type : CounterBasedGauge64
Field Status : current
Description : recreation and hobbies category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.82

Field Name : fashionAndBeauty
Field Type : CounterBasedGauge64
Field Status : current
Description : fashion and beauty category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.81

Field Name : imageAndVideoSearch
Field Type : CounterBasedGauge64
Field Status : current
Description : image and video search category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.80

Field Name : privateIPAddresses
Field Type : CounterBasedGauge64
Field Status : current
Description : private IP addresses category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.79

Field Name : alcoholAndTobacco
Field Type : CounterBasedGauge64
Field Status : current
Description : alcohol and tobacco category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.78

Field Name : parkedDomains
Field Type : CounterBasedGauge64
Field Status : current
Description : parked domains category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.77

Field Name : dynamicallyGeneratedContent
Field Type : CounterBasedGauge64
Field Status : current
Description : dynamically generated content category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.76

Field Name : openHTTPProxies
Field Type : CounterBasedGauge64
Field Status : current
Description : open HTTP proxies category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.75

Field Name : unconfirmedSPAMSources
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WEB-CATEGORY-STATS-MIB_acosWebCategory_oid_list

Description : unconfirmed SPAM sources category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.74

Field Name : spamUrls
Field Type : CounterBasedGauge64
Field Status : current
Description : SPAM URLs category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.73

Field Name : confirmedSPAMSources
Field Type : CounterBasedGauge64
Field Status : current
Description : confirmed SPAM sources category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.72

Field Name : healthAndMedicine
Field Type : CounterBasedGauge64
Field Status : current
Description : health and medicine category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.71

Field Name : abortion
Field Type : CounterBasedGauge64
Field Status : current
Description : abortion category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.70

Field Name : botNets
Field Type : CounterBasedGauge64
Field Status : current
Description : bot nets category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.69

Field Name : internetCommunications
Field Type : CounterBasedGauge64
Field Status : current
Description : internet communications category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.68

Field Name : cDNs
Field Type : CounterBasedGauge64
Field Status : current
Description : content delivery networks category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.67

Field Name : illegal
Field Type : CounterBasedGauge64
Field Status : current
Description : illegal category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.66

Field Name : newsAndMedia
Field Type : CounterBasedGauge64
Field Status : current
Description : news and media category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.65

ACOS-WEB-CATEGORY-STATS-MIB_acosWebCategory_oid_list

Field Name : nudity
Field Type : CounterBasedGauge64
Field Status : current
Description : nudity category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.64

Field Name : government
Field Type : CounterBasedGauge64
Field Status : current
Description : government category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.63

Field Name : music
Field Type : CounterBasedGauge64
Field Status : current
Description : music category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.62

Field Name : spywareAndAdware
Field Type : CounterBasedGauge64
Field Status : current
Description : spyware and adware category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.61

Field Name : proxyAvoidAndAnonymizers
Field Type : CounterBasedGauge64
Field Status : current
Description : proxy avoid and anonymizers category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.60

Field Name : phishingAndOtherFraud
Field Type : CounterBasedGauge64
Field Status : current
Description : phishing and other fraud category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.59

Field Name : malwareSites
Field Type : CounterBasedGauge64
Field Status : current
Description : malware sites category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.58

Field Name : webBasedEmail
Field Type : CounterBasedGauge64
Field Status : current
Description : web based email category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.57

Field Name : gross
Field Type : CounterBasedGauge64
Field Status : current
Description : gross category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.56

Field Name : cheating
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WEB-CATEGORY-STATS-MIB_acosWebCategory_oid_list

Description : cheating category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.55

Field Name : webAdvertisements

Field Type : CounterBasedGauge64

Field Status : current

Description : web advertisements category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.54

Field Name : internetPortals

Field Type : CounterBasedGauge64

Field Status : current

Description : internet portals category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.53

Field Name : searchEngines

Field Type : CounterBasedGauge64

Field Status : current

Description : search engines category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.52

Field Name : keyloggersAndMonitoring

Field Type : CounterBasedGauge64

Field Status : current

Description : keyloggers and monitoring category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.51

Field Name : violence

Field Type : CounterBasedGauge64

Field Status : current

Description : violence category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.50

Field Name : personalStorage

Field Type : CounterBasedGauge64

Field Status : current

Description : personal storage category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.49

Field Name : hateAndRacism

Field Type : CounterBasedGauge64

Field Status : current

Description : hate and racism category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.48

Field Name : kids

Field Type : CounterBasedGauge64

Field Status : current

Description : kids category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.47

Field Name : questionable

Field Type : CounterBasedGauge64

Field Status : current

Description : questionable category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.46

ACOS-WEB-CATEGORY-STATS-MIB_acosWebCategory_oid_list

Field Name : swimsuitsAndIntimateApparel
Field Type : CounterBasedGauge64
Field Status : current
Description : swimsuits and intimate apparel category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.45

Field Name : sports
Field Type : CounterBasedGauge64
Field Status : current
Description : sports category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.44

Field Name : onlineGreetingCards
Field Type : CounterBasedGauge64
Field Status : current
Description : online greeting cards category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.43

Field Name : educationalInstitutions
Field Type : CounterBasedGauge64
Field Status : current
Description : educational institutions category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.42

Field Name : society
Field Type : CounterBasedGauge64
Field Status : current
Description : society category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.41

Field Name : huntingAndFishing
Field Type : CounterBasedGauge64
Field Status : current
Description : hunting and fishing category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.40

Field Name : payToSurf
Field Type : CounterBasedGauge64
Field Status : current
Description : pay to surf category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.39

Field Name : weapons
Field Type : CounterBasedGauge64
Field Status : current
Description : weapons category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.38

Field Name : philosophyAndPolitics
Field Type : CounterBasedGauge64
Field Status : current
Description : philosophy and politics category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.37

Field Name : games
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WEB-CATEGORY-STATS-MIB_acosWebCategory_oid_list

Description : games category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.36

Field Name : hacking
Field Type : CounterBasedGauge64
Field Status : current
Description : hacking category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.35

Field Name : marijuana
Field Type : CounterBasedGauge64
Field Status : current
Description : marijuana category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.34

Field Name : peerToPeer
Field Type : CounterBasedGauge64
Field Status : current
Description : peer to peer category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.33

Field Name : sharewareAndFreeware
Field Type : CounterBasedGauge64
Field Status : current
Description : shareware and freeware category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.32

Field Name : referenceAndResearch
Field Type : CounterBasedGauge64
Field Status : current
Description : reference and research category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.31

Field Name : translation
Field Type : CounterBasedGauge64
Field Status : current
Description : translation category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.30

Field Name : gambling
Field Type : CounterBasedGauge64
Field Status : current
Description : gambling category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.29

Field Name : jobSearch
Field Type : CounterBasedGauge64
Field Status : current
Description : job search category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.28

Field Name : streamingMedia
Field Type : CounterBasedGauge64
Field Status : current
Description : streaming media category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.27

ACOS-WEB-CATEGORY-STATS-MIB_acosWebCategory_oid_list

Field Name : localInformation
Field Type : CounterBasedGauge64
Field Status : current
Description : local information category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.26

Field Name : legal
Field Type : CounterBasedGauge64
Field Status : current
Description : legal category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.25

Field Name : personalSitesAndBlogs
Field Type : CounterBasedGauge64
Field Status : current
Description : personal sites and blogs category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.24

Field Name : entertainmentAndArts
Field Type : CounterBasedGauge64
Field Status : current
Description : entertainment and arts category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.23

Field Name : religion
Field Type : CounterBasedGauge64
Field Status : current
Description : religion category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.22

Field Name : sexEducation
Field Type : CounterBasedGauge64
Field Status : current
Description : sex education category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.21

Field Name : dating
Field Type : CounterBasedGauge64
Field Status : current
Description : dating category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.20

Field Name : trainingAndTools
Field Type : CounterBasedGauge64
Field Status : current
Description : training and tools category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.19

Field Name : stockAdviceAndTools
Field Type : CounterBasedGauge64
Field Status : current
Description : stock advice and tools category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.18

Field Name : deadSites
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WEB-CATEGORY-STATS-MIB_acosWebCategory_oid_list

Description : dead sites category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.17

Field Name : socialNetwork

Field Type : CounterBasedGauge64

Field Status : current

Description : social network category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.16

Field Name : military

Field Type : CounterBasedGauge64

Field Status : current

Description : military category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.15

Field Name : homeAndGarden

Field Type : CounterBasedGauge64

Field Status : current

Description : home and garden category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.14

Field Name : adultAndPornography

Field Type : CounterBasedGauge64

Field Status : current

Description : adult and pornography category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.13

Field Name : drugs

Field Type : CounterBasedGauge64

Field Status : current

Description : drugs category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.12

Field Name : travel

Field Type : CounterBasedGauge64

Field Status : current

Description : travel category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.11

Field Name : cultAndOccult

Field Type : CounterBasedGauge64

Field Status : current

Description : cult and occult category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.10

Field Name : shopping

Field Type : CounterBasedGauge64

Field Status : current

Description : shopping category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.9

Field Name : auctions

Field Type : CounterBasedGauge64

Field Status : current

Description : auctions category

OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.8

ACOS-WEB-CATEGORY-STATS-MIB_acosWebCategory_oid_list

Field Name : computerAndInternetInfo
Field Type : CounterBasedGauge64
Field Status : current
Description : computer and internet info category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.7

Field Name : businessAndEconomy
Field Type : CounterBasedGauge64
Field Status : current
Description : business and economy category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.6

Field Name : financialServices
Field Type : CounterBasedGauge64
Field Status : current
Description : financial services category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.5

Field Name : computerAndInternetSecurity
Field Type : CounterBasedGauge64
Field Status : current
Description : computer and internet security category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.4

Field Name : realEstate
Field Type : CounterBasedGauge64
Field Status : current
Description : real estate category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.3

Field Name : uncategorized
Field Type : CounterBasedGauge64
Field Status : current
Description : uncategorized category
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Web Category List name
OID : 1.3.6.1.4.1.22610.2.4.10.106.7.1.1.1.1

Field Name : webCategoryReputationScopeSTable
Field Type : TABLE
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1

Field Name : webCategoryReputationScopeSEntry
Field Type : CounterBasedGauge64
Field Status : current
Description :
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1

Field Name : malicious
Field Type : CounterBasedGauge64
Field Status : current

ACOS-WEB-CATEGORY-STATS-MIB_acosWebCategory_oid_list

Description : Malicious level(1-20)
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1.6

Field Name : suspicious
Field Type : CounterBasedGauge64
Field Status : current
Description : Suspicious level(21-40)
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1.5

Field Name : moderateRisk
Field Type : CounterBasedGauge64
Field Status : current
Description : Moderate-risk level(41-60)
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1.4

Field Name : lowRisk
Field Type : CounterBasedGauge64
Field Status : current
Description : Low-risk level(61-80)
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1.3

Field Name : trustworthy
Field Type : CounterBasedGauge64
Field Status : current
Description : Trustworthy level(81-100)
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1.2

Field Name : name
Field Type : String
Field Status : current
Description : Reputation Scope name
OID : 1.3.6.1.4.1.22610.2.4.10.106.9.1.1.1.1



©2025 A10 Networks, Inc. All rights reserved. A10 Networks, the A10 Networks logo, ACOS, A10 Thunder, Thunder TPS, A10 Harmony, SSLi and SSL Insight are trademarks or registered trademarks of A10 Networks, Inc. in the United States and other countries. All other trademarks are property of their respective owners. A10 Networks assumes no responsibility for any inaccuracies in this document. A10 Networks reserves the right to change, modify, transfer, or otherwise revise this publication without notice. For the full list of trademarks, visit: www.a10networks.com/company/legal/trademarks/.